



## hp fc/san backup solution compatibility matrix

Version 4.1

Date: November 27, 2008

The tables below show HP OpenView Storage Data Protector 5.5 fully tested recommended and supported HP FC/SAN backup configurations. Please note, this compatibility matrix is not the definitive list of SAN environments supported by Data Protector. The environments listed within this matrix are those that have been fully tested and therefore highly recommended. All media technologies and devices listed as supported with HP-UX, Windows, AIX, Tru64, Linux, Netware, OpenVMS and Solaris within the Data Protector 5.5 Device Support Matrix are supported in a SAN environment. The SAN is transparent to Data Protector.

### Data Protector 5.5 Device Support Matrix

For recommendations on hardware installation, please refer to the SAN Backup Solution Installation Guide at <http://www.hp.com/>. For recommendations on software installation, please refer to the HP OpenView Storage Data Protector Installation and Licensing Guide, included with the software.

The FC/SAN configurations are structured into the following tables:

1. Point-To-Point
2. Switch Fabric
3. Arbitrated-Loop

Note that the HP Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 Tape Libraries listed within this document are supported with DLT8000 and HP Ultrium tape drives, while the HP Surestore 10/180 and 20/700 Tape Libraries are supported with DLT7000, DLT8000, HP 9840, and HP Ultrium tape drives. The HP Surestore 10/588 Tape Library is supported with HP 9840 and DLT7000 tape drives. Firmware and device driver version numbers are the minimum requirements for support. In most cases, the most recently released version is recommended.

point-to-point (fc bridge required)				
server	FC HBA	FC interface	tape libraries	remarks
Windows 2000	HP D8602A/B <ul style="list-style-type: none"><li>• Driver v2.06</li></ul> QLogic QLA-2200F <ul style="list-style-type: none"><li>• Driver v7.05.05 + SNIA Library Patch</li></ul> Emulex LP8000-N1,F1 <ul style="list-style-type: none"><li>• Driver v4.52a7 + firmware 3.82a1</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A5590A (HVDS)</li><li>• A4687A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT) <ul style="list-style-type: none"><li>• Firmware 1.33</li></ul>	For best performance, one drive per SCSI bus on library's FC interface card.

Windows 2000	HP D8602A/B • Driver v2.06  QLogic QLA-2200F • Driver v7.05.05 + SNIA Library Patch  Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware 3.82a1	Internal FC Card • A4673A (HVDS) • A4674A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	For best performance, one drive per SCSI bus on library's FC interface card.
Windows 2000	HP D8602A/B • Driver v2.06  QLogic QLA-2200F • Driver v7.05.05 + SNIA Library Patch  Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware 3.82a1	Bridge FC 4/1 HV • A4688A • Firmware 2008e  Surestore Interface Manager • A6356A with A4673A cards	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00  Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	For best performance, one drive per SCSI bus. High Voltage Diff SCSI devices only.
Windows 2000	HP D8602A/B • Driver v2.06  QLogic QLA-2200F • Driver v7.05.05 + SNIA Library Patch  Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware 3.82a1	Bridge FC 2/1 LV • A4689A • Firmware 2008e  Surestore Interface Manager • A6356A with A4674A cards	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	For best performance, one drive per SCSI bus. Low Voltage Diff SCSI devices only.
HP 9000 HP-UX 11.0, 11.i	On HSC-Bus: • A3740A (V, N, L classes) • A3636A (T class) • A3404A (K class) • A3591A (R, D classes) • A6685A (K class) • A6684A (R, D classes)  On PCI Bus • A5158A (SuperDome, V, N, L, A classes) • A6795A (SuperDome, rp8400, V, N, L, A classes)	FC Bridge 4/2 • A3308A • A3511A • A3511AZ • Firmware 4010	Surestore 2/20, 4/40, 6/60, and 6/140 tape libraries (DLT) • Firmware 1.14  Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00  Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	For best performance, one drive per SCSI bus. High Voltage Diff SCSI devices only.

HP 9000 HP-UX 11.0, 11.i	On HSC-Bus:	Bridge FC 4/1 HV	Surestore 10/180 and 20/700 (DLT & 9840)	For best performance, one drive per SCSI bus. High Voltage Diff SCSI devices only.
	<ul style="list-style-type: none"> <li>• A3740A (V, N, L classes)</li> <li>• A3636A (T class)</li> <li>• A3404A (K class)</li> <li>• A3591A (R, D classes)</li> <li>• A6685A (K class)</li> <li>• A6684A (R, D classes)</li> </ul> <p>On PCI Bus</p> <ul style="list-style-type: none"> <li>• A5158A (SuperDome, V, N, L, A classes)</li> <li>• A6795A (SuperDome, rp8400, V, N, L, A classes)</li> </ul>	<ul style="list-style-type: none"> <li>• A4688A</li> <li>• Firmware 2008e</li> </ul> <p>Surestore Interface Manager</p> <ul style="list-style-type: none"> <li>• A6356A with A4673A cards</li> </ul>	<ul style="list-style-type: none"> <li>• Firmware 2.00</li> </ul> <p>Surestore 10/588 (DLT &amp; 9840)</p> <ul style="list-style-type: none"> <li>• Firmware 1.9.03</li> </ul>	
HP 9000 HP-UX 11.0, 11.i	On HSC-Bus:	Bridge FC 2/1 LV	Surestore 10/180 and 20/700 (LTO)	For best performance, one drive per SCSI bus. Low Voltage Diff SCSI devices only.
	<ul style="list-style-type: none"> <li>• A3740A (V, N, L classes)</li> <li>• A3636A (T class)</li> <li>• A3404A (K class)</li> <li>• A3591A (R, D classes)</li> <li>• A6685A (K class)</li> <li>• A6684A (R, D classes)</li> </ul> <p>On PCI Bus</p> <ul style="list-style-type: none"> <li>• A5158A (SuperDome, V, N, L, A classes)</li> <li>• A6795A (SuperDome, rp8400, V, N, L, A classes)</li> </ul>	<ul style="list-style-type: none"> <li>• A4689A</li> <li>• Firmware 2008e</li> </ul> <p>Surestore Interface Manager</p> <ul style="list-style-type: none"> <li>• A6356A with A4674A cards</li> </ul>	<ul style="list-style-type: none"> <li>• Firmware 2.00</li> </ul>	
HP 9000 HP-UX 11.0, 11.i	On HSC-Bus:	Internal FC Card	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT)	For best performance, one drive per SCSI bus on library's FC interface card.
	<ul style="list-style-type: none"> <li>• A3740A (V, N, L classes)</li> <li>• A3636A (T class)</li> <li>• A3404A (K class)</li> <li>• A3591A (R, D classes)</li> <li>• A6685A (K class)</li> <li>• A6684A (R, D classes)</li> </ul> <p>On PCI Bus</p> <ul style="list-style-type: none"> <li>• A5158A (SuperDome, V, N, L, A classes)</li> <li>• A6795A (SuperDome, rp8400, V, N, L, A classes)</li> </ul>	<ul style="list-style-type: none"> <li>• A5590A (HVDS)</li> <li>• A4687A (LVDS)</li> </ul>	<ul style="list-style-type: none"> <li>• Firmware 1.33</li> </ul>	

HP 9000 HP-UX 11.0, 11.i	On HSC-Bus: <ul style="list-style-type: none"><li>• A3740A (V, N, L classes)</li><li>• A3636A (T class)</li><li>• A3404A (K class)</li><li>• A3591A (R, D classes)</li><li>• A6685A (K class)</li><li>• A6684A (R, D classes)</li></ul> On PCI Bus <ul style="list-style-type: none"><li>• A5158A (SuperDome, V, N, L, A classes)</li><li>• A6795A (SuperDome, rp8400, V, N, L, A classes)</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A4673A (HVDS)</li><li>• A4674A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	For best performance, one drive per SCSI bus on library's FC interface card.
SUN Solaris 7, 8	SBUS <ul style="list-style-type: none"><li>• JNI FC64-1063-N</li><li>• JNI FCE-1063-N</li></ul> PCI-Bus <ul style="list-style-type: none"><li>• JNI FCI-1063-N</li><li>• JNI FCE-6410-N</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A5590A (HVDS)</li><li>• A4687A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT) • Firmware 1.33	• HBA's fca_nport parameter should be set to 0
SUN Solaris 7, 8	SBUS <ul style="list-style-type: none"><li>• JNI FC64-1063-N</li><li>• JNI FCE-1063-N</li></ul> PCI-Bus <ul style="list-style-type: none"><li>• JNI FCI-1063-N</li><li>• JNI FCE-6410-N</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A4673A (HVDS)</li><li>• A4674A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	• HBA's fca_nport parameter should be set to 0
SUN Solaris 7, 8	SBUS <ul style="list-style-type: none"><li>• JNI FC64-1063-N</li><li>• JNI FCE-1063-N</li></ul> PCI-Bus <ul style="list-style-type: none"><li>• JNI FCI-1063-N</li><li>• JNI FCE-6410-N</li></ul>	Bridge FC 4/1 HV <ul style="list-style-type: none"><li>• A4688A</li><li>• Firmware 2008e</li></ul> Surestore Interface Manager <ul style="list-style-type: none"><li>• A6356A with A4673A cards</li></ul>	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00 Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	• HBA's fca_nport parameter should be set to 0
SUN Solaris 7, 8	SBUS <ul style="list-style-type: none"><li>• JNI FC64-1063-N</li><li>• JNI FCE-1063-N</li></ul> PCI-Bus <ul style="list-style-type: none"><li>• JNI FCI-1063-N</li><li>• JNI FCE-6410-N</li></ul>	Bridge FC 2/1 LV <ul style="list-style-type: none"><li>• A4689A</li><li>• Firmware 2008e</li></ul> Surestore Interface Manager <ul style="list-style-type: none"><li>• A6356A with A4674A cards</li></ul>	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	• HBA's fca_nport parameter should be set to 0
Novell Netware 5.x	QLogic QLA-2200F <ul style="list-style-type: none"><li>• Driver v6.50c + firmware 1.74</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A5590A (HVDS)</li><li>• A4687A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT) • Firmware 1.33	For best performance, one drive per SCSI bus on library's FC interface card.
Novell Netware 5.x	QLogic QLA-2200F <ul style="list-style-type: none"><li>• Driver v6.50c + firmware 1.74</li></ul>	Internal FC Card <ul style="list-style-type: none"><li>• A4673A (HVDS)</li><li>• A4674A (LVDS)</li></ul>	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	For best performance, one drive per SCSI bus on library's FC interface card.

Novell Netware 5.x	QLogic QLA-2200F • Driver v6.50c + firmware 1.74	Bridge FC 4/1 HV • A4688A • Firmware 2008e  Surestore Interface Manager • A6356A with A4673A cards	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00 Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	For best performance, one drive per SCSI bus. High Voltage Diff SCSI devices only.
Novell Netware 5.x	QLogic QLA-2200F • Driver v6.50c + firmware 1.74	Bridge FC 2/1 LV • A4689A • Firmware 2008e  Surestore Interface Manager • A6356A with A4674A cards	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	For best performance, one drive per SCSI bus. Low Voltage Diff SCSI devices only.

### SAN switch supported configurations

<b>FC switch</b>	<b>server</b>	<b>FC HBA</b>	<b>FC interface</b>	<b>tape libraries</b>	<b>switch mode</b>
HP/Brocade 2400 • A5625A • A5667A • Firmware 2.1.3	Windows 2000	HP D8602A/B • Driver v2.06	Internal FC Card • A5590A (HVDS) • A4687A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT) • Firmware 1.33	<ul style="list-style-type: none"> <li>• Fabric (no QuickLoop)</li> <li>• For D8602A/B, set "InitAsNport=1" parameter in Registry</li> </ul>
HP/Brocade 2800 • A5624A • Firmware 2.1.3		QLogic QLA-2200F • Driver v7.05.05 + SNIA			
HP FC-64 Director • A6534A/AZ • Firmware 1.1.2		Library Patch			
HP 6164 • A7326A • Firmware 2.4.1		Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware			
HP switch 8/16B • A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01		3.82a1			
HP/Brocade 2400 • A5625A • A5667A • Firmware 2.1.3	Windows 2000	HP D8602A/B • Driver v2.06	Internal FC Card • A4673A (HVDS) • A4674A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	<ul style="list-style-type: none"> <li>• Fabric (no QuickLoop)</li> <li>• For D8602A/B, set "InitAsNport=1" parameter in Registry</li> </ul>
HP/Brocade 2800 • A5624A • Firmware 2.1.3		QLogic QLA-2200F • Driver v7.05.05 + SNIA			
HP FC-64 Director • A6534A/AZ • Firmware 1.1.2		Library Patch			
HP 6164 • A7326A • Firmware 2.4.1		Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware			
HP switch 8/16B • A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01		3.82a1			

HP/Brocade 2400	Windows 2000	HP D8602A/B • Driver v2.06	Bridge FC 4/1 HV • A4688A • Firmware 2008e	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00	• Fabric (no QuickLoop) • For D8602A/B, set "InitAsNport=1" parameter in Registry
HP/Brocade 2800		QLogic QLA-2200F • Driver v7.05.05 + SNIA Library Patch	Surestore Interface Manager • A6356A with A4673A cards	Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	
HP FC-64 Director					
• A6534A/AZ					
• Firmware 2.1.3					
HP 6164		Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware			
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B			3.82a1		
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	Windows 2000	HP D8602A/B • Driver v2.06	Bridge FC 2/1 LV • A4689A • Firmware 2008e	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	• Fabric (no QuickLoop) • For D8602A/B, set "InitAsNport=1" parameter in Registry
HP/Brocade 2800		QLogic QLA-2200F • Driver v7.05.05 + SNIA Library Patch	Surestore Interface Manager • A6356A with A4674A cards		
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164		Emulex LP8000-N1,-F1 • Driver v4.52a7 + firmware			
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B			3.82a1		
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	HP 9000	<ul style="list-style-type: none"> <li>A3740A (V, N, L classes)</li> <li>A3636A (T class)</li> <li>A3591A (R, D classes)</li> <li>A3404A (K class)</li> </ul>	Not Currently Supported - Plans TBD	Not Currently Supported - Plans TBD	Not Currently Supported - Plans TBD
HP/Brocade 2800	HP-UX 11.0 (32-bit)				
	• A5624A				
	• Firmware 2.1.3				
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	HP 9000	<ul style="list-style-type: none"> <li>A3740A (V, N, L classes)</li> <li>A3636A (T class)</li> <li>A3591A (R, D classes)</li> <li>A3404A (K class)</li> </ul>	Not Currently Supported - Plans TBD	Not Currently Supported - Plans TBD	Not Currently Supported - Plans TBD
• A5625A	HP-UX 11.0				
• A5667A	& 11.i (64-bit)				
• Firmware 2.1.3					
HP/Brocade 2800					
• A5624A					
• Firmware 2.1.3					
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	HP 9000	On HSC-Bus:	FC Bridge 4/2	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT)	• Fabric (no QuickLoop) • See Note 1
• A5625A	HP-UX	• A6685A (K class)	• A3308A		
• A5667A	11.0 & 11.i	• A6684A (R, D classes)	• A3511A		
• Firmware 2.1.3			• A3511AZ		
			• Firmware 4010		
HP/Brocade 2800		On PCI Bus			
• A5624A		• A5158A (SuperDome, rp8400, V, N, L, A classes)		• Firmware 1.33 Surestore 10/180 and 20/700 (DLT & 9840)	
• Firmware 2.1.3				• Firmware 2.00 Surestore 10/588 (DLT & 9840)	
HP FC-64 Director		• A6795A (SuperDome, rp8400, V, N, L, A classes)		• Firmware 1.9.03	
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	HP 9000	On HSC-Bus:	Bridge FC 4/1 HV	Surestore 10/180 and 20/700 (DLT & 9840)	• Fabric (no QuickLoop)
• A5625A	HP-UX	• A6685A (K class)	• A4688A		• See Note 1
• A5667A	11.0 & 11.i	• A6684A (R, D classes)	• Firmware 2008e		
• Firmware 2.1.3				• Firmware 2.00 Surestore 10/588 (DLT & 9840)	
HP/Brocade 2800		On PCI Bus	Surestore Interface Manager	• Firmware 1.9.03	
• A5624A		• A5158A (SuperDome, rp8400, V, N, L, A classes)	• A6356A with A4673A cards		
• Firmware 2.1.3					
HP FC-64 Director		• A6795A (SuperDome, rp8400, V, N, L, A classes)			
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	HP 9000	On HSC-Bus:	Bridge FC 2/1 LV	Surestore 10/180	• Fabric (no QuickLoop)
• A5625A	HP-UX	• A6685A (K class)	• A4689A	and 20/700 (LTO)	• See Note 1
• A5667A	11.0 & 11.i	• A6684A (R, D classes)	• Firmware 2008e	• Firmware 2.00	
• Firmware 2.1.3					
HP/Brocade 2800		On PCI Bus	Surestore Interface Manager		
• A5624A		• A5158A (SuperDome, rp8400, V, N, L, A classes)	• A6356A with A4674A cards		
• Firmware 2.1.3		• A6795A (SuperDome, rp8400, V, N, L, A classes)			
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	HP 9000	On HSC-Bus:	Internal FC Card	Surestore 2/20, 4/40, 6/60, /80, 10/100, and 6/140 tape libraries (DLT)	• Fabric (no QuickLoop)
• A5625A	HP-UX	• A6685A (K class)	• A5590A (HVDS)	• A4687A (LVDS)	• See Note 1
• A5667A	11.0 & 11.i	• A6684A (R, D classes)			
• Firmware 2.1.3					
HP/Brocade 2800		On PCI Bus		• Firmware 1.33	
• A5624A		• A5158A (SuperDome, rp8400, V, N, L, A classes)			
• Firmware 2.1.3		• A6795A (SuperDome, rp8400, V, N, L, A classes)			
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	HP 9000	On HSC-Bus:	Internal FC Card	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO)	• Fabric (no QuickLoop) • See Note 1
• A5625A	HP-UX	• A6685A (K class)	• A4673A (HVDS)		
• A5667A	11.0 & 11.i	• A6684A (R, D classes)	• A4674A (LVDS)		
• Firmware 2.1.3					
HP/Brocade 2800		On PCI Bus		• Firmware 1.33	
• A5624A		• A5158A (SuperDome, rp8400, V, N, L, A classes)			
• Firmware 2.1.3		• A6795A (SuperDome, rp8400, V, N, L, A classes)			
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	SUN Solaris	SBUS	Internal FC Card	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT)	• Fabric (no QuickLoop) • HBA's fca_nport parameter should be set to 1
• A5625A	7	• JNI FC64- 1063	• A5590A (HVDS)		
• A5667A			• A4687A (LVDS)		
• Firmware 2.1.3	32 bit				
HP/Brocade 2800		PCI-Bus		• Firmware 1.33	
• A5624A		• JNI FC- 1063			
• Firmware 2.1.3					
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	SUN Solaris 7	SBUS • JNI FC64- 1063	Internal FC Card • A4673A (HVDS) • A4674A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	• Fabric (no QuickLoop) • HBA's fca_nport parameter should be set to 1
HP/Brocade 2800	32 bit	PCI-Bus • JNI FC- 1063			
HP FC-64 Director					
• A6534A/AZ					
• Firmware 2.1.3					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					
HP/Brocade 2400	SUN Solaris 7	SBUS • JNI FC64- 1063	Bridge FC 4/1 HV • A4688A • Firmware 2008e	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00	• Fabric (no QuickLoop) • HBA's fca_nport parameter should be set to 1
HP/Brocade 2800	32 bit	PCI-Bus • JNI FC- 1063	Surestore Interface Manager • A6356A with A4673A cards	Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	
HP FC-64 Director					
• A6534A/AZ					
• Firmware 1.1.2					
HP 6164					
• A7326A					
• Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ					
• A7347A/AZ					
• A7340A/AZ					
• Firmware 3.01					

HP/Brocade 2400	SUN Solaris • A5625A • A5667A • Firmware 2.1.3	SBUS • JNI FC64-1063 PCI-Bus • JNI FC-1063	Bridge FC 2/1 LV • A4689A • Firmware 2008e Surestore Interface Manager • A6356A with A4674A cards	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	<ul style="list-style-type: none"> <li>• Fabric (no QuickLoop)</li> <li>• HBA's fca_nport parameter should be set to 1</li> </ul>
HP/Brocade 2800	• A5624A • Firmware 2.1.3				
HP FC-64 Director	• A6534A/AZ • Firmware 1.1.2				
HP 6164	• A7326A • Firmware 2.4.1				
HP switch 8/16B	• A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01				
HP/Brocade 2400	Novell Netware • A5625A • A5667A • Firmware 2.1.3	QLogic QLA-2200F • Driver v6.50c + firmware 1.74	Internal FC Card • A5590A (HVDS) • A4687A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (DLT) • Firmware 1.33	<ul style="list-style-type: none"> <li>• Fabric (no QuickLoop)</li> </ul>
HP/Brocade 2800	• A5624A • Firmware 2.1.3				
HP 6164	• A7326A • Firmware 2.4.1				
HP switch 8/16B	• A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01				
HP/Brocade 2400	Novell Netware • A5625A • A5667A • Firmware 2.1.3	QLogic QLA-2200F • Driver v6.50c + firmware 1.74	Internal FC Card • A4673A (HVDS) • A4674A (LVDS)	Surestore 2/20, 4/40, 6/60, 8/80, 10/100, and 6/140 tape libraries (LTO) • Firmware 1.33	<ul style="list-style-type: none"> <li>• Fabric (no QuickLoop)</li> </ul>
HP/Brocade 2800	• A5624A • Firmware 2.1.3				
HP 6164	• A7326A • Firmware 2.4.1				
HP switch 8/16B	• A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01				

HP/Brocade 2400	Novell Netware 5.x	QLogic QLA- 2200F • Driver v6.50c + firmware 1.74	Bridge FC 4/1 HV • A4688A • Firmware 2008e Surestore Interface Manager • A6356A with A4673A cards	Surestore 10/180 and 20/700 (DLT & 9840) • Firmware 2.00 Surestore 10/588 (DLT & 9840) • Firmware 1.9.03	• Fabric (no QuickLoop)
HP/Brocade 2800					
• A5624A • Firmware 2.1.3					
HP 6164					
• A7326A • Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01					
HP/Brocade 2400	Novell Netware 5.x	QLogic QLA- 2200F • Driver v6.50c + firmware 1.74	Bridge FC 2/1 LV • A4689A • Firmware 2008e Surestore Interface Manager • A6356A with A4674A cards	Surestore 10/180 and 20/700 (LTO) • Firmware 2.00	• Fabric (no QuickLoop)
HP/Brocade 2800					
• A5624A • Firmware 2.1.3					
HP 6164					
• A7326A • Firmware 2.4.1					
HP switch 8/16B					
• A7346A/AZ • A7347A/AZ • A7340A/AZ • Firmware 3.01					
Brocade 2800	OpenVMS V7.3-1	DS-KGPSA-EA • Driver VMS 731_update -V0100	Compaq MDR • Firmware 1180	Compaq TL891 (DLT8000) • Firmware 05.19	• Fabric
• Firmware 2.6.0C					

Note 1 - HP-UX minimum fabric driver requirements and dependencies

<b>Platform</b>	<b>FC HBA</b>	<b>driver release (version)</b>	<b>FCMS driver dependency patch</b>
HP-UX 11.0 (64 bit only)	A5158A	AP0900 (B.11.00.04)	PHKL_23939
HP-UX 11.0 (64 bit only)	A6795A	AR1201 (B.11.00.10)	PHKL_23939
HP-UX 11.0 (32/64 bit)	A6684A	Web only (B.11.00.09)	PHKL_23939
HP-UX 11.0 (32/64 bit)	A6685A	Web only (B.11.00.09)	PHKL_23939
HP-UX 11.i (64 bit only)	A5158A	AP0301 (B.11.11.04)	PHKL_23626
HP-UX 11.i (64 bit only)	A6795A	AR1201 (B.11.11.09)	PHKL_23626
HP-UX 11.i (64 bit only)	A6684A	Web only (B.11.11.07)	PHKL_23626
HP-UX 11.i (64 bit only)	A6685A	Web only (B.11.11.07)	PHKL_23626

For driver released presented, it is important that the dependency patch for the FCMS driver is installed PRIOR to installing the Application Release with the fabric driver.

<b>SAN hub supported configuration</b>					
<b>server/OS</b>	<b>FC HBA</b>	<b>FC hub</b>	<b>loop mode</b>	<b>FC interface</b>	<b>tape libraries</b>
HP 9000	HP HBA	Short Wave	Arbitrated-Loop	FC Bridge 4/2	Surestore 2/20
HP-UX 11.0	A3740A	(10 SW Ports)		<ul style="list-style-type: none"> <li>• A3308A</li> <li>• A3511A</li> <li>• A3511AZ</li> <li>• Firmware 4010</li> </ul>	Surestore 4/40
	A3636A	• A3724A	(Note: Only a single server per loop is supported)		Surestore 6/60
	A3404A	• A3724AZ			Surestore 6/140
	A3591B				<ul style="list-style-type: none"> <li>• Firmware 1.14</li> </ul>
	A5158A	Long Wave (9 SW Ports, 1 LW Port)			Surestore 10/180
		• A4839A			Surestore 20/700
		• A4839AZ			<ul style="list-style-type: none"> <li>• Firmware 2.00</li> </ul>
HP 9000	HP HBA	Short Wave	Arbitrated-Loop	Internal FC Card	Surestore 2/20
HP-UX 11.0	A3740A	(10 SW Ports)		<ul style="list-style-type: none"> <li>• A5590A (HVDS)</li> <li>• A4687A (LVDS)</li> </ul>	Surestore 4/40
	A3636A	• A3724A	(Note: Only a single server per loop is supported)		Surestore 6/60
	A3404A	• A3724AZ			Surestore 6/140
	A3591B				<ul style="list-style-type: none"> <li>• Firmware 1.14</li> </ul>
	A5158A	Long Wave (9 SW Ports, 1 LW Port)			
		• A4839A			
		• A4839AZ			