Peregrine AssetCenter 4.3 Cable and Circuit



© Copyright 2004 Peregrine Systems, Inc. All Rights Reserved.

Information contained in this document is proprietary to Peregrine Systems, Incorporated, and may be used or disclosed only with written permission from Peregrine Systems, Inc. This manual, or any part thereof, may not be reproduced without the prior written permission of Peregrine Systems, Inc. This document refers to numerous products by their trade names. In most, if not all, cases these designations are claimed as Trademarks or Registered Trademarks by their respective companies.

Peregrine Systems [®] and AssetCenter [®] are trademarks of Peregrine Systems, Inc. or its subsidiaries.

This document and the related software described in this manual are supplied under license or nondisclosure agreement and may be used or copied only in accordance with the terms of the agreement. The information in this document is subject to change without notice and does not represent a commitment on the part of Peregrine Systems, Inc. Contact Peregrine Systems, Inc., Customer Support to verify the date of the latest version of this document.

The names of companies and individuals used in the sample database and in examples in the manuals are fictitious and are intended to illustrate the use of the software. Any resemblance to actual companies or individuals, whether past or present, is purely coincidental.

If you need technical support for this product, or would like to request documentation for a product for which you are licensed, contact Peregrine Systems, Inc. Customer Support by email at support@peregrine.com.

If you have comments or suggestions about this documentation, contact Peregrine Systems, Inc. Technical Publications by email at doc_comments@peregrine.com.

This edition applies to version 4.3 of the licensed program

AssetCenter

Peregrine Systems, Inc. Worldwide Corporate Campus and Executive Briefing Center 3611 Valley Centre Drive San Diego, CA 92130 Tel 800.638.5231 or 858.481.5000 Fax 858.481.1751 www.peregrine.com



Cable and Circuit Table of Contents

Introduction (Cable and Circuit)	11
Who is the Cable and Circuit module intended for? .	11 12
How to use this guide	12
Chapter 1. Overview (Cable and Circuit)	17
Areas covered by the Cable and Circuit module	17
Principal concepts	19
Chapter 2. Presentation of the practical case (Cable and Circuit)	21
Chapter 3. Implementing cable management (Cable and Circuit)	25
Preliminary steps	25
Cable-device types	27
Cable types	28
Cable roles	29
Colors to use for the color codes	30
Color codes	33
Label rules	37
Types of pairs and conductors	43
Connection types	45

Cable duties	48
Locations	50
Projects and work orders associated with cabling	52
Natures for cables and cable devices	55
Brands of cable and cable device models	58
Cable models	59
Cable device models without slots.	63
Slot types	68
Cable device models with slots	72
Topologies	76
Topology groups	82
Termination-field configurations	86
Chapter 4. Termination fields	97
Create a termination field wizard	99
Expand termination field wizard	104
Duplicate wiring closet wizard	110
	110
Chapter 5. Cable devices, cables and connections - manual creation	117
Cable devices - manual creation	118
Cables - manual creation	129
Connections - manual creation	132
Chapter 6. Connections - creation with the wizards	145
Run riser cables wizard	145
Run lateral cables wizard	159
Cross connect bundles wizard	168
	100
Chapter 7. Viewing the traces	179
Cable cross-connections wizard	180
Device cross-connections wizard	182
Display device traces wizard	184
Display cable traces wizard	186
Chapter 8. Glossary (Cable and Circuit)	189
AssetCenter key terms (Cable and Circuit)	189
Key terms of the profession (Cable and Circuit)	207
Chapter 9. References (Cable and Circuit)	219
Menus and tabs (Cable and Circuit)	219

Toolbar icons (Cable and Circuit)	224
Interface options (Cable and Circuit)	224
Tables (Cable and Circuit)	224
Interdependence of tables used in cable management (Cable and Circuit)	229
Itemized lists (Cable and Circuit)	232
Calculated fields (Cable and Circuit)	233
Counters (Cable and Circuit)	234
Actions and wizards (Cable and Circuit)	235
Modules of the AssetCenter Server (Cable and Circuit)	238
System data and Line-of-business data (Cable and Circuit)	239
Reports and forms (Cable and Circuit)	240
Automatic actions (Cable and Circuit)	240
APIs (Cable and Circuit)	241
Views (Cable and Circuit)	241
Other sources of information (Cable and Circuit)	241
Indexes	243

Cable and Circuit List of Figures

1.1. Cable and Circuit module - area of coverage	18				
2.1. Practical case - locations to use	22				
2.2. Practical case - network to use	23				
3.1. Color codes - data model	34				
3.2. Labels and label rules - data model	38				
3.3. Cable label - example	39				
3.4. Pair/conductor types - data model	44				
3.5. Duties - data model	49				
3.6. Practical case - locations to use	51				
3.7. Cables and cable devices - data model	56				
3.8. Slots - data model	70				
3.9. Topologies - data model	77				
3.10. Topology groups - data model	83				
3.11. Topologies - correspondence between the termination field of a network	84				
3.12. Termination-field configuration - data model	87				
3.13. Example of termination-field configuration - representation in AssetCenter					
3.14. Example of termination-field configuration - correspondence at the termination field level	89				
3.15. Termination-field configuration - example of the impact resulting from changing the starting					
position	89				
3.16. Termination-field configuration - example of the impact resulting from changing the cable device					
and role orientations	90				

3.17. Termination-field configuration - example of the impact resulting from changing the flow
specification
3.18. Termination-field configuration - signification of the starting positions
3.19. Termination-field configuration - signification of the flow specification
3.20. Practical case - Termination-field configuration to create
5.1. Cables and cable devices - data model
5.2. Ports and virtual bundles - representation
5.3. Double-sided devices (port/port) - representation
5.4. Double-sided devices (port/pins) - representation
5.5. Double-sided devices (pin/pin) - representation
5.6. Cable link - representation of implicated components
5.7. Cable links - simple data model
5.8. Cable links - correspondence between the cable link to represent and the database 136
5.9. Cable links - detailed data model
7.1. Cable cross-connections wizard - browser window
7.2. Device cross-connections wizard - browser window
7.3. Display device traces wizard - browser window
7.4. Display cable traces wizard - browser window
8.1. Cable with its pairs and its wires - photo
8.2. Color code - relation between cable wires, connector pins and colors
8.3. Cable device slots - representation
8.4. Cable label - example
8.5. RJ-45 connector - photo
8.6. Adapter - photo
8.7. Rack - photo
8.8. Punchdown block - photos
8.9. Vertical distribution of a cable network - representation
8.10. Lateral distribution of a cable network - representation
8.11. Hub - photo
8.12. Patch cord - photo
8.13. Patch panel - photo
8.14. Repeater - photo
8.15. Router - photo
8.16. Switch - photo

Cable and Circuit List of Tables

2.1. Practical case - list of components to use	•	24
3.1. Color codes - Fields and links that must absolutely be populated		35
3.2. Label rules - Fields and links that must absolutely be populated		40
3.3. Pair/conductor types - Fields and links that must absolutely be populated	•	45
3.4. Connection types - Fields and links that must absolutely be populated	•	46
3.5. Cable duties - Fields and links that must absolutely be populated		50
3.6. Projects and work orders associated with cabling - Fields and links that must absolutely be populated	ted	
		53
3.7. Natures reserved for cables and cable devices - Fields and links that must absolutely be populate	d	
		57
3.8. Brands of cable and cable device models - Fields and links that must absolutely be populated .	· •	58
3.9. Cable models - Fields and links that must absolutely be populated	•	60
3.10. Create pairs wizard - description of fields to populate	•	61
3.11. Create pairs wizard - created or modified data	· •	62
3.12. Models of cable devices without slots - Fields and links that must absolutely be populated .		64
3.13. Create ports wizard - description of fields to populate	· •	66
3.14. Create ports wizard - data created or modified by the wizard	· •	66
3.15. Slot types - Fields and links that must absolutely be populated	· •	71
3.16. Models of cable devices with slots - Fields and links that must absolutely be populated .		73
3.17. Create slots wizard - description of fields to populate	•	74
3.18. Create slots wizard - created or modified data	· •	75
3.19. Topologies - Fields and links that must absolutely be populated		78

3.20. Topology groups - Fields and links that must absolutely be populated
3.21. Termination-field configurations - Fields and links that must absolutely be populated 93
4.1. Termination fields - Fields and links that must absolutely be populated
4.2. Create a termination field wizard - description of fields to populate
4.3. Create a termination field wizard - data created or modified by the wizard
4.4. Expand termination field wizard - description of fields to populate
4.5. Expand termination field wizard - data created or modified by the wizard
4.6. Duplicate wiring closet wizard - description of fields to populate
4.7. Duplicate wiring closet wizard - data created or modified by the wizard
5.1. Cable devices - Fields and links that must absolutely be populated
5.2. Cables - Fields and links that must absolutely be populated
5.3. Connections - Fields and links that must absolutely be populated
6.1. Run riser cables wizard - description of fields to populate
6.2. Run riser cables wizard - created or modified data
6.3. Run lateral cables wizard - description of fields to populate
6.4. Run lateral cables wizard - created or modified data
6.5. Cross connect bundles wizard - description of fields to populate
6.6. Cross connect bundles wizard - created or modified data
8.1. Color codes - description for an RJ-45 connector
9.1. Menus and tabs (Cable and Circuit) - list
9.2. Tables (Cable and Circuit) - list
9.3. Interdependence of tables (Cable and Circuit) - table
9.4. Itemized lists (Cable and Circuit) - list
9.5. Calculated fields (Cable and Circuit) -list
9.6. Counters (Cable and Circuit) - list
9.7. Actions and wizards (Cable and Circuit) - list
9.8. Other documentation (Cable and Circuit) -list

Introduction (Cable and Circuit)



! Warning:

The Cable and Circuit module relies on the technical knowledge of the following domains:

- Organization of cabling systems
- Cabling techniques
- Cabling material
- Cabling standards

This guide does not explain the technical knowledge related to the domains mentioned above; it is assumed that you are already familiar with it.

Who is the Cable and Circuit module intended for?

The Cable and Circuit module is mainly intended for organizations with a complex networking system (LAN, WAN, telephony, video, etc).

In general, it is used by the following people:

Network administrators

Maintenance technicians

What does the Cable and Circuit module do?

The Cable and Circuit module enables you to perform the following tasks:

- Conduct a physical and detailed inventory of your cables and cable devices:
 - Technical description
 - Geographic location
- Locate your cables and cable devices:
 - Labeling system
 - Description of links between cable devices and cables.
 - Verify the continuity of the cables' paths (from the user to the server or to the PABX).
 - Create projects and work orders to mange the placement or removal of cables and cable devices.

Managing these tasks enables you to:

- Locate each cable and cable device.
- Easily intervene in case of a problem at level of the faulty cable or cable device.
- Create, modify or cancel connections.
- Homogenize the mode of connection between cables and cable devices.
- Define cabling standards all the way to the conductors and connector pins.

How to use this guide

Chapter Overview (Cable and Circuit)

This chapter outlines some important principals relating to the cabling of a network and explains how AssetCenter represents a cable network.

You should read this information to form a general idea of how AssetCenter functions.

Chapter Presentation of the practical case (Cable and Circuit)

To make this guide as simple as possible, we have developed an example that is used throughout its entirety. This example represents a part of a network in the AssetCenter database. Using this example, you will be guided through the various tables involved in the Cable and Circuit module and will use most of the cabling wizards that automate the most common tasks.

Read the chapter Presentation of the practical case (Cable and Circuit) [page 21] to better understand what you are going to create in the AssetCenter database using the practical case, and how to best use this practical case throughout the course of this guide.

Chapter Implementing cable management (Cable and Circuit)

Before creating cable devices, cables and cable links, it is indispensable that you perform some preliminary tasks and populate certain tables of reference.

Read this chapter to understand what these tasks are, what purpose these tables of reference serve and how to populate them.

The steps outlined in this chapter are done so in an ordered fashion. You must respect this order in order to properly perform these steps.

Each step brings you information on the following points:

ጆ Note:

The following points are only detailed if necessary.

- General information:
 - Definitions

This section indicates which definitions you should consult in the chapter Glossary (Cable and Circuit) [page 189]. It is important to read these definitions since each one of these glossary terms has a precise signification in AssetCenter.

Table names

Names of the reference tables to populate.

Access menu

Menu enabling you to access the tables to populate.

Simplified data model

This model is for the administrator who wants to understand how the database is structured. This information is indispensable for creating

data in an appropriate manner and for customizing the use of AssetCenter for your personal needs.

Process of creating records

This point provides you the information you need to create records in the table.

Prerequisites

In order to populate certain tables, you need to have previously populated certain others. The list of such tables is provided for you in this point.

· Fields and links that must absolutely be populated

There are numerous fields and links in the AssetCenter database. Certain are mandatory, others are optional. This point provides you the list of fields and links that are mandatory in order for the Cable and Circuit module to function correctly.

Creation of records for the practical case

Nothing speaks louder than an example! That's why we have illustrated each step necessary to implement the Cable and Circuit module with a concrete example. All you need to do is adapt this example to your own needs.

In order to keep the amount of extra information to a minimum, the detailed descriptions of fields and links present in the database is not provided in this guide. You can obtain this information by using the contextual help available for these fields (Help on this field).

To learn more about the help on fields and links, refer to chapter References (Cable and Circuit) [page 219], section Other sources of information (Cable and Circuit) [page 241].

In the same way, we will not detail each step taken to create records in all the different tables. This is because the steps taken are always the same and always respect the general interface of AssetCenter application.

Chapter Termination fields

Once the tables of reference are created, you can concentrate on creating the termination fields. Termination fields must be created before running the riser and lateral cables in order to take advantage of the cabling wizards, which help you accomplish these tasks.

Read this chapter to understand how to create, expand and duplicate termination fields.

ጆ Note:

To create termination fields, you use cabling wizards and rely on the termination-field configurations.

Chapter Cable devices, cables and connections - manual creation

Of course, you can also create cable devices, cables and connections manually. This chapter explains how to do this.

However, AssetCenter is also provided with cabling wizards that automate these common tasks.

Read this chapter if you wish to learn how these wizards create such records. Otherwise, you can skip this chapter.

Chapter Connections - creation with the wizards

This chapter presents the cabling wizards that automate the main tasks required to manage your cables.

Each wizard is presented with the following information:

- Functions performed by the wizard
- Prerequisites
- Launching the wizard
- Information used when using the wizard
- Data created or modified by the wizard
- Viewing the result
- After having launched the wizard
- Resolving possible problems

Read this chapter to learn about the possibilities offered by these wizards as well as how they function.

Chapter Viewing the traces

A cable network is composed of numerous cables and connections. In order to help you locate them all, AssetCenter represents the traces of your network. Read this chapter to understand how to access the representation of these traces, how to read them and how to browse through them.

Chapter Glossary (Cable and Circuit)

The terminology for the Cable and Circuit module is very specialized. The glossary that we propose contains the key terms used in the AssetCenter application and a selection of terms common to this profession. Read this glossary to better understand what these terms signify.

Chapter References (Cable and Circuit)

This chapter contains exhaustive and systematic reference information.

Read this chapter if you want to learn about all the AssetCenter components that are linked to the Cable and Circuit module, or to access advanced or supplementary information.

Overview (Cable and Circuit)

CHAPTER

Managing a cable network is extremely complex: There is a large number of cables and cable devices involved in a network. You need to be able to locate these cables and cable devices with precision and simplicity.

AssetCenter offers this possibility and enables you to manage large quantities of information that would otherwise be difficult to store on paper or in an generic database.

Areas covered by the Cable and Circuit module

This section covers certain aspects of managing a cable network and explains how the network is represented in AssetCenter. Some principal terms are also defined in this section.

The Cable and Circuit module concerns the "hidden" part of the cable network, from the wall outlet to the termination fields.

Examples:

• The invisible side of the wall outlet is also taken into consideration. The visible side of the outlet and its connection to computers, peripheral devices and telephones is not taken into consideration here.

• The termination-field devices, the riser and the lateral cables are also included here. The servers, the PABX and the connection to them are not concerned by the module.

The following illustration shows you the part of a network covered by the Cable and Circuit module.



Figure 1.1. Cable and Circuit module - area of coverage

Principal concepts

This section explains the key terms used in the Cable module. For definitons of these terms: ► Glossary (Cable and Circuit) [page 189]

Cables: pairs, conductors, bundles

- Pair/conductor [page 200]
- ▶ Bundle [page 197]

Cable devices: pins, terminals, ports

- Pin/ Terminal [page 189]
- ▶ Port [page 201]

The connection between cable devices and cables: connection types

Connection type [page 204]

The cable devices and cables are connected in the following ways:

- From device pin to device pin.
- · From device pin to cable conductor or wire.
- From device port to device port.
- From device port to cable bundle.

Thus, AssetCenter distinguishes between two types of connections:

- By pin: Each pin is identified.
- By port: Pins are not longer identified individually.

Connections: cable links, user and host directions

- ▶ Cable link [page 199]
- ▶ Host [page 199]
- ▶ User [page 206]

💋 Note:

The patch cords used to cross connect the termination-field devices are not described in the database. Only the cable links between the ports and these devices are described.

Locating wires and pins: color codes

► Color code [page 190]

2 Presentation of the practical case (Cable and Circuit)

In order to facilitate your learning experience, we will develop a practical case throughout the course of this guide.

This will help you better understand what the Cable and Circuit module represents and how it represents it.

🐓 Warning:

For an example to work, you must perform each step in its entirety and respect the order in which these steps are presented. Only the fields and links that are absolutely necessary to perform most procedures are referred to in this guide. Feel free to explore the utility of the other fields and links on your own.

Locations of the practical case

The network that we are going to represent is divided up in the locations illustrated by the following diagram:





Network of the practical case

The following diagram illustrates which portion of the network we will use in the AssetCenter database for our practical case.





This network contains components that will not be used in the example illustrating the Cable and Circuit module:

- 1 telephone connected to the wall outlet by 1 telephone cable.
- 1 stationary computer connected to the wall outlet by 1 LAN cable.
- 1 portable computer connected to the wall outlet by 1 LAN cable.

Then there are the components that will be used:

Table 2.1. Practical case - list of components to use

Location on the diagram	Quantity	Component	Composition	Connection type
4	1	Termination field	2 columns and 6 rows	Does not apply.
2	1	Wall outlet	3 ports with 8 pins	By pin
<mark>3</mark>	4	Patch panels	Back side: 24 ports with 8 preloaded pins	By port
			Front side: 24 RJ45 ports	By port (patch)
4	6	Patch panels	Back side: 256 pins (32 x 8)	By pin
			Back side: 24 RJ45 ports	By port (patch)
5	2	Switch	10 slots	Does not apply.
-	1	Module (for one of the switch slots)	8 RJ45 ports	By port
6	3	Lateral cables	4 twisted pairs with 2 copper wires	Does not apply.
4	1	Riser cable	32 twisted pairs with 2 copper wires	Does not apply.
*	1	Riser cable	4 twisted pairs with 2 copper wires	Does not apply.
2	1	Port	2 pins (back side)	By pin
10	1	Port	8 pins (front side)	By port
11	1	Port	$\frac{8 \text{ pins (front side)}}{8 \text{ pins (back side)}}$	By port By pin
12	2	Ports	8 pins (2 sides)	By port
13	2	Ports	8 pins (front side)	By port
14	1	Port	8 pins (back side)	By port

3 Implementing cable management (Cable and Circuit)

Before implementing the Cable and Circuit module, you need to perform certain preliminary steps, which are described in this chapter.

You must then define the reference information that will be used to create and define your cables, cable devices and cable links. This reference information must be created first: You can create it all right away, or do so as you go.

Preliminary steps

To continue reading this guide

Before continuing to read this guide, you must first:

- 1 Install AssetCenter.
- 2 Execute AssetCenter.
- 3 Connect to AssetCenter's demonstration database.
- 4 Activate the Cable and Circuit module using the **File**/ **Activate modules** menu item.

Working with your own database using the Cable and Circuit module

In order to work with your own database, you must:

- 1 Install AssetCenter.
- 2 Execute AssetCenter Database Administrator.
- 3 Create your database by importing the Cable and Circuit **line-of-business data** (Procedure detailed below).
- 4 Insert your user's license that includes authorization for the Cable and Circuit module.
- 5 Execute AssetCenter.
- 6 Connect to your database.
- 7 Activate the Cable and Circuit module using the **File**/ Activate modules menu item.

Importing the System data when you create your database

Proceed in the following manner:

- 1 Execute AssetCenter Database Administrator.
- 2 Select the File/ Open menu item.
- 3 Select the **Open database description file create new database** option.
- 4 Select the **gbbase.xml** file, located in the **config** sub-folder of the AssetCenter installation folder.
- 5 Select the Action/ Create database menu item.
- 6 Check the Create system data option.
- 7 Populate the other fields and continue creating the database.

Importing the Line-of-business data when you create the database

Proceed in the following manner:

- 1 Execute AssetCenter Database Administrator.
- 2 Select the File/ Open menu item.
- 3 Select the **Open database description file create new database** option.
- 4 Select the **gbbase.xml** file, located in the **config** sub-folder of the AssetCenter installation folder.
- 5 Select the Action/ Create database menu item.
- 6 Check the **Import extra data** option.

- 7 Select the Cable and Circuit Line-of-business data from the Data to import list.
- 8 Populate the other fields and continue creating the database.

Importing the Line-of-business into an existing database

Proceed in the following manner:

- 1 Execute AssetCenter Database Administrator.
- 2 Select the File/ Open menu item.
- 3 Select the **Open database description file create new database** option.
- 4 Select the **gbbase.xml** file, located in the **config** sub-folder of the AssetCenter installation folder.
- 5 Select the Action/ Create database menu item.
- 6 Unselect the Create database option.
- 7 Unselect the **Create system data** option.
- 8 Check the Import extra data option.
- 9 Select the Cable and Circuit Line-of-business data from the Data to import list.
- 10 Click Create.

To learn more about installing AssetCenter

Refer to the Installation guide.

Cable-device types

Definitions

► Cable device type [page 205]

Table names

The types of cable devices are stored in the **amDeviceType** itemized list in the **Itemized lists** table (**amItemizedList**).

Access menu

Administration/ Itemized lists

Creating cable device types

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amDeviceType** itemized list.
- 3 Create the values that you need.

Prerequisites

No prerequisites.

The **amDeviceType** itemized list already exists in the **Itemized lists** table.

Creating the cable device types for the practical case

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amDeviceType** itemized list.
- 3 Create the following values if they don't already exist:
 - Switch module
 - Patch panel
 - Wall outlet
 - Switch

Cable types

Definitions

▶ Cable type [page 204]

Table names

The types of cables are stored in the **amCableType** itemized list in the **Itemized lists** table (**amItemizedList**).

Access menu

Administration/ Itemized lists

Creating cable types

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the amCableType itemized list.
- 3 Create the values that you need.

Prerequisites

No prerequisites.

The amCableType itemized list already exists in the Itemized lists table.

Creating the cable types for the practical case

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amCableType** itemized list.
- 3 Create the following values if they don't already exist:
 - Twisted pairs

Cable roles

Definitions

▶ Role [page 202]

Table names

The cable roles are stored in the **amCableRole** itemized list in the **Itemized lists** table (**amItemizedList**).

Access menu

Administration/ Itemized lists

Creating cable roles

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the amCableRole itemized list.

3 Create the values that you need.

Prerequisites

No prerequisites.

The amCableRole itemized list already exists in the Itemized lists table.

Creating the cable roles for the practical case

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amCableRole** itemized list.
- 3 Create the following values if they don't already exist:
 - Riser
 - Lateral

Colors to use for the color codes

Table names

The colors are stored in the Itemized lists table (amItemizedList):

- amColor
- amTipColor
- amRingColor

Access menu

Administration/ Itemized lists

The **amColor**, **amTipColor** and **amRingColor** itemized lists already exist in the **Itemized lists** table.

Creating colors

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amColor** itemized list.
- 3 Create the values that you need.
- 4 Select the **amTipColor** itemized list.

- 5 Create the values that you need.
- 6 Select the **amRingColor** itemized list.
- 7 Create the values that you need.

😯 Tip:

You can begin by creating the colors in the **amColor** itemized list, then copy them into the **amTipColor** and **amRingColor** itemized lists.

Prerequisites

No prerequisites.

Creating the colors for the practical case

We are going to create the colors that we need for the color code entries for our practical case.

First, we will create them in the **amColor** itemized list, and then we will copy them into the **amTipColor** and **amRingColor** itemized lists.

Creating the colors in the amColor itemized list

- 1 Display the list of itemized lists (Administration/ Itemized lists).
- 2 Select the **amColor** itemized list.
- 3 Add the following values to the itemized list:
 - white/blue
 - white/brown
 - white/orange
 - white/green
 - blue
 - blue/white
 - blue/yellow
 - blue/black
 - blue/red
 - blue/violet
 - yellow/blue
 - yellow/brown

- yellow/green
- brown
- brown/white
- brown/yellow
- brown/black
- brown/red
- brown/violet
- black/blue
- black/brown
- black/orange
- black/green
- orange
- orange/black
- red/blue
- red/brown
- red/green
- green
- green/white
- green/yellow
- green/black
- green/red
- green/violet
- violet/blue
- violet/brown
- violet/green

Creating the colors in the amTipColor and amRingColor itemized lists

Follow the same steps you used for the **amColor** itemized list (by creating the same colors).

Color codes

Definition

- ► Color code [page 190]
- ▶ Color code entry [page 196]
- ▶ Ring [page 200]
- ▶ Tip [page 200]

Table names

- Color codes (amColorCode)
- Color code entries (amColorDet)

Access menu

Cable/ Color codes

Simplified data model

Figure 3.1. Color codes - data model



Creating color codes

- 1 Display the list of color codes (Cable/ Color codes).
- 2 For each color code to create:
 - 1 Create a record in the **Color codes** table.
 - 2 Add a color code entry by pair or by conductor.

Prerequisites

We recommend that you first create the colors in the following itemized lists of the **Itemized lists** table (**amItemizedList**):

- amColor
- amTipColor
- amRingColor

If you have not already done this, you can add the colors on the fly while you create the color codes.

Fields and links that must absolutely be populated

Table 3.1. Color codes - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Color codes table (amColorCode)	
Name	Name
Color code entries	ColorDetail
Color code entries table (amColorDet)	
#	sSequenceNumber
Color	Color

Creating the color codes for the practical case

We are going to create 2 color codes and their entries.

Creating the color codes

- 1 Display the list of color codes (Cable/ Color codes).
- 2 Create a new record for each color code in the **Color codes** table (**amColorCode**) and populate the following fields:

Value of the field or link	Record 1	Record 2
Name (Name)	568B - 4 pairs	32 pairs

Creating the entries of color code 568B - 4 pairs

- 1 Select the color code **568B 4 pairs**.
- 2 Create the following color codes:

Value of the # field (sSequenceNum- ber)	Value of the Color field (Color)	Value of the Tip color field (TipColor)	Value of the Ring color field (RingColor)
1	blue	white/blue	blue
2	orange	white/orange	orange
3	green	white/green	green
4	brown	white/brown	brown

Creating the entries for the color code 32 pairs

- 1 Select the color code **568B 32 pairs**.
- 2 Select the color code and create the following color code entries:

Value of the # field (sSequenceNum- ber)	Value of the Color field (Color)	Value of the Tip color field (TipColor)	Value of the Ring color field (RingColor)
1	white/blue	white/blue	blue/white
2	white/brown	white/brown	brown/white
3	white/green	white/green	green/white
4	blue/yellow	blue/yellow	yellow/blue
5	blue/black	blue/black	black/blue
6	blue/red	blue/red	red/black
7	blue/violet	blue/violet	violet/blue
8	yellow/brown	yellow/brown	brown/yellow
9	yellow/green	yellow/green	green/yellow
10	brown/black	brown/black	black/brown
11	brown/red	brown/red	red/brown
12	brown/violet	brown/violet	violet/brown
13	black/orange	black/orange	orange/black
14	black/green	black/green	green/black
15	red/green	red/green	green/red
Value of the # field (sSequenceNum- ber)	Value of the Color field (Color)	Value of the Tip color field (TipColor)	Value of the Ring color field (RingColor)
--	----------------------------------	--	--
16	green/violet	green/violet	violet/green
17	white/blue	white/blue	blue/white
18	white/brown	white/brown	brown/white
19	white/green	white/green	green/white
20	blue/yellow	blue/yellow	yellow/blue
21	blue/black	blue/black	black/blue
22	blue/red	blue/red	red/black
23	blue/violet	blue/violet	violet/blue
24	yellow/brown	yellow/brown	brown/yellow
25	yellow/green	yellow/green	green/yellow
26	brown/black	brown/black	black/brown
27	brown/red	brown/red	red/brown
28	brown/violet	brown/violet	violet/brown
29	black/orange	black/orange	orange/black
30	black/green	black/green	green/black
31	red/green	red/green	green/red
32	green/violet	green/violet	violet/green

Label rules

Definitions

- Label rule [page 201]
- Label [page 196]

Table names

Label rules (amLabelRule)

Access menu

Cable/ Label rules

Simplified data model





Label example

Figure 3.3. Cable label - example



Creating label rules

🐓 Warning:

In order for the wizards to function, you must create label rules to identify the following components:

- Cable devices
- Termination-field devices
- Cables
- Links

😯 Tip:

There are several ways to create cable-link labels according to, for example:

- The connection can be made by port or by pin.
- You can use either the starting and ending numbers in a sequence of pins or you can use all the numbers in the sequence.
- The link can reference a cable or a cable device.

You can create label rules for the following components:

- Bundles
- Pins/ terminals
- Ports
- Pairs/conductors

To create label rules:

- 1 Display the list of label rules (**Cable/ Label rules**).
- 2 Create the records from the list.

Prerequisites

Determine with precision which information you want to use to create labels.

Fields and links that must absolutely be populated

Table 3.2. Label rules - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Field	FieldName
Name	Name
SQL name	SQLName
Script	memScript
Table	TableName

Creating the label rules for the practical case

We are going to create the lable rules we need to use in the practical case in order to:

• Recognize the cables according to their model and their code.

- Name the links.
- Populate the lables and cable devices.

To do this:

- 1 Display the list of label rules (Cable/ Label rules).
- 2 Create a new record for each lable rule in the **Label rules** table (**amLabelRule**) and populate the following fields:

Field	Record 1	Record 2	Record 3	Record 4	Record 5
Name	Practical case -				
	Cables	Link - Sequen-	Wallfield assets	Wall outlet link	Port of a termin-
		tially, by pairs			ation-field patch
					panel link
Table	Cables (amC-	Links (amC-	Assets (amAs-	Links (amC-	Links (amC-
	able)	ableLink)	set)	ableLink)	ableLink)
Field	Label	Label	Label	Label	Label
Script	See below.				

😯 Tip:

To avoid typing the following scripts by hand, you can copy and paste them from the online help to AssetCenter.

The values of the **Script** field are:

• Record 1:

```
RetVal = [Model.Name] + " - " + [Code]
```

• Record 2:

```
Dim lErr As Long
Dim hqPair As Long
Dim strResult As String
Dim strVal As String
hqPair = AmQueryCreate()
lErr = AmQueryExec(hqPair, "SELECT Name FROM amCablePair WHERE lBun
dleId = " & [lBundleId] & " ORDER BY sSequenceNumber")
Do While ( lErr = 0 )
strVal = AmGetFieldStrValue(hqPair, 0)
If ( strResult = "" ) Then
strResult = strVal
Else
strResult = strResult & " " & strVal
```

```
End If

lErr = AmQueryNext(hqPair)

Loop

AmReleaseHandle(hqPair)

RetVal = [Cable.Model.Name] & " (" & [Cable.Label] & ") - (" & strR

esult & ")"
```

• Record 3:

```
Dim lErr
              As Long
Dim hqTFDev As Long
Dim strTFName As String
Dim lCol As Long
Dim lRow
            As Long
hqTFDev = AmQueryCreate()
lErr = AmQueryExec(hqTFDev, "SELECT DeviceTermFieldDev.TerminationF
ield.Name, DeviceTermFieldDev.sHoriz, DeviceTermFieldDev.sVert FROM
amAsset WHERE lAstId = " & [lAstId])
If ( lErr = 0  ) Then
 strTFName = AmGetFieldStrValue(hqTFDev, 0)
 lCol = AmGetFieldLongValue(hqTFDev, 1)
 lRow = AmGetFieldLongValue(hqTFDev, 2)
End If
AmReleaseHandle(hqTFDev)
RetVal = FormatResString("$1 Co: $2 Li: $3", strTFName, lCol, lRow)
```

• Record 4:

RetVal = FormatResString("\$1:\$2", [Device.Label], [Port.PortNo])

• Record 5:

```
RetVal = FormatResString("$1 Port: $2", [Device.Label], [Port.Port
No])
```

When you select the label rule **Practical case - Cables** for a cable, the label will indicate:

- The cable's model.
- The cable's code.

It is presented in the form of:

<Name of the cable model> - <Code of the cable>

Example:

FTP - Category 5 - 4 twisted pairs - 000001

Types of pairs and conductors

Definitions

▶ Pair/Conductor type [page 206]

Table names

Pair/conductor types (amCabPairType)

Access menu

Cable/ Cable pair/conductor types

Simplified data model





Creating pair/conductor types

- 1 Display the list of pair/conductor types (Cable/ Cable pair/conductor types).
- 2 Create as many records as there are pair/conductor types that you use.

Prerequisites

None

Fields and links that must absolutely be populated

Table 3.3. Pair/conductor types - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Name	Name
No. of conductors	sConductors

Creating the pair/conductor types for the practical case

We are going to create a pair type composed of 2 copper wires:

- 1 Display the list of pair/conductor types (Cable/ Cable pair/conductor types).
- 2 Create a new record in the **Pair/Conductor types** table (**amCabPairType**) and populate the following fields:

Field or link to populate	Value
Name (Name)	Copper
No. of conductors (sPairs)	2

Connection types

Definitions

▶ Connection type [page 204]

Table names

Cable connection types (amCabCnxType) Connection pin mappings (amCnxPinMap)

Access menu

Cable/ Cable connection types

Creating connection types

- 1 Identify the connection types that you use in your network.
- 2 Display the list of connection types (Cable/ Cable connection types).
- 3 Create a record by identified connection type.
- 4 If you want to associate each of this connection-type's pins to a color code entry, then you have to populate the **Connection pin mappings** link. Create as many links as the connection type contains pins/terminals.

Prerequisites

.

You need to have already created the color codes.

Fields and links that must absolutely be populated

Table 3.4. Connection types - Fields and links that must absolutely be populated

. . .

Label of the field or link	SQL name of the field or link	Remarks
Connection types tab	le (amCabCnxType)	
Name	Name	
Port-based or pin-	seMode	
based		
No. of pins/terminals	sPinCount	
Color code	ColorCode	
Connection pin map- pings	CnxPinMaps	• If the Port-based or pin-based field has Pin for its value, then this link must be populated.
		• If the Port-based or pin-based field has Port for its value, then this field is optional.
Connection pin mapp	oings table (amCnxPin	nMap)
#	sPinSeq	
Color code entry	ColorCodeDet	

Creating the connection types for the practical case

We are going to create the following connection types:

- RJ45 568B Port
- RJ45 568B Pin

Creating the connection types

- 1 Display the list of connection types (Cable/ Cable connection types).
- 2 Create a new record in the**Connection types** table (**amCabCnxType**) and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2	Value for record 2	
Name (Name)	RJ45 - 568B - Port	RJ45 - 568B - Pin		
Port-based or pin-based	Port	Pin		
(Name)				
No. of pins/terminals (sPin-	0	8		
Count)				
Color code (ColorCode)		568B - 4 pairs		

Populate the Connection pin mappings link for the RJ45 - 568B - Pin connection type.

- 1 Select the **RJ45 568B Pin** connection type.
- 2 Create the connection-pin mapping entries by populating the following fields:

Value of the # field (sPinSeq)	Color code entry (ColorCodeDet)	
1	orange	
2	orange	
3	green	
4	blue	
5	blue	
6	green	
7	brown	

Value of the # field (sPinSeq)	
8	

Color code entry (ColorCodeDet) brown

Cable duties

Definitions

- Duty [page 198]
- **Table names**

Cable duties (amCableDuty)

Access menu

Cable/ Cable duties

Simplified data model

Figure 3.5. Duties - data model



Creating cable duties manually

- 1 Display the list of cable duties (Cable/ Cable duties).
- 2 Create a record for each of the duties that your cable network fulfills.

💡 Tip:

At this stage, we advise against populating the **Topologies** link (**Topology**) since the topologies have not yet been created. It is better to associate a duty with the topologies after they have been created.

Prerequisites

No prerequisites.

Fields and links that must absolutely be populated

Table 3.5. Cable duties - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Name	Name

Creating the cable duties manually for the practical case

We are going to create two duties.

- 1 Display the list of cable duties (Cable/ Cable duties).
- 2 Create a new record and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2
Name (Name)	Data	Voice

Locations

We are introducing the Locations table for the needs of our practical case.

Table names

Locations (amLocation)

Access menu

Portfolio/ Locations

Creating the locations for the practical case

We are going to create the records that correspond to the locations represented by the following diagram:

Figure 3.6. Practical case - locations to use



- 1 Display the list of locations (**Portfolio/ Locations**).
- 2 Create a new record per location and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2	Value for record 3
Name (Name)	Cabled building	1st floor	2nd floor

Field or link to populate	Value for record 1	Value for record 2	Value for record 3
Sub-location of (Par-	Do not populate.	Cabled building	Cabled building
ent)			
Field on link to nonvieto	Value for monoid 4	N.L. C	
Field of link to populate	value for record 4	value for record 5	value for record 6
Name (Name)	Wiring closet for each floor	Main wiring closet	Office 1
Name (Name) Sub-location of (Par-	Wiring closet for each floor Cabled building/1st	Main wiring closet Cabled building/2nd	Office 1 Cabled building/1st

Projects and work orders associated with cabling

The projects and work orders enable you to conserve a trace of the operations carried out on the network:

- Running or removing cables.
- Connecting or disconnecting bundles and ports.
- Installing a cable device.

You need to create projects and work orders before launching the cabling wizards. Due to this constraint, you must create at least one project containing at least one work order.

The cabling wizards do not populate the following tables, unless you select a project and a work order at the end of the wizard's execution:

- Trace outputs (amTraceOutput)
- Trace histories (amTraceHistory)
- Trace operations (amTraceOp)

Table names

- Projects (amProject)
- Work orders (amWorkOrder)

Access menu

- Portfolio/ Projects
- Portfolio/ Work orders

Creating projects and work orders associated to the Cable and Circuit module

- 1 Display the list of projects (**Portfolio**/**Projects**).
- 2 Create a project for each cabling operation you will perform.
- 3 Associate one or more work orders with the project.
- 4 Execute the cabling wizards by referencing the appropriate project and work order.

These wizards automatically populate the following links in the projects:

- Assets (AstProjDescs)
- Cables (ProjectCables)
- **Project traces (ProjectTraces)**

These wizards automatically populate the following links in the work orders:

- Title (Title)
- Work order devices (ProjBien)
- **Project cables** (**ProjCable**)
- **Project traces (ProjTraceOut)**

Prerequisites

No prerequisites.

Fields and links that must absolutely be populated

Table 3.6. Projects and work orders associated with cabling - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	
Projects table (amProject)		
Title	Title	
Work orders	WorkOrders	
Work orders table (amWorkOrd	er)	
Work order #	WONo	

Creating the projects and work orders for the practical case

We are going to create one project per wizard, which you will execute in the practical case. We will also associate a work order to each one of these projects.

Thus, you will be able to consult these projects and work orders in able to better understand what the wizards create, modify or delete.

Creating the projects

- Display the list of projects (Portfolio/ Projects). 1
- 2 Create a new record per project and populate the following fields:

	Label (Title)
Value for record 1	Create a termination field
Value for record 2	Disconnect bundles
Value for record 3	Disconnect ports
Value for record 4	Duplicate a wiring closet
Value for record 5	Swap assets
Value for record 6	Remove cables
Value for record 7	Remove lateral cables
Value for record 8	Remove cables by location
Value for record 9	Expand a termination field
Value for record 10	Cross-connect generic hub
Value for record 11	Cross-connect specific hub
Value for record 12	Cross-connect bundles
Value for record 13	Cross-connect ports
Value for record 14	Cross-connect ports (internal)
Value for record 15	Cross-connect wallfield
Value for record 16	Run lateral cables
Value for record 17	Run riser cables
Value for record 18	Relocate cables
Value for record 19	Transfer project assets
Value for record 20	Relocate project connections
Value for record 21	Transfer project cables

.

Creating a Work orders link for each project

- Select each project one by one. 1
- 2 Select the **Work orders** tab and add a new work order to the project by populating the following fields:

Project label	Value of the # of work orders (WONo)
Create a termination field	Accept the value proposed by AssetCenter.
Disconnect bundles	Accept the value proposed by AssetCenter.
Disconnect ports	Accept the value proposed by AssetCenter.
Duplicate a wiring closet	Accept the value proposed by AssetCenter.
Swap assets	Accept the value proposed by AssetCenter.
Remove cables	Accept the value proposed by AssetCenter.
Remove lateral cables	Accept the value proposed by AssetCenter.
Remove cables by location	Accept the value proposed by AssetCenter.
Expand a termination field	Accept the value proposed by AssetCenter.
Cross-connect generic hub	Accept the value proposed by AssetCenter.
Cross-connect specific hub	Accept the value proposed by AssetCenter.
Cross-connect bundles	Accept the value proposed by AssetCenter.
Cross-connect ports	Accept the value proposed by AssetCenter.
Cross-connect ports (internal)	Accept the value proposed by AssetCenter.
Cross-connect wallfield	Accept the value proposed by AssetCenter.
Run lateral cables	Accept the value proposed by AssetCenter.
Run riser cables	Accept the value proposed by AssetCenter.
Relocate cables	Accept the value proposed by AssetCenter.
Transfer project assets	Accept the value proposed by AssetCenter.
Relocate project connections	Accept the value proposed by AssetCenter.
Transfer project cables	Accept the value proposed by AssetCenter.

Natures for cables and cable devices

The natures define the information that is common to certain groups of assets. The cables and cable devices each require a specific nature that will be associated with the models of cables and cable devices.

The information that you define at the nature level determines whether certain fields and links will be displayed in the detail of models, cables and assets.

Table names

Natures (amNature)

Access menu

Portfolio/ Natures

Simplified data model

Figure 3.7. Cables and cable devices - data model



Creating the natures of cables and cable devices

- 1 Display the list of natures (**Portfolio/ Natures**).
- 2 Create a nature for the cable devices and a nature for the cables.

Prerequisites

No prerequisites.

Fields and links that must absolutely be populated

Table 3.7. Natures reserved for cables and cable devices - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks
Name	Name	
Created	seBasis	Must be set to Asset for the cable devices and
		Cable for the cables.
Management con-	seMgtConstraint	Does not apply to cables. This field must be
straints		set to Unique asset tag for the cable devices.
Also create	seOverflowTbl	Does not apply to cables. This field must be
		set to None for the cable devices.
Cable device	bDevice	Does not apply to cables. This option must be
		checked for the cable devices.
Can be connected	bIsCnxClient	Does not apply to cables. This option must be
		checked for the cable devices.

Creating the natures of cables and cable devices for the practical case

We are going to create a nature for the cable devices and a nature for the cables.

- 1 Display the list of natures (**Portfolio/ Natures**).
- 2 Create a new record per nature and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2	
Name (Name)	Cable	Cable device	
Created (seBasis)	Cable	Portfolio item	
Management constraints	Do not populate.	Unique asset tag	
(seMgtConstraint)			
Also create (seOverflowTbl)	Do not populate.	None	
Cable device (bDevice)	Do not populate.	Check	

Field or link to populate	Value for record 1	Value for record 2
Can be connected (bIsCnxCli-	Do not populate.	Check
ent)		

Brands of cable and cable device models

Table names

 $Brands \ (amBrand)$

Access menu

Portfolio/ Brands

Creating the brands of the cable and cable device models

- 1 Display the list of brands (**Portfolio/ Brands**).
- 2 Create one record per brand of cable device and cable of your network.

Prerequisites

No prerequisites.

Fields and links that must absolutely be populated

Table 3.8. Brands of cable and cable device models - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Name	Name

Creating the brands of the cable and cable device models for the practical case

We are going to create the brands of the cable devices and cables for our practical case. You will then be able to associate them with the models that you will create later.

- 1 Display the list of brands (**Portfolio/ Brands**).
- 2 Create a new record per brand and populate the following fields:

Field or link to popu- late	Value for record 1	Value for record 2	Value for record 3	Value for record 4
Name (Name)	Corel	Hewlett Packard	ITT	Generic

Cable models

The cable models enable you to create the cables in your network in the **Cables** table (**amCable**).

Definitions

▶ Cable [page 190]

Table names

- Models (amModel)
- Pairs/Conductors (amCablePair)

Access menu

Portfolio/ Models

Creating cable models

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a record for each cable model in your network.
- 3 Associate pairs/conductors with the cable model.

You have the following possibilities:

- Add each pair/conductor manually by clicking +.
- Launch the **Create pairs** wizard.

Prerequisites

You should have already created:

- A nature for the cables.
- The brands of the cables.
- Label rules.
- Cable types.
- Color codes.
- Pair/ Conductor types.

Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks
Models table (amModel)		
Name	Name	
Nature	Nature	Must be a cable nature.
Label rule	LabelRule	
Cable type	CableType	
Color code	ColorCode	If you want the pairs/conduct- ors to be identified by a color code.
Model pairs/conductors	Pairs	
Pairs/Conductors table (an	nModelPair)	
Name	Name	
#	sSequenceNumber	
Pair/Conductor type	CabPairType	
Color code entry	ColorCodeDet	If you selected a color code at the level of the cable model.

Table 3.9. Cable models - Fields and links that must absolutely be populated

Create pairs wizard

Functions performed by the wizard

This wizard generates pairs having the same type.

Prerequisites

You should have already created:

• Pair/ Conductor types

Launching the wizard

To access this wizard, you need to select a record or field (not a link) in the **Models** table (**amModel**):

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Select the model in the list window, or select a field (not a link) in the **Models** table.
- 3 Select the **Create pairs** wizard.

Information used when using the wizard

Table 3.10. Create pairs wizard - description of fields to populate

Label displayed by the wizard	Explanations
Default type for each	The selected value populates the Pair/conductor type link
pair/conductor created.	(CabPairType) of each pair/conductor created.
Number to begin with	For example, enter 1 if you want to create 4 numbered pairs from 1 to 4. Enter 5 if you want to create 4 numbered pairs from 5 to 8.
	This number populates the # field (sSequenceNumber) of the model pairs.
	The number displayed by default in this field corresponds to the largest value that already exists in the # field (sSequen- ceNumber), plus 1 (if the model contains 4 pairs, numbered 1 through 4, this number will be 5).
	The pair number is linked with the number of the color code entries of the model in order to associate a color code entry to a pair/conductor.

Data created or modified by the wizard

The wizard creates records in the **Pairs/Conductors** table (**amModelPair**). The wizard populates the following fields:

Table 3.11. Create pairs wizard - created or modified data

Field label	SQL name of the field	Explanations
Name	Name	The same value as the # field (sSequenceNum-
		ber).
#	sSequenceNumber	A sequential number just after the largest value
		already existing in the # field (sSequenceNum-
		ber).
Pair/Conductor type	CabPairType	The pair/conductor type is selected using the
		wizard.
Color code entry	ColorCodeDet	Color code entry associated with the cable
		whose number (sSequenceNumber) corres-
		ponds to the number of the conductor pair
		(sSequenceNumber).

Viewing the result

The easiest way to view the result of this wizard is to look at the **Cable** tab of the model.

After having launched the wizard

You need to edit the pairs/conductors manually if you want to change certain information relating to them.

Creating the cable models for the practical case

We are going to create a 32-pair cable model (for the telephone riser) and a 4-pair cable model (for the given lateral and riser cables).

Creating the models

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a new record per model and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2
Name (Name)	L 120 - Category 5 - 32 twisted	FTP - Category 5 - 4 twisted
	pairs	pairs
Nature (Nature)	Cable	Cable
Brand (Brand)	Corel	Corel
Label rule (LabelRule)	Practical case - Cables	Practical case - Cables
Cable type (CableType)	Twisted pairs	Twisted pairs
Color code (ColorCode)	32 pairs	568B - 4 pairs

Creating the pairs/conductors for each cable model

- 1 Select the model.
- 2 Launch the **Create pairs** wizard one time for each model, and specify the following values:

Label displayed by the wizard	Value for the L 120 - Category 5 - 32 twisted pairs cable	Value for the FTP - Category 5 - 4 twisted pairs cable
Number of pairs/conductors to	32	4
generate		
Default type for each pair/con-	Copper	Copper
ductor created		
Number to begin with	1	1

Cable device models without slots.

Definitions

► Cable device [page 193]

Table names

- Models (amModel)
- Model ports (amModelPort)

Access menu

Portfolio/ Models

Creating the models of cable devices without slots

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a record for each cable device model in your network.
- 3 Add ports to the model.

You have the following choices:

- Add each port manually by clicking +.
- Launch the **Create ports** wizard.

Prerequisites

You should have already created:

- A nature for the cable devices.
- The brands of the cable devices.
- Label rules.
- Device types.
- Connection types.
- Duties.

Fields and links that must absolutely be populated

Table 3.12. Models of cable devices without slots - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks
Models table (amModel)		
Name	Name	
Nature	Nature	Must be a cable device nature.
Label rule	LabelRule	
Device type	DeviceType	
Number of pins/terminals	lPins	If the device is connected to the network by pins on at least one side.
Number of sides	seDevSdType	
Ports	Ports	If the device is connected to the network by ports on all sides.
Ports table (amModelPort)		
Port #	PortNo	If you create ports.

Label of the field or link	SQL name of the field or link	Remarks
#	sSequenceNumber	If you create ports.
Connection type	CabCnxType	If you create ports.
Function	Duty	If you create ports.

Connection by ports or by pins

There are two connection modes for the cable devices:

- By ports
- By pins

If the device is connected to the network by ports on all sides:

- Assign the value **0** to the **Number of pins/terminals** field (**lPins**).
- Create the **Ports** links (**Ports**). These ports will be associated with the cable bundles using the **Cable links** table (**amCableLink**).

If the device is connected to the network by pins on at least one side:

- Populate the **Number of pins/terminals** field (**lPins**) with the total number of pins contained by the cable device.
- Only create the **Ports** (**Ports**) link if you want to use the cabling wizards to create cable links to the device pins. In effect, such wizards create virtual ports that they associate automatically to the existing pins that are free.

Create ports wizard

Functions performed by the wizard

This wizard generates ports having the same duty and the same connection type.

Prerequisites

You should have already created:

- Connection types
- Functions

Launching the wizard

To access this wizard, you need to select a record or a field (not a link) in the **Models** table (**amModel**):

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Select the model in the list window, or select a field (not link) in the **Models** table.
- 3 Select the **Create ports** wizard.

Information used when using the wizard

Table 3.13. Create ports wizard - description of fields to populate

Label displayed by the wizard	Explanations
Default type for each port created	The selected value populates the Connection
	type link (CabCnxType) of each port created.
Type of duty by default for each port created	The selected value populates the Duty link
	(Duty) of each port created.
Number to begin with	For example, enter 1 if you want to create 4 numbered ports from 1 to 4. Enter 5 if you want to create 4 numbered ports from 5 to 8.
	This number populates the Port # field (PortNo) of the model ports.
	The number displayed by default by the wizard corresponds to the largest existing port num- ber plus 1 (if the model contains 4 ports, numbered 1 through 4, this number will be 5).

Data created or modified by the wizard

The wizard creates records in the **Model ports** table (**amModelPort**). The wizard populates the following fields:

Table 3.14. Create ports wizard - data created or modified by the wizard

Field label	SQL name of the field	Explanations
Sequence number of	sSequenceNumber	A sequential number that begins with the
the port in the model		starting number specified using the wizard.
Port #	PortNo	A sequential number that begins with the
		starting number specified using the wizard.
Connection type	CabCnxType	The connection type selected using the wizard.

Field label	SQL name of the field	Explanations
Function	Duty	The duty selected using the wizard.

Viewing the result

The easiest way to view the result of this wizard is to look at the **Ports** tab of the model.

After having launched the wizard

You need to edit the ports manually if you want to change certain information relating to them.

Creating the models of cable devices without slots for the practical case

We are going to create the models that will help create the following cable devices without slots:

- 3-port wall outlet
- Patch panels
- Switch modules

Creating the models

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a new record per model and populate the following fields:

Field or link to popu- late	Value for record 1	Value for record 2	Value for record 3	Value for record 4
Name (Name)	Procurve 10/100	24-port preloaded	32-port patch	3-port wall outlet
	Base T - 8 ports	patch panel	panel (256 pins)	
Nature (Nature)	Cable device	Cable device	Cable device	Cable device
Brand (Brand)	Hewlett Packard	Generic	Generic	ITT
Device type	Switch module	Patch panel	Patch panel	Wall outlet
(DeviceType)				
Number of	0	0	256	24
pins/terminals				
(lPins)				

Field or link to popu- late	Value for record 1	Value for record 2	Value for record 3	Value for record 4
Number of sides	Single sided	Double sided	Double sided	Single sided
(seDevSdType)				

Creating the ports for each device model for which the network connection is established by ports

For each model whose Number of pins/terminals (lPins) is null:

- 1 Select the Procurve 10/100 Base T- 8 ports model.
- 2 Launch the **Create ports** wizard one time by entering the following information:

Label displayed by the wizard	Value
Number of ports to generate	8
Default connection type for each port to generate	RJ45 - 568B - Port
Default type for each port created	Data
Number to begin with	1

- 3 Select the 24-port preloaded patch panel model.
- 4 Launch the **Create ports** wizard one time by entering the following information:

Label displayed by the wizard	Value
Number of ports to generate	24
Connection type by default for each port to gen-	RJ45 - 568B - Port
erate	
Type of duty by default for each port created	Data
Number to begin with	1

Slot types

Definitions

▶ Slot type [page 206]

Table names

Slot types (amSlotType)

Access menu

Cable/ Slot types

Simplified data model

Figure 3.8. Slots - data model



Creating slot types

- 1 Display the list of slot types (**Cable/ Slot types**).
- 2 Create a record per slot type of your termination-field devices.

Prerequisites

You need to have already created the models of modules or extensions to insert in the slots.

Fields and links that must absolutely be populated

Table 3.15. Slot types - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Name	Name
Compatible models	SlotTypeModels

Creating the slot types for the practical case

We are going to create a slot type for the **ProCurve Switch 4000 M - 10 slots** model that will receive the **Procurve 10/100 Base T - 8 ports** models.

ጆ Note:

You are going to create the ProCurve Switch 4000 M - 10 slots in another step.

- 1 Display the list of slot types (**Cable/ Slot types**).
- 2 Create a new record in the **Slot types** table (**amSlotType**) and populate the following fields:

Field or link to populate	Value
Name (Name)	8-port switch module

Field or link to populate	Value
Compatible models (SlotTypeModels)	Procurve 10/100 Base T - 8 ports

Cable device models with slots.

Definitions

► Cable device [page 193]

Table names

- Models (amModel)
- Model slots (amModelSlot)
- Model ports (amModelPort)

Access menu

Portfolio/ Models

Creating the models of cable devices with slots

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a record for each cable device model in your network.
- 3 Associate ports or slots to the model.

You have the following choices:

- Add each port or slot manually by clicking +.
- Launch either the Create ports or Create slots wizard.

Connection by ports or by pins

Connection by ports or by pins [page 65]

Create ports wizard

Create ports wizard [page 65]
Prerequisites

You should have already created:

- A nature for the cable devices.
- The brands of the cable devices.
- Label rules.
- Device types.
- Connection types.
- Duties.
- Slot types.

Fields and links that must absolutely be populated

Table 3.16. Models of cable devices with slots - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks
Models table (amModel)		
Name	Name	
Nature	Nature	Must be a cable device nature.
Label rule	LabelRule	
Device type	DeviceType	
Number of pins/terminals	lPins	If the device is connected to the network by pins on at least one side.
Number of sides	seDevSdType	
Ports	Ports	If the device is connected to the network by ports on all sides.
Model slots	ModelSlots	If the device must receive connection modules in its slots.
Ports table (amPort)		
Port #	PortNo	If you create ports.
#	sSequenceNumber	If you create ports.
Connection type	CabCnxType	If you create ports.
Function	Duty	If you create ports.
Model slots table (amModelS	lot)	
Name	Name	If you create slots.
#	sSequenceNumber	If you create slots.

Label of the field or link	SQL name of the field or link	Remarks
Slot type	SlotType	If you create slots.

Create slots wizard

Functions performed by the wizard

This wizard generates slots having the same type.

Prerequisites

You should have already created:

• Slot types

Launching the wizard

To access this wizard, you need to select a record or select a field (not a link) in the **Models** table (**amModel**).

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Select the model in the list window, or select a field (not a link) in the **Models** table.
- 3 Select the **Create slots** wizard.

Information used when using the wizard

Table 3.17. Create slots wizard - description of fields to populate

Label displayed by the wizard	Explanations
Default type for each slot created	The selected value populates the Slot type link
	(SlotType) of each slot created.

Label displayed by the wizard	Explanations
Number to begin with	For example, enter 1 if you want to create 4 numbered slots from 1 to 4. Enter 5 if you want to create 4 numbered slots from 5 to 8.
	This number populates the # field (sSequen- ceNumber) and Name field (amModelSlot) of the model slots.
	The number displayed by default by the wizard corresponds to the largest existing slot number plus 1 (if the model contains 4 slots, numbered 1 through 4, this number will be 5).

Data created or modified by the wizard

The wizard creates records in the **Model slots** table (**amModelSlot**).

The wizard populates the following fields:

Table 3.18. Create slots wizard - created or modified data

Field label	SQL name of the field	Explanations
Name	Name	A sequential number that begins with the
		starting number specified using the wizard.
#	sSequenceNumber	A sequential number that begins with the
		starting number specified using the wizard.
Slot type	SlotType	The slot type selected using the wizard.

Viewing the result

The easiest way to view the result of this wizard is to look at the **Slots** tab of the model.

After having launched the wizard

You need to edit the slots manually if you want to change certain information relating to them.

Creating the models of cable devices with slots for the practical case

We are going to create the model of a modular switch that has 10 slots:

Creating the model

- 1 Display the list of models (**Portfolio/ Models**).
- 2 Create a new record and populate the following fields:

Field or link to populate	Value
Name (Name)	ProCurve Switch 4000 M - 10 slots
Nature (Nature)	Cable device
Brand (Brand)	Hewlett Packard
Device type (DeviceType)	Switch
Number of pins/terminals (lPins)	0
Number of sides (seDevSdType)	Single sided

Creating the slots

- 1 Select the ProCurve Switch 4000 M 10 slots model.
- 2 Launch the **Create slots** wizard one time for each model, and specify the following values:

Label displayed by the wizard	Value
Number of slots to generate	10
Default type for each slot created	8-ports switch module
Number to begin with	1

Topologies

Definitions

- ▶ Topology [page 203]
- ► Topology step [page 196]
- ▶ Host [page 199]
- ▶ User [page 206]

Table names

Topologies (amTopology)

Topology steps (amTopologyDet)

Access menu

Cable/Topologies

Simplified data model

Figure 3.9. Topologies - data model



Creating topologies

- 1 Display the list of topologies (Cable/ Topologies).
- 2 Create a topology and its steps for each standard trace of your network.

Topology example

The topology of a telephone connection between the standard user and the floor's termination field is composed of the following steps:

- 1 A link at the level of the wall outlet.
- 2 A link at the level of a lateral cable.
- 3 A link at the level of a termination-field device.

Prerequisites

You should have already created the:

- Duties
- Label rules
- Cable types
- Pair/conductor types
- Device types
- Connection types
- Roles
- Models of cables and cable devices to create from the topology step.

Fields and links that must absolutely be populated

Table 3.19. Topologies - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks	
Topologies table (amTopology)			
Name	Name		
Direction	seTraceDir		
Function	Duty		
Topology steps	Detail		
Topology steps table (amTopologyDet)			
#	sSequenceNumber		
Link type	seLinkType		
Label rule	LabelRule		
Cable type	CableType	If seLinkType = Cable	
Device type	DeviceType	If seLinkType = Device	
Pair/Conductor type	CabPairType	If seLinkType = Cable	
Connection type	CabCnxType	If seLinkType = Device	

Label of the field or link	SQL name of the field or link	Remarks
Map bundles at pair/conduct-	bPairLevelMapping	If seLinkType = Cable
or level		
Termination-field device	bTermField	If seLinkType = Device
No. of pairs/conductors	sPairs	If seLinkType = Cable
Auto-create	seCreateType	
Model	Model	If seCreateType <> Never
		create
Role	CableRole	• If seLinkType = Cable
		• or bTermField = Yes

Creating the topologies for the practical case

We are going to create two topologies:

- Data connection between the wall outlet and the floor's termination field.
- Telephone connection between the wall outlet and the floor's termination field.

These topologies break down into three steps:

- 1 A link at the level of the wall outlet.
- 2 A link at the level of the lateral cable.
- 3 A link at the level of the termination-field device.

These topologies are then assembled together in a group of topologies.

Creating the topologies

- 1 Display the list of topologies (**Cable/ Topologies**).
- 2 Create a new record per topology and populate the following fields:

Field or link to populate	Value for record 1	Value for record 2
Name (Name)	Telephone outlet to termination	Local network outlet to termin-
	field.	ation field
Direction (seTraceDir)	User to host	User to host
Duty (Duty)	Voice	Data

Creating the steps for the Telephone outlet to termination field topology

1 Select the topology.

2 Create step 1 by populating the following fields:

Field or link to populate	Value
# (sSequenceNumber)	1
Cable link type (seLinkType)	Device
Termination field device (bTermField)	Unselect the box.
Label rule (LabelRule)	Practical case - Wall outlet link
Connection type (CabCnxType)	RJ45 - 568B - Pin
Device type (DeviceType)	Wall outlet
Auto-create (seCreateType)	Create if not available
Model (Model)	3-port outlet

3 Create step 2 by populating the following fields:

Field or link to populate	Value
# (sSequenceNumber)	2
Cable link type (seLinkType)	Cable
Role (CableRole)	Lateral
Label rule (LabelRule)	Practical case - Link - Sequen-
	tially, by pairs
Pair/ Conductor type (CabPairType)	Copper (2)
Cable type (CableType)	Twisted pairs
Auto-create (seCreateType)	Always create
Map bundles at pair/conductor level (bPairLevelMapping)	Check this selection box.
No. of pairs/conductors (sPairs)	2
Model (Model)	FTP - Category 5 - 4 twisted
	pairs

4 Create step 3 by populating the following fields:

Field or link to populate	Value
# (sSequenceNumber)	3
Cable link type (seLinkType)	Device
Termination field device (bTermField)	Check this selection box.
Role (CableRole)	Lateral
Label rule (LabelRule)	Practical case - Port of a termin-
	ation-field patch panel link
Connection type (CabCnxType)	RJ45 - 568B - Pin

Field or link to populate	Value
Device type (DeviceType)	Patch panel

Creating the steps for the Local network outlet to termination field topology

- 1 Select the topology.
- 2 Create step 1 by populating the following fields:

Value
1
Device
Unselect the box.
Practical case - Wall outlet link
RJ45 - 568B - Pin
Wall outlet
Create if not available
3-port outlet

3 Create step 2 by populating the following fields:

Field or link to populate	Value
# (sSequenceNumber)	2
Cable link type (seLinkType)	Cable
Role (CableRole)	Lateral
Label rule (LabelRule)	Practical case - Link - Sequen-
	tially, by pairs
Pair/ Conductor type (CabPairType)	Copper (2)
Cable type (CableType)	Twisted pairs
Auto-create (seCreateType)	Always create
Model (Model)	FTP - Category 5 - 4 twisted
	pairs
Map bundles at pair/conductor level (bPairLevelMapping)	Check this selection box.
No. of pairs/conductors (sPairs)	4

4 Create step 3 by populating the following fields:

Field or link to populate	Value
# (sSequenceNumber)	3
Cable link type (seLinkType)	Device

Field or link to populate	Value
Termination field device (bTermField)	Check this selection box.
Role (CableRole)	Lateral
Label rule (LabelRule)	Practical case - Port of a termin-
	ation-field patch panel link
Connection type (CabCnxType)	RJ45 - 568B - Port
Device type (DeviceType)	Patch panel

Topology groups

Definitions

► Topology group [page 198]

Table names

- Topology groups (amTopologyGroup)
- Topologies in a group (amTopoGroupDet)

Access menu

Cable/ Topology groups

Simplified data model

Figure 3.10. Topology groups - data model





Figure 3.11. Topologies - correspondence between the termination field of a network

Creating topology groups

- 1 Display the list of topology groups (Cable/ Topology groups).
- 2 Create one record per configuration type of your network.

Example - A standard workstation is composed of 3 topologies:

- Telephone outlet to a termination field.
- Local network outlets to a termination field.
- Local network outlets to termination field.

Prerequisites

You need to have already created the topologies.

Fields and links that must absolutely be populated

Table 3.20. Topology groups - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	
Topology groups table (amTopologyGroup)		
Name	Name	
Topologies of the group	TopoGrpDetail	
Topologies in a group table (amTopoGroupDet)		
#	sSequenceNumber	

Creating the topology groups for the practical case

We are going to create a group of topologies that reunite the following topologies:

- 1 telephone outlet to a termination field.
- 2 local network outlets to a termination field.

Creating the topology group

- 1 Display the list of topology groups (**Cable/ Topology groups**).
- 2 Create a record and populate the following fields:

Field or link to populate	Value
Name (Name)	Standard workstation

Adding topologies to the Standard workstation group

1 Select the **Standard workstation** topology group.

2 Add topology 1 by populating the following fields and links:

Field or link to populate	Value
# (sSequenceNumber)	1
Topology (Topology)	Telephone outlet to termination field.

3 Add topology 2 by populating the following fields and links:

Field or link to populate	Value
# (sSequenceNumber)	2
Topology (Topology)	Local network outlet to termination field

4 Add topology 3 by populating the following fields and links:

Field or link to populate	Value
# (sSequenceNumber)	3
Topology (Topology)	Local network outlet to termination field

Termination-field configurations

Definitions

▶ Termination-field configuration [page 193]

Table names

- Termination field configurations (amTermFldConfig)
- Termination-field configuration duties/services (amTermFldCfgDuty)
- Termination field configuration roles and devices (amTermFldCfgRole)

Access menu

Cable/ Termination field configurations

Simplified data model



Figure 3.12. Termination-field configuration - data model

Parameters of a termination-field configuration

A termination-field configuration defines numerous parameters that are used by the cabling wizards to create a termination field.

The following diagrams will explain how these parameters are interpreted when you create a termination field.



Figure 3.13. Example of termination-field configuration - representation in AssetCenter



Figure 3.14. Example of termination-field configuration - correspondence at the termination field level

Figure 3.15. Termination-field configuration - example of the impact resulting from changing the starting position

If starting	positi	ion =	Lower right
	D12	D6	
	D1 1	D5	
	D10	D4	
	D9	D3	
	D8	D2	
	D7	D1	

D="Duty"

Role and device orientation = Vertical

Figure 3.16. Termination-field configuration - example of the impact resulting from changing the cable device and role orientations



Figure 3.17. Termination-field configuration - example of the impact resulting from changing the flow specification

If flow specification = Horizontal

D1	D2
D3	D4
D5	D6
D7	D8
D9	D1 0
D1 1	D12

D="Duty"

Starting position

Termination field			
Upper left			Upper right
Lower left			Lower right

Figure 3.18. Termination-field configuration - signification of the starting positions

Flow specification

Figure 3.19. Termination-field configuration - signification of the flow specification



Creating termination-field configurations

- 1 Display the list of termination-field configurations (**Cable/ Termination field configurations**).
- 2 Create one record per termination-field type of your network.

Prerequisites

You should have already created the:

- Functions
- Label rules
- Roles
- Termination-field configuration models

Fields and links that must absolutely be populated

Table 3.21. Termination-field configurations - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	
Termination field configurations table (amTermFldConfig)		
Name	Name	
Number of columns	sHoriz	
Number of rows	sVert	
Flow specification	seFlowSpec	
Starting position	seStartingPos	
Termination field configuration duties/services	TermFldCfgDuty	
Role and device orientation	seRoleDevOrient	
Label rule	LabelRule	
Termination field configuration roles and	TermFldConfRoles	
devices		
Termination field configuration duties/servi	ces (amTermFldCfgDuty)	
#	sSequenceNumber	
Function	Duty	
Termination field configuration roles and devices table (amTermFldCfgRole)		
Row or column	sRowCol	
Role	CableRole	
Model	Model	

Creating the termination-field configurations for the practical case

We are going to create a termination-field configuration based on the following model:





Creating the termination-field configuration

- 1 Display the list of termination-field configurations (**Cable/ Termination field configurations**).
- 2 Create a record and populate the following fields:

Field or link to populate	Value
Name (Name)	Standard termination field
Number of columns (sHoriz)	2
Number of rows (sVert)	6
Flow specification (seFlowSpec)	Vertical
Starting position (seStartingPos)	Top-left
Role and device orientation (seRoleDevOrient)	Vertical
Label rule (LabelRule)	Practical case - Wallfield assets

Creating the duties of the Standard termination field configuration

- 1 Select the termination-field configuration.
- 2 Select the **Duties** tab and add duties by populating the following fields and links:

Field or link to populate	# (sSequenceNumber)	Duty (Duty)	
Value for duty 1	1	Voice	
Value for duty 2	2	Voice	
Value for duty 3	3	Data	
Value for duty 4	4	Data	
Value for duty 5	5	Data	
Value for duty 6	6	Data	
Value for duty 7	7	Voice	
Value for duty 8	8	Voice	
Value for duty 9	9	Data	
Value for duty 10	10	Data	
Value for duty 11	11	Data	
Value for duty 12	12	Data	

Creating the roles of the Standard termination field configuration

1 Select the termination-field configuration.

2 Select the **Roles and devices** tab and add roles/devices by populating the following fields and links:

	Row or column (sRowCol)	Role (CableRole)	Model (Model)
Value for role 1	1	Riser	32-port patch panel
			(256 pins)
Value for role 2	2	Lateral	32-port patch panel
			(256 pins)
Value for role 3	3	Lateral	24-port preloaded
			patch panel
Value for role 4	4	Lateral	24-port preloaded
			patch panel
Value for role 5	5	Lateral	24-port preloaded
			patch panel
Value for role 6	6	Riser	ProCurve Switch 4000
			M - 10 slots



Definitions

▶ Termination field [page 202]

Table names

Termination fields (amTermField)

Access menu

Cable/ Termination fields

Creating termination fields

You can create the termination field manually or you can use one of the following wizards:

- Create a termination field
- Expand termination field
- Duplicate wiring closet

Prerequisites

You should have already created the:

- Termination-field configurations.
- Location of termination fields and work posts served by the termination fields.
- Duties
- Label rules
- Roles
- Termination-field device models.

Fields and links that must absolutely be populated

Table 4.1. Termination fields - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link
Termination fields table (amTermField)	
Name	Name
Location	Location
Termination field devices	TermFieldDevices
User locations	UserLocs
Termination field devices table (amTermFld	Device)
Role	CableRole
Label	Label
Horizontal position	sHoriz
#	sSequenceNumber
Vertical position	sVert

Creating termination fields manually

For each termination field in your network (main termination field or the one on each floor):

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Create a record.
- 3 Create the termination-field slots using the **Termination field devices** link (**TermFieldDevices**).
- 4 Select the termination fields served by the termination field using the User locations link (UserLocs).

Create a termination field wizard

Functions performed by the wizard

The **Create termination field** wizard creates a termination field from a termination-field configuration.

Prerequisites

You should have already created the:

- Termination-field configurations
- Locations of the served termination fields and workstations.

Launching the wizard

Launching a wizard does not necessarily require that you be in a specific context.

To launch a wizard:

- 1 Display the list of actions (**Tools/ Actions**).
- 2 Select the **Create a termination field** wizard.

Information used when using the wizard

Table 4.2. Create a termination field wizard - description of fields to populate

Label displayed by the wizard	Explanations
Configure the termination fie	ld page
Automatically name the ter- mination field?	If you check this option, the wizard uses the TermFieldName calculated field to populate the Name field (Name) of the termination field.
	Calculated fields (Cable and Circuit) [page 233]
Termination field name	This field populates the Name field (Name) of the termination field if you did not check the Automatically name the termin- ation field option.
Location of the termination field	Select the termination field's location.
Termination-field configura- tions	Select the configuration that must be used as the model for the creation of the termination field.
Specify the options page	

Label displayed by the wizard	Explanations	
Column	Indicate the number of termination field columns to create.	
	This number must be inferior or equal to the Number of columns field (sHoriz) of the termination-field configuration.	
	The value of this field is proposed by default.	
Line	Indicate the number of termination-field rows to create.	
	This number must be inferior or equal to the Number of rows field (sVert) of the termination-field configuration.	
	The value of this field is proposed by default.	
Auto-generate devices	If you check this option, the wizard creates a termination-field device for the termination-field slots.	
	The wizard uses the Model link (Model) for this, which is defined at the level of the termination-field configuration roles and devices.	
Select the label rule for new devices	Select the label rule to associate with the termination-field devices created by the wizard.	
	This label rule populates the devices' Label rule (LabelRule) link. It also populates the devices' Label field (Label) in reference to this label rule.	
	The label rule that the wizard proposed by default is the rule selected using the Label rule link (LabelRule) of the termination-field configuration.	
Select a project and a work o	rder page	
Apply all changes to a pro-	Check this option if you want to:	
ject/work order:	• Keep a trace of the operations performed in the database at the project level.	
	• Describe the actions that you need to perform for (during) the work order.	
Projects	The project in which is stored a trace of the operations per- formed in the database by the wizard.	
Work orders	The work orders in which is described the actions that you must physically perform for the work order.	
Device comments	Enter the value to create for the Description field (Description) of the Assets included in projects table (amAstProjDesc).	
	This applies to all the devices created by the wizard.	

Data created or modified by the wizard

The wizard creates:

- 1 termination field (**amTermField**).
- Termination field devices (amTermFldDevice).
- The assets corresponding to the termination-field devices (**amAsset**).
- Ports for the devices (**amPort**).
- Slots for the devices (**amSlot**).
- Pins/terminals for the devices (amDevicePin).

The wizard populates the following fields:

Table 4.3. Create a termination field wizard - data created or modified by the wizard

Field label	SQL name of the field	Explanations
Termination field	d table (amTermFi	eld)
Name	Name	The name that you selected using the wizard or the name determined by the TermFieldName calculated field.
Termination	TermFldConfig	The configuration selected using the wizard.
field configura-		
tion		
Location	Location	The location selected using the wizard.
Termination-	TermField-	The wizard creates a device for each termination-field
field devices	Devices	slot is created if you checked the Automatically generate
		the devices option in the wizard.
User locations	UserLocs	The locations selected with the wizard.
Termination field	d devices table (am	TermFldDevice)
#	sSequenceNum-	Defined according to the termination-field configuration
	ber	parameters.
Horizontal posi-	sHoriz	Defined according to the termination-field configuration
tion		parameters.
Vertical position	sVert	Defined according to the termination-field configuration
		parameters.
Role	CableRole	The Role field (CableRole) of the termination-field
		configuration role corresponding to the position of the
		device in the termination field.
Device	Device	The device created by the wizard using the Model link
		(Model) of the termination-field configuration role
		corresponding to the position of the device in the ter-
		mination field.
Assets table (amA	Asset)	

Field label	SQL name of the field	Explanations
Model	Model	The Model (Model) of the termination-field configura-
		tion role corresponding to the position of the device in
		the termination field.
Label rule	LabelRule	Label rule selected using a wizard.
Label	Label	Label calculated by a wizard and based on the label rule
		of the device.
Slots	AssetSlots	Slots of the device model.
Device pins/ter-	Pins	AssetCenter creates as many pins as there are defined
minals		by the Number of pins/terminals field (lPins) of the
		model.
Ports	Ports	Ports of the device model.
Ports table (amP	ort)	
Port #	PortNo	Same as for the model.
#	sSequenceNum-	Same as for the model.
	ber	
Connection type	CabCnxType	Same as for the model.
Status	seCnxStatus	Value set to Available by the wizard.
Function	Duty	The Duty link (Duty) of the termination-field configur-
		ation duty defined for the device slot, of which the port
		is a part.
Slots table (amSl	ot)	
Name	Name	Same as for the model.
#	sSequenceNum-	Same as for the model.
	ber	
Slot type	SlotType	Same as for the model.
Pins table (amDe	evicePin)	
Name	Name	Automatic sequential number.
#	sSequenceNum-	Automatic sequential number.
	ber	-
Status	seCnxStatus	Value set to Available by the wizard.

Viewing the result

The termination field created can be viewed by selecting it in one of the following manners:

- Option 1:
 - 1 Display the list of termination fields (Cable/ Termination fields).
 - 2 Select the termination field created by the wizard.
- Option 2:

- 1 Display the list of locations (**Portfolio/ Locations**).
- 2 Select the location of the termination field created by the wizard.
- 3 Select the **Termination fields** tab.
- 4 Select the termination field created by the wizard.

After having launched the wizard

The wizard does not populate the **Device** link (**Asset**) of the termination field device slots.

You therefore need to:

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Select the termination field created by the wizard.
- 3 Select the **Devices** tab.
- 4 One by one, select the devices with their slots, and for each one of them:
 - 1 Click the **Magnifier**.
 - 2 Click the **Magnifier** to the right of the **Device** link (**Device**).
 - 3 Select the **Slots** tab.
 - 4 One by one, select the slots to use, and for each one of them:
 - 1 Click the Magnifier.
 - 2 Populate the fields and links in the detail window.
 - 5 Click **Modify**.
 - 6 Click Modify.
 - 7 Click Close.
- 5 Click **Modify**.

Use the Create a termination field wizard for the practical case.

We are going to create 1 termination-field column from the **Standard termination field** configuration. The second column will be added later using the **Expand termination field** wizard.

- 1 Display the list of actions (**Tools/ Actions**).
- 2 Select the Create a termination field wizard.
- 3 Enter the following information:

Label displayed by the wizard	Value to enter or select
Configure the termination field page	
Automatically name the termination field?	Do not check this option.
Termination field name	Floor's termination field
Location of the termination field	Cabled building/1st floor/1st floor's wiring closet
Termination-field configurations	Standard termination field
Specify the options page	
Column	1
Line	6
Auto-generate devices	Check this selection box.
Select the label rule for new devices	Practical case - Wallfield assets
Locations served by the new termination field	Cabled building/1st floor/Office 1
Select a project and a work order page	
Apply all changes to a project/work order?	Check this selection box.
Projects	Create a termination field
Work orders	Select the work order proposed by the wizard.
Device comments	Install the device in termination field.

4 Add the modules in the slots of the **ProCurve Switch 4000 M - 10 slots** devices:

! Warning:

This will be done later on, according to the procedure described in section Creating the cable devices manually for the practical case [page 127] of this guide.

5 View the results created by the wizard by looking at the other tabs.

Expand termination field wizard

Functions performed by the wizard

The **Expand termination field** wizard adds rows or columns to an existing termination field from a termination-field configuration.

Prerequisites

You should have already created:

• The workstation locations served by the termination fields.

• The termination field to expand.

The existing termination field must have less rows or columns than the termination-field configuration.

Launching the wizard

To access this wizard, you must select a record or a field (not a link) from the **Termination fields** table (**amTermField**):

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Select the termination field to expand from the list in the window.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the **Expand termination field** wizard.

Information used when using the wizard

Label displayed by the wizard	Explanations	
Specify the options page		
Column	Indicate the number of termination field columns to add.	
	This number must be inferior or equal to the Number of columns field (sHoriz) of the termination-field configuration.	
	The possible number of columns that you can add is proposed by default.	
Line	Indicate the number of termination-field rows to add.	
	This number must be inferior or equal to the Number of rows field (sVert) of the termination-field configuration.	
	The possible number of rows that you can add is proposed by default.	
Auto-generate devices	If you check this option, the wizard creates a termination-field device for the termination field slots.	
	The wizard uses the Model link (Model) for this, which is defined at the level of the termination-field configuration roles and devices.	

Table 4.4. Expand termination field wizard - description of fields to populate

Label displayed by the wizard	Explanations		
Select the label rule for new	Select the label rule to associate with the termination-field		
devices	devices created by the wizard.		
	This label rule populates the devices' Label rule link (Label- Rule).		
	The wizard also populates the devices' Label field (Label) in reference to this label rule.		
	The label rule that the wizard proposed by default is the rule selected using the Label rule link (LabelRule) of the termination-field configuration.		
Select a project and a work or	rder page		
Apply all changes to a pro-	Check this option if you want to:		
ject/work order?	• Keep a trace of the operations performed in the database at the project level.		
	• Describe the actions that you need to perform for (during) the work order.		
Projects	The project in which is stored a trace of the operations per- formed in the database by the wizard.		
Work orders	The work orders in which is described the actions that you		
	must physically perform for the work order.		
Device comments	Enter the value to create for the Description field (Descrip -		
	tion) of the Assets included in projects table (amAstProj-		
	Desc). This applies to the devices created while extending the		
	termination field.		

Data created or modified by the wizard

The wizard creates:

- Termination field devices (amTermFldDevice)
- The assets corresponding to the termination-field devices (amAsset).
- Ports for the devices (**amPort**).
- Slots for the devices (**amSlot**).
- Pins/terminals for the devices (amDevicePin).

The wizard populates the following fields:

Table 4.5. Expand termination field wizard - data created or modified by the wizard

Field labelSQL name of the fieldExplanationsTermination field table (amTermField)

Field label	SQL name of the field	Explanations
Termination-field	TermFieldDevices	The wizard creates a device for each termina-
devices		tion-field slot is created if you checked the
		Automatically generate the devices option in
		the wizard.
Termination field dev	vices table (amTermFl	dDevice)
#	sSequenceNumber	Defined according to the termination-field
		configuration parameters.
Horizontal position	sHoriz	Defined according to the termination-field
		configuration parameters.
Vertical position	sVert	Defined according to the termination-field
		configuration parameters.
Role	CableRole	The Role field (CableRole) of the termination-
		field configuration role corresponding to the
		position of the device in the termination field.
Device	Device	The device created by the wizard using the
		Model link (Model) of the termination-field
		configuration role corresponding to the posi-
		tion of the device in the termination field.
Assets table (amAsset	:)	
Model	Model	The Model (Model) of the termination-field
		configuration role corresponding to the posi-
		tion of the device in the termination field.
Label rule	LabelRule	The label rule selected using a wizard.
Label	Label	The label is calculated by a wizard and is based
		on the label rule of the device.
Slots	AssetSlots	Slots of the device model.
Device pins/terminals	Pins	AssetCenter creates as many pins as there are
		defined by the Number of pins/terminals field
	_	(IPins) of the model.
Ports	Ports	Ports of the device model.
Ports table (amPort)		
Port #	PortNo	Same as for the model.
#	sSequenceNumber	Same as for the model.
Connection type	CabCnxType	Same as for the model.
Status	seCnxStatus	Value set to Available by the wizard.
Function	Duty	The Duty link (Duty) of the termination-field
		configuration duty defined for the device slot,
		of which the port is a part.
Slots table (amSlot)		
Name	Name	Same as for the model.
#	sSequenceNumber	Same as for the model.

Field label	SQL name of the field	Explanations		
Slot type	SlotType	Same as for the model.		
Pins table (amDevicePin)				
Name	Name	Automatic sequential number.		
#	sSequenceNumber	Automatic sequential number.		
Status	seCnxStatus	Value set to Available by the wizard.		

Viewing the result

You can view the newly created termination field by selecting it in one of the following ways:

- Option 1:
 - 1 Display the list of termination fields (Cable/ Termination fields).
 - 2 Select the termination field created by the wizard.
- Option 2:
 - 1 Display the list of locations (**Portfolio**/ **Locations**).
 - 2 Select the location of the termination field created by the wizard.
 - 3 Select the **Termination fields** tab.
 - 4 Select the termination field created by the wizard.

After having launched the wizard

The wizard does not populate the following links:

- User locations link (UserLocs) of the termination fields (if it concerns locations served by the termination field).
- Device (Asset) of the termination-field device slots.

You therefore need to:

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Select the termination field created by the wizard.
- 3 Select the **Served locations** tab.
- 4 One by one, add the locations served by the termination field.
- 5 Select the **Devices** tab.
- 6 One by one, select the devices with their slots, and for each one of them:
 - 1 Click the Magnifier.
 - 2 Click the **Magnifier** to the right of the **Device** link (**Device**).
 - 3 Select the **Slots** tab.
 - 4 One by one, select the slots to use, and for each one of them:
- 1 Click the **Magnifier**.
- 2 Populate the fields and links in the detail window.
- 5 Click Modify.
- 6 Click Modify.
- 7 Click Close.
- 7 Click Modify.

Using the Expand termination field wizard in the practical case

We are going to add 1 column to the termination field that was previously created from the **Standard termination field** configuration.

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Select the **Floor's termination field**.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the **Expand termination field** wizard.
- 5 Enter the following information:

Label displayed by the wizard	Value to enter or select	
Specify the options page		
Line	0	
Column	1	
Auto-generate devices	Check this selection box.	
Select the label rule for new devices	Practical case - Wallfield assets	
Select a project and a work order page		
Apply all changes to a project/work order?	Check this selection box.	
Projects	Expand a termination field	
Work orders	Select the work order proposed by the wizard.	
Device comments	Install the device in termination field.	

- 6 In a real-life situation, you would have to create the modules to insert in the slots of the **ProCurve Switch 4000 M 10 slots**. However, in this practical case, it is not required.
- 7 Look at the results:
 - Display the list of termination fields (Cable/ Termination fields).
 - Select the Floor's termination field.
 - Browse through the different tabs

Duplicate wiring closet wizard

Functions performed by the wizard

The **Duplicate wiring closet** wizard duplicates the termination fields of a source location into a target location.

ጆ Note:

This target location can already contain termination fields.

Prerequisites

You should have already created:

- The parent location of the new wiring closet.
- The wiring closet (location + termination fields) to duplicate.
- Locations of the served termination fields and workstations.

Launching the wizard

To access the wizard, you must select a record or a field (not a link) in the **Locations** table (**amLocation**):

- 1 Display the list of locations (**Portfolio/ Locations**).
- 2 Select any location from the list or select a field (not a link) in the **Locations** table.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the **Duplicate wiring closet** wizard.

Information used when using the wizard

Table 4.6. Duplicate wiring closet wizard - description of fields to populate

Label displayed by the wizard	Explanations	
Select the source and destination locations page		
Destination location	Select the location where you want to duplicate	
	the source location.	

Label displayed by the wizard	Explanations	
Name of the new wiring closet	• If you leave this field empty, the wizard will only duplicate the termination fields from the source location in the target location.	
	• If you populate this field, the wizard creates a sub-location in the target location.	
	The source termination fields are duplic- ated in this sub-location.	
Duplicate the sub-locations	If you check this option, the sub-locations of the source location are also duplicated.	
Rename the new termination field automatic- ally	 If you check this option, the wizard uses the TermFieldName calculated field to populate the Name field (Name) of the termination field. 	
	• If you don't check this option, the wizard duplicates the names of the source termination fields.	
	 Calculated fields (Cable and Circuit) [page 233]. 	
Refresh new termination-field device's labels	• If you check this option, the wizard recal- culates the devices' Label field (Label) in reference to the label rule, selected by the devices' Label rule link (LabelRule).	
	• If you don't check this option, the wizard duplicates the labels of the source termination-field devices.	
Select the termination field(s) to duplicate p	age	
Select the termination field(s) to duplicate	The wizard displays the termination fields of the selected, source location.	
Select a project and a work order page		
Apply all changes to a project/work order?	Check this option if you want to:	
·	• Keep a trace of the operations performed in the database at the project level.	
	• Describe the actions that you need to per- form for (during) the work order.	
Projects	The project in which is stored a trace of the operations performed in the database by the wizard.	

Label displayed by the wizard	Explanations
Work orders	The work orders in which is described the ac-
	tions that you must physically perform for the
	work order.
Device comments	Enter the value to create for the Description
	field (Description) of the Assets included in
	projects table (amAstProjDesc).
	This applies to all the devices created by the wizard.

Data created or modified by the wizard

The wizard creates:

- Locations (amLocation)
- Termination fields (**amTermField**)
- Termination field devices (amTermFldDevice)
- The assets corresponding to the termination-field devices (**amAsset**).
- Ports for the devices (**amPort**).
- Slots for the devices (**amSlot**).
- Pins/terminals for the devices (amDevicePin).

The wizard populates the following fields:

Table 4.7. Duplicate wiring closet wizard - data created or modified by the wizard

Field label	SQL name of the field	Explanations
Locations table (amI	ocation)	
Name	Name	• It is the value of the New wiring closet name field in the wizard, if you have pop- ulated it.
		• Otherwise, it is the name of the target loc- ation that you have selected with the wiz- ard.
Termination field tal	ble (amTermField)	
Termination-field	TermFieldDevices	The wizard creates a record for each device in
devices		the source termination fields selected using
		the wizard.
User locations	UserLocs	The locations selected with the wizard.
Termination field de	vices table (amTermFlo	lDevice)
#	sSequenceNumber	Same as for the source device.

Field label	SQL name of the field	Explanations	
Horizontal position	sHoriz	Same as for the source device.	
Vertical position	sVert	Same as for the source device.	
Role	CableRole	Same as for the source device.	
Device	Device	The device created by the wizard using the	
		Model link (Model) of the source device.	
Assets table (amAsset)		
Model	Model	Same as for the source device.	
Label rule	LabelRule	Same as for the source device.	
Label	Label	• If you checked the Refresh new termina-	
		tion field device's labels option in the	
		wizard: It is the value calculated by the	
		wizard in reference to this device's label	
		rule.	
		• If you did not check this option: It is the	
		same value as for the source device.	
Slots	AssetSlots	Same as for the source device.	
Device pins/terminals	Pins	Same as for the source device.	
Ports	Ports	Same as for the source device.	
Ports table (amPort)			
Port #	PortNo	Same as for the port of the source device.	
#	sSequenceNumber	Same as for the port of the source device.	
Connection type	CabCnxType	Same as for the port of the source device.	
Status	seCnxStatus	Same as for the port of the source device.	
Function	Duty	Same as for the port of the source device.	
Slots table (amSlot)			
Name	Name	Same as for the slot of the source device.	
#	sSequenceNumber	Same as for the slot of the source device.	
Slot type	SlotType	Same as for the slot of the source device.	
Pins table (amDevice)	Pin)		
Name	Name	Automatic sequential number.	
#	sSequenceNumber	Automatic sequential number.	
Status	seCnxStatus	Value set to Available by the wizard.	

Viewing the result

You can view the newly created termination field by selecting it in one of the following ways:

- Option 1:
 - 1 Display the list of termination fields (Cable/ Termination fields).
 - 2 Select the termination field created by the wizard.

- Option 2:
 - 1 Display the list of locations (**Portfolio/ Locations**).
 - 2 Select the location of the termination field created by the wizard.
 - 3 Select the **Termination fields** tab.
 - 4 Select the termination field created by the wizard.

After having launched the wizard

The wizard does not populate the **Device** link (**Asset**) of the termination field device slots.

You therefore need to:

- 1 Display the list of termination fields (Cable/ Termination fields).
- 2 Select the termination field created by the wizard.
- 3 Select the **Devices** tab.
- 4 One by one, select the devices with their slots, and for each one of them:
 - 1 Click the **Magnifier**.
 - 2 Click the **Magnifier** to the right of the **Device** link (**Device**).
 - 3 Select the **Slots** tab.
 - 4 One by one, select the slots to use, and for each one of them:
 - 1 Click the **Magnifier**.
 - 2 Populate the fields and links in the detail window.
 - 5 Click Modify.
 - 6 Click **Modify**.
 - 7 Click Close.
- 5 Click Modify.

Use the Duplicate wiring closet wizard for the practical case.

We are going to duplicate the termination field of the floor's wiring closet, which was previously created in the main wiring closet.

- 1 Display the list of locations (**Portfolio/ Locations**).
- 2 Select the location: Cabled building/1st floor/1st floor wiring closet.
- 3 Display the list of actions (**Tools**/ Actions).
- 4 Select the **Duplicate wiring closet** wizard.
- 5 Enter the following information:

Label displayed by the wizard	Value to enter or select	
Select the source and destination locations page		
Destination location	Cabled building/2ndfloor/Main wiring closet	
Name of the new wiring closet	Leave this field empty.	
Duplicate the sub-locations	Do not check this option.	
Rename the new termination field automatically	Check this selection box.	
Refresh new termination field device's labels	Check this selection box.	
Select the termination field(s) to duplicate page		
Select the termination field(s) to duplicate	Floor's termination field	
Locations served by the new termination field(s)	Cabled building/1st floor/1st floor wiring closet	
Select a project and a work order page		
Apply all changes to a project/work order?	Check this selection box.	
Projects	Duplicate a wiring closet	
Work orders	Select the work order proposed by the wizard.	
Device comments	Install the device in termination field.	

- 6 Select the termination field just created:
 - 1 Display the list of locations (**Portfolio/ Locations**).
 - 2 Select the **Cabled building/2nd floor/Main wiring closet** location.
 - 3 Select the **Termination fields** tab.
 - 4 Select the new termination field.
 - 5 Click the **Magnifier** button.
- 7 Rename the termination field to Main termination field.
- 8 Add the modules in the slots of the **ProCurve Switch 4000 M 10 slots** devices:

! Warning:

This will be done later on, according to the procedure described in section Cable devices - manual creation [page 118].

9 Look at the results of the wizard's actions by browsing through the other tabs.

5 Cable devices, cables and connections manual creation

CHAPTER

The cable devices, cables and cable links can be created manually or via the cabling wizards:

- Creating them manually requires more time, obviously, but it also allows you more control over the creation process.
- Creating them with wizards is more rapid, but you have less control.

💋 Note:

Let's recall that the cable devices are stored in the **Assets** table (**amAsset**), while the cables are stored in the **Cables** table (**amCable**). However, the models of these cable devices and cables come from the same table: **Models** (**amModel**).





Cable devices - manual creation

Definitions

- ► Cable device [page 193]
- ▶ Port [page 201]
- ▶ Pin/ Terminal [page 189]
- ▶ Slot [page 194]

Table names

- Assets (amAsset)
- Ports (amPort)
- Pins (amDevicePin)
- Slots (amSlot)

Access menu

Cable/ Cable devices

Letting AssetCenter create the ports and virtual bundles for pin connections

Certain cables/cable devices are composed of numerous bundles/pairs. It would be a tedious task to declare each bundle/pair manually. The cabling wizards are capable of creating virtual bundles and ports when they are required for a cable link. The virtual bundles and ports are also automatically deleted when the cable links that use them are no longer used.

ጆ Note:

The wizards use the topologies to identify the models of the cables/cable devices and the pairs/pins.



Figure 5.2. Ports and virtual bundles - representation

• You start by creating a cable with its pairs, or you let the wizard create it.

Chen, you create a cable device with its pins, or you can let the wizard create it.

Č The wizard creates a virtual bundle using the first available pairs.

The wizard creates a virtual port using the first available pins.

Single or double-sided devices

The cable devices can be single or double-sided. They are single-sided when the device ports or pins are all grouped together on one side. They are double-sided when the ports or pins are present on both sides of the device. Example:

The patch panels are double-sided devices. The back side is frequently used to connect lateral or riser cables. The front side is often used to perform a patch to another patch panel.

When a device is double-sided, the cabling wizards can create more than one cable link on a given port of the device.

The single or double-sided feature of the cable devices is defined by the **Number** of sides field (seDevSdType) in the model.

The following diagram illustrates the different types of double-sided devices, depending on whether the connection is by pin or by port.

In each case, you will need to:

- Declare ports to the level of the device model.
- Populate the Number of pins/terminals field (lPins).

important:

It is very important to respect the directives of these diagrams if you want the wizards to correctly create the virtual ports.



Figure 5.3. Double-sided devices (port/port) - representation



Figure 5.4. Double-sided devices (port/pins) - representation



Figure 5.5. Double-sided devices (pin/pin) - representation

Creating cable devices manually

If you created appropriate device models, you just need to:

- 1 Display the list of assets (Cable/ Cable devices).
- 2 Click New.
- 3 Populate the following fields and links:
 - Model (Model)
 - Max no. connections (sMaxCnxCount)
- 4 Click Create.

The other fields and links to populate are automatically inherited from the model.

Prerequisites

You should have already created the:

- Cable device models (amModel)
- Label rules of the cable devices, ports, slots and pins/terminals (amLabelRule)
- Device types (amItemizedList)
- Cable connection types of the device ports (amCabCnxType)
- Duties of the device ports (amCableDuty)
- Slot types of the devices (**amSlotType**)
- Termination fields containing the devices (amTermField)
- Device locations (amLocation)

Label of the field or link COL name of the field or Domarks

• Modules to insert in the slots (**amAsset**)

Fields and links that must absolutely be populated

Table 5.1. Cable devices - Fields and links that must absolutely be populated

Label of the field of link	link	Remarks
Assets table (amAsset))	
Model	Model	The model must have a cable device nature.
Portfolio items	Assignment	
Status	seCnxStatus	
Max no. connections	sMaxCnxCount	If you want to receive a warning - during a manual creation - in case you create more ports than what is defined by this field.
Device pins/terminals	Pins	If the device is connected to the network by pins.
Ports	Ports	If the device is connected to the network by ports.
Slots	AssetSlots	If the device must receive connection modules in its slots.
Label rule	LabelRule	
Label	Label	

	link	
Ports table (amPort)		
Port #	PortNo	If you create non-virtual ports.
#	sSequenceNumber	If you create non-virtual ports.
Connection type	CabCnxType	If you create non-virtual ports.
Function	Duty	If you create non-virtual ports.
Label rule	LabelRule	
Label	Label	
Status	seCnxStatus	
Port pins/terminals	DevPin	
Slots table (amSlot)		
Name	Name	If you create slots.
#	sSequenceNumber	If you create slots.
Slot type	SlotType	If you create slots.
Assigned device	AssignedAsset	If you create slots, and they are occupied.
Pins table (amDeviceI	Pin)	
Name	Name	If you create pins.
#	sSequenceNumber	If you create pins.
Port	Port	If you create pins.
Status	seCnxStatus	If you create pins.
Label rule	LabelRule	If you create pins.
Label	Label	If you create pins.

Label of the field or link SQL name of the field or Remarks

Connection by ports or by pins

Connection by ports or by pins [page 65]

Double-sided devices

When a device contains ports and/or pins on 2 sides (a patch panel, for example), you need to proceed in one of the following manners:

- If the 2 sides contain ports:
 - 1 Create as many ports as there are on one side or the other of the device (this number should be the same on either side).
 - 2 The ports thus created will appear in two cable links: a host-side link (corresponding to the port on one of the sides) and a user-side link (corresponding to the port on the other side).
- If the 2 sides contain pins:
 - 1 Do not create any pins manually, unless you are not using cabling wizards to create cable links.

- ² The cabling wizards that create cable links will create virtual ports according to your needs as you go. The virtual ports thus created will appear in two cable links: a host-side link (corresponding to the pins on one of the sides) and a user-side link (corresponding to the pins on the other side).
- If 1 side contains ports and the other contains pins:
 - 1 Do not create any ports manually, unless you are not using cabling wizards to create cable links.
 - 2 Create the cable links on the pin side before creating them on the port side. The cabling wizards that create the cable links to the pins will create virtual ports according to your needs as you go. Each virtual port thus appears in a first cable link.
 - 3 Create the cable links on the port side. The cabling wizards that create the cable links to the ports will use the existing virtual ports. The virtual ports thus associated appear in a second cable link.

Slots

If the device contains slots destined to receive connection modules:

- 1 Create the connection modules in the Assets table (amAsset).
- 2 Create the **Slots** links (**AssetSlots**) by associating them to a connection module.

Creating the cable devices manually for the practical case

We are going to:

- 1 Create 2 modules.
- 2 Insert the first module in one of the switch slots of this floor's termination field.
- 3 Insert the second module in one of the switch slots of the main termination field.

To do this:

- 1 Create the 2 modules. For each module:
 - 1 Display the list of assets (Cable/ Cable devices).
 - 2 Click New.
 - 3 Populate the following links and fields:

Field or link to populate	Value for record 1	Value for record 2
Model (Model)	Procurve 10/100 Base T - 8	Procurve 10/100 Base T - 8
	ports	ports
Max no. connections (sMax-	8	8
CnxCount)		
Asset tag (AssetTag	EXAMPLE005	EXAMPLE006

- 4 Click Create.
- 5 Certain fields and links are automatically inherited from the model. You can view this by looking at the different tabs of the module that was just created.
- 2 Associate one of the modules to one of the switch slots of this floor's termination field:
 - 1 Display the list of termination fields (Cable/ Termination fields).
 - 2 Select the **Floor's termination field**.
 - 3 Select the **Devices** tab.
 - 4 Select one of the devices whose **Model** field (**Model**) has the value **ProCurve Switch 4000 M 10 slots**.
 - 5 Click the Magnifier button.
 - 6 Click the **Magnifier** button to the right of the **Device** link (**Device**).
 - 7 Select the **Slots** tab.
 - 8 Select one of the slots.
 - 9 Click the Magnifier button.
 - 10 Select the Assigned device field (AssignedAsset).
 - 11 Select one of the **Hewlett Packard Procurve 10/100 Base T 8 ports** devices that you just created.
 - 12 Click Modify.
 - 13 Click Modify.
 - 14 Click Close.
- 3 Associate the other module with one of the switch slots of the main termination field:
 - 1 Display the list of termination fields (Cable/ Termination fields).
 - 2 Select the Main termination field.
 - 3 Select the **Devices** tab.
 - 4 Select one of the devices whose **Model** field (**Model**) is set to **ProCurve Switch 4000 M - 10 slots**.

- 5 Click the Magnifier button.
- 6 Click the **Magnifier** button to the right of the **Device** field (**Device**).
- 7 Select the **Slots** tab.
- 8 Select one of the slots.
- 9 Click the Magnifier button.
- 10 Select the Assigned device field (AssignedAsset).
- 11 Select one of the **Hewlett Packard Procurve 10/100 Base T 8 ports** devices that you just created.
- 12 Click Modify.
- 13 Click Modify.
- 14 Click Close.

Cables - manual creation

Definitions

- Cable [page 190]
- ▶ Pair/conductor [page 200]
- Bundle [page 197]

Table names

- Cables (amCable)
- Pairs/Conductors (amCablePair)
- Cable bundles (amCableBundle)

Access menu

Cable/ Cables

Creating cables manually

If you created appropriate cable models, you just need to:

- 1 Display the list of cables (Cable/ Cables).
- 2 Click New.
- 3 Populate the Model link (Model).

4 Click Create.

The other fields and links to populate are automatically inherited from the model.

😯 Tip:

It is not necessary to create bundles manually. The cabling wizards can create virtual bundles for you.

▶ Cable devices - manual creation [page 118]

Prerequisites

You should have already created the:

- Cable models (**amModel**)
- Label rules of the cable devices, pairs/conductors and bundles (amLabelRule)
- Cable types (amItemizedList)
- Cable pair/conductor types (CabPairType)
- Duties of the cable bundles (**amCableDuty**)
- Locations of the host and user cables (amLocation)

Fields and links that must absolutely be populated

Table 5.2. Cables - Fields and links that must absolutely be populated

Label of the field or link	SQL name of the field or link	Remarks
Cables table (amCable)		
Model	Model	The model must have a cable
		nature.
Label rule	LabelRule	
Label	Label	
User location	UserLoc	
Host location	HostLoc	
Role	CableRole	
Status	seCnxStatus	
Pairs/Conductors	Pairs	
Pairs/Conductors table (am	ModelPair)	
Name	Name	

Label of the field or link	SQL name of the field or link	Remarks
#	sSequenceNumber	
Pair/Conductor type	CabPairType	
Color code entry	ColorCodeDet	If you selected a color code at the level of the cable model.

Creating the cables manually for the practical case

We are going to create an FTP cable - Category 5 - 4 twisted pairs with a bundle:

- 1 Display the list of cables (Cable/ Cables).
- 2 Click New.
- 3 Populate the following fields and links:

Field or link to populate	Value
Model (Model)	FTP - Category 5 - 4 twisted pairs
Code (Code)	Example001

- 4 Click **Create**.
- 5 Certain fields and links are automatically inherited from the model. You can view this by looking at the different tabs of the cable that was just created.
- 6 Select the **Bundles** tab.
- 7 Click the + button.
- 8 Populate the following fields and links:

Field or link to populate	Value	
# (sSequenceNumber)	1	
Name (Name)	1	
Duty (Duty)	Data	
Status (seCnxStatus)	Available	

- 9 Click Add.
- 10 Select the bundle from the list.
- 11 Click the Magnifier.
- 12 Select the **Pairs/conductors** tab.
- 13 Add the 4 pairs of this cable to the bundle.
- 14 Click Modify.

Connections - manual creation

Definitions

- Cable link [page 199]
- Trace output [page 192]
- Trace [page 190]
- Cross connection [page 199]
- ▶ Host [page 199]
- ▶ User [page 206]

Table names

- Cable links (amCableLink)
- Trace outputs (amTraceOutput)
- Trace histories (amTraceHistory)
- Trace operations (amTraceOp)

Access menu

Cable/ Traces Administration/List of screens

Simplified data model

Relationship between the cable links, device ports and cable bundles

Principals

The connections are made between cable bundles and ports of cable devices. These connections are represented by cable links. A cable link corresponds either to a port or a bundle, but not to both at the same time. Using the hierarchic link between two cable links, you can indicate that a port or a bundle is connected to a port or a bundle. There is thus no direct link between ports and bundles. Using the hierarchic links (which indicate that a such a cable link is a parent link or sub-link of another cable link), you can create a trace. The parent cable links must be on the "host" side, in other words, the most important side of the termination field.

Trace example

port -> bundle -> port

Correspondence between your network and the AssetCenter database

The following diagrams illustrate the way in which we represent a connection between a device port (a wall outlet, for example) and a cable bundle (a lateral cable, for example).

United to connect to "user" port.

e "User" port to connect to "host" bundle.

"Host" cable link concerning the bundle. This link is the parent of the "user" link.

User" cable link concerning the port. This link is the sub-link of the "host" link.



Figure 5.6. Cable link - representation of implicated components







Figure 5.8. Cable links - correspondence between the cable link to represent and the database

Tables used in the complete description of the connections



Figure 5.9. Cable links - detailed data model

Comments on the diagram

This diagram enables you to understand how the numerous tables, used in the description of the connections, work together.

- Connected bundle.
- **Connected port.**
- Cable links concerning either a bundle or a port.
- Copy of the cable link.
- Description of the connection.
- Intermediary table between projects/work orders and trace outputs.
- Project enabling you to find the connection detail.

Work order that enables you to manage the implementation of the physical connection.

Creating connections manually

The following tables were not designed to be manually populated:

- amCableLink
- amTraceOutput
- amTraceHistory
- Trace operations

The explanations that we provide here are intended for those wanting to know more about how these tables function.

Before creating a connection manually:

1 Define the traces to represent.

Example: wall outlet->lateral cable->termination field

In general, a trace is composed of 2 cable devices linked by a cable.

- 2 Determine which direction you want to follow: host->user or user->host.
- 3 Begin with the very last point.

Examples:

- 1 If you create the cable links in the user->host direction, you will begin with a termination-field device.
- 2 If you create the cable links in the host->user direction, you will begin with a user wall outlet.
- 4 Create one cable link per connection point.

In general: 2 device links and 1 cable link.

Use the **Parent** link to connect the trace components.

For each trace to create:

- 1 Display the list of traces (**Cable/ Traces**).
- 2 Click New.
- 3 Populate the fields and links in the link window.
- 4 Display the list of screens (Administration/List of screens).
- 5 Select the Trace outputs table (amTraceOutput).
- 6 Click New.
- 7 Populate the fields and links that are not inside the tabs of the detail window.
- 8 Click + in the following tabs:
 - 1 Trace history: This creates a record in the **Trace histories** table (**amTraceHistory**). Simply copy the information from the cable link detail and paste it here.
 - 2 Operation: This creates a record in the **Trace operations** table (**amTraceOp**).

Prerequisites

You should have already created:

- The cable devices (**amAsset**) to connect and their ports (**amPort**).
- The cables (**amCable**) to connect and their bundles (**amCableBundle**).
- The label rules for the cable links (**amLabelRule**).
- The cable duties (**amCableDuty**).

Fields and links that must absolutely be populated

Table 5.3. Connections - Fields and links that must absolutely be populated

Remarks

Label of the field or link	SQL name of the field or link	Remarks	
Cable	Cable	If the cable link concerns a	
		cable.	
Bundle	Bundle	If the cable link concerns a	
		cable.	
Device	Device	If the cable link concerns a	
		cable device.	
Port	Port	If the cable link concerns a	
		cable device.	
Trace outputs table (amT	raceOutput)		
Туре	seTraceType		
Function	Duty		
Label	ModifiedLinkLabel		
Summary of the trace	TraceString		
Trace history	TraceHist		
Trace operations	TraceOps		
Trace histories table (am	TraceHistory)		
Name	Name		
Туре	seLinkType		
Parent history	Parent		
Label	Label		
Cable	Cable		
Bundle	Bundle		
Device	Device		
Port	Port		
Link	Link		
Trace operations table (an	mTraceOp)		
Title	Label		
Host trace history	HostTraceHist		
User trace history	UserTraceHist		

Creating the connections manually for the practical case

We are going to create a trace composed of the following cable links:

```
secondary termination-field device -> 4 twisted pairs -> principal ter mination-field device
```

The direction of such a trace is user to host. We will thus begin by creating the host-side cable link.

Creating the cable links

- 1 Display the list of traces (**Cable/ Links**).
- 2 For each cable link, create a record and populate the following fields and links:

Field or link to populate	Value for record 1	Value for record 2	Value for record 3
Name (Name)	Example002	Example003	Example004
Cable link type	Device	Cable	Device
(seLinkType)			
Parent link (Parent)	Do not populate.	Device (Example002)	Cable (Example003)
Label rule (LabelRule)	Practical case - Port of	Practical case - Link -	Practical case - Port of
	a termination-field patch panel link	Sequentially, by pairs	a termination-field patch panel link
Label (Label)	Do not enter any val- ues; accept the pro- posed default value.	Do not enter any val- ues; accept the pro- posed default value.	Do not enter any val- ues; accept the pro- posed default value.
Duty (Duty)	Data	Data	Data
Cable (Cable)	Field not available.	Corel FTP - Category 5 - 4 twisted pairs (EX- AMPLE001)	Field not available.
Bundle (Bundle)	Field not available.	1 (EXAMPLE001)	Field not available.
Device (Device)	Hewlett Packard Pro- curve 10/100 Base T - 8 ports (EXAMPLE006)	Field not available.	Hewlett Packard Pro- curve 10/100 Base T - 8 ports (EXAMPLE005)
Port (Port)	1 (EXAMPLE006)	Field not available.	1 (EXAMPLE005)

Creating the trace history

- 1 Display the list of screens (Administration/List of screens).
- 2 Select the **Trace outputs** table (**amTraceOutput**).
- 3 Create a record and populate the following fields and links:

Field or link to populate	Value
Type (seTraceType)	Connect
Duty (Duty)	Data
Label (ModifiedLinkLabel)	'Data' riser run from location '/Cabled building/2nd floor/Main wiring closet' to '/Cabled building/1st floor/1st floor wiring closet/'

Field or link to populate	Value	
Trace summary (TraceString)	Hewlett Packard Procurve 10/100 Base T - 8 ports (EXAMPLE005)	
	- (1) <connecter> Corel FTP - Category 5 - 4 twisted pairs</connecter>	
	(EXAMPLE001) - (1) <connecter> Hewlett Packard Procurve</connecter>	
	10/100 Base T - 8 ports (EXAMPLE006) - (2)	

Creating the trace histories for the trace output

- 1 Display the list of screens (Administration/List of screens).
- 2 Select the **Trace histories** table (**amTraceHistory**).
- 3 Create a new record in the **Trace histories** table (**amTraceHistory**) and populate the following fields and links:

ጆ Note:

Most of the information is duplicated from the cable link corresponding to the history.

Field or link to populate	Value for record 1	Value for record 2	Value for record 3
Name (Name)	Example002	Example003	Example004
Type (seLinkType)	Device	Cable	Device
Parent history (Parent)	Do not populate.	Device (Example002)	Cable (Example003)
Label (Label)	Same as for links	Same as for links	Same as for links
Cable (Cable)	Field not available.	Corel FTP - Category 5 - 4 twisted pairs (EX- AMPLE001)	Field not available.
Bundle (Bundle)	Field not available.	1 (EXAMPLE001)	Field not available.
Device (Device)	Hewlett Packard Pro- curve 10/100 Base T - 8 ports (EXAMPLE006)	Field not available.	Hewlett Packard Pro- curve 10/100 Base T - 8 ports (EXAMPLE005)
Port (Port)	1 (EXAMPLE006)	Field not available.	1 (EXAMPLE005)
Cable link (Link)	Device (Example002)	Cable (Example003)	Device (Example004)

Creating the trace operations for the trace outputs

There are two operations to perform:

- Connecting the main termination field to the cable.
- Connecting the cable to the secondary termination field.
- 1 Display the list of screens (Administration/List of screens).

- 2 Select the **Trace operations** table (**amTraceOp**).
- 3 Create a new record for each operation in the **Trace operations** table (**amTraceOp**) and populate the following fields and links:

Field or link to populate	Value for record 1	Value for record 3
Label (Label)	Connect	Connect
Host trace history (HostTrace-	Hewlett Packard Procurve	Corel FTP - Category 5 - 4
Hist)	10/100 Base T - 8 ports (EX-	twisted pairs (EXAMPLE001)
	AMPLE006)	
User trace history (UserTrace-	Corel FTP - Category 5 - 4	Hewlett Packard Procurve
Hist)	twisted pairs (EXAMPLE001)	10/100 Base T - 8 ports (EX-
		AMPLE005)
6 Connections – creation with the wizards

AssetCenter is provided with numerous cabling wizards that automate the creation of connections.

This chapter explains how they work.

💋 Note:

The cabling wizards do not populate the following tables unless you select a project and a work order at the end of the wizard's execution:

- Trace outputs (amTraceOutput)
- Trace histories (amTraceHistory)
- Trace operations (amTraceOp)

Run riser cables wizard

Functions performed by the wizard

This wizard connects two termination fields using a riser cable.

Prerequisites

You should have already created:

- The host termination field.
- The devices of the host termination field to which the riser cable will connect.

🐓 Warning:

You must respect different conditions according to the connection to the device and whether it is made by ports or by pins.

- Connection by ports or by pins [page 65]
- The user termination field.
- The devices of the user termination field to which the riser cable will connect.

! Warning:

You must respect different conditions according to the connection to the device and whether it is made by ports or by pins.

- Connection by ports or by pins [page 65]
- The connection types you will use to connect the cable to the host and user devices.
- The label rules you will use to label the cable, the host links and the user links.
- The riser cable model to create.
- A project and a work order, if you want to store the trace of the connections carried out.

Use the Run riser cables wizard.

Launching the wizard

This wizard does not require any particular context:

- 1 Display the list of actions (**Tools/ Actions**).
- 2 Select the **Run riser cables** wizard.

Information used when using the wizard

🜻 Warning:

Certain labels in the following table are not displayed by the wizard unless you select the appropriate option.

Table 6.1. Run riser cables wizard - description of fields to populate

Label displayed by the wizard	Explanations
Select a host termination field page	
Locations	Select the location of the host termination field
	that you want to connect to the riser cable.
Host termination field	Select the host termination field to connect to the riser cable.
Do you want to select the starting position?	 If you check this option, the wizard will display the list of positions of the termination field with its roles and the termination-field device. If you don't check this option, the wizard automatically searches for the first available termination-field device having a port that is: Available Associated with a connection type that you will select on another page.
Termination-field devices	Select the termination-field device from which you will connect the riser cable.
Select the host termination field connectors	and a label rule page
Cable connection types	Select the connection type enabling you to connect the riser cable to the termination field.
	The wizards use the connection type, which you choose, as part of their criteria to select a port in order to create a cable link.
	If the connection type is by pin and the wizard created a virtual port to create a cable link, the connection type selected is associated with this virtual port.

Label displayed by the wizard	Explanations
Select the label rule for the links	You use this label rule to populate the Label field (Label) of the link created at the level of the host-termination-field device.
Do you want to search (not create) for ports of this pin mode?	If you check this option, the wizard only looks for ports:
	• That already exist (the wizard does not create virtual ports).
	• Associated with a connection type that you will select with the wizard.
Map consecutive pins to virtual port for pin- based devices (default is next available pin)?	• If you check this option, the wizard only uses the pins with consecutive numbers to create virtual ports.
	• If you don't check this option, the wizard selects the first available pins without re- quiring them to have consecutive numbers.
Type of cable connection for odd pins	This part of the wizard handles pins that do not exist in numbers large enough to create a connection after having associated all the other pins to virtual ports.
	These pins can, however, be used in other ways. Indicate in this field what type of connection to use for the remaining pins.
Type of duty for odd pins connector	Select the duty assigned to the remaining pins.
Do you want to select the starting port?	Select this option if you want to specify from which number the wizard should associate a port to a bundle of the riser cable to create a link.
	This refers to a port of the termination-field device that was selected with the wizard on the previous page.
Starting port	This port specifies from which number the wizard can associate a port to a bundle of the riser cable to create a link.
	This refers to a port of the termination-field device that was selected with the wizard on the previous page.

Label displayed by the wizard	Explanations	
Do you want to select the starting pin?	Select this option if you want to specify from	
	which pin number the wizard can start using	
	pins to create a virtual port.	
	This port will be associated to a riser-cable	
<u>.</u>	bundle to create a link.	
Starting pin	This pin determines from which pin number the wirgend can start using pine to greate a vir	
	tual port	
	This port will be associated to a risor cable	
	bundle to create a link	
Select a user termination field page		
Locations	Select the location of the user termination field	
	to connect to the riser cable.	
	Only the locations served by the host termina-	
	tion field are listed.	
User termination field	Select the user termination field to connect to	
	the riser cable.	
Do you want to select a starting position?	• If you check this option, the wizard will	
	tion field with its roles and the termina	
	tion-field device.	
	• If you don't check this option, the wizard	
	automatically searches for the first available	
	termination-field device having a port that	
	is:	
	Available	
	• Associated with a connection type that	
	you will select on another page.	
Termination-field devices	Select the termination-field device to which	
	you will connect the riser cable.	
Select the user termination field connectors and a label rule page		
Cable connection types	Select the connection type enabling you to connect the riser cable to the termination field.	
	The wizards use the connection type, which	
	you choose, as part of their criteria to select a	
	port in order to create a cable link.	
	If the connection type is by pin and the wizard	
	created a virtual port to create a cable link, the	
	virtual port	
	Filturi Polt.	

Label displayed by the wizard	Explanations
Select the label rule for the links	You use this label rule to populate the Label field (Label) of the link created at the level of the user-termination-field device.
Do you want to search (not create) for ports of this pin mode?	If you check this option, the wizard only looks for ports:
	• That already exist (the wizard does not create virtual ports).
	• Associated with a connection type that you will select with the wizard.
Map consecutive pins to virtual port for pin- based devices (default is next available pin)?	• If you check this option, the wizard only uses the pins with consecutive numbers to create virtual ports.
	• If you don't check this option, the wizard selects the first available pins without re- quiring them to have consecutive numbers.
Type of cable connection for odd pins	This part of the wizard handles pins that do not exist in numbers large enough to create a connection after having associated all the other pins to virtual ports.
	These pins can, however, be used in other ways. Indicate in this field what type of connection to use for the remaining pins.
Type of duty for odd pins connector	Select the duty assigned to the remaining pins.
Do you want to select an starting port?	Select this option if you want to specify from which number the wizard should associate a port to a bundle of the riser cable to create a link.
	This refers to a port of the termination-field device that was selected with the wizard on the previous page.
Starting port	This port specifies from which number the wizard can associate a port to a bundle of the riser cable to create a link.
	This refers to a port of the termination-field device that was selected with the wizard on the previous page.

Label displayed by the wizard	Explanations
Do you want to select a starting pin?	Select this option if you want to specify from
	which pin number the wizard can start using
	This was taken in the second start of the second start with the second start of the se
	his port will be associated to a riser-cable
Starting pin	This pin determines from which pin number
otariting pin	the wizard can start using pins to create a vir-
	tual port.
	This port will be associated to a riser-cable
	bundle to create a link.
Select a riser cable page	
Cable role	The selected role is used to:
	• Populate the Role field (CableRole) of a cable created by the wizard
	Select a device to connect
	• Filters the existing cables that the wizard
	displays.
Do you want to use an existing cable?	• If you check this option, the wizard asks you to select an existing cable.
	• If you do not check this option, the wizard asks you to select a riser-cable model in order to create the cable itself.
Number of pairs to be connected:	Define how many cable pairs must be connec- ted to the termination fields by the wizard.
Do you want to select a starting pair?	• If you check this option, you can specify from which number the wizard can associ- ate an available pair to a bundle of the riser cable to create a link.
	• If you do not check this option, the wizard selects the first available pairs.
Starting pairs for the cable model	Select the starting pair.
Starting pairs for the cable	Select the starting pair.
Select label rule for riser page	
Do you want to use a label rule for the cable label?	• If you check this option, the wizard uses a label rule to populate the Label field (Label) of the cable.
	• If you check this option, you can directly enter the label using the wizard.
Select the label rule for the cable	You use this label rule to populate the Label field (Label) of the cable.

Label displayed by the wizard	Explanations
Duty of the new cable	 The selected duty is: Part of the criteria the wizards use to select ports to connect. Associated to the ports and virtual bundles created by the wizard to create the links.
Number of pairs in a bundle	Indicates the number of pairs to associated to each virtual bundle created by the wizard.
	You must be able to divide the total number of pairs to be connected, which you defined in the previous page, by this number.
	 The default value is calculated in the following manner: 1 The wizard subtracts the connection type with the least numbers of pins (from the host and user connection types selected with the wizard)
	 2 It then divides the number of pins of the connection type that was subtracted by the number of pairs/conductors of the pair/conductor type of the cable selected with the wizard.
Select the label rule for the links	You use this label rule to populate the Label field (Label) of the cable link created from the cable.
Select a project and a work order page	
Cable comments	Value for the Description field (Description) of the Cables concerned by the project table (amProjCable).
Connection comments	Value for the Description field (Description) of the Traces concerned by the project table (amProjTraceOut).
Connection termination field for the work order	Value for the Label field (Label) of the Trace operations table (amTraceOp).

Data created or modified by the wizard

The wizard creates, if appropriate, the following items:

- A cable (**amCable**)
- Pairs for this cable (amCablePair)
- Virtual bundles (amCableBundle)

- Virtual ports (**amPort**)
- Cable links (**amCableLink**)
- Trace histories (**amTraceHistory**)
- Trace outputs (**amTraceOutput**)
- Trace operations (**amTraceOp**)

The wizard populates the following fields:

Table 6.2. Run riser cables wizard - created or modified data

Field label	SQL name of the field	Explanations
Assets table (amAsset	:)	
Ports	Ports	The wizard creates virtual ports connected to bundles of the riser cable if it is necessary.
Ports table (amPort)		
Port #	PortNo	This field is only populated for the virtual ports created by the wizard.
		Its value is the number after the last port number existing for the device.
#	sSequenceNumber	This field is only populated for the virtual ports created by the wizard.
		Its value is the number after the last port number existing for the device.
Connection type	CabCnxType	This field is only populated for the virtual ports created by the wizard.
		Connection type selected using the wizard for the host or user termination field.
Function	Duty	This field is only populated for the virtual ports created by the wizard.
		Duty defined by the wizard for the cable.
Status	seCnxStatus	This field is only populated for the virtual ports created by the wizard.
		Its value is set to Available by the wizard.
Virtual port	bVirtual	This field is only populated for the virtual ports created by the wizard.
		Its value is set to Yes.
Port pins/terminals	DevPin	Pins selected by the wizard to create a cable link.
Cables table (amCabl	e)	

Field label	SQL name of the field	Explanations
Model	Model	Cable model selected using the wizard.
Label rule	LabelRule	This field is only modified for the cables cre- ated by the wizard.
		The label rule selected using a wizard for the cable.
Label	Label	This field is only modified for the cables cre- ated by the wizard.
		The label is calculated according to the label rule.
User location	UserLoc	This field is only modified for the cables cre- ated by the wizard.
		Location of the user termination field selected using the wizard.
Host location	HostLoc	This field is only modified for the cables cre- ated by the wizard.
		Location of the host termination field selected using the wizard.
Role	CableRole	Role selected using the wizard.
Status	seCnxStatus	This field is only modified for the cables cre- ated by the wizard.
		Its value is set to Available by the wizard.
Pairs/Conductors	Pairs	This field is only modified for the cables cre- ated by the wizard.
		Pairs/conductors of the model.
Bundles	Bundles	Virtual bundles created by the wizard if it is necessary.
Pairs/Conductors ta	able (amCablePair)	
Bundle	Bundle	Bundle with which the pair/conductor is asso- ciated to create a cable link.
Pins table (amDevic	cePin)	
Port	Port	Port with which the pin/terminal is associated to create a cable link.
Cable bundle table	(amCableBundle)	
#	sSequenceNumber	This field is only populated for the virtual bundles created by the wizard.
		Its value is the number after the last bundle number existing for the device.

Field label	SQL name of the field	Explanations
Name	Name	This field is only populated for the virtual
		bundles created by the wizard.
		Its value is the number after the last bundle
		number existing for the device.
Function	Duty	This field is only populated for the virtual
		bundles created by the wizard.
		Duty defined by the wizard for the cable.
Status	seCnxStatus	This field is only populated for the virtual
		bundles created by the wizard.
		Its value is set to Available by the wizard.
Virtual bundle	bVirtual	This field is only populated for the virtual
		bundles created by the wizard.
		Its value is set to Yes .
Pairs/Conductors	Pair	Pairs/conductors selected by the wizard to
		create a cable link.
Cable links table (an	nCableLink)	
Name	Name	Default value of the field.
Link type	seLinkType	Populated by the wizard according to whether
		the cable link concerns a cable device or a
		cable.
Parent link	Parent	
Label rule	LabelRule	The label rule selected using a wizard.
Label	Label	The label is calculated according to the label
<u> </u>		rule.
Function	Duty	Duty selected using the wizard.
Device	Device	Device selected automatically by the wizard
D	D	or by you using the wizard.
Port	Port	Port selected or created by the wizard.
Cable	Cable	Cable created by the wizard or selected by you
D 11	ון ת	using the wizard.
Bundle	Bundle	Bundle selected or created using the wizard.
I race histories table	e (am I raceHistory)	
Name	Name	Copy the value defined for the same field used
Tumo	a LinkTuna	at the level of the cable link.
Type	selinkiype	copy the value defined for the same field used
Parant history	Daront	Copy the value defined for the same field used
i arciit ilistory		at the level of the cable link
Label	Label	Copy the value defined for the same field used
Lauti	Lauci	at the level of the cable link
		at the level of the cable link.

Field label	SQL name of the field	Explanations
Device	Device	Copy the value defined for the same field used
		at the level of the cable link.
Port	Port	Copy the value defined for the same field used
		at the level of the cable link.
Cable	Cable	Copy the value defined for the same field used
		at the level of the cable link.
Bundle	Bundle	Copy the value defined for the same field used
		at the level of the cable link.
Link	Link	Cable link created by the wizard.
Trace outputs table (a	mTraceOutput)	
Туре	seTraceType	Value set to To connect by the wizard.
Function	Duty	Duty selected using the wizard.
Label	ModifiedLinkLabel	The label is calculated by the wizard and is not
		based on a label rule in any way.
Summary of the trace	TraceString	Calculated by the wizard.
Trace history	TraceHist	Histories created by the wizard.
Trace operations	TraceOps	Operations created by the wizard.
Trace operations table	e (amTraceOp)	
Title	Label	Value defined by the wizard according to the
		comments that you entered using the wizard.
Host trace history	HostTraceHist	Defined by the wizard.
User trace history	UserTraceHist	Defined by the wizard.

Viewing the result

The easiest way to view the result of this wizard is to display the detail of the project selected on the last page of the wizard:

- 1 Display the list of projects (**Portfolio/ Projects**).
- 2 Select the project created by the wizard.
- 3 Select the **Cables** tab.

The **Cables** tab enables you to locate the cable that connects the two termination fields:

- 1 Select the cable to examine.
- 2 Click the magnifier to display an intermediary window.
- 3 In the intermediary window, click the magnifier to the right of the **Cable** field to view the detail of the device.
- 4 Right-click on any field (not link) in the **Assets** table (**amAsset**) to display the shortcut menu.

5 From the shortcut menu, select either the Actions/ Cable cross-connections or Actions/ Display cable traces menu entry to view and browse through the traces.

This particularly enables you to access the termination-field devices that were connected to the cable by a wizard.

4 Select the **Traces** tab.

The Traces tab displays the list of trace outputs created by the wizard.

After having launched the wizard

Run the riser cable at the level of your network, being sure to respect the indications listed in the project and the work order, and update the follow-up information of the project and work order.

Resolving possible problems

If the **Select a host termination field** page or **Select a user termination field** page does not display any termination field to select:

- 1 Click **Cancel** to interrupt the execution of the wizard.
- 2 Display the list of termination fields (Cable/ Termination fields).
- 3 Select the host termination field (the one that was not listed by the wizard).
- 4 Select the **Served locations** tab.
- 5 Add the location to the location of the user termination field to the list.
- 6 Click **Modify**.
- 7 Click Close.
- 8 Execute the Run riser cables wizard again.

Use the Run riser cables wizard for the practical case.

We are going to run a telephone riser cable between the floor's termination field and the main termination field.

- 1 Display the list of actions (**Tools/ Actions**).
- 2 Select the **Run riser cables** wizard.
- 3 Enter the following information:

Value to enter or select

Select a host termination field page

Label displayed by the wizard	Value to enter or select
Locations	/Cabled building/2nd floor/Main wiring closet/
Host termination field	Main wiring closet
Do you want to select a starting position?	Do not check this option.
Select the host termination field connectors and	l a label rule page
Cable connection types	RJ45 - 568B - Pin
Select the label rule for the links	Practical case - Port of a termination-field patch
	panel link
Do you want to search (not create) ports of this	Do not check this option.
pin mode?	
Map consecutive pins to virtual port for pin-	Check this selection box.
based devices (default is next available pin)?	
Type of cable connection for odd pins	Do not change the information displayed by the
	wizard; it will not be used.
Type of duty for odd pins connector	Do not change the information displayed by the
	wizard; it will not be used.
Select a user termination field page	
Locations	Cabled building/1st floor/1st floor wiring closet
User termination field	Wiring closet for each floor
Do you want to select a starting position?	Do not check this option.
Select the user termination field connectors and	l a label rule page
Cable connection types	RJ45 - 568B - Pin
Select the label rule for the links	Practical case - Port of a termination-field patch
	panel link
Do you want to search (not create) ports of this	Do not check this option.
pin mode?	
Map consecutive pins to virtual port for pin-	Check this selection box.
based devices (default is next available pin)?	
Type of cable connection for odd pins	Do not change the information displayed by the
	wizard; it will not be used.
Type of duty for odd pins connector	Do not change the information displayed by the
	wizard; it will not be used.
Select a riser cable page	
Cable role	Riser
Do you want to use an existing cable?	Do not check this option.
Model of the cable to create	L 120 - Category 5 - 32 twisted pairs
Number of pairs to be connected:	32
Do you want to select a starting pair?	Do not check this option.
Select label rule for riser page	
Do you want to use a label rule for the cable la-	Check this selection box.
bel?	
Select the label rule for the cable	Practical case - Cables

Label displayed by the wizard	Value to enter or select
Duty for the new cable:	Voice
Number of pairs in a bundle	1
Select the label rule for the links	Practical case - Link - Sequentially, by pairs
Select a project and a work order page	
Apply all changes to a project/work order?	Check this selection box.
Projects	Run riser cables
Work orders	Select the work order proposed by the wizard.
Comments on the cable	Install the new cable
Connection comments	Riser run to connect devises
Connection termination field for the work order	CONNECT

Look at the result:

- 1 Display the list of projects (**Portfolio/ Projects**).
- 2 Select the **Run riser cables** project.
- 3 Select the **Cables** tab.
- 4 Select the cable just created.
- 5 Click the magnifier to display an intermediary window.
- 6 In the intermediary window, click the magnifier to the right of the **Cable** field to view the detail of the device.
- 7 Have a look at the different tabs at your own pace.
- 8 Select any field (not link) in the **Cables** table (**amCable**).
- 9 Right-click.
- 10 From the shortcut menu, select either the Actions/ Cable cross-connections or Actions/ Display cable traces menu entry to view and browse through the traces.

This particularly enables you to access the termination-field devices that were connected to the cable by a wizard.

Run lateral cables wizard

Functions performed by the wizard

This wizard connects wall outlets to a termination field using lateral cables. The wizard uses a group of topologies as its model.

Prerequisites

You should have already created:

- The location of the wall outlets.
- The group of topologies to use as the model.
- The topologies that compose the topology group.
- The termination fields that serve the locations of the wall outlets.
- The devices of the termination field to which the lateral cable will connect.

! Warning:

You must respect different conditions according to the connection to the device and whether it is made by ports or by pins.

- Connection by ports or by pins [page 65]
- A project and a work order, if you want to store the trace of the connections carried out.

Use the Run lateral cables wizard.

Launching the wizard

This wizard does not require any particular context.

- 1 Display the list of actions (**Tools/ Actions**).
- 2 Select the **Run lateral cables** wizard.

😯 Tip:

If you display the list of locations (**Portfolio/Locations** menu item) and select all the locations of the wall outlets before executing the wizard, the wizard will not ask to you perform this selection again.

Information used when using the wizard

ጆ Note:

Certain labels in the following table are not displayed by the wizard unless you select the appropriate option.

Table 6.3. Run lateral cables wizard - description of fields to populate

Label displayed by the wizard	Explanations
Select user locations page	
Locations	Select one location per wall outlet to connect.
Select the topology group page	
Topology groups	Select the group of topologies that will be used as the connection model of the wall outlets to the termination field that serves them.
Are there any topologies in which you want to look for ports with pin-based connectors?	Check this option if you want the wizard to look for virtual ports that have already been created on the host or the user side of the to- pology. This option's only result is that it displays two other options that will have an effect on how
Do you want to look for ports on the host side of the topology?	the wizard works. If you check this option, the wizard looks for virtual ports that exist at the level of the ter- mination fields in order to create the connec- tion with the lateral cable.
	This is valid for the topologies selected from the following list.
Do you want to look for ports on the user side of the topology?	If you check this option, the wizard looks for virtual ports that exist at the level of the wall outlets in order to create the connection with the lateral cable.
	This is valid for the topologies selected from the following list.
Topology in a group	Select the topologies to which apply the op- tions previously checked.
Map consecutive pins to virtual port for pin- based devices (default is next available pin)?	 If you check this option, the wizard only uses the pins with consecutive numbers to create virtual ports. If you don't check this option, the wizard selects the first available pins without requiring them to have consecutive numbers.
Select a project and a work order page	
Comments on the devices	Value for the Description field (Description) of the Assets included in projects table (amAstProjDesc).

Label displayed by the wizard	Explanations
Cable comments	Value for the Description field (Description)
	of the Cables concerned by the project table
	(amProjCable).
Connection comments	Value for the Description field (Description)
	of the Traces concerned by the project table
	(amProjTraceOut).
Connection termination field for the work	Value for the Label field (Label) of the Trace
order	operations table (amTraceOp).

Data created or modified by the wizard

The wizard creates, if appropriate, the following items:

- Cables (**amCable**)
- Pairs for this cable (**amCablePair**)
- Virtual bundles (amCableBundle)
- Cable devices (**amAsset**)
- Pins for the devices (amDevicePin).
- Virtual ports for the devices (**amPort**).
- Cable links (**amCableLink**)
- Trace histories (**amTraceHistory**)
- Trace outputs (**amTraceOutput**)
- Trace operations (**amTraceOp**)

The wizard populates the following fields:

Table 6.4. Run lateral cables wizard - created or modified data

Field label	SQL name of the field	Explanations
Assets table (amAss	set)	
Ports	Ports	The wizard creates virtual ports connected to bundles of the lateral cable if it is necessary.
Location	Location	The wizard links wall outlets to the location selected using the wizard, if it creates wall outlets.
Ports table (amPor	t)	

Field label	SQL name of the field	Explanations
Port #	PortNo	This field is only populated for the virtual
		ports created by the wizard.
		Its value is the number after the last port
		number existing for the device.
#	sSequenceNumber	This field is only populated for the virtual
		ports created by the wizard.
		Its value is the number after the last port
		number existing for the device.
Connection type	CabCnxType	This field is only populated for the virtual
		ports created by the wizard.
		Its value corresponds to the connection type
		defined at the level of the topology step for the
		device to which the port belongs.
Function	Duty	This field is only populated for the virtual
		ports created by the wizard.
		Its value corresponds to the duty defined at
		the level of the topology for the device to
		which the port belongs.
Status	seCnxStatus	This field is only populated for the virtual
		ports created by the wizard.
		Its value is set to Available by the wizard.
Virtual port	bVirtual	This field is only populated for the virtual
		ports created by the wizard.
		Its value is set to Yes.
Port pins/terminals	DevPin	Pins selected by the wizard to create a cable
		link, if the connection is by pin.
Cables table (amCab	le)	
Model	Model	This field is only modified for the cables cre-
		ated by the wizard.
		Cable model defined at the level of the topo-
		logy step.
Label rule	LabelRule	Default value of the field.
Label	Label	This field is only modified for the cables cre-
		ated by the wizard.
		The label is calculated according to the label
.		rule.
User location	UserLoc	This field is only modified for the cables cre-
		ated by the wizard.
		Location of the wall outlet.

Host location HostLoc This field is only modified for the cables cre- ated by the wizard. Location of the termination field found by the wizard to create the connection. Role CableRole This field is only modified for the cables cre- ated by the wizard. Role defined at the level of the topology step. Status secNxStatus This field is only modified for the cables cre- ated by the wizard. Its value is set to Available by the wizard. Pairs/Conductors Pairs This field is only populated for the cables cre- ated by the wizard. Pairs/conductors of the model. Bundles Bundles Virtual bundles created by the wizard if it is neccessary. Pairs/Conductors table (amCablePair) Bundle Bundle Bundle Bundle with which the pair/conductor is asso- ciated to create a cable link. Pins table (amCetPin) Port Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # sSequenceNumber fits value is the number after the last bundle number existing for the device. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard.	Field label	SQL name of the field	Explanations	
ated by the wizard. Location of the termination field found by the wizard to create the connection. Role CableRole This field is only modified for the cables created by the wizard. Role defined at the level of the topology step. Status seCnxStatus This field is only modified for the cables created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Bundles Bundles Virtual bundles created by the wizard. Pairs/Conductors table (amCablePair) Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # sSequenceNumber # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Duty defined at the level of the topology. Status seCn	Host location	HostLoc	This field is only modified for the cables cre-	
Role CableRole This field is only modified for the cables created by the wizard. Role CableRole This field is only modified for the cables created by the wizard. Role defined at the level of the topology step. Status Status Status seCnxStatus This field is only modified for the cables created by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Bundles Bundles Virtual bundles created by the wizard. Pairs/Conductors table (amCablePair) Bundle with which the pair/conductor is associated to create a cable link. Pins table (amCablePair) Port Port with which the pin/terminal is associated to create a cable link. Pins table (amCableBundle) # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is noly populated for the virtual bundles created by the wizard. Functi			ated by the wizard.	
Role CableRole This field is only modified for the cables created by the wizard. Role defined at the level of the topology step. Status seCnxStatus This field is only modified for the cables created by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Bundles Bundles Virtual bundles created by the wizard. Pairs/Conductors table (amCablePair) Bundle Bundle with which the pair/conductor is associated to create a cable link. Port Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Mame This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. This field is only populated for the virtual bundles created by the wizard. Its value is the number after			Location of the termination field found by the wizard to create the connection.	
ated by the wizard. Role defined at the level of the topology step. Status Status SeCnxStatus This field is only modified for the cables created by the wizard. Pairs/Conductors Pairs/Conductors of the model. Bundles Bundles Pairs/Conductors table (amCablePair) Bundle Bundle Bundle <td co<="" td=""><td>Role</td><td>CableRole</td><td>This field is only modified for the cables cre-</td></td>	<td>Role</td> <td>CableRole</td> <td>This field is only modified for the cables cre-</td>	Role	CableRole	This field is only modified for the cables cre-
Role defined at the level of the topology step. Status seCnxStatus This field is only modified for the cables created by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Pairs/Conductors of the model. Bundles Bundles Pairs/Conductors table (amCablePair) Bundle Bundle Bundle Bundle (amCablePair) Port Port with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # # sSequenceNumber # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Name Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Its			ated by the wizard.	
Status seCnxStatus This field is only modified for the cables created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Pairs/Conductors Pairs This field is only populated for the cables created by the wizard. Bundles Bundles Virtual bundles created by the wizard if it is necessary. Pairs/Conductors table (amCablePair) Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Duty defined at the level of the topology. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard.			Role defined at the level of the topology step.	
Its value is set to Available by the wizard.Pairs/ConductorsPairsThis field is only populated for the cables cre- ated by the wizard. Pairs/conductors of the model.BundlesBundlesVirtual bundles created by the wizard if it is necessary.Pairs/Conductors table (amCablePair)BundleBundle with which the pair/conductor is asso- ciated to create a cable link.Pins table (amDevicePin)PortPort with which the pin/terminal is associated to create a cable link.PortPortPort with which the pin/terminal is associated to create a cable link.MameSequenceNumberThis field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device.NameNameThis field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device.FunctionDutyThis field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device.FunctionDutyThis field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard.StatusseCnxStatusThis field is only populated for the virtual bundles created by the wizard.Virtual bundlebVirtualThis field is only populated for the virtual bundles created by the wizard.Its value is set to Available by the wizard.Its value is set to Available by the wizard.	Status	seCnxStatus	This field is only modified for the cables cre- ated by the wizard.	
Pairs/Conductors Pairs This field is only populated for the cables cre-ated by the wizard. Bundles Bundles Virtual bundles created by the wizard if it is necessary. Pairs/Conductors table (amCablePair) Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Ymathematical table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Yes. Its value is set to Yes.			Its value is set to Available by the wizard.	
Pairs/conductors of the model. Bundles Bundles Virtual bundles created by the wizard if it is necessary. Pairs/Conductors table (amCablePair) Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle bundles created by the wizard. Function Duty This field is only populated for the virtual bundles created by the wizard. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Yes. <td>Pairs/Conductors</td> <td>Pairs</td> <td>This field is only populated for the cables cre- ated by the wizard.</td>	Pairs/Conductors	Pairs	This field is only populated for the cables cre- ated by the wizard.	
Bundles Virtual bundles created by the wizard if it is necessary. Pairs/Conductors table (amCablePair) Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. This field is only populated for the virtual bundles created by the wizard. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard.			Pairs/conductors of the model.	
Pairs/Conductors table (amCablePair) Bundle Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # SSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard.	Bundles	Bundles	Virtual bundles created by the wizard if it is necessary.	
Bundle Bundle Bundle with which the pair/conductor is associated to create a cable link. Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Duty defined at the level of the topology. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard.	Pairs/Conductors ta	uble (amCablePair)		
Pins table (amDevicePin) Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) # # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Name Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard.	Bundle	Bundle	Bundle with which the pair/conductor is asso- ciated to create a cable link.	
Port Port with which the pin/terminal is associated to create a cable link. Cable bundle table (amCableBundle) This field is only populated for the virtual bundles created by the wizard. # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard.	Pins table (amDevic	cePin)		
Cable bundle (amCableBundle) # sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is only populated for the virtual bundles created by the wizard. Name Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard.	Port	Port	Port with which the pin/terminal is associated to create a cable link.	
# sSequenceNumber This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Its value is the number after the last bundle bundles created by the wizard. Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Duty defined at the level of the topology. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual	Cable bundle table ((amCableBundle)		
Its value is the number after the last bundle number existing for the device.NameNameNameThis field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device.FunctionDutyFunctionDutyStatusseCnxStatusStatusseCnxStatusVirtual bundleby the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Its value is set to Yes.	#	sSequenceNumber	This field is only populated for the virtual bundles created by the wizard.	
Name This field is only populated for the virtual bundles created by the wizard. Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Duty This field is only populated for the virtual bundles created by the wizard. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard.			Its value is the number after the last bundle number existing for the device.	
Its value is the number after the last bundle number existing for the device. Function Duty This field is only populated for the virtual bundles created by the wizard. Duty defined at the level of the topology. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Yes.	Name	Name	This field is only populated for the virtual bundles created by the wizard.	
Function Duty This field is only populated for the virtual bundles created by the wizard. Duty defined at the level of the topology. Duty defined at the level of the topology. Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available is only populated for the virtual bundles created by the wizard. Its value is set to Yes.			Its value is the number after the last bundle number existing for the device.	
Duty defined at the level of the topology. Status SeCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the virtual bundles created by the wizard. Its value is set to Yes.	Function	Duty	This field is only populated for the virtual bundles created by the wizard.	
Status seCnxStatus This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Available by the wizard. Its value is set to reated by the wizard. Its value is set to Yes.			Duty defined at the level of the topology.	
Its value is set to Available by the wizard. Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Yes.	Status	seCnxStatus	This field is only populated for the virtual bundles created by the wizard.	
Virtual bundle bVirtual This field is only populated for the virtual bundles created by the wizard. Its value is set to Yes .			Its value is set to Available by the wizard.	
Its value is set to Yes.	Virtual bundle	bVirtual	This field is only populated for the virtual bundles created by the wizard.	
			Its value is set to Yes .	

Field label	SQL name of the field	Explanations
Pairs/Conductors	Pair	Pairs/conductors selected by the wizard to
		create a cable link.
Cable links table (am	CableLink)	
Name	Name	Default value of the field.
Link type	seLinkType	Populated by the wizard according to whether the cable link concerns a cable device or a cable.
Parent link	Parent	
Label rule	LabelRule	The label rule selected at the level of the topo- logy.
Label	Label	The label is calculated according to the label rule.
Function	Duty	Duty defined at the level of the topology.
Device	Device	Device selected or created using the wizard.
Port	Port	Port selected or created by the wizard.
Cable	Cable	Cable selected or created by the wizard.
Bundle	Bundle	Bundle selected or created using the wizard.
Trace histories table (amTraceHistory)	
Name	Name	Copy the value defined for the same field used at the level of the cable link.
Туре	seLinkType	Copy the value defined for the same field used at the level of the cable link.
Parent history	Parent	Copy the value defined for the same field used at the level of the cable link.
Label	Label	Copy the value defined for the same field used at the level of the cable link.
Device	Device	Copy the value defined for the same field used at the level of the cable link.
Port	Port	Copy the value defined for the same field used at the level of the cable link.
Cable	Cable	Copy the value defined for the same field used at the level of the cable link.
Bundle	Bundle	Copy the value defined for the same field used at the level of the cable link.
Link	Link	Cable link created by the wizard.
Trace outputs table (a	mTraceOutput)	
Туре	seTraceType	Value defined using the wizard.
Function	Duty	Duty defined at the level of the topology.
Label	ModifiedLinkLabel	The label is calculated by the wizard and is not based on a label rule in any way.
Summary of the trace	TraceString	Calculated by the wizard.

Field label	SQL name of the field	Explanations
Trace histories	TraceHist	Histories created by the wizard.
Trace operations	TraceOps	Operations created by the wizard.
Trace operations tab	ole (amTraceOp)	
Title	Label	Value defined by the wizard according to the
		comments that you entered using the wizard.
Host trace history	HostTraceHist	Defined by the wizard.
User trace history	UserTraceHist	Defined by the wizard.

Viewing the result

The easiest way to view the result of this wizard is to display the detail of the project selected on the last page of the wizard:

- 1 Display the list of projects (**Portfolio**/**Projects**).
- 2 Select the project created by the wizard.
- 3 Select the **Cables** tab.

The **Cables** tab enables you to locate the cable that connects the two termination fields:

- 1 Select the cable to examine.
- 2 Click the magnifier to display an intermediary window.
- 3 In the intermediary window, click the magnifier to the right of the **Cable** field to view the detail of the device.
- 4 Right-click on any field (not link) in the **Assets** table (**amAsset**) to display the shortcut menu.
- 5 From the shortcut menu, select either the Actions/ Cable cross-connections or Actions/ Display cable traces menu entry to view and browse through the traces.

This particularly enables you to access the termination-field devices that were connected to the cable by a wizard.

4 Select the **Assets** tab.

The **Assets** tab enables you to locate the devices created by the wizard (not those that already existed):

- 1 Select the device to examine.
- 2 Click the magnifier to display an intermediary window.
- 3 In the intermediary window, click on the magnifier to the right of the **Asset** field to view the detail of the device.
- 4 Right-click on any field (not link) in the **Assets** table (**amAsset**) to display the shortcut menu.

5 From the shortcut menu, select either the **Actions/ Cable cross-connections** or **Actions/ Display cable traces** menu entry to view and browse through the traces.

This particularly enables you to access the termination-field devices that were connected to the cable by a wizard.

5 Select the **Traces** tab.

The Traces tab displays the list of trace outputs created by the wizard.

After having launched the wizard

Run the lateral cable and install the cable devices as you need them, being sure to respect the indications listed in the project and the work order, and update the follow-up information of the project and work order.

Use the Run lateral cables wizard for the practical case.

We are going to run a lateral cable between the wall outlet of Office 1 and the floor's termination field.

- 1 Display the list of actions (Tools/ Actions).
- 2 Select the Run riser cables wizard.
- 3 Enter the following information:

Label displayed by the wizard	Explanations
Select user locations page	
Locations	Cabled building/1st floor/Office 1
Select the topology group page	
Topology groups	Standard workstation
Are there any topologies in which you want to	Do not check this option.
look for ports with pin-based connectors?	
Map consecutive pins to virtual port for pin-	Do not check this option.
based devices (default is next available pin)?	
Select a project and a work order page	
Apply all changes to a project/work order?	Check this selection box.
Projects	Run lateral cables
Work orders	Select the work order proposed by the wizard.
Comments on the devices	Install the device.
Cable comments	Install new cable
Connection comments	Lateral run to connect devices

Label displayed by the wizard	Explanations
Connection termination field for the work order	CONNECT

Look at the result:

- 1 Display the list of projects (**Portfolio**/**Projects**).
- 2 Select the **Run lateral cables** project.
- 3 Select the **Cables** tab.
- 4 Select one of the cables just created.
- 5 Click the magnifier to display an intermediary window.
- 6 In the intermediary window, click the magnifier to the right of the **Cable** field to view the detail of the device.
- 7 Have a look at the different tabs at your own pace.
- 8 Select any field (not link) in the **Cables** table (**amCable**).
- 9 Right-click.
- 10 From the shortcut menu, select either the Actions/ Cable cross-connections or Actions/ Display cable traces menu entry to view and browse through the traces.

This particularly enables you to access the termination-field devices that were connected to the cable by a wizard.

Cross connect bundles wizard

Functions performed by the wizard

This wizard connects bundles of the same cable to one of the following components:

- Bundles of one or more cables.
- Ports of one or more cable devices.
- · Ports of termination-field devices.

If the selected bundles or ports are already connected, the wizard begins by breaking the existing cable links before creating new ones.

Prerequisites

You should have already created:

- The source cable to connect, with its bundles, its user location and its host location.
- The cable device to which the cable connects, with its ports and its location. Otherwise, the cable to which the cable connects with its bundles, its user location and its host location.
- The termination fields that serve the user or host location of the cable to connect.
- A project and a work order, if you want to store the trace of the connections carried out.

! Warning:

The wizard does not know how to create a virtual port.

Use the Cross connect bundles wizard.

Launching the wizard

To access this wizard, you must select a record or a field (not a link) from the **Cable bundles** table (**amCableBundle**):

To position yourself in the appropriate context:

- 1 Display the list of cables (Cable/ Cables).
- 2 Display the cable to connect.
- 3 Select the **Bundles** tab.
- 4 Select the bundles to cross connect.
- 5 Display the list of actions (**Tools/ Actions**).
- 6 Select the **Cross connect bundles** action.

Information used when using the wizard

💋 Note:

Certain labels in the following table are not displayed by the wizard unless you select the appropriate option.

Label displayed by the wizard	Explanations
Cross connect the bundles page	
Display available host bundles	• If you check this option, the wizard only displays the cable bundles whose host side is not used by any cable link.
	• If you check this option, the wizard displays all the cable's bundles.
	If you select a bundle whose host side is used by a cable link, the wizard will break the exist- ing cable link before creating a new one.
Display available user bundles	• If you check this option, the wizard only displays the cable bundles whose user side is not used by any cable link.
	• If you check this option, the wizard displays all the cable's bundles.
	If you select a bundle whose user side is used by a cable link, the wizard will break the exist- ing cable link before creating a new one.
Select the bundles to connect	Select the cable bundles to connect.
Select label rule for the link of the selected bundle(s)	You use this label rule to populate the Label field (Label) of the links created at the level of the cable bundles.
Select connection side	Indicate which side of the cable you want to connect.
Connect to	Indicate to which component you want to connect the selected bundles: • Ports: to the ports of one or more cable
	devices.
	• Bundles: to the bundles of one or more cables.
	• Termination fields: to the ports of the ter- mination-field devices that serve the loca- tion of the cable.
Select a device and ports page	
Select a device	Select the cable devices to which you want to connect the bundles of the source cable.

Table 6.5. Cross connect bundles wizard - description of fields to populate

Label displayed by the wizard	Explanations
Show available host ports	 If you check this option, the wizard only displays the ports of the device that are not used as hosts by any cable link. If you check this option, the wizard displays all the device's ports.
	If you select a port that is already used as a host, the wizard will break the existing cable link before creating a new one.
Show available user ports	• If you check this option, the wizard only displays the ports of the device that are not used as users by any cable link.
	• If you check this option, the wizard displays all the device's ports.
	If you select a port that is already used as a user, the wizard will break the existing cable link before creating a new one.
Select the target ports	You must select as many ports as you have se- lected bundles for the cable in the previous window.
Select label rule for the link of the selected port(s)	You use this label rule to populate the Label field (Label) of the links created at the level of the port device.
Select a cable and bundles page	
Cables	Select the cable to which you want to connect the bundles of the source cable.
Display available host bundles	• If you check this option, the wizard only displays the cable bundles whose host side is not used by any cable link.
	• If you check this option, the wizard displays all the cable's bundles.
	If you select a bundle whose host side is used by a cable link, the wizard will break the exist- ing cable link before creating a new one.

Label displayed by the wizard	Explanations
Display available user bundles	• If you check this option, the wizard only displays the cable bundles whose user side is not used by any cable link.
	• If you check this option, the wizard displays all the cable's bundles.
	If you select a bundle whose user side is used by a cable link, the wizard will break the exist- ing cable link before creating a new one.
Select label rule for destination bundle	You use this label rule to populate the Label field (Label) of the links created at the level of the target cable bundles.
Select a termination field and ports page	
Termination fields	Select the termination fields to which you want to connect the bundles of the source cable.
Show available host ports	 If you check this option, the wizard only displays the ports of the termination-field devices that are not used as hosts by any cable link. If you check this option, the wizard dis-
	plays all the ports.
	If you select a port that is already used as a host, the wizard will break the existing cable link before creating a new one.
Show available user ports	• If you check this option, the wizard only displays the ports of the termination-field devices that are not used as users by any cable link.
	• If you check this option, the wizard displays all the device's ports.
	If you select a port that is already used as a user, the wizard will break the existing cable link before creating a new one.
Select the target ports	You must select as many ports as you have se- lected bundles for the cable in the previous window.
Select label rule for the link of the selected port(s)	You use this label rule to populate the Label field (Label) of the links created at the level of the termination-field port devices.
Select a project and a work order page	-

Label displayed by the wizard	Explanations
Connection comments	Value for the Description field (Description)
	of the Traces concerned by the project table
	(amProjTraceOut), when the wizard creates
	a connection.
Disconnection comments	Value for the Description field (Description)
	of the Traces concerned by the project table
	(amProjTraceOut), when the wizard deletes
	a connection.
Comments on the termination field connected	Value for the Label field (Label) of the Trace
during work order	operations table (amTraceOp), when the
	wizard creates a connection.
Comments on the termination field disconnec-	Value for the Label field (Label) of the Trace
ted during work order	operations table (amTraceOp), when the
-	wizard deletes a connection.

Data created or modified by the wizard

To create a connection, the wizard creates the following items:

- Cable links (amCableLink)
- Trace histories (amTraceHistory)
- Trace outputs (**amTraceOutput**)
- Trace operations (**amTraceOp**)

To delete a connection, the wizard performs the following tasks:

- Deletes the cable links (amCableLink).
- Creates trace outputs (amTraceOutput).
- Creates trace operations (**amTraceOp**).

The wizard populates the following fields:

Table 6.6. Cross connect bundles wizard - created or modified data

Field label	SQL name of the field	Explanations
Cable links table	e (amCableLink)	
Name	Name	Default value of the field.
Link type	seLinkType	Populated by the wizard according to whether the cable link concerns a cable device or a cable.
Parent link	Parent	

Field label	SQL name of the field	Explanations
Label rule	LabelRule	The label rule selected using a wizard.
		If no label rule has been selected, this is the default value of the field.
Label	Label	The label is calculated according to the label rule.
Function	Duty	Duty of the port or bundle connected by the wizard.
Device	Device	Device selected using the wizard.
Port	Port	Port selected using the wizard.
Cable	Cable	Cable selected using the wizard.
Bundle	Bundle	Bundle selected using the wizard.
Trace histories table (amTraceHistory)	
Name	Name	Default value of the field.
Туре	seLinkType	Copy the value defined for the same field used at the level of the cable link.
Parent history	Parent	Copy the value defined for the same field used at the level of the cable link.
Label	Label	Copy the value defined for the same field used at the level of the cable link.
Device	Device	Copy the value defined for the same field used at the level of the cable link.
Port	Port	Copy the value defined for the same field used at the level of the cable link.
Cable	Cable	Copy the value defined for the same field used at the level of the cable link.
Bundle	Bundle	Copy the value defined for the same field used at the level of the cable link.
Link	Link	 If the wizard creates a connection: It is the cable link created by the wizard. If the wizard deletes a connection: It is empty.
Trace outputs table (a	mTraceOutput)	
Туре	seTraceType	• To connect: if it's a connection.
		• To disconnect : if it's a disconnection.
Function	Duty	Duty of the port or the bundle connected by the wizard.
Label	ModifiedLinkLabel	The label is calculated by the wizard and is not based on a label rule in any way.
Summary of the trace	TraceString	Calculated by the wizard.

Field label	SQL name of the field	Explanations
Trace history	TraceHist	• If the wizard creates a connection: They are the histories created by the wizard.
		• If the wizard deletes a connection: They are the histories that exist for the deleted cable links.
Trace operations	TraceOps	Operations created by the wizard.
Trace operations (an	nTraceOp)	
Title	Label	Value defined by the wizard according to the comments that you entered using the wizard.
Host trace history	HostTraceHist	Defined by the wizard.
User trace history	UserTraceHist	Defined by the wizard.

Viewing the result

The easiest way to view the result of this wizard is to display the detail of the project selected on the last page of the wizard.

- 1 Display the list of projects (**Portfolio**/**Projects**).
- 2 Select the project created by the wizard.
- 3 Select the **Traces** tab.

The **Traces** tab displays the list of trace outputs created by the wizard.

- 1 Select the trace output to examine.
- 2 Click the magnifier to display an intermediary window.
- 3 In the intermediary window, click on the magnifier to the right of the **Trace output** field.
- 4 Examine the trace output information.

You can also display the cross connections screen or the cable trace outputs screen:

- 1 Display the list of cables (Cable/ Cables).
- 2 Select the cable that you just connected from the list of cables.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the Cable cross-connections or Display cable traces action.

After having launched the wizard

Perform the physical cross connections, being sure to respect the indications listed in the project and the work order, and update the follow-up information of the project and work order.

Use the Cross connect bundles wizard for the practical case.

We are going to perform a modification at the level of the lateral cable that links the telephone outlet from Office 1 to the floor's termination field: We will connect the cable to another termination-field port.

Proceed in the following manner:

- 1 Display the list of locations (**Portfolio/ Locations**).
- 2 Select the **Cabled building/1st floor/Office 1** location.
- 3 Select the **Cable users** tab.
- 4 Select the cable that connects the telephone to the termination field (this bundle's duty is **Voice**).
- 5 Click the Magnifier button.
- 6 Select the **Bundles** tab.
- 7 Select the bundle from the list.
- 8 Display the list of actions (**Tools/ Actions**).
- 9 Select the **Cross connect bundles** action.
- 10 Enter the following information:

Label displayed by the wizard	Value
Cross connect the bundles page	
Select connection side	Host side
Display available host bundles	Unselect this option.
Select the bundles to connect	Select the bundle.
Select label rule for the link of the selected	Practical case - Link - Sequentially, by pairs
bundle(s)	
Connect to	Termination fields
Select a termination field and ports page	
Termination fields	Floor's termination field
Show available host ports	Check this selection box.
Select the target ports	Select a port whose function is Voice.
Select label rule for the link of the selected port(s)	Practical case - Port of a termination-field patch
	panel link
Select a project and a work order page	
Apply all changes to a project/work order?	Check this selection box.
Projects	Cross connect bundles
Work orders	Select the work order proposed by the wizard.
Connection comments	Connect cables
Disconnection comments	Disconnect cables

Label displayed by the wizard	Value
Comments on the termination field connected	CONNECT
during work order	
Comments on the termination field disconnected	DISCONNECT
during work order	

Look at the result:

- 1 Display the list of projects (**Portfolio/ Projects**).
- 2 Select the **Cross-connect bundles** project.
- 3 Select the **Traces** tab.
- 4 Select the trace.
- 5 Click the **Magnifier** button.
- 6 Click the **Magnifier** button to the right of the **Trace** field.
- 7 Examine the detail of the trace output.

7 Viewing the traces

There are several ways to view a trace:

- Connection point by connection point, using the **Trace** tabs of the following tables:
 - Cables (amCable)
 - Assets (amAsset)
 - Ports (amPort)
 - Cable bundles (amCableBundle)
- In a more general manner, using the windows displayed by the following shortcut menus:
 - Actions/ Cable cross-connections
 - Actions/ Device cross-connections
 - Actions/ Display device traces
 - Actions/ Display cable traces

This chapter explains how to view the traces in a general manner.

Cable cross-connections wizard

Definitions

 AssetCenter key terms (Cable and Circuit) [page 189]/ Cross connection [page 199]

Functions performed by the wizard

The **Cable cross-connections** wizard displays a window that enables you to perform the following tasks:

- View the host and user links of the cable.
- Navigate through the traces, which are made up of cable links (either in the host direction or the user direction).

This enables you, for example, to answer the following questions:

- Which links are for this cable?
- Which bundles are used by links?
- To which wall outlet port is such cable bundle connected?
- To which termination field port is such a cable bundle connected?

Prerequisites

No prerequisites.

Use the Cable cross-connections wizard.

Launching the wizard

To access this wizard, you need to select a record or a field (not a link) in the **Cables** table (**amCable**):

- 1 Display the list of cables (Cable/ Cables).
- 2 Select the cable in the list window, or select a field (not link) in the **Cables** table.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the **Cable cross-connections** wizard.
Information used when using the wizard

Figure 7.1. Cable cross-connections wizard - browser window

🎨 Cross connections					
Corel L 120 - Category 5 - 32 twisted pairs (001001) 🔥					
User 8 de trace	2	Z	8 Host side trace		
_ Label	AName (AName	A Label (Links.Parent link)		
Floor wiring closet Vert 1 Row: 1 Port: 1	1	1	/Cabled building/Floor 2/Main wiring closet/-Standard termination field		
Floor wiring closet Vert 1 Row: 1 Port: 2	2	2	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert1 Row: 1 Port: 3	3	3	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert1 Row: 1 Port: 4	4	4	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port 5	5	5	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port 6	6	6	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert:1 Row: 1 Port: 7	7	7	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert:1 Row: 1 Port: 8	8	8	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port: 9	9	9	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port: 10	10	10	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert:1 Row: 1 Port: 11 🛛 🔼	11	11 🊨	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert:1 Row: 1 Port: 12	12	12	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port: 13	13	13	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert1 Row: 1 Port: 14	14	14	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert1 Row: 1 Port: 15	15	15	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert1 Row: 1 Port: 16	16	16	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port: 17	17	17	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert 1 Row: 1 Port: 18	18	18	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
Floor wiring closet Vert:1 Row: 1 Port: 19	19	19	/Cabled building/Floor 2/Main wiring closet/-Standard termination field V		
A 20	32/32		↓ ⁽²⁾ 32/32		
	567.56	1			
🔶 User 🍯			Sector Host		
			Close		

▲ Cable or device whose ▲ and ▲ tables display the cable links.

 \clubsuit User cable links and devices that connect to the cable or the device \clubsuit .

 ${}^{\textcircled{\circ}}$ Host cable links and devices that connect to the cable or the device ${}^{\textcircled{\circ}}$.

 ${}^{igstyle }$ Click the magnifier to display the detail of the cable or the device ${}^{igstyle }$.

Click this arrow to display the browser window for the user cable or device that corresponds to the selected link ².

[●] Click this arrow to display the browser window for the host cable or device that corresponds to the selected link [●].

Cable bundle numbers 4 (if 4 is a cable) or device ports 4 (if 4 is a device).

 \clubsuit Label of the user link that connects to the bundle or the port \clubsuit .

 \clubsuit Label of the host link that connects to the bundle or the port \clubsuit .

Data created or modified by the wizard

This wizard does not create, delete or modify any data.

Device cross-connections wizard

Definitions

Cross connection [page 199]

Functions performed by the wizard

The **Device cross-connections** wizard displays a window to help you perform the following tasks:

• View the host and user links of the device to which the device links belong (in the host or user direction)

This enables you, for example, to answer the following questions:

- Which links are for this device?
- Which ports are used by links?
- To which cable bundle is such a device port connected?

Prerequisites

No prerequisites.

Use the Device cross-connections wizard.

Launching the wizard

To access this wizard, you need to select a record or a field (not a link) in the **Assets** table (**amAsset**):

- 1 Display the list of cable devices (**Cable/ Cable devices**).
- 2 Select the cable device in the list window, or select a field (not link) in the **Assets** table.
- 3 Display the list of actions (**Tools/ Actions**).
- 4 Select the **Device cross-connections** wizard.

Information used when using the wizard

Cross connections			
ieneric Patch pannel 32 ports 256 pins (001	053) 💧		📣 🕹
Jser <mark>8</mark> de trace	Δ Δ	2	Host side trace
Label	△Port#(Par + △Port#	 Label (Links.Parent link) 	+
		L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs 📃
	2	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
	3	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
	4	L 120 - Category 5 - 32 twisted pairs (L 120 - Categ	gory 5 - 32 twisted pairs
	5	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
	6	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
	7	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	8	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	9	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
2	10 3	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
–	11 -	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	12	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate	gory 5 - 32 twisted pairs
	13	L 120 - Category 5 - 32 twisted pairs (L 120 - Categ	gory 5 - 32 twisted pairs
	14	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	15	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	16	L 120 - Category 5 - 32 twisted pairs (L 120 - Categ	gory 5 - 32 twisted pairs
	17	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
		L 120 - Category 5 - 32 twisted pairs (L 120 - Category	gory 5 - 32 twisted pairs
	+ 19	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate)	gory 5 - 32 twisted pairs
1	20	L 120 - Category 5 - 32 twisted pairs (L 120 - Cate)	jory 5 - 32 twisted pairs
_ ⊗_	0/0	L 120 - Catedony 5 - 32 twisted bairs (L 120 - Cater	201V 5 - 1/2 Twisted pairs A 😪 32 / 32
🔶 User 🤞			<mark>é</mark> → <u>H</u> ost
			<u>C</u> lose

Figure 7.2. Device cross-connections wizard - browser window

[▲] Cable or device whose [▲] and [▲] tables display the cable links.

 \clubsuit User cable links and devices that connect to the cable or the device \clubsuit .

 $\stackrel{\bullet}{\rightarrow}$ Host cable links and devices that connect to the cable or the device $\stackrel{\bullet}{\leftarrow}$.

 \clubsuit Click this magnifier to display the detail of the cable or the device \clubsuit .

Click this arrow to display the browser window for the user cable or device that corresponds to the selected link **a**.

Click this arrow to display the browser window for the host cable or device that corresponds to the selected link ³.

Cable bundle numbers 4 (if 4 is a cable) or device ports 4 (if 4 is a device).

 \clubsuit Label of the user link that connects to the bundle or the port \clubsuit .

 \clubsuit Label of the host link that connects to the bundle or the port \clubsuit .

Data created or modified by the wizard

This wizard does not create, delete or modify any data.

Display device traces wizard

Definitions

▶ Trace [page 190]

Functions performed by the wizard

The **Display device traces** wizard displays a window to help you perform the following tasks:

- View the host and user traces of the device.
- Print the list of traces.

Prerequisites

No prerequisites.

Use the Display device traces wizard.

Launching the wizard

To access this wizard, you need to select a record or a field (not a link) in the **Assets** table (**amAsset**):

- 1 Display the list of cable devices (Cable/ Cable devices).
- 2 Select the cable device in the list window, or select a field (not link) in the **Assets** table.
- 3 Display the list of actions (**Tools**/ **Actions**).
- 4 Select the **Display device traces** wizard.

Information used when using the wizard

Figure 7.3. Display device traces wizard - browser window

Detail of device trace 'Generic Pate	h pannel 32 ports 256 pins (001053)'			
Assets			+	Delete
lewlett Packard Procurve 10/100 Base T -	- 8 ports (001052)			-
Generic Patch pannel 32 ports 256 pins (00	1053)			
eneric Patch pannel 32 ports 256 pins (00	1054)			
neric Patch panel 24 ports pre-loaded (001055)			
Generic Patch panel 24 ports pre-loaded (001056)		▼	
eneric Patch panel 24 ports pre-loaded (001057)		.+.	
5.3	4	A △ 😪 <u>26 / 26</u>		
Source	Host side cable trace	Host side device trace		Print
Floor wiring closet Vert 1 Row: 1 Port: 1	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar.		Denview
Floor wiring closet Vert1 Row: 1 Port 2	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar	6	Preview
Floor wiring closet Vert1 Row: 1 Port 3	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar		Configure
Floor wiring closet Vert1 Row: 1 Port 4	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar.		Page cotur
oor wiring closet Vert1 Row: 1 Port 5	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar.		1 age setup
Floor wiring closet Vert1 Row: 1 Port 6	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar		
Floor wiring closet Vert1 Row: 1 Port 7	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar.		
Floor wiring closet Vert1 Row: 1 Port 8	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar		
Floor wiring closet Vert1 Row: 1 Port 9	L 120 - Category 5 - 32 twisted pairs (L 120 - Catego	/Cabled building/Floor 2/Main wiring closet/-Standar	•	
•				Close

Select the device to examine.

This table contains one row per trace that is directly attached to the device
as well as one line per free port (in other words, one that is not used by any link).

 $\stackrel{\bullet}{\rightarrow}$ The **Source** column displays the labels of the links that are directly attached to the device $\stackrel{\bullet}{\rightarrow}$, as well as a label for the free ports.

- The blue labels designate the ports used by at least one link.
- The red labels designate the ports that are not used by any links.

The **xxx Host side trace** columns are located to the right of the **Source** column. They display the labels of the traces in the host direction.

⁵ The xxx User side trace columns are located to the left of the Source column. They display the labels of the traces in the user direction.

Data created or modified by the wizard

This wizard does not create, delete or modify any data.

Display cable traces wizard

Definitions

▶ Trace [page 190]

Functions performed by the wizard

The **Display cable traces** wizard displays a window to help you perform the following tasks:

- View the host and user traces of the cable.
- Print the list of traces.

Prerequisites

No prerequisites.

Use the Display cable traces wizard.

Launching the wizard

To access this wizard, you need to select a record or a field (not a link) in the **Cables** table (**amCable**):

- 1 Display the list of cables (**Cable/ Cables**).
- 2 Select the cable in the list window, or select a field (not link) in the **Cables** table.
- 3 Display the list of actions (**Tools**/ Actions).
- 4 Select the **Display cable traces** wizard.

Information used when using the wizard

Figure 7.4. Display cable traces wizard - browser window

Detail of cable trace 'Corel L 120 - C	ntegory 5 - 32 twisted pairs (001001)'		
Cables			<u>D</u> elete
Corel L 120 - Category 5 - 32 twisted pairs (001	001)		
		*	
5	3	△ 😪/1/1	
User side device trace	Source	Host side device trace	Print
Floor wiring closet Vert:1 Row: 1 Port: 1	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stand	Dura inte
Floor wiring closet Vert:1 Row: 1 Port: 2	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	6 Preview
Floor wiring closet Vert:1 Row: 1 Port: 3	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	Configure
Floor wiring closet Vert:1 Row: 1 Port: 4	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	Page cotup
Floor wiring closet Vert:1 Row: 1 Port: 5	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	Page setup.
Floor wiring closet Vert:1 Row: 1 Port: 6	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	
Floor wiring closet Vert:1 Row: 1 Port: 7	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	
Floor wiring closet Vert:1 Row: 1 Port: 8	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc	
Floor wiring closet Vert:1 Row: 1 Port: 9	L 120 - Category 5 - 32 twisted pairs (L 120 - Category	/Cabled building/Floor 2/Main wiring closet/-Stanc 🔫	
•			Close

Select the cable to examine.

This table contains one row per trace that is directly attached to the cable
(in other words, one that is not used by any links).

The **Source** column displays the labels of the links that are directly attached to the cable 4, as well as a label for the free bundles.

- The blue labels designate the labels of the bundles used by at least one link.
- The red labels designate the labels of the bunles that are not used by any links.

⁴ The **xxx Host side trace** columns are located to the right of the **Source** column. They display the labels of the traces in the host direction.

⁵ The **xxx User side trace** columns are located to the left of the **Source** column. They display the labels of the traces in the user direction.

Data created or modified by the wizard

This wizard does not create, delete or modify any data.



AssetCenter key terms (Cable and Circuit)

Pin/Terminal

Component of a cable device port that creates an electronic connection (pin) or optical connection (terminal) with a connector pin/terminal or a cable wire.

The cable-device pins/terminals are associated with a port. The ports, themselves, can be associated with a bundle of cable pairs/conductors to create a cable link.

At the level of the connection types, the pins/terminals are associated with a color code entry.

Opposites

Pin is one of the two connection modes whose opposite is Port [page 201].

Table in the AssetCenter database that describes these objects

Pins (amDevicePin)

Cable

A cable is composed of one of the following sets of components:

- A set of wire pairs, if it conducts electrically.
- A set of conductors, if it conducts optically.

The pairs or conductors are grouped into bundles in order to create a connection with a cable device.

The cables connect the cable devices together.

Opposites

```
Cable device [page 193]
```

Table in the AssetCenter database that describes these objects

Cables (amCable)

Figure 8.1. Cable with its pairs and its wires - photo



Trace

Succession of links (in the logical sense) between cables and cable devices.

Opposites

This is opposite to Cabling path [page 210], which describes the cabling in a physical sense.

Color code

We use color codes in order find and distinguish between:

- A wire pair
- And a connector pin

Each wire and each pin are associated with a color code entry which identifies the wire.

When you create pairs using the **Create pairs** wizard, the wizard automatically assigns a color code entry to each created pair according to the pair's **Sequential number** field.





If we take the **RJ-45** connector, each pin is associated with a wire having a given color and a given duty:

Pin num- ber	Color of the associated pair.	Colors of the tip wire	Colors of the ring wire	Function
1	orange	white/blue	orange	Data
				transmis-
				sion +
2	orange	white/orange	orange	Data
				transmis-
				sion -
3	green	white/green	green	Data re-
				ception +
4	blue	white/blue	blue	Voice
				transmis-
				sion +
5	blue	white/blue	blue	Voice
				transmis-
				sion -
6	green	white/green	green	Data re-
				ception -
7	brown	white/brown	brown	Voice re-
				ception +
8	brown	white/brown	brown	Voice re-
				ception -

Table 8.1. Color codes - description for an RJ-45 connector

Table in the AssetCenter database that describes these objects

Color codes (amColorCode)

Column

Vertical axis of a termination field.

Opposites

▶ Line [page 200]

Trace output

Description of a trace.

Table in the AssetCenter database that describes these objects

Trace outputs (amTraceOutput)

Termination-field configuration

Defines the typical organization of a termination field type. Specifically:

- The duty assigned to each row or column of the termination field.
- The role assigned to each row or column of the termination field (and as a consequence, the roles of the cable devices that are there).

The termination-field configuration is used by the cabling wizards to automate the creation of termination fields (with their devices).

Examples

A termination field with 2 columns and 6 row will have 12 duties (voice or data, for example) and 6 roles (riser or lateral, for example).

Table in the AssetCenter database that describes these objects

Termination field configurations (amTermFldConfig)

Cable device

The cable devices corresponding to the network components that are not cables. The cable devices that connect to the cables and cable devices using:

- Pins, if it conducts electrically.
- Terminals, if it conducts optically.

The pins or connectors are grouped into ports in order to create a connection with the cable bundle or the port of another cable device.

Examples

- Controller card
- Wall outlets
- Patch panels
- Switches
- Hubs

Synonyms

Cable equipment

Tables in the AssetCenter database that describe these objects

Assets (amAsset)

Slot

The slot of a cable device in which you can introduce an extension card or module. These are, themselves, cable devices and create cable links with other cables or cable devices.





Examples

A HP Procurve 10/100 Base T - 8 ports module which inserts itself in a ProCurve Switch 4000 M - 10 slots switch.

Synonyms

Expansion connector

Tables in the AssetCenter database that describe these objects

- Slots (amSlot)
- Model slots (amModelSlot)

Color code entry

One of the colors of a color code.

Each color code entry can be associated with:

- Cable pairs/conductors
- Cable-device port pins

Tables in the AssetCenter database that describe these objects

Color code entries (amColorDet)

Topology step

One of the cable links to create in order to lay out a topology. The steps of a topology are ordered.

Tables in the AssetCenter database that describe these objects

Topology steps (amTopologyDet)

Label

An identifier, in the cable network, of the:

- Cable devices
- Bundles
- Cables
- Pins/ terminals
- Pairs/conductors

- Ports
 - Links

They are created in the database, then physically attached to these components in order to locate and identify them.

Labels are created using label rules.

The label must best represent the item that it identifies. The label rule can create, for example, labels using the following information:

- Location of the host and the user.
- Host and user ports (identifier of the asset and the port).
- Type of cable or device (4 pairs, patch panel, etc.).

The corresponding label is presented in the following form:

Figure 8.4. Cable label - example



Bundle

Sub-set of pairs of a cable to which we assign a particular duty. The bundles are used for the creation of cable links between a cable and a cable device: We link a bundle of the cable to a port of the device. We make sure that the duty of the bundle is the same as the one of the port.

Tables in the AssetCenter database that describe these objects

Cable bundles (amCableBundle)

Duty

Type of data transported or processed by a:

- Cable bundle
- · Cable device port
- Cable link

Duties are used by the cabling wizards that create links. They enable the wizards to reconcile a ports with bundles performing the same duty.

A duty is also assigned to a:

- Termination-field configuration slot: in order that this duty be propagated to the level of the ports of the device that is created there.
- A topology: in order that this duty be searched for or populated at the level of the bundles and ports to use in laying out a topology.
- A trace: in order to represent the duty fulfilled by the links, ports and bundles that compose the trace.

Examples

- Data
- Voice
- Video

Tables in the AssetCenter database that describe these objects

Cable duties (amCableDuty)

Topology group

A topology group brings together several topologies. The groups of topologies are used by the cabling wizards to automate the creation of cables, cable devices and cable links.

A topology group can, for example, regroup a topology for the creation of each of the following items:

- Fax link
- Telephone link
- LAN link

A topology group describes a standard configuration of the cable network. You can define different topology groups according to their location, for example.

Tables in the AssetCenter database that describe these objects

Topology groups (amTopologyGroup)

Host

This concept is used to define the direction of a trace. This determines which cable links will be hosts (parents) of other cable links when the wizards create the links between cables and/or cable devices.

In general the host direction is the one that goes to the main termination field.

Opposites

▶ User [page 206]

Cross connection

An action that consists of linking together network items (cables and cable devices).

Cable link

A cable link represents in AssetCenter the connection point at the level of a cable device (port) or cable (bundle). The succession of the links enables you to constitute a trace.

Tables in the AssetCenter database that describe these objects

Cable links (amCableLink)

Line

Horizontal axis of a termination field

Opposites

Column [page 192]

Ring

A jack outlet is composed of a **tip** and a **ring**, which are opposites. The jack connector uses a 2-pair cable. One of this cable's wires goes to the tip; the other to the ring. Thus, the **tip** and the **ring** help distinguish the two wires in a pair, no matter how many pairs there are in a cable.

Opposites

Tip [page 200]

Pair/conductor

Data transmission media. Can be optic fiber or a pair of electric wires.

Tables in the AssetCenter database that describe these objects

Pairs/Conductors (amCablePair)

Tip

A jack outlet is composed of a **tip** and a **ring**, which are opposites. The jack connector uses a 2-pair cable. One of this cable's wires goes to the tip; the other to the ring. Thus, the **tip** and the **ring** help distinguish the two wires in a pair, no matter how many pairs there are in a cable.

Opposites

Ring [page 200]

Port

Slot used to transfer data into and out of a cable device.

In the Cable and Circuit module, the ports serve as the connection point with another port or a cable bundle when the cable links are created.

Tables in the AssetCenter database that describe these objects

- Ports (amPort)
- Model ports (amModelPort)

Opposites

Port is one of the two connection modes, opposite of the **Pin** connection mode.

Label rule

Formula for the composition of labels destined for the following items:

- Cable devices
- Bundles
- Cables
- Pins/ terminals
- Pairs/conductors
- Ports
- Links

These labels, except for those for the cable links, enable you to physically locate and identify components in a precise manner.

The label for the cable link helps you rapidly view what the link represents.

The calculation formulas are composed using Basic script.

Contrary to the default values of the fields, the label rules are never applied automatically. You must use a wizard for this.

Synonyms

None

Tables in the AssetCenter database that describe these objects

Label rules (amLabelRule)

Termination field

Designates a cable distribution entity that enables you to link the cables coming from users to the cables going to hosts.

A termination field can be composed of:

- Patch panels
- Hubs
- Punchdown blocks
- Switches
- Etc.

Synonyms

Patch panel

Tables in the AssetCenter database that describe these objects

Termination fields (amTermField)

Role

The role corresponds to the part of the network that a cable serves.

The roles are associated to the following items:

- Cables
- · Termination-field device models
- Termination-field devices
- Cables in a topology step

The role enables certain cabling wizards to create adequate connections between cable devices and cables.

To do this, the wizards match the roles of the:

- Topology steps
- Cables
- Termination-field configurations

• Termination field devices

Example of how this works

If, using a wizard that runs cables, you create cables whose roles are **Riser**, AssetCenter will automatically connect these cables to a device included in a termination field column whose role is also **Riser**.

Examples of roles

- Lateral (termination field to user equipment).
- Riser (termination field to another termination field).

Tables in the AssetCenter database that describe these objects

Itemized lists (amItemizedList)

Sequence

Ordered number to identify items from numerous tables of the AssetCenter application.

Terminal

See Pin/ Terminal.

Topology

A topology groups together the necessary data to automate the creation of a link:

- Links to create.
- Cables and cable devices to look for or create.

Examples

A topology describing the link that links a user to the telephone network (wall outlet -> cable -> patch panel).

Tables in the AssetCenter database that describe these objects

Topologies (amTopology)

Cable type

A cable type qualifies the models and the topology steps. This enables the cabling wizards to find or create the right type of cable from the topology step.

Examples

Twisted pairs

Tables in the AssetCenter database that describe these objects

Itemized lists (amItemizedList)

Connection type

A connection type represents a mode of connection between components of the cable network.

Example: RJ-45, RJ-11, Block of 4 pairs, etc.

It is a physical description of the pins of a port or the terminal fields of a connector.

Examples:

- The ports of the workstations, PABX or servers.
- Wall-mounted telephone sockets (RJ-45, RJ-9 sockets)
- The terminals of the termination-field punchdown blocks (CAD, RAC IBM).

The connection type enables the cabling wizards to:

- Find the ports of a cable device that correspond to the connection type defined in a topology step.
- Or to create virtual ports of the given type if necessary.

Tables in the AssetCenter database that describe these objects

Connection types (amCabCnxType)

Figure 8.5. RJ-45 connector - photo



Cable device type

The device type qualifies the models and the topology steps. This enables the cabling wizards to find or create the right type of cable device from a topology step.

Examples

- Switch module
- Patch panel
- Wall outlet
- Switch

Example of use

Let's suppose that you created a connection between a cable and a cable device whose connection type is **XXX** (Connection mode = **Pins**, number of pins/connectors = **8**). Once the 8 pins of the terminal of the cable device are associated to a wire, AssetCenter automatically creates a virtual port.

Tables in the AssetCenter database that describe these objects

Itemized lists (amItemizedList)

Pair/Conductor type

A pair or conductor type is defined by its name and the number of physical conductors that compose it.

The pair/conductor type enables the cabling wizards to find the pairs/conductors of a cable that correspond to the type defined in a topology step. The pairs/conductors thus selected are grouped together in the form of a virtual bundle, and these virtual bundles are associated to ports (in a cable link).

Examples

Copper, 2 conductors

Tables in the AssetCenter database that describe these objects

Pair/conductor types (amCablePairType)

Slot type

The slot type defines which extension models or module it is possible to insert in a given slot of a cable device.

This link is used when you select an asset for the slot of a cable device: Only the assets whose model is compatible with the slot type are proposed.

Tables in the AssetCenter database that describe these objects

Slot types (amSlotType)

User

This concept is used to define the direction of a trace. This determines which cable links will be users (sub-links) of other cable links when the wizards create the links between cables and/or cable devices.

In general the user direction is the one that goes to the user's wall outlet.

Opposites

▶ Host [page 199]

Key terms of the profession (Cable and Circuit)

Adapter

Set of male and female connectors that enable a cable device to use a peripheral for which it doesn't have the necessary circuits and connections: models, CD-ROM drives. The adapters go into the expansion slots.

Figure 8.6. Adapter - photo







Rack

Storage unit that contains the cable distribution devices.

Figure 8.7. Rack - photo



Punchdown block

A box enabling you to connect the wires of a cable to a port in order to facilitate the connection with the cable.

Figure 8.8. Punchdown block - photos



Chassis

Metal frame upon which cable devices are mounted.

Cabling path

Physical path of the cable, which is opposite of the trace, which provides the logical path.

Opposites

► Trace [page 190] (logic)

Converter

Device that:

- Changes the electronic signals or the IT data from one form into another. Example: An **ADC** converter that translates analog signals to digital signals.
- Connects equipment with incompatible interfaces.
- Converts the signal coming from one cable type in order to transmit it to another cable type.

Vertical distribution

Distribution of the cables between different termination fields. The cables linking the termination fields are generally composed of numerous pairs, and are called risers.



Figure 8.9. Vertical distribution of a cable network - representation

Opposites

▶ Lateral distribution [page 212]

Lateral distribution

Distribution of the cables between the users and the termination fields.



Figure 8.10. Lateral distribution of a cable network - representation

Synonyms

Horizontal distribution

Opposites

▶ Vertical distribution [page 211]

Hub

The hub is a box where cables come in from computers, servers, printers and other peripheral devices. It establishes communication between different network users.

There are passive hubs that are nothing more than simple **multiple outlet adapter**, which do not modify the signals going through them.

Then there are active hubs that regenerate the signals, thus eliminating the possible errors that can occur due to the distance or the electrical interference.

It is possible to connect several hubs together, thus expanding the existing network.

Hubs do not intervene in the transmission of messages. When a computer sends information, the hub transmits it to all the other computers, and only the computer for whom the message was intended will process it. If the message's receiver sends a response, the hub transmits this message to everyone as well: Again, only the computer for whom the message was intended will receive it. The authorized debit on the network is divided between the number of computers or peripheral devices that "communicate" at the same time.

Figure 8.11. Hub - photo



Synonyms

- Concentrator
- Multiplexer

Jumper/ Patch cord

Short cord used to establish a permanent, yet modifiable, connection between devices and termination fields.

Figure 8.12. Patch cord - photo



Length

Dimension of a cable.

Patch panel

Device of a termination field situated in the proximity of hubs, switches, etc. It comes in between them and the cables distributed throughout the location. The cables connect to the back of the patch panels. To each cable corresponds a connector on the panel. The other sides of the cables are linked to a wall outlet in an office. We use jumpers to link the panel's connectors (front side) to the ports of the termination field's active item.

Figure 8.13. Patch panel - photo



Synonyms

Interconnect

Wall outlet

Device that enables a male connector of a cable (of a computer, peripheral device, or telephone) to connect to the network.

Main termination field

Processed in AssetCenter as a termination field.

Repeater

Device used to reduce distortion by amplifying or regenerating a signal so that it can be transmitted farther with its original form and intensity. On the network, it connects two networks - or two segments of the network - at the level of the physical layer of the OSI model and regenerates the signal.

Figure 8.14. Repeater - photo



Synonyms

Regenerator

Riser

Vertical distribution cable (between floors or buildings).

Router

Even more **intelligent** than switches, the router is generally used to connect different networks together, for example, a company's internal network to the Internet network. These are veritable computers capable of filtering information according to criteria established by the user. They know how to direct information to a destination via the available paths and by choosing the most appropriate itinerary. They also know how to make two different types of networks, using different types of communication protocols, coexist.
Figure 8.15. Router - photo



Wallfield

Dealt with in AssetCenter as a termination field.

Switch

Like a hub, it also concentrates the cables coming from all the computers and peripheral devices of the network. Unlike a hub, the switch has a memory where it stores the addresses of the machines that it connects. When a computer sends a messages to another computer, the switch knows who is "communicating" and for whom the information is intended. It sends the data to the destination without having to involve the rest of the network. The target machine receives this data at the same rate as the transmitter.

Figure 8.16. Switch - photo





Synonyms

PABX

Run (a cable)

Action that consists of laying a cable.

Synonyms

Lay

Run

Section of cable.



Menus and tabs (Cable and Circuit)

The Cable and Circuit module uses numerous menus. The following menus are directly linked to the Cable and Circuit module:

Table 9.1. Menus and tabs (Cable and Circuit) - list

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
File me	nu				

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
Activ- ating the mod- ules	Does not apply.	Not available	Cable and Cir- cuit	Enables you to activate or deac- tivate the Cable and Circuit module, if your license author- izes it.	Not available
				This is the menu to use if you can't see the following menus in your application:	
Cable r	nenu				
Cables	Cables (amC- able)	All	All		Cables - manu- al creation [page 129]
Cable	Assets (amAs-	Pins/Terminals	Not available	This menu dis-	Cable devices -
devices	set)	Ports		plays records	manual cre-
		Slots		from the same	ation [page 118]
		Trace		table as the As-	
		Connections		Sets and Batches menu	
		Connections		but filters the	
				records: Only	
				assets linked to	
				a model with	
				nature Cable	
				device are dis-	
Linke	Links (amC-	A 11	A 11	played.	Connections -
LIIIKS	ableLink)	7.11	7.11		manual cre-
	,				ation [page 132]
Торо-	Topology	All	All		Topology
logy	groups (amTo-				groups
groups	pologyGroup)				[page 82]
Торо-	Topologies	All	All		Topologies
logies	(amTopology)				[page 76]

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
Ter- mina- tion fields	Termination fields (amTer- mField)	All	All		Termination fields [page 97]
Con- figura- tion of the ter- mina- tion fields	Termination field configura- tions (amTerm- FldConfig)	All	All		Termination- field configura- tions [page 86]
Label rules	Label rules (amLabelRule)	All	All		Label rules [page 37]
Color codes	Color codes (amColor- Code)	All	All		Color codes [page 33]
Cable duties	Cable duties (amCable- Duty)	All	All		Cable duties [page 48]
Cable con- nec- tion types	Connection types (amCab- CnxType)	All	All		Connection types [page 45]
Pait/con- ductor types	Pair/Conduct- or types (amC- ablePairType)	All	All		Types of pairs and conductors [page 43]
Slot types	Cable/ Slot types (amSlot- Type)	All	All		Slot types [page 68]
Portfol	io menu				
Assets	Assets (amAs-	Pins/Terminals	Not available		Cable devices -
and batches	set)	Ports Slots			manual cre- ation [page 118]
		Trace Connections			

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
Assign- ments	Portfolio items (amPortfolio)	Not available	Not available		Cable devices - manual cre- ation [page 118]
Natures	Natures (am- Nature)	Not available	Cable device (bDevice) Cre- ate (seBasis) Management constraints (seMgtCon - straint)		Natures for cables and cable devices [page 55]
Mod- els	Models (am- Model))	Devices Slots Cables	Can be connec- ted (blsCnxCli- ent)		Cable device models with slots. [page 72] and Cable models [page 59]
Pro- jects	Projects (amProject)	Cables Traces	Not available		Projects and work orders as- sociated with cabling [page 52]
Loca- tions	Locations (am- Location)	User cables Host cables Termination fields	Not available		Locations [page 50]
Brands	Product brands (amBrand)	Not available	Not available		Brands of cable and cable device models [page 58]
Portfol	io menu				
Work orders	Work orders (am- WorkOrder)	Not available	Not available		Projects and work orders as- sociated with cabling [page 52]
Tools n	nenu				

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
Ac- tions/ Edit	Actions (amAction)	Not available	Not available		Actions and wizards (Cable and Circuit) [page 235]
Ac- tions/ <name of ac- tion></name 	Does not apply.	Not available	Not available	Proposes the actions that are either non- contextual or whose contexts are active. Enables you to trigger the selec- ted action.	Actions and wizards (Cable and Circuit) [page 235]
Cus- tom- ize tool- bar	Does not apply.	Not available	Not available	Enables you to add or remove cable icons from the tool- bar.	Toolbar icons (Cable and Cir- cuit) [page 224]
Admin	istration menu				
Item- ized lists	Itemized lists (amItemized- List)	Not available	Not available		Itemized lists (Cable and Cir- cuit) [page 232]
Coun- ters	Counters (am - Counter)	Not available	Not available		Counters (Cable and Cir- cuit) [page 234]
Calcu- lated fields	Calculated fields (amCal- cField)	Not available	Not available		Calculated fields (Cable and Circuit) [page 233]

Sub- menu	Table that the menu accesses (label and SQL name)	Tabs dedicated to cable manage- ment	Important fields or links (outside of the dedicated tabs)	Comments	Section of the guide to consult
List of	Does not apply.	Not available	Not available	Enables you to	
screens				access tables	
				that are not ac-	
				cessible by the	
				present menus.	
				This task is re-	
				served for the	
				administrator	
				since these	
				tables were not	
				really designed	
				to be modified.	

Toolbar icons (Cable and Circuit)

Certain toolbar icons are used exclusively for the Cable and Circuit module.

To obtain this list and add these icons to the toolbar:

- 1 Select the Tools/ Customize toolbar menu.
- 2 Select the **Tools** tab.
- 3 Select **Cable** from the list of **Categories**.

To learn more about customizing the toolbar, refer to the **Introduction** guide, chapter **Customizing a client workstation**, section **Customizing the toolbar**.

Interface options (Cable and Circuit)

There are no options dedicated to the Cable and Circuit module.

Tables (Cable and Circuit)

The Cable and Circuit module uses numerous tables. The following tables are directly linked to the Cable and Circuit module:

Table 9.2. Tables (Cable and Circuit) - list

Table label	SQL name of the table	Menu item used to access the table	Section of the guide to consult
Actions	amAction	Tools/ Actions/ Edit	Actions and wizards (Cable and Circuit) [page 235]
		Tools/ Actions/ <name ac-<br="" of="">tion></name>	
Portfolio items	amPortfolio	Portfolio/ Portfo- lio items	Cable devices - manual creation [page 118]
Assets	amAsset	Portfolio/ Assets and Batches	Cable devices - manual creation [page 118]
Pins	amDevicePin	Administra- tion/List of screens	Cable devices - manual creation [page 118]
		Cable/ Cable devices, Pins/Terminals tab	
		Portfolio/ Assets and batches, Pins/Terminals tab	
Cables	amCable	Cable/ Cables	Cables - manual creation [page 129]
Cables con- cerned by the project	amProjCable	Administra- tion/List of screens	Projects and work orders associated with cabling [page 52]
		Portfolio/ Pro- jects, Cables tab	
Traces con- cerned by the project	amProjTraceOut	Administra- tion/List of screens	Projects and work orders associated with cabling [page 52]
		Portfolio/ Pro- jects, Traces tab	
Calculated fields	amCalcField	Administration/ Calculated fields	Calculated fields (Cable and Circuit) [page 233]
Color codes	amColorCode	Cable/ Color codes	Color codes [page 33]

Table label	SQL name of the table	Menu item used to access the table	Section of the guide to consult
Trace outputs	amTraceOutput	Administra-	Connections - manual creation
		tion/List of	[page 132]
		screens	
Counters	amCounter	Administration/	Counters (Cable and Circuit)
		Counters	[page 234]
Termination	amTermFldCon-	Cable/ Termina-	Termination-field configurations
field configura-	fig	tion-field config-	[page 86]
tions		urations	
Termination	amTermFld-	Administra-	Termination fields [page 97]
field devices	Device	tion/List of	
		screens	
		Cable/ Termina-	
		tion fields,	
		Devices tab	
Model slots	amModelSlot	Administra-	Cable device models with slots.
		tion/List of	[page 72]
		screens	
		Portfolio/ Mod-	
		els, Slots tab	
Slots	amSlot	Administra-	Cable devices - manual creation
		tion/List of	[page 118]
		screens	
		Portfolio/Assets	
		and Batches.	
		Slots tab	
		Cable/ Cable	
		devices Slote tab	
Color code	amColorDet	Administra-	Color codes [page 33]
entries	amcolorDet	tion/List of	Color codes [page 55]
cittites		screens	
		Cable/ Color	
Te 11'e	Te 111	codes	
Itemized lists	amItemizedList	Administration/	Itemized lists (Cable and Circuit)
T 1			[page 252]
l opology steps	amTopologyDet	Administra-	l'opologies [page /6]
		uon/List of	
		Cable/ Topolo-	
		gies	

Table label	SQL name of the table	Menu item used to access the table	Section of the guide to consult
Cable bundles	amCableBundle	Administra- tion/List of screens	Cables - manual creation [page 129]
		Cable/ Cables, Bundles tab	
Cable duties	amCableDuty	Cable/ Cable du- ties	Cable duties [page 48]
Termination field configura- tion duties/ser-	amTermFldCfg- Duty	Administra- tion/List of screens	Termination-field configurations [page 86]
vices		Cable/ Termina- tion-field config- urations, Duties tab	
Topology groups	amTopology- Group	Cable/ Topology groups	Topology groups [page 82]
Trace histories	amTraceHistory	Administra- tion/List of screens	Connections - manual creation [page 132]
Work orders	amWorkOrder	Portfolio/ Work orders	Projects and work orders associated with cabling [page 52]
Links	amCableLink	Cable/ Cable links	Connections - manual creation [page 132]
Locations	amLocation	Portfolio/ Mod- els	Locations [page 50]
Connection pin mappings	amCnxPinMap	Administra- tion/List of screens Cable/ Cable connection types	Connection types [page 45]
Models	amModel	Portfolio/ Mod- els	Cable device models with slots. [page 72] and Cable models [page 59]
Nature	amNature	Portfolio/ Natures	Natures for cables and cable devices [page 55]
Trace operations	amTraceOp	Administra- tion/List of screens	Connections - manual creation [page 132]

Table label	SQL name of the table	Menu item used to access the table	Section of the guide to consult
Pairs/Conduct- ors	amCablePair	Administra- tion/List of screens	Cables - manual creation [page 129]
		Cable/ Cables, Pairs/Conduct- ors tab	
Cable model pairs/conductors	amModelPair	Administra- tion/List of screens	Create pairs wizard [page 61]
		Portfolio/ Mod- els, Cable tab	
Ports	amPort	Administra- tion/List of screens	Cable devices - manual creation [page 118]
		Portfolio/ Assets and batches, Ports tab	
		Cable/ Cable devices, Ports tab	
Model ports	amModelPort	Administra- tion/List of screens	Cable device models without slots. [page 63]
		Portfolio/ Mod- els, Ports tab	
Projects	amProject	Portfolio/ Pro- jects	Projects and work orders associated with cabling [page 52]
Label rules	amLabelRule	Cable/ Label rules	Label rules [page 37]
Locations - Ter- mination fields relation	amRelTermLoc		Termination fields [page 97]
Models - Slot types relation	amSlotTypeMod- el		Slot types [page 68]
Termination fields	amTermField	Cable/ Termina- tion fields	Termination fields [page 97]

Table label	SQL name of the table	Menu item used to access the table	Section of the guide to consult
Termination	amTermFldCf-	Administra-	Termination-field configurations
field configura- tion roles	gRole	tion/List of screens	[page 86]
		Cable/ Termina-	
		tion-field config-	
		urations, Roles	
		and devices tab	
Topologies	amTopology	Cable/ Topolo-	Topologies [page 76]
		gies	
Topologies in a	amTopoGroup-	Administra-	Topology groups [page 82]
group	Det	tion/List of	
		screens	
		Cable/ Topology	
		groups	
Connection	amCabCnxType	Cable/ Cable	Connection types [page 45]
types		connection types	
Pair/Conductor	amCablePair-	Cable/ Types of	Types of pairs and conductors
types	Туре	pairs/conductors	[page 43]
Slot types	amSlotType	Cable/ Slot types	Slot types [page 68]

Interdependence of tables used in cable management (Cable and Circuit)

The Cable and Circuit module uses numerous tables in the AssetCenter database. There are multitudes of links between these tables. It is thus convenient to optimize the order in which you populate these tables.

The order that we propose below is not mandatory: AssetCenter enables you to create missing records in linked tables whenever it is necessary.

Example: We recommend that you create the duties, label rules, roles and models before creating the termination-field configurations. However, you can add a value on the fly to the itemized list that populates the **Role** field. Then you can create on the fly a model, a duty and a label rule. Keep in mind, though, that you will have to populate numerous, interwoven, tables, which can be quite complicated

Here is a table that optimizes the order of how you should create your records. It indicates which dependant tables you need to populate. The practical case that is developed throughout the course of this guide respects these recommendations.

We have voluntarily excluded the tables that are indirectly linked to cable management:

- Brands
- Assets and Batches
- Models
- Locations
- Projects
- Work orders

We have also excluded the secondary tables, even if they are directly linked to the Cable and Circuit module. These tables are automatically populated when you create records in the main tables.

Table 9.3. Interdependence of tables (Cable and Circuit) - table

Ta	ble label	SQL name of the table	Menu to access the table	Tables to populate first	Comments
1	Itemized lists	amItemizedList	Administration/ Itemized lists		Itemized list must first be populated before being closed by the administrat- or as users will no longer be able to create values on the fly. List of the item- ized lists in the Cable and Cir-
					cuit module: ► Itemized lists (Cable and Cir- cuit) [page 232].
1	Color codes	amColorCode	Cable/ Color codes		
1	Label rules	amLabelRule	Cable/ Label rules		

Table label		SQL name of the table	Menu to access the table	Tables to populate first	Comments
1	Types of pairs and conductors	amCablePair- Type	Cable/ Types of pairs/conductors		
1	Connection types	amCabCnxType	Cable/ Cable connection types	amColorCode	
1	Cable duties	amCableDuty	Cable/ Cable du- ties		
1	Locations	amLocation	Portfolio/ Loca- tions		
1	Projects	amProject	Portfolio/ Pro- jects		
1	Work orders	amWorkOrder	Portfolio/ Work orders		
1	Nature	amNature	Portfolio/ Natures		
1	Models	amModel	Portfolio/ Mod- els	amNature amLa- belRule amItem- izedList amColor- Code amCab- CnxType amC- ableDuty amC- ablePairType	Cable device models without slots.
1	Slot types	amSlotType	Cable/ Slot types	amModel	
1	Models	amModel	Portfolio/ Mod- els	amNature amLa- belRule amItem- izedList amColor- Code amCab- CnxType amC- ableDuty amC- ablePairType amSlotType	Cable device models with slots.
1	Topologies	amTopology	Cable/ Topolo- gies	amCableDuty amLabelRule amItemizedList amCabCnxType amModel amC- ablePairType	
1	Topology groups	amTopology- Group	Cable/ Topology groups	amTopology	

Table label		SQL name of the table	Menu to access the table	Tables to populate first	Comments
1	Termination	amTermFldCon-	Cable/ Termina-	amCableDuty	
	field configur-	fig	tion-field config-	amLabelRule	
	ations.		urations	amItemizedList	
				amModel	
1	Termination	amTermField	Cable/ Termina-	amTermFldCon-	
	fields		tion fields	fig amLocation	
				amItemizedList	
				amModel	
1	Assets	amAsset	Portfolio/ Assets	amNature amLa-	
			and Batches	belRule amItem-	
				izedList amMod-	
				el amCab-	
				CnxType amC-	
				ableDuty	
				amSlotType	
				amTermField	
				amLocation	
1	Cables	amCable	Cable/ Cables	amNature amLa-	
				belRule amItem-	
				izedList amMod-	
				el amColorCode	
				amCabCnxType	
				amCableDuty	
				amCablePair-	
				Type amSlot-	
				Type amLoca-	
				tion	

Itemized lists (Cable and Circuit)

Certain fields can be populated by selecting their values from a list. These itemized lists are such lists.

You can access the **Itemized lists** table (**amItemizedList**) using the **Administration/ Itemized lists** menu item.

The Cable and Circuit module uses the following itemized lists:

Itemized list identi-	Field populated using an itemized list (la-	Table in which field is found (label and SQL	
fier	bel and SQL name)	name)	
amDeviceType	Device type (DeviceType)	Models (amModel))	
	Device type (DeviceType)	Topology steps (amTopologyDet)	
amCableType	Cable type (CableType)	Models (amModel))	
	Cable type (CableType)	Topology steps (amTopologyDet)	
amCableRole	Role (CableRole)	Cables (amCable)	
	Role (CableRole)	Termination field configuration	
		roles and devices (amTermFldCf-	
		gRole)	
	Role (CableRole)	Termination field devices (amTerm-	
		FldDevice)	
	Role (CableRole)	Topology steps (amTopologyDet)	
amColor	Color code entries (amColorDet)	Color (Color)	
amTipColor	Color code entries (amColorDet)	Tip color (TipColor)	
amRingColor	Color code entries (amColorDet)	Ring color (RingColor)	

Table 9.4. Itemized lists (Cable and Circuit) - list

To learn more about itemized lists, refer to the **Advances use** guide, chapter **Itemized lists**.

Calculated fields (Cable and Circuit)

The Cable and Circuit module uses numerous calculated fields.

These calculated fields are used in the default values of certain fields.

You can access the **Calculated fields** table (**amCalcField**) using the **Administration/ Calculated fields** menu item.

The following calculated fields are directly linked to the Cable and Circuit module:

Label of the cal- culated field	SQL name of the calculated field	Label and SQL name of the field that uses the calculated field	Utilization
TermField- Name	csf_sysCableTermFieldName	Termination fields (amTerm- Field)	This calculated field is used by certain AssetCenter APIs to automatically generate a ter- mination field name (gf_Cre- ateTerminationField , for ex- ample).
			Certain cabling wizards call on this API (the Create a ter- mination field wizard, for ex- ample).

Table 9.5. Calculated fields (Cable and Circuit) -list

You can customize these calculated fields.

To learn more about using calculated fields, refer to the **Advanced use** guide, chapter **Calculated fields**.

To learn more about composing scripts, refer to the **Advanced use** guide, chapter **Scripts**.

To learn more about APIs, refer to the Programmer's reference guide.

Counters (Cable and Circuit)

The Cable and Circuit module uses numerous counters.

These counters are used in the default values of certain fields.

You can access the **Counters** table (**amCounter**) using the **Administration**/ **Counters** menu item.

The following counters are directly linked to the Cable and Circuit module:

Table 9.6. Counters (Cable and Circuit) - list

SQL name of the counter	Label and SQL name of the table that uses the counter	Label and SQL name of the field that uses the counter
amCableLink_BarCode	Links (amCableLink)	Name (Name)
amTraceHistory_BarCode	Trace histories (amTraceHis-	Name (Name)
	tory)	
amCable_CableTag	Cables (amCable)	Code (Code)

To learn more about using counters, refer to the **Administration** guide, chapter **Customizing the database**, section**Counters in field default values**.

Actions and wizards (Cable and Circuit)

The Cable and Circuit module uses numerous actions to automate certain tasks. Most of these actions are performed by wizards.

You can access the **Actions** table (**amAction**) using the **Tools/ Actions/ Edit** menu item.

You can easily filter the actions linked to the Cable and Circuit module by using a simple filter on the following fields:

- Domain (**Domain**)
- Nature (**Nature**)

The following actions are directly linked to Cable and Circuit module:

Name of ac- tion	SQL name of the action	Action type	Context of the action (SQL name of the table)	Section of the guide to con- sult
Create	sysCableCreatePair	Wizard	amModel	Create pairs wizard
pairs				[page 61]
Create	sysCableCreatePort	Wizard	amModel	Create ports wizard
ports				[page 65]
Create slots	sysCableCreateSlot	Wizard	amModel	Create slots wizard
				[page 74]

Name of ac- tion	SQL name of the action	Action type	Context of the action (SQL name of the table)	Section of the guide to con- sult
Create a termina- tion field	sysCableCreateTermField	Wizard	amLoca- tion	Create a termination field wizard [page 99]
Disconnect bundles	sysCableDisCnxBundle	Wizard	amCable- Bundle	
Disconnect ports	sysCableDisCnxPort	Wizard	amPort	
Duplicate wiring closet	sysCableDupCloset	Wizard	amLoca- tion	Duplicate wiring closet wizard [page 110]
Expand ter- mination field	sysCableExpTermField	Wizard	amTerm- Field	Expand termination field wizard [page 104]
Hub cross- connect (generic)	sysCableHubCnx	Wizard		
Cross con- nect ports (internal)	sysCableIntern- alXCnxPort	Wizard	amPort	
Display cable trace	sysCableOutCabTr	Wizard	amCable	
Display device traces	sysCableOutDevTr	Wizard	amAsset	
Refresh as- set label	sysCableRefreshAssetLbl	Script	amAsset	
Refresh bundle la- bel	sysCableRefreshBundleL- bl	Script	amCable- Bundle	
Refresh cable label	sysCableRefreshCableLbl	Script	amCable	
Refresh the link label	sysCableRefreshC- ableLinkLbl	Script	amC- ableLink	
Refresh pair/con- ductor la- bel	sysCableRefreshPairLbl	Script	amCable- Pair	

Name of ac- tion	SQL name of the action	Action type	Context of the action (SQL name of the table)	Section of the guide to con- sult
Refresh	sysCableRefreshPinLbl	Script	amDevi-	
pin/termin-			cePin	
al label				
Refresh	sysCableRefreshPortLbl	Script	amPort	
port label				
Refresh	sysCableRefreshProjectTr	Script	amPro-	
project			jTraceOut	
trace				
Refresh	sysCableRefreshTrHist	Script	amTrace-	
trace his-			History	
tory				
Relocate	sysCableRelocateCable	Wizard		
cables				
Remove	sysCableRemoveCab	Wizard	amCable	
cables				
Remove	sysCableRemoveCabLo-	Wizard		
cables by	cRole			
location				
and roles				
Remove lat-	sysCableRemoveLateral-	Wizard		
eral cables	Cable			
Run lateral	sysCableRunLateral	Wizard		Run lateral cables wizard
cables				[page 159]
Run riser	sysCableRunRiser	Wizard		Run riser cables wizard
cables				[page 145]
Hub cross-	sysCableSpecificHubX-	Wizard		
connect	Cnx			
(specific)				
Swap a	sysCableSwapAsset	Wizard	amAsset	
device in a				
termina-				
tion field				
Cross-con-	sysCableWallCnx	Wizard		
nect wall-				
field				
Cross con-	sysCableXCnxBundle	Wizard	amCable-	Cross connect bundles
nect			Bundle	wizard [page 168]
bundles				

Name of ac- tion	SQL name of the action	Action type	Context of the action (SQL name of the table)	Section of the guide to con- sult
Cross con- nect ports	sysCableXCnxPort	Wizard	amPort	
Transfer project as- sets	sysCableXferAsset	Wizard	amAstProj- Desc	
Transfer project cables	sysCableXferCable	Wizard	amProjC- able	
Relocate project con- nections	sysCableXferTrace	Wizard	amPro- jTraceOut	
Cable cross-con- nections	sysCableCableXCnx	Script	amCable	Cable cross-connections wizard [page 180]
Device cross-con- nections	sysCableDeviceXCnx	Script	amAsset	Device cross-connections wizard [page 182]
Display cable traces	sysCableCableTrace	Script	amCable	Display cable traces wiz- ard [page 186]
Display device traces	sysCableDeviceTrace	Script	amAsset	Display device traces wiz- ard [page 184]

To learn more about using actions, refer to the **Advanced use** guide, chapter **Actions**.

To learn more about composing scripts, refer to the **Advanced use** guide, chapter **Scripts**.

To learn more about APIs, refer to the Programmer's reference guide.

You can create new actions or customize existing ones.

Modules of the AssetCenter Server (Cable and Circuit)

There are no modules dedicated to the Cable and Circuit module.

System data and Line-of-business data (Cable and Circuit)

AssetCenter is provided with a set of data that can be imported to a demonstration database or your own database.

ጆ Note:

Certain of these sets of data are already imported in the installation database installed with AssetCenter.

These data sets are a part of one of the following groups:

- System data: data that is indispensable in order for AssetCenter to function.
- **Line-of-business data**: basic data to insert into your production database if you find it useful.

This data is divided into functional areas.

• Sample data: data that is useful to familiarize yourself with AssetCenter.

System data specific to the Cable and Circuit module

For everything concerning the Cable and Circuit module, the **System data** contains data for the following tables:

Actions (amAction)

Example: cabling wizards

• Calculated fields (amCalcField)

The **System data** relating to the Cable and Circuit module is already included in the demonstration database installed with AssetCenter.

The **System data** specific to the Cable and Circuit module will be incorporated into your production database if you select this option when creating the database using AssetCenter Database Administrator (> Preliminary steps [page 25]).

Line-of-business data for the Cable and Circuit module

Here are a few examples of **Line-of-business data** specific to the Cable and Circuit module:

- Label rules (amLabelRule)
- Color codes (amColorCode)
- Topologies (amTopology)

- Termination field configurations (amTermFldConfig)
- Models (amModel)

The Line-of-business data specific to the Cable and Circuit module are included systematically in the demonstration database installed with AssetCenter. They will be incorporated into your production database if you select this option when creating the database using AssetCenter Database Administrator (▶ Preliminary steps [page 25]).

Reports and forms (Cable and Circuit)

AssetCenter is provided with reports and forms. Certain are specific to the Cable and Circuit module.

In order for these reports and forms to be available in your database, you must import them from the AssetCenter Database Administrator.

Importing and identifying reports specific to the Cable and Circuit module

To find out how to import reports, refer to the Advanced use guide, chapter Crystal Reports, section Installing and using the reporting tool, sub-section Installing preconfigured Crystal Reports in your database.

To identify the reports specific to the Cable module, refer to the **Advanced use** guide, chapter **Crystal Reports**, section **Identifying Crystal reports specific** to a given module.

Importing and identifying forms specific to the Cable and Circuit module

To find out how to import forms, refer to the **Advanced use** guide, chapter **Forms**, section **Installing preconfigured forms into your working database**. To identify the forms specific to the Cable module, refer to the **Advanced use** guide, chapter **Forms**, section **Identifying forms specific to a given module**.

Automatic actions (Cable and Circuit)

To see the list of actions that are automatically executed in the background by AssetCenter, refer to the **Database structure** document.

References: Other sources of information (Cable and Circuit) [page 241].

APIs (Cable and Circuit)

Certain ; AssetCenter APIs are used in the Cable and Circuit module.

These APIs perform the following functions:

- Verification of the integrity rules of the database. Example: They verify that the pins of a port belong to the same cable device as the port itself.
- Triggering of certain agents on the database.

Example: They duplicate the pairs of a cable model when a cable is created.

To obtain a list and description of the APIs used in cable management, refer to the documentation: **Programmer's reference**.

Views (Cable and Circuit)

There are no views dedicated to the Cable and Circuit module.

To learn more about using views, refer to the **Introduction** guide, chapter **Using views**.

Other sources of information (Cable and Circuit)

This manual includes information directly linked to the Cable and Circuit module.

To obtain associated information not covered in this guide, we recommend that you read the following documents:

Table 9.8. Other documentation (Cable and Circuit) -list

The document	Covers information relat- ing to the	Format	Location in the AssetCenter installation folder
Installation	Installation of As-	Printed	\doc\pdf\Installation*.pdf
	setCenter	Online	\doc\chm\install*.chm
Core tables	Location manage-	Printed	\doc\pdf\CommonTables*.pdf
	ment	Online	\doc\chm\common*.chm

The document	Covers information relat- ing to the	Format	Location in the AssetCenter installation folder
Introduction	General interface	Printed	\doc\pdf\UserInterface*.pdf
	of the application	Online	\doc\chm\userint*.chm
Portfolio	Management of	Printed	\doc\pdf\Portfolio*.pdf
	natures, models, assets, projects and work orders in general	Online	\doc\chm\portfol*.chm
Administration	Customization of	Printed	\doc\pdf\Administration*.pdf
	fields	Online	\doc\chm\admin*.chm
Advanced use	 Itemized-list 	Printed	\doc\pdf\AdvancedUse*.pdf
	management	Online	\doc\chm\advanced*.chm
	Use of wizards		
	Creation of scripts		
	• Use of calculated fields		
Contextual help on fields and links	• Use of database fields and links	Online	This help is accessible using one of the following methods after
nerus una mino	nerds und mitto		having selected the field or link:
			• Right-click and select Help on
			this field from the shortcut menu.
			• Press Shift+F1 .
			• Select the Help/ Help on this
			field menu.
Programmer's refer-	• Use of APIs	Printed	\doc\pdf\ProgrammersRefer-
ence		Onling	ence".pdf
Database structure	• List of the data	Text file	doc\infos\database txt
Database structure	base's tables.	I CAT IIIC	Vinfos/tables tyt
	fields, links and	Online	
	indexes	Unline	\doc\cnm\dbstruct".cnm
	• Automatic agents triggered by Asset- Center.		
General online help	The functioning	Online	This help is accessible using one
	of the entire ap-		of the following methods, after
	plication		having selected the field or link:
			• Press F1 on the keyboard.
			• Select the Help/ Index menu.

Indexes

Index

A

Actions, 235 Activate modules (menu), 26 Adapters, 207 Administering AssetCenter, 242 Advanced use of AssetCenter, 242 amCableRole (itemized list), 29 amCableType (itemized list), 29 amColor (itemized list), 35, 30 amDeviceType (énumération), 28 amRingColor (itemized list), 35, 30 amTipColor (itemized list), 35, 30 API, 241 AssetCenter Database Administrator Line-of-business data - import Existing database, 27 New database, 26 System data - import, 26 AssetCenter - Installation, 27 AssetCenter manuals, 241 AssetCenter Server modules, 238 AssetCenter Server - modules, 238 Automatic actions, 240

B

Brands, 58

C

Cable

(See Also Cable duties) Cable and Circuit module Implementation, 25-96 Preliminary steps, 25 Required knowledge, 11 Cable bundles, 132 Definition, 197 Virtual bundles, 119 Cable cross-connections (wizard), 180 Cable device models (See Also Brands) Create ports (wizard), 65 Creating ports using a wizard, 72 Creating slot using a wizard, 74 Devices without slots, 63 Devices with slots, 72 Cable devices (See Also Brands) (See Also Natures) Cable device models without slots, 72 Cable-device types, 205 Connection modes, 19 Creation methods, 117 Definition, 193 Devices without slots - models, 63 Manual creation, 118 Single or double-sided devices, 120 Traces, 182 Types, 27

Cable-device types, 205 Cable duties, 198, 48 Cable models (See Also Brands) Cables, 59 Create pairs (wizard), 61 Cable roles, 29 Definition, 202 Cables (See Also Brands) (See Also Models) (See Also Natures) Cable types, 204, 28 Connection modes, 19 Creation methods, 117 Cross connection, 180 Definition, 190 Manual creation, 129 Riser cables, 145 Risers, 216 Roles, 29 Run a cable, 218 Cable types, 204, 28 Cabling Cabling paths, 210 Cabling paths, 210 Calculated fields, 233 Chassis, 210 Color code entries, 196 Color codes, 33 Color code entries, 196 Colors, 30 Definition, 190 Colors, 30 Color code entries, 196 Color codes, 190, 33 Columns, 192 Concentrators, 214 Conductors, 200 (See Also Pair/Conductor types) config (folder), 26 Connections (See Also Connection types)

Bundles - cross-connections, 168 Connection modes, 19 Connection types, 204 Creation, 145-177 Creation methods, 117 Lateral cables, 159 Manual creation, 138, 132 Riser cables, 145 Connection types, 204, 45 Converters, 211 Counters, 234 Create database (option), 27 Create pairs (wizard), 61 Create ports (wizard), 72, 65 Create slots (wizard), 74 Create system data (option), 27, 26 Create termination field (wizard), 99 Cross connect bundles (wizard), 168 Cross connections, 199

D

Database Line-of-business data - import Existing database, 27 New database, 26 Preparation, 26 Structure, 242 System data - import, 26 Definitions Adapter, 207 Bundle, 197 Cable, 190 Cable type, 204 Riser, 216 Run a cable, 218 Cable device, 193 Cable device type, 205 Cable device type, 205 Cable type, 204 Cabling path, 210 Cabling - path, 210 Chassis, 210 Color

Color code, 190 Color code entry, 196 Color code, 190 Color code entry, 196 Color code entry, 196 Column, 192 Concentrator, 214 Conductor, 200 Pair/Conductor type, 206 Connection type, 204 Connection - type, 204 Converter, 211 Cross connection, 199 Distribution Horizontal, 212 Lateral, 212 Patch panel, 215 Vertical, 211 Duty, 198 Expansion connector, 194 Horizontal distribution, 212 Host, 199 Hub, 214 Jumper, 214 Label, 196 Label rule, 201 Label rule, 201 Lateral distribution, 212 Line, 200 Link, 199 Trace, 190 Trace output, 192 Multiplexer, 214 Pair, 200 Pair/Conductor type, 206 Pair/Conductor type, 206 Patch cord, 214 Patch panel, 215, 202 Pin, 189 Port, 201 Punchdown block, 210, 210 Rack, 209 Wiring closet, 209

Regenerator, 216 Repeater, 216 Ring, 200 Riser, 216 Role, 202 Router, 216 Run, 218 Run a cable, 218 Sequence, 203 Slot, 194 Slot type, 206 Slot type, 206 Switch, 217 Terminal, 189 Termination field, 202 Main termination field, 216 Termination-field configuration, 193 Wallfield, 217 Termination-field configuration, 193 Tip, 200 Topology, 203 Topology group, 198 Topology step, 196 Topology group, 198 Topology step, 196 Trace, 190 Trace output, 192 Trace output, 192 User, 206 Vertical - distribution, 211 Wallfield, 217 Wall outlet, 215 Wiring Patch panel, 215 Définitions Switch, 217 Demonstration database, 239 Device cross-connections (wizard), 182 Display cable traces (wizard), 186 Display device traces (wizard), 184 Distribution Horizontal, 212 Lateral, 212

Patch panels, 215 Vertical, 211 Double sided, 120 Duplicate wiring closet (wizard), 110

E

Expand termination field (wizard), 104 Expansion connectors, 194

F

Flow specification, 92 Forms, 240

G

gbbase.xml, 26 Glossary, 189-218 AssetCenter terms, 189-206 Professional terms, 207-218

Η

Help on fields and links, 242 Horizontal distribution, 212 Hosts, 199 Hubs, 214

Import extra data (option), 27, 26 Installing AssetCenter, 241 Interface options, 224 Interface - options, 224 Itemized lists, 232

J

Jumpers, 214

L

Label rules, 37 Definition, 201 Labels (See Also Label rules) Definition, 196 Examples, 39 Lateral distribution, 212 License agreement, 26 Line-of-business data, 239, 27, 26 Lines, 200 Links, 132 Definition, 199 Trace outputs, 192 Traces, 190 Locations, 50

М

Menus, 219 Multiplexers, 214

Ν

Natures, 55

0

On-line help, 242 Open database description file - create new database (option), 27 , 26

P

Pair/Conductor types, 206, 43 Pairs, 200 (See Also Pair/Conductor types) Patch cords, 214, 19 Patch panel, 202 Patch panels, 215 Pins Connection modes, 19 Definition, 189 Ports, 132 Connection modes, 19 Definition, 201 Practical case Brands, 59 Bundles - cross-connections, 176 Cable device models without slots, 67 Cable device models with slots, 75 Cable devices, 127 Cable-device types, 28 Cable duties, 50

Cable models, 62 Cable roles, 30 Cables, 131 Cable types, 29 Color codes, 35 Colors, 31 Connections, 140 Connection types, 46 Label rules, 40 Lateral cables, 167 Links, 141 Locations, 51 Natures, 57 Precautions, 21 Presentation, 21 Projects, 54 Riser cables, 157 Slot types, 71 Termination field configurations, 93 Termination fields, 103 Termination fields - expansion, 109 Topologies, 79 Topology groups, 85 Trace histories, 142 Trace operations, 142 Trace outputs, 141 Types of pairs and conductors, 45 Wiring closet - duplication, 114 Work orders, 54 Programming, 242 Projects, 52 Punchdown blocks, 210, 210

R

Rack, 209 References, 219-242 Regenerators, 216 Repeaters, 216 Reports, 240 Rings, 200 Riser, 216 Routers, 216 Run a cable, 218 Run lateral cables (wizard), 159 Run riser cables (wizard), 145 Runs, 218

S

Sequences, 203 Single sided, 120 Slots (See Also Models) (See Also Slot types) Creating slot using a wizard, 74 Definition, 194 Slot types, 206, 68 Starting position, 91 Switches, 217, 217 System data, 239, 26

T

Tables, 224 Core tables, 241 Dependency relations, 229 Tabs, 219 Terminals, 189 Termination field configurations, 86 Definition, 193 Flow specification, 92 Parameters, 87 Starting position, 91 Termination fields, 97 (See Also Termination field configurations) Creation using a wizard, 99 Definition, 202 Expansion, 104 Main termination field, 216 Manual creation, 98 Wallfields, 217 Wiring closet - duplication, 110 Tips, 200 Toolbar, 224 Toolbar icons, 224 Topologies, 76 (See Also Topology groups) Definition, 203

Examples, 78 Topology steps, 196 Topology groups, 198, 82 Topology steps, 196 Trace outputs, 192, 192 Traces Definition, 190 Printing Cables, 186 Devices, 184 Viewing, 179 Cables, 186, 180 Devices, 184, 182

U

Users, 206

V

Vertical - distribution, 211 Views, 241 Vrtual ports Cable devices - manual creation, 119 Wizards - limitations, 169

W

Wallfields, 217 Wall outlets, 215 Wiring Patch panels, 215 Wiring closet, 209 Wizards Identification, 235 Prerequisites, 145, 87, 52, 39 Work orders, 52

