

HP Network Node Manager i Software

For the Windows® and Linux operating systems

Software Version: 10.00

Online Help: Help for Administrators

Document Release Date: May 2014

Software Release Date: May 2014



Legal Notices

Warranty

The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

The information contained herein is subject to change without notice.

Restricted Rights Legend

Confidential computer software. Valid license from HP required for possession, use or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Oracle Technology — Notice of Restricted Rights

Programs delivered subject to the DOD FAR Supplement are 'commercial computer software' and use, duplication, and disclosure of the programs, including documentation, shall be subject to the licensing restrictions set forth in the applicable Oracle license agreement. Otherwise, programs delivered subject to the Federal Acquisition Regulations are 'restricted computer software' and use, duplication, and disclosure of the programs, including documentation, shall be subject to the restrictions in FAR 52.227-19, Commercial Computer Software-Restricted Rights (June 1987). Oracle America, Inc., 500 Oracle Parkway, Redwood City, CA 94065.

For the full Oracle license text, see the license-agreements directory on the NNMi product DVD.

Copyright Notice

© Copyright 2008–2014 Hewlett-Packard Development Company, L.P.

Trademark Notices

Adobe® is a trademark of Adobe Systems Incorporated.

HP-UX Release 10.20 and later and HP-UX Release 11.00 and later (in both 32 and 64-bit configurations) on all HP 9000 computers are Open Group UNIX 95 branded products.

Intel® is a trademark of Intel Corporation in the U.S. and other countries.

Microsoft® and Windows® are U.S. registered trademarks of Microsoft Corporation.

Oracle and Java are registered trademarks of Oracle and/or its affiliates.

Red Hat® Enterprise Linux Certified is a registered trademark of Red Hat, Inc. in the United States and other countries.

UNIX® is a registered trademark of The Open Group.

Acknowledgements

This product includes software developed by the Apache Software Foundation.
(<http://www.apache.org>)

This product includes software developed by the Indiana University Extreme! Lab.
(<http://www.extreme.indiana.edu>)

Documentation Updates

The title page of this document contains the following identifying information:

- Software Version number, which indicates the software version.
- Document Release Date, which changes each time the document is updated.
- Software Release Date, which indicates the release date of this version of the software.

To check for recent updates or to verify that you are using the most recent edition of a document, go to: <http://h20230.www2.hp.com/selfsolve/manuals>

This site requires that you register for an HP Passport and sign in. To register for an HP Passport ID, go to: <http://h20229.www2.hp.com/passport-registration.html>

Or click the **New users - please register** link on the HP Passport login page.

You will also receive updated or new editions if you subscribe to the appropriate product support service. Contact your HP sales representative for details.

Support

Visit the HP Software Support Online web site at: <http://www.hp.com/go/hpsoftwaresupport>

This web site provides contact information and details about the products, services, and support that HP Software offers.

HP Software online support provides customer self-solve capabilities. It provides a fast and efficient way to access interactive technical support tools needed to manage your business. As a valued support customer, you can benefit by using the support web site to:

- Search for knowledge documents of interest
- Submit and track support cases and enhancement requests
- Download software patches
- Manage support contracts

- Look up HP support contacts
- Review information about available services
- Enter into discussions with other software customers
- Research and register for software training

Most of the support areas require that you register as an HP Passport user and sign in. Many also require a support contract. To register for an HP Passport ID, go to:

<http://h20229.www2.hp.com/passport-registration.html>

To find more information about access levels, go to:

http://h20230.www2.hp.com/new_access_levels.jsp

HP Software Solutions Now accesses the HPSW Solution and Integration Portal Web site. This site enables you to explore HP Product Solutions to meet your business needs, includes a full list of Integrations between HP Products, as well as a listing of ITIL Processes. The URL for this Web site is <http://h20230.www2.hp.com/sc/solutions/index.jsp>

About this PDF Version of Online Help

This document is a PDF version of the online help. This PDF file is provided so you can easily print multiple topics from the help information or read the online help in PDF format. Because this content was originally created to be viewed as online help in a web browser, some topics may not be formatted properly. Some interactive topics may not be present in this PDF version. Those topics can be successfully printed from within the online help.

Contents

Contents	4
Chapter 1: Introduction for NNMi Administrators	26
Administrator Tools in the Console	30
Quick Start Configuration Wizard	30
Configuration Workspaces	31
Enable or Disable Configurations	36
Lookup Fields	37
Use the Quick Find Window	38
Use Autocomplete	39
Create a Configuration Object Instance Using the Form Toolbar	39
Delete One or More Objects	40
Actions Provided by NNMi	41
About Environment Variables	86
NNMi Processes and Services	86
About Each NNMi Process	87
Verify that NNMi Processes Are Running	87
Stop or Start an NNMi Process	87
About Each NNMi Service	88
Verify that NNMi Services are Running	91
Stop or Start NNMi Services	93
Chapter 2: Overlapping Addresses in NAT Environments	94
Chapter 3: Use NNMi Help Anywhere, Anytime	97
Chapter 4: Connecting Multiple NNMi Management Servers (NNMi Advanced)	98
About Multi-Tenancy and Global Network Management	100
Tenants for Overlapping Address Domains	101
Tenant Best Practices for Global Network Management	102
Troubleshooting Tenants in Global Network Management	104
Regional Manager Configuration	107

Global Manager Configuration	109
Global Manager: Connect to a Regional Manager	110
Global Manager: Configure Regional Manager Connection	112
Global Manager: Configure Custom Attribute Replication	115
Custom Attribute Replication Form	117
Disconnect Communication with a Regional Manager	117
Troubleshoot Global Network Management	119
Clock Synchronization Issues (SSO / Global Network Management)	120
Determine the State of the Connection to a Regional Manager	121
Thresholds in the Global Network Management Environment	122
Check the Health of Global Managers and Regional Managers	123
Node Synchronization Issues	125
Error Messages About Regional Managers (NNMi Advanced)	127
Chapter 5: Configuring Communication Protocol	129
Configure Default SNMP, Management Address, and ICMP Settings	130
Timeout / Retry Behavior Example for SNMP	138
Timeout / Retry Behavior Example for ICMP	139
Configure Default Community Strings (SNMPv1 or SNMPv2c)	140
Default Read Community String Form	143
Configure Default SNMPv3 Settings	145
Default SNMPv3 Settings form	146
Configure the Default Device Credentials	147
Configure Regions (Communication Settings)	148
Communication Region Form	150
Configure Address Ranges for Regions	157
Configure Hostname Filters for Regions	160
Configure SNMPv1/v2c Community Strings for Regions	162
Configure SNMPv3 Settings for Regions	165
Communication Region SNMPv3 Settings form	166
Configure Credential Settings for Regions	168
Configure Specific Nodes	169

Specific Node Settings Form (Communication Settings)	171
Configure SNMPv1/v2c Community Strings for a Specific Node	180
Configure SNMPv3 Settings for a Specific Node	182
Configure Credential Settings for a Specific Node	183
Load Communication Settings from a File	185
Restrict SNMP Communication for a Node	186
Troubleshooting Communication Settings	187
Verify That All Nodes Support SNMP	188
Verify a Node's Communication Settings	188
Verify Communication Settings	190
Resolve Authentication Errors	191
Chapter 6: Discovering Your Network	194
How Spiral Discovery Works	195
Which Nodes Are Discovered?	195
What Information Is Collected?	196
Consider IPv4 Subnet Connection Rules	200
Keep Requests to a Minimum	202
Correct Any Misinformation	203
When Does Discovery Happen?	204
How Is Discovery Configured?	206
Determine Your Approach to Discovery	206
Prerequisites for Discovery	207
SNMP Prerequisites	207
Well-Configured DNS Prerequisite	208
Overlapping Address Mapping	210
Overlapping Address Mapping Form	211
Configure Tenants	213
Use the Tenant Form	215
Tenant and Initial Discovery Security Group Assignments	217
Configure Discovery	219
Establish Global Defaults for Spiral Discovery	221

Configure Discovery of ATM/Frame Relay Interfaces	221
Configure Ping Sweep (override for all Auto-Discovery Rules)	222
Configure the Node Name Strategy	223
Discovery Node Name Choices	226
Node Name Decision Tree	227
Configure Layer 2 Connection Source	228
Configure Schedule Settings	230
Adjust the Rediscovery Interval	231
Adjust the Node Group Rediscovery Interval	232
Configure Whether to Delete Unresponsive Nodes	233
Configure Whether to Delete Layer 2 Connections	235
Configure Auto-Discovery Rules	236
Auto-Discovery Rule Behavior Choices	238
Configure Basic Settings for the Auto-Discovery Rule	240
IP Address Ranges for the Auto-Discovery Rule	244
SNMP System Object ID Ranges for the Auto-Discovery Rule	248
Example Uses of Auto-Discovery	251
Set Outside Limits for Auto-Discovery	251
Only Routers and Switches Discovered	255
Only Routers' Physical Interfaces Discovered	257
Only Specific Vendor/Make/Models Discovered	258
All SNMP Devices Discovered	260
Everything Discovered	261
Strategies to Exclude Certain Nodes from Auto-Discovery	262
Limit Sources of Neighbor Information	263
Configure IPv4 Subnet Connection Rules	265
Subnet Connection Rules Provided by NNMi	267
Configure Unnumbered Interface Node Groups	268
Configure Unnumbered Interface Subnets	270
Configure an Excluded IP Addresses Filter	274
Configure an Included Interface Ranges Filter	277

Configure an Excluded Interfaces Filter	280
Choose Techniques to Launch Discovery	282
Discovery Seeds for Auto-Discovery in Default Tenant	283
Ping Sweep for Auto-Discovery in Default Tenant	285
Spiral Discovery of Only Seeds (all Tenants)	285
Specify Discovery Seeds	287
In the Console, Configure Discovery Seeds	288
From the Command Line, Add Discovery Seeds	293
Add Multiple Seeds, Configure Discovery Seeds	293
Examine Discovery Results	297
Check Initial Progress of Discovery	298
Node Discovery State Check	298
Verify Success of Discovery Seeds	299
Discovery Seed Results	299
Examine Discovery Inventory	303
Examine Layer 2 Discovery Results	303
Troubleshooting Layer 2 Connections	305
Examine Layer 3 Discovery Results	306
Keep Your Topology Accurate	307
Delete Nodes	308
Delete Discovery Seeds	310
Detect Interface Changes	311
Add or Delete a Layer 2 Connection	314
Start Discovery On-Demand	320
Change Tenant Assignment for a Node	321
Chapter 7: Configure Device Profiles	323
Chapter 8: Creating Groups of Nodes or Interfaces	325
Create Node Groups	326
Create Node Groups Using Filters or Hostname Lists (Configuration: Node Groups) ..	327
Specify Node Group Additional Filters	330
Node Groups of IPv4 or IPv6 Addresses	339

Guidelines for Creating Additional Filters for Node Groups	341
Add Boolean Operators in the Additional Filters Editor	344
Create Node Groups From the Actions Menu	347
Add Nodes to a Node Group From the Actions Menu	349
From the Command Line, Define Node Groups	351
Remove Nodes from Node Groups	351
Configure Node Group Status	352
Configure Percentage Values for the Target Status	353
Node Group Status Settings Form	354
Create Interface Groups	356
Create Interface Groups Using ifType Values and Filters (Configuration: Interface Groups)	356
Specify Interface Group Additional Filters	358
Interface Groups of IPv4 or IPv6 Addresses	368
Guidelines for Creating Additional Filters for Interface Groups	369
Add New ifType Values (Interface Types) to the List	371
From the Command Line, Define Interface Groups	371
Troubleshooting Interface Changes	372
Node Groups Provided by NNMi	372
Node Groups As Predefined View Filters	373
Island Node Groups	375
Interface Groups Provided by NNMi	376
Chapter 9: Monitoring Network Health	378
Examples of Count-Based Threshold Monitoring	378
Examples of Time-Based Threshold Monitoring	382
Configure NNMi Monitoring Behavior	387
About the State Poller	389
The NNMi Causal Engine and Monitoring	390
Global Control Settings for Monitoring	391
Default Settings for Monitoring	393
About Threshold Settings Provided by NNMi	405
Interface Settings for Monitoring	416

Configure Threshold Monitoring for Interface Groups	426
Configure Count-Based Threshold Monitoring for Interface Groups	426
Configure Time-Based Threshold Monitoring for Interface Groups	430
Configure Baseline Settings for Interfaces	435
Monitor Wireless Interfaces	438
NNM iSPI Performance for Metrics and Wireless Interfaces	441
Node Settings for Monitoring	443
Configure Threshold Monitoring for Node Groups	458
Configure Count-Based Threshold Monitoring for Node Groups	458
Configure Time-Based Threshold Monitoring for Node Groups	462
Configure Baseline Settings for Nodes	467
Troubleshooting Monitoring Configuration	470
Determine Reasonable Threshold Settings	471
Find Threshold Results	472
Threshold Monitoring Behavior After a System Restart or Configuration Change ..	473
Monitor Router Redundancy Groups (NNMi Advanced)	474
Current Health of the State Poller Service	474
Verify the Monitoring Settings	474
Monitor Status Distribution for Network Objects	478
Create Custom Polling Configurations	478
Enable or Disable Custom Poller	480
Create a Custom Poller Collection	481
Configure Basic Settings for a Custom Poller Collection	484
Specify the MIB Variable Information for a Custom Poller Collection	493
MIB Expressions Form (Custom Poller)	495
Test a MIB Expression (Custom Poller)	500
Use the MIB Expression Editor (Custom Poller)	501
Configure Threshold Information for a Custom Poller Collection	507
Configure Comparison Maps for a Custom Poller Collection	513
Create a Policy	516
Create a Report Group (NNM iSPI Performance for Metrics)	520

Create a Report Collection (NNM iSPI Performance for Metrics)	521
Chapter 10: Configuring the NNMi User Interface	524
Define Default Map Settings	527
Configure Default Settings for Line Graph	530
Customize Device Profile Icons	532
Add Device Profile Icons	532
View the Device Profile Icons Available	535
Change the Image for a Specified Icon	536
Configure the Device Profile Icon for Specified Nodes	538
Configure Device Family Icons	539
Configure Device Vendor Icons	540
Configure Device Category Icons	542
Customize Object Attributes	543
Add a Custom Attribute to One Object	543
Add Custom Attributes to Multiple Objects	546
Add Custom Attributes Using the Actions Menu	546
Add Custom Attributes Using the Command Line	547
Remove Custom Attributes from Objects	548
Configure Maps	549
Define Node Group Map Settings	550
Node Group Map Settings Form	551
Configure Basic Settings for a Node Group Map	552
Configure the Connectivity to be Displayed for a Node Group Map	556
Configure Background Image Information for a Node Group Map	559
Background Image Sources in Node Group Maps	561
Scale Background Images in Node Group Maps	562
Troubleshoot URLs When Specifying a Background Image	563
Configure a Path View Map	563
Configure Menus	568
Configure Menu Items	568
Chapter 11: Configuring Security	569

Choose a Mode for NNMi Access	570
NNMi Configuration Settings to Control NNMi Access	571
Lightweight Directory Access Protocol (LDAP) to Control NNMi Access	572
X.509 Certificates to Control NNMi Access	573
Determine Your Security Strategy	574
About User Accounts	579
About User Groups	580
About User Account Mappings	581
About Security Groups	582
About Security Group Mappings	583
Using the Security Folder	584
Configure Security: All Users Access All Nodes	586
Configure Security: Limit Node Access	588
Using the Security Wizard View	591
Configure Security Example (Divide Node Access Between Two or More User Groups)	593
Configure Security Example (Allow a Subset of Users to Access a Subset of Nodes)	602
User Account Tasks	610
Configure User Accounts (User Account Form)	611
Delete a User Account	613
Change Password, Name	614
Create and Delete User Accounts Using the Security Wizard	616
User Group Tasks	617
User Groups Provided in NNMi	618
Determine which NNMi User Group to Assign	619
Configure User Groups (User Group Form)	621
Create and Delete User Groups Using the Security Wizard	623
User Account Mapping Tasks	624
Map User Accounts to User Groups (User Account Mapping Form)	624
Remove a User from a User Group (User Account Mapping)	626
Remove User Accounts from User Groups	627
Map User Accounts and User Groups	628

Assign User Groups to User Accounts Using the Security Wizard Page	628
Assign User Groups to User Accounts Using the Security Wizard Dialog Box	629
Assign User Accounts to User Groups Using the Security Wizard Page	630
Assign User Accounts to User Groups Using the Security Wizard Dialog Box	631
Security Group Tasks	632
Configure Security Groups (Security Group Form)	632
Create and Delete Security Groups Using the Security Wizard	633
Assign Nodes to Security Groups	635
Methods for Assigning Nodes to Security Groups	636
Security Group Mapping Tasks	638
Map User Groups to Security Groups (Security Group Mapping Form)	638
Object Access Privileges Provided in NNMi	640
Remove User Groups from Security Group Mappings	640
Change the User Group to Security Group Assignment	641
Map User Groups and Security Groups	644
Assign Security Groups to User Groups Using the Security Wizard Page	644
Assign Security Groups to User Groups Using the Security Wizard Dialog Box ...	645
Assign User Groups to Security Groups Using the Security Wizard Page	646
Assign User Groups to Security Groups Using the Security Wizard Dialog Box	647
Remove User Groups from Security Group Mappings	648
Control Menu Access	649
Set Up Command Line Access to NNMi	653
Communicate Console Access Information to Your Team	655
Open the NNMi Console	655
Configuring Sign-In to the NNMi Console	657
Sign Out from the Console	658
Chapter 12: Troubleshoot NNMi Access	659
Check Security Configuration	661
View Summary of Changes in the Security Wizard	662
View the Users who are Signed In to NNMi	663
Audit NNMi User Sign-In and Sign-Out Activity	663

Audit NNMi User Actions	665
Restore the Administrator NNMi Role	666
Restore NNMi Access for the system User	666
Chapter 13: Configuring Incidents	667
Manage Incidents Using Incident Configurations	668
How NNMi Gathers Incidents	668
The NNMi Causal Engine and Incidents	670
The NNMi Causal Engine and Object Status	672
About the Trap Service Stages	684
About the Event Pipeline	685
How NNMi Closes Incidents	687
Incident Configurations Provided by NNMi	688
Custom Incident Attributes Provided by NNMi (Information for Administrators)	688
SNMP Trap Incident Configurations Provided by NNMi	695
Syslog Message Incident Configurations Provided by NNMi	708
Management Event Configurations Provided by NNMi	716
Incident Pair (Pairwise) Configurations Provided by NNMi	730
About Custom Incident Attributes for an Incident	732
Custom Incident Attributes Provided by NNMi (Information for Administrators)	733
Manage the Number of Incoming Incidents	739
Establish Criteria or Relationships for Incoming Incidents	740
Correlate Duplicate Incidents (Deduplication Configuration)	745
Deduplication Comparison Parameters Form	746
Track Incident Frequency (Rate: Time Period and Count)	746
About Pairwise Configurations	746
Incident Pair (Pairwise) Configurations Provided by NNMi	748
Configure Pairwise Configurations	750
Prerequisites for Pairwise Configurations	750
Pairwise Configuration Form (Correlate Pairs of Incidents)	752
Configure a Payload Filter to Enrich a Pairwise Incident Configuration	755
Matching Criteria Configuration Form (Identify Incident Pairs)	762

Pairwise Configuration Example	765
Rate Comparison Parameters Form	767
Suppress Incident Configurations	767
Enrich Incident Configurations	768
Dampening Incident Configurations	769
Configure Custom Correlations	769
Configure a Correlation Rule	771
Configure a Parent Incident Filter for a Correlation Rule	775
Configure a Child Incident Filter for a Correlation Rule	785
Configure a Correlation Filter	795
Correlation Rule Example	804
Configure a Causal Rule	808
Configure a Child Incident for a Causal Rule	814
Configure a Child Incident Filter for a Causal Rule	817
Configure a Source Object Filter for a Causal Rule	827
Configure a Source Node Filter for a Causal Rule	836
Causal Rule Example	842
Configure an Action for an Incident	847
Lifecycle Transition Action Form	848
Valid Parameters for Configuring Incident Actions (Management Events)	848
Handling Special Characters in Action Arguments	854
Example Jython Methods Provided by NNMi	856
Configure Diagnostics for an Incident	857
Diagnostic Selections Form	858
Diagnostics (Flows) Provided by NNM iSPI NET	859
Incident Configurations You Might Want to Enable	862
Generate Interface Disabled Incidents	863
Generate Card Disabled Incidents	864
Generate Card Undetermined State Incidents	864
Generate Node Deleted Incidents	864
Generate Performance Threshold Incidents (NNM iSPI Performance for Metrics)	865

Using the Command Line to Manage Incident Configurations	866
Generate a File of Your Incident Configurations	866
Load Incident Configurations Using the Command Line	869
Manage Incoming SNMP Traps	871
Configure Network Devices to Send SNMP Notifications to NNMi	872
Load SNMP Trap Incident Configurations	873
Load SNMP Trap Incident Configurations from the Command Line	874
Load SNMP Trap Incident Configurations using the Console	876
Control which Incoming Traps Are Visible in Incident Views	877
Handle Unresolved Incoming Traps	878
Analyze Trap Information	879
Control the Times within which NNMi Causal Engine Accepts SNMP Traps	884
Configure Incident Logging	884
Configure SNMP Trap Incidents	886
SNMP Trap Configuration Form	887
Configure Basic Settings for an SNMP Trap Incident	889
Specify the Incident Configuration Name (SNMP Trap Incident)	891
Specify the SNMP Object ID	892
SNMP Object ID Format for SNMPv2c\SNMPv3 Traps	892
SNMP Object ID Format for SNMPv1 Generic Traps	894
SNMP Object ID Format for a Specific SNMPv1 Trap	895
Display an SNMP Trap as a Root Cause Incident	897
Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)	898
Create an Incident Category (SNMP Trap Incident)	901
Create an Incident Family (SNMP Trap Incident)	902
Specify the Incident Severity (SNMP Trap Incident)	903
Specify Your Incident Message Format (SNMP Trap Incident)	904
Valid Parameters for Configuring Incident Messages (SNMP Trap Incident) ...	904
Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)	911
Specify a Description for Your Incident Configuration (SNMP Trap Incident) ...	912

Configure Interface Settings for an SNMP Trap Incident	913
Configure Incident Suppression Settings for an Interface Group (SNMP Trap Incident)	914
Configure Incident Enrichment Settings for an Interface Group (SNMP Trap Incident)	923
Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (SNMP Trap Incidents)	928
Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (SNMP Trap Incidents)	930
Configure Incident Dampening Settings for an Interface Group (SNMP Trap Incident)	938
Configure Incident Actions for an Interface Group (SNMP Trap Incident)	947
Configure a Payload Filter for an Incident Action (Interface Settings) (SNMP Trap Incidents)	949
Configure Node Settings for an SNMP Trap Incident	957
Configure Incident Suppression Settings for a Node Group (SNMP Trap Incident)	959
Configure Incident Enrichment Settings for a Node Group (SNMP Trap Incident)	968
Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (SNMP Trap Incidents)	973
Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (SNMP Trap Incidents)	975
Configure Incident Dampening Settings for a Node Group (SNMP Trap Incident)	982
Configure Incident Actions for a Node Group (SNMP Trap Incident)	992
Configure a Payload Filter for an Incident Action (Node Settings) (SNMP Trap Incidents)	994
Configure Diagnostics Selections for a Node Group (SNMP Trap Incident) ...	1001
Configure Suppression Settings for an SNMP Trap Incident	1004
Configure Enrichment Settings for an SNMP Trap Incident	1013
Configure Dampening Settings for an SNMP Trap Incident	1018
Configure Deduplication for an SNMP Trap Incident	1029
Deduplication Comparison Parameters Form (SNMP Trap Incident)	1036
Configure Rate (Time Period and Count) for an SNMP Trap Incident	1038
Rate Comparison Parameters Form (SNMP Trap Incident)	1041

Configure Actions for an SNMP Trap Incident	1042
Lifecycle Transition Action Form (SNMP Trap Incidents)	1044
Configure a Payload Filter for an Action (SNMP Trap Incidents)	1046
Valid Parameters for Configuring Incident Actions (SNMP Trap Incident)	1054
Configure Forward to Global Manager Settings for an SNMP Trap Incident (NNMi Advanced)	1059
Configure Syslog Message Incidents (HP ArcSight)	1068
Syslog Message Configuration Form (HP ArcSight)	1069
Configure Basic Settings for a Syslog Message Incident (HP ArcSight)	1071
Specify the Incident Configuration Name (Syslog Messages) (HP ArcSight) .	1074
Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)	1074
Create an Incident Category (Syslog Message) (HP ArcSight)	1077
Create an Incident Family (Syslog Message) (HP ArcSight)	1078
Specify the Incident Severity (Syslog Message) (HP ArcSight)	1079
Specify Your Incident Message Format (Syslog Message) (HP ArcSight)	1080
Valid Parameters for Configuring Incident Messages (Syslog Message) (HP ArcSight)	1080
Include Custom Incident Attributes in Your Message Format (Syslog Message) (HP ArcSight)	1087
Specify a Description for Your Incident Configuration (Syslog Messages)(HP ArcSight)	1088
Configure Interface Settings for a Syslog Message Incident (HP ArcSight)	1089
Configure Incident Suppression Settings for an Interface Group (Syslog Message)(HP ArcSight)	1090
Configure Incident Enrichment Settings for an Interface Group (Syslog Message)(HP ArcSight)	1099
Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (Syslog Message)(HP ArcSight)	1104
Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (Syslog Message) (HP ArcSight)	1106
Configure Incident Dampening Settings for an Interface Group (Syslog Message) (HP ArcSight)	1114
Configure Incident Actions for an Interface Group (Syslog Message) (HP ArcSight)	1123

Configure a Payload Filter for an Incident Action (Interface Settings) (Syslog Message) (HP ArcSight)	1125
Configure Node Settings for a Syslog Message Incident (HP ArcSight)	1133
Configure Incident Suppression Settings for a Node Group (Syslog Message) (HP ArcSight)	1134
Configure Incident Enrichment Settings for a Node Group (Syslog Message) (HP ArcSight)	1143
Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (Syslog Message) (HP ArcSight)	1148
Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (Syslog Message) (HP ArcSight)	1150
Configure Incident Dampening Settings for a Node Group (Syslog Message) (HP ArcSight)	1157
Configure Incident Actions for a Node Group (Syslog Message) (HP ArcSight)	1167
Configure a Payload Filter for an Incident Action (Node Settings) (Syslog Message) (HP ArcSight)	1169
Configure Diagnostics Selections for a Node Group (Syslog Message) (HP ArcSight)	1177
Configure Suppression Settings for a Syslog Message Incident (HP ArcSight) ...	1179
Configure Enrichment Settings for a Syslog Message Incident (HP ArcSight)	1189
Configure Dampening Settings for a Syslog Message Incident (HP ArcSight)	1194
Configure Deduplication for a Syslog Message Incident (HP ArcSight)	1204
Deduplication Comparison Parameters Form (Syslog Message) (HP ArcSight)	1211
Configure Rate (Time Period and Count) for a Syslog Message Incident (HP ArcSight)	1213
Rate Comparison Parameters Form (Syslog Message) (HP ArcSight)	1216
Configure Actions for a Syslog Message Incident (HP ArcSight)	1217
Lifecycle Transition Action Form (Syslog Message) (HP ArcSight)	1219
Configure a Payload Filter for an Action (Syslog Message) (HP ArcSight)	1221
Valid Parameters for Configuring Incident Actions (Syslog Message) (HP ArcSight)	1230
Configure Management Events	1236
Management Event Form	1236
Configure Basic Settings for a Management Event Incident	1239

Specify the Incident Configuration Name (Management Events)	1242
Specify Category and Family Attribute Values for Organizing Your Incidents (Management Events)	1242
Create an Incident Category (Management Events)	1245
Create an Incident Family (Management Events)	1246
Specify the Incident Severity (Management Events)	1247
Specify Your Incident Message Format (Management Events)	1248
Valid Parameters for Configuring Incident Messages (Management Events) .	1248
Include Custom Incident Attributes in Your Message Format (Management Events)	1255
Specify a Description for Your Incident Configuration (Management Events) .	1256
Configure Interface Settings for a Management Event Incident	1257
Configure Incident Suppression Settings for an Interface Group (Management Events)	1258
Configure Incident Enrichment Settings for an Interface Group (Management Events)	1267
Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (Management Events)	1272
Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (Management Events)	1274
Configure Incident Dampening Settings for an Interface Group (Management Events)	1282
Configure Incident Actions for an Interface Group (Management Events)	1291
Configure a Payload Filter for an Incident Action (Interface Settings) (Management Events)	1293
Configure Node Settings for a Management Event Incident	1301
Configure Incident Suppression Settings for a Node Group (Management Events)	1302
Configure Incident Enrichment Settings for Node Group (Management Events)	1311
Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (Management Events)	1316
Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (Management Events)	1318
Configure Incident Dampening Settings for a Node Group (Management Events)	1325

Configure Incident Actions for a Node Group (Management Events)	1335
Configure a Payload Filter for an Incident Action (Node Settings) (Management Events)	1337
Configure Diagnostics Selections for a Node Group (Management Events) ...	1344
Configure Suppression Settings for a Management Event Incident	1347
Configure Enrichment Settings for a Management Event Incident	1356
Configure Dampening Settings for a Management Event Incident	1361
Configure Deduplication for a Management Event Incident	1372
Deduplication Comparison Parameters Form (Management Events)	1379
Configure Rate (Time Period and Count) for a Management Event Incident	1380
Rate Comparison Parameters Form (Management Events)	1383
Configure Actions for a Management Event Incident	1384
Lifecycle Transition Action Form (Management Events)	1386
Configure a Payload Filter for an Action (Management Events)	1388
Valid Parameters for Configuring Incident Actions (Management Events)	1397
Troubleshoot Incident Configurations	1402
View an Incident Configuration Report	1403
Configure Trap Forwarding	1407
Configure NNMi SNMPv3 Security Settings for Trap Forwarding and Inform- Requests	1407
Configure Trap Forwarding Filters	1410
Trap Forwarding Filter Form	1411
Filter Form	1412
Configure Trap Forwarding Destinations	1413
Trap Forwarding Destination Form	1414
Destination Filter Form	1416
Forward Traps to a Remote Server Example	1418
Trap Varbinds Provided by NNMi	1419
Configure Trap Logging	1420
Trap Logging Configuration Form	1421
Node Group Logging Configuration Form	1430
Valid Parameters for Trap Logging Messages	1438

Include varbinds in Your Log Message Format	1442
Chapter 14: Using Route Analytics Management System (RAMS) with NNMi Advanced	1443
HP RAMS MPLS WAN (NNMi Advanced)	1444
Configure HP Route Analytics Management System (NNMi Advanced)	1445
HP RAMS MPLS WAN Configuration (NNMi Advanced)	1446
HP RAMS and Global Network Management (NNMi Advanced)	1449
Chapter 15: Extending NNMi Capabilities	1452
Control the NNMi Console Menus	1452
Create Menu Nesting	1453
Configure Menu Item Basic Details	1456
Configure Menu Item Context Basic Details	1459
Configure Launch Actions	1462
W3C Rules for URLs	1466
Attributes per Object Type for Full URLs	1467
Capability Attributes in Full URLs	1470
Custom Attributes in Full URLs	1472
Custom Incident Attributes (CIAs) in Full URLs	1473
Database Object Identifiers for Full URLs	1475
Path View Attributes for Full URLs	1475
MIB Expressions in Full URLs	1476
Configure SNMP Line Graph Actions	1477
MIB Specification Form	1480
Specify Optional Menu Item Enablement Filters	1484
Managing MIBs	1490
Upload MIB Files for NNMi's Use	1491
Load MIBs	1492
Load MIBs from the Console	1492
Load MIBs from the Command Line	1495
Unload MIBs	1496
Available MIBs Files and MIB Variables	1498

Loaded MIBs View	1499
Configure MIB Expressions	1500
MIB Expressions View	1500
MIB Expression Form (Line Graph)	1500
Test a MIB Expression (Line Graph)	1505
Use the MIB Expression Editor (Line Graph)	1506
Override MIB OID Types	1512
Purchase HP Network Node Manager i Smart Plug-ins and More	1515
Annotate NNM iSPI Performance for Metrics Reports	1517
Integrations with HP and Third-Party Products	1519
Integration Configuration Form	1520
Chapter 16: Integrating NNMi Elsewhere with URLs	1522
W3C Rules for URLs	1522
Authentication Requirements for URLs Access	1523
Pass Environment Attributes	1525
Launch the Console (showMain)	1526
Launch a View (showView)	1527
Launch an Incident View	1531
Launch the All Incidents View Filtered by Node	1534
Launch a Topology Maps Workspace View	1536
Launch a Monitoring Workspace View	1546
Launch a Troubleshooting Workspace View	1550
Launch an Inventory Workspace View	1559
Launch a Management Mode Workspace View	1563
Launch a Configuration Workspace View	1566
Launch a Form (showForm)	1568
Launch a Node Form	1569
Launch an Interface Form	1573
Launch an IP Address Form	1575
Launch a Subnet Form	1576
Launch an Incident Form	1578

Launch a Node Group Form	1580
Launch a Configuration Form	1582
Launch Menu Items (runTool)	1584
Launch the Actions: Communication Configuration Command	1585
Launch the Actions: Configuration Poll Command	1586
Launch the Actions: Line Graph (showLineGraph)	1587
Launch the Actions: Monitoring Settings Command	1590
Launch the Actions: Ping Command	1594
Launch the Actions: Status Details Command (for Node Groups)	1595
Launch the Actions: Status Poll Command	1596
Launch the Actions: Trace Route Command	1598
Actions: Execute a Launch Action	1598
Launch the Tools: MIB Browser (showMibBrowser)	1599
Launch the Tools: NNMi Status Command	1600
Launch the File: Sign-Out Command	1601
Launch the Tools: Sign-In/Out Audit Log Command	1601
Confirm that NNMi Is Running (cmd=isRunning)	1602
Chapter 17: Maintaining NNMi	1603
Check NNMi Health	1603
Track Your NNMi Licenses	1604
Extend a Licensed Capacity	1605
Resolve Inconsistencies between State and Status	1607
Recalculate Management Mode for Out of Sync Physical Components	1608
Export and Import Configuration Settings	1610
Export/Import Behavior and Dependencies	1610
Export a Snapshot of Your Configuration Settings	1616
Import Configuration Files to Restore Previous Settings	1618
Transfer Configuration Settings to Another NNMi Management Server	1620
Troubleshooting Imports of Configuration Files	1623
Back Up and Restore NNMi	1628
Archive and Delete Incidents	1631

Delete Nodes	1635
Delete One or More Objects	1638
Glossary	1640
We appreciate your feedback!	1645

Chapter 1: Introduction for NNMi Administrators

As an NNMi administrator, you can use the console to configure the items described in the following table.

Configure NNMi

What You Can Configure	Description
Custom Polling	Using the Custom Poller option in the Monitoring folder of the Configuration workspace, take a proactive approach to network management by using SNMP MIB Expressions to specify additional information that NNMi should poll. You can also specify States that should be assigned to polled MIB Expression values, including any thresholds that should be set and monitored.
Custom Correlation	Using the Custom Correlation option in the Incidents folder of the Configuration workspace, correlate groups of incidents under a Parent Incident. This feature is useful when you want to define a relationship between a number of incidents potentially from different network objects that form a logical set to identify a problem. The set of correlations is considered complete if all of the incidents arrive within a specified time window.
Device Profiles	HP provides well over three thousand pre-configured Device Profiles, one for each known MIB-II sysObjectID at the time NNMi released. NNMi uses Device Profiles (which equate to sysObjectID) to control certain types of behavior. Using the Device Profiles option in the Configuration workspace, you can update Device Profile information. See "Configure Device Profiles" on page 323 for more information.
Discovery	<p>Using the Discovery Configuration option in the Discovery folder of the Configuration workspace, configure NNMi to discover only those devices that are important to you and your team. See "Discovering Your Network" on page 194 for more information.</p> <p>If <i>static</i> Network Address Translation (NAT), <i>dynamic</i> Network Address Translation (NAT), or <i>dynamicPort</i> Address Translation (PAT/NAPT) are used in your network management domain, see also "Overlapping Addresses in NAT Environments" on page 94.</p>
Global Network Management	(<i>NNMi Advanced - Global Network Management feature</i>) Using the Global Network Management option in the Configuration workspace, you can configure NNMi to share the workload among multiple NNMi management servers in your network environment. See "Connecting Multiple NNMi Management Servers (NNMi Advanced)" on page 98 .
ICMP and	Using the Communication Configuration option in the Configuration

Configure NNMi , continued

What You Can Configure	Description
SNMP Communication Protocols	workspace, provide the SNMPv1 or SNMPv2c community strings (read and write) for your network environment, or provide the SNMPv3 User Names for your network environment. Configure NNMi settings for timeout, retry, and port usage for ICMP and SNMP traffic. See "Configuring Communication Protocol" on page 129 for more information.
Incidents	Using the Incidents folder in the Configuration workspace, review the many predefined incident configurations provided by NNMi . Edit any of the configurations provided by NNMi or create your own . See "Configuring Incidents" on page 667 for more information.
Interface Groups	Using the Interface Groups option in the Object Groups folder of the Configuration workspace, identify important devices. Interface Groups are filters for interface and IP address views. Interface Groups can also control how NNMi monitors network devices. See "Create Interface Groups" on page 356 for more information.
Interface Types	Interface Type definitions cover all known industry-standard IANA ifType-MIB variables at the time of the release of NNMi. Using the ifTypes view in the Configuration workspace, add an additional ifType values to the NNMi list. This option is useful if your team acquires new devices that are configured with new industry-standard ifType values not yet preconfigured by NNMi. See "Add New ifType Values (Interface Types) to the List" on page 371 for more information.
MIBs	<p>Using the MIB Expressions option in the MIBS folder of the Configuration workspace, take a proactive approach to network management by using SNMP MIB Expressions to specify additional information that NNMi should poll. See "Configure MIB Expressions" on page 1500 for more information.</p> <p>Using the MIBs folder, you can view and configure the following:</p> <ul style="list-style-type: none"> • Loaded MIBs view • MIB Variables view • MIB Notifications view • Textual Conventions view • MIB Expressions view • MIB OID Types view • ifTypes view
Monitoring	Using the Monitoring Configuration option in the Monitoring folder of the

Configure NNMi , continued


What You Can Configure	Description
	Configuration workspace, define how and how often important devices are monitored by NNMi . See "Monitoring Network Health" on page 378 for more information.
Node Groups	Using the Node Groups option in the Object Groups folder of the Configuration workspace, identify important devices. You can then filter node, interface, IP address, and incident views by Node Group. You can also specify Node Groups when configuring monitoring and incidents. See "Create Node Groups" on page 326 for more information.
Node Group Map Settings	Using the User Interface Configuration option in the Configuration workspace, specify the Node Group map configuration including the Node Group and background image to be used in a Node Group map. See "Define Node Group Map Settings" on page 550 for more information.
Object Groups	Using the Node Groups and Interface Groups options in the Object Groups folder of the Configuration workspaces, define groups of nodes or interfaces. Use these object groups as filters to quickly locate information in views. See "Creating Groups of Nodes or Interfaces" on page 325 for more information. You can also monitor the health of each group, see "Configure NNMi Monitoring Behavior" on page 387 .
Route Analytic Management Servers (RAMS)	(<i>NNMi Advanced</i> , plus <i>HP Route Analytics Management System (RAMS) for MPLS WAN</i>) Using the RAMS Servers option in the Configuration workspace, configure sources of Route Analytics Management System data for NNMi to use. See "HP RAMS MPLS WAN Configuration (NNMi Advanced)" on page 1446 .
Security	Using the Security option in the Configuration workspace, control access to NNMi. See "Configuring Security" on page 569 for more information. Tip: NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See "Choose a Mode for NNMi Access" on page 570 .
Status	Using the Status Configuration option in the Configuration workspace, configure how Node Group Status is calculated. You can choose to assign the Node Group the most severe status of any Node Group member or configure the percentage thresholds for one or more Node Group target statuses. See "Configure Node Group Status" on page 352 for more information.
Trap Forwarding	Using the Trap Forwarding Configuration option in the Trap Server folder under the Incidents folder of the Configuration workspace, configure trap

Configure NNMi , continued

What You Can Configure	Description
	forwarding filters and destinations. See "Configure Trap Forwarding" on page 1407 for more information.
Trap Logging	Using the Trap Logging Configuration option in the Trap Server folder under the Incidents folder of the Configuration workspace, configure how you want trap information to appear in the trap logging file. See "Configure Trap Logging" on page 1420 for more information.
User Interface	Using the User Interface Configuration option in the Configuration workspace, configure the following user interface features: <ul style="list-style-type: none"> • User accounts • Default map settings • Node Group map settings • Default Line Graph settings • Menus and menu items • Icons displayed for Device Profiles

NNMi provides a variety of tools to assist you with these configuration tasks. Each of these tools is described in the following table. You can extend NNMi using HP Network Node Manager i Software Smart Plug-ins (ISPIs) as described in ["Extending NNMi Capabilities" on page 1452](#).

NNMi Administrator Tools

Tool	Description
Actions	Used to perform automated tasks on a single object or on a group of objects. For example, you can use the Actions menu to change the Management Mode of one or more nodes from Managed to Out of Service . Actions are available from table views, map views, and forms. See "Actions Provided by NNMi" on page 41 for more information
Configuration Workspaces	The console provides a workspace for each kind of item you can configure in NNMi . See the preceding "Configure NNMi " table for more information.
Lookup Fields	Provided in forms, fields that include the  icon provide access to a list of all available attribute values, and in some locations enable you to create attribute values. See "Lookup Fields" on page 37 for more information.
NNMi Processes and Services	NNMi is built on a group of processes and services. You can list these processes and services. You can stop and start individual processes and services. See "NNMi Processes and Services" on page 86 for more information.

NNMi Administrator Tools, continued

Tool	Description
Tools	Used to access the following types of information: <ul style="list-style-type: none">• Attached switch port information for a selected Node• NNMi audit log information• NNMi status and monitoring information• MIB Browser• Security configuration reports• Trap analysis information• User information and log files

Administrator Tools in the Console

When configuring settings for NNMi, you create configuration object instances. For example, to create a new URL action, you must create a new URL action instance. As another example, to specify configuration settings for discovery, you might create object instances that contain ranges of IP addresses that you want NNMi to use as hints for Spiral Discovery.

The console provides the following tools to assist you with configuration tasks:

- ["Configuration Workspaces" on the next page](#)
- ["Lookup Fields" on page 37](#)
- ["Create a Configuration Object Instance Using the Form Toolbar" on page 39](#)
- ["Delete One or More Objects" on page 1638](#)

Quick Start Configuration Wizard

Before you use the Quick Start Configuration Wizard, review "Using the Quick Start Configuration Wizard" in the *NNMi Interactive Installation Guide*. To access the *NNMi Interactive Installation Guide*, follow these steps:

1. Unzip the `nnmi_interactive_installation_en.zip` file located in the top level directory of the NNMi 9.20 installation media.
2. Double-click `nnmi_interactive_installation_en.htm`.

The Quick Start Configuration Wizard automatically runs immediately after Network Node Manager (NNMi) installation completes. Use the Quick Start Configuration Wizard to configure NNMi in a

limited (or test) environment. The Quick Start Configuration Wizard helps you to complete the following initial set up tasks:

- Provide the *read community strings* for your SNMPv1 or SNMPv2c environment to enable "Get" commands
- Provide the USM settings for your SNMPv3 environment
- Discover a limited range of network nodes
- Set up an initial administrator account

You can launch the wizard using the following URL:

`http://<serverName>:<portNumber>/quickstart/`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

Note: HP recommends that you run the Quick Start Configuration Wizard only one time immediately after NNMi installation.

After using the Quick Start Configuration Wizard to set up a test network, see ["Configuration Workspaces" below](#) for information about completing additional NNMi configuration tasks.

Configuration Workspaces

NNMi administrators use the Configuration workspaces to configure the following items related to NNMi.

Note: On tables in configuration forms, if the cursor changes to indicate a hyperlink when you mouse over a column heading, you are able to sort the column's data. You cannot change the sort on some of the tables on the forms in the configuration workspace.

NNMi Configuration Workspaces

Name	Description
Communication Configuration	Use to configure how NNMi uses ICMP and SNMP in your network environment. See "Configuring Communication Protocol" on page 129 .
Discovery →	Use to specify the devices to be discovered. See "Discovering Your Network"

NNMi Configuration Workspaces, continued

Name	Description
Discovery Configuration	on page 194.
Discovery → Seeds	A discovery seed is a specific node that you want NNMi to discover. Discovery seeds are sometimes optional and sometimes required. See "Specify Discovery Seeds" on page 287.
Discovery → Tenants	Each Node must be assigned to a Tenant. NNMi provides a Tenant named Default Tenant. NNMi administrators can create additional Tenant objects as needed. <i>Auto-Discovery</i> is available only for the Default Tenant. See "Configure Tenants" on page 213. Note: If your network management environment includes overlapping address domains, you must configure each domain as a unique Tenant.
Discovery → Overlapping Address Mappings	If <i>static</i> Network Address Translation (NAT) is part of your network management domain, and the NNMi management server is outside of that static NAT domain, you can configure NNMi to display the NAT <i>external IP address</i> (public address) in the Mapped Address attribute of the IP Address form for a NAT <i>internal IP address</i> (such as a private IPv4 address) pair. See "Overlapping Address Mapping" on page 210.
Monitoring → Monitoring Configuration	Use to enable the NNMi State Poller. See "Monitoring Network Health" on page 378.
Monitoring → Custom Poller Configuration	Use to configure SNMP MIB Expressions that specify additional information NNMi should poll. See "Create Custom Polling Configurations" on page 478
Incidents → Incident Configuration	Use to specify the information displayed with an incident, including its name, the message you want to be displayed, the way it should be categorized, its initial status, and how you want to identify duplicate traps. See "Configuring Incidents" on page 667.
Incidents → SNMP Trap Configurations	Use to configure incidents that originate from an SNMP trap.
Incidents → Syslog Message Configurations	HP ArcSight. Use to map syslog information to a Syslog Message incident configuration.
Incidents → Management Event Configurations	Use to configure incidents that are generated from the NNMi Causal Engine.

NNMi Configuration Workspaces, continued

Name	Description
Incidents → Pairwise Configurations	Use the Pairwise Configuration to pair the occurrence of one incident with another subsequent incident. See "About Pairwise Configurations" on page 746 .
Incidents → Custom Correlation Configuration	Use to correlate groups of incidents under a Parent Incident.
Incidents → Trap Server → Trap Forwarding Configuration	Use to forward SNMP trap to other servers in your network environment. See "Configure Trap Forwarding" on page 1407 .
Incidents → Trap Server → Trap Logging Configuration	Use to configure how SNMP traps should appear in the <code>trap.log</code> and <code>trap.csv</code> log files. See "Trap Logging Configuration Form" on page 1421
Status Configuration	<p>Use to configure Node Group status calculations using either of the following methods:</p> <ul style="list-style-type: none"> Assign the Node Group the most severe status of any Node Group member. This is the default. Configure the percentage thresholds for one or more Node Group target statuses. <p>See "Configure Node Group Status" on page 352.</p>
Global Network Management	<i>(NNMi Advanced - Global Network Management feature)</i> Use to configure communication between Global Managers and Regional Managers in your network environment. See "Connecting Multiple NNMi Management Servers (NNMi Advanced)" on page 98 .
User Interface → User Interface Configuration	<p>Use to configure many user interface features:</p> <ul style="list-style-type: none"> The NNMi console timeout interval. The initial view that you want NNMi to display. Specify that NNMi users must provide one of the following in the URL for accessing NNMi: <ul style="list-style-type: none"> The Fully Qualified Domain Name (FQDN) of the NNMi management server. Any hostname or IP address associated with the NNMi management server (NNMi automatically redirects these to the FQDN)

NNMi Configuration Workspaces, continued

Name	Description
	<ul style="list-style-type: none"> Whether NNMi displays unlicensed features that require a special license, such as NNMi Advanced. <p>See "Configuring the NNMi User Interface" on page 524.</p> <p>Default Map Settings tab - Use to configure the default settings for map views. These settings can be overridden for a specific map using the Node Group Map Settings tab. See "Configure Maps" on page 549.</p> <p>Default Line Graph Settings tab - Use to configure the SNMP MIB data that you want to make available to your network operators in a graph format. This graph is available through the Actions menu and displays in real time. See "Configure Default Settings for Line Graph" on page 530.</p> <p>Tip: You can also right-click any object in a table or map view to access the items available within the Actions menu.</p>
User Interface → Node Group Map Settings	<p>- Use to specify the Node Group and background image to be used in a Node Group map. Map settings include the following:</p> <ul style="list-style-type: none"> Node group name The order in which Node Group maps should appear in the Topology workspace Minimum User Group for saving edited locations for each node in the map Refresh information Connectivity information Background image URL Background image scale
User Interface → Menus	Use to configure how menu items are nested in the NNMi console. See "Configure Menus" on page 568 .
User Interface → Menu Items	Use to make changes or additions to the items available in the Actions menu. See "Configure Menu Items" on page 568 for more information.
User Interface → Icons	Use to customize the icons associated with a Device Profile or specific Nodes. These icons appear in table views, menu items, and as foreground images on an NNMi topology map. See "Customize Device Profile Icons" on page 532 .
Security	Use to map the following objects to control access to the network:

NNMi Configuration Workspaces, continued

Name	Description
	<ul style="list-style-type: none"> • Users to User Groups • User Groups to Security Groups • Security Groups to Nodes <p>See "Configuring Security" on page 569</p>
MIBs → Loaded MIBs	Use to determine the MIBs loaded on the NNMi management server. See "Available MIBs Files and MIB Variables" on page 1498 .
MIBs → MIB Variables	Use to determine the MIB Variables available from all installed MIB files. See MIB Variable Form and "Available MIBs Files and MIB Variables" on page 1498 .
MIBs → MIB Notifications	Enables you to view the SNMP trap information, if any, that is defined by the selected MIB. See MIB Notification Form and "Load SNMP Trap Incident Configurations" on page 873 .
MIB → MIB Textual Conventions	Use to examine the format rules for the selected Textual Convention that are defined in the MIB. NNMi uses these MIB format rules to determine how to display any associated MIB variable values of type Octet String. See the MIB Textual Convention Form .
MIBs → MIB Expressions	Use to determine the MIB Expressions available for Custom Poller or Line Graphs. See "Create a Custom Poller Collection" on page 481 and "Configure SNMP Line Graph Actions" on page 1477 .
MIBs → MIB OID Types	If you find that the results of a MIB Expression displayed in a Line Graph or a Gauge or used by Custom Poller are not as expected, use the MIB OID Types configuration to override values for the following items for a MIB Object Identifier (OID). See "Override MIB OID Types" on page 1512 .
MIBs → ifTypes	Use to determine the list of available interface types. NNMi administrators use these ifType values to define Interface Groups. See "Add New ifType Values (Interface Types) to the List" on page 371 .
Device Profiles	Use to see and edit device profile information. Device profile information includes the SNMP object ID, model, and vendor. See "Configure Device Profiles" on page 323 .
Object Groups → Node Groups	Use to group your devices for viewing and monitoring purposes. See "Create Node Groups" on page 326 .
Object Groups → Interface Groups	Use to group your devices for viewing and monitoring purposes. See "Create Interface Groups" on page 356 .

NNMi Configuration Workspaces, continued

Name	Description
RAMS Servers	(<i>NNMi Advanced</i> , plus <i>HP Route Analytics Management System (RAMS) for MPLS WAN</i>) Use to configure sources of Route Analytics Management System data for NNMi to use. See " HP RAMS MPLS WAN Configuration (NNMi Advanced) " on page 1446.

Enable or Disable Configurations

Using the **Actions** menu, you can enable or disable one or more of the following configurations:

Note: When you enable or disable a configuration, NNMi assigns the value **Customer** as the Author name. See [Author form](#) for important information.

Enable or Disable NNMi Configurations

Configuration	Configuration Workspace Option
SNMP Trap Incidents	Incidents
Syslog Messages Incidents	Incidents
Management Event Incidents	Incidents
Pairwise	Pairwise Configuration
Menus	User Interface Configuration
Menu Items	User Interface Configuration

To enable an NNMi configuration:

1. Navigate to the table view of the configurations you want to change. For example, select **User Interface Configuration** from the **Configuration** workspace and select the **Menus** tab.
2. To enable a configuration, select the row representing the configuration you want to enable.
3. Select **Actions** → **Enable Configuration**.

If you are in the configuration form, NNMi selects Enabled ☒.

If you are in the table view, NNMi displays a ✓ check in the Enabled column for each instance selected.

To disable an NNMi configuration:

1. Navigate to the table view of the configurations you want to change. For example, select **User Interface Configuration** from the **Configuration** workspace and select the **Menus** tab.

2. Do one of the following:
 - a. To disable a configuration, select the row representing the configuration you want to edit.
 - b. To disable more than one configuration, press Ctrl-Click to select each row that represents a configuration instance that you want to disable.
3. Select **Actions** → **Disable Configuration**.

If you are in the configuration form, NNMi removes the check mark from Enabled ☐.





If you are in the table view, NNMi removes the ✓ check mark in the Enabled column for each instance selected.

Lookup Fields



Lookup fields have the following icon: .


The Lookup field represents an associated object instance. For example, an Incident form has an associated Source Node attribute. Information about this source node is available in and accessed through the Lookup field.

Possible Drop-Down Menu Options in Lookup Fields

Option	Description
 Show Analysis	Display Analysis Pane information for the selected object. (See Use the Analysis Pane for more information about the Analysis Pane.)
 Quick Find	Display a list of valid choices for populating the current attribute field.
 Open	Open the form for the related object instance that is currently selected in the lookup field. Review all attributes of the related object. Depending on your role, you can edit these attributes.
 New	Create a new object instance to relate to the current object.


You can use Lookup fields in a variety of ways:

- **Read-only fields - to provide additional information about the associated object.** Click  Show Analysis ([Use the Analysis Pane](#)) or  Open to see the details of this object.




- **Selection fields - to change the association to another object instance.** Click  Quick


Find to select from a list of previously configured objects ("[Use the Quick Find Window](#)" below).





Or type a case-sensitive string into the input box ("[Use Autocomplete](#)" on the next page).



- **Read-write fields - create an entirely new object instance for this association.** Click  New. An empty form opens for you to fill in, creating a new object instance.




Use the Quick Find Window

The  Quick Find option is available only in Lookup fields that are modifiable. Use the  Quick Find option to see the list of available object instances appropriate for populating the current Lookup field.

To list all existing object instances that could be related to the current object:




1. From the lookup field of interest, click the  Look up icon:



2. Select  Quick Find.

NNMi displays a table view of object instances that are available to associate with to the current object instance.

3. In the Quick Find window, do one of the following:


	Click the Clear button to remove an association with this object. The Quick Find window closes, and the current lookup field is empty.
	Select a row in the table, and click the OK button. The Quick Find window closes, and the object instance you selected populates the current lookup field.
	Click the Cancel button to return to the previous form without making any changes

Use Autocomplete

The autocomplete feature is available only in Lookup fields that are modifiable. As you type, NNMi lists the available object instances for populating the current Lookup field.

To use the autocomplete feature:

1. Start typing the first few letters (case-sensitive) of the name of the object you want to associate with the current one.



The Lookup field displays a drop-down list below the input field. This list includes all potential existing objects with names that match the letters as you enter them.



2. Use the scroll arrows or the mouse to select from the displayed list.


The selected object populates the Lookup field and is now associated with the current object.

Create a Configuration Object Instance Using the Form Toolbar

You can save time by generating a new form from within another form. The new form is based on the object type for the original form and contains only the default values set by NNMi for particular attributes for that object. Any attributes that have no default value appear blank.

This tool is useful when you want to create multiple object instances that have similar attribute values.

To create a new object instance using the form toolbar:

1. Open the form representing the object of interest.
2. From the form toolbar, click the  Save and New icon.

A new form appears that contains the default attribute values for the object type represented by the original form.

3. Select the  **Save and Close** icon to save your changes and return to the view.


Delete One or More Objects

Each row in a table view and each symbol in a map view represents an instance of the object type being displayed. For example, in a node view, each row of the table represents an instance of a node in your network.

Some NNMi users can delete object instances. For example, you might need to delete a node that is no longer being managed. See ["Delete Nodes" on page 1635](#) for more information.


To delete an object instance:

1. Select the object of interest:
 - In a table view, select the row that represents the object.
 - In a map view, click the map symbol.
 - In a form, proceed to step 2.

2. To delete the object, click the  Delete icon.

The object is deleted from the NNMi database and removed from the current view.

To delete multiple object instances:

1. Select the objects of interest:
 - In a table view, press Ctrl-Click to select each row that represents each object you want to delete.
 - In a map view, Ctrl-Click each map symbol.
2. To delete the objects, click the  Delete icon.

Note: For Node objects, you can use this method to delete up to 20 nodes at one time. To delete more than 20 nodes, see the [nnmnodedelete.ovpl](#) Reference Page.

Tip: For all other objects, you can delete any number.

Each object is deleted from the NNMi database and removed from the current view.

Related Topics

[Using Table Views](#)

[Using Map Views](#)

["Configure Whether to Delete Unresponsive Nodes" on page 233](#)

Actions Provided by NNMi

Note: (*NNMi Advanced - Global Network Management feature*) If your NNMi console is a Global Manager and the selected node is being managed by a Regional Manager (another NNMi management server in your network environment), some actions are not available.

The following tables describe the actions provided by NNMi:

[Actions Provided for Incidents](#)

[Actions Provided for Trap Logging Configuration](#)

[Actions Provided for Nodes](#)

[Actions Provided for Interfaces](#)

[Actions Provided for Addresses](#)

[Actions Provided for Cards](#)

[Actions Provided for Chassis](#)

[Actions Provided for Node Groups](#)

[Actions Provided for Interface Groups](#)

[Actions Provided for Router Redundancy Groups](#)

[Actions Provided for Router Redundancy Member](#)

[Actions Provided for Custom Polled Instances](#)

[Actions Provided for Custom Poller Collections and Report Groups](#)

[Actions Provided for Node Sensor and Physical Sensor](#)

[Actions Provided for iSPIs](#)

As shown in the table, the actions available depend on the object selected.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Note the following:

- The Default NNMi Role determines the Actions displayed.
- The Minimum NNMi Role determines the lowest NNMi Role to which the Action can be configured.
- The Default Object Access Privileges determines the Actions a user can execute.
- As the NNMi Administrator, you determine a user's NNMi Role and Object Access Privileges. See ["Configuring Security" on page 569](#) for more information.

Actions Provided for Incidents

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Node Actions	Provides access to all of the actions available for a the Incident's Source Node. See Actions Provided for Nodes for more information.	See Actions Provided for Nodes .	See Actions Provided for Nodes .
Interface Actions	Only available for incidents with the Source Object attribute value set to Interface. Provides access to all of the actions available for an interface. See Actions Provided for Interfaces for more information.	See Actions Provided for Interfaces .	See Actions Provided for Interfaces
IP Address Actions	Only available for incidents with the Source Object attribute value set to IP Address. Provides access to all of the actions available for an IP address. See Actions Provided for Addresses for more information.	See Actions Provided for IP Addresses .	See Actions Provided for IP Addresses
Node Group Map	Maps → Node Group Map Displays the lowest level Node Group map to which the Source Node belongs. For example, if the node belongs to a <i>Child</i> Node Group, the <i>Child</i> Node Group displays. See Node Group Maps .	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Incidents, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: If the Source Node is a member of more than one Node Group, NNMi displays the list of possible Node Groups. Right-click the Node Group of interest and select Maps → Node Group Map.</p> <p>If the incident's Source Object is an Island Node Group, NNMi displays the Island Node Group map. See "Island Node Groups" on page 375.</p> <p>Note: Incidents with the Source Object attribute value set to Island Node Group include Remote site in the incident message. See Island Node Group Map for more information.</p> <p>When the selected Source Node is not a member of any Node Group, and you select the Node Group Map action, NNMi displays an information message.</p>		
Path View	<p>Maps → Path View</p> <p>Displays a map showing the route between two specified nodes, using the Source Node as the starting point.</p> <p>Note: (NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in</p>	Operator Level 1/ Guest	Object Operator Level 1

Actions Provided for Incidents, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	your network that are configured with IPv6 addresses cannot be displayed on Path View maps.		
Source Node	Source Node Displays the Node form of the Source Node object instance.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Source Object	Displays the form of the source object instance.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Node Group Members	Node Group Members <i>Island Node Group incidents only.</i> Displays a table of the nodes that are members of the Island Node Group that is the Source Object for the selected incident. See " Island Node Groups " on page 375. Note: Incidents with the Source Object attribute value set to Island Node Group include Remote site in the incident message.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Graph Custom Poller Results	Graph Custom Poller Results Graphs all MIB expressions from each of the Custom Poller Collections associated with the selected incident's Source Node.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Ping	Node Access → Ping Tests whether a node or IP address is reachable using the ping command from the NNMi console.	Operator Level 1/Operator Level 1	Object Operator Level 1
Open Web Page	Node Access → Open Web Page	Operator Level 1/Operator Level 1	Object Operator

Actions Provided for Incidents, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	Opens the default Web page for the selected node.		Level 1
Trace Route	Node Access → Trace Route Trace the route path to identify bottlenecks along the destination path provided.	Operator Level 1/Operator Level 1	Object Operator Level 1
Telnet	Node Access → Telnet Establish a connection to a node to view or change configuration information	Operator Level 2/Operator Level 2	Object Operator Level 2
Secure Shell	Node Access → Secure Shell Establish a connection to a node to view or change configuration information.	Operator Level 2/Operator Level 2	Object Operator Level 2
Delete	Delete Deletes the selected Incident object or objects (maximum 20). To delete more than 20 nodes, see the nnmnodedelete.ovpl Reference Page.	Administrator/Administrator	Object Administrator
In Progress	Change Lifecycle → In Progress Changes the lifecycle state to In Progress for the selected incident.	Operator Level 1/Operator Level 1	Object Operator Level 1
Completed	Change Lifecycle → Completed Changes the lifecycle state to Completed for the selected incident.	Operator Level 1/Operator Level 1	Object Operator Level 1
Close	Change Lifecycle → Close Changes the lifecycle state to Closed for the selected incident.	Operator Level 1/Operator Level 1	Object Operator Level 1
Assign Incident	Assign → Assign Incident Displays a list of registered users to select from. This user name	Operator Level 1/Operator Level 1	Object Operator Level 1

Actions Provided for Incidents, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	appears in the Assigned To column of the incident view.		
Own Incident	Assign → Own Incident Assigns the incident to the current user. This user name appears in the Assigned To column of the incident view.	Operator Level 1/Operator Level 1	Object Operator Level 1
Unassign Incident	Assign → Unassign Incident Removes the user name from the Assigned To column of the incident view.	Operator Level 1/Operator Level 1	Object Operator Level 1
Incident Configuration Reports	Displays a report of the configuration settings that define this Incident. See " View an Incident Configuration Report " on page 1403 for more information.	Administrator/Administrator	Object Administrator
Open Incident Configuration	Displays the selected Incident's configuration form.	Administrator/Administrator	Object Administrator
Run Diagnostics	<p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – click here for more information.</p> <p>When installed, NNM iSPI NET gathers diagnostic information from the Source Node.</p>	Operator Level 1/Operator Level 1	Object Operator Level 1

Actions Provided for Trap Logging Configuration

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Show SNMP Trap Configuration	Displays the SNMP Trap Incident Configuration form, if any, for the current Trap Logging Configuration. The Configuration form displayed is for the SNMP Trap Incident associated with the Trap Logging Configuration.	Administrator/Administrator	Object Administrator

Actions Provided for Nodes

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Layer 2 Neighbor View	Maps → Layer 2 Neighbor View Represents your network's physical connections and LAN switch traffic routes.	Operator Level 1/ Guest	Object Operator Level 1
Layer 3 Neighbor View	Maps → Layer 3 Neighbor View Represents your network's router traffic.	Operator Level 1/ Guest	Object Operator Level 1
Node Group Map	Maps → Node Group Map Displays the lowest level Node Group map to which the selected Node belongs. For example, if the node belongs to a <i>Child</i> Node Group, the <i>Child</i> Node Group displays. See Node Group Maps . If the Node is a member of more than one Node Group, NNMi displays the list of possible Node Groups. Right-click the Node Group of interest and select Maps > Node Group Map . When the selected Source Node is not a member of any Node Group, and you select the Node Group Map action, NNMi displays an information message.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Path View	Maps → Path View Displays a map showing the route between two specified nodes, using the Source Node as the	Operator Level 1/ Guest	Object Operator Level 1

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>starting point.</p> <div> <p>Note: (NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.</p> </div>		
Graphs	<p>Displays a pre-configured graph of real-time data for a selected node.</p> <p>NNMi provides a set of Line Graph that are configured to display real-time SNMP data. See Line Graphs Provided by NNMi for more information.</p> <p>Line Graph graphs can also come from the following sources:</p> <ul style="list-style-type: none"> Your NNMi administrator might configure additional graphs. NNM iSPI software. 	Operator Level 1/ Guest	Object Operator Level 1
Ping (from server)	<p>Node Access → Ping (from server)</p> <p>Tests whether a node is reachable using the ping command.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Ping issues an ICMP request from the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Ping accesses that Regional Manager (NNMi management server) and issues the ICMP request. 	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Open Web Page	<p>Node Access → Open Web Page</p> <p>Opens the default Web page for the selected node.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Trace Route (from server)	<p>Node Access → Trace Route (from server)</p> <p>Traces a route path from the using the traceroute command.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Node Access → Trace Route issues a request from the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Node Access → Trace Route accesses that Regional Manager (NNMi management server) and issues the request in a manner appropriate for the operating system in use on the Regional Manager. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>(SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Telnet (from client)	<p>Node Access → Telnet (from client)</p> <p>Uses Transmission Control Protocol (TCP) protocol from the computer that launched your current browser (not the NNMi management server) to open a Telnet (teletype network) virtual terminal command-line interface from the selected node or Source Node of the selected object. See Establish Contact with a Node.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Secure Shell (from client)	<p>Node Access → Secure Shell (from client)</p> <p>Uses Secure Shell (SSH) protocol from the computer that launched your current browser (not the NNMi management server) to open a Secure Shell virtual terminal command-line interface from the selected node or Source Node of the selected object. See Establish Contact with a Node.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Status Poll	<p>Polling → Status Poll</p> <p>Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for each selected Node (maximum 10). A window for each Node displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.</p> <p>Note the following:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<ul style="list-style-type: none"> Status Poll might cause an object's Status to be updated. To see the resulting Node status, see Verify Current Status of a Device. Using Actions → Status Poll does not affect the timing of the Polling interval configured for the device. <p>Tip: The <code>nnmstatuspoll.ovpl</code> command line tool does the same thing as Actions → Status Poll.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Status Poll requests that the Global Manager (NNMi management server) perform a status poll on the node. Node managed by a Regional Manager = Actions → Status Poll requests that the Regional Manager perform a status poll on the node, the Global Manager displays the results. Latest Status Poll results are available on both NNMi management servers (Global and Regional). <p>Note: You do not need to sign-in to the Regional Manager.</p>		
Configuration Poll	<p>Polling → Configuration Poll</p> <p>Runs a real-time configuration check of the selected device to detect any changes since the last discovery cycle.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Polling → Configuration Poll results are provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Polling → Configuration Poll requests an updated <i>copy</i> of the configuration information from the Regional Manager, then the Global Manager displays the results. <p>Note: You do not need to sign-in to the Regional Manager.</p>		
Communication Settings	<p>Configuration Details → Communication Settings</p> <p>Displays the communication configuration information for the selected node.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Communication Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Communication Settings accesses that Regional Manager (NNMi management server) and requests the report. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single</p>	Administrator/ Administrator	Object Administrator


Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Monitoring Settings	<p>Configuration Details → Monitoring Settings</p> <p>Displays the Monitoring Settings report about a particular node's SNMP Agent.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Monitoring Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Monitoring Settings accesses that Regional Manager (NNMi management server) and requests the report. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
List	MIB Information → List Supported MIBs	Operator Level	Object




Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Supported MIBs	Display a list of the MIBs (Management Information Base) supported by a selected node. See Determine which MIBs a Specific Node Supports for more information.	2/ Operator Level 1	Operator Level 2
MIB Browser	MIB Information → MIB Browser The Using the MIB Browser , run SNMP Walk and Set commands on a particular node in your network environment and display the results.	Operator Level 2/ Operator Level 1	Object Operator Level 2 for SNMP Walk Object Administra- tor for SNMP Set
Node Group Membership	Create or modify a Node Group using the selected nodes. This action also enables you to remove Node Groups. See "Create Node Groups From the Actions Menu" on page 347	Operator Level 1/ Operator Level 1	Object Administra- tor
Custom Attributes	Add Custom Attributes to the selected nodes or interfaces. See "Add Custom Attributes Using the Actions Menu" on page 546	Administrator/ Administrator	Object Administra- tor
Open from Regional Manager	Issues a request to the Regional Manager (the NNMi management server that is responsible for monitoring the selected node) asking to display the Node form of the selected object. Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i> , which is available at: http://h20230.www2.hp.com/selfsolve/-manuals .	Operator Level 1/ Operator Level 1	Object Operator Level 1
Regional	Issues a request to the Regional Manager (the	Operator Level	Object



Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Manager Console	<p>NNMi management server that is responsible for monitoring the selected node) asking to display the NNMi console.</p> <p>Note: You must sign into that Regional Manager unless your network environment provides Single Sign-On (SSO) to that Regional Manager.</p>	1/ Operator Level 1	Operator Level 1
Delete	<p>Deletes the selected object or objects.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Delete removes the Node object (and all related object data) from the Global Manager's database. Node managed by a Regional Manager = Actions → Delete removes the <i>copy of the Node object</i> (and all related object data) from the Global Manager's database. <p>Note: To delete this Node object from the Regional Manager's database, click Actions → Open from Regional Manager and delete the Node object. You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Administrator/ Administrator	Object Administrator
Manage	Management Mode →  Manage	Operator Level	Object



Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Changes the Management Mode of the selected node to  Managed. Leaves the Direct Management Mode of any contained interfaces and addresses unchanged.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>	2/ Operator Level 2	Operator Level 2
Manage (Reset All)	<p>Management Mode →  Manage (Reset All)</p> <p>Changes the Management Mode of the objects associated with the selected node (IP Addresses, Interfaces, etc) to  Inherited.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = 	Operator Level 2/ Operator Level 2	Object Operator Level 2



Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Actions → Management Mode → Manage (Reset All) modifies the Node object plus all associated interface objects and address objects in the Global Manager's database.</p> <ul style="list-style-type: none"> Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Not Managed	<p>Management Mode →  Not Managed</p> <p>Changes the Management Mode of the selected node to  Not Managed. Leaves the Direct Management Mode of any associated Interfaces and IP Addresses unchanged.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Unmanage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. 	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Out of Service	<p>Management Mode →  Out of Service</p> <p>Changes the Management Mode of the selected node to  Out of Service. Leaves the Direct Management Mode of any associated Interfaces and IP Addresses unchanged.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Out of Service modifies the Node object in the Global Manager’s database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Recalculate Out of Sync Physical Components	<p>Recalculates the Management Mode of all physical components that are in the hierarchy of the selected node.</p> <ul style="list-style-type: none"> The child physical components must have a Direct Management Mode of Inherited The Management Mode for all of the physical components in the node hierarchy are recalculated. The Management Mode of any Physical Sensor object that resides on a physical component in the node hierarchy is also recalculated. See Physical Sensor View for more information. 	NNMi Administrator	NNMi Administrator
Schedule Node Outage	<p>Management Mode →  Schedule Node Outage</p> <p>Opens the Scheduled Node Outage dialog, allowing you to notify NNMi of a past, present, or future event (Schedule Outage or Record a Past Outage). See Scheduling Outages for Nodes or Node Groups.</p> <p>During the Scheduled Outage:</p> <ul style="list-style-type: none"> NNMi does not discover or monitor any aspect of the Node. Changes the Management Mode of the selected node to  Out of Service. Leaves the Direct Management Mode of any associated Interfaces and IP Addresses unchanged. 	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> If the Node is managed by the Global Manager = applying Actions → Management Mode → Schedule Node Outage modifies the Node object in the Global Manager's database. The information is not sent to any Regional Manager. If the Node is managed by a Regional Manager = you must first use Actions → Open from Regional Manager prior to scheduling the outage on Regional Manager that is responsible for this Node. Any resulting change in a Node's Management Mode is communicated to the Global Manager. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>		
Run Diagnostics	<div style="background-color: #f0f0f0; padding: 10px; margin-bottom: 10px;"> <p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – click here for more information.</p> </div> <p>When installed, NNM iSPI NET gathers diagnostic information on the current node.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Nodes, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Show Attached End Nodes	<p>Displays information about the end nodes that NNMi determines are attached to the specified switch.</p> <p><i>(NNMi Advanced)</i> If the Global Network Management feature is enabled and you are signed into a Global Manager: The results are based on the current information in the NNMi database of the Global Manager (which contains <i>copies of Node objects</i> from all Regional Managers).</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1




Actions Provided for Interfaces

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Graphs	<p>Displays a pre-configured graph of real-time data for a selected interface.</p> <p>NNMi provides a set of Line Graphs that are configured to display real-time SNMP data. See Line Graphs Provided by NNMi for more information.</p> <p>Line Graphs can also come from the following sources:</p> <ul style="list-style-type: none"> Your NNMi administrator might configure additional graphs. NNMi SPI software. 	Operator Level 1/ Guest	Object Operator Level 1
Status Poll	<p>Polling → Status Poll</p> <p>Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for each selected Interface. A window for each Interface displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Interfaces, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note the following:</p> <ul style="list-style-type: none"> Status Poll might cause an object's Status to be updated. To see the resulting Interface Status, see Verify Current Status of a Device. Using Actions → Status Poll does not affect the timing of the Polling interval configured for the device. <p>Tip: The <code>nnmstatuspoll.ovpl</code> command line tool does the same thing as Actions → Status Poll.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Status Poll requests that the Global Manager (NNMi management server) perform a status poll on the node. Node managed by a Regional Manager = Actions → Status Poll requests that the Regional Manager perform a status poll on the node, the Global Manager displays the results. Latest Status Poll results are available on both NNMi management servers (Global and Regional). <p>Note: You do not need to sign-in to the Regional Manager.</p>		
Monitoring Settings	<p>Configuration Details → Monitoring Settings</p> <p>Displays the Monitoring Settings report about a particular Interface.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Custom Attributes	<p>Add Custom Attributes to the selected nodes or interfaces. See "Add Custom Attributes Using the Actions Menu" on page 546</p>	Administrator/ Administrator	Object Administrator


Actions Provided for Interfaces, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Manage	<p>Management Mode → Manage</p> <p>Changes the Direct Management Mode of the interface to  Inherited. Leaves the Direct Management Mode of any associated addresses unchanged.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Manage (Reset All)	<p>Management Mode → Manage (Reset All)</p> <p>Changes the Management Mode of the interface to  Inherited. Changes the Direct Management Mode of any associated addresses to  Inherited.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Interfaces, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage (Reset All) modifies the Node object plus all associated interface objects and address objects in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve-/manuals.</p>		
Not Managed	<p>Management Mode → Not Managed</p> <p>Changes the Management Mode of the interface to Not Managed. Leaves the Direct Management Mode of any associated addresses unchanged.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Unmanage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. 	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Interfaces, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve-/manuals.</p>		
Out of Service	<p>Management Mode → Out of Service</p> <p>Changes the Management Mode of the interface to  Out of Service.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Out of Service modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Interfaces, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	http://h20230.www2.hp.com/selfsolve- manuals.		

Actions Provided for Addresses

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Layer 2 Neighbor View	Maps → Layer 2 Neighbor View Represents your network's physical connections and LAN switch traffic routes.	Operator Level 1/ Guest	Object Operator Level 1
Layer 3 Neighbor View	Maps → Layer 3 Neighbor View Represents your network's router traffic.	Operator Level 1/ Guest	Object Operator Level 1
Node Group Map	<p>Maps → Node Group Map</p> <p>Displays the lowest level Node Group map to which the Node that is hosting the selected IP Address belongs.</p> <p>For example, if the Node belongs to a <i>Child</i> Node Group, the <i>Child</i> Node Group displays. See Node Group Maps.</p> <p>If the Node that is hosting the selected IP address belongs to multiple Node Groups, NNMi displays the list of possible Node Groups. Right-click the Node Group of interest and select Maps → Node Group Map.</p> <p>When the selected Source Node is not a member of any Node Group, and you select the Node Group Map action, NNMi displays an information message.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Path View	<p>Displays a map showing the route between two specified nodes, using the selected IP Address as the starting point.</p> <p>Note: (NNMi Advanced) Path View works</p>	Operator Level 1/ Guest	Object Operator Level 1

Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.</p>		
Ping (from server)	<p>Node Access → Ping (from server)</p> <p>Tests whether the Node that is hosting the selected IP Address is reachable using the ping command.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Ping issues an ICMP request from the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Ping accesses that Regional Manager (NNMi management server) and issues the ICMP request. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Open Web Page	Opens the default Web page for the selected IP Address.	Operator Level 1/ Operator	Object Operator

Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
		Level 1	Level 1
Trace Route (from sever)	<p>Node Access → Trace Route (from sever)</p> <p>Traces a route path using the traceroute command.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Node Access → Trace Route issues a request from the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Node Access → Trace Route accesses that Regional Manager (NNMi management server) and issues the request in a manner appropriate for the operating system in use on the Regional Manager. <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Telnet (from client)	<p>Node Access → Telnet (from client)</p> <p>Uses Transmission Control Protocol (TCP) protocol from the computer that launched your current browser (not the NNMi management server) to open a Telnet (teletype network) virtual terminal command-line interface from the selected IP Address. See Establish Contact with</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2


Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	a Node.		
Secure Shell (from client)	<p>Node Access → Secure Shell (from client)</p> <p>Uses Secure Shell (SSH) protocol from the computer that launched your current browser (not the NNMi management server) to open a Secure Shell virtual terminal command-line interface from the selected IP Address. See Establish Contact with a Node.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Communication Settings	<p>Configuration Details → Communication Settings</p> <p>Displays the communication configuration information for the Node that is hosting the selected IP Address.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Communication Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Communication Settings accesses that Regional Manager (NNMi management server) and requests the report. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at:</p>	Administrator/ Administrator	Object Administrator


Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Monitoring Settings	<p>Configuration Details → Monitoring Settings</p> <p>Displays the Monitoring Settings report about a particular IP address.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Monitoring Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Monitoring Settings accesses that Regional Manager (NNMi management server) and requests the report. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Status Poll	<p>Polling → Status Poll</p> <p>Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for the Node that is hosting the selected</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2


Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	IP Address. A window for each IP Address displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.		
Configuration Poll	<p>Polling → Configuration Poll</p> <p>Runs a real-time configuration check of the Node that is hosting the selected IP Address to detect any changes since the last discovery cycle.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Polling → Configuration Poll results are provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Polling → Configuration Poll requests an updated copy of the configuration information from the Regional Manager, then the Global Manager displays the results. <p>Note: You do not need to sign-in to the Regional Manager.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Manage	<p>Management Mode → Manage</p> <p>Changes the Direct Management Mode of the address to  Inherited.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage 	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>modifies the Node object in the Global Manager's database.</p> <ul style="list-style-type: none"> Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>		
Not Managed	<p>Management Mode → Not Managed</p> <p>Changes the management mode of the address to  Not Managed.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Unmanage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional</p> </div>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Out of Service	<p>Management Mode → Out of Service</p> <p>Changes the management mode of the address to  Out of Service.</p> <p>(NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Out of Service modifies the Node object in the Global Manager’s database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2


Actions Provided for Addresses, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	ve/manuals.		



Actions Provided for Cards

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Status Poll	Polling → Status Poll Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for each selected card (maximum 10). A window for each card displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.	Operator Level 2/ Operator Level 2	Object Operator Level 2
Monitoring Settings	Configuration Details → Monitoring Settings Displays the Monitoring Settings report about a particular card. <i>(NNMi Advanced)</i> If the Global Network Management feature is enabled and you are signed into a Global Manager: <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Monitoring Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Monitoring Settings accesses that Regional Manager (NNMi management server) and requests the report. 	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Cards, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Manage	<p>Management Mode → Manage</p> <p>Changes the Direct Management Mode of the card to  Inherited.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Cards, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Not Managed	<p>Management Mode → Not Managed</p> <p>Changes the management mode of the card to  Not Managed.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Unmanage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Out of Service	<p>Management Mode → Out of Service</p> <p>Changes the management mode of the card to  Out of Service.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2



Actions Provided for Cards, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Out of Service modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Recalculate Out of Sync Physical Components	<p>Recalculate the Management Mode of all physical components that are in the node hierarchy of the selected card.</p> <ul style="list-style-type: none"> The child physical components must have a Direct Management Mode of Inherited The Management Mode for all of the physical components in the node hierarchy are recalculated. The Management Mode of any Physical Sensor object that resides on a physical component in the node hierarchy is also recalculated. See Physical Sensor View for more information. 	NNMi Administrator	NNMi Administrator


Actions Provided for Chassis

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Status Poll	<p>Polling → Status Poll</p> <p>Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for each selected chassis (maximum 10). A window for each chassis displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Monitoring Settings	<p>Configuration Details → Monitoring Settings</p> <p>Displays the Monitoring Settings report about a particular chassis.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Configuration Details → Monitoring Settings opens a report, provided by the Global Manager (NNMi management server). Node managed by a Regional Manager = Actions → Configuration Details → Monitoring Settings accesses that Regional Manager (NNMi management server) and requests the report. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolv-</p> </div>	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Chassis, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	e/manuals.		
Manage	<p>Management Mode → Manage</p> <p>Changes the Direct Management Mode of the chassis to  Inherited.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Manage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Not Managed	<p>Management Mode → Not Managed</p> <p>Changes the management mode of the chassis to  Not Managed.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Chassis, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Unmanage modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. <div style="border: 1px solid black; padding: 10px; margin-top: 10px;"> <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div>		
Out of Service	<p>Management Mode → Out of Service</p> <p>Changes the management mode of the chassis to  Out of Service.</p> <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled and you are signed into a Global Manager:</p> <ul style="list-style-type: none"> Node managed by the Global Manager = Actions → Management Mode → Out of Service modifies the Node object in the Global Manager's database. Node managed by a Regional Manager = Use Actions → Open from Regional Manager to set Management Mode on the Regional Manager that is responsible for this Node. 	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Chassis, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		
Recalculate Out of Sync Physical Components	<p>Recalculates the Management Mode of all physical components that are in the node hierarchy of the selected chassis.</p> <ul style="list-style-type: none"> The child physical components must have a Direct Management Mode of Inherited The Management Mode for all of the physical components in the node hierarchy are recalculated. The Management Mode of any Physical Sensor object that resides on a physical component in the node hierarchy is also recalculated. See Physical Sensor View for more information. 	NNMi Administrator	NNMi Administrator

Actions Provided for Node Groups

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Node Group Map	<p>Maps → Node Group Map</p> <p>Displays a current map of all nodes that belong to the selected Node Group.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Preview	Node Group Details → Preview Members	Operator Level 1/	Object

Actions Provided for Node Groups, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Members	(Current Group Only) Displays a list of all nodes that belong to the selected Node Group as well as all of its Child Node Groups.	Operator Level 1	Operator Level 1
Show Members	Node Group Details → Show Members (Include Child Groups) Displays a list of all nodes that belong to the selected Node Group.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Show All Incidents	Node Group Details → Show All Incidents Checks for any Incidents associated with the selected Node Group.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Show All Open Incidents	Node Group Details → Show All Open Incidents Checks for any open Incidents associated with the selected Node Group.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Status Details	Node Group Details → Status Details Displays a report about the status of all members of the selected Node Group. See Check Status Details for a Node Group .	Operator Level 1/ Operator Level 1	Object Operator Level 1
Schedule Group Members Outage	Management Mode → Schedule Group Members Outage Opens the Scheduled Node Outage dialog, allowing you to notify NNMi of a past, present, or future event (Schedule Outage or Record a Past Outage). NNMi does not discover or monitor any aspect of the Nodes in the list during the Scheduled Outage. The list of Nodes is not dynamic. You can delete or add Nodes as you wish. If the Node Group membership changes prior to the Scheduled Outage, the Node list is not dynamically updated. (NNMi Advanced) If the Global Network Management feature is enabled and you are signed into a Global Manager: <ul style="list-style-type: none">If the Node is managed by the Global Manager = applying Actions → Management Mode →	Operator Level 2/ Operator Level 2	Object Operator Level 2

Actions Provided for Node Groups, continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
	<p>Schedule Node Outage modifies the Node object in the Global Manager's database. The information is not sent to any Regional Manager.</p> <ul style="list-style-type: none"> If the Node is managed by a Regional Manager = you must first use Actions → Open from Regional Manager prior to scheduling the outage on Regional Manager that is responsible for this Node. Any resulting change in a Node's Management Mode is communicated to the Global Manager. <p>Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p>		

Actions Provided for Interface Groups

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Show Members	<p>Show Members</p> <p>Displays a list of all nodes that belong to the selected Node Group.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Router Redundancy Groups

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Ping	<p>Node Access → Ping</p> <p>Tests whether the node is reachable using the ping command from the NNMi console.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Router Redundancy Group Members

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Monitoring Settings	Configuration Details → Monitoring Settings Displays the Monitoring Settings report about a particular Router Redundancy Member.	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Custom Polled Instances

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Graph Polled Instance	Graphs the line representing the Custom Poll results for the selected Custom Polled Instance. See Display an Line Graph for a Custom Polled Instance .	Operator Level 1/ Operator Level 1	Object Operator Level 1




Actions Provided for Custom Poller Collections and Report Groups (NNM iSPI Performance for Metrics only)

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information .			
Show Report Configuration	Displays the Report Collection configuration associated with the selected Custom Poller Collection or Report Group. See Create a Report Group and Create a Report Collection for more information.	Administrator/ Administrator	Object Administrator
Reporting - Report Menu	Launches the Network Performance Server (NPS) console to show reports.	Operator Level 1/ Operator Level 1	Object Operator Level 1
Reporting - Path Health	Launches the NPS console to show the report of the health of the network path displayed by Path View. This action is enabled only on the Path View.	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Custom Poller Collections and Report Groups (NNM iSPI Performance for Metrics only), continued

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Sync Interface and Node Groups	Forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance for Metrics more quickly than the default time frame.	Operator Level 1/ Operator Level 1	Object Operator Level 1

Actions Provided for Node Sensor and Physical Sensor

Action	Description	NNMi Role Default/Minimum	Default Object Access Privilege
Status Poll	<p>Polling → Status Poll</p> <p>Instructs NNMi to gather real-time data for all the information that NNMi uses to calculate Status for each selected sensor.</p> <p>A window for each selected sensor displays with a report about which information was gathered.</p> <p>The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See "Monitoring Network Health" on page 378 for more information.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Monitoring Settings	<p>Configuration Details → Monitoring Settings</p> <p>Displays the Monitoring Settings report about the sensor. See "Verify the Monitoring Settings" on page 474 and View the Monitoring Configuration Details.</p>	Operator Level 1/ Operator Level 1	Object Operator Level 1
Manage	<p>Management Mode → Manage</p> <p>Changes the Direct Management Mode of the sensor to  Inherited.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Not Managed	<p>Changes the Management Mode of the sensor to  Not Managed.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2
Out of Service	<p>Changes the Management Mode of the sensor to  Out of Service.</p>	Operator Level 2/ Operator Level 2	Object Operator Level 2

About Environment Variables

These are the default values for NNMi environment variables. Actual values depend on the selections made during NNMi installation. See the [nnm.envvars](#) Reference Page for more information.

Operating System	Environment Variable Values
Windows Server 2008 R2	<p>%NnmInstallDir% = <drive>\Program Files(x86)\HP\HP BTO Software\ %NnmDataDir% = <drive>\ProgramData\HP\HP BTO Software\ <drive> is the location where NNMi was installed.</p> <p>Note: On Windows systems, the NNMi installation process creates these environment variables so they are always available.</p>
Linux	<p>\$NnmInstallDir = /opt/OV/ \$NnmDataDir = /var/opt/OV/</p> <p>Note: On Linux systems, you must manually create these environment variables if you want to use them. See the HP Network Node Manager i Software Deployment Reference, which is available at: http://h20230.www2.hp.com/selfsolve/manuals and the nnm.envvars Reference Page for more information.</p>

NNMi Processes and Services

NNMi is built on a group of processes and services. For information about each process or service, see the following:

- ["About Each NNMi Process" on the next page](#)
- ["About Each NNMi Service" on page 88](#)

To verify that everything is running properly, you can use the [ovstatus](#) command:

- ["Verify that NNMi Processes Are Running" on the next page](#)

About Each NNMi Process

HP Network Node Manager Processes

Process Name	Description
OVsPMD	The control process that manages all the other NNMi processes.
ovjboss	The process that controls the NNMi application server that contains all of the NNMi Services (see "About Each NNMi Service" on the next page for more information).
nnmaction	The process that controls the Action Server. The NNMi Action Server runs any actions configured for incidents. See "Configure an Action for an Incident" on page 847 for more information about incident actions. See also the nnmaction Reference Page for more information
nmsdbmgr	NMS Database Manager. Controls the NNMi embedded database, including periodic database connectivity testing.

Verify that NNMi Processes Are Running

After you install Network Node Manager, a group of processes run on the NNMi management server.

To verify that all NNMi processes are running, do one of the following:

1. Select **Tools** → **NNMi Status** to display a report.
2. At the command line, type: **ovstatus -c**

See the [ovstatus](#) Reference Page for more information.

Review the list of processes to ensure that all are running. For more information about each process, see ["About Each NNMi Process" above](#).

Stop or Start an NNMi Process

You can stop and start NNMi processes from the command line. See the [ovstop](#) and [ovstart](#) Reference Pages for more information.

Caution: If your NNMi management server participates in a high availability (HA) environment, under certain circumstances, you should not use `ovstop` or `ovstart`. Before using either of these commands, see the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To stop or start an NNMi process:

At the command line, type the appropriate command (see ["About Each NNMi Process" above](#)):

ovstop <process name>

ovstart <*process name*>

Note: If you use **ovstop** and **ovstart** without providing a process name, NNMi stops and starts all NNMi processes.

To generate a list of process names, see ["Verify that NNMi Processes Are Running" on the previous page.](#)

About Each NNMi Service

NNMi Services run inside the **ovjboss** process. The **ovjboss** process controls the NNMi application server that contains all of the NNMi services.

HP Network Node Manager Services

ovjboss Service Name	Description
CommunicationModelService	Creates the cache for communication configuration and listens for changes.
CommunicationParametersStatsService	Tracks internal statistics for measuring SNMP and ICMP configuration performance.
CustomPoller	Provides MIB instance polling to augment out-of-the-box state polling (performed by StatePoller). Enables users to create configurations based on dynamic grouping. Data collected by CustomPoller can be consumed by the NNM iSPI Performance for Metrics.
IslandSpotterService	Automatically discovers any Island Node Groups using Layer 2 connectivity information in the topology. An Island Group is a group of fully-connected nodes discovered by NNMi, and NNMi determines this group is not connected to the rest of the topology.
ManagedNodeLicenseManager	Responsible for ensuring that the number of managed nodes does not exceed the NNMi licensed capacity limit.
MonitoringSettingsService	Calculates how to monitor each device based on the Monitoring Configuration settings.
NamedPoll	NMS Named Poll Service. Used to trigger immediate

HP Network Node Manager Services, continued

ovjboss Service Name	Description
	state polls for monitored objects. Used by the Causal Engine ¹ during neighbor analysis and interface up/down investigations.
NnmTrapService	Used by trapd to receive traps from the standalone Operating System TrapReceiver process and forwards them to events.
NmsApa	NMS Active Problem Analyzer (APA) service determines the root cause of network problems and reports the root cause to the NMS Event Service. The NNMi APA service depends on the Causal Engine ² .
NmsCustomCorrelation	Custom Correlation Service. Enables the NNMi administrator to correlate one or more child incidents under an existing incident or a new parent incident.
NmsDisco	<p>NMS Discovery Service. Adds new devices to the database and keeps the configuration of the managed devices up to date in the database by periodically rechecking the configuration of the devices.</p> <p>State Poller uses the Discovery service results to determine what to monitor.</p> <p>The Causal Engine³ depends on the Discovery service to monitor node configurations. The Causal Engine uses the configuration information when calculating status and root cause.</p> <p>NNMi uses the information provided by the Discovery service to maintain current device configuration</p>

¹The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an Origin of NNMi in your incident views.

²The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an Origin of NNMi in your incident views.

³The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an Origin of NNMi in your incident views.

HP Network Node Manager Services, continued

ovjboss Service Name	Description
	information.
NmsEvents	NMS Events Service. Populates and manages the information displayed in the incident table. The information displayed comes from the other NNMi services that are running on your system. The incidents are filtered so you see only the most important information about your network.
NmsEventsConfiguration	Handles incident configuration changes.
NmsExtensionNotificationService	Responsible for applications that are integrated into NNM using the extension deployment model.
NmsTrapReceiver	Used by NNMi events to receives traps from the NnmTrapService and sends them to the events pipeline. For information about the standalone TrapReceiver service that is started automatically by the Operating System, see NNMi TrapReceiver Process in the "NNMi Incidents" chapter of the HP Network Node Manager i Software Deployment Reference for more information.
PerformanceSpiConsumptionManager	Verifies licensing capacity for HP Network Node Manager iSPI Performance for Metrics Software.
SpmddjbossStart	The SpmddjbossStart service interacts with the OVSPMD process during startup (ovstart), shutdown (ovstop), and reporting on the status of the ovjboss services (ovstatus -v ovjboss). Caution: If your NNMi management server participates in a high availability (HA) environment, under certain circumstances, you should not use ovstop or ovstart . Before using either of these commands, see the <i>HP Network Node Manager i Software Deployment Reference</i> , which is available at: http://h20230.www2.hp.com/selfsolve/manuals .
StagedIcmp	Used by the State Poller to ping IP addresses using the Internet Control Message Protocol (ICMP). Also used by auto-discovery if Ping Sweep is enabled.
StagedSnmp	Used by the State Poller and Discovery to perform

HP Network Node Manager Services, continued

ovjboss Service Name	Description
	Simple Network Management Protocol (SNMP) read-only queries.
StatePoller	NMS State Poller Service. State Poller collects measurements that assess the current state of discovered devices. This information is provided for the Causal Engine ¹ to use when calculating device health.
TrapConfigurationServices	Merges configuration changes between the NNMi database and Trap Server.
TrapPropertiesService	Handles properties of the Trap Server.
TrustManager	Manages the trust information that is used when making trust decisions. Decides whether credentials presented by a peer should be accepted.

HP Network Node Manager iSPI Network Engineering Toolset Software Services (NNM iSPI NET)

ovjboss Service Name	Description
RbaManager	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- click here for more information.</div> <div>Tracks internal statistics and provides performance counters related to diagnostic flow execution using HP Operations Orchestration servers through the HP Network Node Manager iSPI Network Engineering Toolset Software. See Rba.</div>

Verify that NNMi Services are Running

After you install Network Node Manager, a group of services run on the NNMi management server. For information about each service, see ["About Each NNMi Service" on page 88](#).

To verify that all NNMi services are running, do one of the following:

¹The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an Origin of NNMi in your incident views.

- Select **Tools** → **NNMi Status** to display a report.
- At the command line, type:

ovstatus -v ovjboss

See the [ovstatus](#) Reference Page for more information.

Review the list of services to ensure that all are running.

"Service is started" means this service is working properly.

"Service is stopped" means this service/process is not running.

If you see any of the messages in this list, investigate the log files and look for the keyword **Exception** (within the log file for the parent ovjboss process and the log file for the specific service):

"Service is in created state"

"Service is in failed state"

"Service is in registered state"

"Service is in destroyed state"

"Service is in started state"

"Service is in starting state"

"Service is in stopped state"

"Service is in stopping state"

"Service is in unregistered state"

Log files are found in the following location. If your NNMi management server participates in a high availability (HA) environment, [click here for more information](#):

1. Before opening the log file, first identify the HA_MOUNT_POINT for your NNMi environment.
2. At the command line, type (see "[About Environment Variables](#)" on page 86 for more information):

Windows:

```
%NnmInstalLDir%/misc/nnm/ha/nnmhaclusterinfo.ovpl NNM -config -get HA_MOUNT_POINT
```

Linux:

```
$NnmInstalLDir/misc/nnm/ha/nnmhaclusterinfo.ovpl NNM -config -get HA_MOUNT_POINT
```

3. At the command line, type the following (/DataDir/ is the literal path):

```
<HA_MOUNT_POINT>/DataDir/log/nnm
```

- **Windows:**

```
%NnmDataDir%\log\nnm\<name>.%g
```


- **Linux:**

`$NnmDataDir/log/nnm/<name>.%g.`

%g represents the archive number of the archived log file

The parent ovjboss process generates the following log files: `ovjboss.log` and `ovjboss.old.log`.

Note: Each restart creates a new `ovjboss.log` and overwrites the `ovjboss.old.log`.

Stop or Start NNMi Services

You can stop or start all NNMi services at the same time. You cannot start and stop most individual services. See the [ovstop](#) and [ovstart](#) Reference Page for more information.

Caution: If your NNMi management server participates in a high availability (HA) environment, under certain circumstances, you should not use `ovstop` or `ovstart`. Before using either of these commands, see the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To stop or start the NNMi services:

At the command line, type the command:

`ovstop`

`ovstart`

Note: The `ovstop` command ignores the TrapReceiver service. If you need to stop this service, See "NNMi Incidents" in the *HP Network Node Manager i Software Deployment Reference* for more information.

Chapter 2: Overlapping Addresses in NAT Environments

NNMi can help you manage areas in your network that are configured using address translation protocols, resulting in Overlapping Addresses / Duplicate Address Domains. Each address domain must be assigned to a unique Tenant, see ["Configure Tenants" on page 213](#). Spiral Discovery requires a Discovery Seed (Tenant / Address pair) to identify each node before NNMi discovers and monitors that node. See ["Specify Discovery Seeds" on page 287](#).


Best Practice: No duplicate Domain Name System (DNS) names. See ["Well-Configured DNS Prerequisite" on page 208](#).

NNMi helps you manage important devices that are using any of the following address translation protocols. The NNMi configuration requirements vary, depending on the protocol:


- *Static* Network Address Translation (NAT)
- *Dynamic* Network Address Translation (NAT)
- *Dynamic* Port Address Translation (PAT/NAPT)

One NNMi management server can manage one or more *static* Network Address Translation (NAT) domains, each address domain must be assigned to a unique Tenant.


If *static* Network Address Translation (NAT) is part of your network management domain, you configure NNMi to display the NAT *external IP address* (public address) in the Mapped Address attribute of the [IP Address form](#) for the identified Tenant / NAT *internal IP address* (such as private IPv4 address) pair. This configuration setting is also important for node monitoring, see ["Overlapping Address Mapping" on page 210](#).



One NNMi management server can manage one *dynamic* Network Address Translation (NAT) domain or *dynamic* Port Address Translation (PAT/NAPT) domain. All nodes in this domain must belong to the same Tenant. The NNMi management server must participate in a Global Network Management environment as a Regional Manager.



Use NNMi's Global Network Management feature to monitor multiple *dynamic* Network Address Translation (NAT), *dynamic* Port Address Translation (PAT/NAPT) domains, or both. Tenants must be unique within the entire NNMi Global Network Management configuration. See ["Connecting Multiple NNMi Management Servers \(NNMi Advanced\)"](#) on page 98 and ["Tenant Best Practices for Global Network Management"](#) on page 102.



Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Tip: Assign any infrastructure device that interconnects multiple NAT domains (such as a NAT gateway) to the Default Tenant. This ensures that NNMi displays the Layer 2 Connections your team and customers need to see.

For more information:

Chapter 3: Use NNMi Help Anywhere, Anytime

The NNMi Help system can run independently from the console. Simply unzip the files into any convenient location.

To locate the NNMi Help files, on the NNMi management server, navigate to the location appropriate for the NNMi management server's operating system (see table and ["About Environment Variables" on page 86](#) for more information):

Location of the NNMi Help System

Operating System	NNMi Help System Files
Windows	%NmInstallDir%\NNM\server\deploy\nnmDocs_en.war
Linux	\$NmInstallDir/NNM/server/deploy/nnmDocs_en.war

To access Help independently from the console:

1. Copy the web archive file `nnmDocs_en.war` to any convenient location.
2. At the command prompt, navigate to the directory where you placed the `nnmDocs_en.war` file. To extract the help directory structure and files, type:

`jar xvf nnmDocs_en.war` (You might need to specify the complete path to the jar command's location on your computer.)

Tip: You can also use WinZip on Windows to decompress the `nnmDocs_en.war` file.

3. Navigate to and open the `/htmlHelp/nmHelp/nmHelp.html` file.
4. The NNMi Help system runs as usual in the default browser window.

To Access a PDF version of the NNMi online help:


Go to: <http://h20230.www2.hp.com/selfsolve/manuals>

This site requires that you register for an HP Passport ID. To obtain an HP Passport ID, go to:

<http://h20229.www2.hp.com/passport-registration.html>

Chapter 4: Connecting Multiple NNMi Management Servers (*NNMi Advanced*)

The Global Network Management feature enables you to configure NNMi to share the workload among multiple NNMi management servers in your network environment. For more information about the Global Network Management feature, [click here](#).



(*NNMi Advanced*) There are many benefits to using the NNMi Global Network Management feature:

- Provides safe and secure communication among multiple NNMi management servers.
- Provides a central big-picture view of your corporate-wide network on the Global Manager for 24-hour/7-days-per-week coverage.
- Enables management of nodes that are configured with address translation protocols to provide their public address (resulting in overlapping addresses domains). An NNMi Regional Manager is required for each address domain configured with following protocols:
 - *Static* Network Address Translation (NAT)
 - *Dynamic* Network Address Translation (NAT)
 - *Dynamic* Port Address Translation (PAT/NAPT)
- Easy to set up:
 - Each Regional Manager administrator specifies *all Node object data* or *a specific Node Group* for participation at the Global Manager level.
 - Each Global Manager administrator specifies which Regional Managers are permitted to contribute information.

- Automatically combines topology from multiple NNMi management servers on the Global Manager, but keeps management responsibilities separate. (No duplication, the responsible NNMi Management server is clearly identified per Node.)
- Generates and manages Incidents independently on each server (generated within the context of topology available on each server).
- Regional Manager administrators can configure specific SNMP Traps to be forwarded from Regional Managers to Global Managers.

Review the Global Network Management deployment choices in the *HP Network Node Manager i Software Deployment Reference* (available at:

<http://h20230.www2.hp.com/selfsolve/manuals>).

All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To configure Global Network Management, do the following:

1. Navigate to the **Global Network Management** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select **Global Network Management**.
2. Do one of the following:
 - ["Regional Manager Configuration" on page 107:](#)

If you are the NNMi administrator for the **Regional Manager**, you control the following aspects of communication with the Global Manager:

 - Configure a Tenant for each address domain. The Tenant name must be unique across all Tenants in the Global Network Management domain. See ["Tenant Best Practices for Global Network Management" on page 102](#).
 - Forward information about *all* Node object data or *only data about Nodes belonging to one Node Group*.

Note: Incidents associated with the specified Nodes are not forwarded to the Global Manager. *Each server maintains an independent group of incidents.*

- ["Global Manager Configuration" on page 109:](#)

If you are the NNMi administrator for the **Global Manager**, decide which Regional Managers are permitted to forward network information to that Global Manager (NNMi management server). Each Regional Manager retains management responsibilities for the forwarded nodes. The Global Manager might or might not directly manage a set of network devices.

3. Click  **Save and Close** to apply your changes.

After Global Network Management is set up in your network environment:

- To troubleshoot any issue with Global Network Management, see ["Troubleshoot Global Network Management" on page 119](#).
- To determine which Nodes are monitored by each NNMi management server, see [View the NNMi Management Servers' Domain List](#).
- To determine which Incidents were forwarded to the Global Manager, see [Monitor Incidents in a Global Network Management Environment \(NNMi Advanced\)](#).

About Multi-Tenancy and Global Network Management

(*NNMi Advanced - Global Network Management feature.*) When configuring NNMi for multiple Tenants in a Global Network Management environment, note the following:

- All NNMi installations (NNMi Regional Managers and NNMi Global Managers) have a Tenant object named *Default* with the following UUID: 1b96011e-8829-4e5d-8ab7-f93b7b10ac79.
- If areas in your network are configured using address translation protocols, each address domain must be assigned to a unique Tenant.
- If a Regional Manager's Node is *replicated* to the Global Manager, and that *replicated Node* is assigned to a Tenant UUID that is not yet defined on the NNMi Global Manager, NNMi creates an additional Tenant definition on the NNMi Global Manager.

Note: Ideally, this would never happen, see ["Tenant Best Practices for Global Network Management" on page 102](#).

- If the NNMi Global Manager creates an additional Tenant object (based on a Regional Manager's replicated Node), NNMi uses the following attribute values for that new Tenant object:

- **UUID:** The NNMi Global Manager uses the Regional Manager Tenant's *UUID* attribute value for the new Global Manager's Tenant definition.
- **Name:** The NNMi Global Manager automatically uses the Regional Manager Tenant's *Name* for that new Global Manager's Tenant object. However, the NNMi administrator on the Global Manager can change that name, but the UUID maintains the relationship. See ["Troubleshooting Tenants in Global Network Management" on page 104](#).
- **Initial Discovery Security Group:** The NNMi Global Manager automatically creates a new Security Group with the same *Name* as that newly created Tenant, and uses that newly created Security Group for this attribute value.

Note: The NNMi Global Manager creates this new Security Group whether or not a Security Group by that name already exists, and that duplicate will have a unique UUID. To avoid duplicates, see ["Tenant Best Practices for Global Network Management" on the next page](#).

The NNMi Regional Manager Tenant's *Initial Discovery Security Group* attribute value is not preserved on the Global Manager because the Security configuration on the Global Manager represents the needs of a different network management team. By creating a new Security Group, no operators or guests on the NNMi Global Manager can see those replicated nodes unless an NNMi administrator intentionally creates an appropriate Security Group Mapping. See ["Configuring Security" on page 569](#) for more information.

When additional Nodes from that Regional Manager are replicated to the NNMi Global Manager, for those Nodes, the NNMi Global Manager uses the same Tenant assigned by the Regional Manager (based on the *UUID* of the Tenant) and the *Initial Discovery Security Group* attribute value for that Tenant as defined on the Global Manager.

Tenants for Overlapping Address Domains

If your network uses any of the following address translation protocols, you must create a unique Tenant (other than *Default Tenant*) for each domain of nodes with addresses determined by the following protocols (see ["Configure Tenants" on page 213](#)):

- *Static* Network Address Translation (NAT)
- *Dynamic* Network Address Translation (NAT)
- *Dynamic* Port Address Translation (PAT/NAPT)

The configuration requirements vary, depending which protocol is used (see ["Overlapping Addresses in NAT Environments" on page 94](#)):

- Any number of *static* Network Address Translation (NAT) instances can be monitored by one NNMi management server, as long as each instance is configured with a unique Tenant.

- Each instance of *dynamic* Network Address Translation (NAT) or *dynamic* Port Address Translation (PAT/NAPT) must be configured as an NNMi Regional Manager, in addition to a unique Tenant. See ["Connecting Multiple NNMi Management Servers \(NNMi Advanced\)" on page 98](#).

Tenant Best Practices for Global Network Management

NNMi Global Manager administrators and NNMi Regional Manager administrators need to *work together* to synchronize Tenants and Security Groups for replicated Nodes.

Note: If using NNM iSPI Performance for Metrics, NNM iSPI Performance for Quality Assurance, or NNM iSPI Performance for Traffic and you want to generate reports from the Global Manager, this Best Practice procedure is a required part of the configuration (not optional) -- [click here for more information](#).

See also ["About Multi-Tenancy and Global Network Management" on page 100](#) and ["Troubleshooting Tenants in Global Network Management" on page 104](#).

Best practice procedure for establishing Tenants in a Global Network Management environment:

1. The NNMi administrators work together to agree on a *naming strategy* for the Tenants assigned to replicated Nodes and the Initial Discovery Security Group attribute value for those Tenants.

When a Tenant is assigned to a particular Node, the associated Security Group for that Tenant can be different on the Regional Manager and Global Manager:

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	Name: <i>ABC</i>	→ Same Name as Regional Setting.
Security Group	Name: < <i>strategy</i> > (These names can be independent of the Security Group names required by the Global Manager. Use any logic that works for your team.)	Name: < <i>strategy</i> > (These names can be independent of the Security Group names required by any of the Regional Managers. For example, consider names that indicate <i>which</i> Regional Manager replicated the Node.)

2. The NNMi Global Manager's administrator does the following according to the new naming strategy (determined in [step 1](#)):

- Defines all Security Groups required by the Global Manager.

If your team plans to use certain Security Groups on *multiple* NNMi management servers (Regional Managers / Global Manager), defines all those shared Security Groups. This establishes the UUID assigned to each shared Security Group.

- Defines all Tenants required by the Regional Managers and all Tenants required by the Global Manager. This establishes the UUID assigned to each Tenant. For each Tenant's *Initial Discovery Security Group* attribute value, use one of the Security Groups that are appropriate for the Global Manager (because this setting is independent of the Regional Manager's setting).
- Uses the `nnmconfigexport.ovpl` command line tool to *export* the new Tenant object definitions and Security Group object definitions for importing into each Regional Manager's database. See the [nnmconfigexport.ovpl](#) Reference Page.
- Updates each Node's Tenant assignment (to match the naming strategy determined in [step 1](#)):

For non-replicated Nodes: Uses the `nnmsecurity.ovpl` command line tool to update Tenant assignments for each Node in the NNMi Global Manager's database to the newly created Tenants. See the [nnmsecurity.ovpl](#) Reference Page.

For replicated Nodes: After completing [step 3](#), each *replicated* Node's *Tenant* assignment is automatically updated in the NNMi Global Manager's database (to match the Regional Manager's assignment the next time the Regional Manager forwards information about discovery and monitoring results to the Global Manager).

- Updates each Node's Security Group assignment (to match the naming strategy determined in [step 1](#)):

Change existing Security Group assignments for *all* Nodes in the Global Manager's database using one of the following methods:

- The Security Wizard. See ["Using the Security Wizard View" on page 591](#).
- The `nnmsecurity.ovpl` command line tool. See the [nnmsecurity.ovpl](#) Reference Page.

Note: These Security Group assignments can be different from the Regional Manager's assignments, and any changes to the Regional Manager's Security Group assignment for each Node are not replicated from Regional Managers to the Global Manager.

3. Each Regional Manager's NNMi administrator does the following according to the new naming strategy (determined in [step 1](#)):
 - Uses the `nnmconfigimport.ovpl -c security` command line tool to import the new Tenant object definitions and Security Group object definitions (the Global Manager's exported settings). See the [nnmconfigimport.ovpl](#) Reference Page.

- *Optional*. Deletes any imported Tenants that are not relevant for *this* Regional Manager.
- If not using *shared* Security Groups: Modifies each Tenant's *Initial Discovery Security Group* setting to one of the Security Groups that are appropriate for *this* Regional Manager.
- *Optional*. Deletes any imported Security Groups that are not relevant for *this* Regional Manager.
- Updates each Node's Tenant assignment (to match the naming strategy determined in [step 1](#)):

Use the [nnmsecurity.ovpl](#) command line tool to change each Node's *Tenant* assignment to the appropriate imported Tenant. See the [nnmsecurity.ovpl](#) Reference Page.

- Updates each Node's Security Group assignment (to match the naming strategy determined in [step 1](#)):

Change existing Security Group assignments for *all* Nodes in the Regional Manager's database using one of the following methods:

- The Security Wizard. See ["Using the Security Wizard View" on page 591](#).
- The [nnmsecurity.ovpl](#) command line tool. See the [nnmsecurity.ovpl](#) Reference Page.

Note: These Security Group assignments can be different from the Global Manager's assignments, and the changes to the Security Group assignments are not replicated to the Global Manager.

- Repeat [step 3](#) for each Regional Manager.

Troubleshooting Tenants in Global Network Management

You need to understand how NNMi determines the Tenant and Security Group setting per replicated Node. For more information, see ["About Multi-Tenancy and Global Network Management" on page 100](#).

The following scenarios explain the results of a potential series of changes when ["Tenant Best Practices for Global Network Management" on page 102](#) was not followed:

1. The first time the Regional Manager forwards information about discovery and monitoring results to the Global Manager. [Click here for details](#).

When a Regional Manager's Nodes are assigned to a custom Tenant (other than *Default*) and those Nodes are replicated to the Global Manager, if the Global Manager's database does not contain a Tenant object with the same *UUID*:

- The Global Manager creates a new Tenant object with the same UUID and Name.
- The Global Manager automatically creates a new Security Group with the same *Name* as the Tenant. This happens whether a Security Group by that name already exists (the duplicate has a unique UUID).

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one Name: MyCustomer	→ Same UUID as Regional Setting. → Same Name as Regional Setting.
Security Group	UUID: uniqueSecurityGrp#one Name: Tier1Support	NNMi creates a new Security Group with same <i>Name</i> as the Regional Manager's custom Tenant name. All other attributes of this Security Group have no relation to the Regional Manager's Tenant object. UUID: <i>uniqueSecurityGrp#two</i> Name: <i>MyCustomer</i>

2. Regional Manager's NNMi administrator changes the name of the *MyCustomer* Tenant object. [Click here for details.](#)

Changes to the NNMi Regional Manager's Tenant *Name* or *Description* are not replicated to the NNMi Global Manager. (No change on the Global Manager.)

Previously Replicated Node

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one Name: <i>MyNewestCustomer</i>	→ Same UUID as Regional Setting. Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: uniqueSecurityGrp#one Name: Tier1Support	UUID: uniqueSecurityGrp#two Name: MyCustomer

Newly Replicated Nodes

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one Name: <i>MyNewestCustomer</i>	→ Same UUID as Regional Setting. Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: uniqueSecurityGrp#one Name: Tier1Support	UUID: uniqueSecurityGrp#two Name: MyCustomer

- Global Manager's NNMi administrator changes the assigned Security Group for a specific Replicated Node. [Click here for details.](#)

(No change on the Regional Manager.)

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one Name: MyNewestCustomer	→ Same UUID as Regional Setting. Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: uniqueSecurityGrp#one Name: Tier1Support	UUID: <i>uniqueSecurityGrp#seven</i> Name: <i>Region1Security</i>

- Regional Manager's NNMi administrator changes the assigned Security Group for a specific Node. [Click here for details.](#)

(No change on the Global Manager.)

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one Name: MyNewestCustomer	→ Same UUID as Regional Setting. Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: <i>uniqueSecurityGrp#four</i> Name: <i>Building4</i>	UUID: uniqueSecurityGrp#seven Name: Region1Security

- Global Manager's NNMi administrator changes the *MyCustomer* Tenant object's definition to have a different Initial Discovery Security Group: *RockyMountRegion*. [Click here for details.](#)

Any Nodes replicated for the first time have Security Group set to the new Initial Discovery Security Group attribute value: *RockyMountRegion*.

Newly Replicated Nodes

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one	→ Same UUID as Regional Setting.
	Name: MyNewestCustomer	Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: uniqueSecurityGrp#four	UUID: <i>uniqueSecurityGrp#ten</i>
	Name: Building4	Name: <i>RockyMountRegion</i>

All previously replicated Node's Security Group settings remain unchanged (unless manually changed). NNMi does not change any Node settings when the Tenant object's Initial Discovery Security Group attribute value changes.

Previously Replicated Node

Node Attribute	Original Node's Attribute Value on NNMi's Regional Manager	Replicated Node's Attribute Value on NNMi's Global Manager
Tenant	UUID: uniqueTenant#one	→ Same UUID as Regional Setting.
	Name: MyNewestCustomer	Name: MyCustomer (name NNMi established during initial replication cycle, see 1).
Security Group	UUID: uniqueSecurityGrp#four	UUID: uniqueSecurityGrp#seven
	Name: Building4	Name: Region1Security

Regional Manager Configuration

(NNMi Advanced - Global Network Management feature) As administrator of the Regional Manager, you can specify which Node object data Global Managers can access:

Prerequisites:

- Each NNMi management server must have a static, routable IP address as the Management Address (for all SNMP/ICMP communication). See ["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#) and ["Specific Node Settings Form \(Communication Settings\)" on page 171](#).

2. Verify that your Tenant definitions have unique names across the entire Global Manager's domain: "[Tenant Best Practices for Global Network Management](#)" on page 102.
3. All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and "Configuring Single Sign-On for Global Network Management" section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:




<http://h20230.www2.hp.com/selfsolve/manuals>.



To provide all Node object data to Global Managers in your environment:

- Do nothing. NNMi automatically forwards all Node object data unless a Forwarding Filter is defined. Also see, "[About Multi-Tenancy and Global Network Management](#)" on page 100.

To limit available Node object data create a Forwarding Filter, [click here](#).

(*NNMi Advanced - Global Network Management feature*) The Global Manager and the Regional Manager maintain separate sets of data. Conclusions about each Node are derived from the available data and can sometimes be different. Regional Managers forward the results of each Auto-Discovery cycle to the Global Manager. The Regional Manager can have a Node Group filter configured to limit the amount of data that is forwarded to the Global Manager. Filters are usually unnecessary for Global Network Management. Do not filter out nodes that are important for connectivity in your network environment to ensure NNMi has the data needed for accurate root cause analysis.

1. Navigate to the **Global Network Management** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form.
2. Select the **Forwarding Filter** tab.
3. Click the **Node Group**  icon and select one of the options from the drop-down menu:
 -  Show Analysis to view Analysis Pane information for the currently selected Node Group name. (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
 -  Quick Find to view and select from the list of all existing Node Groups (for more information see "[Use the Quick Find Window](#)" on page 38).

-  Open to display the details of the currently configured (selected) Node Group (see [Node Group form](#) for more information).
-  New to create a new Node Group (see ["Create Node Groups" on page 326](#) for more information).

4. Click  **Save and Close**.

5. Global Managers in your network environment can now access only information about the Nodes in the specified Node Group. If any Global Managers have previously gathered a wider range of Node object data, that extra data is automatically removed from the Global Managers database.

To verify that your Forwarding Filter is working as expected, wait until the next NNMi rediscovery cycle finishes on your NNMi management server and then log on to the Global Manager. Follow the directions in [View the NNMi Management Servers' Domain List](#). You should see only the members of the Node Group specified as your Forwarding Filter.

Incidents associated with the specified Nodes are not forwarded to the Global Manager. *Each server maintains an independent group of incidents.*

Regional Manager administrators can make exceptions to this for SNMP traps. The administrator must specifically configure forwarding to the Global Managers:

- ["Configure Forward to Global Manager Settings for an SNMP Trap Incident \(NNMi Advanced\)" on page 1059](#)

To identify these specifically forwarded SNMP traps on the Global Manager, see [Monitor Incidents in a Global Network Management Environment \(NNMi Advanced\)](#).

Global Manager Configuration

(*NNMi Advanced - Global Network Management feature*) As administrator, you can set up this NNMi management server as a Global Manager that displays information from other NNMi management servers (Regional Managers).

There are two steps involved:

- ["Global Manager: Connect to a Regional Manager" on the next page](#)
- ["Global Manager: Configure Custom Attribute Replication" on page 115](#)

Tip: If the group of nodes being managed by a Regional Manager includes nodes already being managed by the Global Manager, the duplicate information from the Regional Manager is not imported into the Global Manager's database. If two Regional Managers are managing the same node, only the first instance to be forwarded is added to the Global Manager's database. Also see, ["About Multi-Tenancy and Global Network Management" on page 100](#).

Global Manager: Connect to a Regional Manager

(*NNMi Advanced - Global Network Management feature*) As administrator, you can set up this NNMi management server as a Global Manager that displays information from other NNMi management servers (Regional Managers).

Tip: If the group of nodes being managed by a Regional Manager includes nodes already being managed by the Global Manager, the duplicate information from the Regional Manager is not imported into the Global Manager's database. If two Regional Managers are managing the same node, only the first instance to be forwarded is added to the Global Manager's database. Also see, "[About Multi-Tenancy and Global Network Management](#)" on page 100

To enable communication from this NNMi management server to another in your network:

1. **Prerequisites:**










Each NNMi management server must have a static, routable IP address as the Management Address (for all SNMP/ICMP communication). See "[Configure Default SNMP, Management Address, and ICMP Settings](#)" on page 130 and "[Specific Node Settings Form \(Communication Settings\)](#)" on page 171.

All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and "Configuring Single Sign-On for Global Network Management" section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

2. Complete the required steps described in the *HP Network Node Manager i Software Deployment Reference* (available at: <http://h20230.www2.hp.com/selfsolve/manuals>), then [navigate to the Global Network Management form](#).
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form.
3. Select the **Regional Manager Connections** Tab.
4. Do one of the following:

- To create a new configuration, click the  New icon.
 - To edit a configuration, click the  Open icon in the row representing the configuration you want to edit.
 - DO NOT delete a configuration (the  Delete icon). See ["Disconnect Communication with a Regional Manager" on page 117](#) for more information.
5. In the **Regional Manager** form, provide the basic configuration settings (see [basic settings table](#)).
 6. From the Connection tab, navigate to the **Regional Manager Connection** form (see ["Global Manager: Configure Regional Manager Connection" on the next page](#) for more information). Do one of the following:
 - To create a new connection, click the  New icon.
 - To edit a connection, select a row, click the  Open icon.
 - To delete a connection configuration, select a row and click the  Delete icon.
 7. Click  **Save and Close** to return to the Regional Manager form.
 8. Click  **Save and Close** to return to the Global Network Management form.
 9. Click  **Save and Close**. NNMi establishes communication with the specified Regional Manager. That NNMi management server now forwards information about discovery and monitoring results to this NNMi management server.

Tip: To verify that the connection is working, see ["Determine the State of the Connection to a Regional Manager" on page 121](#).

Basic Settings for this Regional Manager (NNMi Management Server)

Attribute	Description
Name	<p>Type a meaningful name for this configuration record about the Regional NNMi management server. For example:</p> <ul style="list-style-type: none">• The name your team uses to refer to the Regional NNMi management server.• The company site being managed by the Regional Manager.• The geographic area (Japan or Germany) being managed by the Regional Manager. <p>The text you type appears in the Node view and NNMi Management Server view. This text string also appears in the Nodes by Management Server view's drop-down filter.</p>

Basic Settings for this Regional Manager (NNMi Management Server), continued

Attribute	Description
	Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No spaces are permitted. Note: Communicate this Name attribute value to your team so they understand the relationship between this name and the NNMi management server's DNS name (used to log on to that NNMi management server).
Connection State	NNMi provides the value for this attribute.
UUID	NNMi provides the value for this attribute. This is a unique number assigned by the NNMi database.
Description	<i>Optional.</i> Provide any description that would be useful for communication purposes within your team. Type a maximum of 250 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Global Manager: Configure Regional Manager Connection

(NNMi Advanced - Global Network Management feature) As administrator, you configure how this NNMi management server communicates with another NNMi management server in your network environment (the Regional Manager).

Tip: If the group of nodes being managed by a Regional Manager includes nodes already being managed by the Global Manager, the duplicate information from the Regional Manager is not imported into the Global Manager's database. If two Regional Managers are managing the same node, only the first instance to be forwarded is added to the Global Manager's database.







To configure the communication connection to another NNMi management server:

1. Prerequisite:




All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

2. Navigate to the **Regional Manager Connection** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form
 - c. Select the **Regional Manager Connections** tab.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit a configuration, click the  Open icon in the row representing the configuration you want to edit.
 - DO NOT delete a configuration (the  Delete icon). See "[Disconnect Communication with a Regional Manager](#)" on page 117 for more information.
 - e. In the **Regional Manager** form, navigate to the Connections tab. Do one of the following:
 - To create a new connection, click the  New icon.
 - To edit a connection, select a row, click the  Open icon.
 - To delete a connection configuration, select a row and click the  Delete icon.
3. Provide the connection configuration settings (see [connection configuration settings table](#)).

Note: If the Regional Manager participates in a high-availability (HA) environment, enter configuration settings for each server in the high-availability group (application fail-over).

4. Click  **Save and Close** to return to the Regional Manager form.
5. Click  **Save and Close** to return to the Global Network Management form.
6. Click  **Save and Close**. NNMi establishes communication with the Regional NNMi management server. The Regional Manager forwards information about discovery and monitoring results.

Tip: To verify that the connection is working, see "[Determine the State of the Connection to a Regional Manager](#)" on page 121.

Connection Configuration Settings for a Regional NNMi Management Server

Attribute	Description
Hostname	<p>The official <i>fully-qualified-domain-name</i> of the Regional Manager (the NNMi management server). To verify the correct value, do one of the following:</p> <ul style="list-style-type: none"> Log on to the Regional Manager, select Help → System Information, and navigate to the Server tab. Use the value displayed in the Official Fully Qualified Domain Name (FQDN) field. Use the <code>nnmofficialfqdn.ovpl</code> command. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: If you want NNMi to use secure sockets layer encryption (HTTPS) to access this Regional NNMi management server, the value must match the hostname as specified in that server's SSL Certificate. For information about establishing the required trust relationship, see the "Global Network Management" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div> <p>NNMi uses this hostname for communication with the Regional NNMi management server and to construct URL Actions. See "Authentication Requirements for URLs Access" on page 1523. See also "Actions Provided by NNMi" on page 41 and read about these actions:</p> <ul style="list-style-type: none"> Actions → Regional Manager Console (opens the NNMi console) Actions → Open from Regional Manager (opens the Node form)
Use Encryption	<p>If <input type="checkbox"/> disabled, NNMi uses hypertext transfer protocol (HTTP) and plain sockets to access this Regional NNMi management server.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi uses secure sockets layer encryption (HTTPS/SSL) to access this Regional NNMi management server.</p>
HTTP(S) Port	<p>The Global Manager initiates all communication sockets. The Global Manager needs access to the following default TCP ports on each Regional Manager:</p> <p>Non-Encrypted</p> <ul style="list-style-type: none"> nmsas.server.port.web.http = 80 nmsas.server.port.hq = 4457 <p>Encrypted</p> <ul style="list-style-type: none"> nmsas.server.port.web.https = 443 nmsas.server.port.hq.ssl = 4459

Connection Configuration Settings for a Regional NNMi Management Server, continued

Attribute	Description
	<p>To determine the current port number configuration or change port settings, access the Regional Manager and look in the nms-local.properties file. See the nnm.ports Reference Page for more information.</p> <p>If <input type="checkbox"/> Use Encryption is disabled (previous attribute), enter the port number for HTTP access to the NNMi console on the Regional NNMi management server. For example <code>http://<serverName>:<portNumber>/nnm/</code></p> <p>If <input checked="" type="checkbox"/> Use Encryption is enabled (previous attribute), enter the port number for HTTPS access to the NNMi console on the Regional NNMi management server. For example <code>https://<serverName>:<portNumber>/nnm/</code></p>
User Name	Type the user name required for NNMi sign-in for the system account on this Regional NNMi management server.
User Password	<p>Type the password for the NNMi system account on this Regional NNMi management server.</p> <p>Note: NNMi encrypts the password and displays asterisks for this attribute. If you want to change the password, first clear the asterisks displayed in the Password attribute and enter the new Password value.</p>
Ordering	<p>A numeric value. NNMi checks for configuration settings in the order you define (lowest number first). NNMi uses the first match found for each address. Provide a unique connection ordering number for each Regional Manager configuration.</p> <p>Any duplicate Ordering numbers are checked in random order, for example that group of Regional Manager Connections can be checked in any order during each discovery cycle.</p> <p>Tip: Consider incrementing Ordering numbers by 10s or 100s to provide flexibility over time.</p>

Global Manager: Configure Custom Attribute Replication



(NNMi Advanced - Global Network Management feature) As administrator, you configure which Custom Attributes from the Regional Managers are visible in the Global Manager.

Tip: If the group of nodes being managed by a Regional Manager includes nodes already being managed by the Global Manager, the duplicate information from the Regional Manager is not imported into the Global Manager's database. If two Regional Managers are managing the same node, only the first instance to be forwarded is added to the Global Manager's database.

To configure the Custom Attribute replication from the command line:

- See the [nnmgnmattcfg.ovpl](#) Reference Page.



To configure the Custom Attribute replication in the console:

1. Navigate to the **Custom Attribute Replication** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form
 - c. Select the **Custom Attribute Replication** tab.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To delete a configuration, click the  Delete icon.

Caution: When you remove a Custom Attribute name using this procedure, NNMi removes matching name/value pairs from all remote objects in your NNMi database. This means both Custom Attributes that were manually added or Replicated are removed from remote objects.

2. Type the text string representing the name of the Custom Attribute as it is defined on the Regional Manager, case-sensitive:
 - Maximum of 50 characters.
 - **Allowed:** Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -)
 - **Not Allowed:** Regular Expressions

Tip: Contact the NNMi administrator for that Regional Manager to request the CSV file they use to define Custom Attributes. Then you can easily copy-paste the name. For details about the CSV file, see the [nnmloadattributes.ovpl](#) Reference Page.



3. Click  **Save and Close** to return to the Global Network Management form.
4. Click  **Save and Close**.

After the next Discovery cycle, NNMi displays that Custom Attribute in the appropriate form (Node, Interface, Chassis, Card), if available from the Regional Manager.

Custom Attribute Replication Form

1. Type the text string representing the name of the Custom Attribute as it is defined on the Regional Manager, case-sensitive:
 - Maximum of 50 characters.
 - **Allowed:** Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -)
 - **Not Allowed:** Regular Expressions

Tip: Contact the NNMi administrator for that Regional Manager to request the CSV file they use to define Custom Attributes. Then you can easily copy-paste the name. For details about the CSV file, see the [nnmloadattributes.ovpl](#) Reference Page.


2. Click  **Save and Close** to return to the Global Network Management form.
3. Click  **Save and Close** on the Global Network Management form.

After the next Discovery cycle, NNMi displays that Custom Attribute in the appropriate form (Node, Interface, Chassis, Card), if available from the Regional Manager.


Disconnect Communication with a Regional Manager



(NNMi Advanced - Global Network Management feature) As administrator, you can disconnect communication between a Global Manager (NNMi management server) and a Regional Manager (another NNMi management server within your network environment).

To disconnect communication with a Regional Manager:

1. On the Global Manager (NNMi management server), navigate to the **Global Network Management** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form.
2. Select the **Regional Manager Connections** tab.
3. Click the  Open icon in the row representing the configuration you want to edit.

In the **Regional Manager** form, delete all Connection objects:

- a. Select the **Connections** tab.
- b. Select all Connection records, and click the  Delete icon.

4. Click  **Save and Close** to return to the Global Network Management form. NNMi disables communication from this Global Manager (NNMi management server) to that Regional Manager (NNMi management server).
5. In the **Regional Manager Connections** tab, note the **Name** attribute value for that connection configuration (case-sensitive). You need to type this text string to replace *<RegionalNNMiServerName>* in a later step.
6. Click  **Save and Close**.
7. On the Global Manager (NNMi management server), at the command line, type the following command (see ["Delete Nodes" on page 1635](#) and [nnmnodedelete.ovpl](#) and ["About Environment Variables" on page 86](#) for more information):

Note: The original *node records* on the Regional Manager (NNMi management server) are not affected. Only the *copy of the node records* will be deleted from the Global Manager's database.

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of *-u* and *-p*). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

Windows:

```
%NmInstallDir%\bin\nnmnodedelete -rm <RegionalNNMiServerName> -u  
<NNMiadminUserName> -p <NNMiadminPassword>
```

Linux:

```
$NmInstallDir/bin/nnmnodedelete -rm <RegionalNNMiServerName> -u  
<NNMiadminUserName> -p <NNMiadminPassword>
```



NNMi searches the Global Manager's database for all nodes that this Regional Manager is responsible for monitoring in your network environment. NNMi removes the node records from the Global Manager's database (these node records represent information *forwarded from the* Regional Manager). NNMi removes all associated data:

- Any interface or IP address information belonging to a deleted node.
- Any discovery seeds that match the name or IP address of a deleted node (unless you use the `nnmnodedelete -keepSeed` option).

Each Incident associated with the deleted Node is modified in the following ways, but not deleted from the NNMi database: The **Status** attribute changes to **Closed**. The **Correlation Notes** indicate the deletion of the associated node, interface, or address. The **RCA State**

attribute changes to **FALSE**. Incidents generated from SNMP traps (received from the deleted Node) appear in the Incident views, but remain unresolved.

To remove the Incidents from your NNMi database, follow the instructions in ["Archive and Delete Incidents" on page 1631](#) to delete "Closed" Incidents. You will be deleting all "Closed" Incidents, not just the "Closed" Incidents associated with this Regional Manager.

8. On the Global Manager (NNMi management server), remove the configuration record for this Regional Manager.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form.
 - c. Select the **Regional Manager Connections** tab.
 - d. Select the row that represents the Regional Manager (NNMi management server) that should no longer communicate with this NNMi management server (the Global Manager), and click the  Delete icon.
 - e. Click  **Save and Close**.
9. NNMi no longer requests information about discovery and monitoring results from that Regional Manager.

Note: The NNMi management server that is no longer one of the Regional Managers is still fully-functioning, but communication between the two NNMi management servers is now disabled.

Traps from that Regional Manager are still forwarded to the Global Manager if configured to do so, see ["Configure Trap Forwarding Destinations" on page 1413](#). Disable any trap forwarding that you no longer need.

Troubleshoot Global Network Management

(NNMi Advanced - Global Network Management feature) The Global Manager and the Regional Manager maintain separate sets of data. Conclusions about each Node are derived from the available data and can sometimes be different. Regional Managers forward the results of each Spiral Discovery cycle to the Global Manager. The Regional Manager can have a Node Group filter configured to limit the amount of data that is forwarded to the Global Manager. Filters are usually unnecessary for Global Network Management. Do not filter out nodes that are important for connectivity in your network environment to ensure NNMi has the data needed for accurate root cause analysis.

- The Global Manager might know information about why a connection from one site to another is down, but the Regional Manager just knows that the router connected to that remote site has an interface that is down. Use **Actions** → **Regional Manager Console** to see the other

perspective.

- When troubleshooting a Node on the Global Manager, you can use **Actions** → **Open from Regional Manager** to see the latest Node information on the Regional Manager.

(*NNMi Advanced - Global Network Management feature*) This group of help topics can help you troubleshoot any problems with Global Network Management:

- ["Clock Synchronization Issues \(SSO / Global Network Management\)" below](#)
- ["Node Synchronization Issues " on page 125](#)
- ["Determine the State of the Connection to a Regional Manager" on the next page](#)
- ["Check the Health of Global Managers and Regional Managers" on page 123](#)

Watch for these Incidents (error messages):

- ["Error Messages About Regional Managers \(NNMi Advanced\)" on page 127](#)
- [Message Queue Size Exceeded](#)
- [Message Queue Incident Rate Exceeded](#)
- [Pipeline Queue Size Exceeded Limit](#)

If you suspect problems, see the following NNMi log file on each NNMi management server for details about any communication problems between the Global Manager and Regional Manager (see ["About Environment Variables" on page 86](#) for more information):

- **Windows:**
`%NnmDataDir%\log\nnm\nnm.0.0.log`
- **Linux:**
`$NnmDataDir/log/nnm/nnm.0.0.log`

See also these topics in NNMi Help for Operators:

- [Is the Global Network Management Feature Enabled?](#)
- [View the NNMi Management Servers' Domain List](#)

Clock Synchronization Issues (SSO / Global Network Management)

(Single Sign-On and *NNMi Advanced - Global Network Management feature*)

All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

- For clock issues when creating Regional Manager Connections, [click here](#).

If you see the following message at the bottom of the NNMi console:

NNMi is not connected to 1 Regional Manager. See Help → System Information, Global Network Management.

Check the `nnm.0.0.log` file on the Global Manager for the following message:

WARNING: Not connecting to system <serverName> due to clock difference of <number of seconds>. Remote time is <date/time>.

- If Regional Manager Connections break after running successfully, [click here](#).

Perhaps the clocks are no longer synchronized. Check the `nnm.0.0.log` file on the Global Manager for the following message:

WARNING: Not connecting to system <serverName> due to clock difference of <number of seconds>. Remote time is <date/time>.

Within a few minutes of this warning, NNMi disconnects the Regional Manager Connection. And the following message appears at the bottom of the NNMi console:

NNMi is not connected to 1 Regional Manager. See Help → System Information, Global Network Management.

Determine the State of the Connection to a Regional Manager

(*NNMi Advanced - Global Network Management feature*) NNMi provides the **Connection State** attribute to help you track the health of communication connections between Global Managers and Regional Managers in your network environment. The table below describes each possible Connection State value.

To verify the state of the communication connection between NNMi management servers:

1. Open the NNMi console on the Global Manager (NNMi management server).
2. Navigate to the **Global Network Management** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Global Network Management** form.

3. Select the **Regional Manager Connections** tab.
4. Locate the **Connection State** column in this view.
5. Check the Connection State value for each Regional NNMi management server.

Tip: To verify the list of Nodes being managed by each NNMi management server, see [View the NNMi Management Servers' Domain List](#).

Possible States for Regional Manager Connections

Connection State	Description
Not Established	The connection configuration was recently saved, and NNMi is attempting to establish the connection.
Partial Connection	The connection state is transitioning between states due to a recent change in your network environment or a change in NNMi configuration settings.
Connected	Communication between the two NNMi management servers is working properly.
Not Connected	<p>An error occurred and the connection failed.</p> <p>Check the Regional Management Server configuration settings. Perhaps one of the designated port numbers is not correct? See "Global Manager: Connect to a Regional Manager" on page 110.</p> <p>Perhaps the Regional NNMi management server is currently down? See "Troubleshoot Global Network Management" on page 119.</p>

Thresholds in the Global Network Management Environment

(*NNMi Advanced*) When using the NNMi Global Network Management feature: Configure thresholds carefully as follows:

- Monitoring Configuration: Interface Group and Node Group thresholds are configured on each NNMi management server (Regional or Global) that is responsible for the objects being monitored (Interface, Node, Node Sensor, Physical Sensor). The threshold results are automatically communicated from Regional Managers to Global Managers (but not visa versa):
 - ["Configure Threshold Monitoring for Interface Groups" on page 426](#)
 - ["Configure Threshold Monitoring for Node Groups" on page 458](#)
- Custom Poller Collection thresholds are configured on the NNMi management server (Regional

or Global) that is responsible for the objects being monitored. The results are *not* communicated to other NNMi management servers.

- ["Configure Threshold Information for a Custom Poller Collection" on page 507](#)

Tip: Although Custom Polled Instances are not sent from a Regional Manager (NNMi management server) to the Global Manager. From the Global Manager, users can access that information by opening the monitored object's form and clicking **Actions** → **Open from Regional Manager** to see the list of Custom Polled Instances on the Regional Manager.

- Trap volume/forwarding is configured on each NNMi management server (Regional or Global).
 - [Interpret Incidents Related to SNMP Traps](#)

Check the Health of Global Managers and Regional Managers

Do one of the following to check the health of the Global Network Management feature:

- Log on to the Global Manager as an NNMi administrator, and open the NNMi console on the Global Manager (NNMi management server). [Click here for more information.](#)
 - a. Click the **Help** → **System Information**.
 - b. Click the **Global Network Management** tab.
 - c. In the **Regional Managers Reporting to this Global Manager** section, review the list of all Regional Managers that report to this Global Manager:
 - **Name:** The current value of the Name attribute for this Regional NNMi management server (as specified in the Remote Manager Connection form).
 - **Connection State:** The current state of communication between the Global Manager and Regional Manager. There are four possible values:
 - **Not Established** — A new Regional Manager Connection is not yet fully functional. This state is brief unless NNMi encounters a problem.
 - **Connected** — Data is flowing between the Global Manager and the Remote Manager.
 - **Not connected** — A previously established connection is no longer working. See ["Clock Synchronization Issues \(SSO / Global Network Management\)" on page 120.](#)

All NNMi management servers in your network environment that participate in Global Network Management (Global Managers and Regional Managers) or Single Sign-On (SSO) must have their internal time clocks synchronized in universal time.

Caution: Use a Time Synchronization program, for example, the Linux tool Network Time Protocol Daemon (NTPD) or one of the available Windows operating system tools.

Review the Global Network Management deployment choices and “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

- **Node Count:** The number of nodes in the Global Manager's database that are being managed by this Regional Manager.
- Log on to the Regional Manager as an NNMi administrator, and open the NNMi console on the Regional Manager (NNMi management server). [click here for more information](#).
 - a. Click the **Help** → **System Information**.
 - b. Click the **Global Network Management** tab.
 - c. Scroll down to the **Reporting to Global Managers** section, and review the list of all Global Managers that receive data from this Regional Manager:
 - **Name:** The fully-qualified DNS hostname of the Global Manager (NNMi management server).

Note: If you see something other than a fully-qualified DNS hostname in the Name column, the Global Manager is down and has been down since this Regional Manager was last restarted (see ["Stop or Start an NNMi Process" on page 87](#) or ["Stop or Start NNMi Services" on page 93](#) for more information).

- **Messages Currently in Queue:** The current number of messages that need to be sent to the Global Manager.

Messages are automatically sent to the Global Manager. If the number of messages in the queue continually increases and never decreases, or if the number of messages in the queue consistently exceeds 10,000, then there might be a problem.

Note: If the Global Manager is down for maintenance for a few hours, the queue size naturally increases until the Global Manager is back online.

Queue size over 100,000 indicates a serious issue. Consider disconnecting that global manager until the issue can be resolved..

- NNMi administrators can use the command line on any NNMi management server to generate a report about NNMi health. See the [nnmhealth.ovpl](#) Reference Page for more information.

There are two ways to log on to a Regional Manager:

- Directly log on to the Regional Manager (NNMi management server).
- From the Global Manager, select any Node being managed by the Regional Manager and click **Actions** → **Regional Manager Console**. See ["Actions Provided by NNMi" on page 41](#).

Node Synchronization Issues

(NNMi Advanced - Global Network Management feature).

Note: The Global Manager and the Regional Manager maintain separate sets of data. Nodes that are managed by the Regional Manager are discovered on the Regional Manager and are not rediscovered by the Global Manager.

Use the [nnmnode rediscover.ovpl](#) command when information about one or more nodes on the Global Manager or on a Regional Manager is not as expected or up-to-date. This is an unlikely scenario, but could be caused by data loss resulting from disk corruption, operator error, or extended downtime of the Global Manager. This command enables you to request that the specified Regional Manager send the most recent discovery information to the Global Manager. You can choose to send information for all nodes or for a subset of nodes.

Tip: Begin by re-synchronizing the smallest set of nodes that appear to have inconsistencies. If you need to re-synchronize all nodes in your managed network, execute this command during off hours when possible.

The [nnmnode rediscover.ovpl](#) command places the node or nodes into the NNMi discovery queue. The amount of time before the node starts discovery depends on how long NNMi takes to work through the nodes in the queue.

Caution: Use [nnmnode rediscover.ovpl](#) and especially `nnmnode rediscover.ovpl -fullsync` with care. Rediscovering all nodes or a large subset of nodes causes a large increase in CPU usage and network bandwidth. The `-fullsync` option with a large number of nodes also can cause a large increase in resource usage due to the increase in status recalculations.

You can re-synchronize discovery information for any of the following:

- All the nodes in your network (from the Global Manager) or a subset of nodes that are handled by a Regional Manager
- All the nodes managed by the local NNMi management server
- All of the nodes listed in a specified file or a single node

For example, to re-synchronize discovery information for all nodes on a specified Regional Manager, from the Global Network manager, use the following syntax:

```
nnmnode rediscover.ovpl -rm <regional_manager>
```

When you want to force the re-synchronization of all information about all nodes managed by an NNMi Regional Manager, including State and Status information, use the `-fullsync` option as shown in the following example:

```
nnmmoderediscover.ovpl -rm <regional_manager> -fullsync
```


NNMi automatically performs a full re-synchronization in the following cases:

- When upgrading an NNMi management server from an earlier NNMi release
- After restoring an NNMi management server from a backup.
- After failover in an NNMi cluster. For more information about NNMi's Application Failover feature, see in the "Resilience" chapter of the *HP Network Node Manager i Software Deployment Reference* which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

When using `nnmmoderediscover.ovpl -fullsync`, NNMi synchronizes information for locally managed nodes. NNMi does the following:

- Performs a Configuration Poll (`nnmconfigpoll.ovpl`) for each node specified.
- Reloads and refreshes the monitoring configuration for the node
- State Poller sends all current State values to the Causal Engine for analysis.
- The Causal Engine recalculates the Status for each node specified using the current State information.
- If the NNMi management server is a Regional Manager, the re-synchronized information is automatically uploaded to the Global Manager.

The following diagram illustrates executing `nnmmoderediscover.ovpl -fullsync` locally on the Regional Manager.




When NNMi synchronizes information for remotely managed nodes (for example using a `nnmmoderediscover.ovpl -rm` command from the Global Manager), NNMi does not execute

an `nnmconfigpoll.ovpl` command for each node. Instead, the Global Manager requests the Node information that is currently stored in the Regional Manager's database.

The following diagram illustrates executing the following command on the Global Manager:

```
nnmnoderediscover.ovpl -rm <regional_manager>
```

```
nnmnoderediscover.ovpl -rm <RegionalManagerName>
```



See [nnmnoderediscover.ovpl](#), [nnmconfigpoll.ovpl](#) and [nnmstatuspoll.ovpl](#) for more information.

Error Messages About Regional Managers (NNMi Advanced)

(NNMi Advanced - Global Network Management feature) A special set of incidents keeps the Global Manager informed of any problems with the Regional Manager:

- Licensing issues
 - License Expired
 - License Mismatch
 - License Node Count Exceeded
- Application fail-over health issues
 - Nnm Cluster Failover
 - Nnm Cluster Lost Standby
 - Nnm Cluster Startup
 - Nnm Cluster Transfer
- Traffic volume issues

- Snmp Trap Limit Critical
- Snmp Trap Limit Major
- Snmp Trap Limit Warning
- Trap Storm


These incidents are generated on the Regional Manager (NNMi management server). The Regional Manager forwards a copy of these incidents to the Global Manager. NNMi dynamically closes these incidents on the Regional Manager when the issue is resolved. The NNMi administrator for the Global Manager (NNMi management server) must manually close the forwarded copy.

From any [Incident view](#), you can identify the forwarding server or servers ([cia.remotemgr](#)). Use the [Custom Incident Attribute tab](#) on the Incident form for the selected incident. NNMi uses Custom Incident Attributes (CIAs) to attach additional information to incidents.

Chapter 5: Configuring Communication Protocol

NNMi uses the following protocols to discover your network and monitor the health of your network environment:

- Simple Network Management Protocol (SNMPv1 and SNMPv2c)
 - Read-only queries, also known as "Get" commands.

SNMPv1 and SNMPv2c require the use of a read community string to authenticate messages that are sent between NNMi and SNMP agents. NNMi cannot discover information about the SNMPv1 and SNMPv2c devices in your network environment until you provide the appropriate read community strings. During discovery and monitoring, NNMi uses the read community strings you provide in the Communication Configurations option of the  Configuration workspace. When a device is first discovered, NNMi tries all appropriate read community strings and makes a record of the first read community string that works. To keep network traffic to a minimum, from then on NNMi uses the recorded read community string when communicating with that device using SNMP. If at some point the device no longer responds to the recorded read community string, NNMi tries all appropriate read community strings and makes a record of the first read community string that now works.

- Write commands, also known as "Set" commands.

SNMPv1 and SNMPv2c require the use of a write community string to authenticate messages that are sent between the [nnmsnmpset.ovpl](#) command and SNMP agents.


- SNMPv3 requires the use of user-based security model (USM) user names instead of *SNMPv1/SNMPv2c community strings* to authenticate messages that are sent between NNMi and SNMP agents. NNMi cannot discover information about the SNMPv3 devices in your network environment until you provide the appropriate user name and authentication. During discovery and monitoring, NNMi uses the *SNMPv3 User Name* attribute value and authentication that the NNMi administrator provides in the Communication Configuration workspace. When a device is first discovered, NNMi tries all appropriate USM user names and makes a record of the first USM user name that works. To keep network traffic to a minimum, from then on NNMi uses the recorded *SNMPv3 User Name* attribute value when communicating with that device using SNMP. If at some point the device no longer responds to the recorded *SNMPv3 User Name* attribute value, NNMi tries all appropriate USM user names and makes a record of the one that now works.
- Internet Control Message Protocol (ICMP) ping commands

Note: If NNMi discovers a device for which no SNMP authentication was provided in the Communication Configuration workspace, that device is treated as a non-SNMP device.

You control the amount of traffic NNMi generates on your network. You can modify the settings to meet your needs.

Note: As an NNMi administrator, you can over-ride the Communication Configuration settings for a Node, using the **Mode** attribute in the [SNMP Agent Form](#).

To configure the way NNMi uses ICMP and SNMP protocols, do the following:

1. Navigate to the **Communication Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
2. Make your configuration choices. The Communication Configuration settings determine whether each NNMi Rediscovery cycle automatically detects the best SNMP choice (v1, v2, or v3) for each Node (automatically detects any upgrade to the SNMP agent on each Node), or uses only the SNMP version that you specify.

Click [here](#) for a list of choices .

Tip: For the alternate method of configuring communication settings from the command line, see the [nnmcommunication.ovpl](#) Reference Page.


3. Click  **Save and Close** to apply your changes.

Note: You control the amount of network traffic generated by NNMi by designating the **Rediscovery Interval** setting (see "[Adjust the Rediscovery Interval](#)" on page 231 for more information) and making choices when you "[Configure NNMi Monitoring Behavior](#)" on page 387.

Configure Default SNMP, Management Address, and ICMP Settings

NNMi generates network traffic using ICMP and SNMP protocols to discover and monitor your network environment. Default settings for the use of these protocols are provided; for example, timeout and retry behavior settings.

To configure the default communication protocol settings for your environment:

1. Navigate to the **Communication Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
2. In the far-left panel of the form, make your configuration choices

- [Default SNMP Settings](#) (table below)
- [Management Address Selection](#) settings (table below)

Note: The NNMi administrator can over-ride this setting and specify the management address on a per-node basis using the [SNMP Agent Form](#).

- [Default ICMP Settings](#) (table below)

For an explanation of how NNMi implements timeout and retry configurations, see "[Timeout / Retry Behavior Example for SNMP](#)" on page 138 and "[Timeout / Retry Behavior Example for ICMP](#)" on page 139.

3. Click  **Save and Close** to apply your changes.

Default SNMP Settings Attributes

Attribute	Description
Enable SNMP Address Rediscovery	<p>Note: The NNMi administrator can over-ride this setting for a Region or on a per-node basis. See "Communication Region Form" on page 150 and "Specific Node Settings Form (Communication Settings)" on page 171.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi automatically identifies which management address (SNMP agent) to use for each device. If the initially configured address becomes unreachable, NNMi automatically locates another address, if possible, and changes the management address attribute value. Click here for more information.</p> <p>When NNMi first discovers a node, the <i>seed address</i> (provided by the NNMi administrator) or discovered address (for non-seeded nodes) becomes the initial address used for SNMP communication. After NNMi builds an inventory of all IP addresses associated with the node (see "How Spiral Discovery Works" on page 195), NNMi follows a set of rules to determine which address is the best choice for each node's Management Address:</p> <p>Note: (<i>NNMi Advanced</i>) The NNMi administrator specifies whether NNMi prefers IPv4 addresses, IPv6 addresses, or dual-stack (both) when selecting the Management Address. See Configure Default SNMP, Management Address, and ICMP Settings.</p> <ol style="list-style-type: none"> 1. NNMi ignores the following addresses when determining which Management Address is most appropriate: <ul style="list-style-type: none"> ■ Any address of an administratively-down interface.

Default SNMP Settings Attributes, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Any address that is virtual (for example, VRRP¹). ■ Any IPv4 Anycast Rendezvous Point IP Address² or IPv6 Anycast address. ■ Any address in the reserved loopback network range. IPv4 uses 127/24 (127.*.*.*) and IPv6 uses ::1. ■ Any IPv6 link-local address³. <p>2. If the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi prefers the last-known Management Address (if any).</p> <p>3. If the Management Address does not respond and the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi uses the Communication Configuration settings for <i>Management Address Selection</i>. The NNMi Administrator chooses the order in which NNMi checks the following:</p> <ul style="list-style-type: none"> ■ Seed IP / Management IP - If the NNMi Administrator configures a Seed, NNMi uses the Seed address (either a specified IP address or the DNS address associated with a specified hostname) only during initial Discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery. ■ Lowest Loopback - If a node supports multiple loopback address⁴, NNMi queries each loopback addresses, starting with the lowest number. NNMi uses the loopback address with the lowest number from which the SNMP agent responds (for example, 10.16.42.197 is a lower number than 10.16.197.42).

¹Virtual Router Redundancy Protocol

²Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

³A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

⁴The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

Default SNMP Settings Attributes, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Highest Loopback - If a node supports multiple loopback address¹, NNMi queries each loopback addresses, starting with the highest number. NNMi uses the loopback address with the highest number from which the SNMP agent responds. ■ Interface Matching - The NNMi Administrator chooses which interface MIB variable NNMi queries to detect changes. NNMi can use the following MIB-II attribute values: <code>ifIndex</code>, <code>ifName</code>, <code>ifDescr</code>, <code>ifAlias</code>, or a combination of these (<code>ifName</code> or <code>ifDescr</code>, <code>ifName</code> or <code>ifDescr</code> or <code>ifAlias</code>). NNMi searches current database entries for information about the interface in this order: <code>index</code>, <code>alias</code>, <code>name</code>, and <code>description</code>. If multiple IP addresses are associated with the interface, NNMi starts by querying the lowest IP address and selects the first responding address in ascending order. <ol style="list-style-type: none"> 4. If no response, NNMi queries any remaining IP addresses in the node's IP address inventory, starting with the lowest number. NNMi uses the address with the lowest number from which the SNMP agent responds. 5. If no response, NNMi checks for any Mapped Address configured for one of the currently known addresses (see the Mapped Address column in the Custom IP Addresses view). <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The address represents a <i>static</i> Network Address Translation (NAT) pair's <i>external IP address</i> from the internal/external IP address pair. NNMi Administrators configure these pairs using the Overlapping IP Address Mapping form. NNMi uses this list of addresses starting with IPv4 from low to high, then IPv6 from low to high.</p> </div> <ol style="list-style-type: none"> 6. If no response, NNMi might be configured to repeat the sequence using SNMPv1, SNMPv2c, or SNMPv3 in the order specified by the NNMi administrator (Communication Configurations <i>SNMP Minimum Security Level</i> settings). 7. When all else fails, NNMi retains the last known Management Address (if any) and automatically changes the State of that SNMP Agent object to Critical. <p>This process is repeated during each Spiral Discovery cycle, and the</p>

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using `ifType` Number 24, `softwareloopback` from the IANA `ifType-MIB`.

Default SNMP Settings Attributes, continued

Attribute	Description
	<p>Management Address can change. For example, NNMi's inventory of addresses for the node expands, or the current Management Address does not respond to SNMP queries due to network problems or node reconfiguration. The NNMi administrator can prevent changes to the management address using the Communication Configurations <i>Enable SNMP Address Rediscovery</i> or <i>Preferred Management Address</i> setting.</p> <p>If <input type="checkbox"/> disabled, when the current management address (SNMP agent) becomes unreachable, NNMi reclassifies the node as a non-SNMP node until the previously configured management address is available again.</p>
Enable SNMP GetBulk	<p><i>Applies only to SNMPv2 or higher.</i> If you have devices in your network environment that have trouble responding to GetBulk commands, you can instruct NNMi to use Get or GetNext instead of GetBulk.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi uses the SNMPv2c GetBulk command to gather information from devices in your network environment.</p> <p>If <input type="checkbox"/> disabled, NNMi uses the SNMP Get or GetNext command to gather information from devices in your network environment (requesting responses for one SNMP OID at a time).</p>
SNMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an SNMP query before reissuing the request. Both the Discovery Process and the State Poller Service use this setting. For an explanation of how NNMi implements timeout and retry configurations, see "Timeout / Retry Behavior Example for SNMP" on page 138.</p>
SNMP Retries Count	<p>Maximum number of retries that NNMi issues for an SNMP query before determining the query result to be "unresponsive". Zero means no retries. Both the Discovery Process and the State Poller Service use this setting.</p>
SNMP Port	<p>Default is 161. Specifies the NNMi management server's port that NNMi uses when generating SNMP traffic. Both the Discovery Process and the State Poller Service use this setting.</p>
SNMP Proxy Address	<p><i>Optional.</i> IP address of the your SNMP Proxy Server (for example, a proxy that gathers data from non-SNMP devices and can use that data to respond to NNMi SNMP requests).</p> <p>To enable a proxy, you must also provide the port number of your SNMP Proxy Server. See SNMP Proxy Port (next attribute).</p> <div> <p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the "NNMi Communications" chapter of</p> </div>

Default SNMP Settings Attributes, continued

Attribute	Description
	<p>the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>
SNMP Proxy Port	<p><i>Optional.</i> Port number of the SNMP Proxy Server.</p> <p>To enable a proxy, you must also provide the IP address of your SNMP Proxy Server. See SNMP Proxy Address (previous attribute).</p> <p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the “NNMi Communications” chapter of the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>
SNMP Minimum Security Level	<p>This setting determines whether each NNMi Rediscovery cycle automatically detects the best SNMP choice (v1, v2, or v3) for each Node (automatically detects any upgrade to the SNMP agent on each Node), or uses only the SNMP version that you specify.</p> <p>For SNMPv1 or SNMPv2c, configure NNMi to use Community Strings in your network environment:</p> <ul style="list-style-type: none"> Community Only (SNMPv1) NNMi tries only SNMPv1 settings. Community Only (SNMPv1 or v2c) NNMi first tries to use SNMPv2c settings, and, if that fails, NNMi tries SNMPv1 settings. Community NNMi first tries to use SNMPv2c settings, and, if that fails, NNMi tries SNMPv1 settings. If both SNMPv2c and SNMPv1 fail, NNMi tries SNMPv3 settings if any are available. <p>For SNMPv3, configure NNMi to use the User-based Security Module (USM) level of security required in your network environment (if your environment also uses SNMPv1/SNMPv2c, select Community):</p> <ul style="list-style-type: none"> No Authentication, No Privacy Authentication, No Privacy Authentication, Privacy <p>See "Timeout / Retry Behavior Example for SNMP" on page 138 for an explanation of NNMi behavior with each of these choices.</p>

Note: NNMi needs to know which SNMPv1 or SNMPv2c community strings (read/write) are used in your environment (see ["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#)) and which SNMPv3 USM settings are used in your environment (see ["Configure Default SNMPv3 Settings" on page 145](#)).

Management Address Selection Settings

Attribute	Description
First Choice	<p>Configure how NNMi chooses the Management Address for Nodes, if possible:</p> <ul style="list-style-type: none"> Seed IP / Management IP <p>NNMi uses the Seed address only during initial Discovery. The Seed address is either the specified IP address or the DNS address associated with the specified hostname. See "Specify Discovery Seeds" on page 287 for more information.</p> <p>Otherwise, NNMi uses the current Management Address.</p> <ul style="list-style-type: none"> Lowest Loopback IP address (loopback address¹) Highest Loopback IP address Interface Matching (instead of addresses)
Second Choice	Configure how NNMi choose the Management Address for Nodes when the First Choice is not available.
Third Choice	Configure how NNMi choose the Management Address for Nodes when the First Choice and Second Choice are not available.
Interface Matching	<p><i>Optional.</i> When First, Second, or Third Choice is set to Interface Matching, provide the appropriate values for the following SNMP MIB-II attributes.</p> <p>Provide more than one value by separating each with a comma.</p> <p>Space characters are permitted within values, but not before or after a comma.</p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>For example, Lo0,My Favorite Interface,Lo1 produces the following results with the spaces "My Favorite Interface"</p> <p>However, Lo0, My Favorite Interface, Lo1 produces the following results with spaces " My Favorite Interface" (initial character is a space) and " Lo1" (initial character is a space)</p> </div>

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

Management Address Selection Settings, continued

Attribute	Description
	<p>No wildcards or quotes allowed within values:</p> <ul style="list-style-type: none"> • ifIndex values (for example, 4) • ifAlias values (for example, Vlan99) • ifName values (for example, lo0) • ifDescr values (for example, 1000Gbic Port 9/27) <p>NNMi searches current interface data for an exact match in this order: index, alias, name, and description. If the interface has multiple IP addresses, NNMi begins with the lowest IP address and selects the first match in ascending order.</p>
IP Version Preference	<p>Tip: If this attribute does not appear in the Management Address Selection settings box, check the following:</p> <ul style="list-style-type: none"> • Are you using NNMi Advanced (required for IPv6 support)? • Did your NNMi Administrator disable NNMi Advanced's IPv6 feature? See the "Configuring NNMi Advanced for IPv6" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals. <p>IP Version Preference: Select one of the following to influence Spiral Discovery's evaluation of <i>newly discovered nodes</i>. Previously established Management Addresses will not change if you modify this IP Version Preference setting:</p> <ul style="list-style-type: none"> • IPv4 • IPv6 • Any (meaning NNMi uses the first address that responds for newly discovered nodes)

Default ICMP Settings

Attribute	Description
ICMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an ICMP query before reissuing the request. For an explanation of how NNMi implements timeout and retry configurations, see "Timeout / Retry Behavior Example for ICMP" on page 139.</p>
ICMP Retries Count	<p>Maximum number of retries that NNMi issues for an ICMP query before logging an error. Zero means no retries.</p>

Related Topics:

["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#)

["Configure Regions \(Communication Settings\)" on page 148](#)

["Configure Specific Nodes " on page 169](#)

Timeout / Retry Behavior Example for SNMP

When NNMi attempts to contact a device, your configuration settings for Timeout and Retry influence NNMi behavior.

NNMi attempts to obtain information about a hostname/IP-address using SNMP, then waits the configured timeout interval for a response. If not successful, NNMi increments the timeout interval before trying again. This process repeats until one of the following is true:

- The device responds to SNMP.
- The maximum configured number of SNMP Retries fails. For example, if your timeout is 2 seconds and your retry is 3:
 - NNMi attempts to communicate with a device and waits 2 seconds for a response.
 - If unsuccessful, NNMi retries and waits 4 seconds for a response.
 - If unsuccessful, NNMi retries a second time and waits 6 seconds for a response.
 - If unsuccessful, NNMi retries a third time and waits 8 seconds for a response.

If no response, NNMi repeats this process using the next configured SNMP level.

- NNMi exhausts all possibilities. NNMi considers the hostname/IP-address to be a *non-SNMP* device until the next Discovery or Monitoring cycle.

Tip: It is best to use the same timeout/retry numbers for both ICMP and SNMP.

Your choice of SNMP Minimum Security Level determines the range of possibilities:

- If your SNMP Minimum Security Level is **Community Only (SNMPv1)**, NNMi uses only SNMPv1 to locate SNMP agents.
- If your SNMP Minimum Security Level is **Community Only (SNMPv1 or v2c)**, NNMi cycles through the following until successful:

SNMPv2c

SNMPv1

- If your SNMP Minimum Security Level is **Community**, NNMi cycles through the following until

successful:

SNMPv2c

SNMPv1

SNMPv3 *No Authentication, No Privacy* settings (if any matching configurations, otherwise skip).

SNMPv3 *Authentication, No Privacy* settings (if any matching configurations, otherwise skip).

SNMPv3 *Authentication, Privacy* settings (if any matching configurations).

- If your SNMP Minimum Security Level is **No Authentication, No Privacy**, NNMi cycles through the following until successful:

SNMPv3 *No Authentication, No Privacy* settings (if any matching configurations at this, otherwise skip)

SNMPv3 *Authentication, No Privacy* settings (if any matching configurations, otherwise skip).

SNMPv3 *Authentication, Privacy* settings (if any matching configurations).

- If your SNMP Minimum Security Level is **Authentication, No Privacy**, NNMi cycles through the following until successful:

SNMPv3 *Authentication, No Privacy* settings (if any matching configurations, otherwise skip).

SNMPv3 *Authentication, Privacy* settings (if any matching configurations).

- If your SNMP Minimum Security Level is **Authentication, Privacy**, NNMi cycles through the following until successful:

SNMPv3 *Authentication, Privacy* settings (if any matching configurations).

Timeout / Retry Behavior Example for ICMP

When NNMi attempts to contact a device, your configuration settings for Timeout and Retry influence NNMi behavior.

NNMi attempts to contact the device using ICMP, then waits the configured timeout interval for a response. If not successful, NNMi increments the timeout interval before trying again. This process repeats until one of the following is true:

- The device responds to ICMP.
- The maximum configured number of ICMP Retries fails. NNMi considers the device unreachable through ICMP until the next Discovery or Monitoring cycle. For example, if your timeout is 2 seconds and your retry is 3:

- NNMi attempts to communicate with a device and waits 2 seconds for a response.
- If unsuccessful, NNMi retries and waits 4 seconds for a response.
- If unsuccessful, NNMi retries a second time and waits 6 seconds for a response.
- If unsuccessful, NNMi retries a third time and waits 8 seconds for a response.

Tip: It is best to use the same timeout/retry numbers for both ICMP and SNMP.

Configure Default Community Strings (SNMPv1 or SNMPv2c)

Use the Default Community Strings tab to provide default SNMPv1 and SNMPv2c community strings. For each address, NNMi checks the communication configuration settings in this order: [communication protocols for Specific Nodes](#), [communication protocols for Network Regions](#), and if no match is found, NNMi tries these default community strings. If NNMi discovers a device for which no SNMP settings are provided, that device is treated as a Non-SNMP device.

During initial discovery, NNMi tries many community strings until a match is found. After a match is identified for a node, the information is recorded to prevent future authentication errors.

Note: If you provide a read community string for a [specific device](#), NNMi honors your choice and does not try any Region or Default community strings for that device.

NNMi uses SNMP read-only queries (Get commands) for ongoing discovery and monitoring of your network environment. SNMP read community strings are the validation passwords used to authenticate messages sent from NNMi to an SNMP agent. NNMi uses SNMP to gather useful information about the devices in your network environment. After receiving an SNMP request, an SNMP agent compares the read community string in the request to the read community strings that are configured for that SNMP agent. The SNMP agent responds to the request only when the request is accompanied by a valid community string.

During NNMi installation, any community strings that were provided are automatically stored in the table on the Default Community Strings tab.

Provide any number of additional community strings that are used broadly in your environment (for example, by default). The order in which your read community string settings appear in the table does not matter. NNMi checks all Default read community strings in parallel.

Tip: Having a large number of default community strings can negatively impact discovery performance. Instead of entering many default community strings, consider fine tuning the community string configuration for particular areas of your network by using the [Regions](#) or [Specific Nodes](#) settings.

NNMi uses the SNMPv2c settings to discover the SNMPv2c information about your network. This also determines whether NNMi *receives or discards incoming* SNMPv2c traps. [Click here for more information.](#)



- If the *incoming* trap's Source Node (and sometimes Source Object, such as card or interface) has not yet been discovered by NNMi, NNMi discards the trap. See ["Handle Unresolved Incoming Traps" on page 878](#) for additional information. See also ["Configure Network Devices to Send SNMP Notifications to NNMi" on page 872.](#)
- If the Source Node was not discovered using SNMv3, NNMi discards any incoming SNMPv3 traps from that Node.
- NNMi discards traps that have no incident configuration or with an incident configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap. See ["Configure SNMP Trap Incidents" on page 886.](#)
- If either the Source Node or Source Object has *Management Mode* set to **Not Managed** or **Out of Service** in the NNMi database, NNMi always discards the incoming trap. See [Understand the Effects of Setting the Management Mode to Not Managed or Out of Service.](#)





NNMi provides the Management Mode workspace so that you can quickly view lists of all nodes, interfaces, IP addresses, chassis, cards, node sensors, or physical sensors that NNMi is not currently discovering or monitoring. For information about these views:

- NNMi discards most incoming traps from network objects that are not monitored. For example, you can configure NNMi to exclude specified interfaces from being monitored. See ["Monitoring Network Health" on page 378](#) for more information.

Note: If you want the NNMi management server to *forward* SNMPv2c traps to other machines in your network environment, see ["Configure Trap Forwarding" on page 1407](#) for additional configuration steps.

To configure default SNMPv1 or SNMPv2c community strings for your environment:

1. Navigate to the **Communication Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
2. Locate the **Default SNMPv1/v2c Community Strings** tab.
3. To provide a default *read community string*, navigate to the **Read Community Strings** table and do one of the following:
 - To establish a community string setting, click the  **New** icon. In the [Default Read Community String form](#), provide the required information (see [table](#)).

- To edit a community string setting, click the  Open icon in the row representing the community string setting you want to edit. In the [Default Read Community String form](#), provide the required information (see [table](#)).
 - To delete a community string setting, select a row and click the  Delete icon.
4. To provide a default *write community string*, navigate to the **Write Community String** attribute (see [table](#)).
 5. Click  **Save and Close** to return to the Communication Configuration form.
 6. Click  **Save and Close** to apply your changes.

Default SNMPv1 or SNMPv2c Community Strings

Attribute	Description
Read Community String	<p>Note: As an NNMi administrator, you can over-ride this setting and specify the Read Community String on a per-node basis using the SNMP Agent Form.</p> <p>The SNMPv1 or SNMPv2c "Get" (read-only) Community String that is used as the default value for each SNMP Agent (case-sensitive).</p> <p>Many proxy vendors use the <i>read community string</i> for specifying remote target information. NNMi supports substitution parameters within read community strings for SNMPv1 or SNMPv2c proxy environments. Click here for more information.</p> <p>Copy and paste these codes at the end of your read community string to provide the values required by your proxy environment. NNMi substitutes the actual attribute values from the NNMi database at runtime:</p> <p><code>\${contextName}</code> = Used for specifying VLAN context for switches (VLAN associated with the remote target node)</p> <p><code>\${managementAddress}</code> = Node form, Management Address attribute value (the remote target node)</p> <p><code>\${snmpPort}</code> = SNMP Agent form, UDP Port attribute value (SNMP agent associated with the remote target node)</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>
Ordering	<p><i>Optional.</i> During the Discovery process, NNMi tries Read Community Strings in priority order (lowest to highest). Then, NNMi tries all unordered Read Community Strings (treated as though they had the same Ordering number). These unordered requests are sent in parallel, with NNMi using the first response.</p>
Write Community String	<p><i>Optional.</i> For use with the nnmsnmpset.ovpl command line tool</p> <p>The SNMPv1 or SNMPv2c "Set" (write) Community String that is used as the default value for each SNMP Agent (case-sensitive).</p>




Default SNMPv1 or SNMPv2c Community Strings , continued

Attribute	Description
	<p>Tip: SNMP Agents are often configured with different community strings for "Set" requests than for "Get" (read) requests.</p> <p>SNMPv1 and SNMPv2c require that you know the SNMP agent's <i>write community string</i> before you can change settings on any device. The nnmsnmpset.ovpl command can use the value you provide here, rather than requiring that you type the write community string each time you invoke the command.</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>Because this is a type of password, you must enter the value twice.</p>

Default Read Community String Form



For each IP address, NNMi checks the communication configuration settings in this order: [communication protocols for Specific Devices](#), [communication protocols for Network Regions](#), and if no match is found, NNMi tries the default community strings. If NNMi discovers a device for which no community string is provided, that device is treated as a Non-SNMP device.

To provide a default community string for your environment:

1. Navigate to the **Default Read Community String** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Default SNMPv1/v2c Community Strings** tab.
 - d. Navigate to the **Read Community Strings** table.
 - e. Do one of the following:
 - To establish a community string setting, click the  **New** icon.
 - To edit a community string setting, select a row, click the  **Open** icon in the row representing the configuration you want to edit.
2. Provide the read community string (see [table](#)).

Provide any number of additional SNMPv1 or SNMPv2c read community strings that are used broadly in your environment (for example, by default).

3. Click either:

-  **Save and Close** to return to the Communication Configuration form.
-  **Save and New** to add another community string.

4. Click  **Save and Close** to apply your changes.

To determine which Community Strings are relevant for a node, select the node in an NNMi map or table view, and click Actions → Configuration Details → Communication Settings. In the Communities list, Ordering number is in parentheses. For example: communityString (200).

Default Read Community String

Attribute	Description
Read Community String	<p>Note: As an NNMi administrator, you can over-ride this setting and specify the Read Community String on a per-node basis using the SNMP Agent Form.</p> <p>The SNMP "Get" (read-only) Community String that is used in your network environment (case-sensitive).</p> <p>Many proxy vendors use the <i>read community string</i> for specifying remote target information. NNMi supports substitution parameters within read community strings for SNMPv1 or SNMPv2c proxy environments. Click here for more information.</p> <p>Copy and paste these codes at the end of your read community string to provide the values required by your proxy environment. NNMi substitutes the actual attribute values from the NNMi database at runtime:</p> <p><code>\${contextName}</code> = Used for specifying VLAN context for switches (VLAN associated with the remote target node)</p> <p><code>\${managementAddress}</code> = Node form, Management Address attribute value (the remote target node)</p> <p><code>\${snmpPort}</code> = SNMP Agent form, UDP Port attribute value (SNMP agent associated with the remote target node)</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>
Ordering	<p><i>Optional.</i> A numeric value. NNMi uses the first Community String that results in successful SNMP communication:</p> <ul style="list-style-type: none"> Each ordering number must be unique (no duplicate numbers). NNMi tries the provided Community Strings in the order you define (lowest number first). <p>Tip: Consider incrementing by 10s or 100s to provide flexibility when adding new Read Community Strings over time.</p> <ul style="list-style-type: none"> If no Ordering numbers are specified, NNMi tries all community strings in

Default Read Community String , continued

Attribute	Description
	<p>parallel.</p> <ul style="list-style-type: none">• If some but not all the community strings have an Ordering number, NNMi tries the community strings with a specified Ordering number first. Then, NNMi tries all the community strings without an Ordering number in parallel.

Configure Default SNMPv3 Settings

Use the Default SNMPv3 Settings tab to provide default SNMPv3 user-based security model (USM) settings. For each address, NNMi checks the communication configuration settings in this order: [communication protocols for Specific Nodes](#), [communication protocols for Network Regions](#), and if no match is found, NNMi tries these default user-based security model (USM) settings. If NNMi discovers a device for which no SNMP settings are provided, that device is treated as a Non-SNMP device.

During initial discovery, NNMi tries many SNMP configuration settings until a match is found. After a match is identified for a Node, the information is recorded to prevent future authentication errors.


Note: If you provide SNMPv3 user-based security model (USM) settings for a [specific device](#), NNMi honors your choice and does not try any Region or Default settings for that device.

NNMi uses SNMP queries for ongoing discovery and monitoring of your network environment. SNMPv3 user-based security model (USM) settings are used to authenticate messages sent from NNMi to an SNMP agent. NNMi uses SNMP to gather useful information about the devices in your network environment. After receiving an SNMP request, an SNMP agent compares the SNMPv3 user-based security model (USM) settings in the request to the SNMPv3 user-based security model (USM) settings that are configured for that SNMP agent. The SNMP agent responds to the request only when the request is accompanied by valid SNMPv3 user-based security model (USM) settings.

Provide any number of additional SNMPv3 user-based security model (USM) settings that are used broadly in your environment (for example, by default). The order in which your SNMPv3 user-based security model (USM) settings appear in this table does not matter. NNMi checks all Default SNMPv3 Settings at a particular security level in parallel.

NNMi uses Default SNMPv3 user-based security model (USM) settings to access devices.

To view the current list of default SNMPv3 USM settings:


1. Navigate to the **Default SNMPv3 Settings** tab.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Default SNMPv3 Settings** tab.


2. The displayed table lists the Unique Name of each default SNMPv3 USM setting.


Note: NNMi tries to use the [Specific Node SNMPv3 Settings](#). If none match, NNMi tries the [Region SNMPv3 Settings](#). If none match, NNMi tries the default SMNPv3 settings provided here.


3. You can do the following:

- To establish a new setting, click the  New icon. See "[Default SNMPv3 Settings form](#)" [below](#).



Click  **Save and Close** to return to the Default SNMPv3 Settings form.

- To edit an existing setting, select a row, click the  Open icon. See "[Default SNMPv3 Settings form](#)" [below](#).

Click  **Save and Close** to return to the Default SNMPv3 Settings form.

- To delete an existing setting from the Default list, select a row and click the  Delete icon.

Note: The record remains in the database for possible use elsewhere and is simply removed from the Default list.


4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.











Default SNMPv3 Settings form

NNMi can use SNMPv3 user-based security model (USM) settings to access devices.

NNMi tries to use the current SNMPv3 Settings attribute value from [Specific Node Settings](#). If none match, NNMi tries the [Region SNMPv3 Settings](#). If none match, NNMi tries the default SMNPv3 settings provided here.

To configure a Default SNMPv3 Setting:

1. Navigate to the **Default SNMPv3 Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Default SNMPv3 Settings** tab.
 - d. Do one of the following:

- To create default SNMPv3 Setting definition, click the  New icon.
 - To edit a default SNMPv3 Setting, select a row, click the  Open icon.
2. Click the SNMPv3 Settings  Lookup icon and select one of the options from the drop-down menu:
 -  Show Analysis to display Analysis Pane information for the currently configured (selected) SNMPv3 Setting name. (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
 -  Quick Find to view and select from the list of all existing SNMPv3 Settings (for more information see "[Use the Quick Find Window](#)" on page 38).
 -  Open to display the details of the currently configured (selected) SNMPv3 Setting (see "[SNMPv3 Settings Form](#)" for more information).
 -  New to create a new SNMPv3 Setting (see "[SNMPv3 Settings Form](#)" for more information).
 3. Click  **Save and Close** to return to the Default SNMPv3 Settings form.
 4. Click  **Save and Close** to return to the Communication Configuration form.
 5. Click  **Save and Close** to apply your changes.

Configure the Default Device Credentials

NNMi uses the Device Credentials settings for the following:




- Device discovery of some vendor-specific devices that require non-SNMP communication, such as Netconf over SSH. For a list of these devices see the NNMi Device Support Matrix.
- Device Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

NNMi uses the following sequence to determine Device Credentials:

- Use the [Specific Node Device Credentials](#). If none match, continue.
- Use the [Region Device Credentials](#). If none match, continue.
- Use the Default Credential settings (provided here).

To provide the default credentials setting:

1. Navigate to the **Default Device Credentials** tab.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Default Device Credentials** tab.
2. Provide the default attribute values (see [table](#)).
3. Click  **Save and Close** to return to the Communication Configuration form.
4. Click  **Save and Close** to apply your changes.

NNM iSPI NET uses the Default Credentials setting to access devices when running Diagnostics either automatically or when the **Actions** → **Run Diagnostics** option is used. (See "[Configure Diagnostics for an Incident](#)" on page 857 and [Node Form: Diagnostics Tab](#) for more information.)

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

At each level in the sequence to determine the Device Credentials (see bullet list above), NNMi first uses Secure Shell (SSH) to establish a secure connection, and if the SSH attempt fails, NNMi tries Telnet protocol as the communication method.

Caution: By default, neither Microsoft Internet Explorer nor Mozilla Firefox defines the telnet command nor the SSH command, so using either of these menu items produces an error message. See the "Configuring the Telnet and SSH Protocols for Use by NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for configuration information.

Default Device Credential Attributes

Attribute	Description
User Name	Type the user name that you want NNMi to use for logging into devices by default (when no Region or Specific Node settings work).
Password	Type the password that you want NNMi to use for logging into devices by default (when no Region or Specific Node settings work). <div>Note: NNMi encrypts the password and displays asterisks for this attribute. If you want to change the password, first clear the asterisks displayed in the Password attribute and enter the new Password value.</div>

Configure Regions (Communication Settings)

Configuring communication protocols for regions is optional.

Note: If you provide an SNMPv1 or SNMPv2c *read community string* or an SNMPv3 USM Setting for a specific device, NNMi honors your choice and does not try any Region or Default settings for that device.





Use the Regions tab to fine tune communication protocol usage and settings for particular regions of your network (for example, buildings, floors within those buildings, workgroups within a particular floor, or [private IP addresses](#)¹). When you leave a field blank in a region definition, NNMi uses the next applicable configuration setting in the following order:

- The value for each field as defined in the first Region definition that matches, Regions are checked according to the Ordering number. The match with the lowest Ordering number applies.
- If no Region definition provides a value for an attribute, the default value is used.



Note: NNMi enables you to set up one or more SNMP Proxy Servers when an SNMP node is otherwise unreachable (for example, when a node you want to manage is behind a firewall). To enable NNMi to use the SNMP Proxy Server, when you configure communication protocols for network regions, you must include the IP address and port number on the SNMP Proxy Server. See "[Communication Region Form](#)" on the next page for more information.

If your communication protocol usage is too complex for Region definitions, see "[Configure Specific Nodes](#)" on page 169.

To configure communication protocols for a particular region of your network:

1. Navigate to the **Communication Region** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:
 - To establish a region definition, click the  New icon, and continue.
 - To edit a region definition, select a row, click the  Open icon, and continue.
 - To delete a region definition, select a row and click the  Delete icon.
2. Provide the required information. Define the regions with wildcard address, wildcard device names, or literal addresses and names . See "[Communication Region Form](#)" on the next page.

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*.*, 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

3. Click  **Save and Close** to return to the Communication Configuration form.
4. Click  **Save and Close** to apply your changes.

Related Topics:






["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#)

["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#)

["Configure Specific Nodes " on page 169](#)

Communication Region Form

To configure communication regions:

1. Navigate to the **Communication Region** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:
 - To establish a region definition, click the  **New** icon.
 - To edit a region definition, select a row, click the  **Open** icon.
2. Provide the basic communication region definition (see the [Regional Basic Settings](#) table, [Regional SNMP Settings](#) table, and [Regional ICMP Settings](#) table).
3. Make your configuration choices. Click [here](#) for a list of choices .
4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.

Regional Basic Settings

Attribute	Description
Name	A name for this region.
Ordering	<p>A numeric value. NNMi checks for configuration settings in the order you define (lowest number first). NNMi uses the first match found for each address.</p> <p>No duplicate Ordering numbers are permitted. Each Communication Region ordering number must be unique.</p>

Regional Basic Settings, continued

Attribute	Description
	<p>Tip: Consider incrementing Ordering numbers by 10s or 100s to provide flexibility when adding new regions over time.</p>
Description	<p><i>Optional.</i> Provide any description that would be useful for communication purposes within your team.</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Regional SNMP Settings

Attribute	Description
Enable SNMP Communication	<p>If <input checked="" type="checkbox"/> enabled, the Discovery Process and State Poller Service generate network traffic with SNMP protocol to discover and monitor your network devices in this region.</p> <p>If <input type="checkbox"/> disabled, NNMi does not generate any SNMP traffic on your network in this region.</p> <p>Caution: At least one IP Address in each node must have SNMP enabled, otherwise no SNMP data is collected from that Node. With no SNMP data, Spiral Discovery interprets each IP Address as a separate node, Causal Engine calculates Status based only on IP address State, previously discovered Interfaces show a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the Interface map-symbol color set to beige, and no new Interfaces are discovered.</p> <p>Note: If you use Auto-Discovery, NNMi might detect Nodes and add them to the NNMi database as non-SNMP nodes. To configure Auto-Discovery to not add specified IP addresses to the NNMi database, not acknowledge any Hints received about them, nor gather Discovery Hints from them unless the address is a discovery seed, see "Set Outside Limits for Auto-Discovery" on page 251.</p>
Enable SNMP Address Rediscovery	<p>Note: The NNMi administrator can over-ride this setting on a per-node basis. See "Specific Node Settings Form (Communication Settings)" on page 171.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi automatically identifies which management address (SNMP agent) to use for each device. If the initially configured address becomes unreachable, NNMi automatically locates another address, if possible, and changes the management address attribute value. Click here for</p>

Regional SNMP Settings, continued

Attribute	Description
	<p>more information.</p> <p>When NNMi first discovers a node, the <i>seed address</i> (provided by the NNMi administrator) or discovered address (for non-seeded nodes) becomes the initial address used for SNMP communication. After NNMi builds an inventory of all IP addresses associated with the node (see "How Spiral Discovery Works" on page 195), NNMi follows a set of rules to determine which address is the best choice for each node's Management Address:</p> <div data-bbox="506 590 1370 768" style="background-color: #f0f0f0; padding: 10px; border: 1px solid #ccc;"> <p>Note: (NNMi Advanced) The NNMi administrator specifies whether NNMi prefers IPv4 addresses, IPv6 addresses, or dual-stack (both) when selecting the Management Address. See Configure Default SNMP, Management Address, and ICMP Settings.</p> </div> <ol style="list-style-type: none"> 1. NNMi ignores the following addresses when determining which Management Address is most appropriate: <ul style="list-style-type: none"> ■ Any address of an administratively-down interface. ■ Any address that is virtual (for example, VRRP¹). ■ Any IPv4 Anycast Rendezvous Point IP Address² or IPv6 Anycast address. ■ Any address in the reserved loopback network range. IPv4 uses 127/24 (127.*.*.*) and IPv6 uses ::1. ■ Any IPv6 link-local address³. 2. If the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi prefers the last-known Management Address (if any). 3. If the Management Address does not respond and the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi uses the Communication Configuration settings for <i>Management Address Selection</i>. The NNMi Administrator chooses the order in which NNMi checks the following:

¹Virtual Router Redundancy Protocol

²Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

³A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

Regional SNMP Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Seed IP / Management IP - If the NNMi Administrator configures a Seed, NNMi uses the Seed address (either a specified IP address or the DNS address associated with a specified hostname) only during initial Discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery. ■ Lowest Loopback - If a node supports multiple loopback address¹, NNMi queries each loopback addresses, starting with the lowest number. NNMi uses the loopback address with the lowest number from which the SNMP agent responds (for example, 10.16.42.197 is a lower number than 10.16.197.42). ■ Highest Loopback - If a node supports multiple loopback address², NNMi queries each loopback addresses, starting with the highest number. NNMi uses the loopback address with the highest number from which the SNMP agent responds. ■ Interface Matching - The NNMi Administrator chooses which interface MIB variable NNMi queries to detect changes. NNMi can use the following MIB-II attribute values: ifIndex, ifName, ifDescr, ifAlias, or a combination of these (ifName or ifDescr, ifName or ifDescr or ifAlias). NNMi searches current database entries for information about the interface in this order: index, alias, name, and description. If multiple IP addresses are associated with the interface, NNMi starts by querying the lowest IP address and selects the first responding address in ascending order. <ol style="list-style-type: none"> 4. If no response, NNMi queries any remaining IP addresses in the node's IP address inventory, starting with the lowest number. NNMi uses the address with the lowest number from which the SNMP agent responds. 5. If no response, NNMi checks for any Mapped Address configured for one of the currently known addresses (see the Mapped Address column in the Custom IP Addresses view).

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

²The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

Regional SNMP Settings, continued

Attribute	Description
	<div data-bbox="542 338 1370 569" style="background-color: #f0f0f0; padding: 10px; border: 1px solid #ccc;"> <p>Note: The address represents a <i>static</i> Network Address Translation (NAT) pair's <i>external IP address</i> from the internal/external IP address pair. NNMi Administrators configure these pairs using the Overlapping IP Address Mapping form. NNMi uses this list of addresses starting with IPv4 from low to high, then IPv6 from low to high.</p> </div> <p>6. If no response, NNMi might be configured to repeat the sequence using SNMPv1, SNMPv2c, or SNMPv3 in the order specified by the NNMi administrator (Communication Configurations <i>SNMP Minimum Security Level</i> settings).</p> <p>7. When all else fails, NNMi retains the last known Management Address (if any) and automatically changes the State of that SNMP Agent object to Critical.</p> <p>This process is repeated during each Spiral Discovery cycle, and the Management Address can change. For example, NNMi's inventory of addresses for the node expands, or the current Management Address does not respond to SNMP queries due to network problems or node reconfiguration. The NNMi administrator can prevent changes to the management address using the Communication Configurations <i>Enable SNMP Address Rediscovery</i> or <i>Preferred Management Address</i> setting.</p> <p>If <input type="checkbox"/> disabled, when the current management address (SNMP agent) becomes unreachable, NNMi reclassifies the node as a non-SNMP node until the previously configured management address is available again.</p>
Enable SNMP GetBulk	<p><i>Applies only to SNMPv2 or higher.</i> If you have devices in your network environment that have trouble responding to GetBulk commands, you can instruct NNMi to use Get or GetNext instead of GetBulk.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi uses the SNMPv2c GetBulk command to gather information from devices in this Region of your network environment.</p> <p>If <input type="checkbox"/> disabled, NNMi uses the SNMP Get or GetNext command to gather information from devices in this Region of your network environment (requesting responses for one SNMP OID at a time).</p>
SNMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an SNMP query before reissuing the request. Both the Discovery Process and the State Poller Service use this setting in this region. For an explanation of how NNMi implements timeout and retry configurations, see "Timeout / Retry Behavior Example for SNMP" on page 138.</p>

Regional SNMP Settings, continued

Attribute	Description
SNMP Retries Count	Maximum number of retries that NNMi issues for an SNMP query before determining the query result to be "unresponsive". Zero means no retries. Both the Discovery Process and the State Poller Service use this setting in this region.
SNMP Port	Default is 161. Specifies the management server's port that NNMi uses when generating SNMP traffic. Both the Discovery Process and the State Poller Service use this setting in this region.
SNMP Proxy Address	<p><i>Optional.</i> IP address of the your SNMP Proxy Server (for example, a proxy that gathers data from non-SNMP devices and can use that data to respond to NNMi SNMP requests).</p> <p>To enable a proxy, you must also provide the port number of your SNMP Proxy Server. See SNMP Proxy Port (next attribute).</p> <div> <p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the "NNMi Communications" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p> </div>
SNMP Proxy Port	<p><i>Optional.</i> Port number of the SNMP Proxy Server.</p> <p>To enable a proxy, you must also provide the IP address of your SNMP Proxy Server. See SNMP Proxy Address (previous attribute).</p> <div> <p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the "NNMi Communications" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p> </div>
SNMP Minimum Security Level	<p>This setting determines whether each NNMi Rediscovery cycle automatically detects the best SNMP choice (v1, v2, or v3) for each Node (automatically detects any upgrade to the SNMP agent on each Node), or uses only the SNMP version that you specify.</p> <p>For SNMPv1 or SNMPv2c, configure NNMi to use Community Strings in your network environment:</p> <ul style="list-style-type: none"> Community Only (SNMPv1) NNMi tries only SNMPv1 settings. Community Only (SNMPv1 or v2c) NNMi first tries to use SNMPv2c settings, and, if that fails, NNMi tries SNMPv1 settings.

Regional SNMP Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> Community NNMi first tries to use SNMPv2c settings, and, if that fails, NNMi tries SNMPv1 settings. If both SNMPv2c and SNMPv1 fail, NNMi tries SNMPv3 settings if any are available. <p>For SNMPv3, configure NNMi to use the User-based Security Module (USM) level of security required in your network environment (if your environment also uses SNMPv1/SNMPv2c, select Community):</p> <ul style="list-style-type: none"> No Authentication, No Privacy Authentication, No Privacy Authentication, Privacy <p>See "Timeout / Retry Behavior Example for SNMP" on page 138 for an explanation of NNMi behavior with each of these choices.</p>

Regional ICMP Settings







Attribute	Description
Enable ICMP Communication	<p>If <input checked="" type="checkbox"/> enabled, NNMi generates network traffic with ICMP protocol in this region.</p> <p>If <input type="checkbox"/> disabled, NNMi does not generate any ICMP traffic on your network in this region:</p> <ul style="list-style-type: none"> Addresses in this Region (both previously discovered and newly discovered) have a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the IP Address map-symbol color set to beige. Nodes with all IP addresses and interfaces showing a Status attribute value of "No Status" have a map-symbol background shape color set to beige. However, it is possible for a node to have IP addresses in multiple regions with multiple Status values. <p>Note: See "Monitoring Network Health" on page 378 for information about enabling/disabling ICMP communication specifically for the State Poller Service.</p>
ICMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an ICMP query before reissuing the request in this region. For an explanation of how NNMi implements timeout</p>

Regional ICMP Settings, continued

Attribute	Description
	and retry configurations, see "Timeout / Retry Behavior Example for ICMP" on page 139 .
ICMP Retries Count	Maximum number of retries that NNMi issues for an ICMP query in this region before logging an error. Zero means no retries.

Configure Address Ranges for Regions



To configure an address range for this region:

1. Navigate to the **Region Included Address Range** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:
 - To establish a region definition, click the  **New** icon.
 - To edit a region definition, select a row, click the  **Open** icon.
 - e. In the **Communication Region** form, navigate to the **Included Address Regions** tab.
 - f. Do one of the following:
 - To establish an address range setting, click the  **New** icon.
 - To edit an address range setting, select a row, click the  **Open** icon.
 - To delete an address range setting, select a row and click the  **Delete** icon.
2. Provide address range definition (see [table](#)).

If you provide multiple IP address ranges for a region, each device must pass at least one to meet the criteria.

Tip: If you provide both IP address ranges and hostname wildcards, each device must pass at least one in either category (not both) to meet the criteria.

3. Click  **Save and Close** to return to the Communication Region form.

4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.

Address Range Definition Attribute

Attribute	Description
IP Range	<p>To specify a range of IP addresses for this Communications Region, use one of the following. Pick one address notation style, combinations of wildcards and CIDR notation are not permitted within one address range. You can provide multiple address range settings:</p> <ul style="list-style-type: none">• IPv4 address wildcard notation.<p>An IPv4 Address range is a modified dotted-notation where each octet is one of the following:</p><ul style="list-style-type: none">■ A specific octet value between 0 and 255■ A low-high range specification for the octet value (for example, "112-119")■ An asterisk (*) wildcard character, which is equivalent to the range expression "0-255"<div>Note: The following two IPv4 addresses are considered invalid: 0.0.0.0 and 127.0.0.0</div><p>Examples of valid IPv4 address wildcards include:</p><p>10.1.1.* 10.*.*.* 10.1.1.1-99 10.10.50-55.* 10.22.*.4 10.1-9.1-9.1-9</p>• IPv4 Classless Inter-Domain Routing (CIDR) notation.<p>The CIDR notation specifies the number of consecutive bits in the IPv4 address that must match.</p><p>For example, 10.2.120.0/21</p><div>Note: NNMi does not support CIDR subnet mask notation such as, 10.2.120.0/255.255.248.0</div>

Address Range Definition Attribute , continued

Attribute	Description										
	<table> <tr> <th>Example IPv4 Prefix Length Values</th><th>Number of Usable IPv4 Addresses</th></tr> <tr> <td>28</td><td>14 (16-2=14)*</td></tr> <tr> <td>29</td><td>6 (8-2=6)*</td></tr> <tr> <td>30</td><td>2 (4-2=2)*</td></tr> <tr> <td>31</td><td>2</td></tr> </table> <p>* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.</p> <ul style="list-style-type: none"> IPv6 address wildcard notation <i>(NNMi Advanced)</i> Separate each 16-bit value of the IPv6 address with a colon. The 16-bit value can be any of the following: <ul style="list-style-type: none"> A specific hexadecimal value between 0 and FFFF (case insensitive). A low-high range specification of the hexadecimal value (for example, 1-1fe). An asterisk (*) wildcard character (equivalent to the range expression 0-ffff). <div> Note: The standard IPv6 short-hand notation (:) is allowed to express one or more 16-bit elements of zero (0) values. However, the mixed IPv6/IPv4 dot-notation (for example, 2001:d88::1.2.3.4) is not permitted as an IPv6 address range. </div> <p>Valid examples of ranges in modified IPv6 address notation include the following:</p> <pre>2001:D88:0:A00-AFF::*:*:* 2001:D88:1::*:*:*:* 2001:D88:2:0:a07:ffff:0a01:3200-37ff</pre> IPv6 Classless Inter-Domain Routing (CIDR) notation <i>(NNMi Advanced)</i> The CIDR notation specifies the number of consecutive bits in the IPv6 address that must match. <p>2001:d88:a00::/44 (equivalent to modified IPv6 address notation 2001:d88:a00-a0f::*:*:*:*)</p> <p>For example, valid IPv6 address ranges in CIDR notation include the following:</p> <pre>2001:d88:0:a00::/56 (equivalent to modified IPv6 address notation 2001:D88:0:A00-AFF::*:*:*:*)</pre> 	Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses	28	14 (16-2=14)*	29	6 (8-2=6)*	30	2 (4-2=2)*	31	2
Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses										
28	14 (16-2=14)*										
29	6 (8-2=6)*										
30	2 (4-2=2)*										
31	2										







Address Range Definition Attribute , continued

Attribute	Description
	2001:d88:1::/48 (equivalent to modified IPv6 address notation 2001:D88:1:*:*:*:*)

Configure Hostname Filters for Regions



Define the [Communication Region](#) with hostname patterns.


To establish a Hostname Filter setting:

1. Navigate to the **Region Hostname Filter** form.
 - From the workspace navigation panel, select the  **Configuration** workspace.
 - Select the **Communication Configuration**.
 - Navigate to the **Regions** tab.
 - Do one of the following:
 - To create a region definition, click the  New icon.
 - To edit a region definition, select a row, click the  Open icon.
 - In the **Communication Region** form, access the **Hostname Filters** tab.
 - Do one of the following:
 - To create a hostname wildcard definition, click the  New icon.
 - To edit a hostname wildcard definition, select a row, click the  Open icon.
 - To delete a hostname wildcard setting, select a row and click the  Delete icon.
2. Type an appropriate hostname filter (see [table](#)).

If you provide multiple hostname wildcard expressions for a region, each device must pass at least one to meet the criteria for the Region.

Tip: If you provide both hostname wildcards and IP address ranges, each device must pass at least one in either category (not both) to meet the criteria for the Region.

3. Click  **Save and Close** to return to the Communication Region form.
4. Click  **Save and Close** to return to the Communication Configuration form.

5. Click  **Save and Close** to apply your changes. See ["Discovering Your Network" on page 194](#) and [Verify Device Configuration Details](#).

Node Hostname Filter Definition

Attribute	Description
Hostname Filter	<p>Enter a wildcard expression using the following characters as wildcards:</p> <ul style="list-style-type: none"> • ? = one character • * = multiple characters <p>Wildcard expressions are <i>not case-sensitive</i>. So a wildcard of ABC* would match devices with hostnames beginning with ABC*, abc*, and Abc*</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: The Hostname attribute value on the Node form of the discovered node must match (not case-sensitive) what is entered here.</p> </div> <p>NNMi follows a set of rules to dynamically generate the value stored in the NNMi database for each Node's Hostname. Click here for details.</p> <ul style="list-style-type: none"> • If the Node supports SNMP, NNMi requests the Hostname using the IP Address of the associated SNMP agent (the Management Address attribute value on the Node form). <p>When the NNMi administrator chooses Enable SNMP Address Rediscovery <input checked="" type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ■ If the SNMP Agent does not respond, NNMi checks for another Management Address to request the Hostname, and the Hostname could change. ■ If the SNMP Agent associated with the node changes, the Management Address and Hostname could change. <p>When the NNMi administrator disables Enable SNMP Address Rediscovery <input type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ■ If the SNMP Agent does not respond, NNMi uses the previously gathered Management Address attribute value to request the Hostname. ■ If the SNMP Agent associated with the node changes, NNMi uses the previously gathered Management Address attribute value to request the Hostname. <ul style="list-style-type: none"> • If the Node does not support SNMP, no Management Address is available. NNMi requests a Hostname starting with the lowest IP Address associated with the node (a Discovery Seed value or an IP address value gathered from a neighboring device). NNMi uses the first Hostname provided. The Hostname might change during a future discovery cycle.

Node Hostname Filter Definition , continued

Attribute	Description
	<p>Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:</p> <ul style="list-style-type: none">• <code>nms-topology.properties</code> file settings: If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.• <code>nms-disco.properties</code> file settings: The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.

Configure SNMPv1/v2c Community Strings for Regions

If more than one SNMPv1 or SNMPv2c "get" community string is used within this region, repeat this step any number of times. Order does not matter because all community strings defined for this Region are checked in parallel.

During initial discovery, NNMi tries many community strings until a match is found. After a match is identified for a Node, the information is recorded to prevent future authentication errors.

NNMi uses the SNMPv2c settings to discover the SNMPv2c information about your network. This also determines whether NNMi *receives or discards incoming* SNMPv2c traps. [Click here for more information](#).

- If the *incoming* trap's Source Node (and sometimes Source Object, such as card or interface) has not yet been discovered by NNMi, NNMi discards the trap. See "[Handle Unresolved Incoming Traps](#)" on page 878 for additional information. See also "[Configure Network Devices to Send SNMP Notifications to NNMi](#)" on page 872.
- If the Source Node was not discovered using SNMv3, NNMi discards any incoming SNMPv3 traps from that Node.
- NNMi discards traps that have no incident configuration or with an incident configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3

protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap. See ["Configure SNMP Trap Incidents" on page 886](#).




- If either the Source Node or Source Object has *Management Mode* set to **Not Managed** or **Out of Service** in the NNMi database, NNMi always discards the incoming trap. See Understand the [Effects of Setting the Management Mode to Not Managed or Out of Service](#).

NNMi provides the Management Mode workspace so that you can quickly view lists of all nodes, interfaces, IP addresses, chassis, cards, node sensors, or physical sensors that NNMi is not currently discovering or monitoring. For information about these views:


- NNMi discards most incoming traps from network objects that are not monitored. For example, you can configure NNMi to exclude specified interfaces from being monitored. See ["Monitoring Network Health" on page 378](#) for more information.



Note: If you want the NNMi management server to *forward* SNMPv2c traps to other machines in your network environment, see ["Configure Trap Forwarding" on page 1407](#) for additional configuration steps.

To provide a community string for this region:




1. Navigate to the **Communication Region** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:
 - To establish a region definition, click the  **New** icon.
 - To edit a region definition, select a row, click the  **Open** icon.
2. In the **Communication Region** form, navigate to the **SNMPv1/v2c Community Strings** tab.
3. To provide a *read community string*, navigate to the **Read Community Strings** table and do one of the following:

Note: If you do not provide any community strings, NNMi uses the [Default Community Strings](#).

- To establish a community string setting, click the  **New** icon, and provide the required information (see [table](#)).

- To edit a community string setting, select a row, click the  Open icon, and provide the required information (see [table](#))
 - To delete a community string setting, select a row and click the  Delete icon
4. To provide a *write community string* for this region, navigate to the **Write Community String** attribute (see [table](#)).

Note: If you do not provide any community strings, NNMi uses the [Default Community Strings](#).

5. Click  **Save and Close** to return to the Communication Region form.
6. Click  **Save and Close** to return to the Communication Configuration form.
7. Click  **Save and Close** to apply your changes.

SNMPv1 or SNMPv2c Community String for this Region

Attribute	Description
Read Community String	<p>Note: As an NNMi administrator, you can over-ride this setting and specify the Read Community String on a per-node basis using the SNMP Agent Form.</p> <p>The SNMPv1 or SNMPv2c "Get" (read-only) Community String that is used for this region (case-sensitive).</p> <p>Tip: If no values appear in this table, the default settings are used (see "Configure Default Community Strings (SNMPv1 or SNMPv2c)" on page 140).</p> <p>Many proxy vendors use the <i>read community string</i> for specifying remote target information. NNMi supports substitution parameters within read community strings for SNMPv1 or SNMPv2c proxy environments. Click here for more information.</p> <p>Copy and paste these codes at the end of your read community string to provide the values required by your proxy environment. NNMi substitutes the actual attribute values from the NNMi database at runtime:</p> <p><code>\${contextName}</code> = Used for specifying VLAN context for switches (VLAN associated with the remote target node)</p> <p><code>\${managementAddress}</code> = Node form, Management Address attribute value (the remote target node)</p> <p><code>\${snmpPort}</code> = SNMP Agent form, UDP Port attribute value (SNMP agent associated with the remote target node)</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special</p>


SNMPv1 or SNMPv2c Community String for this Region , continued



Attribute	Description
	characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
Ordering	<i>Optional.</i> During the Discovery process, NNMi tries Read Community Strings in priority order (lowest to highest). Then, NNMi tries all unordered Read Community Strings (treated as though they had the same Ordering number). These unordered requests are sent in parallel, with NNMi using the first response.
Write Community String	<p><i>Optional.</i> For use with the nnmsnmpset.ovpl command line tool.</p> <p>The SNMPv1 or SNMPv2c "Set" (write) Community String that is used for the SNMP Agent for each node in this region (case-sensitive).</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: SNMP Agents are often configured with different community strings for "Set" requests than for "Get" (read) requests.</p> </div> <p>SNMPv1 and SNMPv2c require that you know the SNMP agent's <i>write community string</i> before you can change settings on any device. The nnmsnmpset.ovpl command can use the value you provide here, rather than requiring that you type the write community string each time you invoke the command.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: If no value is provided here, the default settings are used (see "Configure Default Community Strings (SNMPv1 or SNMPv2c)" on page 140).</p> </div> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>Because this is a type of password, you must enter the value twice.</p>

Configure SNMPv3 Settings for Regions

NNMi can use SNMPv3 user-based security model (USM) settings to access devices.


To view the current list of SNMPv3 USM settings for a Region:


1. Navigate to the **SNMPv3 Settings** tab on the Communication Region form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:


- To create a region definition, click the  New icon.
 - To edit a region definition, select a row, click the  Open icon.
 - e. In the **Communication Region** form, access the **SNMPv3 Settings** tab.
2. The displayed table lists the Unique Name of each SNMPv3 USM setting for this region.


Note: NNMi tries to use the [Specific Node SNMPv3 Settings](#). If none match, NNMi tries the Region SNMPv3 Settings provided here. If none match, NNMi tries the [default SNMPv3 settings](#).

3. You can also do the following:

- To establish a new setting, click the  New icon. See "[Communication Region SNMPv3 Settings form](#)" below.



Click  **Save and Close** to return to the Communication Region form.

- To edit an existing setting, select a row, click the  Open icon. See "[Communication Region SNMPv3 Settings form](#)" below.

Click  **Save and Close** to return to the Communication Region form.

- To delete a setting from the Region's list, select a row and click the  Delete icon.

Note: The record remains in the database for possible use elsewhere and is simply removed from this Communication Region's list.


4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.






Communication Region SNMPv3 Settings form

NNMi can use SNMPv3 user-based security model (USM) settings to access devices.










NNMi tries to use the current SNMPv3 Settings attribute value from [Specific Node Settings](#). If none match, NNMi tries the Region SNMPv3 Settings provided here. If none match, NNMi tries the [default SNMPv3 settings](#).

To configure an SNMPv3 Setting for a Region:

1. Navigate to the **Communication Region SNMPv3 Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.

- b. Select the **Communication Configuration**.
- c. Navigate to the **Regions** tab.
- d. Do one of the following:
 - To create a region definition, click the  New icon.
 - To edit a region definition, select a row, click the  Open icon.
- e. In the **Communication Region** form, navigate to the **SNMPv3 Settings** tab.
- f. Do one of the following:
 - To create an SNMPv3 Setting definition, click the  New icon.
 - To edit an SNMPv3 Setting, select a row, click the  Open icon.
 - To remove an SNMPv3 Setting from this Region, select a row, click the  Delete icon.

Note: The record remains in the database for possible use elsewhere and is simply removed from this Communication Region's list.

2. Click the SNMPv3 Settings  Lookup icon and select one of the options from the drop-down menu:
 -  Show Analysis to display Analysis Pane information for the currently configured (selected) SNMPv3 Setting name. (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
 -  Quick Find to view and select from the list of all existing SNMPv3 Settings (for more information see ["Use the Quick Find Window" on page 38](#)).
 -  Open to display the details of the currently configured (selected) SNMPv3 Setting (see [SNMPv3 Settings Form](#) for more information).
 -  New to create a new SNMPv3 Setting (see [SNMPv3 Settings Form](#) for more information).
3. Click  **Save and Close** to return to the Communication Region SNMPv3 Settings form.
4. Click  **Save and Close** to return to the Communication Region form.
5. Click  **Save and Close** to return to the Communication Configuration form.
6. Click  **Save and Close** to apply your changes.

Configure Credential Settings for Regions

NNMi uses the Device Credentials settings for the following:







- Device discovery of some vendor-specific devices that require non-SNMP communication, such as Netconf over SSH. For a list of these devices see the NNMi Device Support Matrix.
- Device Diagnostics




Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

NNMi uses the following sequence to determine Device Credentials:

- Use the [Specific Node Device Credentials](#). If none match, continue.
- Use the Region Device Credentials (provided here). If none match, continue.
- Use the [Default Credential](#) settings.

To provide credential settings for this region:

1. Navigate to the **Region Device Credentials** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Regions** tab.
 - d. Do one of the following:
 - To establish a region definition, click the  **New** icon.
 - To edit a region definition, select a row, click the  **Open** icon.
 - e. In the **Communication Region** form, navigate to the **Device Credentials** tab.
 - f. Do one of the following:
 - To establish a credential setting, click the  **New** icon, and continue.
 - To edit a credential setting, select a row, click the  **Open** icon, and continue.
 - To delete a credential setting, select a row and click the  **Delete** icon.
2. Provide the attribute values of credentials for this region (see [table](#)).

3. Click  **Save and Close** to return to the Communication Region form.
4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.

NNM iSPI NET uses the Default Credentials setting to access devices when running Diagnostics either automatically or when the **Actions** → **Run Diagnostics** option is used. (See "[Configure Diagnostics for an Incident](#)" on page 857 and [Node Form: Diagnostics Tab](#) for more information.)

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

At each level in the sequence to determine the Device Credentials (see bullet list above), NNMi first uses Secure Shell (SSH) to establish a secure connection, and if the SSH attempt fails, NNMi tries Telnet protocol as the communication method.

Caution: By default, neither Microsoft Internet Explorer nor Mozilla Firefox defines the telnet command nor the SSH command, so using either of these menu items produces an error message. See the "Configuring the Telnet and SSH Protocols for Use by NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for configuration information.

Device Credential Attributes for this Region

Attribute	Description
User Name	Type the user name that you want NNMi to use for logging into devices in this Communication Region.
Password	Type the password that you want NNMi to use for logging into devices in this Communication Region. <div>Note: NNMi encrypts the password and displays asterisks for this attribute. If you want to change the password, first clear the asterisks displayed in the Password attribute and enter the new Password value.</div>

Configure Specific Nodes

Configuring communication protocols for specific devices is optional.

NNMi supports the following ways to configure communication protocol for devices:

- Use the [Specific Node Settings](#) tab from the [Communication Configuration](#) form.
Use the **Specific Node Settings** tab when you want to provide exceptions to the Communication Region configurations rather than to directly manage settings for a large numbers of nodes. The **Specific Node Settings** tab enables you to fine tune communication

protocol usage and settings for a particular device within your environment. For example, provide settings for your most important devices, or disable communication with the least important devices.

When you leave a field blank, NNMi uses the next applicable configuration setting for that field in the following order:

- The value configured for a Region that includes this device. If multiple Region definitions include this device (for example, buildings, floors within those buildings, or work groups within a particular floor), the first match applies (the matching region with the lowest Ordering number) . See ["Configure Regions \(Communication Settings\)" on page 148](#).
- The default value for this field (see ["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#), ["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#), ["Configure the Default Device Credentials" on page 147](#), and ["Configure Default SNMPv3 Settings" on page 145](#).

Note: You can use the **Specific Node Settings** tab to configure Communication Protocol for a Node before it is discovered. During discovery, NNMi uses the Node host name to match the Specific Node Communication Configuration settings. If the Node host name changes, the Specific Node Communication Configuration settings no longer match and NNMi uses the settings configured in the Communication Configuration **Regions** tab.

See ["Specific Node Settings Form \(Communication Settings\)" on the next page](#) for more information.

- [Use the Locked SNMP Agent Settings Mode to directly manage communications parameters.](#)

Use the [SNMP Agent Form Mode](#) attribute when you want to directly manage Communication Configuration settings for one or more nodes.

Set Mode to **Locked** when you want full control over the communication configuration settings. When the SNMP Agent Settings Mode is set to **Locked**, NNMi ignores the Communication Configuration Settings and uses the SNMP Agent values configured in the SNMP Agent Form.

Note: Using **Locked** Mode is only available after the Node is discovered. The SNMP Agent Settings will be used for the Node even if the Node host name changes.

Use the [SNMP Agent Form](#) or [nnmcommunication.ovpl](#) to set the **Mode** value and any additional SNMP Agent Settings for one or more nodes.

If you change the SNMP Agent Form configuration settings, note the following:

- If you do not set a node's SNMP Agent Form Settings **Mode** to **Locked**, your changes might be subsequently overwritten by the Communication Configuration settings.

- Editing the SNMP Agent Settings using the SNMP Agent Form is most useful after you have used [nnmcommunication.ovpl](#) to set configuration values for a large number of nodes and then need to change the one or more SNMP Agent Settings for a small number of nodes.
- You can also use the `listSnpAgentSettings` and `updateSnpAgentSettings` options to [nnmconfiguration.ovpl](#) to view the current SNMP Agent Settings for a specified node.
- ["Load Communication Settings from a File" on page 185](#)
NNMi enables you to bulk load or update any of the Communication Configuration or SNMP Agent Settings that you can configure when using [nnmcommunication.ovpl](#).





Specific Node Settings Form (Communication Settings)

Create specific node settings to control the way NNMi monitors your most important devices or least important devices.

Tip: If no value is provided for an attribute in the Communication Node form, NNMi uses the applicable [Region settings](#) and if none match, NNMi uses the [default settings](#).



If configuring Specific Node Settings, also see the *HP Network Node Manager i Software Deployment Reference* which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To configure communication protocol settings for a specific node:

1. [Access the Specific Node Settings form.](#)
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Communication Configuration**.
 - c. Navigate to the **Specific Node Settings** tab.
 - d. Do one of the following:
 - To establish settings for a node, click the  New icon, and continue.
 - To edit settings for a node, select a row, click the  Open icons, and continue.
 - To delete settings for a node, select a row and click the  Delete icon.
2. Provide the communication protocol settings for the node (see the [Basic Settings](#) table, [SNMP Settings](#) table, and [ICMP Settings](#) table).

For an explanation of how NNMi implements timeout and retry configurations, see ["Timeout / Retry Behavior Example for SNMP" on page 138](#) and ["Timeout / Retry Behavior Example for ICMP" on page 139](#).

3. *Optional.* Make additional configuration choices. Click [here](#) for a list of choices .

4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.

Basic Settings for this Device

Attribute	Description
Target Hostname	<p>The Hostname attribute value from the Node form of the discovered node must match what is entered here. Case-insensitive, NNMi automatically converts the hostname to all lowercase on the Node form.</p> <p>NNMi follows a set of rules to dynamically generate the value stored in the NNMi database for each Node's Hostname. Click here for details.</p> <ul style="list-style-type: none"> • If the Node supports SNMP, NNMi requests the Hostname using the IP Address of the associated SNMP agent (the Management Address attribute value on the Node form). <p>When the NNMi administrator chooses Enable SNMP Address Rediscovery <input checked="" type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ■ If the SNMP Agent does not respond, NNMi checks for another Management Address to request the Hostname, and the Hostname could change. ■ If the SNMP Agent associated with the node changes, the Management Address and Hostname could change. <p>When the NNMi administrator disables Enable SNMP Address Rediscovery <input type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ■ If the SNMP Agent does not respond, NNMi uses the previously gathered Management Address attribute value to request the Hostname. ■ If the SNMP Agent associated with the node changes, NNMi uses the previously gathered Management Address attribute value to request the Hostname. <ul style="list-style-type: none"> • If the Node does not support SNMP, no Management Address is available. NNMi requests a Hostname starting with the lowest IP Address associated with the node (a Discovery Seed value or an IP address value gathered from a neighboring device). NNMi uses the first Hostname provided. The Hostname might change during a future discovery cycle. <p>Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:</p> <ul style="list-style-type: none"> • <code>nms-topology.properties</code> file settings:

Basic Settings for this Device , continued

Attribute	Description
	<p>If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> <ul style="list-style-type: none"> nms-disco.properties file settings: The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.
Preferred Management Address	<p>Do one of the following:</p> <ul style="list-style-type: none"> Specify the address you want NNMi to use for SNMP communications with this device. If you enter an invalid or unreachable address, the device is not discovered or monitored. Leave this attribute empty. NNMi dynamically selects the management address, based on responses from the device's SNMP agent and your choices in "Configure Default SNMP, Management Address, and ICMP Settings" on page 130. <p>Note: The NNMi administrator can over-ride this setting. See the Enable SNMP Communication attribute and the Enable SNMP Address Rediscovery attribute settings.</p>
Description	<p><i>Optional.</i> Provide a description for this configuration that would be useful for communication purposes within your team.</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ +) are permitted.</p>

SNMP Settings for this Device

Attribute	Description
Enable SNMP Communication	<p>If <input checked="" type="checkbox"/> enabled, the Discovery Process and State Poller Service generate network traffic with SNMP protocol to discover and monitor this device.</p>

SNMP Settings for this Device , continued

Attribute	Description
	<p>Note: Your choice might be overridden if Monitoring Configuration settings disable SNMP usage for the State Poller Service, see "Global Control Settings for Monitoring" on page 391 or "Configure NNMi Monitoring Behavior" on page 387.</p> <p>If <input type="checkbox"/> disabled, NNMi does not generate any SNMP traffic to this device.</p> <p>Caution: With no SNMP data, Spiral Discovery interprets each IP Address as a separate node, Causal Engine calculates Status based only on IP address State, previously discovered Interfaces show a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the Interface map-symbol color set to beige, and no new Interfaces are discovered.</p>
Enable SNMP Address Rediscovery	<p>Note: The NNMi administrator can over-ride this setting. See the Enable SNMP Communication and the Preferred Management Address attributes.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi automatically identifies which management address (SNMP agent) to use for each device. If the initially configured address becomes unreachable, NNMi automatically locates another address, if possible, and changes the management address attribute value. Click here for more information.</p> <p>When NNMi first discovers a node, the <i>seed address</i> (provided by the NNMi administrator) or discovered address (for non-seeded nodes) becomes the initial address used for SNMP communication. After NNMi builds an inventory of all IP addresses associated with the node (see "How Spiral Discovery Works" on page 195), NNMi follows a set of rules to determine which address is the best choice for each node's Management Address:</p> <p>Note: (<i>NNMi Advanced</i>) The NNMi administrator specifies whether NNMi prefers IPv4 addresses, IPv6 addresses, or dual-stack (both) when selecting the Management Address. See Configure Default SNMP, Management Address, and ICMP Settings.</p> <ol style="list-style-type: none"> 1. NNMi ignores the following addresses when determining which Management Address is most appropriate: <ul style="list-style-type: none"> ■ Any address of an administratively-down interface.

SNMP Settings for this Device , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Any address that is virtual (for example, VRRP¹). ■ Any IPv4 Anycast Rendezvous Point IP Address² or IPv6 Anycast address. ■ Any address in the reserved loopback network range. IPv4 uses 127/24 (127.*.*.*) and IPv6 uses ::1. ■ Any IPv6 link-local address³. <p>2. If the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi prefers the last-known Management Address (if any).</p> <p>3. If the Management Address does not respond and the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi uses the Communication Configuration settings for <i>Management Address Selection</i>. The NNMi Administrator chooses the order in which NNMi checks the following:</p> <ul style="list-style-type: none"> ■ Seed IP / Management IP - If the NNMi Administrator configures a Seed, NNMi uses the Seed address (either a specified IP address or the DNS address associated with a specified hostname) only during initial Discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery. ■ Lowest Loopback - If a node supports multiple loopback address⁴, NNMi queries each loopback addresses, starting with the lowest number. NNMi uses the loopback address with the lowest number from which the SNMP agent responds (for example, 10.16.42.197 is a lower number than 10.16.197.42).

¹Virtual Router Redundancy Protocol

²Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

³A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

⁴The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

SNMP Settings for this Device , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Highest Loopback - If a node supports multiple loopback address¹, NNMi queries each loopback addresses, starting with the highest number. NNMi uses the loopback address with the highest number from which the SNMP agent responds. ■ Interface Matching - The NNMi Administrator chooses which interface MIB variable NNMi queries to detect changes. NNMi can use the following MIB-II attribute values: <code>ifIndex</code>, <code>ifName</code>, <code>ifDescr</code>, <code>ifAlias</code>, or a combination of these (<code>ifName</code> or <code>ifDescr</code>, <code>ifName</code> or <code>ifDescr</code> or <code>ifAlias</code>). NNMi searches current database entries for information about the interface in this order: index, alias, name, and description. If multiple IP addresses are associated with the interface, NNMi starts by querying the lowest IP address and selects the first responding address in ascending order. <ol style="list-style-type: none"> 4. If no response, NNMi queries any remaining IP addresses in the node's IP address inventory, starting with the lowest number. NNMi uses the address with the lowest number from which the SNMP agent responds. 5. If no response, NNMi checks for any Mapped Address configured for one of the currently known addresses (see the Mapped Address column in the Custom IP Addresses view). <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The address represents a <i>static</i> Network Address Translation (NAT) pair's <i>external IP address</i> from the internal/external IP address pair. NNMi Administrators configure these pairs using the Overlapping IP Address Mapping form. NNMi uses this list of addresses starting with IPv4 from low to high, then IPv6 from low to high.</p> </div> <ol style="list-style-type: none"> 6. If no response, NNMi might be configured to repeat the sequence using SNMPv1, SNMPv2c, or SNMPv3 in the order specified by the NNMi administrator (Communication Configurations <i>SNMP Minimum Security Level</i> settings). 7. When all else fails, NNMi retains the last known Management Address (if any) and automatically changes the State of that SNMP Agent object to Critical.

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using `ifType` Number 24, `softwareloopback` from the IANA `ifType-MIB`.

SNMP Settings for this Device , continued

Attribute	Description
	<p>This process is repeated during each Spiral Discovery cycle, and the Management Address can change. For example, NNMi's inventory of addresses for the node expands, or the current Management Address does not respond to SNMP queries due to network problems or node reconfiguration. The NNMi administrator can prevent changes to the management address using the Communication Configurations <i>Enable SNMP Address Rediscovery</i> or <i>Preferred Management Address</i> setting.</p> <p>If <input type="checkbox"/> disabled, when the current management address (SNMP agent) becomes unreachable, NNMi reclassifies the node as a non-SNMP node until the previously configured management address is available again.</p>
Enable SNMP GetBulk	<p><i>Applies only to SNMPv2 or higher.</i> If you have devices in your network environment that have trouble responding to GetBulk commands, you can instruct NNMi to use Get or GetNext instead of GetBulk.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi uses the SNMPv2c GetBulk command to gather information from this device.</p> <p>If <input type="checkbox"/> disabled, NNMi uses the SNMP Get or GetNext command to gather information from this device (requesting responses for one SNMP OID at a time).</p>
SNMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an SNMP query before reissuing the request. Both the Discovery Process and the State Poller Service use this setting for this device. For an explanation of how NNMi implements timeout and retry configurations, see "Timeout / Retry Behavior Example for SNMP" on page 138.</p>
SNMP Retries Count	<p>Maximum number of retries that NNMi issues for an SNMP query before determining the query result to be "unresponsive". Zero means no retries. Both the Discovery Process and the State Poller Service use this setting for this device.</p>
SNMP Port	<p>Default is 161. Specifies the management server's port that NNMi uses when generating SNMP traffic. Both the Discovery Process and the State Poller Service use this setting for this device.</p>
SNMP Proxy Address	<p><i>Optional.</i> IP address of the your SNMP Proxy Server (for example, a proxy that gathers data from non-SNMP devices and can use that data to respond to NNMi SNMP requests).</p> <p>To enable a proxy, you must also provide the port number of your SNMP Proxy Server. See SNMP Proxy Port (next attribute).</p>

SNMP Settings for this Device , continued

Attribute	Description								
	<p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the “NNMi Communications” chapter of the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>								
SNMP Proxy Port	<p><i>Optional.</i> Port number of the SNMP Proxy Server.</p> <p>To enable a proxy, you must also provide the IP address of your SNMP Proxy Server. See SNMP Proxy Address (previous attribute).</p> <p>Note: When you configure NNMi to use a Proxy Server, you must ensure that the Proxy Server vendor supports the Object Identifiers used to handle SNMP requests and responses. See the “NNMi Communications” chapter of the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>								
SNMP Preferred Version	<p>This setting determines whether each NNMi Rediscovery cycle automatically detects the best SNMP choice (v1, v2, or v3) for this Node (automatically detects any upgrade to the SNMP agent on each Node), or uses only the SNMP version that you specify.</p> <p>Specifies the SNMP version that NNMi should use when communicating with a device. Select one of the following options:</p> <table> <tr> <td>1</td><td>Indicates you want NNMi to try only SNMPv1 settings.</td></tr> <tr> <td></td><td> <p>Tip: Use this option when you do not want NNMi to use GetBulk commands on the device.</p> </td></tr> <tr> <td>2</td><td>Indicates you want NNMi to use SNMPv2c settings, and, if that fails, try SNMPv1 settings. If both SNMPv2c and SNMPv1 fail, NNMi tries SNMPv3 settings if any are available.</td></tr> <tr> <td>3</td><td>Indicates you want NNMi to use SNMPv3 settings for this device. NNMi uses the SNMPv3 Settings configuration to determine which of the following User-based Security Module (USM) levels of security to provide: <ul style="list-style-type: none"> No Authentication, No Privacy Authentication, No Privacy </td></tr> </table>	1	Indicates you want NNMi to try only SNMPv1 settings.		<p>Tip: Use this option when you do not want NNMi to use GetBulk commands on the device.</p>	2	Indicates you want NNMi to use SNMPv2c settings, and, if that fails, try SNMPv1 settings. If both SNMPv2c and SNMPv1 fail, NNMi tries SNMPv3 settings if any are available.	3	Indicates you want NNMi to use SNMPv3 settings for this device. NNMi uses the SNMPv3 Settings configuration to determine which of the following User-based Security Module (USM) levels of security to provide: <ul style="list-style-type: none"> No Authentication, No Privacy Authentication, No Privacy
1	Indicates you want NNMi to try only SNMPv1 settings.								
	<p>Tip: Use this option when you do not want NNMi to use GetBulk commands on the device.</p>								
2	Indicates you want NNMi to use SNMPv2c settings, and, if that fails, try SNMPv1 settings. If both SNMPv2c and SNMPv1 fail, NNMi tries SNMPv3 settings if any are available.								
3	Indicates you want NNMi to use SNMPv3 settings for this device. NNMi uses the SNMPv3 Settings configuration to determine which of the following User-based Security Module (USM) levels of security to provide: <ul style="list-style-type: none"> No Authentication, No Privacy Authentication, No Privacy 								

SNMP Settings for this Device , continued

Attribute	Description
	<ul style="list-style-type: none">• Authentication, Privacy <p>See "Configure Default SNMP, Management Address, and ICMP Settings" on page 130 for more information.</p>

Note: The SNMP Minimum Security Level is determined by the settings on the Communication Configurations' Specific Node Settings form, [SNMPv3 Settings](#) tab where SNMPv3 Settings for this Node are established.

ICMP Settings for this Device

Attribute	Description
Enable ICMP Communication	<p>If <input checked="" type="checkbox"/> enabled, NNMi generates network traffic with ICMP protocol to this device.</p> <p>If <input type="checkbox"/> disabled, NNMi does not generate any ICMP traffic to this device:</p> <ul style="list-style-type: none">• Addresses in this Node (both previously discovered and newly discovered) have a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the IP Address map-symbol color set to beige.• If both ICMP and SNMP are disabled, the Node has a Status attribute value of "No Status" have a map-symbol background shape color set to beige. <p>Note: Your choice might be overridden if Monitoring Configuration settings disable ICMP usage for the State Poller Service, see "Global Control Settings for Monitoring" on page 391 or "Configure NNMi Monitoring Behavior" on page 387.</p>
ICMP Timeout	<p>(Seconds:Milliseconds) Maximum 1 millisecond less than a minute: 59 seconds 999 milliseconds.</p> <p>Time that NNMi waits for a response to an ICMP query before reissuing the request to this device. For an explanation of how NNMi implements timeout and retry configurations, see "Timeout / Retry Behavior Example for ICMP" on page 139.</p>
ICMP Retries Count	<p>Maximum number of retries that NNMi issues for an ICMP query to this device before logging an error. Zero means no retries.</p>

Related Topics:

["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#)

["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#)

["Configure Regions \(Communication Settings\)" on page 148](#)

Configure SNMPv1/v2c Community Strings for a Specific Node

Optional. Configure the SNMPv1 or SNMPv2c community strings for each node.

NNMi uses the SNMPv2c settings to discover the SNMPv2c information about your network. This also determines whether NNMi *receives or discards incoming* SNMPv2c traps. [Click here for more information.](#)


- If the *incoming* trap's Source Node (and sometimes Source Object, such as card or interface) has not yet been discovered by NNMi, NNMi discards the trap. See ["Handle Unresolved Incoming Traps" on page 878](#) for additional information. See also ["Configure Network Devices to Send SNMP Notifications to NNMi" on page 872](#).
- If the Source Node was not discovered using SNMv3, NNMi discards any incoming SNMPv3 traps from that Node.
- NNMi discards traps that have no incident configuration or with an incident configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap. See ["Configure SNMP Trap Incidents" on page 886](#).
- If either the Source Node or Source Object has *Management Mode* set to **Not Managed** or **Out of Service** in the NNMi database, NNMi always discards the incoming trap. See [Understand the Effects of Setting the Management Mode to Not Managed or Out of Service](#).



NNMi provides the Management Mode workspace so that you can quickly view lists of all nodes, interfaces, IP addresses, chassis, cards, node sensors, or physical sensors that NNMi is not currently discovering or monitoring. For information about these views:

- NNMi discards most incoming traps from network objects that are not monitored. For example, you can configure NNMi to exclude specified interfaces from being monitored. See ["Monitoring Network Health" on page 378](#) for more information.

Note: If you want the NNMi management server to *forward* SNMPv2c traps to other machines in your network environment, see ["Configure Trap Forwarding" on page 1407](#) for additional configuration steps.

To provide SNMPv1/v2c community strings for a specific device:



1. Navigate to the **Specific Node Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.

- c. Navigate to the **Specific Node Settings** tab.
- d. Do one of the following:
 - To establish a node definition, click the  New icon.
 - To edit a node definition, select a row, click the  Open icon.
2. Navigate to the **SNMPv1/v2c Community Strings** tab.
3. To provide a *read community string*, navigate to the **Read Community String** attribute and provide the appropriate string (see [table](#)).

Tip: If you do not provide any read community string, NNMi uses the applicable [Region settings](#) and if none match, NNMi uses the [default settings](#).

4. To provide a *write community string*, navigate to the **Write Community String** attribute and provide the appropriate string (see [table](#)).

Tip: If you do not provide any write community string, NNMi uses the applicable [Region setting](#) and if none match, NNMi uses the [default setting](#).

5. Click  **Save and Close** to return to the Communication Configuration form.
6. Click  **Save and Close** to apply your changes.

SNMPv1 or SNMPv2c Community String for this Device

Attribute	Description
Read Community String	<p>The SNMPv1 or SNMPv2c "Get" (read-only) Community String that is used for this device (case-sensitive).</p> <div> <p>Tip: If you do not provide any read community string, NNMi uses the applicable Region settings and if none match, NNMi uses the default settings.</p> </div> <p>Many proxy vendors use the <i>read community string</i> for specifying remote target information. NNMi supports substitution parameters within read community strings for SNMPv1 or SNMPv2c proxy environments. Click here for more information.</p> <p>Copy and paste these codes at the end of your read community string to provide the values required by your proxy environment. NNMi substitutes the actual attribute values from the NNMi database at runtime:</p> <p><code>\${contextName}</code> = Used for specifying VLAN context for switches (VLAN associated with the remote target node)</p>

SNMPv1 or SNMPv2c Community String for this Device , continued


Attribute	Description
	<p>$\{\text{managementAddress}\}$ = Node form, Management Address attribute value (the remote target node)</p> <p>$\{\text{snmpPort}\}$ = SNMP Agent form, UDP Port attribute value (SNMP agent associated with the remote target node)</p> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>
Write Community String	<p><i>Optional.</i> For use with the nnmsnmpset.ovpl command line tool.</p> <p>The SNMPv1 or SNMPv2c "Set" (write) Community String that is used for the SNMP Agent for each node specified (case-sensitive).</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: SNMP Agents are often configured with different community strings for "Set" requests than for "Get" (read) requests.</p> </div> <p>SNMPv1 and SNMPv2c require that you know the SNMP agent's <i>write community string</i> before you can change settings on any device. The nnmsnmpset.ovpl command can use the value you provide here, rather than requiring that you type the write community string each time you invoke the command.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: If you do not provide any write community string, NNMi uses the applicable Region setting and if none match, NNMi uses the default setting.</p> </div> <p>Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>Because this is a type of password, you must enter the value twice.</p>











Configure SNMPv3 Settings for a Specific Node

NNMi can use SNMPv3 user-based security model (USM) settings to access devices.

NNMi uses the current SNMPv3 Settings provided for a node, if available.

To configure an SNMPv3 Settings for a specific node:

1. Navigate to the **Specific Node Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Specific Node Settings** tab.
 - d. Do one of the following:

- To establish a node definition, click the  New icon, and continue.
 - To edit a node definition, select a row, click the  Open icon, and continue.
2. Navigate to the **SNMPv3 Settings** tab.
 3. Click the SNMPv3 Settings  Lookup icon and select one of the options from the drop-down menu:
 -  Show Analysis to display Analysis Pane information for the currently configured (selected) SNMPv3 Setting name. (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
 -  Quick Find to view and select from the list of all existing SNMPv3 Settings (for more information see ["Use the Quick Find Window" on page 38](#)).
 -  Open to display the details of the currently configured (selected) SNMPv3 Setting (see ["SNMPv3 Settings Form"](#) for more information).
 -  New to create a new SNMPv3 Setting (see ["SNMPv3 Settings Form"](#) for more information).
 4. Click  **Save and Close** to return to the Specific Node Settings form.
 5. Click  **Save and Close** to return to the Communication Configuration form.
 6. Click  **Save and Close** to apply your changes.

Configure Credential Settings for a Specific Node

NNMi uses the Device Credentials settings for the following:







- Device discovery of some vendor-specific devices that require non-SNMP communication, such as Netconf over SSH. For a list of these devices see the NNMi Device Support Matrix.
- Device Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).




NNMi uses the following sequence to determine Device Credentials:

- Use the Specific Node Device Credentials (provided here). If none match, continue.
- Use the [Region Device Credentials](#). If none match, continue.
- Use the [Default Credential](#) settings.

To provide credential settings for a specific node:

1. Navigate to the **Specific Node Device Credentials** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Communication Configuration**.
 - c. Navigate to the **Specific Node Settings** tab.
 - d. Do one of the following:
 - To establish a definition, click the  **New** icon.
 - To edit a definition, click the  **Open** icon in the row representing the configuration you want to edit.
 - e. In the **Specific Nodes Settings** form, navigate to the **Device Credentials** tab.
 - f. Do one of the following:
 - To establish a credential setting, click the  **New** icon, and continue.
 - To edit a credential setting, click the  **Open** icon in the row representing the configuration you want to edit, and continue.
 - To delete a credential setting, select a row and click the  **Delete** icon
2. Provide the attribute values of credentials for this node (see [table](#)).

Note: NNMi tries to use the Specific Node Device Credentials provided here. If none match, NNMi tries the [Region Device Credential](#) settings. If none match, NNMi tries the [Default Device Credentials](#).

3. Click  **Save and Close** to return to the Specific Node Settings form.
4. Click  **Save and Close** to return to the Communication Configuration form.
5. Click  **Save and Close** to apply your changes.

NNM iSPI NET uses the Default Credentials setting to access devices when running Diagnostics either automatically or when the **Actions** → **Run Diagnostics** option is used. (See ["Configure Diagnostics for an Incident" on page 857](#) and [Node Form: Diagnostics Tab](#) for more information.)

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

At each level in the sequence to determine the Device Credentials (see bullet list above), NNMi first uses Secure Shell (SSH) to establish a secure connection, and if the SSH attempt fails, NNMi tries Telnet protocol as the communication method.

Caution: By default, neither Microsoft Internet Explorer nor Mozilla Firefox defines the telnet command nor the SSH command, so using either of these menu items produces an error message. See the "Configuring the Telnet and SSH Protocols for Use by NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for configuration information.

Specific Node Device Credential Attributes

Attribute	Description
User Name	Type the user name that you want NNMi to use for logging into this device.
Password	Type the password that you want NNMi to use for logging into this device. Note: NNMi encrypts the password and displays asterisks for this attribute. If you want to change the password, first clear the asterisks displayed in the Password attribute and enter the new Password value.

Load Communication Settings from a File

NNMi enables you to bulk load or update any of the Communication Configuration or SNMP Agent Settings that you can configure when using [nnmcommunication.ovpl](#).

Note the following:

- If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See "[Set Up Command Line Access to NNMi](#)" on page 653 for more information.
- For more information, see the [nnmcommunication.ovpl](#) Reference Page and "[About Environment Variables](#)" on page 86.

To load Communication Configuration or SNMP Agent Setting updates from a file:

1. On the NNMi management server's hard drive, create a text batch file according to the specifications in the [nnmcommunication.ovpl](#) Reference Page.

To add comments to your file, place a # character at the beginning of each comment line.

2. Use the following command line command to load the information into the NNMi database:

Windows:

```
%NmInstallDir%\bin\nnmcommunication.ovpl -u <NNMiadminUserName> -p  
<NNMiadminPassword> -batch <path/filename>
```

Linux:

```
$NnmInstallDir/bin/nnmcommunication.ovpl -u <NNMiadminUserName> -p  
<NNMiadminPassword> -batch <path/filename>
```

View the Communication Configuration Settings for a node:

View the Communication Configuration Settings when the node's SNMP Agent Settings **Mode** value is set to **Auto**. If the node's [SNMP Agent Settings](#) Mode value is **Locked**, the Communication Configuration Settings for the node are ignored.

To view the Communication Configuration Settings for a node, enter:

Windows:

```
%NnmInstallDir%\bin\nnmcommunication.ovpl -u <NNMiadminUsername> -p  
<NNMiadminPassword> listEffective -node <node name>| <node IP address>
```

Linux:

```
$NnmInstallDir/bin/nnmcommunication.ovpl -u <NNMiadminUsername> -p  
<NNMiadminPassword> listEffective -node <node name>| <node IP address>
```

View the SNMP Agent Settings for a node

Note: When the SNMP Agent Settings **Mode** value is **Locked**, NNMi uses the SNMP Agent Settings and ignores the Communication Configuration Settings for the associated node.

To view the SNMP Agent Settings for a node, enter:

Windows:

```
%NnmInstallDir%\bin\nnmcommunication.ovpl -u <NNMiadminUsername> -p  
<NNMiadminPassword> listSnpAgentSettings -node <node name>|<node IP address>
```

Linux:

```
$NnmInstallDir/bin/nnmcommunication.ovpl -u <NNMiadminUsername> -p  
<NNMiadminPassword> listSnpAgentSettings -node <node name>|<node IP address>
```

Restrict SNMP Communication for a Node

For security reasons, you might need to restrict SNMP access to one or more nodes after they are discovered.

Tip: You can also use [nnmcommunication.ovpl](#) to configure SNMP Agent settings.

To restrict SNMP Communication for a node:

1. From the workspace navigation panel, select the  **Inventory** workspace.

You can also use [nnmcommunication.ovpl](#) to configure SNMP Agent settings.

2. Navigate to the **SNMP Agent** form for the node to which you want to restrict access.
 - a. Select **SNMP Agents**.
 - b. Double-click the row of interest.
3. In the **Mode** attribute, select **Locked**.

Note: When the SNMP Agent Settings **Mode** value is **Locked**, NNMi uses the SNMP Agent Settings and ignores the Communication Configuration Settings for the associated node.

NNMi discovers Nodes using the Communication Configuration settings. See [Configuring Communication Protocol](#) for more information. After the node is discovered, the SNMP Settings Mode remains **Auto** by default.

4. Disable the SNMP Agent.

In the **Agent Enabled** attribute, clear the check mark ☐.

Disabling the SNMP Agent ensures that the SNMP Agent is not polled.

Troubleshooting Communication Settings

After you configure your communication settings and wait until Auto-Discovery completes at least one cycle, you can verify your Communication Settings:

Verify That All Nodes Support SNMP	188
Verify a Node's Communication Settings	188
Verify Communication Settings	190
Resolve Authentication Errors	191

Tip: For the alternate method of configuring communication settings from the command line, see the [nnmcommunication.ovpl](#) Reference Page.

You can fine tune NNMi's SNMP/ICMP traffic in the following ways:

- Minimize timeouts and retries.


When NNMi attempts to contact a node using ICMP / SNMP during an Auto-Discovery cycle, the Communication Configuration settings determine what information NNMi can gather. If the correct ICMP / SNMP settings are not provided or if NNMi discovers non-SNMP devices (see ["Verify That All Nodes Support SNMP" on the next page](#)), NNMi resorts to timeouts and retries.

Large timeout values or a high number of retries can degrade overall performance of discovery. If your network environment contains nodes that you know respond slowly to ICMP / SNMP requests, consider using the [Regions](#) or [Specific Nodes](#) settings to fine tune the number of timeouts and retries NNMi uses during each Auto-Discovery cycle.

- Limit the number of *default* SNMPv1/SNMPv2c Community Strings to ensure efficient Auto-Discovery performance. See ["Configure Default Community Strings \(SNMPv1 or SNMPv2c\)" on page 140](#).
- Limit the number of *default* SNMPv3 user-based security model (USM) settings to ensure efficient Auto-Discovery performance. See ["Configure Default SNMPv3 Settings" on page 145](#).

Verify That All Nodes Support SNMP

After you configure your communication settings and wait until Auto-Discovery completes at least one cycle, check for any nodes that do not respond to SNMP:

1. From the workspace navigation panel, select the  **Inventory** workspace.
2. Select the **Nodes** view.
3. Right-click the **Device Profile** column, and select **Create Filter**.
4. Select "contains", and type the following text into **Enter a string**: No SNMP.
5. NNMi displays a list of all nodes in your network environment that did not respond to SNMP during Auto-Discovery.
6. Verify that the resulting list is valid.
7. To troubleshoot unexpected results, see:
 - ["Verify a Node's Communication Settings" below](#)
 - ["Verify Communication Settings" on page 190](#)
 - ["Resolve Authentication Errors" on page 191](#)

Verify a Node's Communication Settings

After you configure your communication settings and wait until Auto-Discovery completes at least one cycle, you can check to determine what settings NNMi is using to communicate with a node of interest.


NNMi provides a report about the communication configuration information for a selected node, including the SNMP and ICMP configuration information.

To display a report of a node's current communication settings:


Note: The User Account must be assigned to the **NNMi Administrators** User Group to use this action.

1. Do one of the following:


Navigate to a table view and select a node:

- a. From the workspace navigation panel, select the workspace of interest. For example,  **Inventory**.
- b. Select the view that contains the node with communication settings you want to check. For example, **Nodes**.
- c. Select the row representing the node with communication settings you want to check.

Navigate to a map view and select a node:

- a. From the workspace navigation panel, select the workspace of interest; for example,  **Topology Maps**.
- b. Click the view that contains the node with communication settings you want to check; for example **Initial Discovery Progress** or **Network Overview** map.
- c. From the map view, click the node with communication settings you want to check.

Navigate to a Node form:

- From a table view, double-click the row representing the node of interest.
- From a map view, click the node of interest on the map and click the  Open icon.


2. Select **Actions** → **Polling** → **Communication Settings**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Sometimes a device is temporarily not responding properly to SNMP during NNMi's initial discovery, so NNMi makes the wrong decision about which version of SNMP to use. Or perhaps you deployed upgrades to the SNMP agents in your network environment.

To update NNMi's choice of SNMP version used for a Node or Nodes:

Note: The User Account must be assigned to the **NNMi Administrators** User Group to use this action.

1. From the workspace navigation panel, select  **Inventory**.
2. Select the **Nodes (All Attributes)** view.

3. Click the **Protocol Version** column heading to sort the view according to SNMP version currently being used by NNMi for communications with each SNMP agent in your network environment.
4. Select all rows that you want NNMi to check for SNMP upgrades or changes.
5. select **Actions** → **Polling** → **Configuration Poll**.

NNMi reconfigures the SNMP Communication settings by verifying the highest SNMP version available to the SNMP Agent assigned to the node (according to your Communication Configuration settings).

6. Click the **Protocol Version** column heading to resort the view according to SNMP version.
7. Verify that NNMi made the expected changes.

If still receiving unexpected results, see ["Verify Communication Settings" below](#).

See ["Configuring Communication Protocol" on page 129](#) for information about configuring communication settings.

Related Topics

[nnmcommunication.ovpl](#) Reference Page


Verify Communication Settings

To verify your Communication Configuration settings:

Note: The User Account must be assigned to the **NNMi Administrators** User Group to use this action.

1. Do one of the following:

Navigate to a table view and select a node:

- a. From the workspace navigation panel, select the workspace of interest. For example,  **Inventory**.
- b. Select the view that contains the node with communication settings you want to check. For example, **Nodes**.
- c. Select the row representing the node with communication settings you want to check.


Navigate to a map view and select a node:

- a. From the workspace navigation panel, select the workspace of interest; for example, .

Topology Maps.

- b. Click the view that contains the node with communication settings you want to check; for example **Initial Discovery Progress** or **Network Overview** map.
- c. From the map view, click the node with communication settings you want to check.

Navigate to a Node form:

- From a table view, select the row representing the node of interest.
 - From a map view, click the node of interest on the map and click the  Open icon.
2. Select **Actions** → **Configuration Details** → **Communication Settings**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

NNMi displays a report showing ICMP and SNMP communication configuration settings for this node's SNMP Agent.


(*NNMi Advanced*) If the Global Network Management feature is enabled and you are signed into a Global Manager:


- Node managed by the Global Manager = **Actions** → **Configuration Details** → **Communication Settings** opens a report, provided by the Global Manager (NNMi management server).
- Node managed by a Regional Manager = **Actions** → **Configuration Details** → **Communication Settings** accesses that Regional Manager (NNMi management server) and requests the report.

Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

Resolve Authentication Errors

To create a list of authentication errors:

1. From the workspace navigation panel, select the  **Incident Browsing** workspace.
2. Select an Incident view.
3. Right-click the **Category** column, and select **Create Filter**.

4. Select "equals", and select  **Security**.
5. NNMi displays a list of all incidents related to authentication errors; for example an SNMP authentication failure (see also [Node Down](#)).

If NNMi generates incidents related to *authentication failure* during discovery, there are several configuration settings that influence authentication errors:

- [Communication Configuration](#).

Each Node's Management Address is the address NNMi uses to communicate with the Node's SNMP agent. The NNMi administrator can control NNMi behavior:

- Specify the Management Address for a node (in the Communications Configuration, [Specific Nodes](#) settings).
- Otherwise, let NNMi choose an address from all IP addresses associated with each node. This NNMi behavior can be fine-tuned by the NNMi administrator in the Discovery configuration settings.

Consider configuring smaller [Regions](#) with more focused lists of possible access credentials. Or configure [Specific Nodes](#) to avoid requiring NNMi to try multiple possible settings.

- [Discovery Configuration](#).

The following Discovery Configuration fields influence NNMi's use of SNMP (see "[Configure Basic Settings for the Auto-Discovery Rule](#)" on page 240):

- **Discover Any SNMP Device** field.

If ☐ disabled, NNMi discovers only Routers and Switches that respond to SNMP.

If ☒ enabled, NNMi discovers all devices that respond to SNMP.

- **Discover Non-SNMP Devices** field.

If ☐ disabled, when there is no SNMP response from the device, NNMi does not discover information about the device or add a record of that device to the NNMi database.

If ☒ enabled, NNMi discovers devices that do not respond to SNMP and assigns the Device Profile named No SNMP as the basis of the database record.

NNMi's access to SNMP agents is also influenced by the [set of rules for choosing management addresses](#) and settings to [exclude certain addresses](#).

- [Device Profiles](#).

The Device Profiles' **Force Device** attribute setting influences NNMi's use of SNMP (see [Device Profile form](#)).

- [Monitoring Configuration](#).

NNMi discovers and monitors devices in an ongoing basis (see ["Monitoring Network Health" on page 378](#)). For example, when previously discovered SNMP agents quit responding (such as when you reconfigure the device's SNMP agent), NNMi detects the alternatives.

To control management address rediscovery after the first NNMi discovery cycle, use Communication Configuration's **Enable SNMP Address Rediscovery** field:

- If ☐ disabled, NNMi reports the device as [Node Down](#) and does not attempt to find another Communication Configuration setting that works.
- If ☒ enabled, NNMi retries any configured values in search of one that works.

Chapter 6: Discovering Your Network

Using a wide range of protocols and techniques, NNMi Spiral Discovery gathers a wealth of information about your network inventory, ascertains the relationships between devices (such as subnets and VLANs), and accurately maps out the connectivity between those devices. The NNMi Causal Engine determines the current status of each device (plus each associated interface and address within that device) and proactively notifies you when NNMi detects any trouble or potential trouble.

This dynamic discovery process continues over time. When things change in your network management domain, Spiral Discovery automatically updates information according to a schedule that you set. The topology maps always reflect accurate and timely information about any changes within your network. For more information, see ["How Spiral Discovery Works" on the next page](#).

The first step is to verify that your network environment supports NNMi's Discovery process: ["Prerequisites for Discovery" on page 207](#).

Then establish the Spiral Discovery default settings: ["Establish Global Defaults for Spiral Discovery" on page 221](#) and ["Configure Schedule Settings" on page 230](#)

If your network environment includes areas that use network address translation protocols, NNMi can successfully co-exist with the following protocol types (see ["Overlapping Address Mapping" on page 210](#)):

- *Static* Network Address Translation (NAT)
- *Dynamic* Network Address Translation (NAT)
- *Dynamic* Port Address Translation (PAT/NAPT)

If your network environment includes areas with conflicting subnet configurations, NNMi can successfully apply subnet masks *separately* to each group of Nodes you identify with a Tenant configuration (see ["Configure Tenants" on page 213](#)).

Tip: NNMi's Tenant configuration settings are useful for a variety of situations. Review the Tenant information so you know about all your options.

The NNMi administrator is responsible for the following:

- Decide which nodes NNMi discovers and how often NNMi checks for new devices in your network (see ["Configure Discovery" on page 219](#)).
- Specify which devices are the best source of information about your network (see ["Specify Discovery Seeds" on page 287](#)).
- Verify that NNMi has an accurate and complete understanding of your network environment (see ["Examine Discovery Results" on page 297](#)).
- Change the Discovery configuration as needed over time (see ["Keep Your Topology Accurate" on page 307](#)).

Related Topics:

For a list of the types of things NNMi can discover, see [About Map Symbols](#).

From the information collected, NNMi constructs a model of your network configuration in the database, and displays this information in the map views. See [View Maps of Network Connectivity](#) for more information about the available map views.

To restrict subsequent SNMP Communication for a node after it is discovered, see ["Restrict SNMP Communication for a Node" on page 186](#).

How Spiral Discovery Works

For details about how Spiral Discovery works, see the following:

Which Nodes Are Discovered?	195
What Information Is Collected?	196
When Does Discovery Happen?	204
How Is Discovery Configured?	206

To ensure that NNMi successfully discovers Nodes in your network environment, verify the following:

- Communication Configuration settings permit NNMi to communicate with all important Nodes using SNMP, ICMP, or both. See ["Configuring Communication Protocol" on page 129](#).
- Prerequisites are met for well-configured SNMP, DNS, and IP address configuration. See ["Prerequisites for Discovery" on page 207](#).
- Global Default settings reflect reality for your network environment. See ["Establish Global Defaults for Spiral Discovery" on page 221](#).

Which Nodes Are Discovered?

You have total control over which Nodes are discovered by configuring a Discovery Seed for each Node. To define a Discovery Seed, you provide one of the following sets of information:

- hostname (*not case-sensitive*) and Tenant
- IP address and Tenant

NNMi uses the Discovery Seed to make initial contact. Discovery seeds are only relevant during initial discovery. NNMi requests each Node's current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery. You can configure discovery seeds three ways, see ["Specify Discovery Seeds" on page 287](#).

If you choose to use Auto-Discovery, NNMi automatically gathers Hints from each discovered Node and uses that information to find any neighboring devices within your Default Tenant's address range. You simply configure one or both of the following:

- Provide a Discovery Seed for one or more devices
- Enable Ping Sweep and let Auto-Discovery find every device that responds

Discovery seeds are required if any of the following are true:

- You want NNMi to discover only what you specify.
- You want to use discovery seeds as starting points for Auto-Discovery Rules. See ["Configure Auto-Discovery Rules" on page 236](#).
- Your network includes nodes with addresses provided by any of the following protocols (see ["Overlapping Addresses in NAT Environments" on page 94](#)):
 - *Static* Network Address Translation (NAT)
 - *Dynamic* Network Address Translation (NAT)
 - *Dynamic* Port Address Translation (PAT/NAPT)
- You want to control which Nodes each NNMi user sees. See ["Tenant and Initial Discovery Security Group Assignments" on page 217](#).

For details about how Spiral Discovery works:

What Information Is Collected?

For details about how Spiral Discovery gathers information, see the following:

Consider IPv4 Subnet Connection Rules	200
Keep Requests to a Minimum	202
Correct Any Misinformation	203

NNMi displays the real-time accumulation of information about each Node as it is collected, rather than waiting until Spiral Discovery scans your entire network environment. Spiral Discovery uses a variety of network protocols (read-only queries) within your defined network management domain to gather information about each discovered Node and that Node's connections to other Nodes (see [diagram](#)):

1. [Information about the node.](#)

NNMi gathers detailed information about each device. You can review this data on the device's [Node form](#). Examples of configuration details include Tenant, IP address, subnet information, system object ID (RFC 1213, MIB-II sysObjectID), number of interfaces, and version of

SNMP supported.

Tip: NNMi does not collect data from Dynamic Host Configuration Protocol (DHCP). Instead, NNMi uses the Media Access Control address (MAC address) of the Node's interfaces to determine a positive ID when hostname changes. See *HP Network Node Manager i Software Deployment Reference* for more information (see **Help** → **Documentation Library**).

2. [Connectivity details](#).

NNMi gathers information about how devices are connected to each other on [Layer 2](#)¹ and [Layer 3](#)² of your network.

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Tip: NNMi's Tenant configuration settings are useful for a variety of situations. Review the Tenant information so you know about all your options. See "[Configure Tenants](#)" on [page 213](#).

During discovery, NNMi reads the Forwarding Database (FDB) tables from Ethernet switches within a network to help NNMi determine communication paths between network devices. NNMi searches these FDB tables for information about discovered nodes. When an NNMi management server finds FDB references to duplicate [MAC addresses](#)³:

- If two or more discovered nodes contain an interface associated with the same Media Access Control (MAC) address within the same Tenant or with one of those nodes in Default Tenant and one in any other Tenant, NNMi disregards the communication paths reported for those duplicate MAC addresses in the FDB. This might result in missing connections on NNMi maps in network areas that include those duplicate MAC addresses.

¹Refers to the Data Link layer of the multilayered communication model, Open Systems Interconnection (OSI). The Data Link layer moves data across the physical links in the network. The switches and switch-routers are devices that redirect data messages at the layer 2 level, using the destination Media Access Control (MAC) address to determine where to direct the message.

²Refers to the Network layer of the multilayered communication model, Open Systems Interconnection (OSI). The Network layer is concerned with knowing the address of the neighboring nodes in the network, selecting routes and quality of service, and recognizing and forwarding incoming messages to local host domains. The router and switch-router are the devices that redirect data messages at the Layer 3 level. Everything in a subnet is connected at the Layer 3 (IP) level.

³The Media Access Control address (hardware address or physical address) that the factory burns into a network adapter or device with built-in networking capability. A MAC address has six pairs of hexadecimal digits, separated by colons or dashes. For example 02:1F:33:16:BC:55

(NNMi Advanced - Global Network Management feature) If two NNMi management servers discover nodes that contain an interface associated with the same Media Access Control (MAC) address, the Global NNMi management server's maps could be missing connections that are visible on the Regional NNMi management server's maps.

- If a single node contains multiple interfaces that have the same MAC address, NNMi gathers all communication path information for those interfaces and displays that information on NNMi maps.


Forwarding Database (FDB) information can cause NNMi to establish wrong Layer 2 Connections in the following cases:

- When the FDB is configured as cache and contains obsolete data.
- In network environments with hardware from a variety of vendors, when each vendor generates different and sometimes conflicting FDB data.

Optional: NNMi administrators can configure Spiral Discovery to ignore the FDB data from one Node Group when calculating Layer 2 Connections (the FDB data is still included in other calculations).

For more information, see ["Configure Layer 2 Connection Source" on page 228](#).

To create connections that NNMi cannot detect, use IPv4 Subnet Connection Rules. See ["Consider IPv4 Subnet Connection Rules" on page 200](#).



For details about how Spiral Discovery works:

Consider IPv4 Subnet Connection Rules


Sometimes it is useful to monitor Layer 2 Connections in the following categories:



- Point-to-point or point-to-multipoint connections between interfaces.
- Virtual IPv4 tunnel connections within your management domain.
- Connections to remote sites (across a Service Provider's network or a WAN).
- Connections among Provider Edge (PE¹) devices in the Default Tenant and Customer Edge (CE²) devices in Tenants defined by the NNMi administrator.


NNMi accomplishes this by following special rules for subnets with prefix lengths between 28 and 31. These special rules are called Subnet Connection Rules.

If you configure a Subnet Connection Rule, the rule independently applies to each Tenant. The members of Subnets must be unique Tenant/Node pairs (each Node assigned to only one Tenant). A Subnet Connection Rule can establish a link between the Default Tenant and another Tenant. However, links between two Tenants are not permitted *unless one of them is the Default Tenant*. See ["Configure Tenants" on page 213](#).

These Subnet Connections Rules enable NNMi to draw arbitrary connections on maps where none would otherwise be detected. If the connection is between two nodes, NNMi draws a standard line on maps. For example:



If the connection is between more than two nodes, NNMi displays an  icon (in prior NNMi releases the  icon):



¹Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

²Customer Edge router. The router in your network that sends data to an Internet Service Provider's router (the Provider Edge) on the path to the data's final destination.

Tip: NNMi uses Subnet Connection Rules to prevent incorrect connection calculations to Provider Edge (PE) interfaces (see [Interface Capability](#) `com.hp.nnm.capability.iface.PE`). If your network environment includes Provider Edge devices, the following HP products can provide additional valuable information for your team ([click here for more information](#)):

- HP Network Node Manager iSPI for MPLS Software
- HP Route Analytics Management System (RAMS) for MPLS WAN

If you are an NNMi administrator, see "[HP RAMS MPLS WAN Configuration \(NNMi Advanced\)](#)" on page 1446 for information about configuring RAMS.

If you double-click the line or the  icon, the [Layer 2 Connection](#) form displays and the **Topology Source** value is SUBNETCONNECTION.

NNMi provides a group of predefined Subnet Connection Rules (see "[Subnet Connection Rules Provided by NNMi](#)" on page 267). You can edit an existing Subnet Connection Rule or create your own (see "[Configure IPv4 Subnet Connection Rules](#)" on page 265).

If you limit Spiral Discovery to only your Discovery Seeds, NNMi uses the Subnet Connection Rules to detect connections among those devices.

If you use Auto-Discovery rules to configure Spiral Discovery, when NNMi detects a subnet prefix between 28 and 31, NNMi uses the Subnet Connection Rules:

1. NNMi checks for an applicable Subnet Connection Rule (see "[Subnet Connection Rules Provided by NNMi](#)" on page 267).
2. If a match is found, Spiral Discovery checks the topology database for existing data about each IPv4 address in the subnet. If no data is found for a particular IPv4 address, NNMi issues an SNMP query to the new IPv4 address. The number of available IPv4 addresses for each valid prefix length is described in the following table:

Valid Minimum Prefix Length Values (Subnet Mask Length)


Valid Minimum IPv4 Prefix Length Values	Number of Usable IPv4 Addresses
28	14 (16-2=14)*
29	6 (8-2=6)*
30	2 (4-2=2)*
31	2

* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.


3. NNMi checks the Excluded IP Addresses list. Any addresses in the list are dropped. For details, see "[Configure an Excluded IP Addresses Filter](#)" on page 274.

4. New IPv4 addresses that respond to SNMP are added to the topology database and available for monitoring purposes. New IPv4 addresses that do not respond to SNMP are ignored.
5. If the IPv4 address on each end of a connection has an associated interface, NNMi uses the subnet connection rule to display the connection on map views.

In a Layer 3 Neighbor View map, if NNMi discovers an interface that is connected to more than one interface, the results of your subnet connection rule look like the following:



In a Layer 2 Neighbor View map, if NNMi discovers an interface that is connected to more than one interface, the results of your subnet connection rule look like the following:



See ["Configure IPv4 Subnet Connection Rules" on page 265](#) to learn how to configure Subnet Connection Rules.

For details about how Spiral Discovery works:

Keep Requests to a Minimum

Often your network environment has devices with thousands of interfaces and you want NNMi to discover and monitor only a subset of the interfaces in these devices. To keep SNMP traffic to a minimum, use the Included Interfaces filter. This filter instructs Spiral Discovery to request information about only the subset of interfaces you specify for each vendor/make/model. See ["Configure an Included Interface Ranges Filter" on page 277](#).


Tip: You can configure NNMi to never send SNMP or ICMP requests to specific IP addresses or hostnames. See ["Configuring Communication Protocol" on page 129](#).

To trim data from responses to Spiral Discovery's requests, use the following:

- ["Configure an Excluded IP Addresses Filter" on page 274](#)
- ["Configure an Excluded Interfaces Filter" on page 280](#)

If you choose to use Auto-Discovery within your Default Tenant's address range, Auto-Discovery Rules provide a wide range of controls. See ["Example Uses of Auto-Discovery" on page 251](#).

NNMi's Spiral Discovery



For details about how Spiral Discovery works:

Correct Any Misinformation

To verify Spiral Discovery's results and correct any problems, see the following:

- ["Examine Discovery Results" on page 297](#)
- ["Keep Your Topology Accurate" on page 307](#)

For details about how Spiral Discovery works:

When Does Discovery Happen?

Initial Discovery

When you add a discovery seed, NNMi immediately tries to discover that device. If discovery is not successful, NNMi tries again 10 minutes later, and continues trying. The time between each attempt is doubled until the time reaches 1 week or equals your current schedule for Rediscovery Interval. See ["Configure Schedule Settings" on page 230](#).

Note: Nodes configured as discovery seeds are always discovered and added to the topology database. If you change your mind and [delete a discovery seed](#) configuration, the node is *not* automatically deleted from the topology database. See ["Delete Nodes" on page 1635](#).

Auto-Discovery

If you choose to use Auto-Discovery, NNMi automatically gathers Hints from each discovered Node and uses that information to find any neighboring devices within your Default Tenant's address range. This happens automatically each time a Hint is detected or an Auto-Discovery Rule includes Ping Sweep to let Auto-Discovery find every device that responds.

Rediscovery

After NNMi completes initial discovery of your network, Spiral Discovery checks for changes according to the current Schedule Settings for Rediscovery Interval:

- If a discovered Node's configuration settings or status changes, NNMi dynamically updates the database and maps to reflect the changes.

The only exception is when non-SNMP nodes that had the same DNS hostname are changed to have separate DNS hostnames, NNMi must completely rediscover the non-SNMP nodes to correctly update the database objects (node, interface, address, connection, and incidents). The NNMi administrator must delete the old non-SNMP node object and force NNMi to rediscover the new node configurations. See ["Delete Nodes" on page 1635](#).

- If a new node is added to your network within the Default Tenant address range and your team uses Auto-Discovery, NNMi dynamically discovers that Node, updates the topology database, and updates the maps. The details of the new node appear in the Node form. The maps reflect the new node's connectivity information.

If a node has not been rediscovered within the current Rediscovery Interval, then NNMi initiates a rediscovery after the Rediscovery Interval time frame has been reached. For example, if you set the Rediscovery Interval to 1 day, NNMi rediscovers all nodes that have not been rediscovered for other reasons after the 1 day interval has passed. NNMi strategically batches groups of nodes over time to reduce the volume of network traffic generated.

On-Going Discovery in Response to Changes

NNMi collects and analyzes data about each Node's Tenant assignment, IP Addresses, MAC Addresses, DNS and system information to determine any change. NNMi collects this data according to the currently configured Discovery Interval value or when polling results or traps indicate that something changed.

Spiral Discovery rediscovers Nodes for a variety of reasons between the scheduled discovery interval:

- If NNMi's State Poller detects the following, NNMi rediscovers the node:
 - An SNMP-enabled Node rebooted (based on detected SNMPv2 MIB sysUpTime values).
 - An object associated with the Node (such as an IP address, interface, or CPU) no longer exists within a previously monitored SNMP-enabled Node.
 - NNMi is configured to use SNMP for detecting ifNumber and entLastChangeTime value changes (indicating interface renumbering, new interfaces, or interfaces being removed). See instructions in the following topics for configuration instructions:
 - ["Detect Interface Changes" on page 311](#).
 - ["Default Settings for Monitoring" on page 393](#)
 - ["Node Settings for Monitoring" on page 443](#)
- If certain traps are received from network devices, these traps indicate that the network topology under NNMi's management potentiality changed. Spiral Discovery rediscovers the Node involved. For example:

SNMPColdStart	CiscoColdStart	CiscoLinkDown
SNMPWarmStart	CiscoWarmStart	CiscoLinkUp
SNMPLinkDown	CiscoFRUInserted	and other vendor-equivalent traps
SNMPLinkUp	CiscoFRURemoved	

Your Rediscovery Requests

At any time, you can initiate a request to rediscover information about a previously discovered node. Select a node in any table or map view, then click the **Actions** → **Polling** → **Configuration Poll** command.

You can also use the [nnmnoderediscover.ovpl](#) or [nnmconfigpoll.ovpl](#) command to issue requests about rediscovering multiple nodes.

For details about how Spiral Discovery works:

How Is Discovery Configured?

A number of NNMi configuration settings let NNMi administrators control how Spiral Discovery works. The steps required depend on what your team wants to accomplish and the details of your network environment. See the following topic for more information:

["Determine Your Approach to Discovery" below](#)

For details about how Spiral Discovery works:

Determine Your Approach to Discovery

Discover and monitor only the network devices that you and your team consider to be important. Take any approach that makes sense to you.

Prepare for Spiral Discovery:

- ["Prerequisites for Discovery" on the next page](#)
- ["Establish Global Defaults for Spiral Discovery" on page 221](#)
- ["Configure Schedule Settings" on page 230](#)
- Does your network include ["Overlapping Addresses in NAT Environments" on page 94?](#)

Maintain absolute control over what is discovered.

- ["Spiral Discovery of Only Seeds \(all Tenants\)" on page 285](#)
- ["Configure Tenants" on page 213](#)

Tenants are required if your network domain includes the following:

- ["Overlapping Addresses in NAT Environments" on page 94](#)
- ["Connecting Multiple NNMi Management Servers \(NNMi Advanced\)" on page 98](#)
See also ["Tenant Best Practices for Global Network Management" on page 102](#)

Fine tune Spiral Discovery behavior:

- ["Configure an Excluded IP Addresses Filter" on page 274](#)
- ["Configure an Included Interface Ranges Filter" on page 277](#)
- ["Configure an Excluded Interfaces Filter" on page 280](#)
- ["Configure IPv4 Subnet Connection Rules" on page 265](#) (add connections that NNMi cannot detect)

Default Tenant only: Configure Auto-Discovery to make decisions about what is discovered within the Default Tenant.

Optional. Create one or more Auto-Discovery Rules that define what is important to you and your team:

- ["Configure Auto-Discovery Rules" on page 236](#)
- ["Example Uses of Auto-Discovery" on page 251](#)

For details about how Spiral Discovery works:

Prerequisites for Discovery

For details about the required prerequisites, see the following:

SNMP Prerequisites	207
Well-Configured DNS Prerequisite	208

Tenant definitions are required if your network domain includes the following:

- ["Overlapping Addresses in NAT Environments" on page 94](#)
- ["Connecting Multiple NNMi Management Servers \(NNMi Advanced\)" on page 98](#)
See also ["Tenant Best Practices for Global Network Management" on page 102](#)

See ["Configure Tenants" on page 213](#)

NNMi uses SNMP and DNS while discovering and monitoring devices. NNMi Advanced can discover and monitor IPv6 addresses in addition to IPv4 addresses. To ensure accurate network topology information about your network environment, verify that your environment complies with the prerequisites.

Verify that your network ACL (Access Control Lists) configuration allows the NNMi management server to talk with the nodes you want NNMi to discover and monitor.

Verify that no firewall configuration in your network environment would block the NNMi management server's SNMP communication with the devices in your network.

SNMP Prerequisites

Spiral Discovery uses SNMP while detecting devices and connections among the devices in your network environment. NNMi also uses SNMP as part of monitoring and reporting on the health of devices in your network environment.

NNMi supports the following SNMP versions:

- SNMPv1
- SNMPv2c
- SNMPv3

NNMi uses information gathered from Routers to establish membership for Subnet connections. [Make sure that important Routers in your network environment are SNMP enabled.](#)

NNMi uses either of the following criteria to identify a Router:

- The Router responds to an SNMP query with appropriate values for `sysServices` (1.3.6.1.2.1.1.7) and `ipForwarding` (1.3.6.1.2.1.4.1). See RFC 1213, MIB-II for details.
- The Router responds to an SNMP query with an appropriate MIB-II `sysObjectID` value according to the current settings in NNMi's [Device Profile configuration](#).

You must provide the appropriate SNMP Community Strings to NNMi. See ["Configuring Communication Protocol" on page 129](#).

Before configuring NNMi discovery, complete the following steps:

1. Enable SNMP communication on important devices in your network (each device that you want NNMi to actively monitor).

See the manufacturer's documentation for information about how to configure SNMP on each of your devices.

- Establish *read community strings* for any SNMPv1 or SNMPv2c agents.
 - Establish the appropriate *User-based Security Module (USM) level of security for authentication and privacy* for any SNMPv3 agents.
2. Configure NNMi to use the appropriate *read community strings* (in the order you specify) or *USM settings* for your network environment. See ["Configuring Communication Protocol" on page 129](#).

Well-Configured DNS Prerequisite

NNMi uses Domain Name System (DNS) to determine relationships between hostnames and IP addresses. This can result in a large number of `nslookup` requests.

Tip: To improve the response time for `nslookup`, deploy a secondary DNS service on the NNMi management server or another system on the same subnet as the NNMi management server. Configure this secondary DNS service to mirror the information from the primary DNS service. Another option is to use `*/etc/hosts` instead of DNS in small environments.

NNMi allows hostname as a configuration criteria for multiple features. For best results ensure that your network domain has no duplicate Domain Name System (DNS) names.

Use nslookup to Verify DNS Server Configurations

Verify that your DNS servers are well configured to prevent long delays when resolving `nslookup` requests. This means the DNS server responding to NNMi `nslookup` requests has these qualities:

- The DNS server is an authoritative server and does not forward DNS requests.
- The DNS server has consistent *hostname-to-IP address* mappings and *IP address-to-hostname* mappings.
- If your network uses multiple DNS servers, all respond consistently to any particular `nslookup` request.

Caution: Round-robin DNS (used to do load balancing of web application servers) is not appropriate because any given hostname can map to different IP addresses over time.

On the NNMi management server, verify that the following configuration settings in your environment:

- **All operating systems:** Locate your `*/etc/hosts` file and ensure that the host file contains a minimum of two entries. When an `nslookup` command is not successful, this file takes over:

```
127.0.0.1 (loopback loghost) or ::1  
<NNMi_server_address> (the IP address of the NNMi management server)
```

If your NNMi management server participates in a high availability (HA) environment, the virtual server name and IP-address is required in the `*/etc/hosts` file in addition to the physical server name and IP-address.

Windows: The following registry key determines the location of this file:

```
\HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Services\Tcpip\Parameters\DataBasePath
```

Linux: This file is in the `/etc` directory.

- **Windows:** Use the Control Panel to navigate to your Network and Internet Connections configuration, Network Connections, Local Area Connections, Support tab, and click the Details button. Verify that all identified DNS servers provide consistent *hostname-to-IP address* mappings and *IP address-to-hostname* mappings.
- **Linux:** Ensure that the `nslookup` search path resolves to the `nsswitch.conf` file. See the `nsswitch.conf(4)` manpage that was provided with your operating system. Verify that all identified DNS servers provide consistent *hostname-to-IP address* mappings and *IP address-to-hostname* mappings.

Exclude Problem Devices from nslookup

You can populate two files that instruct `nslookup` to exclude certain addresses. The benefits of doing this are as follows:

- Speed up Spiral Discovery.
- Keep network traffic generated by NNMi to a minimum.

If you know there are problems with the DNS configuration in your network domain (hostnames or addresses that do not resolve properly), instruct NNMi to avoid `nslookup` requests for unimportant devices.

To identify problem devices, create the following two files before configuring NNMi discovery. NNMi never issues a DNS request for hostnames or IP addresses identified in these files:

- [hostnolookup.conf](#) — Enter fully-qualified hostnames or wildcards that identify groups of hostnames.
- [ipnolookup.conf](#) — Enter fully-qualified IP addresses or wildcards that identify groups of IP addresses.

Use an ASCII editor to populate the files. Place the files in the following location on the NNMi management server (see ["About Environment Variables" on page 86](#) for more information):

- **Windows:**
`%NnmDataDir%\shared\nnm\conf\`
- **Linux:**
`$NnmDataDir/shared/nnm/conf/`

Overlapping Address Mapping

Overlapping Address Mapping can help you manage areas in your network that are using address translation protocols, resulting in overlapping and duplicate addresses. See ["Overlapping Addresses in NAT Environments" on page 94](#) for more information about possible network configurations.

Caution: If you are configuring NNMi for areas of your network management domain that use *dynamic* Network Address Translation (NAT) or *dynamic* Port Address Translation (PAT/NAPT), the information in this section does not apply.

If *static* Network Address Translation (NAT) is part of your network management domain, and the NNMi management server is outside of that static NAT domain, you can use Overlapping Address Mapping to configure NNMi for displaying the NAT *external IP address* (public address). This value appears in the Mapped Address attribute of the IP Address form for the identified Tenant / NAT *internal IP address* pair. This configuration setting is also important for node monitoring,

Your network domain's *static* NAT configuration might apply to public IP addresses, private IP addresses, or both.

Network administrators use address translation protocols as a strategy in the following situations:

- When preventing direct Internet access to increase security.
- When not enough public IPv4 addresses are available within their network domain. Packets from the private IP address range are not permitted on the public Internet unless they pass through a protocol that converts the private IP address to a valid public address.

To configure NNMi to display the *static NAT external IP address* in the Mapped Address attribute of the IP Address form for the identified Tenant / NAT *internal IP address* pair, you must configure each domain as a unique Tenant. See ["Configure Tenants" on page 213](#).

Then do one of the following:

- Use the ["Overlapping Address Mapping Form" below](#).
- Use the command line tool [nnmloadipmappings.ovpl](#).

Tip: To see the results of all mappings, use the [Inventory: IP Addresses \(All Attributes\) view](#).

Private IP Address Ranges

The Internet Engineering Task Force (IETF) and Internet Assigned Numbers Authority (IANA)'s reserved the following IP address ranges for private networks, for example enterprise local area networks (LANs), corporate offices, or residential networks.

IPv4 private address ranges (RFC 1918):

- 10.0.0.0 – 10.255.255.255 (24-bit block)
- 172.16.0.0 – 172.31.255.255 (20-bit block)
- 192.168.0.0 – 192.168.255.255 (16-bit block)


IPv6 private address ranges:

- fc00::/7 address block = RFC 4193 Unique Local Addresses (ULA)
- fec0::/10 address block = deprecated (RFC 3879)

Overlapping Address Mapping Form

If *static* Network Address Translation (NAT) is part of your network management domain, and the NNMi management server is outside of that static NAT domain, you can use [Overlapping Address Mapping](#) to configure NNMi for the following:

- Populate the Mapped Address attribute of the IP Address form for the identified Tenant / NAT *internal IP address*. This Mapped Address attribute displays the corresponding NAT *external IP address* (public address).
- Ensure that in the following special cases, Spiral Discovery successfully detects changes:
 - The Communication Configuration you establish for a Node enables the **Enable SNMP Address Rediscovery** ☒ attribute (["Configuring Communication Protocol" on page 129](#)). This setting instructs NNMi to search for a new SNMP agent for the Node if the currently configured SNMP agent stops communicating for any reason (rather than waiting for the SNMP agent to come back online).





- The Monitoring Configuration you establish for a Node enables the **Enable IP Address Fault Polling**  attribute ("[Monitoring Network Health](#)" on page 378). This setting instructs NNMi to use ICMP. When using ICMP for this purpose, the Overlapping IP Address Mapping is required for each monitored internal address within the Static NAT.

Your network domains might use *static* NAT for duplicate addresses in enterprise local area networks (LANs), corporate offices, or residential networks. See "[Overlapping Addresses in NAT Environments](#)" on page 94 for more information about possible network configurations.

Note: If you are configuring NNMi for areas of your network management domain that use *dynamic* Network Address Translation (NAT) or *dynamic* Port Address Translation (PAT/NAPT), do not use this form. For more information:




To configure NNMi to display *static* Network Address Translation (NAT) external IP address in the IP Address form, do the following:

Tip: There is also a command line tool for this task [nnmloadipmappings.ovpl](#).

1. Prerequisite: Configure each network management domain as a unique Tenant. See "[Configure Tenants](#)" on the next page.
2. Navigate to the **Overlapping Address Mapping** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Discovery**.
 - c. Select **Overlapping Address Mapping**.
3. Do one of the following:
 - To create a new configuration, click the  **New** icon.
 - To edit an existing configuration, double-click the Overlapping IP Address Mapping definition you want to edit.
 - To delete a configuration, select the Overlapping IP Address Mapping definition you want to delete and click the  Delete icon.
4. Make your configuration choices, all three settings are required. (See the [Overlapping IP Address Mapping Attributes](#) table.)
5. Click  **Save and Close**.

Note: If you reassign a Node from one Tenant to another Tenant, this setting does not automatically update.

Overlapping Address Mapping Attributes

Attribute	Description
Tenant	<p>Designate which Tenant owns the Addresses you are mapping. See "Configure Tenants" below.</p> <p>Click the  Lookup icon and do one of the following:</p> <ul style="list-style-type: none"> To select an existing Tenant configuration, click the  Quick Find icon To create a new configuration, click the  New icon. <p>Note: This attribute value does not automatically update if the NNMi administrator reassigns the Node to another Tenant.</p>
External Address	<p>Provide the appropriate substitute address configured in <i>static</i> Network Address Translation (NAT) for the Internal Address (next value).</p> <p>The address you provide here shows up in the IP Address form's Mapped Address attribute if NNMi discovers the designated Tenant / Internal Address pair.</p>
Internal Address	<p>Provide the address that requires mapping.</p> <p>The External Address you map to this address appears in the IP Address form's Mapped Address attribute.</p>

Configure Tenants

For details about configuring Tenants, see the following:

Use the Tenant Form	215
Tenant and Initial Discovery Security Group Assignments	217

NNMi administrators use Tenant settings to accomplish the following:

- Identify overlapping address domains in your network so NNMi can avoid duplicate address problems. An unique Tenant is required for each group of devices configured to use any of the following *address translation protocols*:
 - Static* Network Address Translation (NAT)
 - Dynamic* Network Address Translation (NAT)
 - Dynamic* Port Address Translation (PAT/NAPT)

For more information:

- Determine precise groups of Nodes when your Subnet mask strategy fails. NNMI uses the Tenant:Subnet pair to identify each group of Nodes. You can manage groups of Nodes even when deployed Subnets conflict within your network management domain. Nodes within a Subnet can belong to different Tenants. NNMI calculates each Tenant's Subnets independently. NNMI administrators can easily change an Node's Tenant assignment, see ["Change Tenant Assignment for a Node" on page 321](#).

If you configure a Subnet Connection Rule, the rule independently applies to each Tenant. The members of Subnets must be unique Tenant/Node pairs (each Node assigned to only one Tenant). A Subnet Connection Rule can establish a link between the Default Tenant and another Tenant. However, links between two Tenants are not allowed *unless one of them is the Default Tenant*. See ["Consider IPv4 Subnet Connection Rules" on page 200](#).

- Control the connections NNMI identifies among Nodes.

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

- Establish the relationship between Provider Edge ([PE¹](#)) devices and Customer Edge ([CE²](#)) devices. Assign Provider Edge ([PE³](#)) devices to the Default Tenant. Assign Customer Edge ([CE⁴](#)) devices to a Tenant created by the NNMI administrator.
- Assign any infrastructure device that interconnects multiple Network Address Translation ([NAT⁵](#)) domains (such as a NAT gateway) to the Default Tenant. This ensures that NNMI displays the Layer 2 Connections your team and customers need to see.
- Identify members of a Router Redundancy Group (all members must be assigned to the same Tenant, multiple Router Redundancy Groups can belong to the same Tenant).
- *Global Network Management*: Manage the Tenant and Security Group settings for Nodes replicated from Regional Managers to the Global Manager. See ["About Multi-Tenancy and Global Network Management" on page 100](#) and ["Tenant Best Practices for Global Network Management" on page 102](#).

Tenant definitions can be exported/imported among all NNMI management servers. See ["Export/Import Behavior and Dependencies" on page 1610](#).

¹Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

²Customer Edge router. The router in your network that sends data to an Internet Service Provider's router (the Provider Edge) on the path to the data's final destination.

³Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

⁴Customer Edge router. The router in your network that sends data to an Internet Service Provider's router (the Provider Edge) on the path to the data's final destination.

⁵Network Address Translation. NNMI supports the following protocols: Static Network Address Translation, Dynamic Network Address Translation, Dynamic Port Address Translation.

- Conveniently assign an *Initial Discovery Security Group* to Seeds before discovery.

NNMi administrators can change a node's Tenant or Security Group assignment at any time. See ["Specify Discovery Seeds" on page 287](#) for more information.

Note: *Auto-Discovery* is available only for the Default Tenant. Each automatically discovered node is assigned to the Default Tenant (and the *Initial Discovery Security Group* currently configured for newly discovered nodes in the Default Tenant).

Devices within the Default Security Group are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

- Identify logical groups of Nodes for any purpose, for example to identify the resources assigned to a specific customer or to identify specific areas of your network or to identify company sites.
- Create Node Groups based on Tenant attribute values. See ["Specify Node Group Additional Filters" on page 330](#) for more information about Node Group filters.
- Configure Incidents based on Tenant attribute values. See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

Use the Tenant Form

NNMi's Tenant configuration settings are useful for a variety of situations. Review the Tenant information so you know about all your options. See ["Configure Tenants" on page 213](#) for more information.

NNMi provides a Tenant named *Default Tenant*. NNMi administrators can create additional Tenant objects as needed. A discovered node that is not specifically assigned to a particular Tenant, automatically becomes a member of the Default Tenant. NNMi administrators can change a Node's Tenant assignment at any time. Depending on the network environment, the NNMi administrator decides whether or not additional Tenants are needed.





When additional Tenants are defined, Tenant assignments are visible in the Node form's [Basic Attributes](#) and in the Tenants column of the [Inventory > Nodes view](#).

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Tip: Assign any infrastructure device that interconnects multiple NAT domains (such as a NAT gateway) to the Default Tenant. This ensures that NNMi displays the Layer 2 Connections your team and customers need to see.

NNMi administrators can easily change a Node's Tenant assignment at any time, see ["Change Tenant Assignment for a Node" on page 321](#).

To configure a Tenant, do the following:

1. Navigate to the **Tenants** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select **Discovery**.
 - c. Select **Tenants**.
 - d. Do one of the following:
 - To create a new configuration, click the  **New** icon.
 - To edit an existing configuration, double-click the Tenant definition you want to edit.
 - To delete a configuration, select the Tenant definition you want to delete and click the  Delete icon.
2. Make your configuration choices. (See the [Tenant Attributes](#) table.)
3. Click  **Save and Close**.
4. Best practice: If the Tenant participates in a Global Network Management environment, replicate the Tenant configuration to the Global Manager.
5. The Tenant attribute displays on each Node form (use the drop-down list to change the assigned Tenant attribute value, or use [nnmsecurity.ovpl](#)).



NNMi administrators use the Tenant object to do the following:

- Associate a Tenant with each Discovery seed - before discovery ("[Specify Discovery Seeds](#)" on page 287).
- Enable monitoring of nodes with addresses provided by *static* Network Address Translation (NAT), *dynamic* Network Address Translation (NAT), or *dynamicPort* Address Translation (PAT/NAPT), see "[Overlapping Addresses in NAT Environments](#)" on page 94.
- "[Specify Node Group Additional Filters](#)" on page 330
- Populate the Tenant attribute on the Node form (see "[Custom Incident Attributes Provided by NNMi \(Information for Administrators\)](#)" on page 733).

Tenant Attributes

Attribute	Description
Name	<p>Enter the name that uniquely identifies this Tenant.</p> <p>If your team uses NNMi's Global Network Management feature, before choosing a name, see "About Multi-Tenancy and Global Network Management" on page 100.</p> <div>Note: You must enter a Name value.</div>

Tenant Attributes, continued

Attribute	Description
UUID	NNMi assigns a Universally Unique Object Identifier to the Tenant. This UUID is unique across all databases.
Description	Type a maximum of 2048 characters to describe this User Group. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
Initial Discovery Security Group	<p>The Initial Discovery Security Group specifies the Security Group assigned to any <i>seed</i> associated with this Tenant object (before discovery). See "Tenant and Initial Discovery Security Group Assignments" below and "About Security Groups" on page 582.</p> <div><p>Caution: Devices within the <i>Default Security Group</i> are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group. NNMi administrators can assign each Node within one Tenant to a different Security Group.</p></div> <p>In the Initial Discovery Security Group attribute, do one of the following:</p> <ul style="list-style-type: none">To change the Initial Discovery Security Group, begin to type a valid Security Group Name and use the auto-complete feature to select the Security Group. <div><p>Tip: You can also select  Quick Find from the Lookup field drop-down list. This option is useful when you want to see more than the Security Group Name when determining which Security Group to select.</p></div> <ul style="list-style-type: none">To create a new Initial Discovery Security Group, in the Lookup field, select the  New icon.

Related Topics

["Troubleshoot NNMi Access" on page 659](#)

["About Security Groups" on page 582](#)

Tenant and Initial Discovery Security Group Assignments

When NNMi discovers nodes in your network environment, Tenant and Security Group settings are established in the following manner:

- Discovery Seeds:** If Nodes are discovered as Discovery seeds, the NNMi administrator specifies a Tenant for each Discovery Seed. See ["Specify Discovery Seeds" on page 287](#). When NNMi administrators define a Tenant, they specify an **Initial Discovery Security Group**.

Any newly discovered Node within the defined Tenant is assigned to this Security Group. NNMi administrators can change either the node's Tenant or Security Group assignment or both at any time.

Nodes assigned to the *Default Security Group* are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

Nodes within one Tenant can each be assigned to different Security Groups, and Nodes within one Security Group each be assigned to different Tenants.

- **Auto-Discovery for Default Tenant:** When you configure Auto-Discovery Rules, NNMi assigns any Nodes discovered using those Auto-Discovery Rules to the *Default Tenant* and whichever Security Group is currently configured as the Default Tenant's Initial Discovery Security Group setting (the *Default Security Group* out-of-box). See ["Configure Tenants" on page 213](#).

Global Network Management: Regional Managers forward information about Nodes to the Global Manager. The Global Manager's copy of the Node object has the same Tenant assignment as the Regional Manager's record of that Node.

In a Global Network Management environment, best practice is to have the NNMi administrators for the Global Manager and all Regional Managers agree to a predefined list of Tenant names. Those Tenants would be defined on the Regional Managers, the Tenant definitions exported, and those Tenant definitions imported onto the Global Manager (thus ensuring that the UUID and name value for each Tenant match on both NNMi management servers). The NNMi administrator on the Global Manager update their Tenant definitions to assign Initial Discovery Security Group values that make sense for the Global Manager's team. See ["About Multi-Tenancy and Global Network Management" on page 100](#) for more information.

Note: If a Regional Manager forwards information about a Node to the Global Manager, and that Node is assigned to a Tenant object that does not exist on the Global Manager, NNMi creates a Tenant with the UUID and name from the Regional Manager, but creates a new Security Group with that Tenant name (does not duplicate the Regional Manager's setting for that Tenant's *Initial Discovery Security Group* setting). NNMi maps that new Security Group to the following:

- User Group = NNMi Administrator
- Object Access Privilege = Object Administrator

The Global Manager's NNMi administrator can assign a *different* Initial Discovery Security Group to a Tenant definition at any time. From that point onward, the NNMi Global Manager uses that new Initial Discovery Security Group setting when creating new nodes within that Tenant.

Consider setting up your Security Configuration so that all newly-discovered Nodes belong to a Security Group that is mapped to User Group = NNMi Administrators. Those Nodes will be visible only to NNMi administrators until an NNMi administrator intentionally moves the node into a Security Group that is also visible to the appropriate NNMi operator or guest.

Tenant assignments determine L2 Connections between nodes on NNMi maps, and are useful for identifying groups of nodes within your network environment (for example, subnets, router redundancy groups, and Node Groups). Security Group assignments enable NNMi administrators to restrict the visibility of nodes within the NNMi console to specific User Groups. See ["Configuring Security" on page 569](#) for more information.

Configure Discovery

NNMi uses Simple Network Management Protocol (SNMP read-only queries), and a variety of communication protocols to discover the devices within the network management domain that you define. See ["How Spiral Discovery Works" on page 195](#) for more information.

NNMi provides one predefined Tenant, the *Default Tenant*. Each Node must be assigned to a Tenant. If you choose to use Auto-Discovery Rules, those rules apply only to the nodes within the Default Tenant. All other Discovery configuration settings apply to the nodes within all Tenants.

Tip: Optional. Establish additional Tenant configurations to identify overlapping address domains or to fine tune Layer 2 connections between devices in your network domain. For details, see ["Configure Tenants" on page 213](#).

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Discovery Configuration Tasks

Task	How
"Prerequisites for Discovery" on page 207	Complete all prerequisites..
"Establish Global Defaults for Spiral Discovery" on page 221	Use the Global Control panel to review the default values that NNMi provides. Determine if those defaults work for Spiral Discovery in your network environment. NNMi administrators can change the default settings at any time.
"Configure Schedule Settings" on page 230	Use the Schedule Settings tab to review the default values that NNMi provides for Spiral Discovery's Schedule Settings. Determine if those defaults work for Spiral Discovery in your network environment. NNMi administrators can change the default settings at any time.
"Configure Auto-Discovery Rules" on page 236	<i>Optional.</i> Use the Auto-Discovery Rules tab to specify ranges of IP addresses or MIB-II sysObjectID values (or both) that you want NNMi to automatically discover or never discover within the Default Tenant.

Discovery Configuration Tasks , continued

Task	How
	<p>Note: NNMi assigns each node found by Auto-Discovery to the <i>Default Tenant</i> (and whichever Security Group attribute value is currently configured for the Default Tenant = the <i>Default Security Group</i> out-of-box). See "Configure Tenants" on page 213 and "About Security Groups" on page 582 for more information.</p>
"Configure IPv4 Subnet Connection Rules" on page 265	<p><i>Optional.</i> Use the IPv4 Subnet Connection Rules tab to establish connections between interfaces on devices that <i>do not respond</i> to Layer 2 <i>discovery protocols</i> (see the list of Topology Source protocols in Layer 2 Connection Form). For example, use Subnet Connection Rules to establish connections to WAN edge devices that NNMi would not automatically detect.</p>
"Configure an Excluded IP Addresses Filter" on page 274	<p><i>Optional.</i> Use the Excluded IP Addresses tab to provide a list of specific addresses or ranges of addresses that you want NNMi to <i>never</i> discover or monitor.</p> <p>This filter applies to all nodes in all Tenants.</p>
"Configure an Included Interface Ranges Filter" on page 277	<p><i>Optional.</i> Use the Included Interface Ranges tab to provide a MIB-II sysObjectID list and designate which Interfaces within devices of that type NNMi is permitted to discovery (all other interfaces within devices meeting the MIB-II sysObjectID criteria are ignored).</p> <p>This filter applies to all nodes in all Tenants.</p>
"Configure an Excluded Interfaces Filter" on page 280	<p><i>Optional.</i> Use the Excluded Interfaces tab to provide a list of specific interfaces that you want NNMi to <i>never</i> discover or monitor.</p> <p>This filter applies to all nodes in all Tenants.</p>
"Choose Techniques to Launch Discovery" on page 282	<p>You control Spiral Discovery's starting points:</p> <ul style="list-style-type: none"> Any Tenant: Use the Seeds Configuration workspace to specify the nodes to be discovered. <p>Tip: Use the Seeds workspace to verify that NNMi successfully located each Discovery Seed that you provided. See "Discovery Seed Results" on page 299.</p> <ul style="list-style-type: none"> Default Tenant only: If you choose to use Auto-Discovery, there are two choices for launching discovery. Seeds can provide the starting points from which Auto-Discovery gathers information about neighboring devices to expand discovery. Or Ping Sweep settings can enable Auto-Discovery to find any device that responds to Ping commands.

Establish Global Defaults for Spiral Discovery

Decide if you want to change any of the global default settings for Spiral Discovery:

Configure Discovery of ATM/Frame Relay Interfaces	221
Configure Ping Sweep (override for all Auto-Discovery Rules)	222
Configure the Node Name Strategy	223
Configure Layer 2 Connection Source	228

The Global Defaults determine the following:


- Enable/Disable ATM / Frame Relay Interfaces for Performance Monitoring.
- Enable/Disable Ping Sweep for Auto-Discovery of IPv4 addresses.
- Configure the strategy NNMi uses to determine Node Names.
- Specify zero or one Node Group from which Spiral Discovery will *ignore* the Forwarding Database (FDB) data when calculating Layer 2 Connections (the FDB data is still included in other calculations).

Configure Discovery of ATM/Frame Relay Interfaces

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

If your network environment includes devices that are using Asynchronous Transfer Mode (ATM) or Frame Relay protocols, NNM iSPI Performance for Metrics can provide useful information about network activity that is using those protocols.

To enable/disable Discovery of ATM/Frame Relay Interfaces:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Locate the **Global Control** settings.

3. Specify the ATM/Frame Relay Discovery setting.

Global Control Attributes

Name	Description
Enable Discovery of ATM/Frame Relay Interfaces for Performance Monitoring	<p>If your team installed <i>HP Network Node Manager iSPI Performance for Metrics Software</i>:</p> <p>If <input checked="" type="checkbox"/> enabled, this attribute extends the range of data that NNMi gathers for ATM and Frame Relay interfaces.</p> <p>If <input type="checkbox"/> disabled NNMi does not discover and gather the extended ATM and Frame Relay data that NNM iSPI Performance for Metrics uses for reporting purposes.</p> <p>See also "Configure NNMi Monitoring Behavior" on page 387 for information about the Monitoring Configuration settings for <i>Enable ATM Interface Performance Polling</i> and <i>Enable Frame Relay Interface Performance Polling</i> (Default, Node, or Interface settings).</p>

4. Click  **Save and Close** to apply your changes.

Configure Ping Sweep (override for all Auto-Discovery Rules)

Default Tenant only: You have two choices for Auto-Discovery starting points. Use either or both to best advantage in your network environment:

- Discovery Seeds: You designate specific hostnames (*not case-sensitive*) or IP addresses where Auto-Discovery starts gathering neighbor information.

For details see ["Discovery Seeds for Auto-Discovery in Default Tenant" on page 283](#). For information about creating Discovery Seeds. See ["Specify Discovery Seeds" on page 287](#).


- Ping Sweep: NNMi issues ICMP pings to certain addresses to find new nodes. For details, see ["Ping Sweep for Auto-Discovery in Default Tenant" on page 285](#).

IPv4 addresses only: In Wide Area Networks (WANs) such as ATM, Frame Relay, and Point-to-Point (where ARP cache is not available), the optional ["Ping Sweep for Auto-Discovery in Default Tenant" on page 285](#) feature locates nodes for Auto-Discovery to use when gathering neighbor information and evaluating connections between nodes, see also ["Consider IPv4 Subnet Connection Rules" on page 200](#).

Note: Ping Sweep works only with IPv4 addresses and only in 16-bit subnets. All nodes discovered using Auto-Discovery are assigned to the *Default Tenant*.

Ping Sweep uses the current default ICMP interval and timeout settings from the Communications Configuration settings. See ["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#).


To configure the global Auto-Discovery setting for Ping Sweep:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Navigate to the **Global Control** settings.
3. Designate the global setting for **Ping Sweep**. Your choice determines how Auto-Discovery uses ICMP ping commands for the discovery process in your network environment:
 - **Each Rule (as configured)**— The instructions for Ping Sweep within each Auto-Discovery Rule configuration are followed exactly.

To configure Ping Sweep for a specific Auto-Discovery Rule, see ["IP Address Ranges for the Auto-Discovery Rule" on page 244](#).

- **All Rules**— Ping Sweep is applied for all of your current Auto-Discovery Rules. This overrides the Ping Sweep settings within each rule. Spiral Discovery issues the initial round of Ping Sweep commands when you click Save and Close.
- **None of the Rules**— Ping Sweep is not used for any of your current Auto-Discovery Rules. This overrides the Ping Sweep settings within each rule. This is useful to temporarily suspend issuing any ping commands within your network.

Note: If things do not work as expected, check whether ICMP is enabled (see if ["Communication Region Form" on page 150](#)).

4. Designate the **Sweep Interval** (days/hours) that controls how often Auto-Discovery reissues ICMP Ping for each address. The minimum Sweep Interval setting is 1 hour. Maximum 99 days.
5. Click  **Save and Close**. Spiral Discovery issues the initial round of Ping Sweep commands when you click Save and Close.

Configure the Node Name Strategy

For more details about how NNMi determines the Node name, see the following:


Discovery Node Name Choices 226

Node Name Decision Tree 227

NNMi administrators control how the Name attribute on the Node form is populated. To resolve issues about choosing the Name value, NNMi follows a sequence of rules. If NNMi is unable to determine a Name based on your three choices, the node name is determined using the NNMi factory defaults for these three choices (see list in step 3).

The node Name shows up beneath the node symbol on the maps and in the Name column on table views.

To control how node names are determined for your network devices:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Locate the **Node Name Resolution** attributes on the left side of the form (see [table](#)).
3. Specify the three-level hierarchy for node naming decisions.

Short name and full name are related. The short name is everything before the first period in the full name. For example, full name `cisco5500.abc.example.com` and the short name `cisco5500`.

Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:


- `nms-topology.properties` file settings:
If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.
- `nms-disco.properties` file settings:
The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

Select among the following choices. Use each choice only one time:

- **Short DNS Name** – (*first by default*) Use the group of characters before the first period in your in-house DNS naming standards. See ["Discovery Node Name Choices" on the next page](#) for possible issues with using DNS names.
- **Fully Qualified DNS Name** – Use the full in-house DNS naming standards.
- **Short sysName** – (*second by default*) Use the group of characters before the first period in the current MIB-II sysName value established by the administrator for each SNMP enabled device. See ["Discovery Node Name Choices" on the next page](#) for possible issues with using sysName.
- **Full sysName** – Use the full MIB-II sysName value established by the administrator for each SNMP enabled device.
- **IP Address** – (*third by default*) Use the IP address. If the node responds to SNMP, the SNMP Management Address is used. For non-SNMP nodes, name is set to either a discovery seed address associated with this node or a neighbor address gathered by Auto-Discovery along the path to this node.

Note: NNMi administrators choose how NNMi uses address protocols:

- The *Excluded IP Addresses* filter, Spiral Discovery skips addresses or ranges of addresses configured in this file. See [Configure an Excluded IP Addresses Filter](#).
- The *IP Version Preference* setting, NNMi Advanced uses IPv4 addresses, IPv6 addresses, or dual-stack (both) addresses according to configuration choices. See [Configure Default SNMP, Management Address, and ICMP Settings](#).

4. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Node Name Resolution Settings

Attribute	Description
First Choice	Click the drop-down list and choose the predefined node name strategy you want discovery to use first.
Second Choice	Click the drop-down list and choose the predefined node name strategy you want discovery to use if the first choice fails.
Third Choice	Click the drop-down list and choose the predefined node name strategy you want discovery to use if the second choice fails.

Discovery Node Name Choices

Control how the **Name** attribute on node forms is populated during discovery. This Name value is used to identify the object in NNMi maps and table views. You specify a hierarchy for discovery to use. You configure three levels in the hierarchy. See ["Node Name Decision Tree" on the next page](#).

You can designate any of the following for each level of the node Name decision hierarchy:

- **DNS Names.** Discovery uses the results of hostname resolution.

NNMi follows a set of rules to dynamically generate the value stored in the NNMi database for each Node's Hostname. [Click here for details](#).

- If the Node supports SNMP, NNMi requests the Hostname using the IP Address of the associated SNMP agent (the Management Address attribute value on the Node form).

When the NNMi administrator chooses **Enable SNMP Address Rediscovery** ☒ in the Communication Configuration:

- If the SNMP Agent does not respond, NNMi checks for another Management Address to request the Hostname, and the Hostname could change.
- If the SNMP Agent associated with the node changes, the Management Address and Hostname could change.

When the NNMi administrator disables **Enable SNMP Address Rediscovery** ☐ in the Communication Configuration:

- If the SNMP Agent does not respond, NNMi uses the previously gathered Management Address attribute value to request the Hostname.
- If the SNMP Agent associated with the node changes, NNMi uses the previously gathered Management Address attribute value to request the Hostname.
- If the Node does not support SNMP, no Management Address is available. NNMi requests a Hostname starting with the lowest IP Address associated with the node (a Discovery Seed value or an IP address value gathered from a neighboring device). NNMi uses the first Hostname provided. The Hostname might change during a future discovery cycle.

Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:

- `nms-topology.properties` file settings:
If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the *HP Network Node Manager i Software*

Deployment Reference, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

- **nms-disco.properties** file settings:

The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

- **MIB-II sysName Values.** Device administrators set the sysName. Discovery avoids populating the NNMi database with multiple devices having the same manufacturer's default sysName. If a sysName matches or starts with the manufacturer's default factory setting (case-sensitive), discovery ignores sysName as a choice for the Name attribute of the node. NNMi ships with a Device Profile for each device type (vendor/make/model). The Device Profile includes a record of the manufacturer's default sysName.

Caution: You can override this choice using the Device Profile's Advanced settings, Never Use sysName attribute. See ["Configure Device Profiles" on page 323](#) for more information.


- **IP addresses.** The addresses are gathered from [discovery seed addresses](#) that you provided, [ping sweep](#) configurations, or neighbor addresses gathered using [Auto-DiscoveryRules](#). Discovery avoids potential confusion when a device has multiple IP addresses by following these rules:
 - If the device supports SNMP, the address of the responding SNMP agent is recorded (the Management Address) and the other addresses are associated with the node. See ["Specific Node Settings Form \(Communication Settings\)" on page 171](#) for more information about configuring the management address.
 - If the device does not support SNMP, NNMi queries DNS to determine the hostname. If this hostname matches another non-SNMP node, NNMi merges the information to create only one node with multiple associated addresses.

See ["Configure the Node Name Strategy" on page 223](#) to learn how to configure the NNMi node name strategy.

Node Name Decision Tree

For each discovered address, NNMi gathers multiple attributes that are used to implement your Node Name strategy. NNMi chooses the Node Name based on the Management Address, System Name, and Hostname collected during discovery. The following diagram shows how NNMi determines values for these attributes.

Note: If you change a node's Hostname, there is a delay before NNMi data reflects the name change, because NNMi caches DNS names to enhance performance.




Configure Layer 2 Connection Source

Note: (NNMi Advanced - Global Network Management feature) Both of the settings described below depend on your Node Group definitions. Node Group definitions are not replicated from Regional Managers to the Global Manager, see ["Create Node Groups" on page 326](#). To easily share your Node Group definitions, see ["Export and Import Configuration Settings" on page](#)

1610.

Optional: To configure NNMi for calculating FDB and unnumbered interface influence on Layer-2 Connections:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.

2. On the left side of the form, locate **Layer 2 Connection Source**.



3. *(Optional)* Configure the **Node Group to disable FDB** setting.

Forwarding Database (FDB) information can cause NNMi to establish wrong Layer 2 Connections in the following cases:

- When the FDB is configured as cache and contains obsolete data.
- In network environments with hardware from a variety of vendors, when each vendor generates different and sometimes conflicting FDB data.

Optional: NNMi administrators can configure Spiral Discovery to ignore the FDB data from one Node Group when calculating Layer 2 Connections (the FDB data is still included in other calculations).

To specify which Node Group's FDB information will be ignored, do one of the following:

- Click the drop-down list and choose a previously defined Node Group.
- Select the  Lookup icon and select  New to create a new Node Group.


Note: (NNMi Advanced - Global Network Management feature) NNMi must read the Forwarding Database (FDB) tables from Ethernet switches within the network before accurate communication paths between these network devices can be calculated. Because FDB data is involved, NNMi can produce different results on a Regional Manager as opposed to the Global Manager.

4. *(Optional)* Configure the **Enable Unnumbered Interface Connectivity** setting.

Unnumbered interface connectivity involves querying routing tables, which can generate a lot of network traffic when the routing tables are large. If your network environment requires monitoring of unnumbered interfaces, configure the following:

- Enable this setting:
☒ Enable Unnumbered Interface Connectivity

Note: (*NNMi Advanced - Global Network Management feature*) This attribute must be enabled on each Regional Manager and the Global Manager.

- Use the [Unnumbered Interface Node Groups tab](#) or `nnmunnumberedcfg.ovpl` command-line tool to designate the following:
 - Which Node Groups will have Layer 2 Connectivity
 - (*Optional*) Which specific subnets within each participating Node Group will be monitored for Layer 2 Connectivity. These settings serve as a filter to further limit NNMi's discovery and monitoring of unnumbered interfaces.
5. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Configure Schedule Settings

For details about Spiral Discovery's Schedule Settings, see the following:

Adjust the Rediscovery Interval	231
Adjust the Node Group Rediscovery Interval	232
Configure Whether to Delete Unresponsive Nodes	233
Configure Whether to Delete Layer 2 Connections	235

Spiral Discovery's Schedule Settings determine how often NNMi requests data and updates information about the devices in your network domain. NNMi requests the following information:

- Information about the nodes, addresses, and interfaces you configure for discovery.
- Information about Level 2 connectivity between interfaces and VLANs in your network.
- Information about Level 3 connectivity between addresses in your network.


Make sure the interval value you choose provides plenty of time so Spiral Discovery cycles do not overlap. The larger your network environment, the longer the time required to complete a Spiral Discovery cycle. These Schedule Settings might help NNMi administrators meet service-level agreement (SLA) commitments.

Adjust the Rediscovery Interval

When configuring Spiral Discovery, you determine how often network traffic is generated to gather and verify information about your network management domain. This time interval controls how frequently information is gathered about nodes, interfaces, IP addresses, subnets, VLANs, and connections in the network. See ["Configure Schedule Settings" on the previous page](#) for more information.

Tip: You can also adjust the Rediscovery Interval for a specified Node Group. See ["Adjust the Node Group Rediscovery Interval" on the next page](#) for more information.


To adjust the rediscovery cycle interval:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Locate the **Schedule Settings** tab.
3. In the **Rediscovery Interval** attribute, set the time interval that Spiral Discovery waits between information gathering cycles.

The default is 24 hours between cycles. The minimum is 1 hour.

Make sure the interval value provides plenty of time so Spiral Discovery cycles do not overlap. The larger your network environment, the longer the time required to complete a Spiral Discovery cycle.

Note: During rediscovery, NNMi checks each Node for membership in Node Groups. If the Node belongs to a Node Group that is associated with a Custom Poller Policy, NNMi might issue additional requests for information. See ["Create Custom Polling Configurations" on page 478](#) for more information.

4. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

5. *Optional.* To establish the *beginning* of the interval, schedule a task to run the `nnmnoderediscover.ovpl -a11` command line tool. Consider choosing a quiet time on your

network so traffic generated by NNMi does not disturb regular business.

The Spiral Discovery cycle start time might change slightly depending on circumstances within your network environment. Use the [Nodes \(All Attributes\)](#) view and sort on the **Last Completed** column (last Discovery cycle) to check recent times.

Related Topics

["Adjust the Node Group Rediscovery Interval" below](#)


Adjust the Node Group Rediscovery Interval

When configuring Spiral Discovery, you determine how often network traffic is generated to gather and verify information about your network management domain. This time interval controls how frequently information is gathered about the nodes, interfaces, IP addresses, subnets, VLANs, and connections in the network for the specified Node Group. See ["Adjust the Rediscovery Interval" on the previous page](#) for more information.

There are two benefits to using a Node Group Rediscovery Interval:

- You have many choices about the criteria for defining your Node Group (see ["Create Node Groups" on page 326](#)).
- Your Node Group Rediscovery Interval enables a subset of devices to be rediscovered at a different rate than the default Rediscovery Interval. For example, this feature could be useful to configure NNMi to do the following:
 - Help NNMi administrators meet service-level agreement (SLA) commitments.
 - More frequently rediscover device configuration changes for frequently changing devices or your most important devices.
 - Less frequently rediscover unimportant devices in your network domain to minimize network traffic.

To adjust the Node Group rediscovery cycle interval:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Locate the **Schedule Settings** tab.
3. In the **Node Group** attribute, specify the name of the Node Group for which you want to configure the Node Group Rediscovery Interval.
4. In the **Node Group Rediscovery Interval** attribute, set the time interval that Spiral Discovery

waits between information gathering cycles.


The default is 24 hours between cycles. The minimum is 1 hour.

Make sure the interval value provides plenty of time so Spiral Discovery cycles do not overlap. The larger your network environment, the longer the time required to complete a Spiral Discovery cycle.

Specify the **Node Group Rediscovery Interval**. If a Node is reconfigured so that one or more attribute values no longer match the specified Node Group's configuration criteria, the next time the Node is discovered, it is removed from the Node Group. NNMi then determines when to rediscover the Node using the **Rediscovery Interval** setting.

For example, if a Node Group is created using sysName as an Additional Filter, and the System Name value is changed for a Node, that Node will no longer belong to the Node Group. After the Node is removed from the specified Node Group, NNMi uses the **Rediscovery Interval** setting instead of the **Node Group Rediscovery Interval** setting to determine when to update discovery information for the Node.

Note: During rediscovery, NNMi checks each Node for membership in Node Groups. If the Node belongs to a Node Group that is associated with a Custom Poller Policy, NNMi might issue additional requests for information. See ["Create Custom Polling Configurations" on page 478](#) for more information.

5. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

6. *Optional.* To establish the *beginning* of the interval, schedule a task to run the [nnmnode rediscover.ovpl](#) -all command line tool. Consider choosing a quiet time on your network so traffic generated by NNMi does not disturb regular business.

The Spiral Discovery cycle start time might change slightly depending on circumstances within your network environment. Use the [Nodes \(All Attributes\)](#) view and sort on the **Last Completed** column (last Discovery cycle) to check recent times.

Related Topics

["Adjust the Rediscovery Interval" on page 231](#)

Configure Whether to Delete Unresponsive Nodes

When configuring Spiral Discovery, you determine whether and how quickly NNMi deletes nodes that are unresponsive.

Note: NNMi does not delete any unresponsive object during the first 24 hours after NNMi is restarted ([ovstart](#)). The 24 hour additional wait time ensures that NNMi has an opportunity to poll each Node.

Caution: To understand the results of deleting a Node, see ["Delete Nodes" on page 1635](#) and ["Delete One or More Objects" on page 1638](#).


NNMi automatically deletes an unresponsive node using the following criteria:

- The node does not respond to SNMP requests for the specified number of days.
- All of the node's IP Addresses do not respond to ICMP for the specified number of days.

One of the following Conclusions must be associated with the Node. See the help for [Node Form: Conclusions Tab](#) for more information:


- NodeUnmanageable
- NonSNMPNodeUnmanageable
- NodeDown
- NodeOrConnectionDown

To configure NNMi to automatically delete Unresponsive Objects:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Navigate to the **Schedule Settings** tab.
3. In the **Period (in Days) to Delete Unresponsive Nodes** attribute, set the number of days that a Node must be unresponsive before NNMi deletes the node and all nodes in its shadow from the NNMi database (as well as each Node's history and related objects). For more information about nodes in the shadow, see [Node Down](#).

0 (zero, the default value) = Do not delete from the NNMi database.

Any number provided represents the number of days that the object must remain unresponsive.

4. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Configure Whether to Delete Layer 2 Connections

When configuring Spiral Discovery, you determine whether and how frequently NNMi deletes connections that are down.

NNMi deletes connections once per day (1 a.m. by default).

NNMi automatically deletes any Layer 2 Connections that are Down using the following criteria:

- The ConnectionDown Conclusion must be associated with the connection for the specified number of days. See [Layer 2 Connection Form: Conclusions Tab](#) for more information.
- (NNMi Advanced) When interfaces are participating in [Link Aggregation](#)¹ or [Split Link Aggregation](#)² protocols, NNMi automatically deletes *Aggregation Member Layer 2 Connections* that have the ConnectionDown Conclusion for the specified number of days.

Note: During the next Rediscovery cycle, NNMi deletes any *Aggregator Layer 2 Connections* without any Aggregation Member Layer 2 Connections.

- When the Layer 2 Connection object's **Topology Source** value is one of the following, NNMi *never* automatically deletes the connection (see the Help topic for [Layer 2 Connection Form](#) for more information):

ROUTES - Indicates that an unnumbered Interface is involved in this connection. The NNMi administrator has enabled the Unnumbered Interface Connectivity feature. For more information:

SUBNETCONNECTION - Subnet Connection Rule. NNMi applied a special configurable rule for subnets (only those IPv4 subnets with a prefix length between 28 and 31) to detect this connection. NNMi gathers information from Layer 3 of the Open System Interconnection (OSI) networking model to detect this connection. Layer 3 is the Network layer that provides switching, routing, and logical paths (virtual circuits) for transmitting data between nodes. The NNMi administrator configures the Subnet Connection Rules, see "Help for

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.


²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Administrators" for more information. On the NNMi map, the following icon is in the middle of the SUBNETCONNECTION line:




USER - This connection was configured by your NNMi administrator (using the Connection Editor). See "Help for Administrators" for more information.

To configure NNMi to automatically delete down Layer 2 Connections:

1. Navigate to the **Discovery Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
2. Navigate to the **Schedule Settings** tab.
3. In the **Period (in Days) to Delete Connections that are Down** attribute, set the number of days that a Connection must be down before NNMi deletes the connection.

0 (the default value) = Do not delete from the NNMi database.

Any number provided represents the number of days that the object must remain unresponsive.

4. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Tip: To confirm that NNMi is successfully automatically deleting Layer 2 Connections, look for the following message in the `nnm.log` file:

One connection with name `<ConnectionName>` has been deleted, because it has been down for `<N>` days with StatusConclusion ConnectionDown. See the "NNMi Logging" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.)

Layer 2 Connections can be deleted manually, see ["Delete One or More Objects"](#) on page 1638.

Configure Auto-Discovery Rules

Auto-Discovery Rule configuration settings control Auto-Discovery behavior within the *Default*

Tenant:

Auto-Discovery Rule Behavior Choices	238
Configure Basic Settings for the Auto-Discovery Rule	240
IP Address Ranges for the Auto-Discovery Rule	244
SNMP System Object ID Ranges for the Auto-Discovery Rule	248
Example Uses of Auto-Discovery	251

Auto-Discovery extends discovery by gathering Hints about additional devices:

- Auto-Discovery gathers information about neighboring devices using ARP cache, DNS, and the following protocols:
 - **BGP** — Border Gateway Protocol
 - **EIGRP** — Cisco Enhanced Interior Gateway Routing Protocol
 - **OSPF** — Open Shortest Path First
 - And data gathered from a variety of Layer 2 *discovery protocols*. See the list of Topology Source protocols in [Layer 2 Connection Form](#).
- Auto-Discovery monitors SNMP traps from previously discovered IP addresses for additional information.

Auto-Discovery also uses the source IP address from SNMP traps as Discovery Hints for new addresses. If your Auto-Discovery Rules' IP Ranges include that new IP address, NNMi uses the Trap Hint for initial discovery of that address. NNMi then requests the Node's current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all further communication. NNMi calculates whether the new address belongs to a previously discovered Node or a new Node.

- Auto-Discovery gathers information about neighbors adjacent to each discovered device. Auto-Discovery then discovers those neighbors and repeats the process. This sequence continues until the Default Tenant's boundaries are reached (identified by Auto-Discovery Rules' IP Address Ranges or Ordering numbers).

Note: NNMi never gathers Auto-Discovery *Hints* from IP addresses assigned to a Tenant other than the Default Tenant.

Before you start, have a clear idea of what you want to accomplish, see "[Example Uses of Auto-Discovery](#)" on page 251.

If you do not configure any Auto-Discovery Rules, Spiral Discovery only finds the configured Discovery Seeds (see "[Specify Discovery Seeds](#)" on page 287 for more information).

Note: When any Node is discovered because of an Auto-Discovery Rule, NNMi assigns that Node to the *Default Tenant* (and whichever Security Group attribute value is currently configured as Default Tenant's *Initial Discovery Security Group*). See ["Configure Tenants" on page 213](#) and ["About Security Groups" on page 582](#) for more information.

Auto-Discovery Rule Configuration Tasks

Task	How
"Configure Basic Settings for the Auto-Discovery Rule" on page 240	<p>Provide the basic requirements for an Auto-Discovery Rule configuration:</p> <ul style="list-style-type: none">• The name of the rule.• Specify the order in which Auto-Discovery applies this rule within the Default Tenant.• Specify how ICMP and SNMP protocols are used for this segment of discovery.• Designate whether devices identified by this rule are <i>Discovered</i> or <i>Rejected</i> during the Auto-Discovery process. <p>See "Auto-Discovery Rule Behavior Choices" below.</p>
Rule Criterion	<p>"IP Address Ranges for the Auto-Discovery Rule" on page 244</p> <p>Use IP addresses with wildcards to specify the area within Default Tenant that this Auto-Discovery Rule controls. You decide whether Ping Sweep is used for this segment of discovery.</p> <p>"SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248</p> <p>Use industry standard System Object IDs to control Auto-Discovery within the Default Tenant.</p> <p>Use the Configuration → Device Profiles view to see the list of all known system object IDs (MIBII sysObjectID) at the time NNMi released. This list of system object IDs is useful to expand or limit the range of devices that Auto-Discovery finds.</p>

Auto-Discovery Rule Behavior Choices

Auto-Discovery Rules control the extent of automatic discovery within the *Default Tenant*. Specify what Auto-Discovery should reject or find within your network environment by defining at least two Auto-Discovery Rules. You assign an Ordering number to each rule. For each discovered Node, Interface, or IP address, NNMi applies the first *matching* rule from lowest to highest Ordering number.

Tip: Give your Reject rule a lower Ordering number than the Include rule or rules to which it

applies.

Purpose = Reject Matching Nodes

Selections	Behavior
<input type="checkbox"/> Discover Matching Nodes <input type="checkbox"/> Discover Any SNMP Device <input type="checkbox"/> Discover Non-SNMP Devices	<p>Auto-Discovery rejects the following within Default Tenant (does not add any information to the NNMI database, does not query for information or Hints about neighboring devices):</p> <ul style="list-style-type: none"> • All addresses specified in the rule's IP Ranges table (if any) • All devices that meet the criteria specified in the rule's System Object ID Ranges table (if any) - based on RFC 1213, MIB-II sysObjectID values <p>Caution: If <i>both ranges are empty</i>, this rule would cause Auto-Discovery to never discover anything specified in all rules with higher Ordering numbers.</p>

The following table shows the choices for instructing Auto-Discovery to discover Nodes.

Note: Configure at least one Auto-Discovery Rule from the following table. And at least one Auto-Discovery Rule from the following table must specify the IP Address Range within which you want to use Auto-Discovery in Default Tenant.

Purpose = Discover Matching Nodes

Selections	Behavior
<input checked="" type="checkbox"/> Discover Matching Nodes <input type="checkbox"/> Discover Any SNMP Device <input type="checkbox"/> Discover Non-SNMP Devices	<p>Auto-Discovery finds the following <i>Routers and Switches</i> within Default Tenant:</p> <ul style="list-style-type: none"> • All must have IP addresses within the ranges specified in the rule's IP Ranges table (if any) • All must meet the criteria specified in the rule's System Object ID Ranges table (if any) - based on RFC 1213, MIB-II sysObjectID values
<input checked="" type="checkbox"/> Discover Matching Nodes <input checked="" type="checkbox"/> Discover Any SNMP Device <input type="checkbox"/> Discover Non-SNMP Devices	<p>Auto-Discovery finds the following devices within Default Tenant:</p> <ul style="list-style-type: none"> • All must have IP addresses within the ranges specified in the rule's IP Ranges table (if any) • Any that answer SNMP queries <i>and</i> meet the


Purpose = Discover Matching Nodes, continued



Selections	Behavior
	<p>criteria specified in the rule's System Object ID Ranges table (if any) - based on RFC 1213, MIB-II sysObjectID values</p>
<p><input checked="" type="checkbox"/> Discover Matching Nodes</p> <p><input checked="" type="checkbox"/> Discover Any SNMP Device</p> <p><input checked="" type="checkbox"/> Discover Non-SNMP Devices</p>	<p>Auto-Discovery finds the following devices within Default Tenant:</p> <ul style="list-style-type: none"> • All must have IP addresses within the ranges specified in the rule's IP Ranges table (if any) <div data-bbox="803 667 1369 856" style="background-color: #f0f0f0; padding: 10px; border: 1px solid #ccc;"> <p>Caution: NNMi ignores <input checked="" type="checkbox"/> <i>Discover Non-SNMP Devices</i> within a particular rule if any <i>System Object ID Ranges</i> are defined (because System Object IDs limit the rule to SNMP only).</p> </div> <ul style="list-style-type: none"> • Any that answer ICMP queries but not SNMP queries
<p><input checked="" type="checkbox"/> Discover Matching Nodes</p> <p><input type="checkbox"/> Discover Any SNMP Device</p> <p><input checked="" type="checkbox"/> Discover Non-SNMP Devices</p>	<p>Auto-Discovery finds the following devices within Default Tenant:</p> <ul style="list-style-type: none"> • All must have IP addresses within the ranges specified in the rule's IP Ranges table (if any) <div data-bbox="803 1182 1369 1371" style="background-color: #f0f0f0; padding: 10px; border: 1px solid #ccc;"> <p>Caution: NNMi ignores <input checked="" type="checkbox"/> <i>Discover Non-SNMP Devices</i> within a particular rule if any <i>System Object ID Ranges</i> are defined (because System Object IDs limit the rule to SNMP only).</p> </div> <ul style="list-style-type: none"> • Any devices that answer ICMP queries but not SNMP queries

Configure Basic Settings for the Auto-Discovery Rule



Default Tenant only: These Auto-Discovery Rule settings determine which methods Auto-Discovery applies when discovering nodes within your Default Tenant.

To configure this Auto-Discovery Rule for the Default Tenant:

1. Navigate to the **Auto-Discovery Rule** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.

- b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Locate the **Auto-Discovery Rules** tab.
 - e. Do one of the following:
 - To establish a rule, click the  New icon, and continue.
 - To edit a rule, double-click the row representing the configuration you want to edit, and continue.
 - To delete a rule, select a row, and click the  Delete icon.
2. Provide the required basic settings for this Auto-Discovery Rule (see the [Basics for this Auto-Discovery Rule](#) table).
3. Determine the Auto-Discovery Rule's behavior (see "[Auto-Discovery Rule Behavior Choices](#)" on page 238):
 - [Purpose of this Auto-Discovery Rule](#)
 - [Extend Default Behavior \(beyond Routers and Switches\)](#)
4. There are many ways to implement discovery. Before you start this step, see "[Example Uses of Auto-Discovery](#)" on page 251.

Configure one or more ranges, to identify the devices you want to discover or reject.

 - ["IP Address Ranges for the Auto-Discovery Rule" on page 244](#)
 - ["SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248](#)
5. Click  **Save and Close** to return to the **Discovery Configuration** form.
6. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#).
7. *Optional:* Open the **Discovery Configuration** workspace again and provide a discovery seed for each address range of this Auto-Discovery Rule. Core routers make the best Auto-Discovery seeds. See "[Specify Discovery Seeds](#)" on page 287.

Basics for this Auto-Discovery Rule

Task	How
Name	Give this Auto-Discovery Rule a meaningful name.
Ordering	Determine the order in which the Auto-Discovery Rules are applied. No duplicate Ordering numbers are permitted. Each Auto-Discovery Rule ordering number must be

Basics for this Auto-Discovery Rule, continued

Task	How
	<p>unique.</p> <p>Tip: Consider incrementing Ordering numbers by 10s or 100s to provide flexibility when adding new rules over time.</p> <p>IP address ranges: If a device falls within two Auto-Discovery Rules, the Auto-Discovery Rule with the lowest ordering number applies. For example, if an Auto-Discovery Rule includes certain IP addresses, then no other Auto-Discovery Rules with higher ordering numbers apply to those addresses.</p> <p>System Object ID ranges:</p> <ul style="list-style-type: none"> • If no IP address range is included in this Auto-Discovery Rule, then the system object ID settings take precedence over all Auto-Discovery Rules that have higher Ordering numbers than this Auto-Discovery Rule. • If an IP address range is included in this Auto-Discovery Rule, your system object ID range applies only within this Auto-Discovery Rule.
Notes	<p>Provide any additional useful information about this Auto-Discovery Rule.</p> <p>Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Purpose of this Auto-Discovery Rule

Task	How
Discover Matching Nodes	<p>If <input checked="" type="checkbox"/> enabled, Auto-Discovery gathers information about neighboring devices and adds devices to the NNMi database if those device meet the rule's criteria. For more information see "Which Nodes Are Discovered?" on page 195.</p> <p>Note: By default NNMi discovers routers and switches. You can expand the number of device types that NNMi discovers by enabling <input checked="" type="checkbox"/> Discover Any SNMP Device and including one or more System Object ID Ranges (based on MIB-II sysObjectID values). Your address ranges and system object ID ranges determine which discovered addresses are added to the NNMi database.</p> <p>If <input type="checkbox"/> disabled, Auto-Discovery rejects devices that match this rule unless:</p> <ul style="list-style-type: none"> • The device's address is a discovery seed. <p>See "Specify Discovery Seeds" on page 287 to learn how to establish discovery seeds.</p> <ul style="list-style-type: none"> • The device's address is reported as a neighbor to another discovered address.

Purpose of this Auto-Discovery Rule, continued

Task	How
	If you want to ensure that an address is never added to the NNMi database, see "Configure an Excluded IP Addresses Filter" on page 274 or "Configure an Excluded Interfaces Filter" on page 280 settings.

Extend Default Behavior (beyond Routers and Switches) for this Auto-Discovery Rule

Task	How
Discover Any SNMP Device	<p>Note: This attribute is ignored if Discover Matching Nodes is unchecked. However, if you configure any device as a discovery seed, discovery always adds that device to the database.</p> <p>If <input checked="" type="checkbox"/> enabled, Auto-Discovery gathers information about any device that responds to SNMP queries (in addition to routers or switches that are discovered by default). These nodes appear on maps and are monitored.</p> <p>If <input type="checkbox"/> disabled, Auto-Discovery rejects all device types except routers, switches, discovery seeds, and device types specified in your system object ID ranges. (Routers and switches are identified by the settings in the device profile.)</p>
Discover Non-SNMP Devices	<p>Note: This attribute is ignored if Discover Matching Nodes is unchecked. However, if you configure any device as a discovery seed, discovery always adds that device to the database.</p> <p>Non-SNMP devices are those that do not respond to SNMP queries.</p> <p>If you enable Discover Non-SNMP Devices, note the following:</p> <ul style="list-style-type: none"> • If you do not want NNMi to discover every node in your network, make sure your Auto-Discovery Rules correctly limit the scope of the discovery. See "Example Uses of Auto-Discovery" on page 251 for more information. • Selecting this option might cause you to reach your licensed capacity very quickly. See "Extend a Licensed Capacity" on page 1605. • If NNMi determines that a non-SNMP node has a hostname matching another non-SNMP node, NNMi merges the information to create only one node and includes any additional IP address information under the same node. <p>Non-SNMP nodes might be inaccurately represented under the following circumstances:</p> <ul style="list-style-type: none"> ■ One or more non-SNMP nodes in your network use the same hostname. ■ The same non-SNMP node has multiple hostnames.

Extend Default Behavior (beyond Routers and Switches) for this Auto-Discovery Rule, continued

Task	How
	<ul style="list-style-type: none">■ A non-SNMP node name changes (see "Delete Nodes" on page 1635). <p>If <input checked="" type="checkbox"/> enabled, Auto-Discovery adds to the database any addresses that do not respond to SNMP queries.</p> <div><p>Caution: NNMi ignores <input checked="" type="checkbox"/> <i>Discover Non-SNMP Devices</i> within a particular rule if any <i>System Object ID Ranges</i> are defined (because System Object IDs limit the rule to SNMP only).</p></div> <p>If <input type="checkbox"/> disabled, Auto-Discovery rejects any address that does not respond to SNMP queries.</p>

IP Address Ranges for the Auto-Discovery Rule

Default Tenant only: Auto-Discovery IP address ranges determine the outer limits for the area controlled by the current Auto-Discovery Rule. You can create multiple IP ranges within one Auto-Discovery Rule (order *within the rule* does not matter). Before you start, have a clear idea of what you want to accomplish, see ["Auto-Discovery Rule Behavior Choices" on page 238](#) and ["Example Uses of Auto-Discovery" on page 251](#).

If the Auto-Discovery Rule's **Discover Matching Nodes** ☐ is disabled, [click here for additional information](#).

- Auto-Discovery *does not gather neighbor information* from the addresses identified in any IP address range included in this rule. The addresses, themselves, might still show up in the topology database.

Note: Neighbor information is still gathered from IP addresses specifically identified in the [discovery seeds](#) configuration settings.

NNMi also uses the source IP address from SNMP traps as hints to discovery. NNMi uses those hint IP address only for initial discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication.




If the Auto-Discovery Rule's **Discover Matching Nodes** ☒ is enabled, [click here for additional information](#).

- At least one of your Auto-Discovery Rules must have an IP address range designated as an **Include in rule** range type. Auto-Discovery *gathers neighbor information* from those addresses to extend discovery.

- *Optional.* You can configure NNMi to ignore subsets of those IP addresses (an **Ignored by rule** range, which means that those addresses are available for other Auto-Discovery Rules with higher Ordering numbers).
- *Optional.* Specify system object ID (MIB-II sysObjectID) ranges to be included or ignored. This technique constricts or extends the types of devices affected by this rule. See ["SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248](#) for more information.

NNMi discovers any devices that comply with your rule configurations, and creates a record of each device in the NNMi database. If the device supports SNMP, all addresses for that device are combined into one Node object. If the device does not support SNMP, NNMi queries DNS to determine the hostname. If this hostname matches another non-SNMP node, NNMi merges the information to create only one node with multiple associated addresses.

To specify an Auto-Discovery Rule IP address range for Default Tenant:

1. Navigate to the **Auto-Discovery** form.
 - a. In the **Workspace** navigation panel, open the  **Configuration** workspace.
 - b. Select **Discovery Configuration**.
 - c. Select the **Auto-Discovery Rule** tab, and do one of the following:
 - To establish an Auto-Discovery Rule, click the  **New** icon.
 - To edit an Auto-Discovery Rule, click the  **Open** icon in the row representing the configuration you want to edit.
2. Provide the Basic Settings, see ["Configure Basic Settings for the Auto-Discovery Rule" on page 240](#).
3. Navigate to the **IP Ranges** tab.
4. *Optional.* Decide if you want to use Ping Sweep in this segment of network discovery.

IPv4 addresses only: In Wide Area Networks (WANs) such as ATM, Frame Relay, and Point-to-Point (where ARP cache is not available), the Ping Sweep locates nodes for Auto-Discovery to use when gathering neighbor information and evaluating connections between Nodes.

Note: Ping Sweep works only with IPv4 addresses and only in 16-bit subnets. All nodes discovered using Auto-Discovery are assigned to the *Default Tenant*.

- **Enable Ping Sweep** ☒
Auto-Discovery can issue a wide range of ICMP ping commands. For details, see ["Ping Sweep for Auto-Discovery in Default Tenant" on page 285](#). NNMi only uses Ping Sweep




across a maximum of the last two octets (/16) of the network specified by each IPv4 IP address range.

If things do not work as expected, check whether Ping Sweep is disabled. See ["Configure Ping Sweep \(override for all Auto-Discovery Rules\)" on page 222](#). Also verify that ICMP communication is enabled, see ["Communication Region Form" on page 150](#) and ["Specific Node Settings Form \(Communication Settings\)" on page 171](#).

- **Enable Ping Sweep** ☐


Auto-Discovery depends on Discovery Seeds as starting points. For details, see ["Discovery Seeds for Auto-Discovery in Default Tenant" on page 283](#) for important information.


5. *Optional.* To provide an IP address range for this Auto-Discovery Rule, do one of the following:

- To create an IP range, click the  New icon, and continue.
- To edit an IP range, click the  Open icon in the row representing the configuration you want to edit, and continue.
- To delete an IP range, select a row, and click the  Delete icon.

6. Define one or more IP address ranges for this Auto-Discovery Rule, the order of ranges defined *within this rule* does not matter (see [table](#)).

7. Click  **Save and Close** to return to the **Auto-Discovery Rule** form.

8. Click  **Save and Close** to return to the **Discovery Configuration** form.

9. Click  **Save and Close**. If you enabled Ping Sweep for this Auto-Discovery Rule, NNMi issues the Ping Sweep when you click Save and Close. Otherwise, Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#).

Discovery IP Range Form

Name	Description
IP Range	<p>Note: If you enter an IP address value that represents only one IP address, Auto-Discovery gathers neighbor information only from the address you enter. (Discovery extends only one hop out from this address.)</p> <p>To specify a range of IP addresses for this Auto-Discovery Rule, use one of the following. Pick one address notation style. Combinations of wildcards and CIDR notation are not permitted within one address range. You can provide multiple address range settings:</p> <ul style="list-style-type: none">• IPv4 address wildcard notation. <p>An IPv4 Address range is a modified dotted-notation where each octet is one of the</p>

Discovery IP Range Form, continued

Name	Description										
	<p>following:</p> <ul style="list-style-type: none">■ A specific octet value between 0 and 255■ A low-high range specification for the octet value (for example, "112-119")■ An asterisk (*) wildcard character, which is equivalent to the range expression "0-255" <p>Note: The following two IPv4 addresses are considered invalid: 0.0.0.0 and 127.0.0.0</p> <p>Examples of valid IPv4 address wildcards include:</p> <p>10.1.1.* 10.*.*.* 10.1.1.1-99 10.10.50-55.* 10.22.*.4 10.1-9.1-9.1-9</p> <ul style="list-style-type: none">• IPv4 Classless Inter-Domain Routing (CIDR) notation. The CIDR notation specifies the number of consecutive bits in the IPv4 address that must match. For example, 10.2.120.0/21 <p>Note: NNMi does not support CIDR subnet mask notation such as, 10.2.120.0/255.255.248.0</p> <table><tr><th>Example IPv4 Prefix Length Values</th><th>Number of Usable IPv4 Addresses</th></tr><tr><td>28</td><td>14 (16-2=14)*</td></tr><tr><td>29</td><td>6 (8-2=6)*</td></tr><tr><td>30</td><td>2 (4-2=2)*</td></tr><tr><td>31</td><td>2</td></tr></table> <p>* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.</p> <ul style="list-style-type: none">• IPv6 address wildcard notation (<i>NNMi Advanced</i>) Separate each 16-bit value of the IPv6 address with a colon. The 16-bit value can be any of the following:	Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses	28	14 (16-2=14)*	29	6 (8-2=6)*	30	2 (4-2=2)*	31	2
Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses										
28	14 (16-2=14)*										
29	6 (8-2=6)*										
30	2 (4-2=2)*										
31	2										

Discovery IP Range Form, continued

Name	Description
	<ul style="list-style-type: none"> ■ A specific hexadecimal value between 0 and FFFF (case insensitive). ■ A low-high range specification of the hexadecimal value (for example, 1-1fe). ■ An asterisk (*) wildcard character (equivalent to the range expression 0-ffff). <p>Note: The standard IPv6 short-hand notation (:) is allowed to express one or more 16-bit elements of zero (0) values. However, the mixed IPv6/IPv4 dot-notation (for example, 2001:d88::1.2.3.4) is not permitted as an IPv6 address range.</p> <p>Valid examples of ranges in modified IPv6 address notation include the following:</p> <pre>2001:D88:0:A00-AFF::*:*:* 2001:D88:1::*:*:*:* 2001:D88:2:0:a07:ffff:0a01:3200-37ff</pre> <ul style="list-style-type: none"> ● IPv6 Classless Inter-Domain Routing (CIDR) notation (<i>NNMi Advanced</i>) The CIDR notation specifies the number of consecutive bits in the IPv6 address that must match. <pre>2001:d88:a00::/44 (equivalent to modified IPv6 address notation 2001:d88:a00-a0f::*:*:*:*)</pre> <p>For example, valid IPv6 address ranges in CIDR notation include the following:</p> <pre>2001:d88:0:a00::/56 (equivalent to modified IPv6 address notation 2001:D88:0:A00-AFF::*:*:*:*)</pre> <pre>2001:d88:1::/48 (equivalent to modified IPv6 address notation 2001:D88:1::*:*:*:*:*)</pre>
Range Type	<p>Include in rule - The current Auto-Discovery Rule's settings apply to the addresses in this range.</p> <p>Ignored by rule - The current Auto-Discovery Rule's settings do not apply to the addresses in this range. Use the Ignored by rule setting to identify a subset of addresses within a larger range. The addresses in the ignored range are available to conform to an Auto-Discovery Rule with a higher ordering number.</p>

SNMP System Object ID Ranges for the Auto-Discovery Rule

Vendors are assigned a system object ID number (RFC 1213 MIB-II sysObjectID) for each network device they manufacture. This system object ID number is unique for each combination of

vendor, device type, and model number (vendor/make/model). For example, all Cisco 6509 routers have the same system object ID.

Tip: See ["Configure Device Profiles" on page 323](#) for more information about system object IDs. In the **Configuration > Device Profiles** view, you can quickly and easily locate the system object IDs of devices in your network environment.

Default Tenant only: System object ID ranges are powerful tools for limiting this Auto-Discovery Rule's behavior. For example, limit this rule by excluding specific models of routers and switches. Before you start, have a clear idea of what you want to accomplish, see ["Example Uses of Auto-Discovery" on page 251](#).

When using system object ID ranges for this Auto-Discovery Rule, note the following:


- The rule applies only to the Default Tenant.
- If no IP Address Ranges are defined within this Auto-Discovery Rule, your System Object ID Ranges affect *all* Auto-Discovery Rules that have higher Ordering numbers than this Auto-Discovery Rule.
- If one or more IP Address Ranges are defined within this Auto-Discovery Rule, your System Object ID Ranges affect *only* the current Auto-Discovery Rule.


The following table includes examples of how you might want to expand or limit Auto-Discovery within the Default Tenant using System Object ID Ranges.


Controlling Auto-Discovery within the Default Tenant using System Object ID Ranges







Task	Related Topics
Exclude certain vendor/make/models of Routers and Switches from Auto-Discovery.	See the Auto-Discovery Rule = Included information in "Only Routers and Switches Discovered" on page 255 topics.
Expand Auto-Discovery to include device types in addition to routers and switches.	See the Auto-Discovery Rule = Included information in "Only Specific Vendor/Make/Models Discovered" on page 258 topics.
Exclude one or more specific device types from all Auto-Discovery rules.	See the Auto-Discovery Rule = Rejects information in "Strategies to Exclude Certain Nodes from Auto-Discovery" on page 262 .

To specify a system object ID range:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Discovery System Object ID Range** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.

- c. Select **Discovery Configuration**.
- d. Select the **Auto-Discovery Rule** tab.
- e. Do one of the following:
 - To create an Auto-Discovery Rule, click the  New icon.
 - To edit an Auto-Discovery Rule, double-click the row representing the configuration you want to edit.
- f. In the **Auto-Discovery Rule** form, verify the following:
 - Required settings are provided (red *).
 - Other desired choices are made.

Caution: NNMi ignores  *Discover Non-SNMP Devices* within a particular rule if any *System Object ID Ranges* are defined (because System Object IDs limit the rule to SNMP only).

- g. Select the **System Object ID Ranges** tab.
- h. Do one of the following:
 - To create a system object ID range, click the  New icon, and continue.
 - To edit a system object ID range, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete a system object ID range, click the  Delete icon.
3. Provide one or more System Object ID ranges for this Auto-Discovery Rule, the order of ranges defined *within this rule* does not matter (see the [table](#)).
4. Click  **Save and Close** to return to the **Auto-Discovery Rule** form.
5. *Optional.* Provide IP Address Ranges to limit the scope of this Auto-Discovery Rule (see "[IP Address Ranges for the Auto-Discovery Rule](#)" on page 244).
6. Click  **Save and Close** to return to the **Discovery Configuration** form.
7. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#).

Discovery System Object ID Range Definition

Attribute	Description
System Object ID Prefix	<p>Enter a prefix of an SNMP system object ID, or enter the entire SNMP system object ID. A partial entry becomes a wildcard.</p> <p>For example, if you enter 1.3.6.1.4.1.11, discovery finds all HP devices. If you enter 1.3.6.1.4.1.9, discovery finds all Cisco devices.</p> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p>
Range Type	<p>Include in rule - Instructs Auto-Discovery to discover devices matching this system object ID range.</p> <p>Ignored by rule - Instructs Auto-Discovery to ignore devices matching this system object ID range. The sysObjectIDs in the ignored range are available to conform to an Auto-Discovery Rule with a higher ordering number.</p>
Notes	<p>Add any information about this rule that would be useful to you and your team.</p> <p>Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Example Uses of Auto-Discovery

Review the following examples to learn how to use Auto-Discovery Rules within the Default Tenant:

Set Outside Limits for Auto-Discovery	251
Only Routers and Switches Discovered	255
Only Routers' Physical Interfaces Discovered	257
Only Specific Vendor/Make/Models Discovered	258
All SNMP Devices Discovered	260
Everything Discovered	261
Strategies to Exclude Certain Nodes from Auto-Discovery	262
Limit Sources of Neighbor Information	263

Set Outside Limits for Auto-Discovery

Default Tenant only: Best practice is to create a pair of Auto-Discovery Rules with carefully chosen Ordering numbers to clearly identify the entire group of IP addresses within your network

management domain and the devices you care about. You can add, remove, or change the settings in this pair of Auto-Discovery Rules at any time.

Define a pair of Auto-Discovery rules as described in the following table. For ideas about how to use this pair of rules:

Configure Outside Limits for Auto-Discovery

Task	How
<p>Auto-Discovery Rule = Included: Create an Auto-Discovery Rule that specifies one or more IP address ranges to identify the outer limits of your management domain. It is recommended that you use your second-lowest Ordering number. This ensures that Auto-Discovery never uses addresses outside the specified range or ranges as discovery Hints.</p>	<p>Use the following settings</p> <ol style="list-style-type: none"> NameIncluded-IP-Ranges (for example) Ordering <input type="text" value="200"/> Specify the techniques Auto-Discovery uses for finding devices: <ul style="list-style-type: none"> ■ Discover Matching Nodes <input checked="" type="checkbox"/> <div style="border: 1px solid #ccc; padding: 5px; margin: 10px 0;"> <p>Tip: With this setting, Auto-Discovery finds only routers and switches.</p> </div> <ul style="list-style-type: none"> ■ Discover Any SNMP Device <input type="checkbox"/> or <input checked="" type="checkbox"/> <p>This setting expands Auto-Discovery to include any device that answers an SNMP query.</p> <ul style="list-style-type: none"> ■ Discover Non-SNMP Devices <input type="checkbox"/> or <input checked="" type="checkbox"/> <p><i>Optional:</i> If enabled, Auto-Discovery uses other protocols to detect devices. For details, see "How Spiral Discovery Works" on page 195 and "What Information Is Collected?" on page 196.</p> <div style="border: 1px solid #ccc; padding: 5px; margin: 10px 0;"> <p>Caution: NNMi ignores <input checked="" type="checkbox"/> Discover Non-SNMP Devices within a particular rule if any <i>System Object ID Ranges</i> are defined (because System Object IDs limit the rule to SNMP only).</p> </div> Create any number of ranges to specify the

Configure Outside Limits for Auto-Discovery, continued

Task	How
	<p>area within Default Tenant that this Auto-Discovery Rule controls:</p> <p>IP Range <input type="text" value="< IPv4 / IPv6 range >"/> (Minimum: One is required in one of your Auto-Discovery Rules.)</p> <p>Range Type <input type="text" value="Include in rule"/> ▼</p> <p>5. <i>Optional:</i> If you want to limit Auto-Discovery to only certain vendor/make/models, create one or more System Object ID Ranges.</p> <div data-bbox="889 741 1370 1020" style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Caution: If you use this setting, NNMi ignores all other devices. If it would be easier to reject a small list of System Object IDs (rather than list all the ones you want NNMi to discover), skip this step and see the <i>Auto-Discovery Rule = Rejects</i> configuration.</p> </div> <div data-bbox="889 1056 1370 1266" style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> </div> <p>SyObjID Range <input type="text" value="< sysObjectID >"/></p> <p>Range Type <input type="text" value="Include in rule"/> ▼</p> <p>For more information, see "SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248.</p>
<p>Auto-Discovery Rule = Rejects: Create a second Auto-Discovery Rule that uses IP Address Ranges, System Object ID Ranges, or both to instruct NNMi to reject a subset of the criterion defined in the Auto-Discovery Rule = Included configuration.</p>	<p>Use the following settings (* = required setting):</p> <ol style="list-style-type: none"> Name Rejected-IPs-sysObjectIDs (for example) Ordering <input type="text" value="100"/> Disable all the following settings to instruct Auto-Discovery to gather data about the Ranges identified in the following steps,

Configure Outside Limits for Auto-Discovery, continued

Task	How
	<p>but then reject that data (do not add it to the NNMi database nor gather Discovery Hints from within the range).</p> <ul style="list-style-type: none"> ■ * Discover Matching Nodes <input type="checkbox"/> ■ * Discover Any SNMP Device <input type="checkbox"/> ■ * Discover Non-SNMP Devices <input type="checkbox"/> <p>4. <i>Optional:</i> Create any number of:</p> <p>IP Range <input type="text" value="< IPv4 / IPv6 range >"/></p> <p>* Range Type <input type="text" value="Ignored by rule"/> <input type="button" value="v"/></p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: These settings instruct Auto-Discovery to not add the specified IP addresses to the NNMi database, not acknowledge any Hints received about them, nor gather Discovery Hints from them unless the address is a discovery seed. See "Specify Discovery Seeds" on page 287 to learn how to establish discovery seeds.</p> <p>If you want to prevent Auto-Discovery from generating <i>any</i> requests for data to certain addresses, see "Configuring Communication Protocol" on page 129.</p> </div> <p>5. <i>Optional:</i> If you want to limit Auto-Discovery to only certain vendor/make/models, create System Object ID Ranges. Once you create a System Object ID Range here, Auto-Discovery rejects any devices that meet this criteria.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: If it would be easier to specify a small list of System Object IDs that should be included (rather than list all the ones you do not want</p> </div>

Configure Outside Limits for Auto-Discovery, continued

Task	How
	<p>Auto-Discovery to find), skip this step and see the Auto-Discovery Rule = Included configuration instructions.</p> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> <p>System Object ID Prefix <input type="text" value="< sysObjectID >"/></p> <p>Range Type <input type="text" value="Include in rule"/> ▼</p> <p>For more information, see "SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248.</p>
You can create additional rules for fine tuning Auto-Discovery behavior.	<p>Note: The pair of rules (Auto-Discovery Rule = Included and Auto-Discovery Rule = Rejects) can potentially cover all requirements.</p> <p>Carefully choose the Ordering Number for any additional Auto-Discovery Rule.</p> <p>Auto-Discovery Rules affect all rules with a higher ordering number.</p>

Only Routers and Switches Discovered

Default Tenant only: If you want Auto-Discovery to automatically find only routers and switches within Default Tenant, use these guidelines.

Note: After you set your configuration according to these guidelines, when a new router or switch is added to your network, you do not need to do anything. NNMi discovers it during the next discovery cycle.

Follow the instructions in "[Set Outside Limits for Auto-Discovery](#)" on page 251 and use the following choices in the appropriate steps:

Only Routers and Switches Discovered

Task	How
Auto-Discovery Rule = Included	<ul style="list-style-type: none"> Discover Matching Nodes <input checked="" type="checkbox"/> Discover Any SNMP Device <input type="checkbox"/> Discover Non-SNMP Devices <input type="checkbox"/> <p>If you want Auto-Discovery to find all routers and switches. Do not create any System Object ID Ranges.</p> <p><i>Optional:</i> If you want to limit Auto-Discovery to only the vendor/make/models of routers and switches that you specify, do the easiest one of the following (for more information see "SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248):</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> </div> <ul style="list-style-type: none"> Create one or more System Object ID Ranges. Your list <i>must include everything</i> you want Auto-Discovery to find. Do nothing here but make changes to the System Object ID Ranges in the <i>Auto-Discovery Rule = Rejects</i> configuration. Use a combination such as: <p><i>Auto-Discovery Rule = Included</i> configuration: Included = 1.3.6.1.4.1.11 (HP)</p> <p><i>Auto-Discovery Rule = Rejects</i> configuration: 1.3.6.1.4.1.11.2.3.7.1.10 (hpnetSwitch200) 1.3.6.1.4.1.11.2.3.7.2.2 (hpicfRouterTR)</p>
Auto-Discovery Rule = Rejects	<p><i>Optional:</i> Create one or more System Object ID Ranges that identify the vendor/make/models of routers and switches you do not want Auto-Discovery to find.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> </div> <p>For example, hpnetSwitch200 and hpicfRouterTR:</p> <ul style="list-style-type: none"> System Object ID Prefix 1.3.6.1.4.1.11.2.3.7.1.10 Range Type <input type="text" value="Include in rule"/> System Object ID Prefix 1.3.6.1.4.1.11.2.3.7.2.2 Range Type <input type="text" value="Include in rule"/>

For additional Auto-Discovery ideas:

Only Routers' Physical Interfaces Discovered

Default Tenant only: If you have routers in your network domain that contain a large number of physical and virtual interfaces, you may want Auto-Discovery to only find and monitor the important interfaces.

Follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and use the following choices in the appropriate steps:

Only Routers' Physical Interfaces Discovered

Task	How
Auto-Discovery Rule = Included	<div>Discover Matching Nodes <input checked="" type="checkbox"/></div> <div>Create one or more IP Ranges settings that identify the location of routers in your network domain (specify the area within Default Tenant that this Auto-Discovery Rule controls):</div>
Auto-Discovery Rule = Rejects	<div>Enter IP Range <input type="text" value="< IPv4 / IPv6 range>"/> (Minimum: One is required in one of your Auto-Discovery Rules.)</div> <div>Set Range Type <input type="text" value="Include in rule"/> <input type="button" value="v"/></div>

Spiral Discovery: For Routers that are in any Tenant:

If routers in your network have more than 2048 physical interfaces plus virtual interfaces, and you want Spiral Discovery to gather data about only a subset of those interfaces, create a *pair* of filters as follows:


- ["Configure an Included Interface Ranges Filter" on page 277](#) (each entry based on one MIB-II sysObjectID and a range of ifIndex values)
- ["Configure an Excluded Interfaces Filter" on page 280](#) (each entry based on a defined Interface Group)

For example, the following *pair* of filters could instruct Spiral Discovery to gather information about an ifIndex range representing the physical Nortel interfaces within that network environment, then reject any virtual interfaces that are an exception to that assumption:

- Included Interface Range defined as sysObjectID = Nortel and ifIndex = 1-256

System Object ID Prefix	Low ifIndex Value	High ifIndex Value	Notes
1.3.6.1.4.1.2505.	1	256	Nortel Routers

Only Routers' Physical Interfaces Discovered, continued

Task	How
<ul style="list-style-type: none"> Excluded Interfaces filter that instructs Spiral Discovery to ignore any exceptions to the assumption of the Included Interface Range defined in the Auto-Discovery Rule = Included configuration. Define an Interface Group that identifies Nortel devices' Virtual Interfaces: 	<p>Tip: The selected Interface Group will be empty after the next Spiral Discovery cycle. Consider disabling the Interface Group definition's Add to View Filter List <input type="checkbox"/> attribute to prevent this empty Interface Group from appearing on selection lists within NNMi views.</p> 

For additional Auto-Discovery ideas:

Only Specific Vendor/Make/Models Discovered

Default Tenant only: If you want Auto-Discovery to find only devices within Default Tenant that were manufactured by a specific vendor, you must use SNMP sysObjectID values. Navigate to the **Configuration** workspace, and select the **Device Profiles** view to see all known system object IDs at the time NNMi released. You can add a Device Profile if the one you need is not yet configured.

For example: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard:

- To include all HP devices, use the following prefix in configuration settings for the pair of Auto-Discovery Rules:
1.3.6.1.4.1.11 (prefix for all HP devices)
- To specify certain HP devices, use the appropriate numbers, such as:
1.3.6.1.4.1.11.2.3.7.1.10 = hpnetSwitch200
1.3.6.1.4.1.11.2.3.7.2.2 = hpicfRouterTR

Note: After you set your configuration according to these guidelines, when a new HP device is added to your network, you do not need to do anything. NNMi discovers it during the next discovery cycle if it matches the criteria you define.

Follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and use the following choices in the appropriate steps:

Only Specific Vendor/Make/Models Discovered

Task	How
Auto-Discovery Rule = Included	<ul style="list-style-type: none"> • Discover Matching Nodes <input checked="" type="checkbox"/> • Discover Any SNMP Device <input checked="" type="checkbox"/> • Discover Non-SNMP Devices <input type="checkbox"/> <p><i>Optional:</i> If you want to limit Auto-Discovery to only the vendor/make/models that you specify, do the easiest one of the following (for more information see "SNMP System Object ID Ranges for the Auto-Discovery Rule" on page 248):</p> <div style="border: 1px solid #ccc; padding: 5px; margin: 10px 0;"> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> </div> <ul style="list-style-type: none"> • Create one or more System Object ID Ranges. Your list <i>must include everything</i> you want Auto-Discovery to find. • Do nothing here but make changes to the System Object ID Ranges in the <i>Auto-Discovery Rule = Rejects</i> configuration. • Use a combination such as: <p><i>Auto-Discovery Rule = Included</i> configuration: Included = 1.3.6.1.4.1.11 (HP)</p> <p><i>Auto-Discovery Rule = Rejects</i> configuration: 1.3.6.1.4.1.11.2.3.7.1.10 (hpnetSwitch200) 1.3.6.1.4.1.11.2.3.7.2.2 (hpicfRouterTR)</p>
Auto-Discovery Rule = Rejects	<p><i>Optional:</i> Create one or more System Object ID Ranges that identify the vendor/make/models that you do not want Auto-Discovery to find.</p> <div style="border: 1px solid #ccc; padding: 5px; margin: 10px 0;"> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character. A partial entry becomes a wildcard.</p> </div> <p>For example, hpnetSwitch200 and hpicfRouterTR:</p> <p>System Object ID Prefix 1.3.6.1.4.1.11.2.3.7.1.10</p> <p>Range Type <input type="text" value="Include in rule"/> <input type="button" value="v"/></p>

Only Specific Vendor/Make/Models Discovered, continued

Task	How
	System Object ID Prefix 1.3.6.1.4.1.11.2.3.7.2.2 Range Type <input type="text" value="Include in rule"/>

For additional Auto-Discovery ideas:

All SNMP Devices Discovered

Default Tenant only: If you want Auto-Discovery to automatically find all devices that respond to SNMP within Default Tenant, use these guidelines.

Note: This strategy might cause you to reach your licensed capacity very quickly. See ["Extend a Licensed Capacity" on page 1605](#).

After you set your configuration according to these guidelines, when a new device is added to your network, you do not need to do anything. NNMi discovers it during the next discovery cycle if the device responds to SNMP queries.

Follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and use the following choices in the appropriate steps:

All SNMP Devices Discovered

Task	How
Auto-Discovery Rule = Included	<ul style="list-style-type: none"> • Discover Matching Nodes <input checked="" type="checkbox"/> • Discover Any SNMP Device <input checked="" type="checkbox"/> • Discover Non-SNMP Devices <input type="checkbox"/> <p>Create one or more:</p> <p>IP Range <input type="text" value="< IPv4 / IPv6 range >"/> (Minimum: One is required in one of your Auto-Discovery Rules.)</p> <p>Range Type <input type="text" value="Include in rule"/></p> <p>If you want Auto-Discovery to find all SNMP devices, do not create any System Object ID Ranges.</p>
Auto-Discovery Rule = Rejects	

For additional Auto-Discovery ideas:

Everything Discovered

Default Tenant only: If you want Auto-Discovery to automatically find all devices within Default Tenant, use these guidelines.

If the device does not support SNMP, NNMi queries DNS to determine the hostname. If this hostname matches another non-SNMP node, NNMi merges the information to create only one node with multiple associated addresses to preserve licensed capacity limits for discovered nodes. This is why the ["Well-Configured DNS Prerequisite" on page 208](#) is very important.

Note: This strategy might cause you to reach your licensed capacity very quickly. See ["Extend a Licensed Capacity" on page 1605](#).

After you set your configuration according to these guidelines, when a new device is added to your network, you do not need to do anything. NNMi discovers it during the next discovery cycle.

Follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and use the following choices in the appropriate steps:

All SNMP Devices Discovered

Task	How
Auto-Discovery Rule = Included	<ul style="list-style-type: none"> Discover Matching Nodes <input checked="" type="checkbox"/> Discover Any SNMP Device <input checked="" type="checkbox"/> Discover Non-SNMP Devices <input checked="" type="checkbox"/> <p>Create one or more:</p> <p>IP Range <input type="text" value="< IPv4 / IPv6 range >"/> (Minimum: One is required in one of your Auto-Discovery Rules.)</p> <p>Range Type <input type="text" value="Include in rule"/> <input type="button" value="v"/></p> <div> <p>Caution: NNMi ignores <input checked="" type="checkbox"/> <i>Discover Non-SNMP Devices</i> within a particular rule if any <i>System Object ID Ranges</i> are defined (because System Object IDs limit the rule to SNMP only).</p> </div>
Auto-Discovery Rule = Rejects	

For additional Auto-Discovery ideas:

Strategies to Exclude Certain Nodes from Auto-Discovery

Default Tenant only: Sometimes it is useful to exclude certain nodes from Auto-Discovery and Monitoring. For example:

- All of your printers
- Certain problem devices

Techniques to exclude nodes include the following:

1. Follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and in the appropriate steps, use any of the following choices required to clearly identify the Nodes that Auto-Discovery should exclude:
 - a. Set up your **Auto-Discovery Rule = Included** IP Ranges without specifying any addresses from the problem nodes.
 - b. Set up your **Auto-Discovery Rule = Rejects** settings to ignore information received about the problem nodes using either or both of the following:

Caution: These settings instruct Auto-Discovery to not add the specified IP addresses or devices with a specified MIB-II `sysObjectID` to the NNMi database, not acknowledge any Hints received about them, nor gather Discovery Hints from them unless the address is a discovery seed. See ["Specify Discovery Seeds" on page 287](#) to learn how to establish discovery seeds.

If you want this behavior for Spiral Discovery in all Tenants, see ["Configure an Excluded IP Addresses Filter" on page 274](#).

- Create any number of:

IP Range
Range Type ▼

- Create any number of:

System Object ID Range
Range Type ▼

System Object ID Ranges enable you to identify the vendor/make/model of the devices that you do not want Auto-Discovery to find. For more information, see ["Only Specific Vendor/Make/Models Discovered" on page 258](#).

For additional Auto-Discovery ideas:


2. If you want to prevent NNMi from generating *any* network traffic to certain Nodes, see ["Configuring Communication Protocol" on page 129](#). Configure NNMi to never attempt any SNMP or ICMP communication with those Nodes.

For strategies to prevent specific devices from being discovered:

Limit Sources of Neighbor Information

Default Tenant only: If you want Auto-Discovery to *never use* a particular IP address as a source for gathering additional information (using SNMP, ICMP, ARP cache, DNS, and a variety of other protocols), follow the instructions in ["Set Outside Limits for Auto-Discovery" on page 251](#) and use the following choices in the appropriate steps:

Limit Auto-Discovery Hints

Task	How
Auto-Discovery Rule = Included	
Auto-Discovery Rule = Rejects	<p>Create one or more IP Ranges settings that clearly identify the addresses. Auto-Discovery does not gather any Hints for further discovery from these addresses:</p> <p>Enter IP Range <input type="text" value="< IPv4 / IPv6 range >"/></p> <p>Set Range Type <input type="text" value="Include in rule"/> </p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: Because the Auto-Discovery Rule = Reject's setting is Discover Matching Nodes <input type="checkbox"/> disabled, Auto-Discovery <i>does not gather neighbor information</i> from the addresses identified in any IP address range included in this rule. The addresses, themselves, might still show up in the topology database because of the following:</p> <ul style="list-style-type: none"> • Neighbor information is still gathered from IP addresses specifically identified in the discovery seeds configuration settings. • NNMi also uses the source IP address from SNMP traps as hints to discovery. NNMi uses those hint IP address only for initial discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication. </div> <p>NNMi never gathers Auto-Discovery <i>Hints</i> from IP addresses assigned to a Tenant other than the Default Tenant.</p>

Limit Auto-Discovery Hints, continued

Task	How
	Caution: If you want to prevent NNMi from generating <i>any</i> network traffic to certain Nodes, see "Configuring Communication Protocol" on page 129 .
Spiral Discovery: For devices in Tenants other than Default Tenant:	"Configure an Excluded IP Addresses Filter" on page 274 (based on IP address ranges) "Configure an Excluded Interfaces Filter" on page 280 (based on defined Interface Groups) "Configure an Included Interface Ranges Filter" on page 277 (based on one or more SNMP sysObjectID and ifIndex range values)

The IP addresses in the following table cannot be used as Discovery Seeds or Auto-Discovery Hints. NNMi still Discovers and Monitors these addresses within the context of a Node, but NNMi does not gather information about neighbors from these addresses.

Invalid IP Addresses for Discovery Seeds or Auto-Discovery Hints

IPv4 Address Range	IPv6 Address Range	Explanation
0.*.*.*	not applicable	Reserved IP addresses
0.0.0.0	::0	Any Local (listen) address
127.*.*.*	::1	Loopback addresses
not applicable	fe80::*:*:*:*	IPv6 link-local address ¹
224-239.*.*.*	not allowed (ff00:: to ffff:ffff:ffff:ffff:ffff:ffff:ffff:ffff)	multicast address ²
255.255.255.255	not applicable	Broadcast address

For additional Auto-Discovery ideas:

For strategies to prevent specific devices from being discovered:

¹A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

²Used to identify a group of hosts joined into a group. IPv4 multicast addresses are in the range 224.0.0.0 to 239.255.255.255 and IPv6 multicast addresses have the prefix ff00::/8.

Configure IPv4 Subnet Connection Rules

NNMi uses Subnet Connection Rules to detect connections between interfaces associated with IPv4 addresses that *do not respond* to Layer 2 *discovery protocols* (see the list of Topology Source protocols in [Layer 2 Connection Form](#)). Subnet Connection Rules take priority over the Layer 2 discovery protocol results. For special cases, you can override a Subnet Connection Rule by using the Connection Editor command line tool, see [nnmconnect.ovpl](#) for more information.

NNMi provides a variety of predefined Subnet Connection Rules. For ideas, see "[Subnet Connection Rules Provided by NNMi](#)" on page 267.



Subnet Connection Rules are ideal for multiple situations. For additional details and examples of how Subnet Connection Rules work, see "[Consider IPv4 Subnet Connection Rules](#)" on page 200.

When Spiral Discovery detects a subnet, NNMi uses the matching Subnet Connection Rule to request information about all possible IPv4 addresses (potentially detecting previously undiscovered IPv4 addresses). NNMi checks the Excluded IP Addresses list. Any addresses in the list are dropped (for details, see "[Configure an Excluded IP Addresses Filter](#)" on page 274). Then NNMi creates connections among any interfaces associated with any newly discovered IPv4 addresses.




If important subnets in your network environment are not automatically connected by Spiral Discovery, edit a Subnet Connection Rule or create your own.

If you configure a Subnet Connection Rule, the rule independently applies to each Tenant. The members of Subnets must be unique Tenant/Node pairs (each Node assigned to only one Tenant). A Subnet Connection Rule can establish a link between the Default Tenant and another Tenant. However, links between two Tenants are not permitted *unless one of them is the Default Tenant*. See "[Configure Tenants](#)" on page 213.

To configure Subnet Connection Rules:

1. Complete all prerequisites. See "[Prerequisites for Discovery](#)" on page 207, .
2. [Navigate to the Subnet Connection Rule form](#).
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Subnet Connection Rules** tab.
 - e. Do one of the following:
 - To establish a rule, click the  New icon, and continue.
 - To edit a rule, double-click the row representing the configuration you want to edit, and

continue.

- To delete a rule, select a row, and click the  Delete icon.
- 3. Provide the required basic settings (see [Basics table](#)).
- 4. Provide the Subnet Connection behavior settings for this rule (see [Details table](#)).
- 5. Click  **Save and Close** to return to the **Discovery Configuration** form.
- 6. Click  **Save and Close** to apply the configuration. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). If more than two nodes are connected using this rule, NNMi uses the following icon to indicate this special connection on maps (see example in "[Consider IPv4 Subnet Connection Rules](#)" on page 200):

 icon (in prior NNMi releases the  icon)

If you double-click the icon, the [Layer 2 Connection Form](#) displays and the **Topology Source** value is SUBNETCONNECTION.

Basics for this Subnet Connection Rule

Task	How
Name	<p>Type a meaningful name for this Subnet Connection Rule. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No spaces are permitted.</p> <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Note: This name is prepended to the Layer 2 connection name (when you request Tool Tips information about the connection on the Layer 2 Neighbor View map). If a subnet matches more than one rule, NNMi randomly chooses from among the matching rules.</p> </div>
Enable	<p>If enabled <input checked="" type="checkbox"/>, NNMi uses the Subnet Connection Rule to create connections between interfaces associated with the IPv4 addresses within the specified subnets.</p> <p>If disabled <input type="checkbox"/>, NNMi ignores the Subnet Connection Rule.</p>

Details for this Subnet Connection Rule

Task	How				
Minimum IPv4 Prefix Length	<p>Specify the minimum prefix length (subnet mask length) for the subnet where you want Spiral Discovery to create Layer 2 Connections. Spiral Discovery creates connections between interfaces associated with IPv4 addresses that have subnet prefix lengths equal to or greater than the specified value and meet the other specified criteria.</p> <table border="1" style="width: 100%; border-collapse: collapse; margin-top: 10px;"> <thead> <tr> <th style="background-color: #003366; color: white;">Valid Minimum IPv4 Prefix Length Values</th><th style="background-color: #003366; color: white;">Number of Usable IPv4 Addresses</th></tr> </thead> <tbody> <tr> <td> </td><td> </td></tr> </tbody> </table>	Valid Minimum IPv4 Prefix Length Values	Number of Usable IPv4 Addresses		
Valid Minimum IPv4 Prefix Length Values	Number of Usable IPv4 Addresses				

Details for this Subnet Connection Rule, continued

Task	How	
	28	14 (16-2=14)*
	29	6 (8-2=6)*
	30	2 (4-2=2)*
	31	2
	* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.	
ifType	<i>Optional.</i> Use this Interface MIB variable as an additional filter to identify the types of interfaces to include when creating the subnet connections. For example, if you want connections only between Frame Relay interfaces, select frameRelay as the ifType.	
ifName	<p><i>Optional.</i> Use this Interface MIB variable as an additional filter to identify the interfaces to include when creating the subnet connections. This attribute is useful if you have a naming convention that is used to identify a set of interfaces. For example, lan0.</p> <p>Maximum 255 characters. The following wildcard characters are permitted: asterisk (*) represents any string, and question mark (?) represents a single character.</p>	
ifDescription	<p><i>Optional.</i> Use this Interface MIB variable as an additional filter to identify the interfaces to include when creating the subnet connections. For example, you might want to select a particular set of interfaces that have the same vendor description.</p> <p>Maximum 255 characters. The following wildcard characters are permitted: asterisk (*) represents any string, and question mark (?) represents a single character.</p>	
ifAlias	<p><i>Optional.</i> Use this Interface MIB variable as an additional filter to identify the interfaces to include when creating the subnet connections. This attribute is useful if you have an alias naming convention that is used to identify a set of interfaces. For example, Connection to remote store in Hawaii.</p> <p>Maximum 255 characters. The following wildcard characters are permitted: asterisk (*) represents any string, and question mark (?) represents a single character.</p>	

Subnet Connection Rules Provided by NNMi

The NNMi Subnet Connection Rules work only with IPv4 subnets.

NNMi provides the Subnet Connection Rules described in the following table (for more information, see ["Consider IPv4 Subnet Connection Rules" on page 200](#)).

The *Small Subnets* Rule ensures that NNMi detects IPv4 addresses within subnets of this size, regardless of the interface type. The remaining Subnet Connection Rules create connections based on interface type and the specified subnet size.

Tip: See ["Consider IPv4 Subnet Connection Rules" on page 200](#) for more information about how Subnet Connection Rules use interface types.

To create new Subnet Connection Rules (or modify the ones provided), see ["Configure IPv4 Subnet Connection Rules" on page 265](#).

If you configure a Subnet Connection Rule, the rule independently applies to each Tenant. The members of Subnets must be unique Tenant/Node pairs (each Node assigned to only one Tenant). A Subnet Connection Rule can establish a link between the Default Tenant and another Tenant. However, links between two Tenants are not permitted *unless one of them is the Default Tenant*. See ["Configure Tenants" on page 213](#).

Subnet Connection Rules Provided by NNMi

Rule Name	Minimum IPv4 Prefix Length (Subnet Mask Length)	Interface Type (#)
Asynchronous Transfer Mode	28	atm (37)
Digital Signal 0	28	ds0 (81)
Digital Signal 1	28	ds1 (18)
Digital Signal 3	28	ds3 (30)
Digital Subscriber Loop over ISDN	28	idsl (154)
Frame Relay Interfaces	28	frameRelay (32)
Integrated Services Digital Network	28	isdn (63)
Multiprotocol Label Switching	28	mpls (166)
Point to Point	28	ppp (23)
Serial Line Internet Protocol	28	slip (28)
Serial Point to Point	28	propPointToPointSerial (22)
Small Subnets	30	
Synchronous Optical Networking	28	sonnet (39)

Configure Unnumbered Interface Node Groups





Unnumbered interface connectivity involves querying routing tables, which can generate a lot of network traffic when the routing tables are large. The steps described in this topic can also be

accomplished using the [nmmunnumberedcfg.ovpl](#) command-line tool.

(*NNMi Advanced - Global Network Management feature*) When using NNMi's Global Network Management feature, remember the following:




- Node Group definitions for the NNMi Global Manager and each NNMi Regional Manager are independent of each other. Each NNMi server can have its own definition for each Node Group name. Node Group definitions are not replicated from Regional Managers to the Global Manager, see ["Create Node Groups" on page 326](#). To easily share your Node Group definitions, see ["Export and Import Configuration Settings" on page 1610](#).
- If Discovery and Monitoring of unnumbered interfaces is enabled, each designated unnumbered interface's form will display the Custom Attributes tab: Custom Attribute: UnnumberedNextHop. This Custom Attribute can be replicated from NNMi Regional Managers to the NNMi Global Manager (["Global Manager: Configure Custom Attribute Replication" on page 115](#)). See the information about Custom Attribute: UnnumberedNextHop in [Custom Interface Attribute Samples](#).

To configure Unnumbered Interface discovery for a Node Group:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Unnumbered Interface Node Group** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Unnumbered Interface Node Groups** tab.
 - e. Do one of the following:
 - To create an Unnumbered Interface Node Group configuration, click the  New icon.
 - To edit an Unnumbered Interface Node Group configuration, double-click the row representing the configuration you want to edit.
3. Specify which Node Group (see the [table](#)).
4. *Optional.* Provide one or more subnet IP Address Ranges to limit the scope of network traffic required for Unnumbered Interface discovery (see ["Configure Unnumbered Interface Subnets" on the next page](#)).
5. Click  **Save and Close** to return to the **Discovery Configuration** form.
6. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#).

7. Verify that the Unnumbered Interface feature is enabled: ["Configure Layer 2 Connection Source" on page 228](#)
8. (NNMi Advanced - Global Network Management feature) On each Regional Manager, consider creating an Interface Group based on the Custom Attribute: UnnumberedNextHop and monitoring that Interface Group (["Interface Settings for Monitoring" on page 416](#)):
 - To easily share your Interface Group definitions, see ["Export and Import Configuration Settings" on page 1610](#).
 - The Global Manager's maps can successfully show status for L2 Connections between unnumbered interfaces discovered on all Regional Managers, see ["Global Manager: Configure Custom Attribute Replication" on page 115](#).

Unnumbered Interface Node Group Definition


Attribute	Description
Node Group	<p>Click the  Lookup icon and do one of the following:</p> <ul style="list-style-type: none">• Select  Quick Find to select the Node Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.• Select  New to create a new Node Group definition. See "Create Node Groups" on page 326.








Configure Unnumbered Interface Subnets

Optional. Specify within which subnets Discovery will search for unnumbered interfaces. Only the nodes within the [specified Node Group](#) are polled for unnumbered interface information.

Note: Unnumbered interface connectivity involves querying routing tables, which can generate a lot of network traffic when querying large routing tables.

To specify a Subnet within which Discovery finds unconnected interfaces:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Unnumbered Interface Subnet** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Unnumbered Interface Node Groups** tab.
 - e. Do one of the following:

- To create an Unnumbered Interface configuration, click the  New icon.
 - To edit an Unnumbered Interface configuration, double-click the row representing the configuration you want to edit.
- f. In the **Unnumbered Interface Node Group** form, select the **Unnumbered Interface Subnets** tab.
- g. Do one of the following:
- To create an Unnumbered Interface Subnet configuration, click the  New icon, and continue.
 - To edit an Unnumbered Interface Subnet configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an Unnumbered Interface Subnet configuration, click the  Delete icon.
3. Provide an IP Address Range in either a wildcard or CIDR notation (see [table](#)).
4. Click  **Save and Close** to return to the **Unnumbered Interface Node Groups** form.
5. Click  **Save and Close** to return to the **Discovery Configuration** form.
6. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#).
7. Verify that the Unnumbered Interface feature is enabled: "[Configure Layer 2 Connection Source](#)" on page 228
8. (*NNMi Advanced - Global Network Management feature*) On each Regional Manager, consider creating an Interface Group based on the Custom Attribute: UnnumberedNextHop and monitoring that Interface Group ("[Interface Settings for Monitoring](#)" on page 416):
- To easily share your Interface Group definitions, see "[Export and Import Configuration Settings](#)" on page 1610.
 - The Global Manager's maps can successfully show status for L2 Connections between unnumbered interfaces discovered on all Regional Managers, see "[Global Manager: Configure Custom Attribute Replication](#)" on page 115.

Unnumbered Interface Subnet Definition

Attribute	Description
IP Range	Note: If you enter an IP address value that represents only one IP address, Discovery gathers neighbor information only from the address you enter. (Discovery extends only one hop out from this address.)

Unnumbered Interface Subnet Definition, continued

Attribute	Description						
	<p>To specify a range of IP addresses for this Discovery Rule, use one of the following. Pick one address notation style. Combinations of wildcards and CIDR notation are not permitted within one address range. You can provide multiple address range settings:</p> <ul style="list-style-type: none"> IPv4 address wildcard notation. <p>An IPv4 Address range is a modified dotted-notation where each octet is one of the following:</p> <ul style="list-style-type: none"> A specific octet value between 0 and 255 A low-high range specification for the octet value (for example, "112-119") An asterisk (*) wildcard character, which is equivalent to the range expression "0-255" <p>Note: The following two IPv4 addresses are considered invalid: 0.0.0.0 and 127.0.0.0</p> <p>Examples of valid IPv4 address wildcards include:</p> <pre>10.1.1.* 10.*.*.* 10.1.1.1-99 10.10.50-55.* 10.22.*.4 10.1-9.1-9.1-9</pre> IPv4 Classless Inter-Domain Routing (CIDR) notation. <p>The CIDR notation specifies the number of consecutive bits in the IPv4 address that must match.</p> <p>For example, 10.2.120.0/21</p> <p>Note: NNMi does not support CIDR subnet mask notation such as, 10.2.120.0/255.255.248.0</p> <table border="1"> <thead> <tr> <th>Example IPv4 Prefix Length Values</th><th>Number of Usable IPv4 Addresses</th></tr> </thead> <tbody> <tr> <td>28</td><td>14 (16-2=14)*</td></tr> <tr> <td>29</td><td>6 (8-2=6)*</td></tr> </tbody> </table> 	Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses	28	14 (16-2=14)*	29	6 (8-2=6)*
Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses						
28	14 (16-2=14)*						
29	6 (8-2=6)*						

Unnumbered Interface Subnet Definition, continued

Attribute	Description						
	<table> <tr> <th>Example IPv4 Prefix Length Values</th><th>Number of Usable IPv4 Addresses</th></tr> <tr> <td>30</td><td>2 (4-2=2)*</td></tr> <tr> <td>31</td><td>2</td></tr> </table> <p>* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.</p> <ul style="list-style-type: none"> IPv6 address wildcard notation <i>(NNMi Advanced)</i> Separate each 16-bit value of the IPv6 address with a colon. The 16-bit value can be any of the following: <ul style="list-style-type: none"> A specific hexadecimal value between 0 and FFFF (case insensitive). A low-high range specification of the hexadecimal value (for example, 1-1fe). An asterisk (*) wildcard character (equivalent to the range expression 0-ffff). <div> Note: The standard IPv6 short-hand notation (: :) is allowed to express one or more 16-bit elements of zero (0) values. However, the mixed IPv6/IPv4 dot-notation (for example, 2001:d88::1.2.3.4) is not permitted as an IPv6 address range. </div> <p>Valid examples of ranges in modified IPv6 address notation include the following:</p> <pre>2001:D88:0:A00-AFF:*:*:*:*</pre> <pre>2001:D88:1:*:*:*:*</pre> <pre>2001:D88:2:0:a07:ffff:0a01:3200-37ff</pre> IPv6 Classless Inter-Domain Routing (CIDR) notation <i>(NNMi Advanced)</i> The CIDR notation specifies the number of consecutive bits in the IPv6 address that must match. <p>2001:d88:a00::/44 (equivalent to modified IPv6 address notation 2001:d88:a00-a0f:*:*:*:*)</p> <p>For example, valid IPv6 address ranges in CIDR notation include the following:</p> <pre>2001:d88:0:a00::/56 (equivalent to modified IPv6 address notation 2001:D88:0:A00-AFF:*:*:*)</pre> <pre>2001:d88:1::/48 (equivalent to modified IPv6 address notation 2001:D88:1:*:*:*:*)</pre> 	Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses	30	2 (4-2=2)*	31	2
Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses						
30	2 (4-2=2)*						
31	2						

Configure an Excluded IP Addresses Filter

This configuration setting instructs NNMi to not add the specified IP addresses to the NNMi database (ignore that information when received from an SNMP agent), not acknowledge any Hints received about them, nor gather Discovery Hints from them, and delete them from the NNMi database during the next Spiral Discovery cycle (if previously discovered). Therefore, NNMi does not monitor or communicate with those addresses. See ["Keep Requests to a Minimum" on page 202](#).

Caution: This filter applies to all nodes that meet the criteria within any Tenant.

Note: The node and interface associated with any address identified in your Excluded IP Address filter still shows up in the topology database and maps. For information about excluding the entire node, see ["Strategies to Exclude Certain Nodes from Auto-Discovery" on page 262](#).

Sometimes there are IP addresses or ranges of IP addresses in your environment that you do not want NNMi to discover or monitor. For example:

- There are multiple Nortel switches in your environment. They each have a non-routable IP address of 192.168.168.168 that is defined by the manufacturer. This special address is used to establish the default VLAN for the switch. However, NNMi discovers this duplicate address and establishes a lot of unnecessary connections on the Layer 3 Neighbor View map.
- Your service provider forbids the generation of ICMP or SNMP traffic from your NNMi installation. That range of addresses can easily be excluded to prevent violating your contractual agreement with the vendor.
- The Provider Edge ([PE¹](#)) routers have addresses that NNMi ICMP ping commands cannot reach or have addresses that you want to exclude from Subnet views.





Carefully select the addresses for your Excluded IP Addresses filter. Do not populate the Excluded IP Addresses filter with the addresses associated with SNMPv1/SNMPv2c agents or SNMPv3 engines (the Management Addresses).

Caution: This filter applies to all nodes in all Tenants. If you exclude an IP address, any duplicates of that address in *static* Network Address Translation (NAT), *dynamic* Network Address Translation (NAT), or *dynamic* Port Address Translation (PAT/NAPT) domains of your network are also excluded. See ["Overlapping Addresses in NAT Environments" on page 94](#).

Tip: If you have a large number of IP addresses that you want to exclude from Spiral Discovery, see the [nnmdiscocfg.ovpl](#) Reference Page.

¹Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

To exclude specific IP addresses from the discovery process:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Excluded IP Address** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Excluded IP Addresses** tab.
 - e. Do one of the following:
 - To exclude an address or range of addresses from Spiral Discovery, click the  **New** icon, and continue.
 - To edit an excluded address setting, click the  **Open** icon in the row representing the configuration you want to edit, and continue.
 - To delete an excluded address setting, select a row, and click the  **Delete** icon.
3. To specify a range of Excluded IP addresses, use one of the following. Pick one address notation style, combinations of wildcards and CIDR notation are not permitted within one address range. You can provide multiple address range settings:

■ **IPv4 address wildcard notation.**

An IPv4 Address range is a modified dotted-notation where each octet is one of the following:

- A specific octet value between 0 and 255
- A low-high range specification for the octet value (for example, "112-119")
- An asterisk (*) wildcard character, which is equivalent to the range expression "0-255"

Note: The following two IPv4 addresses are considered invalid: 0.0.0.0 and 127.0.0.0

Examples of valid IPv4 address wildcards include:

10.1.1.*
10.*.*.*
10.1.1.1-99
10.10.50-55.*
10.22.*.4 10.1-9.1-9.1-9

- **IPv4 Classless Inter-Domain Routing (CIDR) notation.**

The CIDR notation specifies the number of consecutive bits in the IPv4 address that must match.

For example, 10.2.120.0/21

Note: NNMi does not support CIDR subnet mask notation such as, 10.2.120.0/255.255.248.0

Example IPv4 Prefix Length Values	Number of Usable IPv4 Addresses
28	14 (16-2=14)*
29	6 (8-2=6)*
30	2 (4-2=2)*
31	2

* Two IPv4 addresses are reserved in each subnet. The first IPv4 address is used for the network itself and the last IPv4 address is reserved for broadcast.

- **IPv6 address wildcard notation**

(NNMi Advanced) Separate each 16-bit value of the IPv6 address with a colon. The 16-bit value can be any of the following:

- A specific hexadecimal value between 0 and FFFF (case insensitive).
- A low-high range specification of the hexadecimal value (for example, 1-1fe).
- An asterisk (*) wildcard character (equivalent to the range expression 0-ffff).

Note: The standard IPv6 short-hand notation (:) is allowed to express one or more 16-bit elements of zero (0) values. However, the mixed IPv6/IPv4 dot-notation (for example, 2001:d88::1.2.3.4) is not permitted as an IPv6 address range.

Valid examples of ranges in modified IPv6 address notation include the following:

```
2001:D88:0:A00-AFF:*.*.*.*.  
2001:D88:1:*.*.*.*.  
2001:D88:2:0:a07:ffff:0a01:3200-37ff
```

- **IPv6 Classless Inter-Domain Routing (CIDR) notation**


(NNMi Advanced) The CIDR notation specifies the number of consecutive bits in the IPv6 address that must match.

2001:d88:a00::/44 (equivalent to modified IPv6 address notation 2001:d88:a00-a0f:*.~:~:~:~:~)

For example, valid IPv6 address ranges in CIDR notation include the following:

2001:d88:0:a00::/56 (equivalent to modified IPv6 address notation 2001:D88:0:A00-AFF:*.~:~:~:~:~)

2001:d88:1::/48 (equivalent to modified IPv6 address notation 2001:D88:1:*.~:~:~:~:~)

4. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

For strategies to prevent specific devices from being discovered:

Configure an Included Interface Ranges Filter

Sometimes there are certain types of interfaces in your environment that you want NNMi to discover. For example, you might have large devices with thousands of interfaces and want NNMi to discover and monitor only a subset of the interfaces in these devices.


This configuration setting instructs Spiral Discovery to only request data about a subset of Interfaces within the specified vendor/make/models (determined by MIBII sysObjectID). See ["Keep Requests to a Minimum" on page 202](#).




Caution: This filter applies to all nodes that meet the criteria within any Tenant.

Rather than requiring that you specify each interface, NNMi enables you to use the System Object ID prefix (SNMP MIBII sysObjectID) and the `ifIndex` values to specify a range of interfaces that you want NNMi to discover. Use the **Configuration** → **Device Profiles** view to see the list of all known system object IDs at the time NNMi released.

Tip: To exclude any particular interfaces within that range you can also use the Excluded Interfaces tab. See ["Configure an Excluded Interfaces Filter" on page 280](#) for more information.

To include Interfaces in the Spiral Discovery process using Included Interface Ranges:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Included Interface Ranges** tab.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.


- b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Included Interface Ranges** tab.
3. Do one of the following:
 - To specify an Interface Range to include in Spiral Discovery, click the  New icon, and continue.
 - To edit an Included Interface Ranges setting, double-click the row representing the configuration you want to edit, and continue.
 - To delete an Included Interface Ranges setting, select a row, and click the  Delete icon.
 - To refresh the list of Included Interface Ranges settings, click the  Refresh icon.
4. Provide the required basic settings (see [Basics table](#))

Many routers have thousands of interfaces. If you want NNMi to actively discover and monitor a subset of those interfaces, consider an Included Interface Range that specifies only those interfaces you care about. For example:

sysObjectID = Nortel and ifIndex = 1-256 (or any range that reflects reality in your network environment)

System Object ID Prefix	Low ifIndex Value	High ifIndex Value	Notes
1.3.6.1.4.1.2505.	1	256	Nortel Routers

Caution: Be careful about determining which Interfaces are important to your team. Make sure all key interfaces (such as Loopbacks) are in the specified ifIndex range.

5. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

6. To further refine the Interfaces you want Spiral Discovery to discover, use the **Excluded Interfaces** tab. See ["Configure an Excluded Interfaces Filter" on page 280](#) for more information.

NNMi first checks for any Included Interface Range filter and then ignores data about any interfaces that are specified using the Excluded Interfaces filter.

Tip: You can configure multiple `ifIndex` ranges for the same System Object ID prefix.

Included Interface Ranges Basic Attributes

Attribute	Description
System Object ID Prefix	<p>Enter a prefix of an SNMP system object ID, or enter the entire SNMP system object ID. NNMi finds the longest (or most specific) matching system Object ID value. This means you can define generic rules for certain device families and more specific rules for specific device types.</p> <p>Note: Do not use dashes or asterisks (*) in your system object ID value. Do not use a period (.) as the first character.</p> <p>A partial entry becomes a wildcard. For example, if you enter 1.3.6.1.4.1.11, discovery finds all HP devices. If you enter 1.3.6.1.4.1.9, discovery finds all Cisco devices.</p> <p>Tip: You can configure multiple <code>ifIndex</code> ranges for the same System Object ID Prefix. For example, to configure Included Interface Ranges filters that specify <code>ifIndex</code> values 10 through 20 and 40 through 50 for the same node, create two Included Interface Range configurations for the same System Object ID Prefix. In the first Included Interface Range Filter, use the Low <code>ifIndex</code> Value 10 and the High <code>ifIndex</code> Value 20. Create a second Included Interface Range Filter using the Low <code>ifIndex</code> Value 40 and the High <code>ifIndex</code> Value 50.</p>
Low <code>ifIndex</code> Value	<p>Enter the lowest <code>ifIndex</code> value for the range of Interfaces you want to include in Spiral Discovery.</p> <p>Note the following</p> <ul style="list-style-type: none"> The Low <code>ifIndex</code> Value must be equal to or greater than 1 and less than 2147483647. This value must be less than the High <code>ifIndex</code> Value
High <code>ifIndex</code> Value	<p>Enter the highest <code>ifIndex</code> value for the range of Interfaces you want to include in Spiral Discovery.</p> <p>Note the following</p> <ul style="list-style-type: none"> The High <code>ifIndex</code> Value must be greater than 1 and less than or equal to 2147483647. This value must be greater than the Low <code>ifIndex</code> Value.

For strategies to prevent specific devices from being discovered:

Configure an Excluded Interfaces Filter

This configuration setting instructs NNMi to not add the specified Interfaces to the NNMi database (ignore that information when received from an SNMP agent), not acknowledge any Hints received about them, nor gather Discovery Hints from them. Therefore, NNMi does not monitor or communicate with those interfaces. See ["Keep Requests to a Minimum" on page 202](#).

Caution: This filter applies to all nodes that meet the criteria within any Tenant.

Once configured as an excluded interface:

- The interface's relationship to other objects is canceled:
 - Node
 - Address
 - VLAN Port
- The interface's membership status within any logical groups is removed:
 - Layer 2 Connections with [Link Aggregation](#)¹ or [Split Link Aggregation](#)² (*NNMi Advanced*)
 - Router Redundancy Groups (*NNMi Advanced*)
 - VLANs
- During the next discovery cycle, NNMi automatically removes any previously discovered data associated with an excluded interface.


Note: The node and addresses associated with any interface identified in your Excluded Interface filter still shows up in the topology database and maps. For information about excluding the entire node, see ["Strategies to Exclude Certain Nodes from Auto-Discovery" on page 262](#).

An Interface Group definition sets the criteria for exclusion. You can define Interface Groups using a wide range of criteria choices. See ["Create Interface Groups" on page 356](#). For example, the following Interface Group when used in an Excluded Interfaces filter instructs Spiral Discovery to ignore any

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Nortel routers' Virtual Interfaces. The selected Interface Group will be empty after the next Spiral Discovery cycle. Consider disabling the Interface Group definition's **Add to View Filter List** ☐ attribute to prevent this empty Interface Group from appearing on selection lists within NNMi views:












Be careful to not exclude Interfaces that are important to your team.

Note: Your Excluded Interfaces filter can be used in combination with an Included Interface Ranges filter. This strategy keeps network traffic to a minimum. The Included Interface Ranges use RFC 1213, MIB-II sysObjectID values paired with ifIndex ranges. Spiral Discovery then *requests only information about that subset of Interfaces from a matching Node's SNMP agent* (see ["Configure an Included Interface Ranges Filter" on page 277](#)).

If your Nodes have a high interface count and you want NNMi to Discover and Monitor only a subset of the most important Interfaces, consider using the Included Interface Ranges settings to identify the subset of important interfaces. Then your Excluded Interfaces Filter can instruct Spiral Discovery to reject a few items from within the included ifIndex ranges.

To exclude specific types of interfaces during the Spiral Discovery process:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Excluded Interfaces** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Discovery Configuration**.
 - d. Select the **Excluded Interfaces** tab.
3. Do one of the following:

- To select an Interface Group to filter certain interfaces out of Spiral Discovery, click the  New icon, and continue.
 - To edit an excluded interfaces setting, double-click the row representing the configuration you want to edit, and continue.
 - To delete an excluded interfaces setting, select a row, and click the  Delete icon.
 - To refresh the list of excluded interface settings, click the  Refresh icon.
4. In the Interface Filter form, click the  Lookup icon and select one of the options from the drop-down menu:
-  Show Analysis to view Analysis Pane information for the currently selected Interface Group. (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
 -  Quick Find to view and select from the list of all existing Interface Groups (for more information see ["Use the Quick Find Window" on page 38](#)).
 -  Open to display the details of the currently selected Interface Group.
 -  New to create a new Interface Group (see ["Create Interface Groups" on page 356](#) for more information).
5. Click  **Save and Close**. Spiral Discovery implements your changes during the next regularly scheduled [discovery interval](#). To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

For strategies to prevent specific devices from being discovered:

Choose Techniques to Launch Discovery

Available choices for Auto-Discovery (within Default Tenant) and Spiral Discovery (all Tenants) are as follows:

Discovery Seeds for Auto-Discovery in Default Tenant	283
Ping Sweep for Auto-Discovery in Default Tenant	285
Spiral Discovery of Only Seeds (all Tenants)	285

Two techniques are available for launching Spiral Discovery:

- Provide a Discovery Seed to identify each Node you want NNMi to Discover.
- Auto-Discovery (in Default Tenant only): Configure either Discovery Seeds or Ping Sweep (ICMP ping), or both as starting points for Auto-Discovery. NNMi requests information about all known neighboring devices and then discovers the neighboring devices within the Default Tenant's address range.

Ping Sweep works only with *IPv4 addresses*. In Wide Area Networks (WANs) such as ATM, Frame Relay, and Point-to-Point (where ARP cache is not available), the Ping Sweep locates nodes for Auto-Discovery to use when gathering neighbor information and evaluating "[Consider IPv4 Subnet Connection Rules](#)" on page 200.

NNMi discovers any devices that comply with your Auto-Discovery Rule configurations and creates a record of each device in the NNMi database. If the device supports SNMP, all addresses for that device are combined into one Node object. If the device does not support SNMP, NNMi queries DNS to determine the hostname. If this hostname matches another non-SNMP node, NNMi merges the information to create only one node with multiple associated addresses.

Two additional methods are possible for launching Discovery:

- NNMi administrators can initiate Discovery for a particular Node using the **Actions** → **Polling** → **Configuration Poll** menu item. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Each time you select **Actions** → **Polling** → **Configuration Poll**, NNMi also applies any Custom Poller Policy to the nodes in its specified Node Group. This determines which instances should be polled. See "[Create Custom Polling Configurations](#)" on page 478 for more information.

- Auto-Discovery also uses the source IP address from SNMP traps as Discovery Hints for new addresses. If your Auto-Discovery Rules' IP Ranges include that new IP address, NNMi uses the Trap Hint for initial discovery of that address. NNMi then requests the Node's current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all further communication. NNMi calculates whether the new address belongs to a previously discovered Node or a new Node.

Discovery Seeds for Auto-Discovery in Default Tenant

Discovery seeds are optional for the Nodes in the Default Tenant, but required for each Node assigned to any other Tenant.

Caution: If your network uses any of the following IPv4 translation protocols, you must create a unique Tenant (other than *Default Tenant*) for each domain of nodes with addresses determined by the following protocols (see "[Overlapping Addresses in NAT Environments](#)" on

[page 94](#)):

- *Static* Network Address Translation (NAT)
- *Dynamic* Network Address Translation (NAT)
- *Dynamic* Port Address Translation (PAT/NAPT)

A discovery seed is a specific node that you want NNMi to discover. For example, a discovery seed might be a core router in your management environment.

Each discovery seed is identified by hostname (*not case-sensitive*) or IP address, and Initial Discovery [Tenant](#) assignment. When you add a discovery seed, NNMi immediately tries to discover that device (without waiting until the next regularly scheduled [discovery interval](#)). If discovery is not successful, NNMi tries again 10 minutes later, and continues trying. The time between each attempt is doubled until the time reaches 1 week or equals your current discovery interval.

NNMi discovers seed addresses regardless of how you configure [Auto-Discovery Rule](#) definitions or the [Excluded IP Addresses](#) filter.

Note: Nodes configured as discovery seeds are always discovered and added to the topology database. If you change your mind and [delete a discovery seed](#) configuration, the node is not automatically deleted from the topology database. See "[Delete Nodes](#)" on [page 1635](#).

If you configure one or more Auto-Discovery Rules, note the following:

- If **Discover Matching Nodes** ☒ is enabled for an Auto-Discovery Rule, NNMi uses each discovery seed as a starting point to gather information about neighboring devices to expand discovery.

Note: You can use the [Ping Sweep](#) option in your Auto-Discovery Rules in addition to or instead of Discovery Seeds.

- If **Discover Matching Nodes** ☐ is disabled for an Auto-Discovery Rule, no devices matching that rule's criteria are discovered and added to the topology database unless:

- The device's address is a discovery seed.

See "[Specify Discovery Seeds](#)" on [page 287](#) to learn how to establish discovery seeds.

- The device's address is reported as a neighbor to another discovered address.

If you want to ensure that an address is never added to the NNMi database, use the settings for "[Configure an Excluded IP Addresses Filter](#)" on [page 274](#) or "[Configure an Excluded Interfaces Filter](#)" on [page 280](#).

Ping Sweep for Auto-Discovery in Default Tenant

Default Tenant only: You have two choices for Auto-Discovery starting points. Use either or both to best advantage for Nodes configured for the *Default Tenant* in your network environment:

- [Discovery Seeds](#)
You designate specific hostnames (*not case-sensitive*) or IP addresses where Auto-Discovery starts gathering neighbor information.
- Ping Sweep
NNMi issues ICMP pings to certain addresses gathered from neighbor information.

Note: Ping Sweep works only with IPv4 addresses and only in 16-bit subnets. All nodes discovered using Auto-Discovery are assigned to the *Default Tenant*.

Ping Sweep sends ICMP ping commands to IP addresses in the ranges defined in your Auto-Discovery rules. Ping Sweep enforces the following limits to the ICMP pings:

- For each specific IP address range, NNMi issues pings across a maximum of the last two octets in the IPv4 address range. This is equivalent to a /16 subnet
- ICMP pings are limited to 500 at one time. This avoids flooding your network or causing spam detection tools to set off an alarm.

Ping Sweep is useful in wide area networks such as ATM, Frame Relay, and Point-to-Point that do not contain an Address Resolution Protocol (ARP) cache.

You configure the Ping Sweep feature at two levels:

- ["Configure Ping Sweep \(override for all Auto-Discovery Rules\)" on page 222](#)
- ["IP Address Ranges for the Auto-Discovery Rule" on page 244](#) (Ping Sweep configuration for each rule)

Spiral Discovery of Only Seeds (all Tenants)

Use these guidelines if any of the following are true:

- You want NNMi to discover only what you specify.
- Your network includes nodes with addresses provided by any of the following protocols (see ["Overlapping Addresses in NAT Environments" on page 94](#)):
 - *Static* Network Address Translation (NAT)
 - *Dynamic* Network Address Translation (NAT)

- *Dynamic* Port Address Translation (PAT/NAPT)
- You want to control which Nodes each NNMI user sees. See ["Tenant and Initial Discovery Security Group Assignments" on page 217](#).

Note: After you set your configuration according to these guidelines, when a new device is added to your network, NNMI does not discover that device unless you configure another discovery seed to identify that device.

Configuration Steps to Discover Only What You Specify

Task	How
<p>Do not include any Auto-Discovery Rules.</p> <p>Note: Auto-Discovery Rules can only be used to find devices assigned to the Default Tenant.</p>	<p>None are required for this strategy.</p>
<p>NNMI provides one <i>Default Tenant</i>. If you do not define any additional Tenants, all nodes belong to the Default Tenant and all NNMI users can see all Nodes within the Default Tenant.</p> <p>Configure a Tenant for each subset of devices you want to identify within your network environment for network segmentation or security purposes. NNMI users can then be assigned to the appropriate Tenant. See "Configuring Security" on page 569.</p> <p>Caution: If your network uses any of the following address translation protocols, you must create a unique Tenant (other than <i>Default Tenant</i>) for each domain of nodes with addresses determined by the following protocols (see "Overlapping Addresses in NAT Environments" on page 94):</p> <ul style="list-style-type: none"> • <i>Static</i> Network Address Translation (NAT) • <i>Dynamic</i> Network Address Translation (NAT) • <i>Dynamic</i> Port Address Translation (PAT/NAPT) <p>Each member node must be identified with a discovery Seed configuration (see next row in this table).</p> <p>Note: All members of a Router Redundancy Group must be assigned to the same Tenant (visible in the Node form's Basic Attributes and in the Tenants column of the Inventory > Nodes view). The NNMI administrator configures the Tenants.</p>	<p>"Configure Tenants" on page 213.</p>
<p>In Discovery Configuration's Seeds view, for each device you want NNMI to</p>	<p>"Specify"</p>

Configuration Steps to Discover Only What You Specify, continued

Task	How
<p>discover:</p> <ul style="list-style-type: none">Designate the hostname (<i>not case-sensitive</i>) or IP address. <div><p>Caution: For nodes with addresses provided by Network Address Translation (NAT) protocols, use the appropriate address (see "Overlapping Addresses in NAT Environments" on page 94):</p><ul style="list-style-type: none">Static Network Address Translation (NAT):<ul style="list-style-type: none">If the NNMi management server is outside the NAT domain - use the node's <i>external IP address</i>If the NNMi management server is inside the NAT domain - use the node's <i>internal IP address</i>Dynamic Network Address Translation (NAT) - use the node's <i>internal IP address</i>.Dynamic Port Address Translation (PAT/NAPT) - use the node's <i>internal IP address</i>.<p>For more information:</p></div> <ul style="list-style-type: none">Designate the Tenant assignment if other than Default Tenant. <p>Then configure NNMi to monitor your SNMP devices. See "Monitoring Network Health" on page 378.</p>	<p>Discovery Seeds" on the next page</p>

Note: You control how often Spiral Discovery checks the discovered nodes based on a **Rediscovery Interval** setting. See ["Adjust the Rediscovery Interval" on page 231](#) for more information.

Specify Discovery Seeds

To configure discovery seeds do one or more of the following:

In the Console, Configure Discovery Seeds	288
From the Command Line, Add Discovery Seeds	293
Add Multiple Seeds, Configure Discovery Seeds	293

A discovery seed is a specific node that you want NNMi to discover.

Discovery seeds are sometimes optional and sometimes required. Before you begin, review the following topics:

- ["Which Nodes Are Discovered?" on page 195](#)
- ["Configure Auto-Discovery Rules" on page 236](#)
- ["Determine Your Security Strategy" on page 574](#)

Nodes specified as discovery seeds are always discovered and added to the topology database. As soon as you enter one or more discovery seeds, discovery begins. As part of the seed configuration, you specify a Tenant attribute value (and indirectly a Security Group attribute value). See ["Configure Tenants" on page 213](#) for more information.

Default Tenant only: If you create Auto-Discovery Rules, NNMi automatically gathers Hints from each discovered Node and uses that information to find any neighboring devices within your Default Tenant's address range.

If you want to use Auto-Discovery within the Default Tenant:

- Configure at least one Auto-Discovery Rule. See ["Configure Auto-Discovery Rules" on page 236](#).
- Configure any number of Auto-Discovery Rules to maintain fine control over the scope of Auto-Discovery within the Default Tenant.

A discovery seed is a hostname (*not case-sensitive*) or IP address. Consider devices with the largest neighbor data in your network environment. For example, a good choice for a discovery seed would be a core router connected to a network you want to discover.

If you change your mind and delete a discovery seed from Discovery Configuration, the corresponding node is not deleted from the topology database. See ["Delete Nodes" on page 1635](#) for information about removing the entire node record from the topology database.

Within the Default Tenant, Auto-Discovery can also use Ping Sweep instead of or in addition to discovery seeds to gather this neighbor information. See ["Ping Sweep for Auto-Discovery in Default Tenant" on page 285](#) and ["Discovery Seeds for Auto-Discovery in Default Tenant" on page 283](#).

Note: Ping Sweep works only with IPv4 addresses and only in 16-bit subnets. All nodes discovered using Auto-Discovery are assigned to the *Default Tenant*.

Related Topics

["Discovery Seed Results" on page 299](#)




["Delete Discovery Seeds" on page 310](#)

In the Console, Configure Discovery Seeds

Discovery seeds are sometimes optional and sometimes required. See ["Specify Discovery Seeds" on the previous page](#) for details.

For the alternate method of configuring Discovery Seeds, see ["From the Command Line, Add Discovery Seeds" on page 293](#) and ["Add Multiple Seeds, Configure Discovery Seeds" on page 293](#).

To add a discovery seed using the console:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Navigate to the **Seeds** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Seeds**.
3. Do one of the following:
 - To add a discovery seed, click the  New icon.
 - To edit a discovery seed, double-click the row representing the discovery seed you want to edit.
 - To delete a discovery seed, select a row, and click the  Delete icon (see ["Delete Discovery Seeds" on page 310](#) and ["Delete Nodes" on page 1635](#) for more information).
4. Provide appropriate information (see [table](#)).


NNMi uses information gathered from Routers to establish membership for Subnet connections. [Make sure that important Routers in your network environment are SNMP enabled](#).


NNMi uses either of the following criteria to identify a Router:

- The Router responds to an SNMP query with appropriate values for `sysServices` (1.3.6.1.2.1.1.7) and `ipForwarding` (1.3.6.1.2.1.4.1). See RFC 1213, MIB-II for details.
- The Router responds to an SNMP query with an appropriate MIB-II `sysObjectID` value according to the current settings in NNMi's [Device Profile configuration](#).

You must provide the appropriate SNMP Community Strings to NNMi. See ["Configuring Communication Protocol" on page 129](#).

5. Click  **Save and Close** to return to the Discovery Configuration form.

Tip: Click the  Save and New icon to continue to adding discovery seeds.

6. Click  **Save and Close**. As soon as you enter one or more discovery seeds, discovery begins.

Discovery Seed Definition

Attribute	Definition
Hostname / IP Address	<p>To identify the node, enter one of the following:</p> <ul style="list-style-type: none"> • Fully-qualified hostname of the discovery seed (<i>not case-sensitive</i>) • IP address of the discovery seed <p>If you specify an IP address, NNMi uses that IP address only during initial discovery of the Seed. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: For nodes with addresses provided by Network Address Translation (NAT) protocols, use the appropriate address (see "Overlapping Addresses in NAT Environments" on page 94):</p> <ul style="list-style-type: none"> • Static Network Address Translation (NAT): <ul style="list-style-type: none"> ▪ If the NNMi management server is outside the NAT domain - use the node's <i>external IP address</i> ▪ If the NNMi management server is inside the NAT domain - use the node's <i>internal IP address</i> • Dynamic Network Address Translation (NAT) - use the node's <i>internal IP address</i>. • Dynamic Port Address Translation (PAT/NAPT) - use the node's <i>internal IP address</i>. <p>For more information:</p> </div> <p>(<i>NNMi Advanced</i>) When providing IPv6 addresses as discovery seeds, use IPv6 notation as defined in RFC 2373. Click here for more information.</p> <ul style="list-style-type: none"> • 16-byte (128-bit) address, composed of eight groups of 2-byte (16-bit) hex values separated by colons (XXXX:XXXX:XXXX:XXXX:XXXX:XXXX:XXXX:XXXX) • Uppercase and lowercase (A-F/a-f) permitted for the hex digits. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: NNMi displays IPv6 addresses as all lowercase.</p> </div> <ul style="list-style-type: none"> • <i>Optional.</i> Omit leading zeros in each 2-byte hex value. • :: means a single contiguous sequence of all zero 2-byte hex values. However,





Discovery Seed Definition , continued

Attribute	Definition																	
	<p>:: is permitted only one time per address. For example, the following three IPv6 address notations are equivalent:</p> <p>2001:0D88:0000:0000:0008:0800:200C:417A</p> <p>2001:d88:0:0:8:800:200c:417a</p> <p>2001:d88::8:800:200C:417a</p> <ul style="list-style-type: none">For the right-most 32-bits, IPv4 dotted-decimal notation can replace the pair of 2-byte hex values. For example, the following two IPv6 address notations are equivalent: <p>2001:D88::5efe:10.7.150.201</p> <p>2001:D88::5efe:a07:96c9</p> <p>Types of IPv6 Addresses</p> <table><tr><th>IPv6 Address Range</th><th>Explanation</th></tr><tr><td>0::to 1fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>unassigned or reserved</td></tr><tr><td>2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>global unicast address¹</td></tr><tr><td>fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>unique local address²</td></tr></table> <p>The IP addresses in the following table cannot be used as Discovery Seeds or Auto-Discovery Hints. NNMi still Discovers and Monitors these addresses within the context of a Node, but NNMi does not gather information about neighbors from these addresses.</p> <p>Invalid IP Addresses for Discovery Seeds or Auto-Discovery Hints</p> <table><tr><th>IPv4 Address Range</th><th>IPv6 Address Range</th><th>Explanation</th></tr><tr><td>0.*.*.*</td><td>not applicable</td><td>Reserved IP addresses</td></tr><tr><td>0.0.0.0</td><td>::0</td><td>Any Local</td></tr></table>	IPv6 Address Range	Explanation	0::to 1fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	unassigned or reserved	2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	global unicast address ¹	fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	unique local address ²	IPv4 Address Range	IPv6 Address Range	Explanation	0.*.*.*	not applicable	Reserved IP addresses	0.0.0.0	::0	Any Local
IPv6 Address Range	Explanation																	
0::to 1fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	unassigned or reserved																	
2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	global unicast address ¹																	
fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff:ffff	unique local address ²																	
IPv4 Address Range	IPv6 Address Range	Explanation																
0.*.*.*	not applicable	Reserved IP addresses																
0.0.0.0	::0	Any Local																

¹(2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff) A publically routable IPv6 unicast address, used for communication between nodes anywhere on the internet. The first part of the address is a global routing prefix in the 2000::/3 address space for your organization (assigned by the Internet Service Providers). The complete host address can either be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

²(fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff:ffff) A privately routable IPv6 unicast address used only for communication between nodes within your organization. The unique local addresses cannot be routed to the public internet. The address consists of a routing prefix in the fd00:/8 address spaces, assigned locally by your organization. And the full host address might be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

Discovery Seed Definition , continued

Attribute	Definition		
	Invalid IP Addresses for Discovery Seeds or Auto-Discovery Hints, continued		
	IPv4 Address Range	IPv6 Address Range	Explanation
			(listen) address
	127.*.*.*	::1	Loopback addresses
	not applicable	fe80::*:*:*:*	IPv6 link-local address ¹
	224-239.*.*.*	not allowed (ff00:: to ffff:ffff:ffff:ffff:ffff:ffff:ffff:ffff)	multicast address ²
Initial Discovery Tenant	255.255.255.255	not applicable	Broadcast address
	<p>For the Initial Discovery Tenant setting, do one of the following:</p> <ul style="list-style-type: none"> • Leave this attribute empty (blank). NNMi assigns each Node to the <i>Default Tenant</i> (and whichever Initial Discovery Security Group attribute value is currently assigned to the Default Tenant). • <i>Optional.</i> Assign a Tenant to a particular seed before discovery. See "Configure Tenants" on page 213 and "About Security Groups" on page 582 for more information. <ul style="list-style-type: none"> ▪ Click the drop-down icon to see the list of previously configured Tenant names or Tenant UUID³s. Use the auto-complete feature to quickly specify which tenant. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: You can also click the  Lookup icon and select  Quick Find for the list of previously defined tenants.</p> </div> <ul style="list-style-type: none"> ▪ To define a new Tenant, click the  Lookup icon and select  New. 		

¹A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

²Used to identify a group of hosts joined into a group. IPv4 multicast addresses are in the range 224.0.0.0 to 239.255.255.255 and IPv6 multicast addresses have the prefix ff00::/8.

³Universally Unique Object Identifier, which is unique across all databases.

Discovery Seed Definition , continued

Attribute	Definition
Discovery Seed Results	An automatically generated value. The most recent discovery status for this discovery seed. See "Discovery Seed Results" on page 299 for details.
Last Modified	The date and time of the last change in Discovery Seed Results.
Notes	<p>Provide any additional information about this discovery seed that would be useful to you or your team.</p> <p>Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

From the Command Line, Add Discovery Seeds

Discovery seeds are sometimes optional and sometimes required. See ["Specify Discovery Seeds" on page 287](#) for details.

Use the following command-line tool to configure discovery seeds:

- See the [nnmloadseeds.ovpl](#) Reference Page.

This command can be used in combination with a text (TXT) file.

Note: The directory and filename of the seed file must be accessible for non-root users.

- Use [nnmloadseeds.ovpl -list](#) to list all configured seeds and to report seed status.

For the alternate method of configuring Discovery Seeds, see ["In the Console, Configure Discovery Seeds" on page 288](#) and ["Add Multiple Seeds, Configure Discovery Seeds" below](#).

Related Topics

["Discovery Seed Results" on page 299](#)

["Delete Discovery Seeds" on page 310](#)

Add Multiple Seeds, Configure Discovery Seeds

Discovery seeds are sometimes optional and sometimes required. See ["Specify Discovery Seeds" on page 287](#) for details.


For the alternate method of configuring Discovery Seeds, see ["In the Console, Configure Discovery Seeds" on page 288](#) or ["From the Command Line, Add Discovery Seeds" above](#).

To add multiple discovery seeds using a seed file:

1. Complete all prerequisites. See ["Prerequisites for Discovery" on page 207](#), .
2. Using a text editor, create a list of seeds, one per line, using the following syntax (see table below for more details):

```
<IP Address or HostName>, "<optional Tenant Name or UUID>" # <optional Notes text>
```

Note: The directory and filename of the seed file must be accessible for non-root users.

3. Navigate to the **Seeds** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Seeds**.
4. Select any row and do one of the following:
 - Click **Actions** → **Add Multiple Seeds**.
 - Right-click any row and select **Add Multiple Seeds**.
5. Follow the instructions in the Add Multiple Seeds dialog.

Discovery Seed Definition

Attribute	Definition
Hostname / IP Address	<p>To identify the node, enter one of the following:</p> <ul style="list-style-type: none">• Fully-qualified hostname of the discovery seed (<i>not case-sensitive</i>)• IP address of the discovery seed <p>If you specify an IP address, NNMi uses that IP address only during initial discovery of the Seed. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery.</p> <div><p>Caution: For nodes with addresses provided by Network Address Translation (NAT) protocols, use the appropriate address (see "Overlapping Addresses in NAT Environments" on page 94):</p><ul style="list-style-type: none">• Static Network Address Translation (NAT):<ul style="list-style-type: none">■ If the NNMi management server is outside the NAT domain - use the</div>

Discovery Seed Definition , continued

Attribute	Definition
	<p>node's <i>external IP address</i></p> <ul style="list-style-type: none"> ■ If the NNMi management server is inside the NAT domain - use the node's <i>internal IP address</i> • <i>Dynamic Network Address Translation (NAT)</i> - use the node's <i>internal IP address</i>. • <i>Dynamic Port Address Translation (PAT/NAPT)</i> - use the node's <i>internal IP address</i>. <p>For more information:</p> <p>(NNMi Advanced) When providing IPv6 addresses as discovery seeds, use IPv6 notation as defined in RFC 2373. Click here for more information.</p> <ul style="list-style-type: none"> • 16-byte (128-bit) address, composed of eight groups of 2-byte (16-bit) hex values separated by colons (XXXX:XXXX:XXXX:XXXX:XXXX:XXXX:XXXX:XXXX) • Uppercase and lowercase (A-F/a-f) permitted for the hex digits. <p>Note: NNMi displays IPv6 addresses as all lowercase.</p> <ul style="list-style-type: none"> • <i>Optional.</i> Omit leading zeros in each 2-byte hex value. • :: means a single contiguous sequence of all zero 2-byte hex values. However, :: is permitted only one time per address. For example, the following three IPv6 address notations are equivalent: 2001:0D88:0000:0000:0008:0800:200C:417A 2001:d88:0:0:8:800:200c:417a 2001:d88::8:800:200C:417a • For the right-most 32-bits, IPv4 dotted-decimal notation can replace the pair of 2-byte hex values. For example, the following two IPv6 address notations are equivalent: 2001:D88::5efe:10.7.150.201 2001:D88::5efe:a07:96c9

Discovery Seed Definition , continued

Attribute	Definition																							
	<div><h3>Types of IPv6 Addresses</h3><table><thead><tr><th>IPv6 Address Range</th><th>Explanation</th></tr></thead><tbody><tr><td>0:: to 1fff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>unassigned or reserved</td></tr><tr><td>2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>global unicast address¹</td></tr><tr><td>fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff</td><td>unique local address²</td></tr></tbody></table><p>The IP addresses in the following table cannot be used as Discovery Seeds or Auto-Discovery Hints. NNMi still Discovers and Monitors these addresses within the context of a Node, but NNMi does not gather information about neighbors from these addresses.</p><h3>Invalid IP Addresses for Discovery Seeds or Auto-Discovery Hints</h3><table><thead><tr><th>IPv4 Address Range</th><th>IPv6 Address Range</th><th>Explanation</th></tr></thead><tbody><tr><td>0.*.*.*</td><td>not applicable</td><td>Reserved IP addresses</td></tr><tr><td>0.0.0.0</td><td>::0</td><td>Any Local (listen) address</td></tr><tr><td>127.*.*.*</td><td>::1</td><td>Loopback addresses</td></tr><tr><td>not applicable</td><td>fe80::*:*:*:*</td><td>IPv6 link-local address³</td></tr></tbody></table></div>	IPv6 Address Range	Explanation	0:: to 1fff:ffff:ffff:ffff:ffff:ffff:ffff	unassigned or reserved	2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff	global unicast address ¹	fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff	unique local address ²	IPv4 Address Range	IPv6 Address Range	Explanation	0.*.*.*	not applicable	Reserved IP addresses	0.0.0.0	::0	Any Local (listen) address	127.*.*.*	::1	Loopback addresses	not applicable	fe80::*:*:*:*	IPv6 link-local address ³
IPv6 Address Range	Explanation																							
0:: to 1fff:ffff:ffff:ffff:ffff:ffff:ffff	unassigned or reserved																							
2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff	global unicast address ¹																							
fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff	unique local address ²																							
IPv4 Address Range	IPv6 Address Range	Explanation																						
0.*.*.*	not applicable	Reserved IP addresses																						
0.0.0.0	::0	Any Local (listen) address																						
127.*.*.*	::1	Loopback addresses																						
not applicable	fe80::*:*:*:*	IPv6 link-local address ³																						

¹(2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff) A publically routable IPv6 unicast address, used for communication between nodes anywhere on the internet. The first part of the address is a global routing prefix in the 2000::/3 address space for your organization (assigned by the Internet Service Providers). The complete host address can either be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

²(fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff) A privately routable IPv6 unicast address used only for communication between nodes within your organization. The unique local addresses cannot be routed to the public internet. The address consists of a routing prefix in the fd00:/8 address spaces, assigned locally by your organization. And the full host address might be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

³A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

Discovery Seed Definition , continued

Attribute	Definition		
	Invalid IP Addresses for Discovery Seeds or Auto-Discovery Hints, continued		
	IPv4 Address Range	IPv6 Address Range	Explanation
	224-239.*.*.*	not allowed (ff00:: to ffff:ffff:ffff:ffff:ffff:ffff:ffff:ffff)	multicast address ¹
	255.255.255.255	not applicable	Broadcast address
Initial Discovery Tenant	For the Initial Discovery Tenant setting, do one of the following: <ul style="list-style-type: none">• Leave this attribute empty (blank). NNMi assigns each Node to the <i>Default Tenant</i> (and whichever Initial Discovery Security Group attribute value is currently assigned to the Default Tenant).• <i>Optional</i>. Assign a Tenant to a particular seed before discovery. See "Configure Tenants" on page 213 and "About Security Groups" on page 582 for more information.		
Notes	Provide any additional information about this discovery seed that would be useful to you or your team. Type a maximum of 1024 characters. Use any combination of alpha-numeric characters, multibyte characters (such as Chinese and Japanese), spaces, punctuation, and special characters (~ ! @ # \$ % ^ & * () _ + -).		

Examine Discovery Results

When verifying discovery, you can do any of the following tasks:

Check Initial Progress of Discovery	298
Node Discovery State Check	298
Verify Success of Discovery Seeds	299
Discovery Seed Results	299
Examine Discovery Inventory	303
Examine Layer 2 Discovery Results	303

¹Used to identify a group of hosts joined into a group. IPv4 multicast addresses are in the range 224.0.0.0 to 239.255.255.255 and IPv6 multicast addresses have the prefix ff00::/8.

Troubleshooting Layer 2 Connections	305
Examine Layer 3 Discovery Results	306

Check Initial Progress of Discovery

During initial NNMi discovery of your network, you can check Spiral Discovery's progress in the following ways:

- Click **Help** → **System Information** (for more information see [Displaying Information About NNMi](#)):
 - Navigate to the **Database** tab to find the real-time list of discovery's progress.
 - Navigate to the **State Poller** tab to see a report of the health of the State Poller Service.
- To see state of discovery for a node, see "[Node Discovery State Check](#)" below.
- NNMi administrators can use the command line on any NNMi management server to generate a report about NNMi health. See the [nnmhealth.ovpl](#) Reference Page for more information.


Check this several times during a one hour period. The numbers in the Nodes, SNMP agents, Interfaces, IP addresses, and Layer 2 Connections fields stabilize when initial discovery is complete

Note: If you configure one or more Auto-Discovery Rules and you get unexpected results, check your ordering numbers. See "[Configure Auto-Discovery Rules](#)" on page 236 for more information.

Node Discovery State Check

You can verify the current discovery state for a node.

To see the current Discovery State for a node:

1. Navigate to a **Node** form.
 - a. From the workspaces navigation panel, select the workspace of interest. For example,  **Inventory**.
 - b. Select the node view of interest. For example **Nodes**.
 - c. Select the row representing the configuration you want to see.
2. Locate the **Discovery State** attribute (in the Discovery section on the left side of the form).


Possible values include:

- **Newly Created** – Indicates the node and its IP addresses are in the NNMi database, but further information needs to be collected before state and status are determined.
- **Discovery Completed** – Indicates that discovery gathered all required information for the node.
- **Rediscovery in Process** – Indicates discovery is updating the information collected for the node.

Verify Success of Discovery Seeds

The discovery seeds provide the starting point for discovery.


To verify that each discovery seed was successfully discovered:

1. Navigate to the **Seeds** view.
 - From the workspace navigation panel, select the  **Configuration** workspace.
 - Expand **Discovery**.
 - Select **Seeds**.
2. Check the value in the Discovery Seed Results column on each row of the table. A value of **Node Created** indicates the successful discovery of each discovery seed. See "[Discovery Seed Results](#)" below for the meaning of other values and how to correct discovery problems.

Discovery Seed Results

When you add a discovery seed, the Discovery Service immediately tries to discover it (without waiting until the next regularly scheduled [discovery interval](#)). If discovery is not successful, NNMi tries again 10 minutes later, and continues trying. The time between each try is doubled until it reaches 1 week or equals your current discovery interval.

To see the current discovery results for each specified discovery seed:

1. Navigate to the **Seeds** view
 - From the workspace navigation panel, select the  **Configuration** workspace.
 - Expand **Discovery**.
 - Select **Seeds**.
2. The table lists each discovery seed and the result that NNMi gathered from the discovery seed. Check the value in the **Discovery Seed Results** column on each row of the table.

Discovery Seed Results Values

Discovery Results	Description
New seed	You just entered a new discovery seed. When discovery begins, Discovery Results changes to "In progress". If the "New seed" value does not change, check to see if the Discovery Service needs to be restarted, see "Verify that NNMI Services are Running" on page 91 .
In progress	Discovery is in progress.
Node created	<p>The discovery seed is successfully discovered and a new Node is created in the database.</p> <p>When NNMI first discovers a seeded node, the <i>seed address</i> (provided by the NNMI administrator) is used for initial SNMP/ICMP communication. After NNMI builds an inventory of all IP addresses associated with the node (see "What Information Is Collected?" on page 196), NNMI follows a set of rules to determine which address is the best choice for each node's Management Address (see "Configure Default SNMP, Management Address, and ICMP Settings" on page 130). NNMI then uses the Management Address for all communication with the node.</p>
Node created (non-SNMP device)	<p>The hostname or IP address you provided is a non-SNMP device. The Node was discovered and added to the database, but no SNMP information is available because no SNMP agent responded.</p> <p>If this result is unexpected, the device might currently be down. Initiate an on-demand discovery poll using Actions → Polling → Configuration Poll</p> <p>Click here for more information. Or try the following:</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: You can also right-click any object in a table or map view to access the items available within the Actions menu.</p> </div> <p>Check whether the IP address is accessible</p> <ol style="list-style-type: none"> 1. Type the following command to verify that the address is accessible: <code>ping <nodename></code> <p>Check the Access Control List</p> <ol style="list-style-type: none"> 1. Access the Node, and open the Access Control List (ACL). 2. Verify that the NNMI management server address is in the list. <p>Ensure that SNMP is working</p> <ol style="list-style-type: none"> 1. Use the nnmsnmpwalk.ovpl command. Type the following to verify that the address has an SNMP agent. Supply one specific MIB variable to limit network traffic to one object rather than requesting all possible SNMP values.

Discovery Seed Results Values, continued

Discovery Results	Description
	<p>For example, use the VendorID prefix:</p> <p>SNMPv1 or SNMPv2c: <code>nnmsnmpwalk -c <communityString> <nodename or IP address> <VendorID></code></p> <p>SNMPv3: <code>nnmsnmpwalk -c <v3u> <UserName> <VendorID></code></p> <ol style="list-style-type: none"> If the nnmsnmpwalk.ovpl fails: <ol style="list-style-type: none"> Use telnet to check the device's SNMP configuration to verify that SNMP is enabled. Verify that the address of the NNMi management server is listed in the SNMP Agent's Access list. <p>Check your communication configuration</p> <ol style="list-style-type: none"> Verify that SNMP communication is enabled for this device: "Configuring Communication Protocol" on page 129. Verify that the device has a properly configured SNMPv1 or SNMPv2c <i>read community string</i>, or that the device has a properly configured SNMPv3 USM security setting. After you correct the problem that caused NNMi to specify the seed as a non-SNMP device, NNMi updates the Node record during the next discovery cycle. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: The Discovery Results value does not change, because NNMi makes only one attempt to contact each discovery seed. However, everything is working properly once the Communication Configuration settings are corrected.</p> </div>
Node not created (DNS name resolution failed)	The Domain Name System (DNS) protocol could not match the hostname you provided for this discovery seed with a valid IP address.
Node not created (duplicate seed)	The address or hostname you provided is a Node that already exists in the database.

Discovery Seed Results Values, continued

Discovery Results	Description
Node not created (IPv6 disabled)	<p>(<i>NNMi Advanced</i>) The address you provided is an IPv6 address. The hostname you provided has only IPv6 addresses.</p> <p>Check the following:</p> <ul style="list-style-type: none"> • Are you using NNMi Advanced (required for IPv6 support)? • Did your NNMi Administrator disable NNMi Advanced's IPv6 feature? See the "Configuring NNMi Advanced for IPv6" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.
(<i>NNMi Advanced</i>) Node not created (IPv6 link local address is invalid seed)	<p>The address you provided is an IPv6 link-local address¹, or the hostname you provided has only one address (an IPv6 link-local address). IPv6 link-local addresses cannot be used as seeds.</p>
Node not created (license exceeded)	<p>Discovery rejected this discovery seed because the number of devices previously discovered reached your licensed capacity limit. See "Extend a Licensed Capacity" on page 1605.</p>
Failed	<p>Contact with this discovery seed failed due to an internal NNMi error. The problem might be related to discovery or to a system wide issue, such as running out of memory or having trouble with database access. Check the discovery log file (see "Verify that NNMi Services are Running" on page 91 and "About Environment Variables" on page 86 for more information):</p> <ul style="list-style-type: none"> • Windows: <code>%NnmDataDir%\log\nnm\nnm.0.0.log</code> • Linux: <code>\$NnmDataDir/log/nnm/nnm.0.0.log</code>

Related Topics:


["Specify Discovery Seeds" on page 287](#)

¹A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

Examine Discovery Inventory

The best method for examining your discovered inventory depends on how you configure discovery.

To examine your Discovery Inventory:

1. In the **Workspace** navigation panel, open the  **Inventory** workspace.
2. Select the **Nodes** view.
3. Verify that each important Node is listed.
4. Select the **IP Addresses** view.
5. Verify that each IP address that you identified as a [discovery seed](#) is listed.
6. Verify that the IP addresses you expect to see are visible (based on any Auto-Discovery Rule configurations - see ["Configure Discovery "](#) on page 219 and ["Configure an Excluded IP Addresses Filter"](#) on page 274).
7. To check on the current discovery state for a particular node, see ["Node Discovery State Check"](#) on page 298.

Note: If you configure one or more Auto-Discovery Rules and you get unexpected results, check your ordering numbers. See ["Configure Basic Settings for the Auto-Discovery Rule"](#) on page 240 for more information.

Related Topics



[Using the IP Addresses View](#)

[Using the Nodes View](#)


Examine Layer 2 Discovery Results

Layer 2 represents your network's physical connections and LAN switch traffic routes. For more information, see ["Configure Tenants"](#) on page 213.

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Note: A cloud  icon (in prior NNMi releases, the  icon) on the NNMi map may represent a missing node. Consider using a router command such as Cisco `show cdp neighbors` to help identify those missing Nodes. Check the Access Control List (ACL) configurations in your network environment to fix the problems.

To examine Layer 2 inventory and connectivity results:

1. In the **Workspace** navigation panel, open the  **Inventory** workspace.
2. Select the **Nodes** view.
3. Select the row representing the node of interest.
4. Select **Actions** → **Layer 2 Neighbor View**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

5. Use the **Number of Hops** field to expand the area shown on the map.


Number of Hops:

6. Examine your network connectivity to ensure it is as expected. See ["Add or Delete a Layer 2 Connection" on page 314](#) if changes are required.

Note: If you configure one or more Auto-Discovery Rules and you get unexpected results:


- Check your ordering numbers. See ["Configure Basic Settings for the Auto-Discovery Rule" on page 240](#) for more information.
- Check the Layer 2 protocol configuration at each end of the problem connection. See ["Troubleshooting Layer 2 Connections" on the next page](#).
- Check each Node's assignment for Tenant. The Tenant assignment can be easily changed, see ["Change Tenant Assignment for a Node" on page 321](#). Subnets are calculated independently within each Tenant.

To examine VLAN results:

1. In the **Workspace** navigation panel, open the  **Inventory** workspace.
2. Select the **VLANs** view.
3. Double-click the row representing the VLAN of interest.
4. Verify that the list includes all nodes and ports assigned to this VLAN.

Note: If you configure one or more Auto-Discovery Rules and you get unexpected results, check your ordering numbers. See ["Configure Basic Settings for the Auto-Discovery Rule" on page 240](#) for more information.

To examine Router Redundancy Group results:

1. In the **Workspace** navigation panel, open the  **Inventory** workspace.
2. Select the **Router Redundancy Groups** view.
3. Use the Tenant assignment column to Sort the view, and verify that all members of each group are assigned to the same Tenant.
4. To correct any problems, change the Tenant assignments, see ["Change Tenant Assignment for a Node" on page 321](#).

Related Topics

[Using the Layer 2 Neighbor View](#)

[Using the Layer 3 Neighbor View](#)

Troubleshooting Layer 2 Connections

If you get unexpected results for Layer 2 Connections in your network environment, review the following information.

A network device's interfaces can be configured with proprietary Layer 2 *discovery protocols*, instead of or in addition to the industry standard LLDP (see the list of Topology Source protocols in [Layer 2 Connection Form](#)).

By default, NNMi checks the interface for standard LLDP and vendor-specific IEEE 802 Layer 2 protocol. NNMi uses data from both protocols to calculate the Layer 2 Connection, but by default prefers the data provided through LLDP.

Note: Forwarding Database (FDB) information can cause NNMi to establish wrong Layer 2 Connections in the following cases:

- When the FDB is configured as cache and contains obsolete data.
- In network environments with hardware from a variety of vendors, when each vendor generates different and sometimes conflicting FDB data.

Optional: NNMi administrators can configure Spiral Discovery to ignore the FDB data from one Node Group when calculating Layer 2 Connections (the FDB data is still included in other calculations).

(*NNMi Advanced - Global Network Management feature*) NNMi must read the Forwarding Database (FDB) tables from Ethernet switches within the network before accurate communication paths between these network devices can be calculated. Because the FDB data is involved, NNMi can produce different results on a Regional Manager as opposed to the Global Manager.


If NNMi discovers more than one IEEE 802 Layer 2 protocol being used by a particular device's interface, the Device Profile's setting controls NNMi's protocol preference:

☒ **Prefer LLDP** = Enabled: NNMi gives priority to the LLDP data.

☐ **Prefer LLDP** = Disabled: NNMi gives priority to the vendor-specific IEEE 802 Layer 2 protocol data.

NNMi cannot detect accurate Layer 2 Connections under the following circumstances:

NNMi does not support the following scenario. Switch-56 has interfaces with one Layer 2 protocol enabled. The devices at the other end of Switch-56's Layer 2 Connections have a different Layer 2 protocol enabled:



NNMi detects a false connection directly from Router-1 to Switch-27.


To fix the problem, configure both sides of each Layer 2 Connection exactly the same (both interfaces enable either the same protocol or dual protocols).

See also "[Configure Layer 2 Connection Source](#)" on page 228.

Examine Layer 3 Discovery Results

Layer 3 represents your network's router traffic.

To examine Layer 3 inventory results:

1. In the **Workspace** navigation panel, open the  **Inventory** workspace.
2. Select the **Nodes** view.
3. Select the row representing the router of interest.
4. Select **Actions** → **Layer 3 Neighbor View**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

5. Use the **Number of Hops** field to expand the area shown on the map.

Number of Hops:

6. Examine your network connectivity to ensure it is as expected. If changes are required, try the following:
 - Use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

- Manually add or delete the connection. See ["Add or Delete a Layer 2 Connection" on page 314](#).
- Verify that the addresses on each end of the connection are not listed in the Excluded IP Address filter. See ["Configure an Excluded IP Addresses Filter" on page 274](#).

Note: If you configure one or more Auto-Discovery Rules and you get unexpected results, check your ordering number for each rule. See ["Configure Auto-Discovery Rules" on page 236](#) for more information.

Related Topics

[Using the Layer 2 Neighbor View](#)

[Using the Layer 3 Neighbor View](#)

Keep Your Topology Accurate

For suggestions see the following topics:

Delete Nodes	308
Delete Discovery Seeds	310
Detect Interface Changes	311
Add or Delete a Layer 2 Connection	314
Start Discovery On-Demand	320
Change Tenant Assignment for a Node	321

With NNMi, discovery is ongoing. After initial discovery, NNMi checks periodically to ensure that the maps accurately reflect the state of your network. By default, NNMi uses the following methods to keep network information accurate and up-to-date:

Spiral Discovery. NNMi tracks MAC addresses in addition to IP addresses so that NNMi knows when devices move from place to place in your network environment. See ["What Information Is Collected?" on page 196](#).

Scheduled Rediscovery. Rediscovery occurs automatically at the interval you define. See ["Configure Schedule Settings" on page 230](#) for more information about setting the discovery schedule.

Optional: Auto-Discovery (Default Tenant only). If you choose to use Auto-Discovery, NNMi uses information gathered from neighboring devices on your network to discover all devices connected to your network. See ["Configure Basic Settings for the Auto-Discovery Rule" on page 240](#).

Delete Nodes

Tip: To configure NNMi to automatically delete unresponsive nodes, see ["Configure Whether to Delete Unresponsive Nodes" on page 233](#).

To ensure that NNMi never discovers a particular Node in the future, change the Communication Configuration settings, see ["Configuring Communication Protocol" on page 129](#).

Sometimes it is useful to delete Nodes. For example:

- Remove any nodes that are no longer being used in the network.
- Avoid reaching the NNMi license limit for number of managed Nodes by deleting less important Nodes.
- When non-SNMP addresses that had the same DNS hostname are changed to have separate DNS hostnames, NNMi must completely rediscover the non-SNMP nodes to correctly update the database objects (for example, node, interface, address, connection, and incidents).

Note: If you delete a Node with many interfaces and VLANs, you might see an error message indicating that the Node could not be deleted. This means the database was busy with discovery. Try again between discovery cycles.


If a deleted Node is one of your seeds, delete that seed from the Discovery Seeds table as well. See ["Delete Discovery Seeds" on page 310](#).

To understand the results of deleting a Node, [click here for more information](#).

- NNMi cleans up the database by deleting the following objects:
 - Any objects associated with the deleted Node (for example, all of that node's interfaces and IP addresses).
 - Any related objects that are empty after deleting the Node (for example, subnets).
 - Any connections with only zero or one end points after deleting the Node.
 - The History of the Node object and all related objects.
- The time required for NNMi to finish deleting depends on the number of objects or related objects being deleted.
- During future discovery cycles, if the deleted Node meets the criteria for an Auto-Discovery Rule and appears in a monitored router's ARP cache, NNMi adds the Node back into the NNMi database during the next discovery cycle. To prevent this, create an Excluded IP Addresses filter for the addresses (see ["Configure an Excluded IP Addresses Filter" on page 274](#)).

- During future monitoring cycles, NNMi polls only objects currently in the database.
- Each Incident associated with the deleted Node is modified in the following ways, but not deleted from the NNMi database:
 - The **Status** attribute changes to **Closed**.
 - The **Correlation Notes** indicate the deletion of the associated node, interface, or address.
 - The **RCA State** attribute changes to **FALSE**.

Note: Incidents generated from SNMP traps (received from the deleted Node) appear in the Incident views, but remain unresolved.

- If you are viewing a Node that has recently been deleted by another user, the deleted Node appears as a transparent icon on the map until the map is refreshed using the  **Refresh** icon. After **Refresh**, the deleted node is removed from the map. NNMi does not automatically refresh the connectivity or set of nodes in a map view, except on the **Initial Discovery Progress** and **Network Overview** maps.

A subset of NNMi users can delete nodes from a table view, map view, or Node form (depending on the assigned NNMi Role).


Note: By default NNMi Administrators can delete nodes. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to delete nodes. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Delete Node".

To delete one or more nodes (maximum 20 at one time):

1. [Unmanage the nodes you want to delete.](#)
 - a. In a table view, press Ctrl-Click to select each row that represents a node you want to unmanage.
 - b. Select **Actions** → **Management Mode** → **Unmanage**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

- c. Wait until the Status=*No Status* for each of the following objects:
 - Each Node to be deleted
 - Each Node's Interfaces, IP Addresses, Cards, Ports, and VLAN Ports
2. Do one of the following:

- **Table views:** Press Ctrl-Click to select each row that represents the objects of interest, and click the  Delete icon. Each selected node is deleted from the NNMi database and removed from the current view.
- **Map views:** click the map symbol representing the node you want to delete, and click **File** → **Delete Node**. The node is deleted from the NNMi database and removed from the current view.
- **Node form:** select **File** → **Delete Node** and in the confirmation dialog, click **OK**. The form is automatically closed after NNMi deletes the Node.

Note: If the delete fails, use the [nnmnodedelete.ovpl](#) command. Wait for the command to complete.

To delete any number of nodes:

Use the `nnmnodedelete.ovpl` command. See the [nnmnodedelete.ovpl](#) Reference Page.

Related Topics

[Using Table Views](#)



[Using Map Views](#)

Delete Discovery Seeds

There are two ways to delete discovery seeds from the NNMi Discovery configuration and the NNMi database.

Note: If you remove a Discovery Seed from Discovery Configuration, the corresponding node is not deleted from the topology database. See ["Delete Nodes" on page 1635](#) for information about removing the entire node record from the topology database.

To delete seeds using the Discovery Configuration view:

1. Navigate to the **Seeds** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand **Discovery**.
 - c. Select **Seeds**.
2. To delete one or more discovery seeds, press Ctrl-Click to select each row that represents a node you want to delete.
3. Click the  Delete icon.

To delete any number of seeds at one time from the command line:

For the alternate method of configuring Discovery Seeds, see the [nnmseedit.ovpl](#) Reference Page.

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of `-u` and `-p`). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See "[Set Up Command Line Access to NNMi](#)" on page 653 for more information.

Detect Interface Changes

During each Spiral Discovery cycle, NNMi responds to Interface changes as follows:

1. NNMi updates the attribute value of the current Interface object if one (*and only one*) of the following attributes change:
 - `ifIndex` or `IfAlias` or `ifSpeed`
2. NNMi creates a new Interface object and deletes the old Interface object if any of the following criteria are met:
 - a. At least one of these attributes change: `ifName`, `ifDescr` (descriptions), `ifType`, or Physical Address (Mac address, Media Access Control address).
 - b. More than one of these attributes change: `ifIndex` or `IfAlias` or `ifSpeed`.
 - c. One or more attributes from the list of both criteria 1 & 2 change.

Note: If using [nnmconnect.ovpl](#) configuration files, any connection settings configured for the deleted Interface would be evaluated for the new Interface object's current attribute settings.

To troubleshoot interface changes in your network environment, do one of the following:

- For immediate results, navigate to a Node view and select one of the problem devices.

Click **Actions** → **Polling** → **Configuration Poll** to instruct Spiral Discovery to rediscover the Node, updating information about interfaces within that device.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Open the Node form for the device and verify that the list of interfaces is correct.

- Wait until the next regularly scheduled Discovery or Monitoring cycle (controlled by the Interval settings the NNMi administrator specifies in the Discovery and Monitoring configuration forms).

NNMi administrators use multiple configuration settings to control how NNMi detects interface changes. To troubleshoot issues, verify the current settings for the following:

1. *Prerequisite:* To detect interface changes, the **Configuration > Monitoring > ☒ Enable Interface Fault Polling** must be enabled. This setting is available at three levels (see ["Configure NNMi Monitoring Behavior" on page 387](#) for more information):

- Interface Settings tab > Interface Settings form > Fault Monitoring section
- Node Settings tab > Node Settings form > Fault Monitoring section
- Default Settings tab: Default Fault Monitoring section

If enabled and the NNMi State Poller detects a change, NNMi does the following:

- Generates a request for Spiral Discovery to rediscover the Node (checking for any changes). If NNMi is busy gathering other information, it may take a while for this request to get to the top of the queue. If NNMi is not busy, the results might seem immediate.
- Suspends monitoring of that node until NNMi finishes gathering the updated information about the Node itself (or for 30 minutes maximum).

2. **Configuration > Monitoring > Monitoring Configuration's Default Settings tab, Default Change Detection Monitoring block of attributes.** If **Number of Interfaces (ifNumber) Polling ☒** is enabled, NNMi does the following:

- Polls for the *total number of interfaces* within the Node by requesting an SNMP response to MIB II ifNumber.
- NNMi compares the answer for *total number of interfaces* within the Node, to the previous answer from that Node's SNMP agent.
- If the number has changed, Spiral Discovery rediscovers the Node.
- NNMi suspends fault, performance, and status monitoring of that Node until updated information about hardware is gathered.

See ["Default Settings for Monitoring" on page 393](#) and ["Node Settings for Monitoring" on page 443](#) for more information.

Tip: This setting detects whether the *total number of interfaces* within the node has increased or decreased. To detect whether the actual number assigned to particular interfaces has changed (the ifIndex value), continue with the next step.

3. For each node vendor/make/model (RFC 1213, MIB-II, sysObjectID), the NNMi administrator chooses which interface MIB variable the NNMi State Poller queries to detect interface changes.

Configuration > Device Profiles: On the Advanced tab, the **Interface Reindexing Types** attribute instructs NNMi to do the following (see [Device Profile Form](#) for more information about the four SNMP values involved in this calculation).

Interface Reindexing Types

MIB II Variable Used to Detect a Change	How State Poller Detect Changes
<p>ifIndex value</p> <div> <p>Note: Note: Use ifIndex only for manufacturers/models that maintain a static ifIndex list.</p> </div>	<p>If an SNMP agent's previous response for SNMP ifIndex values (numbers assigned to each interface) does not match the current response, State Poller requests that NNMi gather new information about the interfaces within the Node.</p> <p>For example, someone installs or removes interfaces from a device in your network:</p> <ul style="list-style-type: none"> ■ Use this MIB-II IfIndex setting for devices that maintain a static list of MIB-II IfIndex numbers. <ul style="list-style-type: none"> ○ When interfaces are added - MIB-II IfIndex numbers are added to the end of the current list of interfaces contained in that device. ○ When interfaces are removed - the MIB-II IfIndex numbers previously used by those interfaces are dropped from the list. ■ Do not use this MIB-II IfIndex setting for devices that reset all MIB-II IfIndex numbers for the group of interfaces contained in that device each time a change occurs. Each manufacturer has a different strategy for identifying each interface and detecting when an existing interface is simply assigned to a different MIB-II IfIndex number or an interface is removed. <div> <p>Caution: When you choose ifIndex, NNMi can detect when a particular number no longer exists (static assignments). However, this choice might not detect interface renumbering (a value now being used by a different interface). To detect this type of interface renumbering, choose any combination of ifName and ifDescr and ifAlias settings, below.</p> </div>
ifName value	<p>Based on the ifIndex number, compares the ifName value on the interface with the previously discovered ifName value. If changes in this name/number relationship are detected, State Poller requests NNMi to gather new information about the Node's interfaces.</p>

Interface Reindexing Types , continued

MIB II Variable Used to Detect a Change	How State Poller Detect Changes
ifDescr value	Based on the ifIndex number, compares the ifDescr value on the interface with the previously discovered ifDescr value. If changes in this description/number relationship are detected, State Poller requests NNMi to gather new information about the Node's interfaces.
ifAlias value	Based on the ifIndex number, compares the ifAlias value on the interface with the previously discovered ifAlias value. If changes in this alias/number relationship are detected, State Poller requests NNMi to gather new information about the Node's interfaces.
Combination of ifName or ifDescr values	Based on the ifIndex number, compares the ifDescr and ifName values on the interface with the previously discovered values. If changes are detected, State Poller requests NNMi to gather new information about the Node's interfaces.
Combination of ifName or ifDescr or ifAlias values	Based on the ifIndex number, compares the ifName and ifDescr and ifAlias values on the interface with the previously discovered values. If changes are detected, State Poller requests NNMi to gather new information about the Node's interfaces.

Tip: Open any Node form and navigate to the Basics' **Device Profile** link. You can open the associated Device Profile to see the current setting.

4. The next time each Node is rediscovered, if something has changed, Spiral Discovery compares the current ifIndex value against the MAC address to determine whether an interface was added, deleted, or renumbered.

Add or Delete a Layer 2 Connection

Layer 2 Connections are only permitted between the Default Tenant, and other Tenants (never between two non-Default Tenants). For more information, see ["Configure Tenants" on page 213](#).

If your network management domain includes ATM, Frame Relay, or MPLS¹ links between wide area networks (WANs), you might need to use the connection editor to show the links in the Layer 2 Neighbor View maps within NNMi. For MPLS, you can provide multiple connections between two nodes.

See also the Schedule Settings for Spiral Discovery: ["Configure Whether to Delete Unresponsive Nodes" on page 233](#) and ["Configure Whether to Delete Layer 2 Connections" on page 235](#).

Subnet Connection Rules

¹Multiprotocol Label Switching

Subnet Connection Rules are ideal for multiple situations. See "[Consider IPv4 Subnet Connection Rules](#)" on page 200 for more information.

NNMi uses Subnet Connection Rules to detect connections between interfaces associated with IPv4 addresses that *do not respond* to Layer 2 *discovery protocols* (see the list of Topology Source protocols in [Layer 2 Connection Form](#)). Subnet Connection Rules take priority over the Layer 2 discovery protocol results. For special cases, you can override a Subnet Connection Rule by using the Connection Editor command line tool, see [nnmconnectit.ovpl](#) for more information.

NNMi provides a variety of predefined Subnet Connection Rules. For ideas, see "[Subnet Connection Rules Provided by NNMi](#)" on page 267.

Connection Editor (to add or delete connections)

In the Inventory workspace > Layer 2 Connections view, you can see a list of connections. No Delete action is available in the Layer 2 Connections view.

Use the [nnmconnectit.ovpl](#) command line tool to do the following:

- delete a connection data
- add connection data
- instruct NNMi to ignore certain connection data

The `nnmconnectit.ovpl` command is used to generate a template XML file (shown in the following example). For each connection to be added or deleted, you provide information about the node and interface at both ends of the connection. Multiple `<connection>` elements are permitted within the template XML file.

```
<connectionedits>
  <connection>
    <operation>add or delete</operation>
    <node>node Name, Hostname or management IP address</node>
    <interface>ifName, ifAlias, ifDescr or ifIndex</interface>
    <node>node Name, Hostname, or management IP address</node>
    <interface>ifName, ifAlias, ifDescr or ifIndex</interface>
  </connection>
</connectionedits>
```

To add or delete a connection:

1. For the devices at both ends of the connection, gather the data required to identify the device and interface (see [table](#)).
2. On the NNMi management server, at the command line, generate a connections template file using either `add` to create an `add.xml` template file or `delete` to create a `delete.xml` template file.

In the following example, NNMi creates an `add.xml` file:

```
nnmconnectit.ovpl -t add
```

Note: If you specify `add`, NNMi creates the template file named `add.xml`. If you use `delete`, the template file is named `delete.xml`.

3. Open the template file in a text editor and fill in the correct information for each node and interface.
4. On the NNMi management server, at the command line, load the new connection information into the NNMi database:
`nnmconnect.ovpl -f <add|delete>.xml`

For example, to load the `add.xml` template file, enter:

```
nnmconnect.ovpl -f add.xml
```

5. Open the Layer 2 Neighbor View map and verify the connection changes.

Required Layer 2 Connection Attributes in the Connection Editor File

Attribute	Description
operation	Specify whether the connection is to be added or deleted.
node	<p>Identify the node using any of the following <i>case-sensitive</i> values:</p> <ul style="list-style-type: none">• node Name• Hostname (<i>case-sensitive</i>) <p>NNMi follows a set of rules to dynamically generate the value stored in the NNMi database for each Node's Hostname. Click here for details.</p> <ul style="list-style-type: none">■ If the Node supports SNMP, NNMi requests the Hostname using the IP Address of the associated SNMP agent (the Management Address attribute value on the Node form). <p>When the NNMi administrator chooses Enable SNMP Address Rediscovery <input checked="" type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none">○ If the SNMP Agent does not respond, NNMi checks for another Management Address to request the Hostname, and the Hostname could change.○ If the SNMP Agent associated with the node changes, the Management Address and Hostname could change. <p>When the NNMi administrator disables Enable SNMP Address Rediscovery <input type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none">○ If the SNMP Agent does not respond, NNMi uses the previously gathered Management Address attribute value to request the Hostname.

Required Layer 2 Connection Attributes in the Connection Editor File , continued

Attribute	Description
	<ul style="list-style-type: none"> ◦ If the SNMP Agent associated with the node changes, NNMi uses the previously gathered Management Address attribute value to request the Hostname. ■ If the Node does not support SNMP, no Management Address is available. NNMi requests a Hostname starting with the lowest IP Address associated with the node (a Discovery Seed value or an IP address value gathered from a neighboring device). NNMi uses the first Hostname provided. The Hostname might change during a future discovery cycle. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:</p> <ul style="list-style-type: none"> ■ <code>nms-topology.properties</code> file settings: If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals. ■ <code>nms-disco.properties</code> file settings: The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals. </div> <ul style="list-style-type: none"> • management IP address <p>NNMi follows a set of rules to determine which address is the best choice as the node's Management Address. Click here for details.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: (NNMi Advanced) The NNMi administrator specifies whether NNMi prefers IPv4 addresses, IPv6 addresses, or dual-stack (both) when selecting the Management Address. See Configure Default SNMP, Management Address, and ICMP Settings.</p> </div> <ul style="list-style-type: none"> a. NNMi ignores the following addresses when determining which Management Address is most appropriate: <ul style="list-style-type: none"> ◦ Any address of an administratively-down interface.

Required Layer 2 Connection Attributes in the Connection Editor File , continued

Attribute	Description
	<ul style="list-style-type: none"> ○ Any address that is virtual (for example, VRRP¹). ○ Any IPv4 Anycast Rendezvous Point IP Address² or IPv6 Anycast address. ○ Any address in the reserved loopback network range. IPv4 uses 127/24 (127.*.*.*) and IPv6 uses ::1. ○ Any IPv6 link-local address³. <p>b. If the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi prefers the last-known Management Address (if any).</p> <p>c. If the Management Address does not respond and the NNMi Administrator specifies Enable SNMP Address Rediscovery in Communication Configuration, NNMi uses the Communication Configuration settings for <i>Management Address Selection</i>. The NNMi Administrator chooses the order in which NNMi checks the following:</p> <ul style="list-style-type: none"> ○ Seed IP / Management IP - If the NNMi Administrator configures a Seed, NNMi uses the Seed address (either a specified IP address or the DNS address associated with a specified hostname) only during initial Discovery. NNMi then requests the current Management Address (the address from which the node's SNMP Agent responds) and uses that IP address for all communication after initial discovery. ○ Lowest Loopback - If a node supports multiple loopback address⁴, NNMi queries each loopback addresses, starting with the lowest number. NNMi uses the loopback address with the lowest number from which the SNMP agent responds (for example, 10.16.42.197 is a lower number than 10.16.197.42).

¹Virtual Router Redundancy Protocol

²Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

³A non-routable IPv6 unicast address only used for communication with other nodes on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

⁴The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

Required Layer 2 Connection Attributes in the Connection Editor File , continued

Attribute	Description
	<ul style="list-style-type: none"> ○ Highest Loopback - If a node supports multiple loopback address¹, NNMi queries each loopback addresses, starting with the highest number. NNMi uses the loopback address with the highest number from which the SNMP agent responds. ○ Interface Matching - The NNMi Administrator chooses which interface MIB variable NNMi queries to detect changes. NNMi can use the following MIB-II attribute values: ifIndex, ifName, ifDescr, ifAlias, or a combination of these (ifName or ifDescr, ifName or ifDescr or ifAlias). NNMi searches current database entries for information about the interface in this order: index, alias, name, and description. If multiple IP addresses are associated with the interface, NNMi starts by querying the lowest IP address and selects the first responding address in ascending order. <p>d. If no response, NNMi queries any remaining IP addresses in the node's IP address inventory, starting with the lowest number. NNMi uses the address with the lowest number from which the SNMP agent responds.</p> <p>e. If no response, NNMi checks for any Mapped Address configured for one of the currently known addresses (see the Mapped Address column in the Custom IP Addresses view).</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The address represents a <i>static</i> Network Address Translation (NAT) pair's <i>external IP address</i> from the internal/external IP address pair. NNMi Administrators configure these pairs using the Overlapping IP Address Mapping form. NNMi uses this list of addresses starting with IPv4 from low to high, then IPv6 from low to high.</p> </div> <p>f. If no response, NNMi might be configured to repeat the sequence using SNMPv1, SNMPv2c, or SNMPv3 in the order specified by the NNMi administrator (Communication Configurations <i>SNMP Minimum Security Level</i> settings).</p> <p>g. When all else fails, NNMi retains the last known Management Address (if any) and automatically changes the State of that SNMP Agent object to Critical.</p> <p>This process is repeated during each Spiral Discovery cycle, and the Management Address can change. For example, NNMi's inventory of addresses for the node expands, or the current Management Address does not respond to</p>

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

Required Layer 2 Connection Attributes in the Connection Editor File , continued

Attribute	Description
	SNMP queries due to network problems or node reconfiguration. The NNMi administrator can prevent changes to the management address using the Communication Configurations <i>Enable SNMP Address Rediscovery</i> or <i>Preferred Management Address</i> setting.
interface	Identify the interface using one or more of the following (MIB-II) values: <ul style="list-style-type: none">• ifName• ifAlias• ifDescr• ifIndex Note the following for ifIndex:<ul style="list-style-type: none">■ For interfaces in Non-SNMP nodes, always use the ifIndex value of 0 (zero).■ For interfaces in SNMP nodes, choose other MIB-II values to identify the interface because often automatic interface renumbering causes confusion. See "Detect Interface Changes" on page 311.

Start Discovery On-Demand

NNMi provides the [nnmnoderediscover.ovpl](#) command line tool for initiating discovery. This tool enables NNMi administrators to do the following:

- Run discovery of a subset of your network domain to get the most recent data without waiting for the next-regularly schedules discovery cycle.

For example: Use [nnmnoderediscover.ovpl](#) to immediately add newly deployed critical devices to the NNMi database without waiting for the next regularly-scheduled discovery cycle.

- Run discovery of your entire network on demand or using an automation script.
- Request updated discovery results from the Regional Managers in your network environment after restoring the Global Manager to a previous state.

(NNMi Advanced - Global Network Management feature) Any change to the Node's Management Mode setting is immediately sent from a Regional Manager (NNMi management server) to the Global Manager. (Changes to Management Mode for other objects are sent during the next Spiral Discovery cycle on the Regional Manager.)

Note: This tool can help you synchronize the Global Manager if for some reason the original information from the Regional Managers is lost from the Global Manager's database.

See [nnmnoderediscover.ovpl](#) for more details.

Change Tenant Assignment for a Node

After discovery, NNMi administrators can change the Tenant settings for any Node:

- Using the [nnmsecurity.ovpl](#) command to change multiple Nodes.
- Using the [Node form](#) to change one Node's setting.

Devices that belong to the Default Tenant can have Layer 2 Connections to any device in any Tenant. Devices within any Tenant *other than* Default Tenant can have Layer 2 Connections *only* to devices within the same Tenant or the Default Tenant.

Tip: Assign any infrastructure device that interconnects multiple NAT domains (such as a NAT gateway) to the Default Tenant. This ensures that NNMi displays the Layer 2 Connections your team and customers need to see.

Caution: Devices within the Default Security Group are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

To assign a Node to a different Tenant:

1. Open the Node's form:



Note: Until an NNMi Administrator defines at least one Tenant in addition to Default Tenant (provided by NNMi):

- The Tenant attribute does not appear on any Node form.
- The Tenant column does not appear in the [Nodes \(All Attributes\) view](#).

2. In the Tenant attribute, do one of the following:

The screenshot shows the 'Node' configuration window in NNMi. The 'Basics' tab is selected. The fields are as follows:



Field	Value
Name	node-name
Hostname	10.2.0.30
Management Address	10.2.0.30
Status	Major
Node Management Mode	Managed
Device Profile	hpRouter
Tenant	Default Tenant
Security Group	Default Security Group

- Select the drop-down list and choose a different Tenant.
- Select the  Lookup icon and select  New to create a new Tenant.

3. Click **Save and Close**.

Caution: Additional steps are now required:

- If the Node is currently a member of a Router Redundancy Group, NNMi creates duplicate Nodes. You must manually delete the record of this Node that is associated with the prior Router Redundancy Group/Tenant pair.
- If the Node was or is now participating in a *static* Network Address Translation domain, you must manually update any associated Overlapping IP Address Mapping. For more information:

4. *Optional.* Any seed configuration that assigned that Node to the old Tenant during initial discovery is now ignored by NNMi. Deleting the obsolete seed configuration is optional.
- Navigate to the **Seeds** view.
 - From the workspace navigation panel, select the  **Configuration** workspace.
 - Expand **Discovery**.
 - Select **Seeds**.
 - Select the row for the seed configuration that assigns that Node to the old Tenant, and click the  Delete icon (see ["Delete Discovery Seeds" on page 310](#) and ["Delete Nodes" on page 1635](#) for more information).

Chapter 7: Configure Device Profiles

You can modify the settings in the Device Profiles to fine-tune Spiral Discovery and the device symbols on the maps.

According to industry standards (RFC 1213, MIB-II), each combination of vendor, device type, and model number is assigned a unique SNMP system object ID (sysObjectID). For example, all Cisco 6500 series switches have the same sysObjectID prefix: .1.3.6.1.4.1.9.*


HP provides well over three thousand preconfigured Device Profiles, one for each known sysObjectID at the time NNMi released.



NNMi uses Device Profiles (which equate to sysObjectID) to control certain types of behavior:

- [Spiral Discovery](#) determines the closest matching device profile, and uses the device profile settings to control certain attribute values for the discovered device. The Device Profile also influences the following:
 - Auto-Discovery Rules can provide an sysObjectID list that expands the default discovery behavior (beyond routers and switches) or prevents troublesome device types from being discovered.
 - The Node Name value might be affected, depending on your choices, see ["Configure the Node Name Strategy" on page 223](#).
- When Node Groups are defined based on system object IDs, the [State Poller Service](#) monitors devices based on attribute values in the device profiles.
- Device Profile settings influence how State Poller detects renumbered interfaces. See ["Detect Interface Changes" on page 311](#).
- In [Map views](#), the background shape of map icons is determined by the Device Category. See [About Map Symbols](#) for an example of each available shape. There is also a [Force Device](#) attribute that enables category overrides in troublesome situations.

Tip: To quickly locate the device profile settings for a particular network device, sort or filter the Device Profiles view by clicking the heading for the Device Vendor, Device Model, or Device Category columns.

To access the device profile definition for a particular device type:

1. Navigate to the **Device Profile** view.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Select the **Device Profiles** view.
2. Do one of the following:


- To create a device profile, click the  New icon.
- To edit a device profile, click the  Open icon in the row representing the configuration you want to edit.

3. Modify the settings as needed:

Caution: When you make a change, NNMi must update all references to device profiles. This can take some time and slow down your system. Consider making this change during a slow time in your network environment.

- The [basic settings](#) Device Category attribute value modifies NNMi behavior for Spiral Discovery and map symbols.

Caution: If you make changes to a Menu Item provided by NNMi, those changes are at risk of being overwritten in the future. See [Author form](#) for important information.

- The [advanced settings](#) control NNMi behavior for Spiral Discovery and Node name selection. For example, instruct NNMi to treat a certain device type as a Router.
4. Click  **Save and Close**. NNMi applies your changes during the next regularly scheduled discovery cycle. To apply the changes immediately, use **Actions** → **Polling** → **Configuration Poll**. See [Using Actions to Perform Tasks](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Chapter 8: Creating Groups of Nodes or Interfaces

Groups of nodes or interfaces are used for a variety of purposes within NNMi. Use of these groups is optional.

- Use node and interface groups to create custom view filters that help your team quickly sift through data in the NNMi views and identify the most important information. See [Filter Views by Node or Interface Group](#).
- [Special Actions are available](#) for Node Groups and Interface Groups.
- Use Node Groups and Interface Groups to specify monitoring configuration settings. See ["Monitoring Network Health" on page 378](#). For example, configure a different health monitoring interval for each group.
- (NNMi Advanced - Global Network Management *feature*) On a Regional Manager, use Node Groups to limit the amount of data available to Global Managers in your network environment. See ["Regional Manager Configuration" on page 107](#) for more information.
- (NNM iSPI Performance) If you are using the NNM iSPI Performance for Metrics or NNM iSPI Performance for Traffic, control performance monitoring and provide report filters by Node Group – [click here for more information](#).

Tip: (NNM iSPI Performance for Metrics only) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.

Once Node Groups or Interface Groups are defined, you can reuse them within any context (view filtering and NNMi configuration settings) or you can configure them to be hidden from the view filter lists.

View Filter Possibilities

Filter	Available in NNMi views based on: Object Type						
	Incident	Node	Interface	IP Address	Card	Node Sensor	Physical Sensor
Node Groups "Create Node Groups" on the next page	x	x	x	x		x	x

View Filter Possibilities, continued

Filter	Available in NNMi views based on: Object Type						
	Incident	Node	Interface	IP Address	Card	Node Sensor	Physical Sensor
Interface Groups "Create Interface Groups" on page 356			x	x	x		

Create Node Groups



Node Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on the previous page](#) for more information.


You can create any number of Node Groups in addition to the ones that NNMi provides (see ["Node Groups Provided by NNMi" on page 372](#)).

To create Node Groups, use one or more of the following methods:

- ["Create Node Groups Using Filters or Hostname Lists \(Configuration: Node Groups\)" on the next page](#)
- ["Create Node Groups From the Actions Menu " on page 347](#)
- ["Add Nodes to a Node Group From the Actions Menu" on page 349](#)
- ["From the Command Line, Define Node Groups" on page 351](#)

To verify the contents of the current Node Group:

1. In the Node Group form, click  **Save**.
2. Select **Actions** → **Node Group Details** → **Preview Members (Current Group Only)**.
3. Click  Refresh to check for the most recent changes to Node Group contents.

Tip: To test the effects of your Node Group definition on Child Node Groups, in the Node Group form, select **Save**, then **Actions** → **Node Group Details** → **Show Members (Include Child Groups)**. NNMi displays the members of the current Node Group members as well as the members of each associated Child Node Group. Depending on the complexity of your Node Group hierarchy, NNMi might take some time to complete updating the results. Click  Refresh to check for the most recent changes to Node Group contents.

[Special Actions](#) are available for Node Groups and Interface Groups.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

You can also use the [nnmloadnodegroups.ovpl](#) command or the [nnmnodegroup.ovpl](#) command to list the following:

- Names of the existing Node Groups
- Selected attributes of nodes that are members of a specified Node Group

Tip: (*NNM iSPI Performance for Metrics only*) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.

NNMi administrators can use Security Groups as [Node Group definitions](#) that become filters in NNMi views. If a user cannot access any nodes in a particular Node Group, that filter dynamically disappears from the filter selection list in the user's NNMi views. Any attribute in a Node form can be used to identify the members of a Node Group (for example, the Security Group attribute value or the Tenant attribute value).

Note: If you use multiple tenants, you might not want users to see all of the Node Groups you create. To remove the Nodes Group view from the NNMi console, see the "NNMi Console" chapter of the *HP Network Node Manager i Software Deployment Reference*.

Related Topics

["Node Groups of IPv4 or IPv6 Addresses " on page 339](#)

["Define Node Group Map Settings" on page 550](#)

["Create Interface Groups" on page 356](#)

Create Node Groups Using Filters or Hostname Lists (Configuration: Node Groups)

Node Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

Note: By default NNMi Administrators can create, modify, and delete Node Groups. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to create, modify, and delete Node Groups. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Node Group".

You can create any number of Node Groups in addition to the ones that NNMi provides (see ["Node Groups Provided by NNMi" on page 372](#)).

One method for creating Node Groups is using filters or hostname lists to match the way your team identifies important network devices. Each Node Group is defined using one or more of the following:



- Device Filters (by any combination of SNMP device category, vendor, family, profile)
- Additional Filters (Boolean expressions based on a list of object attributes)
- Additional Nodes (identified by *case-sensitive* Hostname)
- Child Node Groups (use any combination of Node Groups to create a filter)

NNMi combines the results of all Node Group configuration settings in the following manner:

- NNMi first evaluates Device Filters. If any exist, nodes must match *at least one* specification to belong to this Node Group.
- NNMi then evaluates any Additional Filters. Nodes *must also pass all* Additional Filters specifications to belong to this Node Group.
- Any Additional Nodes specified are *always* included in the Node Group, regardless of any filters.
- Any Child Node Group results are treated the same as Additional Nodes.

Note: You can also create Node Groups using the **Actions** → **Node Group Membership** option. This method adds the selected nodes to a Node Group that NNMi creates. See "[Create Node Groups From the Actions Menu](#)" on page 347 for more information.

To create a Node Group Using Filters or Hostname Lists (if your role permits you to do this):

1. Navigate to the **Node Group** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Object Groups** folder.
 - c. Select the **Node Groups** view.
 - d. Do one of the following:
 - To create a Node Group, click the  New icon.
 - To edit a Node Group, click the  Open icon in the row representing the Node Group you want to edit.
2. In the [Node Group form](#), provide the required information in the [Basics](#) section.
3. (NNM iSPI Performance) Make the Node Group available within NNM iSPI Performance products (see [NNM NNM iSPI Performance table](#)).


4. Identify the nodes that belong to this Node Group.

Do one or more of the following:

- [Specify a filter based on Device Profile settings using the Device Filters tab](#) (any combination of category, vendor, family, or profile).

Tip: To base your filter on the SNMP system Object ID number, use the Additional Filters `sysOidNode` code.

- [Specify a Node Group filter using the Additional Filters tab](#) (use a variety of available codes to filter by object attribute values in the NNMi database).
- [Specify individual nodes using the Additional Nodes tab](#) (provide a list of Hostnames, as they appear in the NNMi database).
- [Specify Child Node Groups using the Child Node Groups tab](#) (use combinations of Node Groups to create a filter).

5. Click  **Save and Close** to return to the Node Group form.

Note: You must click **Save and Close** to save your changes each time you create a Node Group.

6. Click  **Save and Close**.

If you configured this Node Group for Monitoring, NNMi applies your changes during the next monitoring cycle. "[Configure NNMi Monitoring Behavior](#)" on page 387.

To review a Node Group definition:

1. From the workspace navigation panel, select the **Inventory** workspace.
2. Select the **Node Groups** view.
3. Double-click the row representing the Node Group definition you want to see.
4. The [Node Group form](#) displays.

Note: NNMi monitors the status of each Node Group over time. To check Node Group status information, access the Node Group form's [Status](#) tab.

5. When finished, click the  Close icon.

You can also use the [nnmloadnodegroups.ovpl](#) command or the [nnmnodegroup.ovpl](#) command to list the following:

- Names of the existing Node Groups
- Selected attributes of nodes that are members of a specified Node Group

[Special Actions are available](#) for Node Groups and Interface Groups.

Related Topics

["Create Node Groups From the Actions Menu " on page 347](#)

["From the Command Line, Define Node Groups" on page 351](#)



Specify Node Group Additional Filters

Use the Additional Filters Editor to create expressions that refine the requirements for membership in a Node Group. Make sure to design any complex Additional Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Additional Filters Editor.

If any Additional Filters are created, NNMi combines any Device Filters and Additional Filters using the AND Boolean operator as follows:

- NNMi first evaluates any Device Filters. Nodes must match *at least one* Device Filter specification to belong to this Node Group.
- NNMi then evaluates the Additional Filters expression. Nodes *must also match all* Additional Filters expression specifications to belong to this Node Group.

To create an Additional Filters expression:

1. Navigate to the **Node Group Form: Additional Filters** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Object Groups** folder.
 - c. Select **Node Group**.
 - d. Do one of the following:
 - To create a Node Group definition, click the  New icon.
 - To edit a Node Group definition, click the  Open icon in the row representing the Node Group definition you want to edit.
 - e. In the Node Group form, select the **Additional Filters** tab.
2. Establish the appropriate settings for the Additional Filters you need (see the [Additional Filters Editor Choices](#) and [Additional Filters Editor Buttons](#) table). See ["Guidelines for Creating](#)

[Additional Filters for Node Groups" on page 341](#) for more information.

- a. Plan out the logic needed for your Filter String.
- b. Use the [buttons on the bottom half of the Additional Filters Editor](#) to establish the logic structure. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#).

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the selected filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: hostedIPAddress Operator: between Value: 0.0.0.0, 255.255.255.255

Buttons: Append, Insert, Replace

Logic Flow: AND, AND, NOT

Filter String: (() AND NOT ())

Highlight the location in the logic flow, then click Insert to define the filter requirement

3. Click **Save and Close**.

Additional Filters Editor Choices for Node Groups

Attribute	Description
Attribute	<p>NNMi provides Additional Filters codes for a subset of object attributes. For more information about the available Additional Filter codes for each NNMi object type, click the link:</p> <ul style="list-style-type: none"> Node attribute codes [click here for a list of attribute codes] <p>Values from the Basic Attributes listed on the Node Form:</p>

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>) ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server) ■ securityGroupName (Security Group) <p>Note: If you enter the Name value for a Security Group that you do not have permission to access, the Node Group will be empty. See "Configuring Security" on page 569 for more information.</p> <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysLocation (System Location) ■ sysContact (System Contact) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>See "Node Groups of IPv4 or IPv6 Addresses " on page 339 for ideas.</p> <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Node Form: Custom Attributes Tab:</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p>

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ customAttrName (Custom Attribute Name) ■ customAttrValue (Custom Attribute Value) • Security Group attribute codes [click here for a list of attribute codes] Values from the Security Group Form: <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: If you enter the Name or UUID value for a Security Group that you do not have permission to access, the Node Group will be empty. See "Configuring Security" on page 569 for more information.</p> </div> <ul style="list-style-type: none"> ■ securityGroupName (Name) ■ securityGroupUuid (UUID) • Tenant attribute codes [click here for a list of attribute codes] Values from the Tenant Form: <ul style="list-style-type: none"> ■ tenantName (Name) ■ tenantUuid (UUID) • Device Profile attribute codes [click here for a list of attribute codes] Values from the Basics Attributes on the Device Profile Form: <p>NNMi matches the Label attribute values from the Device Profile Form for each of the following:</p> <ul style="list-style-type: none"> ■ devCategoryNode (Device Category) ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>To filter on the SNMP system object ID number assigned to a particular make/model, use the sysOidNode attribute. See Values from the Node Form: General Tab.</p> • Regional Manager attribute codes (<i>NNMi Advanced</i>) [click here for a list of attribute codes] Values from the associated entry on the Regional Manager Form: Connection Tab: <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>)

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server).
Operator	<p>The standard query language (SQL) operations to be used for the search.</p> <div> <p>Note: Only the <code>is null</code> Operator returns null values in its search.</p> </div> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>sysName = cisco2811</code> finds all devices with system name equal to cisco2811. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>sysName != cisco2811</code> finds all system names other than cisco2811. • < Finds all values less than the value specified. Click here for an example. IPv4 example: <code>mgmtIPAddress < 15.239.255.255</code> finds all IP address values less than 15.239.255.255 IPv6 example: <code>mgmtIPAddress < ::ffff:0:0</code> finds all IP address values less than ::ffff:0:0 • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>mgmtIPAddress <= 15.239.255.255</code> finds all IP address values less than or equal to 15.239.255.255. • > Finds all values greater than the value specified. Click here for an example. IPv4 example: <code>mgmtIPAddress > 15.238.0.0</code> finds all IP address values greater than 15.238.0.0 IPv6 example: <code>mgmtIPAddress > ::ffff:ffff:ffff</code> finds all IP address values greater than ::ffff:ffff:ffff • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>mgmtIPAddress >= 15.238.0.0</code> finds all IP address values greater than or equal to 15.238.0.0. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>mgmtIPAddress between 15.238.0.10 15.238.0.120</code> finds all IPv4 address values equal to or greater than 15.238.0.10 and equal to or less than

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	<p>15.238.0.120.</p> <p>See "Node Groups of IPv4 or IPv6 Addresses " on page 339 for more examples of using the between Operator.</p> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>sysName in</p> <div> Value <div> cisco2811 cisco5500 </div> </div> <p>finds all systems with names that are cisco2811 or cisco5500.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (cisco2811, cisco550). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. <p>Example: sysName is not null finds all systems that have a name value.</p> <ul style="list-style-type: none"> • is null Finds all blank values. Click here for an example. <p>Example: sysName is null finds all systems that do not have an assigned name value.</p> <ul style="list-style-type: none"> • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. <p>The following attributes cannot be used with the like operator:</p> <ul style="list-style-type: none"> ■ hostedIPAddress ■ mgmtIPAddress <p>The asterisk (*) character means <i>any number of characters of any type at this location</i>.</p>

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	<p>Note: For optimum performance, avoid beginning your search string with an asterisk (*).</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Examples:</p> <ul style="list-style-type: none"> ▪ <code>sysName like cisco*</code> finds all system names that begin with cisco. ▪ <code>sysName like cisco??*</code> finds all system names that <i>start with cisco followed by two characters</i>. ▪ <code>sysName like rtr??bld5*</code> finds all system names that have <i>specific characters at an exact location</i>, positions 1-3 (rtr) and 6-9 (bld5). <ul style="list-style-type: none"> • not between finds all values except those between the two values specified. Click here for an example. Example: <code>mgmtIPAddress not between 15.238.0.10 15.238.0.120</code> finds all IP address values less than 15.238.0.10 and greater than 15.238.0.120. See "Node Groups of IPv4 or IPv6 Addresses " on page 339 for more examples of using the not between Operator. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>sysName not in</code> <div data-bbox="444 1358 742 1493" data-label="Form"> <div>Value</div> <div>cisco2811 cisco5500</div> </div> finds all system name values other than cisco2811 and cisco5500. <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (cisco2811, cisco5500). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p>

Additional Filters Editor Choices for Node Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p>The following attributes cannot be used with the not like operator:</p> <ul style="list-style-type: none"> ■ hostedIPAddress ■ mgmtIPAddress <p>The asterisk (*) character means <i>any number of characters of any type at this location</i>.</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Examples:</p> <ul style="list-style-type: none"> ■ sysName not like cisco* finds all system names that do not begin with cisco. ■ sysName not like cisco??* finds all system names that do not <i>begin with cisco followed by two characters</i>. ■ sysName not like rtr??bld5* finds all system names that do not have <i>specific characters at an exact location</i>, positions 1-3 (rtr) and 6-9 (bld5).
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The in and not in operators require that each value be entered on a separate line. • When entering a value for the Capability attribute, copy and paste the Unique Key value from the Node form: Capability tab.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor

Additional Filters Editor Buttons, continued

Button	Description
	location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude nodes with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following Filter String, NNMi includes nodes with a hostname that contains router, followed by any number of characters, followed by hp.com and excludes any nodes with a Device Profile that includes Cisco as the Vendor value:</p> <pre>(hostname like router*.hp.com OR NOT (devVendorNode = Cisco))</pre>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider nodes that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes nodes with a hostname that includes router, followed by any number of characters, followed by hp.com as well as any nodes that have the Custom Attribute edge and that edge value is true:</p> <pre>(hostname like router*.hp.com OR EXISTS((customAttrName=edge AND customAttrValue=true)))</pre>
NOT	Used for filters that include Capabilities or Custom Attribute names and values in the

Additional Filters Editor Buttons, continued

Button	Description
EXISTS	<p>Filer String. Indicates that you want NNMi to consider nodes that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the nodes that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> </div> <p>For example, when evaluating the following Filter String, NNMi includes nodes with a hostname that includes router, followed by any number of characters, followed by hp.com and excludes any nodes with Custom Attribute edge and that edge value is true.</p> <pre>(hostname like router*.hp.com OR NOT EXISTS((customAttrName=edge AND customAttrValue=true)))</pre>
Delete	<p>Deletes the selected expression.</p> <div> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p> </div>

Node Groups of IPv4 or IPv6 Addresses

Use the Node Group form's Additional Filters editor to create Node Groups based on the following criteria ("[Specify Node Group Additional Filters](#)" on page 330):

- All nodes that have *only* IPv4 addresses
[\[click here for details of this filter.\]](#)

Both of the following example Node Group's Additional Filters provide the same results. The first example uses IPv4 address notation. The second example uses IPv6 address notation:

```
((hostedIPAddress between 0.0.0.0 AND 255.255.255.255) AND NOT  
(hostedIPAddress not between 0.0.0.0 AND 255.255.255.255))
```

or (NNMi Advanced)

```
((hostedIPAddress between 0.0.0.0 AND 255.255.255.255) AND NOT  
(hostedIPAddress not between ::ffff:0:0 AND ::ffff:ffff:ffff))
```

- All nodes that have *any* IPv4 addresses (could also have IPv6)
[\[click here for details of this filter.\]](#)

The following example Node Group's Additional Filter finds any node that has at least one IPv4 address:

```
(hostedIPAddress between 0.0.0.0 AND 255.255.255.255)
```

- (NNMi Advanced) All nodes that have *only* IPv6 addresses
[\[click here for details of this filter.\]](#)

IPv6 addresses extend the number of possible IP addresses. The old IPv4 address range falls within the new IPv6 range. Valid IPv6 address values can be less than or greater than the old IPv4 range of addresses. NNMi Advanced converts the IPv4 addresses to the new IPv6 notation, then stores and filters the IPv4 addresses as IPv6 addresses (::ffff:a.b.c.d).

Both of the following example Node Group's Additional Filters provide the same results. The first example uses IPv4 address notation. The second example uses IPv6 address notation:

```
((hostedIPAddress not between 0.0.0.0 AND 255.255.255.255) AND NOT  
(hostedIPAddress between 0.0.0.0 AND 255.255.255.255))
```

or

```
((hostedIPAddress not between ::ffff:0:0 AND ::ffff:ffff:ffff) AND NOT  
(hostedIPAddress between 0.0.0.0 AND 255.255.255.255))
```

- (NNMi Advanced) All nodes that have *any* IPv6 addresses (could also have IPv4)
[\[click here for details of this filter.\]](#)

The following example Node Group's Additional Filter finds any node that has at least one IPv6 address:

```
((hostedIPAddress between ::0 AND ::fffe:ffff:ffff) OR (hostedIPAddress  
::1:0:0:0 AND ffff:ffff:ffff:ffff:ffff:ffff:ffff:ffff))
```

- (NNMi Advanced) All nodes that have *both* IPv4 and IPv6 addresses (also known as dual-stack nodes)
[\[click here for details of this filter.\]](#)

The following example Node Group's Additional Filter finds any node that has at least one IPv4 address and at least one IPv6 address:


```
((hostedIPAddress between 0.0.0.0 AND 255.255.255.255) AND (hostedIPAddress  
not between 0.0.0.0 AND 255.255.255.255))
```

Note: To maximize the performance of Additional Filters based on an IP Address range, avoid multiple filter expressions. For example, use the *between* operator instead of the greater than or equal to (*>=*) and less than or equal to (*<=*) operators that cause NNMi to use multiple queries for finding all addresses that match the filter.

Guidelines for Creating Additional Filters for Node Groups

The Additional Filters Editor enables you to create expressions to further define the nodes to be included in a Node Group. Make sure to design any complex Additional Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Additional Filters Editor.

When creating Additional Filters for a Node Group, note the following:

- NNMi treats each set of expressions associated with a Boolean Operator as if it were enclosed in parentheses and evaluated together rather than in order of grouping as the nesting implies. Therefore, when using the AND operator to combine expressions that include Custom Attributes, include only one customAttrName/customAttrValue pair in the expression. Otherwise, if you use multiple customAttrName and customAttrValue pairs with the AND operator, the results might not be as expected. [Click here for an example.](#)

In the following example, because the AND Boolean operator indicates that NNMi should evaluate all of the customAttrname and customAttrvalue pairs together, it is not possible for any nodes to match this Additional Filters expression:

Additional Filter Expression Example 1:

```
((customAttrName = capability) AND (customAttrValue =  
com.hp.nnm.capability.card.fru)) AND ((customAttrName = location) AND  
(customAttrValue = datacenter1))
```

This is because customAttrName would need to match both *capability and* location at the same time. However, if you use the OR operator to combine the customAttrName and customAttrValue pairs as shown in the following example, the filter should work as expected.

Additional Filter Expression Example 2:

```
((customAttrName = capability) AND (customAttrValue =  
com.hp.nnm.capability.card.fru)) OR ((customAttrName = location) AND  
(customAttrValue = datacenter1))
```

Using the Node values listed in the following table, all three nodes (nodeA, nodeB, and nodeC) pass the filter in Example 2 because each of these nodes has either the value `com.hp.nnm.capability.card.fru` for `capability` or the value `datacenter1` for `location`.

Example Data

Node Name	capability	customAttrName	customAttrValue
nodeA	com.hp.nnm.capability.card.fru	location	datacenter1
nodeB	com.hp.nnm.capability.card.fru	<undefined>	<undefined>
nodeC	<undefined>	location	datacenter1

- Use the EXISTS and NOT EXISTS operators when you want NNMi to consider nodes that either do or do not have any Capabilities or Custom Attributes when evaluating the Filter String. See ["Specify Node Group Additional Filters" on page 330](#) for more information.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions as shown in the example below.

AND

```
sysName like cisco*
```

```
sysName != cisco2811
```

OR

```
sysLocation = Boston
```

```
sysContact In (Johnson,Hickman)
```

NNMi evaluates the expression above as follows:

```
sysName like cisco* AND sysName != cisco2811 AND (sysLocation = Boston OR  
sysContact in (Johnson, Hickman))
```

- NNMi finds all nodes with a (system name) `sysName` beginning with **cisco**, except not **cisco2811**.
- Of these nodes, NNMi then finds all nodes with a (system location) `sysLocation` of **Boston** or (system contact name) `sysContact` of **Johnson** or **Hickman**.
- NNMi evaluates only those nodes that contain values for *all* of the attributes included in the Additional Filter expression. [Click here for an example.](#)

If your Node Group filter expression includes the `capability` and `customAttrName` attributes, then NNMi evaluates only nodes that have a value defined for *both* `capability` and

customAttrName. For example, if you create a Node Group using the following Additional Filters expression, then NNMi evaluates only those nodes that have a value defined for capability and a value defined for customAttrName:

```
(capability = com.hp.nnm.capability.card.fru) OR (customAttrName = location)
```

Using the Node values listed in the following table, NNMi only evaluates nodeA. This is because nodeA contains a value for capability and a value for customAttrName. NNMi does not evaluate nodeB because it does not have a value for customAttrName. NNMi does not evaluate nodeC because it does not have a value for capability. NodeA also passes Node Group Additional Filter because its capability value of com.hp.nnm.capability.card.fru matches the value specified in the Additional Filter expression. Therefore, only nodeA is included in this example Node Group.

Example Data

Node Name	capability	customAttrName	customAttrValue
nodeA	com.hp.nnm.capability.card.fru	location	datacenter1
nodeB	com.hp.nnm.capability.card.fru	<undefined>	<undefined>
nodeC	<undefined>	location	datacenter1

Tip: You can populate a placeholder value, such as "none" or "undefined" for any attribute that you want to use in an Additional Filter.

- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on the next page](#) for more information.
- You can drag any of the following items to a new location in the Filter String:
 - Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS
 - Filter Expression (Attribute, Operator and Value)
- When moving items in the Filter String, note the following:
 - Click the item you want to move before dragging it to a new location.
 - As you drag a selected item, an underline indicates the target location.
 - If you are moving the selection up, NNMi places the item above the target location.
 - If you are moving the selection down, NNMi places the item below the target location.

- If you attempt to move the selection to an invalid target location, NNMi displays an error message.

Add Boolean Operators in the Additional Filters Editor

When adding or deleting Boolean Operators using the Additional Filters Editor, note the following:

- Add your highest level Boolean operator first. For example, **AND** is the highest level Boolean operator in the following expression

(sysName like cisco* OR sysName like hp*) **AND** (sysLocation = Boston OR sysContact in Johnson,Hickman)

- Add each additional Boolean Operator before the expressions to which it applies.
- Select the appropriate Boolean Operator in the expression before you add the expressions to which the Boolean Operator applies.
- When a Boolean Operator is selected and you click **Delete**, any expressions that are associated with the Boolean Operator are also deleted.

In the example expression below, If you select **AND** and then click **Delete**, the Additional Filters Editor deletes the entire expression.



[Click here for an example](#) for creating Node Group Additional Filters.


Node Group Additional Filters Expression Example


((sysName like cisco* OR sysName like hp*) **AND** (sysLocation = Boston OR sysContact in (Johnson, Hickman)))

To add the expression above, after you are in the Additional Filters Editor, follow these steps:

1. Click **AND**.
2. Click **OR**.
3. Select the **OR** you just added to the expression.
4. In the **Attribute** field select **sysName** from the drop-down list.
5. In the **Operator** field, select **like** from the drop-down list.
6. In the **Value** field, enter **cisco***.

7. Click **Append**.
8. In the **Attribute** field, select **sysName** from the drop-down list.
9. In the **Operator** field, select **like** from the drop-down list.
10. In the **Value** field, enter **hp***.
11. Click **Append**.
12. Select the **AND** that you previously added to the expression.
13. Click **OR**.
14. Select the **OR** you just added to the expression.
15. In the **Attribute** field, select **sysLocation** from the drop-down list.
16. In the **Operator** field, select **=** from the drop-down list.
17. In the **Value** field, enter **Boston**.
18. Click **Append**.
19. In the **Attribute** field, select **sysContact** from the drop-down list.
20. In the **Operator** field, select **in** from the drop-down list.
21. In the **Value** field:
 - a. enter **Johnson** and press **<Enter>**.
 - b. On the new line, enter **Hickman**.
22. Click **Append**.
23. Click **Save** to save your Additional Filters.
24. Select **Actions > Preview Members (Current Group Only)** to view the members of the Node Group that is a result of this filter.

Tip: To test the effects of your Node Group definition on Child Node Groups, in the Node Group form, select **Save**, then **Actions > Node Group Details > Show Members (Include Child Groups)**. NNMi displays the members of the current Node Group members as well as the members of each associated Child Node Group. Depending on the complexity of your Node Group hierarchy, NNMi might take some time to complete updating the results. Click  Refresh to check for the most recent changes to Node Group contents.

25. Click  Refresh to check for the most recent changes to Node Group contents.

[Click here for an example](#) for creating an Interface Group Additional Filters.

Interface Group Additional Filters Expression Example

```
((ifName like ATM* AND ifName != ATMS/O/A) AND (ifSpeed = 10 OR ifSpeed = 100))
```

To add the expression above, follow these steps:

1. Click **AND**.
2. Click **AND**.
3. Select the **AND** you just added to the expression.
4. In the **Attribute** field select **ifName** from the drop-down list.
5. In the **Operator** field, select **like** from the drop-down list.
6. In the **Value** field, enter **ATM***.
7. Click **Append**.
8. In the **Attribute** field, select **ifName** from the drop-down list.
9. In the **Operator** field, select **!=not equal to** from the drop-down list.
10. In the **Value** field, enter **ATMS/O/A**.
11. Click **Append**.
12. Select the first **AND** that you added to the expression.
13. Click **OR**.
14. Select the **OR** you just added to the expression.
15. In the **Attribute** field, select **ifSpeed** from the drop-down list.
16. In the **Operator** field, select **=** from the drop-down list.
17. In the **Value** field, enter **10**.
18. Click **Append**.
19. In the **Attribute** field, select **ifSpeed** from the drop-down list.
20. In the **Operator** field, select **=** from the drop-down list.
21. In the **Value** field, enter **100**.

22. Click **Append**.
23. Click **Save** to save your Additional Filters.
24. Select **Actions > Show Members** to view the members of the Interface Group that is a result of this filter.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Create Node Groups From the Actions Menu

Node Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

Note: By default NNMi Administrators can create, modify, and delete Node Groups. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to create, modify, and delete Node Groups. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Node Group".

You can create any number of Node Groups in addition to the ones that NNMi provides (see ["Node Groups Provided by NNMi" on page 372](#)).

You can easily create a Node Group from any Nodes or map view using the **Actions** menu. NNMi adds the selected nodes to the Node Group that it creates. When creating Node Groups using the **Actions** menu, note the following:

- Multiple nodes can be associated with one Node Group.
- One node can be associated with multiple Node Groups.
- If you change the Node Group name, the Group Membership does not change.

To create a Node Group from the Actions menu (if your role permits you to do this):

1. Navigate to a **Node** inventory view.
 - a. From the workspace navigation panel, select the **Inventory** workspace.
 - b. Select the node view of interest (for example, **Nodes** view).

Tip: You can also select Nodes from a map view.

2. Use Ctrl-Click to select each node you want to add to a Node Group.


3. Select **Actions** → **Node Group Membership**.
4. Select **Add to a new Node Group**.
5. In the **Node Group Membership** dialog box, enter the Name of the Node Group you want to create. This name is a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Tip: If you want to view the associated Node Group form, in the Node Group Membership dialog box, check ☒ **Open the Node Group form**. When selected, NNMi opens the Node Group form so that you can view your changes.

Note: NNMi lists the nodes you have added on the **Additional Nodes** tab.

6. In the **Node Group Membership** dialog box, click **OK** to save your changes.

If you configured this Node Group for Monitoring, NNMi applies your changes during the next monitoring cycle. "[Configure NNMi Monitoring Behavior](#)" on page 387.

If you specified to open the Node Group form and then made additional changes, click  **Save and Close** to save your changes.

To review a Node Group definition:

1. From the workspace navigation panel, select the **Inventory** workspace.
2. Select the **Node Groups** view.
3. Double-click the row representing the Node Group definition you want to see.
4. The [Node Group form](#) displays.

Note: NNMi monitors the status of each Node Group over time. To check Node Group status information, access the Node Group form's [Status](#) tab.

5. When finished, click the  Close icon.

You can also use the [nnmloadnodegroups.ovpl](#) command or the [nnmnodegroup.ovpl](#) command to list the following:

- Names of the existing Node Groups
- Selected attributes of nodes that are members of a specified Node Group

[Special Actions](#) are available for Node Groups and Interface Groups.

Related Topics

["Create Node Groups Using Filters or Hostname Lists \(Configuration: Node Groups\)" on page 327](#)

["From the Command Line, Define Node Groups" on page 351](#)

Add Nodes to a Node Group From the Actions Menu

Node Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

Note: By default NNMi Administrators can create, modify, and delete Node Groups. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to create, modify, and delete Node Groups. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Node Group".

You can create any number of Node Groups in addition to the ones that NNMi provides (see ["Node Groups Provided by NNMi" on page 372](#)).

You can easily add one or more Nodes to a Node Group from any Nodes or map view using the **Actions** menu. NNMi adds the selected nodes to the Node Group specified.

When adding Nodes to an existing Node Groups using the **Actions** menu, note the following:


- Multiple nodes can be associated with one Node Group.
- One node can be associated with multiple Node Groups.
- If you change the Node Group name, the Group Membership does not change.

Tip: (*NNM iSPI Performance for Metrics only*) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.


To create a Node Group using the Actions menu (if your role permits you to do this):

1. Navigate to a **Nodes** inventory view.
 - a. From the workspace navigation panel, select the **Inventory** workspace.
 - b. Select the node view of interest (for example, **Nodes** view).

Tip: You can also select Nodes from a map view.

2. Use Ctrl-Click to select each node you want to add to a Node Group.
3. Select **Actions** → **Node Group Membership**
4. Select **Add to an existing Node Group**.
5. In the **Node Group Membership** dialog, box, select the  Lookup icon and select one of the options from the drop-down menu:

 Quick Find to view and select from the list of all existing Node Groups.


 Open to display the details of a selected Node Group.

Tip: If you want to view the associated Node Group form, in the Node Group Membership dialog box, check ☒ **Open the Node Group form**.

Note: NNMi adds the nodes on the **Additional Nodes** tab. NNMi automatically opens the Node Group form so that you can make any additional changes.

6. In the **Node Group Membership** dialog box, click **OK** to save your changes.

If you configured this Node Group for Monitoring, NNMi applies your changes during the next monitoring cycle. ["Configure NNMi Monitoring Behavior" on page 387](#).

If you specified to open the Node Group form and then made additional changes, click  **Save and Close** to save your changes.

To review a Node Group definition:

1. From the workspace navigation panel, select the **Inventory** workspace.
2. Select the **Node Groups** view.
3. Double-click the row representing the Node Group definition you want to see.
4. The [Node Group form](#) displays.

Note: NNMi monitors the status of each Node Group over time. To check Node Group status information, access the Node Group form's [Status](#) tab.

5. When finished, click the  Close icon.

You can also use the [nnmloadnodegroups.ovpl](#) command or the [nnmnodegroup.ovpl](#) command to list the following:

- Names of the existing Node Groups
- Selected attributes of nodes that are members of a specified Node Group

[Special Actions](#) are available for Node Groups and Interface Groups.

Related Topics

["Create Node Groups Using Filters or Hostname Lists \(Configuration: Node Groups\)" on page 327](#)

["From the Command Line, Define Node Groups" below](#)

From the Command Line, Define Node Groups

Node Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

Note: By default NNMi Administrators can create, modify, and delete Node Groups. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to create, modify, and delete Node Groups. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Node Group".

You can create any number of Node Groups in addition to the ones that NNMi provides (see ["Node Groups Provided by NNMi" on page 372](#)).

Use the following command-line tools to create or modify existing Node Groups:

- See the [nnmnodegroup.ovpl](#) Reference Page.
- See the [nnmloadinterfacegroups.ovpl](#) Reference Page.

This command is used in combination with a comma separated values (CSV) file - for example, a Microsoft Excel spreadsheet saved as a .csv file.

For the alternate method of creating Interface Groups, see ["From the Command Line, Define Interface Groups" on page 371](#).



Remove Nodes from Node Groups

NNMi enables you to remove one or more nodes from a selected Node Group or from all of the Node Groups to which they belong.

To remove one or more nodes from an Node Group (if your role permits you to do this):

1. Navigate to an **Nodes** inventory view.
 - a. From the workspace navigation panel, select the **Inventory** workspace.
 - b. Select the node view of interest (for example, **Nodes** view).

Tip: You can also select Nodes from a map view.

2. Use Ctrl-Click to select each node you want to remove from a Node Group.
3. Select **Actions** → **Node Group Membership** → **Remove from a Node Group....**
4. In the **Node Group Membership** dialog, box, select the  Lookup icon, and then  Quick Find to select the Node Group from which you want to remove the selected nodes.
5. In the **Node Group Membership** dialog box, click **OK**.

Tip: (*NNM iSPI Performance for Metrics only*) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.

Related Topics

["Create Node Groups From the Actions Menu" on page 347](#)

Configure Node Group Status

NNMi enables an NNMi administrator to configure the Node Group status calculations using either of the following methods:

- Assign the Node Group the most severe status of any Node Group member. This is the default method for obtaining Node Group Status.
- Configure the percentage thresholds for one or more Node Group target statuses. For example, when defining percentage values for a target status of **Critical**, you might change the default so that 30 percent of the nodes in the group must have a status of Critical for the Node Group Status to be **Critical**.


Tip: Use the **Actions** → **Status Details** to see how NNMi calculates the status for a selected Node Group.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

To configure Node Group status calculations, do the following:

1. Navigate to the **Status Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select **Status Configuration**.
2. Make one of the following configuration choices:
 - To assign the Node Group the most severe Status of any Node Group member, in the **Status Configuration** form, under **Global Control**, make sure **Propagate Most Severe Status** is checked:

Propagate Most Severe Status ☒
 - To configure percentage values for a Node Group Target Status, do the following:
 - i. In the **Status Configuration** form, under **Global Control**, make sure the **Propagate Most Severe Status** is cleared:

Propagate Most Severe Status ☐
 - ii. [Configure the percentage values for a Node Group Target Status](#)
3. Click  **Save and Close**.

NNMi applies your changes after the configuration is saved. Node Group status is updated anytime a Node Group membership changes.




Configure Percentage Values for the Target Status

NNMi enables you to configure how the status of a Node Group is calculated.

Note: The percentage is calculated using only those nodes in the Node Group that have a Management Mode value of **Managed**. For example, if a Node Group includes 10 nodes and 3 of the nodes are **Not Managed**, 5 of the nodes have a Status of **Normal**, and 2 have a status of **Critical**, the percentage of **Critical** nodes is $2/7 * 100$.

To configure the percentage values for a Node Group Target Status:

1. Navigate to the **Status Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select **Status Configuration**.
2. Locate the **Node Group Status Settings** tab.
3. Do one of the following:

- To create a Node Group Status Settings definition, click the  New icon.
 - To edit a Node Group Status Settings definition, select a row and click the  Open icon.
 - To delete a Node Group Status Settings definition, select a row and click the  Delete button
4. Establish the appropriate settings to identify this Node Group Status Settings definition. (See the ["Node Group Status Settings Form" below.](#))




Note: You can only define one configuration for each Target Status.



Node Group Status Settings Form

The Node Group Status Settings form is used to configure the percentage thresholds for a Node Group Target Status. The percentage thresholds you specify define what percentage of nodes within the group must have a particular Status. When the percentage thresholds are reached, the Node Group is assigned the associated Target Status. For example, when defining percentage thresholds for a target status of **Critical**, you might change the default so that 10 percent of the nodes in the group must have a status of **Critical** for the Node Group Status to be **Critical**.

Note: Use a percentage threshold between 0 (zero) and 1 (for example, .01) to indicate the Target Status to be reached when one node in the Node Group reaches a specified Status. For example, if you want the Node Group Status to be set to **Critical** when the Status of one node in the Group becomes **Critical**, enter a percentage less than one for the **Critical %** value.

To define percentage thresholds for a Target Status:

1. [Navigate to the Node Group Status Settings form.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select **Status Configuration**.
 - c. Navigate to the **Node Group Status Settings** tab.
 - d. Do one of the following:
 - To create a Node Group Status Settings definition, click the  New icon.
 - To edit a Node Group Status Settings definition, select a row and click the  Open icon.
 - To delete a Node Group Status Settings definition, select a row and click the  Delete icon.
2. Set the Target Status and percentages you want (see [Basic Attributes table](#)).

3. Click  **Save and Close** to return to the **Status Configuration** form.
4. Click  **Save and Close**. NNMi applies your changes after the configuration is saved.

Basics Attributes

Attribute	Description
Target Status	<p>The Status you are configuring. This Status is assigned to the Node Group whenever the specified percentage thresholds are reached.</p> <p>Note the following:</p> <ul style="list-style-type: none"> Whether all or one of the percentage thresholds must be reached for a Target Status configuration depends on the Boolean operator you select. The default Boolean operator is OR. (Also see Combine with AND below.) If you do not specify any percentages for a Target Status, it does not appear as a Status for a Node Group.
Critical %	Specifies the required percentage of nodes in the group that must have a Status value set to Critical before NNMi assigns the Target Status.
Major %	Specifies the required percentage of nodes in the group that must have a Status value set to Major before NNMi assigns the Target Status.
Minor %	Specifies the required percentage of nodes in the group that must have a Status value set to Minor before NNMi assigns the Target Status.
Warning %	Specifies the required percentage of nodes in the group that must have a Status value set to Warning before NNMi assigns the Target Status.
Non-Normal %	<p>Specifies the required percentage of nodes in the group that must have a Status value set to any of the following before NNMi assigns the Target Status:</p> <ul style="list-style-type: none"> Critical Major Minor Warning
Unknown %	Specifies the required percentage of nodes in the group that must have a Status value set to Unknown before NNMi assigns the Target Status.
Combine with AND	<p>Specifies that you want NNMi to combine the percentage thresholds you enter using the AND Boolean operator.</p> <p>When using this option, note the following:</p> <ul style="list-style-type: none"> All percentage thresholds you enter must be reached for the Node Group to be assigned the Target Status.

Basics Attributes, continued

Attribute	Description
	<ul style="list-style-type: none">• The percentage thresholds you enter must not exceed 100 percent.

Create Interface Groups

Interface Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

You can create any number of Interface Groups in addition to the ones that NNMi provides (see ["Interface Groups Provided by NNMi" on page 376](#)).

Tip: (*NNM iSPI Performance for Metrics only*) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.

To create Interface Groups, use one or more of the following methods:

- ["Create Interface Groups Using ifType Values and Filters \(Configuration: Interface Groups\)" below](#)
- ["From the Command Line, Define Interface Groups" on page 371](#)

Related Topics

["Interface Groups of IPv4 or IPv6 Addresses" on page 368](#)

["Troubleshooting Interface Changes" on page 372](#)

["Create Node Groups" on page 326](#)

Create Interface Groups Using ifType Values and Filters (Configuration: Interface Groups)

Interface Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

You can create any number of Interface Groups in addition to the ones that NNMi provides (see ["Interface Groups Provided by NNMi" on page 376](#)).



One method for creating Interface Group is using ifType values or Filters to match the way your team identifies important network devices. For example, each interface group can include one or

more interface-type specifications (based on industry-standard IANA ifType-MIB variables, see Configuration workspace → MIBs → ifTypes view).

When determining membership in this Interface Group, NNMi combines the results of all Interface Group configuration settings in the following manner:




- NNMi first evaluates ifType Filters. If any exist, interfaces must match *at least one* specification to belong to this Interface Group.
- NNMi then evaluates any Additional Filters. Interfaces *must also pass all* Additional Filters specifications to belong to this Interface Group.
- If a Node Group is specified for this Interface Group, any interface in this group must be contained in a node that is a member of the Node Group specified in the Basics section.


To define an Interface Group using ifType values or Filters (if your role permits you to do this):





1. Navigate to the **Interface Group** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Object Groups** folder.
 - c. Select the **Interface Groups** view.
2. Do one of the following:
 - To create an Interface Group, click the  New icon.
 - To edit an Interface Group, click the  Open icon in the row representing the Interface Group you want to edit.
3. Provide the Basics for this interface group, such as Name, Notes, and behavior designations (see [Interface Group Form](#) help).
4. *Optional.* Navigate to the **ifType Filters** tab.

Identify one or more interface types that belong to this group:

Tip: To see a quick list of all available ifType codes, see the Configuration workspace → MIBs → ifTypes view. Or open the IF-MIB ([MIB Form](#)), navigate to the MIB Variables tab, and double-click ifType (.1.3.6.1.2.1.2.2.1.3).


- To add an ifType filter, click the  New icon, and continue.
- To change an ifType filter, click the  Open icon in the row representing the configuration you want to edit, and continue.
- To delete an ifTypefilter, select a row and click the  Delete icon.

5. In the **ifType Filter form**, click the  Lookup icon and select one of the options from the drop-down menu:

-  Show Analysis to view Analysis Pane information for the currently selected ifType . (See [Use the Analysis Pane](#) for more information about the Analysis Pane.)
-  Quick Find to view and select from the list of all existing ifType values (for more information see ["Use the Quick Find Window" on page 38](#)).
-  Open to display the details of the currently selected ifType.
-  New to create a new ifType (see ["Add New ifType Values \(Interface Types\) to the List" on page 371](#)).

6. *Optional.* Navigate to the **Additional Type Filters** tab.

Use the Additional Filters Editor to filter based on the current values of a subset of Interface object attributes. See ["Specify Interface Group Additional Filters" below](#).


7. Click  **Save and Close** to return to the Interface Group form.

Note: You must click **Save and Close** to save your changes each time you create an Interface Group.

8. Click  **Save and Close**.

If you configured this Interface Group for Monitoring, NNMi applies your changes during the next monitoring cycle. See ["Configure NNMi Monitoring Behavior" on page 387](#).

To review an Interface Group definition:

1. From the workspace navigation panel, select the **Inventory** workspace.
2. Select the **Interface Groups** view.
3. Double-click the row representing the Interface Group.
4. The [Interface Group form](#) displays.
5. When finished, click the  Close icon.

[Special Actions are available](#) for Node Groups and Interface Groups.

Specify Interface Group Additional Filters



The Additional Filters Editor enables you to create expressions to further define the interfaces to be included in an Interface Group. Make sure to design any complex Additional Filters offline as a

Boolean expression first. This method can help to minimize errors when entering your expressions using the Additional Filters editor.

If any Additional Filters are created:

- NNMi first evaluates any Interface Type filter. Nodes must match *at least one* specification to belong to this Interface Group.
- NNMi then evaluates the Additional Filters expression. Nodes *must also match all* Additional Filters expression specifications to belong to this Interface Group.

To create any Additional Filters expression:

1. Navigate to the **Interface Group Form: Additional Filters** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Object Groups** folder.
 - c. Select **Interface Groups**.
 - d. Do one of the following:
 - To create an Interface Group definition, click the  New icon.
 - To edit an Interface Group definition, click the  Open icon in the row representing the configuration you want to edit.
 - e. In the Interface Group form, select the **Additional Filters** tab.
2. Establish the appropriate settings for the Additional Filters you need. (See the [Additional Filters Editor Choices](#), [Additional Filters Editor Buttons](#) table. See also "[Guidelines for Creating Additional Filters for Interface Groups](#)" on page 369.)
 - a. Plan out the logic needed for your Filter String.
 - b. Use the [buttons on the bottom half of the Additional Filters Editor](#) to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the selected filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

3. Click **Save and Close**.

Additional Filters Editor Choices for Interface Groups

Attribute	Description
Attribute	<p>NNMi provides Additional Filters codes for a subset of object attributes. For more information about each one, click the link:</p> <ul style="list-style-type: none"> Interface attribute codes [click here for a list of attribute codes] <p>Values from the Basic Attributes listed on the Interface Form:</p> <ul style="list-style-type: none"> ifName (Name) hostedOn (Hosted On Node) ifPhysAddress (Physical Address) <p>Values from the Interface Form: General Tab:</p> <ul style="list-style-type: none"> ifAlias (Interface Alias) <p>Note the following when using the ifAlias attribute:</p> <ul style="list-style-type: none"> To include empty (or null) ifAlias entries in your search criteria, match the value "null" (for example: ifAlias is null) If you search for an empty ifAlias in your search criteria, the empty value will not be matched (for example do not use: ifAlias != <string>)

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ ifDesc (Interface Description) ■ ifIndex (Interface Index) ■ ifSpeed (Interface Speed) <p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) <p>See "Interface Groups of IPv4 or IPv6 Addresses" on page 368 for ideas.</p> <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Interface Form: Custom Attributes Tab:</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: When using customAttrName and customAttrValue pairs, use EXISTS if you want NNMi to consider Nodes that <i>do not have Custom Attributes</i> when evaluating the entire Filter String. Otherwise Nodes that do not have Custom Attributes are automatically excluded from the Node Group even if they have values that pass other aspects of your filter.</p> </div> <ul style="list-style-type: none"> ■ customAttrName (Custom Attribute Name) ■ customAttrValue (Custom Attribute Value) <ul style="list-style-type: none"> • Node attribute codes [click here for a list of attribute codes] <p>Values from the Basics information on the Node Form:</p> <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled) <p>Values from the Node Form: General Tab.</p> <ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <ul style="list-style-type: none"> • Device Profile attribute codes [click here for a list of attribute codes] <p>Values from the Basics information on the Device Profile Form:</p> <p>NNMi matches the Label attribute values from the Device Profile Form for each of the following:</p> <ul style="list-style-type: none"> ■ devCategoryInterface (Device Category) ■ devVendorInterface (Device Vendor)

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ devFamilyInterface (Device Family) <p>To filter on the parent node's SNMP system object ID number (assigned to a particular make/model), use the sysOidInterface attribute. See Values from the Interface Form: General Tab.</p> <ul style="list-style-type: none"> • VLAN attribute codes [click here for a list of attribute codes] Values from the Basic Attributes on the VLAN form:: <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: To maximize performance, when you want to filter interfaces based on a VLAN Id or VLAN Name, avoid using multiple filter expressions. For example, use the <i>between</i> operator instead of the greater than or equal to (\geq) and less than or equal to (\leq) operators.</p> </div> <ul style="list-style-type: none"> ■ vlanid (VLAN Id) ■ vlanName (Global VLAN Name) • Port attribute codes [click here for a list of attribute codes] Values from the Basic Attributes on the Port form:: <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: If the interface has multiple ports, the interface is selected if there is a match on any one port associated with the interface.</p> </div> <ul style="list-style-type: none"> ■ configuredDuplexSetting (Configured Duplex Setting) <p>See Port form for a list of possible values.</p>
Operator	<p>The standard query language (SQL) operations to be used for the search.</p> <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: Only the <code>is null</code> Operator returns null values in its search.</p> </div> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ifName=Fa0/14</code> finds all interface names that are equal to Fa0/14. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ifName != lan0</code> finds all interface names other than lan0. • < Finds all values less than the value specified. Click here for an example. Example: <code>ifSpeed <= 100000000</code> finds all interfaces with an (interface speed) ifSpeed less than 100 Mbps.

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ifSpeed <= 100000000 finds all interfaces with an (interface speed) ifSpeed less than or equal to 100 Mbps. • > Finds all values greater than the value specified. Click here for an example. Example: ifSpeed >= 100000000 finds all interfaces with an (interface speed) ifSpeed greater than 10 Mbps. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ifSpeed >= 100000000 finds all interfaces with an (interface speed) ifSpeed greater than or equal to 10 Mbps. • between Finds all values equal to and between the two values specified. Click here for an example. Example: ifSpeed between 100000000 1000000000 finds all interfaces with an (interface speed) ifSpeed equal to or greater than 10 Mbps and equal to or less than 100 Mbps. See "Interface Groups of IPv4 or IPv6 Addresses" on page 368 for more examples of using the between Operator. • in Finds any match to at least one value in a list of values. Click here for an example. Example: ifName in <div data-bbox="446 1327 743 1461" data-label="Form"> <div>Value</div> <div>Fa0/14 Fa0/15</div> </div> finds all interfaces with names that are Fa0/14 or Fa0/15. <div data-bbox="464 1585 1320 1648" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (Fa0/14, Fa0/15). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example.

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<p>Example: <code>ifName is not null</code> finds all interfaces that have a name value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. Example: <code>ifName is null</code> finds all interfaces that do not have an assigned name value. like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The following attributes cannot be used with the <code>like</code> operator: <ul style="list-style-type: none"> ifIndex ifSpeed IPAddress <p>The asterisk (*) character means <i>any number of characters of any type at this location.</i></p> <p>The question mark (?) character means <i>any single character of any type at this location.</i></p> <p>Examples:</p> <ul style="list-style-type: none"> <code>ifName like ATM*</code> finds all interface names that begin with ATM. <code>ifName like Ethernet??*</code> finds all interface names that <i>begin with Ethernet</i> followed by two characters. <code>ifName like 10/???BASE-TX*</code> finds all interface names that have <i>specific characters at an exact location</i>, positions 1-3 (10/) and 7-13 (BASE-TX). not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ifSpeed not between 10000000 100000000</code> finds all interfaces with an (interface speed) ifSpeed less than 10 Mbps and greater than 100 Mbps. See "Interface Groups of IPv4 or IPv6 Addresses" on page 368 for more examples of using the not between Operator. not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ifName not in</code>

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<div data-bbox="451 317 745 453"> <p>Value</p> <div> Fa0/14 Fa0/15 </div> </div> <p>finds all interface name values other than Fa0/14 or Fa0/15.</p> <div data-bbox="469 575 1320 638"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (Fa0/14, Fa0/15). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p>The following attributes cannot be used with the not like operator:</p> <ul style="list-style-type: none"> ■ ifIndex ■ ifSpeed ■ IPAddress <p>The asterisk (*) character means <i>any number of characters of any type at this location</i>.</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Examples:</p> <ul style="list-style-type: none"> ■ ifName not like ATM* finds all interface names that do not begin with ATM. ■ ifName not like Ethernet??* finds all interface names that do not <i>begin with Ethernet</i> followed by two characters. ■ ifName not like 10/???BASE-TX* finds all interface names that do not have <i>specific characters at an exact location</i>, positions 1-3 (10/) and 7-13 (BASE-TX).
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive.

Additional Filters Editor Choices for Interface Groups, continued

Attribute	Description
	<ul style="list-style-type: none"> NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The in and not in operators require that each value be entered on a separate line. When entering a value for the Capability attribute, copy and paste the Unique Key value from the Interface form: Capability tab.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.

Additional Filters Editor Buttons, continued

Button	Description
	<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	Deletes the selected expression.

Additional Filters Editor Buttons, continued

Button	Description
	Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.

Interface Groups of IPv4 or IPv6 Addresses

Use the Interface Group form's Additional Filters Editor to create Interface Groups based on the following criteria ("[Specify Interface Group Additional Filters](#)" on page 358):

- All interfaces that have *only* IPv4 addresses

[\[click here for details of this filter.\]](#)

Both of the following example interface Group's Additional Filters provide the same results. The first example uses IPv4 address notation. The second example uses IPv6 address notation:

```
((ipAddress between 0.0.0.0 AND 255.255.255.255) AND NOT (ipAddress not  
between 0.0.0.0 AND 255.255.255.255))
```

or (NNMi Advanced)

```
((ipAddress between 0.0.0.0 AND 255.255.255.255) AND NOT (ipAddress not  
between ::ffff:0:0 AND ::ffff:ffff:ffff))
```

- All interfaces that have *any* IPv4 addresses (could also have IPv6)

[\[click here for details of this filter.\]](#)

The following example interface Group's Additional Filter finds any interface that has at least one IPv4 address:

```
(ipAddress between 0.0.0.0 AND 255.255.255.255)
```

- (NNMi Advanced) All interfaces that have *only* IPv6 addresses

[\[click here for details of this filter.\]](#)

IPv6 addresses extend the number of possible IP addresses. The old IPv4 address range is within the new IPv6 range. Valid IPv6 address values can be less than or greater than the old IPv4 range of addresses. NNMi Advanced converts the IPv4 addresses to the new IPv6 notation, then stores and filters the IPv4 addresses as IPv6 addresses (::ffff:a.b.c.d).

Both of the following example interface Group's Additional Filters provide the same results. The first example uses IPv4 address notation. The second example uses IPv6 address notation:

```
((ipAddress not between 0.0.0.0 AND 255.255.255.255) AND NOT (ipAddress  
between 0.0.0.0 AND 255.255.255.255))
```

or

```
((ipAddress not between ::ffff:0:0 AND ::ffff:ffff:ffff) AND NOT (ipAddress  
between 0.0.0.0 AND 255.255.255.255))
```

- (NNMi Advanced) All interfaces that have *any* IPv6 addresses (could also have IPv4)
[\[click here for details of this filter.\]](#)

The following example interface Group's Additional Filter finds any interface that has at least one IPv6 address:

```
((ipAddress between ::0 AND ::fffe:ffff:ffff) OR (ipAddress ::1:0:0:0 AND  
ffff:ffff:ffff:ffff:ffff:ffff:ffff:ffff))
```

- (NNMi Advanced) All interfaces that have *both* IPv4 and IPv6 addresses (also known as dual-stack interfaces)
[\[click here for details of this filter.\]](#)

The following example interface Group's Additional Filter finds any interface that has at least one IPv4 address and at least one IPv6 address:

```
((ipAddress between 0.0.0.0 AND 255.255.255.255) AND (ipAddress not between  
0.0.0.0 AND 255.255.255.255))
```

Note: To maximize the performance of Additional Filters based on an IP Address range, avoid multiple filter expressions. For example, use the *between* operator instead of the greater than or equal to (\geq) and less than or equal to (\leq) operators that cause NNMi to use multiple queries for finding all addresses that match the filter.

Guidelines for Creating Additional Filters for Interface Groups

The Additional Filters Editor enables you to create expressions to further define the interfaces to be included in an Interface Group. Make sure to design any complex Additional Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Additional Filters Editor.

When creating any Additional Filters for an Interface Group, note the following:

- Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- When using the AND operator to combine expressions that include Custom Attributes, include only one customAttrName/customAttrValue pair in a sub-expression.
- The AND and OR Boolean Operators must contain at least two expressions as shown in the example below.

```
AND
  ifName like ATMS*
  ifName != ATMS/0/A
OR
  ifSpeed = 10000000
  ifSpeed = 100000000
```

Note: As shown in the example above, you must use the actual ifSpeed number.

NNMi evaluates the expression above as follows:

```
(ifName like ATMS* AND ifName != ATMS/0/A) AND (ifSpeed = 10000000 OR ifSpeed = 100000000)
```

- NNMi finds all interfaces with an (interface name) ifName that begins with **ATMS**, but does not include **ATMS/0/A**.
- Of these interfaces, NNM then finds all interfaces with an (interface speed) ifSpeed of **10 Mbps** or **100 Mbps**.
- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.
- You can drag any of the following items to a new location in the Filter String:
 - Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS
 - Filter Expression (Attribute, Operator and Value)
- When moving items in the Filter String, note the following:
 - Click the item you want to move before dragging it to a new location.
 - As you drag a selected item, an underline indicates the target location.

- If you are moving the selection up, NNMi places the item above the target location.
- If you are moving the selection down, NNMi places the item below the target location.
- If you attempt to move the selection to an invalid target location, NNMi displays an error message.





Add New ifType Values (Interface Types) to the List

Interface Type definitions cover all known industry-standard IANA ifType-MIB values at the time of the release of NNMi. Interface Groups can be built using ifType filters. See ["Create Interface Groups" on page 356](#)

Occasionally new industry-standard ifType values are announced between releases of NNMi. If your team acquires new devices configured with new ifType values, you can add the new ifType values to NNMi's list of definitions.

When NNMi discovers an Interface that responds to an SNMP ifType query with a new value, NNMi automatically adds a new ifType using the IANA ifType-MIB Number value. NNMi uses that number for both the ifType attribute and the Number attribute values. You can provide a more meaningful ifType text string and optional description.

To configure an IANA ifType-MIB definition:

1. Navigate to the **ifTypes** view:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **MIBs**.
 - c. Select the **ifTypes** view.
2. Do one of the following:
 - To create an ifType definition, click the  New icon, and continue.
 - To edit an ifType definition, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an ifType definition, select a row and click the  Delete icon.
3. In the [ifType form](#), provide the ifType text string, number, and description.
4. Click  **Save and Close**.

From the Command Line, Define Interface Groups

Interface Groups are used for a variety of purposes in NNMi. See ["Creating Groups of Nodes or Interfaces" on page 325](#) for more information.

You can create any number of Interface Groups in addition to the ones that NNMi provides (see ["Interface Groups Provided by NNMi" on page 376](#)).

Use the following command-line tool to create or modify existing Interface Groups:

- See the [nnmloadinterfacegroups.ovpl](#) Reference Page.

This command is used in combination with a comma separated values (CSV) file - for example, a Microsoft Excel spreadsheet saved as a .csv file.

To create Node Groups using a CSV file, see ["From the Command Line, Define Node Groups" on page 351](#)

Troubleshooting Interface Changes

If your Interface Group definition results in unexpected membership or the membership changes, consider the strategy NNMi uses to detect Interfaces during Spiral Discovery.

During each Spiral Discovery cycle, NNMi responds to Interface changes as follows:

1. NNMi updates the attribute value of the current Interface object if one (*and only one*) of the following attributes change:
 - ifIndex or IfAlias or ifSpeed
2. NNMi creates a new Interface object and deletes the old Interface object if any of the following criteria are met:
 - a. At least one of these attributes change: ifName, ifDescr (descriptions), ifType, or Physical Address (Mac address, Media Access Control address).
 - b. More than one of these attributes change: ifIndex or IfAlias or ifSpeed.
 - c. One or more attributes from the list of both criteria 1 & 2 change.

Note: If using [nnmconnect.ovpl](#) configuration files, any connection settings configured for the deleted Interface would be evaluated for the new Interface object's current attribute settings.

Node Groups Provided by NNMi

NNMi Provides the following kinds of Node Groups:

- [Node Groups as Predefined View Filters](#). These Node Groups can also be used for Monitoring Configuration if you find them useful.
- ["Island Node Groups" on page 375](#). NNMi automatically creates Island Node Groups whenever it detects changes in Layer 2 Connections. An Island Node Group is a group of fully-connected nodes that NNMi displays in a group that is not connected to the rest of the topology.

Node Groups As Predefined View Filters


NNMi provides the following Node Groups. You can configure these Node Groups with specific information about your management domain and change them to meet your needs.

Caution: Do not delete these Node Groups.

Node Groups can be used to filter table views and map views, used for multiple configuration tasks, and exported to NNM iSPI Performance for Metrics and NNM iSPI Performance for Traffic for report filters -- [click here for more information](#).

Note: Node Groups can contain child Node Groups.

Node Groups Provided by NNMi

Name	Purpose
Important Nodes	<p>This Node Group is used by the Causal Engine. Any devices in this group receive special treatment. When a current member of this group stops responding, the Causal Engine generates a "Node Down" incident and sets the device status to Critical. For example, when a WAN Edge Device is in the shadow of another problem (and, therefore, NNMi would normally not generate an incident about that WAN edge router), NNMi generates a "Node Down" incident because the router is listed in this Important Nodes group.</p> <p>This Node Group is empty by default. Consider populating this group with critical servers that run important applications and critical WAN routers.</p> <p>(NNM iSPI Performance) This group automatically becomes a filter for Performance Reports (unless the group has no members). The NNMi administrator can change this default behavior. See "Create Node Groups Using Filters or Hostname Lists (Configuration: Node Groups)" on page 327.</p>
Microsoft Windows Systems	<p>This Node Group includes any device manufactured by Microsoft. The Node Group definition is populated with one vendor entry. Any Microsoft devices within your management domain are automatically included in this Node Group.</p>
Neighbor Connections Filter	<p>Your NNMi administrator can configure a Node Group map to show devices that are connected to Node Group members (one-hop neighbors), but not themselves a member.</p> <p>A gray halo around the map icon indicates a one-hop neighbor:</p>  <p>Not all one-hop neighbors are shown. Your NNMi administrator chooses a</p>

Node Groups Provided by NNMi, continued

Name	Purpose
	particular Node Group as the Neighbor Connections Filter. Only one-hop devices within the specified Node Group are displayed.
Networking Infrastructure Devices	<p>This Node Group is populated with a list of categories for network devices. Any devices within your management domain that match these categories are automatically included in this Node Group.</p> <p>Devices in this group are automatically monitored for Node Sensor and Physical Sensor fault metrics.</p> <p><i>(NNM iSPI Performance)</i> This group automatically becomes a filter for Performance Reports (unless the group has no members). The NNMi administrator can change this default behavior. See "Create Node Groups Using Filters or Hostname Lists (Configuration: Node Groups)" on page 327.</p> <p><i>(NNM iSPI NET)</i> By default, HP Network Node Manager iSPI Network Engineering Toolset Software automatically uses diagnostic flows to monitor devices in this group.</p>
Non-SNMP Devices	<p>This Node Group includes any device that does not respond to SNMP. The Node Group definition is populated with one entry for a null MIB-II sysObjectID value. Any device within your management domain that fails to respond to SNMP queries is automatically included in this Node Group.</p>
Routers	<p>This Node Group is populated with a list of categories for network devices that represent routers. Any router, switch-router, or gateway within your management domain is included in this Node Group. See Node Capabilities Provided by NNMi for more information.</p> <p>This filter is used to create the Routers Node Group map that NNMi provides by default in the Topology Maps workspace.</p> <p>Devices in this group are automatically monitored for Node Sensor and Physical Sensor fault metrics.</p> <p><i>(NNM iSPI Performance)</i> Devices in this group are automatically monitored for performance, including Node Sensor and Physical Sensor performance metrics. This group automatically becomes a filter for Performance Reports.</p> <p>The NNMi administrator can change this default behavior. See "Default Settings for Monitoring" on page 393, "Node Settings for Monitoring" on page 443, and "Create Node Groups Using Filters or Hostname Lists (Configuration: Node Groups)" on page 327 for more information.</p>
Switches	<p>This Node Group is populated with a list of categories for network devices that represent switches. Any switch, ATM switch, or switch-router within your management domain is included in this Node Group. See Node Capabilities Provided by NNMi for more information.</p> <p>This filter is used to create the Switches Node Group map that NNMi provides by default in the Topology Maps workspace.</p>

Node Groups Provided by *NNMi Advanced*

Name	Purpose
Virtual Machines	(<i>NNMi Advanced</i>) Virtual machines being hosted on a VMware ESX/ESXi server. These servers are identified by a <code>com.hp.nnm.capability.node.VM</code> capability.
VMware ESX Hosts	(<i>NNMi Advanced</i>) A VMware ESX/ESXi server that is hosting virtual machines. These servers are identified by a <code>com.hp.nnm.capability.node.hypervisor.vmware.ESX</code> capability.

Related Topics

["Island Node Groups" below](#) (dynamically generated Node Groups)

Island Node Groups

An Island Group is a group of fully-connected nodes discovered by NNMi, and NNMi determines this group is not connected to the rest of the topology.

An example of an environment with multiple Island Node Groups is a financial institution or retail store with many branches or stores. Each branch or store might be connected to other branches or stores with a WAN (Wide Area Network) connection. Each branch or store appears as an isolated island of nodes in the NNMi topology.

NNMi automatically updates Island Node Group discovery information whenever it detects changes in Layer 2 Connections. NNMi begins rediscovery of the Island Node Group within a range of 10 seconds to 10 minutes, depending on current network traffic volume. NNMi uses the Discovery Interval to determine when the updates occur.

Note the following about Island Node Groups:

- NNMi selects a representative node in each Island Node Group as the Source Node associated with an Island Node Group incident. The representative node is selected using the following criteria:
 - Sort all routers in the Node Group alphabetically by name and choose the first one in the list
 - If no routers are in the Node Group, sort all nodes in the Node Group alphabetically by name and choose the first one in the list.
- Island Node Groups are identified using "Island" in the Node Group Name. NNMi also assigns each Island Node Group name a number to ensure the name is unique.
- Island Node Groups are managed internally. Therefore, NNMi administrators should not modify Island Node Group configurations. NNMi overrides any user changes the next time NNMi updates the Island Node Group discovery information.
- Island Node Groups must have at least two nodes.
- How the Status of Island Node Groups is calculated cannot be changed.

The only possible Status values for Island Node Groups are Unknown and Normal. Unknown indicates that NNMi cannot reach any nodes in the group. Normal indicates that NNMi can reach at least one node in the group.

Related Topics

["Node Groups As Predefined View Filters" on page 373](#)

Interface Groups Provided by NNMi

NNMi Provides the following Interface Groups as predefined view filters. These Interface Groups can also be used for Monitoring Configuration if you find them useful.

Feel free to populate these Interface Groups with specific information about your management domain and change them to meet your needs.

Interface Groups Provided by NNMi

Name	Purpose
ATM Interfaces	This Interface Group includes all Interfaces identified as Asynchronous Transfer Mode (ATM) links. These Interfaces use a cell-based switching technique using asynchronous time division multiplexing.
DSx Interfaces	This Interface Group includes all Interfaces identified as Digital signal 1 (DS1, also known as T1) links. These Interfaces use a T-carrier signaling scheme to transmit voice and data between devices. Digital Signal 3 (DS3, also known as T3) links use a digital signal level 3 T-carrier.
Frame Relay Interfaces	This Interface Group includes all Interfaces identified as Frame Relay links. These Interfaces use a standardized wide area networking technology that specifies the physical and logical link layers of digital telecommunications channels using a packet switching methodology.
ISDN Interfaces	This Interface Group includes multiple Interface types known to be commonly used for ISDN purposes. Any Interface within your management domain that meets the defined criteria is automatically included in this Interface Group.
Link Aggregation Interfaces	(NNMi Advanced) Link Aggregation ¹ or Split Link Aggregation ² protocols: This Interface Group includes all <i>Aggregator Interfaces</i> . Network administrators can configure multiple <i>Aggregation Member Interfaces</i> on a switch to behave as one, the Aggregator Interface. This technique uses multiple interfaces in parallel to

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Interface Groups Provided by NNMi, continued

Name	Purpose
	increase bandwidth, increase the speed at which data travels, and increase redundancy. See the Interface Form: Link Aggregation tab's Help topic for more information about Interfaces with Capability set to Aggregator Interface.
Point to Point Interfaces	This Interface Group includes multiple Interface types known to be commonly used for point-to-point purposes. Any Interface within your management domain that meets the defined criteria is automatically included in this Interface Group.
SONET Interfaces	This Interface Group includes all Interfaces identified as Synchronous Optical Networking (SONET) or Synchronous Digital Hierarchy (SDH) links. These Interfaces use a standardized multiplexing protocol that transfers multiple digital bit streams over optical fiber using lasers or light-emitting diodes (LEDs).
Software Loopback Interfaces	This Interface Group includes any Interface with an <code>ifTypeNumber</code> value of 24, software loopback from the IANA <code>ifType-MIB</code> . Any Interface within your management domain that meets this loopback address ¹ criteria is automatically included in this Interface Group.
VLAN Interfaces	This Interface Group includes Interfaces of <code>ifTypeNumber</code> value of 135. The NNMi default Monitoring Configuration settings enable fault monitoring for these Interfaces, but disable performance monitoring (because collection of performance data for VLAN Interfaces tends to be problematic).
Voice Interfaces	This Interface Group includes multiple interface types known to be commonly used for voice purposes. Any Interface within your management domain that meets the defined criteria is automatically included in this Interface Group.
WLAN Interfaces	This Interface Group includes all Interfaces identified as Wireless Local Area Network (WLAN) links. These Interfaces connect two or more devices using some wireless distribution method, and might provide a connection through an access point to the wider Internet.

¹The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using `ifType Number 24`, softwareloopback from the IANA `ifType-MIB`.

Chapter 9: Monitoring Network Health

NNMi administrators control which network devices NNMi monitors. By monitoring only the devices that are important within your network environment, the amount of traffic generated by NNMi is kept to a minimum. NNMi administrators can configure NNMi to check devices with status *other than critical* less frequently (if at all) to prevent unimportant incidents from showing up in the Incident views.

Before configuring NNMi monitoring behavior, the following tasks must be completed:

- ["Configuring Communication Protocol" on page 129](#)
- ["Discovering Your Network" on page 194](#)

For the most flexibility, also complete these tasks:

- Review the ["Interface Groups Provided by NNMi" on page 376](#) and ["Node Groups Provided by NNMi" on page 372](#).
- Create your own groups by ["Creating Groups of Nodes or Interfaces" on page 325](#).

For ideas about what is possible, see these topics:

- ["Examples of Count-Based Threshold Monitoring" below](#)
- ["Examples of Time-Based Threshold Monitoring" on page 382](#)

NNMi administrators configure NNMi monitoring behavior to meet your team's needs:

1. Start by establishing the appropriate settings for the monitoring tools provided by NNMi. See ["Configure NNMi Monitoring Behavior" on page 387](#).

The State Poller and the Causal Engine work together to monitor the health of your network. Many of the tasks your team normally does to troubleshoot network problems can be automated. To learn more about how this works, see the following topics:

- ["About the State Poller" on page 389](#)
 - ["The NNMi Causal Engine and Monitoring" on page 390](#)
2. Then write your own custom monitoring tools to meet any special requirements for your team. See ["Create Custom Polling Configurations" on page 478](#).

Examples of Count-Based Threshold Monitoring

There are two alternatives for configuring these example thresholds in NNMi:

- Just provide a few settings ("[Configure Count-Based Threshold Monitoring for Node Groups](#)" on page 458 and "[Configure Count-Based Threshold Monitoring for Interface Groups](#)" on page 426).
- Use the Custom Poller configuration and polling policies to create the required logic ("[Create Custom Polling Configurations](#)" on page 478).

Several examples of Count-Based Threshold Settings are presented. These examples are not intended to be recommendations. Consider all aspects of your network environment and set performance thresholds that are meaningful in your environment.


Example 1: Monitor Utilization on WAN Connections

You want to monitor the connections between two sites to verify that your service provider is meeting their guaranteed throughput volume. You pay a fixed cost for a specific bandwidth over this WAN interface.

- Monitor for under-utilization which wastes money (less than 10%).

Tip: If you do not care about under-utilization, set Low Value and Low Value Rearm to 0% as shown in Example 2. The Low Value threshold is then disabled because it cannot be crossed.

- Monitor for over-utilization (greater than 80%), which might result in performance bottlenecks or service provider surcharges.



Note: Sometimes an Interface's MIB-II ifspeed value is not reported accurately.

This might result in threshold calculations outside the 0.00 - 100.00 range. If this happens, the Interface threshold State set to "Unavailable." [To correct the problem:](#)


1. Access the **Inventory** workspace

2. Open **Interface** view.
3. Open the form for the Interface that is reporting a threshold state of "Unavailable."
4. Navigate to the **General** tab.
5. Enter a valid entry in **Input Speed** or **Output Speed** (this overrides the value returned by the device's SNMP agent so that NNMi can accurately calculate utilization thresholds).

Example 2: Monitor Utilization on Important Interfaces

You want to monitor an important Ethernet interface and be notified if it is getting overloaded.

An Ethernet interface configured for full-duplex operation has an acceptable operating range of 0-60%. When average utilization is greater than 60%, you want NNM to generate a High Threshold incident.




Example 3: Monitor Utilization on Important Interfaces for States (High, Nominal, None)

You want to monitor an important Ethernet interface and be notified if it is getting overloaded or if no data has passed through the interface during the polling interval. This might indicate a problem with the interface or its connection. If a formerly connected interface is *Administratively Down*, NNMi honors that and does not generate a fault condition.

This example monitors for the following:


- When the average utilization is greater than 60%
- When zero data is passing through the interface

Tip: The Low Value of 0.000000000000001 used in this example because it is the smallest value greater than zero available in NNMi. When you configure a Threshold, to use this value, simply type 1E-15 and press Enter. NNMi converts that Scientific Notation to the text string 0.000000000000001 (with 1 entered in the 15th position after the decimal).



Example 4: Monitor Important Interfaces for Discards


You want to know any time an interface is dropping data. The acceptable limit for interface discards is 10%. A High Threshold situation occurs when the discard rate exceeds 10% and returns to Nominal when the discard rate drops below 5%.



Example 5: Monitor Important Interfaces for Errors

You want to know if packet errors occur. The acceptable limit for packet errors is 2%. A High Threshold situation occurs when the error rate exceeds 2% and returns to normal when the error rate drops below 1%.

Tip: To monitor for any errors greater than zero, set the **High Value**, **High Value Rearm**, **Low Value**, and **Low Value Rearm** to: 0.0



Examples of Time-Based Threshold Monitoring

There are two alternatives for configuring these example thresholds in NNMi:

- Just provide a few settings ("[Configure Time-Based Threshold Monitoring for Node Groups](#)" on page 462 and "[Configure Time-Based Threshold Monitoring for Interface Groups](#)" on page 430).
- Use the Custom Poller configuration and polling policies to create the required logic ("[Create Custom Polling Configurations](#)" on page 478).


Several Time-Based Threshold Settings examples are presented. These examples are not intended to be recommendations. Consider all aspects of your network environment and set performance thresholds that are meaningful in your environment.

Example 1: Monitor CPU Utilization for an Important Node

You want to know when the CPU Utilization is above 75% for 20 out of 30 minutes. A High Threshold situation occurs when the CPU Utilization exceeds 75% for 20 out of 30 minutes and returns to normal when the Utilization drops below 70%.

High Value: 75%
High Value Rearm: 70%
High Duration: 20 minutes


High Duration Window: 30 minute
Polling Interval: 5 minutes



Example 2: Monitor Important Interfaces for Interface Input Utilization

You want to know when the Bandwidth Utilization is above 90% for 30 out of 30 minutes. A High Threshold situation occurs when the bandwidth utilization exceeds 90% for 30 out of 30 minutes and returns to normal when the utilization drops below 80%.

High Value: 90%
High Value Rearm: 80%
High Duration: 30 minutes
High Duration Window: 30 minutes
Polling Interval: 5 minutes



Example 3: Monitor Using Rearm Values

You want to reduce the frequency of interface State changes when the polled value is close to the threshold.

The first example shows the Performance Polling results with **High Value Rearm** set to 80% (same percentage as the threshold).


High Value: 80%

High Value Rearm: 80%

High Duration: 10 minutes


High Duration Window: 15 minutes

Polling Interval: 5 minutes



The second example shows the same set of Performance Polling results with **High Value Rearm** set to 50%.


High Value: 80%
High Value Rearm: 50%
High Duration: 10 minutes
High Duration Window: 15 minutes
Polling Interval: 5 minutes



Example 4: Monitor Important Interfaces for Interface Errors

You want to know when the Interface Errors are above 10% for 15 out of 20 minutes. A High Threshold situation occurs when the interface errors exceed 10% for 15 out of 20 minutes and returns to normal when the interface errors drops below 5%.


High Value: 10%
High Value Rearm: 5%
High Duration: 15 minutes
High Duration Window: 20 minutes
Polling Interval: 5 minutes



Example 5: Monitor Important Interfaces for Interface Discards

You want to know when the Interface Discards are above 10% for 30 out of 45 minutes. A High Threshold situation occurs when the interface discards exceed 10% for 30 out of 45 minutes and returns to normal when the interface discards drop below 5%.

High Value: 10%
High Value Rearm: 5 %
High Duration: 30 minutes
High Duration Window: 45 minutes
Polling Interval: 5 minutes



Configure NNMi Monitoring Behavior

Certain devices in your network are the most important ones. You and your team must keep those devices up and running at all times. Adjust NNMi monitoring behavior to focus on the important devices and to check devices with status *other than critical* less frequently (if at all).

Note: NNMi does not poll any [private interface](#), IPv4 [Anycast Rendezvous Point IP Address](#)¹ or IPv6 Anycast address.

Based on your individual situation, adjust the NNMi behavior to meet your needs. NNMi applies your Monitoring Configuration settings in the following sequence:

1. **Interface Settings:** NNMi monitors each of the Node's Interfaces and IP Addresses based on the first matching Interface Settings definition. The first match is the Interface Settings definition with the lowest Ordering number, then Baseline Settings.
2. **Node Settings:** NNMi monitors each Node and each previously unmatched Interface or IP Address based on the first matching Node Settings definition. The first match is the Node Settings definition with the lowest Ordering number, then Baseline Settings.

Note: Child node groups are included in the Ordering hierarchy. This means that if the parent node group has a lower Ordering number (for example, parent=10, child=20), then the monitoring configuration specified for the parent node group also applies to the nodes in the child node group. To override a parent node group monitoring configuration, set the Ordering number for the child node group to a number that is lower than the parent (for example, parent=20, child=10).

3. **Default Settings:** If no match is found for a Node, Interface, or IP Address in 1 or 2, NNMi applies the default Monitoring Configuration settings.

Tasks for Configuring the Monitoring Behavior

Task	How
"Global Control Settings for Monitoring" on page 391.	<i>Optional.</i> Use the Global Control group.
"Default Settings for Monitoring" on page 393.	Use the Default Settings tab to establish monitoring behavior for any devices that are discovered, but not included in any Node Settings or Interface Settings definitions.
"Interface Settings for Monitoring" on page 416.	<i>Optional.</i> Use the Interface Settings tab. Configure settings based on Interface Groups to customize the way NNMi monitors certain groups of interfaces in your environment. Prerequisite: "Create Interface Groups" on page 356.
"Node Settings for Monitoring" on page 443.	<i>Optional.</i> Use the Node Settings tab. Configure settings based on Node Groups to customize the way NNMi monitors certain groups of devices in your environment. Prerequisite: "Create Node Groups" on page 326.

¹Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

Tasks for Configuring the Monitoring Behavior, continued

Task	How
"Detect Interface Changes" on page 311.	<i>Optional.</i> Use Device Profiles to configure how NNMi detects interface changes.
"Monitor Router Redundancy Groups (NNMi Advanced)" on page 474.	<i>Optional.</i> Use additional settings to fine tune the way NNMi monitors Router Redundancy Groups.

About the State Poller

The State Poller Service monitors each discovered interface, address, card, and SNMP agent that is designated to be actively monitored in your management domain. State Poller can also be configured to provide Node Sensor, Physical Sensor, and Router Redundancy Group monitoring.

State Poller gathers information in the following area and updates the **State** field on each object's form:

- Verifies that each monitored IP Address is responding to ICMP ping.
- Verifies that each monitored SNMP Agent is responding to SNMP queries.
- Issues SNMP queries for the following:
 - Each monitored interface, requesting the current value for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)
 - Router Redundancy Groups.
 - Node Sensor data.
 - Physical Sensor data.
- By default, State Poller monitors interfaces connected to another known interface through a Layer 2 Connection.
- You can extend monitoring to include the following:
 - Unconnected interfaces
 - Interfaces that have an IP address (for example a router interface that services mobile laptop machines)
 - (NNMiSPI Performance for Metrics). The State Poller also collects performance data and monitors thresholds. See ["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515.](#)

The State Poller stores the State changes resulting from the queries in the NNMi database and notifies the Causal Engine of any changes. When notifying the Causal Engine of any changes, the State Poller sends only those State values that have changed.

Tip: To force the State Poller to send the Causal Engine all of the State information it can collect regardless of changes, use **Actions** → **Status Poll** or the `nnmstatuspoll.ovpl` command. See [Verify the Current Status for a Device](#) for more information about Status Poll.

The Causal Engine gathers additional information about the overall health of each interface and SNMP agent. Using the State information collected from the State Poller as well as this additional information the Causal Engine calculates the **Status** of each node, interface, and SNMP agent.

Note: Any time the State Poller sends updated State values for a selected object, the Causal Engine reanalyzes Status, Conclusions, and Incidents, and updates this information if needed.

See ["The NNMi Causal Engine and Monitoring"](#) below for more information.

To configure the behavior of the State Poller, see:

- ["Default Settings for Monitoring" on page 393](#)
- ["Global Control Settings for Monitoring" on the next page](#)
- ["Configure Default SNMP, Management Address, and ICMP Settings" on page 130](#)

The NNMi Causal Engine and Monitoring

The Causal Engine actively gathers information about your network devices from incoming incidents and traps. The Causal Engine also uses the data gathered by [State Poller](#) and by [Spiral Discovery](#) to calculate the current health status of each managed object.

The health status is dynamic (based on the current reality of your network environment). Any time the State Poller sends updated State values for an object, the Causal Engine reanalyzes Status, Conclusions, and Incidents, and updates this information if needed.

Note: The Causal Engine performs a Status Poll of each node every 24 hours and updates Status, Conclusion, and Incident information as needed. This Status Poll does not affect the timing of the Polling interval configured for the device.

The NNMi Causal Engine communicates device health information in the following ways:

- In the database, the Causal Engine stores a multitude of information about each device. You can access this information in the Node, Interface, IP Address, SNMP Agent, and connection forms.
- On the maps, the color of the background shape for each map icon changes to the color that represents the currently calculated health status, based on Causal Engine calculations for that node, interface, address, or connection ([click here for information about status colors](#)).

- On forms for Nodes, Interfaces, IP addresses, SNMP Agents, and connections, the Causal Engine updates the Status attribute to show the current status: **Normal**, **Warning**, **Minor**, **Major**, **Critical**, **Unknown**, or **No Status**.
- The Status column in table views is updated.

The Causal Engine also uses health status information to determine root cause. See ["The NNMi Causal Engine and Incidents" on page 670](#) for more information about the Causal Engine, incidents, and root cause analysis.

Global Control Settings for Monitoring

Note: To suspend all SNMP traffic generated by NNMi, rather than only the State Poller Service SNMP traffic, see ["Communication Region Form" on page 150](#) and ["Specific Node Settings Form \(Communication Settings\)" on page 171](#).

Tip: By default, NNMi suppresses the monitoring of IP addresses on interfaces that are administratively down. You can configure this behavior by editing the `nms-disco.properties` file. See the "Maintaining NNMi" chapter of the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To temporarily turn off all NNMi monitoring activity without tampering with your customized monitoring configuration settings:

1. Navigate to the **Monitoring Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Monitoring Configuration**.
2. Locate the **Global Control** group box and for each setting do the following (see [table](#)):

☐ = disable

☒ = enable
3. Click **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.

Global Control

Name	Description
Enable State Polling	If <input checked="" type="checkbox"/> enabled, State Poller monitors all managed objects (for example, interfaces, IP addresses, and SNMP agents) by issuing ICMP pings and SNMP read-only

Global Control , continued

Name	Description
	<p>queries for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the overall health of the device and is supplied by the SNMP Agent.) You can also configure NNMi so that State Poller gathers additional information about Node Sensors, Physical Sensors, and Router Redundancy Groups.</p> <p>If <input type="checkbox"/> disabled:</p> <ul style="list-style-type: none"> Previously discovered devices remain with the last calculated state/status. Newly discovered devices are set to "No Status" with map-symbol background shape color set to beige.
Enable Card Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors all managed cards. See Card Form for more information about card metrics.</p> <div data-bbox="456 821 1370 898" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: Card monitoring is enabled by default.</p> </div> <p>If <input type="checkbox"/> disabled:</p> <ul style="list-style-type: none"> Previously discovered cards are assigned a State of Not Polled and a Status of No Status for Card metrics. Newly discovered cards are assigned a State of Not Polled and a Status of No Status.
Enable Chassis Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors all managed chassis. See Chassis Form for more information about chassis metrics.</p> <div data-bbox="456 1262 1370 1339" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: Chassis monitoring is enabled by default.</p> </div> <p>If <input type="checkbox"/> disabled:</p> <ul style="list-style-type: none"> Previously discovered chassis are assigned a State of Not Polled and a Status of No Status for chassis metrics. Newly discovered chassis are assigned a State of Not Polled and a Status of No Status.
Enable Node Sensor Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors Node Sensor metrics for all managed nodes. See Node Form: Node Sensor Tab for more information about Node Sensor metrics.</p> <div data-bbox="456 1738 1370 1816" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: Node Sensor Polling is enabled by default.</p> </div> <p>If <input type="checkbox"/> disabled:</p>

Global Control , continued

Name	Description
	<ul style="list-style-type: none"> Previously discovered devices are assigned a State of Not Polled and a Status of No Status for Node Sensor metrics. Node Sensor metrics for newly discovered devices are assigned a State of Not Polled and a Status of No Status.
Enable Physical Sensor Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors Physical Sensor metrics for all managed chassis and cards. See Chassis Form: Physical Sensor Tab and Card Form: Physical Sensor Tab for more information about Physical Sensor metrics.</p> <p>Note: Physical Sensor Polling is enabled by default. Only the Physical Sensor States for Fan and Power Supply contribute towards the status calculation for the host node.</p> <p>If <input type="checkbox"/> disabled:</p> <ul style="list-style-type: none"> Previously discovered devices are assigned a State of Not Polled and a Status of No Status for Physical Sensor metrics. Physical Sensor metrics for newly discovered devices are assigned a State of Not Polled and a Status of No Status.
Enable Router Redundancy Group Polling (NNMi Advanced)	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all managed Router Redundancy Groups. See Router Redundancy Group View (NNMi Advanced) for more information about Router Redundancy Groups.</p> <p>Note: Router Redundancy Group monitoring is enabled by default.</p> <p>If <input type="checkbox"/> disabled:</p> <ul style="list-style-type: none"> Previously discovered Router Redundancy Groups are assigned a State of Not Polled and a Status of No Status. Newly discovered Router Redundancy Groups are assigned a State of Not Polled and a Status of No Status.

Default Settings for Monitoring

The choices you make for "defaults" apply only to devices with interfaces, IP addresses, chassis, cards, SNMP agents (Management Addresses), Tracked Objects, Router Redundancy Groups, Node Sensors, or Physical Sensors that are not covered by any monitoring Interface Settings or Node Settings.

To establish default NNMi monitoring behavior:


1. Navigate to the **Defaults Settings** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Locate the **Defaults Settings** tab.
2. To prevent NNMi from generating any SNMP traffic to Nodes that are not covered by Monitoring Configuration's Node Settings. See [Enable SNMP Polling on Node](#).
3. Locate the **Default Fault Monitoring** group box.
 - a. Configure the Default Fault Monitoring behavior for ICMP traffic (see [Default Fault Monitoring table](#) ICMP Fault Monitoring).
 - b. Configure the Default Fault Monitoring behavior for SNMP traffic (see [Default Fault Monitoring table](#) SNMP Fault Monitoring).
 - c. Configure the Default Fault Monitoring: interval (see [Default Fault Monitoring: table](#) Fault Polling Interval).

4. (*NNMi SPI Performance for Metrics*) If the HP Network Node Manager iSPI Performance for Metrics Software is installed, locate the **Default Performance Monitoring** group box.

Configure the Default Performance Monitoring behavior (see and [Default SNMP Performance Monitoring table](#)).

5. By default, NNMi monitors only interfaces that are connected to other interfaces. When SNMP polling is enabled, NNMi automatically detects most connections. See "[Add or Delete a Layer 2 Connection](#)" on page 314 for information about manual overrides.

Optional. If you want to expand default monitoring behavior to include unconnected Interfaces, indicate your choices in the [Default Extend the Scope of Polling Beyond Connected Interfaces](#) group box

6. *Optional.* Configure the Default Change Detection Monitoring (see [Default Change Detection Monitoring table](#)).
7. *Optional.* To establish custom monitoring behavior for one or more groups of interfaces, configure Interface Settings, see "[Interface Settings for Monitoring](#)" on page 416.
8. *Optional.* To establish custom monitoring behavior for one or more groups of nodes, configure Node Settings, see "[Node Settings for Monitoring](#)" on page 443.
9. Click  **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.

Caution: When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment.

Default Monitoring

Attribute	Description
Enable SNMP Polling on Node	<p>If <input checked="" type="checkbox"/> enabled, NNMi contacts the SNMP Agent on each node in your network to gather SNMP data for monitoring purposes (unless the Monitoring Configuration's Node Settings specifically disables SNMP for monitoring purposes).</p> <p>If <input type="checkbox"/> disabled, NNMi does not contact the SNMP Agent on this node for monitoring purposes (does not generate SNMP traffic to the node).</p> <p>Note: If you use Auto-Discovery, NNMi might detect Nodes and add them to the NNMi database as non-SNMP nodes. To configure Auto-Discovery to not add specified IP addresses to the NNMi database, not acknowledge any Hints received about them, nor gather Discovery Hints from them unless the address is a discovery seed, see "Set Outside Limits for Auto-Discovery" on page 251.</p>

Default Fault Monitoring

Attribute	Description
ICMP Fault Monitoring	<p>Enable Management Address Polling</p> <p>If <input checked="" type="checkbox"/> enabled, State Poller only issues ICMP (ping) requests to the management address for a node.</p> <p>Note: In the Global Control section of the Monitoring Configuration form, the Enable State Polling attribute must be enabled, too.</p> <p>If <input type="checkbox"/> disabled, State Poller does one of the following:</p> <ul style="list-style-type: none"> • If neither this attribute nor <i>Enable ICMP Fault Polling</i> is selected, State Poller does not use ICMP to monitor nodes covered by this configuration setting. • If <i>Enable ICMP Fault Polling</i> is selected, State Poller uses ICMP to monitor ALL IP addresses covered by this configuration setting. <p>Changing the default monitoring settings for the management addresses takes effect immediately. To verify the change, see "Verify the Monitoring Settings" on page 474.</p>
	<p>Enable IP Address</p> <p>Note: This monitoring option is useful for devices that do not</p>

Default Fault Monitoring, continued

Attribute		Description
	Fault Polling	<p>support SNMP. By default, this feature is enabled for the "Non-SNMP Devices" Node Group.</p> <p>If <input checked="" type="checkbox"/> enabled, State Poller issues ICMP (ping) requests to verify the availability of discovered IP address.</p> <p>Note: In the Global Control section of this form, the Enable State Polling attribute must be enabled, too.</p> <p>If <input type="checkbox"/> disabled, State Poller does the following:</p> <ul style="list-style-type: none"> • If neither this attribute nor <i>Management IP Address Polling</i> is selected, State Poller does not use ICMP to monitor nodes covered by this configuration setting. • IP addresses (both previously discovered and newly discovered) have a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the color of the IP address map-symbol set to beige. See Layer 3 Neighbor View. • If both ICMP and SNMP are disabled for a Node, the Node has a Status attribute value of "No Status" and the color of the Node map-symbol background shape is set to beige. <p>Tip: To turn off ICMP polling within a subset of your network environment, use the Communication Configuration workspace Region definitions. You can define your own Regions that identify any unreachable addresses in your management domain (for example, the private IP addresses¹).</p>
SNMP Fault Monitoring	Enable Interface Fault Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors all interfaces by issuing SNMP read-only queries to devices assigned to this level of the monitoring hierarchy.</p> <p>By default, any connected interface is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.) If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior with the Poll Unconnected Interfaces and the Poll Interfaces Hosting IP</p>

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*., 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

Default Fault Monitoring, continued

Attribute	Description
	<p>Addresses attributes.</p> <div data-bbox="617 380 1370 453"> <p>Note: The following attributes must also be enabled:</p> </div> <ul style="list-style-type: none"> • In the Global Control section of this form, the Enable State Polling attribute must be enabled, too. See Layer 2 Neighbor View. (See "Global Control Settings for Monitoring" on page 391 for more information.) • In the Communication Configuration view, enable State Poller queries with the applicable Enable SNMP Communication attributes (see "Configuring Communication Protocol" on page 129 for more information). <p>If <input type="checkbox"/> disabled, for devices assigned to this level of the monitoring hierarchy:</p> <ul style="list-style-type: none"> • Causal Engine calculates Status based only on IP address State. • The Interface objects previously discovered change to a State attribute value of "Not Polled" and a Status attribute value of "No Status" (plus any related map-symbol changes to a beige color).
Enable Card Fault Polling	<p>Use this attribute to poll fault metrics for cards. Card fault metrics include Administrative State, Operational State, and Standby State.</p> <div data-bbox="617 1257 1370 1331"> <p>Note: Card Fault Polling is enabled by default.</p> </div> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the card fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include card fault data about devices assigned to this level of the monitoring hierarchy.</p> <div data-bbox="617 1604 1370 1713"> <p>Tip: NNMi uses the same polling interval set for the Fault Polling Interval.</p> </div>
Enable Chassis Fault Polling	<p>Use this attribute to poll fault metrics for chassis. Chassis fault metrics include Administrative State, Operational State, and Standby State.</p>

Default Fault Monitoring, continued

Attribute	Description
	<p>Note: Chassis Fault Polling is enabled by default.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the chassis fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include chassis fault data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the same polling interval set for the Fault Polling Interval.</p>
Enable Node Sensor Fault Polling	<p>Note: Node Sensor Fault Polling is disabled here by default.</p> <p>Use this attribute to poll Node Sensor fault metrics.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the Node Sensor fault data in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Node Sensor fault data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the current setting for the Fault Polling Interval in combination with this setting.</p>
Enable Physical Sensor Fault Polling	<p>Note: Physical Sensor Fault Polling is disabled here by default.</p> <p>Use this attribute to poll for Physical Sensor faults on fan, power supply, temperature, and voltage. Only the health of the power supply and fan Physical Sensors are propagated to the Node level to affect Node Status.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the Physical Sensor fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Physical Sensor fault data about devices assigned to this level of the monitoring hierarchy.</p>

Default Fault Monitoring, continued

Attribute		Description
		<p>Tip: NNMi uses the current setting for the Fault Polling Interval in combination with this setting.</p>
Fault Polling Interval		<p>The time that State Poller waits between issuing queries to gather information for any of the following that are enabled: ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses.</p> <p>The default Fault Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p> <p>Note: NNMi monitors SNMP agents (Management Addresses) according to this Fault Polling Interval, <i>even if ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses are all disabled</i>. To prevent an SNMP Agent's address from being monitored, one of the following must be true: State Polling is disabled, current Communication Configuration settings turn off SNMP for the SNMP agent's address, the parent Node is set to Not Managed or Out of Service, or the parent node belongs to a Monitoring Configuration's Node Group with <input type="checkbox"/> Enable SNMP Polling on Node disabled.</p>

Default SNMP Performance Monitoring (NNM iSPI Performance for Metrics)

Attribute		Description
		<p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information.</p>
LAN Performance Monitoring	Enable Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 for more information. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of this group on a regular schedule.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers basic Interface performance data from Interfaces in devices assigned to this level of the monitoring hierarchy.</p>

Default SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute		Description
		<p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include performance data about Interfaces assigned to this level of the monitoring hierarchy.</p> <div> <p>Note: The Enable State Polling field must be enabled, too. By default the performance of connected interfaces and addresses is monitored. If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior by enabling Poll Unconnected Interfaces.</p> </div>
WAN Performance Monitoring	Enable DSx Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of the DSx Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p>
	Enable SONET Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of the SONET Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p>
	Enable ATM Interface Performance	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of</p>

Default SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
Polling	<p>performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each ATM Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note:</p> <ul style="list-style-type: none"> • This option gathers metrics from ATM-MIB and CISCO-AAL5-MIB. • See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221. </div>
Enable Frame Relay Interface Performance Polling	<p><i>(NNM iSPI Performance for Metrics)</i> Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each Frame Relay Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers Frame Relay performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather Frame Relay performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>This option gathers the following types of metrics:</p> <ul style="list-style-type: none"> • Circuit in and out octets, errors, and discards • Committed Information Rate (CIR) and Extended Information Rate (EIR) utilization • Forward Error Congestion Notification (FECN) and Backward Error Congestion Notification (BECN) counts <p>See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221.</p>

Default SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute		Description
Sensor Performance Monitoring	Enable Node Sensor Performance Polling	<p>Note: Node Sensor Performance Polling is disabled here by default.</p> <p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to poll Node Sensor performance. An NNMi administrator can set the threshold for Node Sensors related to the buffer, CPU, disk, and memory metrics.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers performance data related to the Node Sensors performance metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Node Sensors performance data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the current setting for the Performance Polling Interval in combination with this setting.</p>
	Enable Physical Sensor Performance Polling	<p>Note: Physical Sensor Performance Polling is disabled here by default.</p> <p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to poll for Physical Sensor performance on backplanes. An NNMi administrator can set thresholds related to Physical Sensor performance metrics for backplanes. The backplane's health is not propagated to the Node level to affect Node Status.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers performance data related to the Physical Sensor performance metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Physical Sensor performance data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the current setting for the Performance Polling Interval in combination with this setting.</p>
Performance Polling Interval		<p>(<i>NNM iSPI Performance for Metrics</i>) Use this field to set the time period that NNMi waits between issuing network traffic to gather performance data for the NNM iSPI Performance for Metrics.</p>

Default SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
	The default Performance Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.

Default Extend the Scope of Polling Beyond Connected Interfaces

Attribute	Description
Poll Unconnected Interfaces	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: Your discovery configuration choices might need to be adjusted to get the results you want. For example, to meet the “connected” criteria for interfaces in switches that do not have an IP address you must add the device to which the interface is connected as a discovery seed. See "Specify Discovery Seeds" on page 287.</p>
Poll Interfaces Hosting IP Addresses	<p>Note: This monitoring option is useful for Router interfaces. By default, this feature is enabled for the "Routers" Node Group.</p> <p>If <input checked="" type="checkbox"/> enabled, any unconnected interface that has one or more addresses associated with it is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>By monitoring the Interface (in addition to the IP address), NNMi can make more informed decisions about the health of each IP address associated with an unconnected interface.</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p>

Default Extend the Scope of Polling Beyond Connected Interfaces , continued

Attribute	Description
	<p>Tip: The Communication Configuration workspace provides a method of overriding this setting for specific Regions. You can define your own Region to easily turn off polling to any unreachable addresses in your management domain (for example, the private IP addresses¹).</p>
Poll Link Aggregation Interfaces <i>(NNMi Advanced)</i>	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors any <i>unconnected</i> Link Aggregation² or Split Link Aggregation³ member interfaces in switch-to-switch and server-to-switch connections:</p> <ul style="list-style-type: none"> Aggregate member interfaces not connected outside the context of the Aggregator membership. Aggregate member interfaces connected to an undiscovered node (for example, the SLAG upstream switch stack). <p>Tip: NNMi calculates the Aggregator status based on current status of all members. This means NNMi changes the status of the Aggregator when one member interface is down, even though the Aggregator is currently functioning well by using the other member interfaces.</p> <p>If <input type="checkbox"/> disabled, you must ensure that other Monitoring Configuration settings allow NNMi to manage each Aggregator member interface (none accidentally excluded or missed). Otherwise, NNMi calculates Aggregator status based on overall Aggregator behavior.</p>

Default Change Detection Monitoring

Attribute	Description
Enable Number of Interfaces (ifNumber) Polling	<p>Tip: For more information, see "Detect Interface Changes" on page 311.</p>

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.* , 169.254.*.* , 172.16-31.*.* , and 192.168.*.*)

²Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

³Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Default Change Detection Monitoring, continued

Attribute	Description
	<p>When enabled <input checked="" type="checkbox"/>, NNMi polls for the number of interfaces using the <code>ifNumber</code> value for the node. If the number of interfaces has changed, NNMi initiates a rediscovery of the node. Polling is suspended until the discovery is complete.</p> <p>When disabled <input type="checkbox"/>, NNMi does not actively poll for a change in the number of interfaces. The change is detected the next time the node is rediscovered.</p>
Enable Entity Change Time (<code>entLastChangeTime</code>) Polling	<p>When enabled <input checked="" type="checkbox"/>, NNMi polls for the last change time from the ENTITY-MIB <code>entLastChangeTime</code> value. If the time has changed, NNMi initiates a rediscovery of the node. Polling is suspended until the discovery is complete.</p> <p>When disabled <input type="checkbox"/>, NNMi does not actively poll the <code>entLastChangeTime</code> MIB value. The change is detected the next time the node is rediscovered.</p>
Change Detection Polling Interval	<p>The time that State Poller waits between issuing queries to gather information for the Number of Interfaces (<code>ifNumber</code>) and Entity Change Time (<code>entLastChangeTime</code>) settings enabled for Change Detection Monitoring.</p> <p>The default Change Detection Polling Interval is 4 hours.</p>

About Threshold Settings Provided by NNMi

Instruct NNMi to monitor thresholds for devices throughout your network (for example, Interface Input Utilization). You can also do the following when any of these thresholds are enabled:

- Configure incidents related to these thresholds, for more information:
- Configure custom incident attributes for these thresholds, for more information:
- There are many benefits to using these thresholds provided by NNMi:
 - a. NNMi provides all the complex logic required to conduct the threshold evaluations, accessing the appropriate MIB to provide the most accurate data for each specific device.
[For more information:](#)
 - In the NNMi console, click Help → NNMi Documentation Library → Release Notes.
 - Click the link to HP Network Node Manager i Software System and Device Support Matrix.
 - Click the link at the top of the file "For the latest additions to the system requirements and device support".



- Click the link to the **device support matrix**. Review the list of MIB files that NNMi is configured to use when appropriate.
- b. NNMi gathers Monitored Attribute data, evaluates any established thresholds to determine State values for the devices you are monitoring.

Tip: If these thresholds do not meet all of your team's needs, write your own. See ["Configure Threshold Information for a Custom Poller Collection" on page 507](#) (your Custom Poller thresholds affect the Custom Polled Instance State, and can be configured to affect Node Status and generate associated incidents).

Available Threshold Attributes for Monitoring Configuration

NNMi Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
Management Address ICMP Response Time Time elapsed (in milliseconds) before receiving a reply to NNMi's Internet Control Message Protocol (ICMP) echo request. NNMi issues the ICMP echo request to the Node's management address.			X	X	Fault Polling

Prerequisite for ICMP monitoring:

1. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the  **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Locate the **Node Settings** tab.
 - e. Open the appropriate **Node Settings** form.

Available Threshold Attributes for Monitoring Configuration, continued

NNMi Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	

2. Scroll down to the **Fault Monitoring** section, locate the ICMP Fault Monitoring settings. The ☒ Enable Management Address Polling must be enabled.

Tip: NNMi administrators can check network latency for a Node Group or Interface Group by adjusting the following for the management addresses associated with the specified group of nodes or interfaces:

- ICMP polling frequency
- ICMP echo request packet data payload size

See "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for more information.


Threshold Settings for NNM iSPI Performance for Metrics

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) -- [click here for more information](#).

NNM iSPI Performance for Metrics provides exception reports to track the frequency of threshold breaches. You can open these reports with **Actions** → **HP NNM iSPI Performance** → **Reporting - Report Menu** in the incident, node, or interface views and forms. (See [NNM iSPI Performance for Metrics Actions](#).)

The following thresholds apply to Nodes (see ["Node Settings for Monitoring" on page 443](#)):

Prerequisite for these Node Group Thresholds:

1. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.

- b. Expand the **Monitoring** folder.
 - c. Select the **Monitoring Configuration** form.
 - d. Locate the **Node Settings** tab.
 - e. Open the appropriate **Node Settings** form.
2. Scroll down to the **SNMP Performance Monitoring** section.
 3. Scroll down to the **Sensor Performance Monitoring** group box.
 4. Select the following:
 - ☒ **Enable Node Sensor Performance Polling** (must be enabled to monitor buffer, CP, and memory).
 - ☒ **Enable Physical Sensor Performance Polling** (must be enabled to monitor backplane).

Available Node Group Threshold Attributes for Monitoring Configuration

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
Backplane Utilization Threshold based on the percentage of backplane usage compared to the total amount of available backplane resources.			X	X	Performance Polling: Physical Sensor
Buffer Failure Rate Threshold based on the percentage of a node's buffer failures compared to the total number of attempts to create new buffers. These failures are caused by insufficient memory when the device			X		Performance Polling: Node Sensor

Available Node Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
tried to create new buffers.					
Buffer Miss Rate Threshold based on the percentage of a Node's buffer misses compared to the total attempts at buffer access. Crossing this threshold indicates the number of available buffers are dropping below a minimum level required for successful operation.			X		Performance Polling: Node Sensor
Buffer Utilization Threshold based on the percentage of a Node's buffers that are currently in use, compared to the total number of available buffers.			X	X	Performance Polling: Node Sensor
CPU 1Min Utilization Threshold based on the percentage of a node's CPU usage compared to the total amount of available CPU capacity. This percentage is the average CPU utilization over the prior 1-minute.			X	X	Performance Polling: Node Sensor
CPU 5Min Utilization Threshold based on the percentage of a node's CPU usage compared to the total amount of available CPU capacity.			X	X	Performance Polling: Node Sensor


Available Node Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
This percentage is the average CPU utilization over the prior 5-minutes.					
CPU 5Sec Utilization Threshold based on the percentage of a node's CPU usage compared to the total amount of available CPU capacity. This percentage is the average CPU utilization over the prior 5-seconds.			X	X	Performance Polling: Node Sensor
Disk Space Utilization Threshold based on the percentage of a node's disk space usage compared to the total amount of available disk space.			X	X	Performance Polling: Node Sensor
Memory Utilization Threshold based on the percentage of a node's memory usage compared to the total amount of available memory.			X	X	Performance Polling: Node Sensor

The Monitored attributes in the following table are available as Interface Group thresholds and Node Group thresholds. For each monitored Interface, NNMi applies any relevant Interface Group threshold configurations first. If none are available, NNMi applies any relevant Node Group threshold configurations.

The following thresholds apply to Interfaces (see ["Interface Settings for Monitoring" on page 416](#)):

Prerequisite for these Interface Group thresholds:

1. Navigate to the **Interface Settings** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Monitoring Configuration** form.
 - d. Locate the **Interface Settings** tab.
 - e. Open the appropriate **Interface Settings** form.
2. Scroll down to the **SNMP Performance Monitoring** section, locate the LAN Performance Monitoring settings. The ☒ Enable Interface Performance Polling must be enabled.

Available Interface Group Threshold Attributes for Monitoring Configuration

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
FCS LAN Error Rate <i>Local Area Network interfaces only.</i> Threshold based on the percentage of incoming frames with a bad checksum (CRC ¹ value) compared to the total number of incoming frames. Possible causes include collisions at half- duplex, a duplex mismatch, bad hardware (NIC ² , cable, or port), or a connected device generating frames with bad Frame Check Sequence.	X		X		Performance Polling

¹Cyclic Redundancy Check

²Network Interface Controller

Available Interface Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
FCS WLAN Error Rate <i>Wireless Local Area Network Interfaces only.</i> Threshold based on the percentage of incoming frames with a bad checksum (CRC ¹ value) compared to the total number of incoming frames. Possible causes include wireless communication interference, bad hardware (NIC ² , cable or port), or a connected device generating frames with bad Frame Check Sequence.	X		X		Performance Polling
Input Discard Rate Threshold based on the percentage of the interface's discarded input packet count compared to the total number of packets received. Packets might be discarded because of a variety of issues, including receive-buffer overflows, congestion, or system specific issues.	X		X		Performance Polling
Input Error Rate Threshold based on the	X		X		Performance Polling

¹Cyclic Redundancy Check

²Network Interface Controller

Available Interface Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
percentage of the interface's input packet error count compared to the total number of packets received. What constitutes an error is system specific, but likely includes such issues as bad packet checksums, incorrect header information, and packets that are too small.					
Input Queue Drops Rate Threshold based on the percentage of the interface's dropped input packets compared to the total number of packets received. Possible causes include the input queue being full.	X		X		Performance Polling
Input Utilization Threshold based on the percentage of the interface's total incoming octets compared to the maximum number of octets possible (determined by the MIB being used to query ifSpeed of the device and whether the host system supports high-speed counters for interfaces).	X	X	X	X	Performance Polling
Tip: Sometimes the					

Available Interface Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
<p>ifSpeed value returned by the device's SNMP agent is not accurate and causes problems with thresholds. If your NNMi role allows, you can override the ifSpeed reported by the SNMP agent:</p> <ol style="list-style-type: none"> 1. Open the problem interface's Interface form. 2. Select the General Tab. 3. Locate the Input/Output Speed section. 4. Change the Input Speed or Output Speed setting. 					
<p>Output Discard Rate</p> <p>Threshold based on the percentage of the interface's discarded output packet count compared to the total number of outgoing packets. Packets might be discarded because of a variety of issues, including transmission buffer</p>	X		X		Performance Polling

Available Interface Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
overflows, congestion, or system specific issues.					
Output Error Rate Threshold based on the percentage of the interface's output packet error count compared to the total number of outgoing packets. What constitutes an error is system specific, but likely includes such issues as collisions and buffer errors.	X		X		Performance Polling
Output Queue Drops Rate Threshold based on the percentage of the interface's dropped output packets compared to the total number of outgoing packets. Possible causes include all buffers allocated to the interface being full.	X		X		Performance Polling
Output Utilization Threshold based on the percentage of the interface's total outgoing octets compared to the maximum number of octets possible (determined by the MIB being used to query ifSpeed of the device and whether the host system supports high-speed counters for interfaces).	X	X	X	X	Performance Polling

Available Interface Group Threshold Attributes for Monitoring Configuration, continued

NNM iSPI Performance for Metrics Monitored Attributes available for Thresholds	Relevant for:				Controlled by:
	Interface Group: Threshold Settings	Interface Group: Baseline Settings	Node Group: Threshold Settings	Node Group: Baseline Settings	
Order applied (low to high #):	1st Group Order #s 1 - x	2nd Group Order #s 1 - x	3rd Group Order #s 1 - x	4th Group Order #s 1 - x	
<p>Tip: Sometimes the <code>ifSpeed</code> value returned by the device's SNMP agent is not accurate and causes problems with thresholds. If your NNMi role allows, you can override the <code>ifSpeed</code> reported by the SNMP agent:</p> <ol style="list-style-type: none"> 1. Open the problem interface's Interface form. 2. Select the General Tab. 3. Locate the Input/Output Speed section. 4. Change the Input Speed or Output Speed setting. 					

Interface Settings for Monitoring

Before you start, you must establish one or more [Interface Group](#) definitions that identify the interface types to which these monitoring settings will apply. NNMi provides nearly 250 interface types to choose from. Interface monitoring applies to matching interfaces and the IP addresses that are hosted on those interfaces. See also, ["Interface Groups Provided by NNMi" on page 376](#).

Tip: (*Global Network Management*) If you have enabled the Discovery of [unnumbered](#)

[Interfaces](#), on each Regional Manager consider creating an Interface Group based on the Custom Attribute: `UnnumberedNextHop` and monitoring that Interface Group. Global Managers can be configured to show status for L2 Connections between unnumbered interfaces discovered on all Regional Managers. For more information:




Tip: NNMi administrators can check network latency for an Interface Group by adjusting the following for the management addresses associated with the specified group of interfaces:

- ICMP polling frequency
- ICMP echo request packet data payload size

See the "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for more information.

Tip: (NNMi Advanced) Global Network Management feature - When viewing maps on the Global Manager, if you want to monitor important WAN interface connections *between Regional Managers*, then within each Regional Manager's Monitoring Configuration settings, enable NNMi's [Poll Unconnected Interfaces](#) for each of those WAN interfaces.



To establish monitoring behavior for one or more predefined Interface Groups:

1. Navigate to the **Interface Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Locate the **Interface Settings** tab.
 - e. Do one of the following:
 - To create an Interface Settings definition, click the  New icon.
 - To edit an Interface Settings definition, select a row and click the  Open icon.
 - To delete an Interface Settings definition, select a row and click the  Delete button
2. Establish the appropriate settings to identify this Interface Group Setting definition (see [Basics table](#)).
3. *Optional.* Configure the Fault Monitoring behavior for this Interface Group Setting definition (see [Fault Monitoring table](#)).
4. (NNMi iSPI Performance for Metrics) If the HP Network Node Manager iSPI Performance for

Metrics Software is installed:

- Configure the Performance Monitoring behavior for this Interface Group Setting definition. See [Performance Monitoring table](#).
 - Configure the Baseline Settings. Navigate to the Baseline Settings tab. See ["Configure Baseline Settings for Interfaces" on page 435](#).
5. *Optional.* Configure thresholds. Navigate to the Threshold Settings tab. See ["Configure Threshold Monitoring for Interface Groups" on page 426](#) for more information.
 6. By default, NNMi monitors only interfaces that are connected to other interfaces. When SNMP polling is enabled, NNMi automatically detects most connections. See ["Add or Delete a Layer 2 Connection" on page 314](#) for information about manual overrides.

Optional. If you want to expand monitoring behavior for this group to include unconnected Interfaces, indicate your choices in the [Extend the Scope of Polling Beyond Connected Interfaces](#) group box.

7. Click  **Save and Close** to return to the Monitoring Configuration form.
8. Click  **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.

Caution: When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment.

To verify that State Poller is working as expected, see **Help** → **System Information** and select the the **State Poller** tab. NNMi displays a report with current details about the State Poller process.

9. (*NNMi Advanced - Global Network Management feature*) On each Regional Manager, consider creating an Interface Group based on the Custom Attribute: UnnumberedNextHop and monitoring that Interface Group (["Interface Settings for Monitoring" on page 416](#)):
 - To easily share your Interface Group definitions, see ["Export and Import Configuration Settings" on page 1610](#).
 - The Global Manager's maps can successfully show status for L2 Connections between unnumbered interfaces discovered on all Regional Managers, see ["Global Manager: Configure Custom Attribute Replication" on page 115](#).

Optional. Customize the node monitoring behavior. See ["Node Settings for Monitoring" on page 443](#). Also see ["Detect Interface Changes" on page 311](#).

Basics

Attribute	Description
Ordering	<p>Enter a unique string (any length), characters 0 through 9. Consider using increments of 100 for the flexibility to insert additional items between existing items over time.</p> <p>NNMi decides which monitoring configurations apply to a node or interface based on the ordering number assigned to the configuration definitions. NNMi monitors the device according to the first match (checked from lowest number to highest number within each category). Categories are read in sequence. Click here for a description of the sequence.</p> <ol style="list-style-type: none"> Interface Settings: NNMi monitors each of the Node's Interfaces and IP Addresses based on the first matching Interface Settings definition. The first match is the Interface Settings definition with the lowest Ordering number, then Baseline Settings. Node Settings: NNMi monitors each Node and each previously unmatched Interface or IP Address based on the first matching Node Settings definition. The first match is the Node Settings definition with the lowest Ordering number, then Baseline Settings. <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: Child node groups are included in the Ordering hierarchy. This means that if the parent node group has a lower Ordering number (for example, parent=10, child=20), then the monitoring configuration specified for the parent node group also applies to the nodes in the child node group. To override a parent node group monitoring configuration, set the Ordering number for the child node group to a number that is lower than the parent (for example, parent=20, child=10).</p> </div> <ol style="list-style-type: none"> Default Settings: If no match is found for a Node, Interface, or IP Address in 1 or 2, NNMi applies the default Monitoring Configuration settings. <p>No duplicate Ordering numbers are permitted. Each Interface Setting ordering number must be unique.</p>
Interface Group	Choose one predefined Interface Group from the list. See "Create Interface Groups" on page 356 for more information.

Fault Monitoring

Attribute	Description
Enable ICMP Monitoring:	<p>Enable IP Address Fault Polling</p> <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: This monitoring option is useful for devices that do not support SNMP.</p> </div> <p>If <input checked="" type="checkbox"/> enabled, State Poller issues ICMP (ping) requests to verify the availability of discovered IP address.</p>

Fault Monitoring , continued

Attribute	Description
	<p>Note: In the Global Control section of this form, the Enable State Polling attribute must be enabled, too.</p> <p>If <input type="checkbox"/> disabled, State Poller does the following:</p> <ul style="list-style-type: none"> • If neither this attribute nor <i>Management IP Address Polling</i> is selected, State Poller does not use ICMP to monitor nodes covered by this configuration setting. • IP addresses (both previously discovered and newly discovered) have a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the color of the IP address map-symbol set to beige. See Layer 3 Neighbor View. • If both ICMP and SNMP are disabled for a Node, the Node has a Status attribute value of "No Status" and the color of the Node map-symbol background shape is set to beige. <p>Tip: To turn off ICMP polling within a subset of your network environment, use the Communication Configuration workspace Region definitions. You can define your own Regions that identify any unreachable addresses in your management domain (for example, the private IP addresses¹).</p>
SNMP Fault Monitoring:	<p>Enable Interface Fault Polling</p> <p>If <input checked="" type="checkbox"/> enabled, State Poller monitors all interfaces by issuing SNMP read-only queries to devices assigned to this level of the monitoring hierarchy.</p> <p>By default, any connected interface is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.) If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior with the Poll Unconnected Interfaces and the Poll Interfaces Hosting IP Addresses attributes.</p> <p>Note: The following attributes must also be enabled:</p> <ul style="list-style-type: none"> • In the Global Control section of this form, the Enable State Polling attribute must be enabled, too. See Layer 2 Neighbor View. (See

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*., 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

Fault Monitoring , continued

Attribute	Description
	<p>"Global Control Settings for Monitoring" on page 391 for more information.)</p> <ul style="list-style-type: none"> In the Communication Configuration view, enable State Poller queries with the applicable Enable SNMP Communication attributes (see "Configuring Communication Protocol" on page 129 for more information). <p>If <input type="checkbox"/> disabled, for devices assigned to this level of the monitoring hierarchy:</p> <ul style="list-style-type: none"> Causal Engine calculates Status based only on IP address State. The Interface objects previously discovered change to a State attribute value of "Not Polled" and a Status attribute value of "No Status" (plus any related map-symbol changes to a beige color).
Fault Polling Interval	<p>The time that State Poller waits between issuing queries to gather information for any of the following that are enabled: ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses.</p> <p>The default Fault Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p> <div data-bbox="581 1115 1370 1499"> <p>Note: NNMi monitors SNMP agents (Management Addresses) according to this Fault Polling Interval, <i>even if ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses are all disabled</i>. To prevent an SNMP Agent's address from being monitored, one of the following must be true: State Polling is disabled, current Communication Configuration settings turn off SNMP for the SNMP agent's address, the parent Node is set to Not Managed or Out of Service, or the parent node belongs to a Monitoring Configuration's Node Group with <input type="checkbox"/> Enable SNMP Polling on Node disabled.</p> </div>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics)

Attribute	Description
	<p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information.</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute		Description
LAN Performance Monitoring	Enable Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 for more information. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of this group on a regular schedule.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers basic Interface performance data from Interfaces in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include performance data about Interfaces assigned to this level of the monitoring hierarchy.</p> <div> <p>Note: The Enable State Polling field must be enabled, too. By default the performance of connected interfaces and addresses is monitored. If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior by enabling Poll Unconnected Interfaces.</p> </div>
	Enable DSx Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of the DSx Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p>
WAN Performance Monitoring	Enable SONET Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers</p>
	Enable SONET Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
	<p>performance data about each member of the SONET Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p>
Enable ATM Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each ATM Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <div data-bbox="703 1194 1370 1472"> <p>Note:</p> <ul style="list-style-type: none"> • This option gathers metrics from ATM-MIB and CISCO-AAL5-MIB. • See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221. </div>
Enable Frame Relay Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each Frame Relay Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers Frame Relay performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather Frame Relay</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
	<p>performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>This option gathers the following types of metrics:</p> <ul style="list-style-type: none"> • Circuit in and out octets, errors, and discards • Committed Information Rate (CIR) and Extended Information Rate (EIR) utilization • Forward Error Congestion Notification (FECN) and Backward Error Congestion Notification (BECN) counts <p>See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221.</p>
Performance Polling Interval	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this field to set the time period that NNMi waits between issuing network traffic to gather performance data for the NNM iSPI Performance for Metrics.</p> <p>The default Performance Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p>

Extend the Scope of Polling Beyond Connected Interfaces

Attribute	Description
Poll Unconnected Interfaces	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <div data-bbox="462 1375 1370 1522"> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> </div> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <div data-bbox="462 1600 1370 1810"> <p>Tip: Your discovery configuration choices might need to be adjusted to get the results you want. For example, to meet the “connected” criteria for interfaces in switches that do not have an IP address you must add the device to which the interface is connected as a discovery seed. See "Specify Discovery Seeds" on page 287.</p> </div>

Extend the Scope of Polling Beyond Connected Interfaces, continued

Attribute	Description
Poll Interfaces Hosting IP Addresses	<p>Note: This monitoring option is useful for Router interfaces.</p> <p>If <input checked="" type="checkbox"/> enabled, any unconnected interface that has one or more addresses associated with it is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>By monitoring the Interface (in addition to the IP address), NNMi can make more informed decisions about the health of each IP address associated with an unconnected interface.</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: The Communication Configuration workspace provides a method of overriding this setting for specific Regions. You can define your own Region to easily turn off polling to any unreachable addresses in your management domain (for example, the private IP addresses¹).</p>
Poll Link Aggregation Interfaces (NNMi Advanced)	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors any <i>unconnected</i> Link Aggregation² or Split Link Aggregation³ member interfaces in switch-to-switch and server-to-switch connections:</p> <ul style="list-style-type: none"> Aggregate member interfaces not connected outside the context of the Aggregator membership. Aggregate member interfaces connected to an undiscovered node (for example, the SLAG upstream switch stack).

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*.*, 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

²Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

³Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Extend the Scope of Polling Beyond Connected Interfaces, continued

Attribute	Description
	<p>Tip: NNMi calculates the Aggregator status based on current status of all members. This means NNMi changes the status of the Aggregator when one member interface is down, even though the Aggregator is currently functioning well by using the other member interfaces.</p> <p>If <input type="checkbox"/> disabled, you must ensure that other Monitoring Configuration settings allow NNMi to manage each Aggregator member interface (none accidentally excluded or missed). Otherwise, NNMi calculates Aggregator status based on overall Aggregator behavior.</p>

Related Topics

["Threshold Monitoring Behavior After a System Restart or Configuration Change" on page 473](#)

Configure Threshold Monitoring for Interface Groups

You can set interface thresholds using either of the following methods:

- ["Configure Count-Based Threshold Monitoring for Interface Groups" below](#)
- ["Configure Time-Based Threshold Monitoring for Interface Groups" on page 430](#)

Related Topics

["About Threshold Settings Provided by NNMi" on page 405](#)






["Threshold Monitoring Behavior After a System Restart or Configuration Change" on page 473](#)

Configure Count-Based Threshold Monitoring for Interface Groups




Count-Based Threshold Settings enable you to determine as soon as a threshold is reached (for example, an interface is dropping data or an Ethernet interface is getting overloaded).

To establish count-based threshold monitoring behavior for interfaces:

1. *Prerequisite.* Before setting thresholds, analyze performance data over time to determine wise threshold settings for each Interface group. For more information, see the following topics:
 - ["Determine Reasonable Threshold Settings" on page 471.](#)
 - ["Examples of Count-Based Threshold Monitoring" on page 378.](#)
2. Navigate to the **Interface Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.

- b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Navigate to the **Interface Settings** tab.
 - e. Do one of the following:
 - To create an Interface Settings definition, click the  New icon.
 - To edit an Interface Settings definition, select a row and click the  Open icon.
3. In the **Interface Settings** form, navigate to the **Threshold Settings** tab.
4. Do one of the following:
 - To create a threshold definition, click the  New icon and select **Count-Based Threshold Settings**.
 - To edit a threshold definition, select a row and click the  Open icon.
 - To delete a threshold definition, select a row and click the  Delete icon.
5. Select the Monitored Attribute you want to monitor and establish the threshold values for that attribute (see [Basic Count-Based Threshold Settings table](#)).


When you configure thresholds using this technique, NNMi uses the assigned Interface Group as a filter (only monitoring the threshold for devices with at least one interface belonging to the specified Interface Group).

6. Click  **Save and Close** to return to the **Interface Settings** form.
7. Click  **Save and Close** to return to the **Monitoring Configuration** form.
8. Click  **Save and Close**. NNMi applies your changes during the next regularly scheduled monitoring cycle.


Note: Threshold Incidents are disabled by default within NNMi to prevent Incident storms. If you are ready to generate Threshold Incidents, see ["Generate Performance Threshold Incidents \(NNM iSPI Performance for Metrics\)" on page 865](#). See also ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#) for a description of the special custom incident attributes available in Threshold Incidents.

9. See also ["Find Threshold Results" on page 472](#).

Basic Count-Based Threshold Settings

Attribute	Description
Monitored Attribute	<p>In the Monitored Attribute drop-down list, select the attribute for which you want to establish a threshold configuration.</p> <p>Tip: Some of the choices in the Monitored Attribute selection list do not apply in this context.</p> <p>See the tables in "About Threshold Settings Provided by NNMi" on page 405 for information about which Monitored Attributes are available for Interface Groups.</p>
<p>A High Threshold situation occurs when: The <i>Monitored Attribute</i> is greater than the <i>High Value</i> for <i>High Trigger Count</i> cycles.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  High for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
High Value	<p>Designate the percentage between 0.00 and 100.00 above which becomes a threshold situation.</p> <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> • 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. • 99.99999999999999 for the highest value less than one hundred. <p>The High Value must be greater than or equal to the designated Low Value.</p> <p>Note: If you use the highest possible value, the High threshold is disabled because it cannot be <i>crossed</i>.</p>
High Value Rearm	<p>The High Value Rearm designates the lower boundary of the High Threshold <i>range of values</i>.</p> <p>After entering a High threshold situation, when a returned value is below the specified High Value Rearm, the High Threshold situation ends (for Count-Based Thresholds).</p> <p>Note: The High Value Rearm must be less than or equal to the High Value and greater than or equal to the Low Value Rearm.</p>
High	Designate the number of consecutive polling intervals the returned value must be

Basic Count-Based Threshold Settings, continued

Attribute	Description
Trigger Count	<p>greater than the specified High Value to meet the High Threshold criteria. The default value is 1.</p> <p>The polled value represents an average over the configured polling interval, so a trigger count of 1 is often appropriate. See the currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting that is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443
<p>A Low Threshold situation occurs when: The <i>Monitored Attribute</i> is less than the <i>Low Value</i> for <i>Low Trigger Count</i> cycles.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  Low for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
Low Value	<p>Designate the percentage between 0.00 and 100.00 below which becomes a threshold situation.</p> <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> • 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. • 99.99999999999999 for the highest value less than one hundred. <p>The Low Value must be less than or equal to the designated High Value.</p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: If you use zero (the minimum possible value), the Low threshold is disabled because it cannot be <i>crossed</i>.</p> </div>
Low Value Rearm	<p>The Low Value Rearm designates the upper boundary of the Low Threshold <i>range of values</i>.</p> <p>After entering a Low threshold situation, when a returned value is above the specified Low Value Rearm, the Low Threshold situation ends (for Count-Based Thresholds).</p>

Basic Count-Based Threshold Settings, continued






Attribute	Description
	Note: The Low Value Rarm must be greater than or equal to the Low Value and less than or equal to the High Value Rarm.
Low Trigger Count	<p>Designate the number of consecutive polling interval the returned value must be less than the specified Low Value to meet the Low Threshold criteria. The default value is 1.</p> <p>The polled value represents an average over the configured polling interval, so a trigger count of 1 is often appropriate. See the currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting that is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none">• "Default Settings for Monitoring" on page 393• "Interface Settings for Monitoring" on page 416• "Node Settings for Monitoring" on page 443

Configure Time-Based Threshold Monitoring for Interface Groups




Time-Based Threshold Settings enable you to determine whether a threshold is reached for a particular duration of time (for example, the bandwidth utilization for an interface is above 90 percent for 20 out of 30 minutes).

To establish time-based threshold monitoring behavior for interfaces:

1. *Prerequisite.* Before setting thresholds, analyze performance data over time to determine wise threshold settings for each Interface group.
 - ["Determine Reasonable Threshold Settings" on page 471.](#)
 - ["Examples of Time-Based Threshold Monitoring" on page 382.](#)
2. Navigate to the **Interface Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Navigate to the **Interface Settings** tab.
 - e. Do one of the following:

- To create an Interface Settings definition, click the  New icon.
 - To edit an Interface Settings definition, select a row and click the  Open icon.
3. In the **Interface Settings** form, navigate to the **Threshold Settings** tab.
 4. Do one of the following:
 - To create a threshold definition, click the  New icon and select **Time-Based Threshold Settings**.
 - To edit a threshold definition, select a row and click the  Open icon.
 - To delete a threshold definition, select a row and click the  Delete icon.
 5. Select the Monitored Attribute you want to monitor and establish the threshold values for that attribute (see [Basic Time-Based Threshold Settings table](#)).

When you configure thresholds using this technique, NNMi uses the assigned Interface Group as a filter (only monitoring the threshold for devices with at least one interface belonging to the specified Interface Group).

6. Click  **Save and Close** to return to the **Interface Settings** form.
7. Click  **Save and Close** to return to the **Monitoring Configuration** form.
8. Click  **Save and Close**. NNMi applies your changes during the next regularly scheduled monitoring cycle.



Note: Threshold Incidents are disabled by default within NNMi to prevent Incident storms. If you are ready to generate Threshold Incidents, see ["Generate Performance Threshold Incidents \(NNM iSPI Performance for Metrics\)" on page 865](#). See also ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#) for a description of the special custom incident attributes available in Threshold Incidents.

9. See also ["Find Threshold Results" on page 472](#).


Basic Time-Based Threshold Settings

Attribute	Description
Monitored Attribute	<p>In the Monitored Attribute drop-down list, select the attribute for which you want to establish a threshold configuration.</p> <div style="border: 1px solid #ccc; padding: 10px; margin-top: 10px;"> <p>Tip: Some of the choices in the Monitored Attribute selection list do not apply in this context.</p> <p>See the tables in "About Threshold Settings Provided by NNMi" on page 405</p> </div>

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>for information about which Monitored Attributes are available for Interface Groups.</p>
	<p>A High Threshold situation occurs when: The <i>Monitored Attribute</i> is greater than the <i>High Value</i> for at least the time specified in <i>High Duration</i> within the <i>High Duration Window</i>.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  High for the appropriate Interface. • Generates the related incident (if one is Enabled ). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met.
High Value	<p>Designate the percentage between 0.00 and 100.00 above which becomes a threshold situation.</p> <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> • 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. • 99.99999999999999 for the highest value less than one hundred. <p>The High Value must be greater than or equal to the designated Low Value.</p> <p>Note: If you use the highest possible value, the High threshold is disabled because it cannot be <i>crossed</i>.</p>
High Value Rearm	<p>The High Value Rearm designates the lower boundary of the High Threshold <i>range of values</i>.</p> <p>After entering a High threshold situation, when a returned value is below the specified High Value Rearm, the following happens (for Time-Based Thresholds):</p> <ul style="list-style-type: none"> • The current polling interval does not contribute toward High Duration. • The criteria for High Duration and High Duration Window determine when the High Threshold situation ends. <p>Note: The High Value Rearm must be less than or equal to the High Value and greater than or equal to the Low Value Rearm.</p>
High Duration	<p>Designate the minimum time within which the value must remain in the High range before the threshold state changes to High and (optionally) an incident is</p>

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>generated.</p> <p>The High Duration should be equal to or greater than which ever currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443 <p>Tip: Setting both the High Duration and High Duration Window to zero disables the High threshold.</p>
High Duration Window	<p>Designate the window of time within which the High Duration criteria must be met.</p> <p>The value must be greater than 0 (zero) and can be the same as or greater than the High Duration value. NNMi uses a sliding window, meaning that each time the High Window Duration is reached, NNMi drops the oldest polling interval and adds the most recent.</p> <p>Tip: Setting both the High Duration and High Duration Window to zero disables the High threshold.</p>
<p>A Low Threshold situation occurs when:</p> <p>The <i>Monitored Attribute</i> is lower than the <i>Low Value</i> for at least the time specified in <i>Low Duration</i> within the <i>Low Duration Window</i>.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  Low for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
Low Value	<p>Designate the percentage between 0.00 and 100.00 below which becomes a Low threshold situation.</p> <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> • 0.0000000000000001 (or 1E-15 in Scientific Notation) for the smallest value

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>greater than zero.</p> <ul style="list-style-type: none"> • 99.99999999999999 for the highest value less than one hundred. <p>The Low Value must be less than or equal to the designated High Value.</p> <p>Note: If you use zero (the minimum possible value), the Low threshold is disabled because it cannot be <i>crossed</i>.</p>
Low Value Rearm	<p>The Low Value Rearm designates the upper boundary of the Low Threshold <i>range of values</i>.</p> <p>After entering a Low threshold situation, when a returned value is above the specified Low Value Rearm, the following happens (for Time-Based Thresholds):</p> <ul style="list-style-type: none"> • The current polling interval does not contribute toward Low Duration. • The criteria for Low Duration and Low Duration Window determine when Low Threshold ends. <p>Note: The Low Value Rearm must be greater than or equal to the Low Value and less than or equal to the High Value Rearm.</p>
Low Duration	<p>Designate the minimum time within which the value must remain in the Low range before the threshold state changes to Low and (optionally) an incident is generated.</p> <p>The Low Duration should be equal to or greater than which ever currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting is influencing the Monitored Attribute you chose, because that is how often NNMI provides a data point. See the tables in "About Threshold Settings Provided by NNMI" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443 <p>Tip: Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p>
Low Duration Window	<p>Designate the window of time within which the Low Duration criteria must be met.</p>

Basic Time-Based Threshold Settings, continued

Attribute	Description
Window	<p>The value must be greater than 0 (zero) and can be the same as or greater than the Low Duration value. NNMi uses a sliding window, meaning that each time the Low Window Duration is reached, NNMi drops the oldest polling interval and adds the most recent.</p> <p>Tip: Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p>

Configure Baseline Settings for Interfaces

Use the **Baseline Settings** form to configure both of the following:

- NNMi
 - If you set baseline ranges, you can configure NNMi to generate an Incident when any value is outside of the baseline range.
- NNM iSPI Performance for Metrics






Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).




The following are affected by the Baseline Settings:

- Triple Exponential Smoothing technique to predict the baseline values of a monitored attribute. See "Integrating with Other iSPIs" in the NNM iSPI Performance for Metrics Online Help for more information about how baseline data is collected.
- Exception reports that track the frequency of threshold breaches. You can open these reports with **Actions** → **HP NNM iSPI Performance** → **Reporting - Report Menu** in the incident, node, or interface views and forms. (See [NNM iSPI Performance for Metrics Actions](#).)

To establish baseline settings for an Interface Group:

1. Navigate to the **Interface Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.

- d. Locate the **Interface Settings** tab.
 - e. Do one of the following:
 - To create an Interface Settings definition, click the  New icon.
 - To edit an Interface Settings definition, select a row and click the  Open icon.
 - To delete an Interface Settings definition, select a row and click the  Delete button.
 2. Navigate to the **Baseline Settings** tab.
 3. Do one of the following:
 - To create an Baseline Settings definition, click the  New icon.
 - To edit an Baseline Settings definition, select a row and click the  Open icon.
 4. Establish the baseline settings (see the [Baseline Settings](#) table).
 5. Navigate to the **Baseline Deviations Settings** tab.
 6. Establish the baseline range for monitoring this Interface Group (see the [Baseline Deviations Settings](#) table).
 7. By default, NNMi monitors only interfaces that are connected to other interfaces. When SNMP polling is enabled, NNMi automatically detects most connections. See ["Add or Delete a Layer 2 Connection" on page 314](#) for information about manual overrides.

Optional. If you want to expand monitoring behavior for this group to include unconnected Interfaces, indicate your choices in the [Extend the Scope of Polling Beyond Connected Interfaces](#) group box.
 8. Click  **Save and Close** to return to the Interface Settings form.
 9. Click  **Save and Close** to return to the Monitoring Configuration form.
 10. Click  **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.
- Caution:** When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment
11. *Optional.* Customize the node monitoring behavior. See ["Node Settings for Monitoring" on page 443](#). Also see ["Detect Interface Changes" on page 311](#).
 12. See also ["Find Threshold Results" on page 472](#).

Baseline Settings for this Interface Group Setting

Attribute	Description
Monitored Attribute	<p>NNMi gathers data to calculate thresholds. See "About Threshold Settings Provided by NNMi" on page 405 for information about which attributes apply here.</p> <p>Tip: You may see attributes in the selection list that do not apply here.</p>
Threshold Enabled	<p>Use this attribute to temporarily disable the threshold:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Duration	<p>Designate the minimum time within which the value must remain out of the configured Baseline Range before the state changes to Abnormal Range and (optionally) an incident is generated. Use the Baseline Deviation Settings tab to set the upper and lower limits of the baseline range.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • If you do not configure a Baseline Range, NNMi uses the default value of 3 standard deviations. • The Polling Interval should be less than or equal to the Duration.
Duration Window	<p>Designate the window of time in which the Upper Baseline Limit or Lower Baseline Limit criteria must be met.</p> <p>Note: The value must be greater than 0 (zero) and can be the same as the Duration value. NNMi uses a sliding window, meaning that each time the Duration is reached, NNMi drops the oldest polling interval and adds the most recent. See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.</p>

Baseline Deviations Settings for this Interface Group Setting

Attribute	Description
Upper Baseline Limit Enabled	<p>If <input checked="" type="checkbox"/> enabled, NNMi uses the Upper Baseline Limit attribute value to determine the number of standard deviations above the average that defines the upper baseline limit.</p> <p>If <input type="checkbox"/> disabled: NNMi does not define the upper baseline limit.</p>
Upper Baseline Limit - Deviations above average	Enter the number of standard deviations above the average values that NNMi should use to determine the upper baseline limit.
Lower Baseline Limit Enabled	<p>If <input checked="" type="checkbox"/> enabled, NNMi uses the Lower Baseline Limit attribute value to determine the number of standard deviations below the average that</p>


Baseline Deviations Settings for this Interface Group Setting, continued

Attribute	Description
	defines the lower baseline limit. If <input type="checkbox"/> disabled: NNMi does not define the lower baseline limit.
Lower Baseline Limit - Deviations below average	Enter the number of standard deviations below the average values that NNMi should use to determine the lower baseline limit.

Monitor Wireless Interfaces




A few Monitoring configuration settings are required for NNMi to successfully monitor wireless interfaces. These setting ensure that wireless interfaces will be monitored even though those interfaces may appear to be unconnected.

To configure NNMi to monitor IEEE 802.11 wireless LAN interfaces:

1. Navigate to the **Monitoring Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
2. Navigate to the **Interface Settings** tab and Click the  New icon.
3. In the Interface Group Settings form:
 - Configure an **Ordering Number**. Choose a small enough value (high enough priority) to ensure that wireless interfaces will match these settings first.
 - Choose the Interface group: **WLAN Interfaces**.
 - Enable ☒ **Enable Interface Performance Polling**.

Note: The WLAN Interfaces group includes other types of wireless interfaces in addition to 802.11. If the default WLAN Interfaces group matches other types of wireless interfaces in your environment that you do not want to monitor, the unwanted types can be removed from the WLAN Interfaces group, or a new interface group can be created that only includes 802.11 interfaces (ifType: ieee80211).

- Choose the **Performance Polling Interval** to establish frequency.
- Enable ☒ **Poll Unconnected Interfaces**.

4. Navigate to the **Threshold Settings** tab. See ["About Threshold Settings Provided by NNMi" on page 405](#).
5. Click  **Save and Close** to return to the Interface Settings form.
6. Click  **Save and Close** to return to the Monitoring Configuration form.
7. Click  **Save and Close**. NNMi applies your changes. The amount of time required for this configuration change to take effect will depend on the number devices in the deployment with interfaces in the WLAN Interfaces group.

Caution: When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment

8. When the configuration settings have taken effect:
 - In the NNMi Console, select an 802.11 interface and click **Actions > Configuration Details > Monitoring Settings** to verify that fault and performance monitoring are enabled, with the desired polling interval.
 - Viewing 802.11 Metrics in Network Performance Server (NPS): see ["NNMi iSPI Performance for Metrics and Wireless Interfaces" on page 441](#).

Basics for Wireless Interfaces

Attribute	Description
Ordering	<p>Enter a unique string (any length), characters 0 through 9. Consider using increments of 100 for the flexibility to insert additional items between existing items over time.</p> <p>NNMi decides which monitoring configurations apply to a node or interface based on the ordering number assigned to the configuration definitions. NNMi monitors the device according to the first match (checked from lowest number to highest number within each category). Categories are read in sequence. Click here for a description of the sequence.</p> <ol style="list-style-type: none">1. Interface Settings: NNMi monitors each of the Node's Interfaces and IP Addresses based on the first matching Interface Settings definition. The first match is the Interface Settings definition with the lowest Ordering number, then Baseline Settings.2. Node Settings: NNMi monitors each Node and each previously unmatched Interface or IP Address based on the first matching Node Settings definition. The first match is the Node Settings definition with the lowest Ordering number, then Baseline Settings.

Basics for Wireless Interfaces, continued

Attribute	Description
	<p>Note: Child node groups are included in the Ordering hierarchy. This means that if the parent node group has a lower Ordering number (for example, parent=10, child=20), then the monitoring configuration specified for the parent node group also applies to the nodes in the child node group. To override a parent node group monitoring configuration, set the Ordering number for the child node group to a number that is lower than the parent (for example, parent=20, child=10).</p> <p>3. Default Settings: If no match is found for a Node, Interface, or IP Address in 1 or 2, NNMi applies the default Monitoring Configuration settings.</p> <p>No duplicate Ordering numbers are permitted. Each Interface Setting ordering number must be unique.</p>
Interface Group	Choose WLAN Interfaces from the drop-down list.

SNMP Performance Monitoring for Wireless Interfaces(NNM iSPI Performance for Metrics)

Attribute	Description
	<p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information.</p>
LAN Performance Monitoring	<p>Enable Interface Performance Polling</p> <p>(NNM iSPI Performance for Metrics) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 for more information. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of this group on a regular schedule.</p> <p>Configure this setting to <input checked="" type="checkbox"/> enabled, NNMi gathers basic Interface performance data from Interfaces in devices assigned to this level of the monitoring hierarchy.</p> <p>Note: The Enable State Polling field must be enabled, too. By default the performance of connected interfaces and addresses is monitored. If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior by enabling Poll Unconnected</p>

SNMP Performance Monitoring for Wireless Interfaces(NNM iSPI Performance for Metrics), continued

Attribute		Description
		Interfaces.
Performance Polling Interval		<p>(NNM iSPI Performance for Metrics) Use this field to set the time period that NNMi waits between issuing network traffic to gather performance data for the NNM iSPI Performance for Metrics.</p> <p>The default Performance Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p>

Extend the Scope of Polling Beyond Connected Interfaces

Attribute	Description
Poll Unconnected Interfaces	<p>Configure this setting to <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p>

NNM iSPI Performance for Metrics and Wireless Interfaces

You can view 802.11 Metrics in Network Performance Server (NPS) reports.

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

For more information:

1. Open the NPS Console.
2. Go to Interface Health Extension Pack.
3. In the NPS Online Help, see About Interface Health Reports > Metrics and Topology Attributes.

If the NNM iSPI Performance for Metrics is already installed and configured in your environment:

1. In the NNMi Console, select: **Actions > HP NNM iSPI Performance > Reporting – Report Menu**.
2. In the NPS report window, select the **Reports** workspace, then **Interface_Health, InterfaceMetrics**.

Some examples of the available metrics are shown in the tables below:

- [IEEE802dot11-MIB](#)
- [CISCO-DOT11-ASSOCIATION-MIB](#)

IEEE802dot11-MIB

Metric	Description
ACKFailureCount	Total number of times the ACK signal was not received when expected.
FrameDuplicateCount	Total number of frames received that are indicated duplicate by the Sequence Control field.
MaxedOutTransmitAttempts	Total number of times the MSDU is not transmitted successfully due to the number of transmit attempts exceeding either the dot11ShortRetryLimit or dot11LongRetryLimit.
ReceivedFragmentCount	Total number of successfully received MPDUs of type Data or Management.
RTSFailureCount	Total number of clear-to-send (CTS) signals failed to be sent in response to a request-to-send (RTS).
RTSSuccessCount	Total number of clear-to-send (CTS) signals received in response to a request-to-send (RTS).
TransmittedFragmentCount	Total number of acknowledged MPDUs that have an individual address in the address 1 field or total number of MPDUs that have a multicast address in the address 1 field of type Data or Management.
SuccessfulRetryCount	Total number of times the MSDU is successfully transmitted after one or more re-transmissions.
UndecryptableFrames	Total number of frames received with the WEP subfield of the Frame Control field set to one and the WEPOn value for the key mapped to the TA's MAC address indicates that the frame should not have been encrypted or that frame is discarded due to the receiving STA not implementing the privacy option.
WLAN FCS Error Count	Total number of Frame Check Sequence errors.
WLAN FCS Error Rate	The percentage of frames with errors out of the total number of frames transmitted through the network.

CISCO-DOT11-ASSOCIATION-MIB

Metric	Description
NumActiveBridges	The number of bridges currently associated with the selected device on the selected interface.
NumActiveRepeaters	The number of repeaters currently associated with the selected device on the selected interface.
NumActiveWirelessClients	The number of wireless clients currently associated with the selected interface on the selected device.
StationsAssociated	The number of stations currently associated with the selected device on the selected interface.
StationsAuthenticated	The number of stations currently authenticated for the selected device on the selected interface.
StationsRoamedAway	Total number of stations roamed (transferred) away from this device on the selected interface. The metric displays the number of stations transferred from the selected interface since the device re-started.
StationsRoamedIn	The total number of stations roamed (transferred) from another device to this device on the selected interface. The metric displays the number of stations transferred to the selected interface since the device re-started.
StationsDeauthenticated	Total number of stations de-authenticated with this device on the selected interface. The metric displays the number of stations for which the authentication were removed from the selected interface since the device re-started.
StationsDisassociated	Total number of stations disassociated with this device on the selected interface. The metric displays the number of stations that were disassociated from the selected interface since the device re-started.

Node Settings for Monitoring




Before you start, you must establish one or more [Node Group](#) definitions that identify the nodes to which these monitoring settings will apply. See also, "[Configure Node Group Status](#)" on page 352 and "[Node Groups Provided by NNMi](#)" on page 372.

Tip: NNMi administrators can check network latency for a Node Group by adjusting the following for the management addresses associated with the specified group of nodes:

- ICMP polling frequency
- ICMP echo request packet data payload size

See the "Maintaining NNMi" chapter in the HP Network Node Manager i Software Deployment Reference for more information.



To establish monitoring behavior for a predefined Node Group:

1. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Locate the **Node Settings** tab.
 - e. Do one of the following:
 - To create an Node Settings definition, click the  New icon.
 - To edit an Node Settings definition, select a row and click the  Open icon.
 - To delete an Node Settings definition, select a row and click the  Delete button
2. Establish the appropriate settings to identify this Node Setting definition (see [Basics table](#)).
3. *Optional.* Configure the Fault Monitoring behavior for this Node Setting definition (see [Fault Monitoring table](#)).
4. (NNM iSPI Performance for Metrics) If the HP Network Node Manager iSPI Performance for Metrics Software is installed:
 - Configure the Performance Monitoring behavior for this Node Setting definition. See [Performance Monitoring table](#).
 - Configure the Baseline Settings. Navigate to the Baseline Settings tab. See "[Configure Baseline Settings for Nodes](#)" on page 467.
5. *Optional.* Set thresholds. Navigate to the Threshold Settings tab. See "[Configure Threshold Monitoring for Node Groups](#)" on page 458 for more information.

When you configure thresholds using this technique, NNMi uses the assigned Node Group as a filter (only monitoring the threshold for devices that belong to the specified Node Group). The thresholds you configure here can be monitoring various aspects (such as CPU utilization, disk space utilization, temperature, or voltage) or monitoring interfaces within nodes (such as input error rate).

6. By default, NNMi monitors only interfaces that are connected to other interfaces. When SNMP polling is enabled, NNMi automatically detects most connections. See ["Add or Delete a Layer 2 Connection" on page 314](#) for information about manual overrides.

Optional. If you want to expand monitoring behavior for this group to include unconnected Interfaces, indicate your choices in the [Extend the Scope of Polling Beyond Connected Interfaces](#) group box.

7. *Optional.* Configure the Default Change Detection Monitoring (see [Default Change Detection Monitoring table](#)).
8. Click  **Save and Close** to return to the Monitoring Configuration form.
9. Click  **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.

Caution: When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment.

To verify that State Poller is working as expected, see **Help** → **System Information** and select the **State Poller** tab. NNMi displays a report with current details about the State Poller process.

Optional. Customize the interface monitoring behavior. See ["Interface Settings for Monitoring" on page 416](#).

Basics

Attribute	Description
Ordering	<p>Enter a unique string (any length), characters 0 through 9. Consider using increments of 100 for the flexibility to insert additional items between existing items over time.</p> <p>NNMi decides which monitoring configurations apply to a node or interface based on the ordering number assigned to the configuration definitions. NNMi monitors the device according to the first match (checked from lowest number to highest number within each category). Categories are read in sequence. Click here for a description of the sequence.</p> <ol style="list-style-type: none">1. Interface Settings: NNMi monitors each of the Node's Interfaces and IP Addresses based on the first matching Interface Settings definition. The first match is the Interface Settings definition with the lowest Ordering number, then Baseline Settings.2. Node Settings: NNMi monitors each Node and each previously unmatched Interface or IP Address based on the first matching Node Settings definition. The first match is the Node Settings definition with the lowest

Basics, continued

Attribute	Description
	<p>Ordering number, then Baseline Settings.</p> <p>Note: Child node groups are included in the Ordering hierarchy. This means that if the parent node group has a lower Ordering number (for example, parent=10, child=20), then the monitoring configuration specified for the parent node group also applies to the nodes in the child node group. To override a parent node group monitoring configuration, set the Ordering number for the child node group to a number that is lower than the parent (for example, parent=20, child=10).</p> <p>3. Default Settings: If no match is found for a Node, Interface, or IP Address in 1 or 2, NNMi applies the default Monitoring Configuration settings.</p> <p>No duplicate Ordering numbers are permitted. Each Node Setting ordering number must be unique.</p>
Node Group	Choose one predefined Node Group from the list. See "Create Node Groups" on page 326 for more information.
Enable SNMP Polling on Node	<p>If <input checked="" type="checkbox"/> enabled, NNMi contacts the SNMP Agent on each node in the specified Node Group to gather SNMP data for monitoring purposes.</p> <p>If <input type="checkbox"/> disabled, NNMi does not contact the SNMP Agent on nodes in the specified Node Group for monitoring purposes (does not generate SNMP traffic to the nodes).</p> <p>Note: If you use Auto-Discovery, NNMi might detect Nodes and add them to the NNMi database as non-SNMP nodes. To configure Auto-Discovery to not add specified IP addresses to the NNMi database, not acknowledge any Hints received about them, nor gather Discovery Hints from them unless the address is a discovery seed, see "Set Outside Limits for Auto-Discovery" on page 251.</p>

Fault Monitoring

Attribute	Description
ICMP Fault Monitoring	<p>Enable Management Address Polling</p> <p>If <input checked="" type="checkbox"/> enabled, State Poller only issues ICMP (ping) requests to the management address for a node.</p> <p>Note: In the Global Control section of the Monitoring Configuration form, the Enable State Polling attribute must be enabled, too.</p> <p>If <input type="checkbox"/> disabled, State Poller does one of the following:</p>

Fault Monitoring, continued

Attribute	Description
	<ul style="list-style-type: none"> • If neither this attribute nor <i>Enable ICMP Fault Polling</i> is selected, State Poller does not use ICMP to monitor nodes covered by this configuration setting. • If <i>Enable ICMP Fault Polling</i> is selected, State Poller uses ICMP to monitor ALL IP addresses covered by this configuration setting.
Enable IP Address Fault Polling	<p>Note: This monitoring option is useful for devices that do not support SNMP. By default, this feature is enabled for the "Non-SNMP Devices" Node Group.</p> <p>If <input checked="" type="checkbox"/> enabled, State Poller issues ICMP (ping) requests to verify the availability of discovered IP address.</p> <p>Note: In the Global Control section of this form, the Enable State Polling attribute must be enabled, too.</p> <p>If <input type="checkbox"/> disabled, State Poller does the following:</p> <ul style="list-style-type: none"> • If neither this attribute nor <i>Management IP Address Polling</i> is selected, State Poller does not use ICMP to monitor nodes covered by this configuration setting. • IP addresses (both previously discovered and newly discovered) have a State attribute value of "Not Polled" and a Status attribute value of "No Status" with the color of the IP address map-symbol set to beige. See Layer 3 Neighbor View. • If both ICMP and SNMP are disabled for a Node, the Node has a Status attribute value of "No Status" and the color of the Node map-symbol background shape is set to beige. <p>Tip: To turn off ICMP polling within a subset of your network environment, use the Communication Configuration workspace Region definitions. You can define your own Regions that identify any unreachable addresses in your management domain (for example, the private IP addresses¹).</p>

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*., 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

Fault Monitoring, continued

Attribute		Description
SNMP Fault Monitoring	Enable Interface Fault Polling	<p>If <input checked="" type="checkbox"/> enabled, State Poller monitors all interfaces by issuing SNMP read-only queries to devices assigned to this level of the monitoring hierarchy.</p> <p>By default, any connected interface is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.) If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior with the Poll Unconnected Interfaces and the Poll Interfaces Hosting IP Addresses attributes.</p> <div data-bbox="643 722 1240 756" style="background-color: #f0f0f0; padding: 5px;"> Note: The following attributes must also be enabled: </div> <ul style="list-style-type: none"> • In the Global Control section of this form, the Enable State Polling attribute must be enabled, too. See Layer 2 Neighbor View. (See "Global Control Settings for Monitoring" on page 391 for more information.) • In the Communication Configuration view, enable State Poller queries with the applicable Enable SNMP Communication attributes (see "Configuring Communication Protocol" on page 129 for more information). <p>If <input type="checkbox"/> disabled, for devices assigned to this level of the monitoring hierarchy:</p> <ul style="list-style-type: none"> • Causal Engine calculates Status based only on IP address State. • The Interface objects previously discovered change to a State attribute value of "Not Polled" and a Status attribute value of "No Status" (plus any related map-symbol changes to a beige color).
	Enable Card Fault Polling	<p>Use this attribute to poll fault metrics for cards. Card fault metrics include Administrative State, Operational State, and Standby State.</p> <div data-bbox="643 1640 1169 1673" style="background-color: #f0f0f0; padding: 5px;"> Note: Card Fault Polling is enabled by default. </div> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the card fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to</p>

Fault Monitoring, continued

Attribute	Description
	<p>include card fault data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the same polling interval set for the Fault Polling Interval.</p>
Enable Chassis Fault Polling	<p>Use this attribute to poll fault metrics for chassis. Chassis fault metrics include Administrative State, Operational State, and Standby State.</p> <p>Note: Chassis Fault Polling is enabled by default.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the chassis fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include chassis fault data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the same polling interval set for the Fault Polling Interval.</p>
Enable Node Sensor Fault Polling	<p>Note: By default, this feature is enabled for the <i>Routers</i> and <i>Networking Infrastructure Devices</i> Node Groups.</p> <p>Use this attribute to poll Node Sensor fault metrics.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the Node Sensor fault data in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Node Sensor fault data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the current setting for the Fault Polling Interval in combination with this setting.</p>
Enable Physical Sensor Fault Polling	<p>Note: By default, this feature is enabled for the <i>Routers</i> and <i>Networking Infrastructure Devices</i> Node Groups.</p>

Fault Monitoring, continued

Attribute	Description
	<p>Use this attribute to poll for Physical Sensor faults on fan, power supply, temperature, and voltage. Only the health of the power supply and fan Physical Sensors are propagated to the Node level to affect Node Status.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers fault data related to the Physical Sensor fault metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Physical Sensor fault data about devices assigned to this level of the monitoring hierarchy.</p> <div data-bbox="626 722 1370 835"> <p>Tip: NNMi uses the current setting for the Fault Polling Interval in combination with this setting.</p> </div>
Fault Polling Interval	<p>The time that State Poller waits between issuing queries to gather information for any of the following that are enabled: ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses.</p> <p>The default Fault Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p> <div data-bbox="626 1104 1370 1520"> <p>Note: NNMi monitors SNMP agents (Management Addresses) according to this Fault Polling Interval, <i>even if ICMP Polling, SNMP Polling, Poll Unconnected Interfaces, and Poll Interfaces Hosting IP addresses are all disabled</i>. To prevent an SNMP Agent's address from being monitored, one of the following must be true: State Polling is disabled, current Communication Configuration settings turn off SNMP for the SNMP agent's address, the parent Node is set to Not Managed or Out of Service, or the parent node belongs to a Monitoring Configuration's Node Group with <input type="checkbox"/> Enable SNMP Polling on Node disabled.</p> </div>

SNMP Performance Monitoring (*NNM iSPI Performance for Metrics*)

Attribute	Description
	<p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information.</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute		Description
LAN Performance Monitoring	Enable Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 for more information. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of this group on a regular schedule.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers basic Interface performance data from Interfaces in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include performance data about Interfaces assigned to this level of the monitoring hierarchy.</p> <div> <p>Note: The Enable State Polling field must be enabled, too. By default the performance of connected interfaces and addresses is monitored. If you have <i>unconnected</i> interfaces that you want to monitor, expand NNMi monitoring behavior by enabling Poll Unconnected Interfaces.</p> </div>
	Enable DSx Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data about each member of the DSx Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather DSx performance data from DSx Interfaces assigned to this level of the monitoring hierarchy.</p>
	Enable SONET Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
	<p>performance data about each member of the SONET Interfaces interface group on a regular schedule. See "Interface Groups Provided by NNMi" on page 376 for more information.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather SONET performance data from SONET Interfaces assigned to this level of the monitoring hierarchy.</p>
Enable ATM Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each ATM Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather ATM performance data from ATM Interfaces assigned to this level of the monitoring hierarchy.</p> <div data-bbox="703 1199 1370 1472"> <p>Note:</p> <ul style="list-style-type: none"> • This option gathers metrics from ATM-MIB and CISCO-AAL5-MIB. • See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221. </div>
Enable Frame Relay Interface Performance Polling	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to extend the range of polling data that NNMi collects. NNM iSPI Performance for Metrics uses the additional data in a series of performance reports. When enabled, network traffic increases on your network because NNMi gathers performance data for each Frame Relay Interface.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers Frame Relay performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not gather Frame Relay</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute		Description
		<p>performance data from Frame Relay Interfaces assigned to this level of the monitoring hierarchy.</p> <p>This option gathers the following types of metrics:</p> <ul style="list-style-type: none"> • Circuit in and out octets, errors, and discards • Committed Information Rate (CIR) and Extended Information Rate (EIR) utilization • Forward Error Congestion Notification (FECN) and Backward Error Congestion Notification (BECN) counts <p>See also "Configure Discovery of ATM/Frame Relay Interfaces" on page 221.</p>
Sensor Performance Monitoring	Enable Node Sensor Performance Polling	<p>Note: By default, this feature is enabled for the <i>Routers Node Group</i> if HP Network Node Manager iSPI Performance for Metrics Software is installed.</p> <p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to poll Node Sensor performance. An NNMi administrator can set the threshold for Node Sensors related to the buffer, CPU, disk, and memory metrics.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers performance data related to the Node Sensors performance metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Node Sensors performance data about devices assigned to this level of the monitoring hierarchy.</p> <p>Tip: NNMi uses the current setting for the Performance Polling Interval in combination with this setting.</p>
	Enable Physical Sensor Performance Polling	<p>Note: By default, this feature is enabled for the <i>Routers Node Group</i> if HP Network Node Manager iSPI Performance for Metrics Software is installed.</p> <p>(<i>NNM iSPI Performance for Metrics</i>) Use this attribute to poll for Physical Sensor performance on backplanes. An NNMi administrator can set thresholds related to Physical Sensor performance metrics for backplanes. The</p>

SNMP Performance Monitoring (NNM iSPI Performance for Metrics), continued

Attribute	Description
	<p>backplane's health is not propagated to the Node level to affect Node Status.</p> <p>If <input checked="" type="checkbox"/> enabled, NNMi gathers performance data related to the Physical Sensor performance metrics in devices assigned to this level of the monitoring hierarchy.</p> <p>If <input type="checkbox"/> disabled, NNMi does not extend data collection behavior to include Physical Sensor performance data about devices assigned to this level of the monitoring hierarchy.</p> <div data-bbox="703 688 1370 835"> <p>Tip: NNMi uses the current setting for the Performance Polling Interval in combination with this setting.</p> </div>
Performance Polling Interval	<p>(<i>NNM iSPI Performance for Metrics</i>) Use this field to set the time period that NNMi waits between issuing network traffic to gather performance data for the NNM iSPI Performance for Metrics.</p> <p>The default Performance Polling Interval is 5 minutes, except for the Node Group named Microsoft Windows Systems which is 10 minutes.</p>

Extend the Scope of Polling Beyond Connected Interfaces

Attribute	Description
Poll Unconnected Interfaces	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: Your discovery configuration choices might need to be adjusted to get the results you want. For example, to meet the “connected” criteria for interfaces in switches that do not have an IP address you must add the device to which the interface is connected as a discovery seed. See "Specify Discovery Seeds" on page 287.</p>
Poll Interfaces Hosting IP Addresses	<p>Note: This monitoring option is useful for Router interfaces. By default, this feature is enabled for the "Routers" Node Group.</p> <p>If <input checked="" type="checkbox"/> enabled, any unconnected interface that has one or more addresses associated with it is monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>By monitoring the Interface (in addition to the IP address), NNMi can make more informed decisions about the health of each IP address associated with an unconnected interface.</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: The Communication Configuration workspace provides a method of overriding this setting for specific Regions. You can define your own Region to easily turn off polling to any unreachable addresses in your management</p>

Extend the Scope of Polling Beyond Connected Interfaces , continued

Attribute	Description
Poll Unconnected Interfaces	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: Your discovery configuration choices might need to be adjusted to get the results you want. For example, to meet the “connected” criteria for interfaces in switches that do not have an IP address you must add the device to which the interface is connected as a discovery seed. See "Specify Discovery Seeds" on page 287.</p>
	<p>domain (for example, the private IP addresses¹).</p>
Poll Link Aggregation Interfaces (NNMi Advanced)	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors any <i>unconnected</i> Link Aggregation² or Split Link Aggregation³ member interfaces in switch-to-switch and server-to-switch connections:</p> <ul style="list-style-type: none"> Aggregate member interfaces not connected outside the context of the Aggregator membership. Aggregate member interfaces connected to an undiscovered node (for example, the SLAG upstream switch stack).

¹These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*., 169.254.*.*, 172.16-31.*.*, and 192.168.*.*)

²Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

³Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Extend the Scope of Polling Beyond Connected Interfaces , continued

Attribute	Description
Poll Unconnected Interfaces	<p>If <input checked="" type="checkbox"/> enabled, NNMi monitors all interfaces within discovered devices (both connected and unconnected). All interfaces are monitored for MIB-II ifAdminStatus and ifOperStatus. (ifAdminStatus is set by the device administrator. ifOperStatus indicates the operational status of interface health.)</p> <p>Note: The Enable State Polling field must be enabled, and SNMP polling of some type must be enabled (for example, Enable SNMP Fault Monitoring and Enable SNMP Performance Polling).</p> <p>If <input type="checkbox"/> disabled, State Poller polls according to other configuration settings.</p> <p>Tip: Your discovery configuration choices might need to be adjusted to get the results you want. For example, to meet the “connected” criteria for interfaces in switches that do not have an IP address you must add the device to which the interface is connected as a discovery seed. See "Specify Discovery Seeds" on page 287.</p>
	<p>Tip: NNMi calculates the Aggregator status based on current status of all members. This means NNMi changes the status of the Aggregator when one member interface is down, even though the Aggregator is currently functioning well by using the other member interfaces.</p> <p>If <input type="checkbox"/> disabled, you must ensure that other Monitoring Configuration settings allow NNMi to manage each Aggregator member interface (none accidentally excluded or missed). Otherwise, NNMi calculates Aggregator status based on overall Aggregator behavior.</p>

Default Change Detection Monitoring

Attribute	Description
Enable Number of Interfaces (ifNumber) Polling	<p>Tip: For more information, see "Detect Interface Changes" on page 311.</p> <p>When enabled <input checked="" type="checkbox"/>, NNMi polls for the number of interfaces using the ifNumber value for the node. If the number of interfaces has changed, NNMi initiates a rediscovery of the node. Polling is suspended until the discovery is complete.</p> <p>When disabled <input type="checkbox"/>, NNMi does not actively poll for a change in the number of interfaces. The change is detected the next time the node is rediscovered.</p>
Enable Entity Change	When enabled <input checked="" type="checkbox"/> , NNMi polls for the last change time from the ENTITY-

Default Change Detection Monitoring, continued

Attribute	Description
Time (entLastChangeTime) Polling	<p>MIB entLastChangeTime value. If the time has changed, NNMi initiates a rediscovery of the node. Polling is suspended until the discovery is complete.</p> <p>When disabled <input type="checkbox"/>, NNMi does not actively poll the entLastChangeTime MIB value. The change is detected the next time the node is rediscovered.</p>
Change Detection Polling Interval	<p>The time that State Poller waits between issuing queries to gather information for the Number of Interfaces (ifNumber) and Entity Change (entLastChangeTime) settings enabled for Change Detection Monitoring.</p> <p>The default Change Detection Polling Interval is 4 hours.</p>

Configure Threshold Monitoring for Node Groups

If you set thresholds, NNMi generates an Incident when any threshold is violated.

You can set node thresholds using either of the following methods:

- ["Configure Count-Based Threshold Monitoring for Node Groups" below](#)
- ["Configure Time-Based Threshold Monitoring for Node Groups" on page 462](#)

Related Topics

["About Threshold Settings Provided by NNMi" on page 405](#)









["Threshold Monitoring Behavior After a System Restart or Configuration Change" on page 473](#)

Configure Count-Based Threshold Monitoring for Node Groups

Count-Based Threshold Settings enable you to determine as soon as a threshold is reached (for example, the CPU utilization for a node reaches 90%).

To establish count-based threshold monitoring behavior for nodes:

1. *Prerequisite.* Before setting thresholds, analyze performance data over time to determine wise threshold settings for each Node Group. For more information, see the following topics:
 - ["Determine Reasonable Threshold Settings" on page 471.](#)
 - ["Examples of Count-Based Threshold Monitoring" on page 378 .](#)
2. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.

- b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Navigate to the **Node Settings** tab.
 - e. Do one of the following:
 - To create an Node Settings definition, click the  New icon.
 - To edit an Node Settings definition, select a row and click the  Open icon.
 3. In the **Node Settings** form, navigate to the **Threshold Settings** tab.
 4. Do one of the following:
 - To create a threshold definition, click the  New icon and select **Count-Based Threshold Settings**.
 - To edit a threshold definition, select a row and click the  Open icon.
 - To delete a threshold definition, select a row and click the  Delete icon.
 5. Select the Monitored Attribute you want to monitor and establish the threshold values for that attribute (see [Basic Count-Based Threshold Settings table](#)).
- When you configure thresholds using this technique, NNMi uses the assigned Node Group as a filter (only monitoring the threshold for nodes belonging to the specified Node Group).
6. Click  **Save and Close** to return to the **Node Settings** form.
 7. Click  **Save and Close** to return to the **Monitoring Configuration** form.
 8. Click  **Save and Close**. NNMi applies your changes during the next regularly scheduled monitoring cycle.



Note: Threshold Incidents are disabled by default within NNMi to prevent Incident storms. If you are ready to generate Threshold Incidents, see ["Generate Performance Threshold Incidents \(NNMi iSPI Performance for Metrics\)" on page 865](#). See also ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#) for a description of the special custom incident attributes available in Threshold Incidents.

9. See also ["Find Threshold Results" on page 472](#).


Basic Count-Based Threshold Settings

Attribute	Description
Monitored	In the Monitored Attribute drop-down list, select the attribute for which you want

Basic Count-Based Threshold Settings, continued

Attribute	Description
	<p>to establish a threshold configuration.</p> <div data-bbox="477 380 1370 611"> <p>Tip: Some of the choices in the Monitored Attribute selection list do not apply in this context.</p> <p>See the tables in "About Threshold Settings Provided by NNMi" on page 405 for information about which Monitored Attributes are available for Node Groups.</p> </div>
<p>A High Threshold situation occurs when:</p> <p>The <i>Monitored Attribute</i> is greater than the <i>High Value</i> for <i>High Trigger Count</i> cycles.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  High for the appropriate Interface. • Generates the related incident (if one is Enabled ). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
High Value	<p>Designate the value that above which becomes a threshold situation. Use one of the following:</p> <ul style="list-style-type: none"> • Designate a percentage between 0.00 and 100.00. <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> ■ 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. ■ 99.99999999999999 for the highest value less than one hundred. • Designate any appropriate integer value (for example, a Management Address ICMP Response Time of 0 or greater milliseconds). <p>The High Value must be greater than or equal to the designated Low Value.</p> <div data-bbox="477 1503 1370 1612"> <p>Note: If you use the highest possible value, the threshold is disabled because it cannot be <i>crossed</i>.</p> </div>
High Value Rearm	<p>The High Value Rearm designates the lower boundary of the High Threshold <i>range of values</i>.</p> <p>After entering a High threshold situation, when a returned value is below the specified High Value Rearm, the High Threshold situation ends (for Count-Based Thresholds).</p>

Basic Count-Based Threshold Settings, continued

Attribute	Description
	<p>Note: The High Value Rearm must be less than or equal to the High Value and greater than or equal to the Low Value Rearm.</p>
High Trigger Count	<p>Designate the number of consecutive polling intervals the returned value must be greater than the specified High Value to meet the High Threshold criteria. The default value is 1.</p> <p>Tip: If the polled value represents an average over the configured polling interval, a trigger count of 1 is often appropriate.</p> <p>See the currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting that is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443
<p>A Low Threshold situation occurs when:</p> <p>The <i>Monitored Attribute</i> is less than the <i>Low Value</i> for <i>Low Trigger Count</i> cycles.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  Low for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
Low Value	<p>Designate the value that below which becomes a threshold situation. Use one of the following:</p> <ul style="list-style-type: none"> • Designate a percentage between 0.00 and 100.00. <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> ■ 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. ■ 99.9999999999999 for the highest value less than one hundred. • Designate any appropriate integer value (for example, a Management Address ICMP Response Time of 0 or greater milliseconds).






Basic Count-Based Threshold Settings, continued




Attribute	Description
	<p>The Low Value must be less than or equal to the designated High Value.</p> <p>Note: If you use the minimum possible value, the Low threshold is disabled because it cannot be <i>crossed</i>.</p>
Low Value Rarm	<p>The Low Value Rarm designates the upper boundary of the Low Threshold <i>range of values</i>.</p> <p>After entering a Low threshold situation, when a returned value is above the specified Low Value Rarm, the Low Threshold situation ends (for Count-Based Thresholds).</p> <p>Note: The Low Value Rarm must be greater than or equal to the Low Value and less than or equal to the High Value Rarm.</p>
Low Trigger Count	<p>Designate the number of consecutive polling interval the returned value must be less than the specified Low Value to meet the Low Threshold criteria. The default value is 1.</p> <p>Tip: If the polled value represents an average over the configured polling interval, a trigger count of 1 is often appropriate.</p> <p>See the currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting that is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443

Configure Time-Based Threshold Monitoring for Node Groups

Time-Based Threshold Settings enable you to determine whether a threshold is reached for a particular duration of time (for example, the CPU utilization for a node is above 90 percent for 20 out of 30 minutes).

To establish time-based threshold monitoring behavior for nodes:

1. *Prerequisite.* Before setting thresholds, analyze performance data over time to determine wise threshold settings for each Node Group.
 - ["Determine Reasonable Threshold Settings" on page 471.](#)
 - ["Examples of Time-Based Threshold Monitoring" on page 382.](#)
2. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Navigate to the **Node Settings** tab.
 - e. Do one of the following:
 - To create an Node Settings definition, click the  New icon.
 - To edit an Node Settings definition, select a row and click the  Open icon.
3. In the **Node Settings** form, navigate to the **Threshold Settings** tab.
4. Do one of the following:
 - To create a threshold definition, click the  New icon and select **Time-Based Threshold Settings**.
 - To edit a threshold definition, select a row and click the  Open icon.
 - To delete a threshold definition, select a row and click the  Delete icon.
5. Select the Monitored Attribute you want to monitor and establish the threshold values for that attribute (see [Basic Time-Based Threshold Settings table](#)).


When you configure thresholds using this technique, NNMi uses the assigned Node Group as a filter (only monitoring the threshold for nodes belonging to the specified Node Group).
6. Click  **Save and Close** to return to the **Node Settings** form.
7. Click  **Save and Close** to return to the **Monitoring Configuration** form.
8. Click  **Save and Close**. NNMi applies your changes during the next regularly scheduled monitoring cycle.

Note: Threshold Incidents are disabled by default within NNMi to prevent Incident storms.

If you are ready to generate Threshold Incidents, see ["Generate Performance Threshold Incidents \(NNM iSPI Performance for Metrics\)" on page 865](#). See also ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#) for a description of the special custom incident attributes available in Threshold Incidents.

9. See also ["Find Threshold Results" on page 472](#).


Basic Time-Based Threshold Settings

Attribute	Description
Monitored Attribute	<p>In the Monitored Attribute drop-down list, select the attribute for which you want to establish a threshold configuration.</p> <div> <p>Tip: Some of the choices in the Monitored Attribute selection list do not apply in this context.</p> <p>See the tables in "About Threshold Settings Provided by NNMi" on page 405 for information about which Monitored Attributes are available for Node Groups.</p> </div>
<p>A High Threshold situation occurs when:</p> <p>The <i>Monitored Attribute</i> is greater than the <i>High Value</i> for at least the time specified in <i>High Duration</i> within the <i>High Duration Window</i>.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  High for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met. 	
High Value	<p>Designate the value that above which becomes a threshold situation. Use one of the following:</p> <ul style="list-style-type: none"> • Designate a percentage between 0.00 and 100.00. <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> ■ 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. ■ 99.9999999999999 for the highest value less than one hundred. • Designate any appropriate integer value (for example, a Management Address ICMP Response Time of 0 or greater milliseconds). <p>The High Value must be greater than or equal to the designated Low Value.</p>

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>Note: If you use the highest possible value, the High threshold is disabled because it cannot be <i>crossed</i>.</p>
High Value Rearm	<p>The High Value Rearm designates the lower boundary of the High Threshold <i>range of values</i>.</p> <p>After entering a High threshold situation, when a returned value is below the specified High Value Rearm, the following happens (for Time-Based Thresholds):</p> <ul style="list-style-type: none"> • The current polling interval does not contribute toward High Duration. • The criteria for High Duration and High Duration Window determine when the High Threshold situation ends. <p>Note: The High Value Rearm must be less than or equal to the High Value and greater than or equal to the Low Value Rearm.</p>
High Duration	<p>Designate the minimum time within which the value must remain in the High range before the threshold state changes to High and (optionally) an incident is generated.</p> <p>The High Duration should be equal to or greater than which ever currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none"> • "Default Settings for Monitoring" on page 393 • "Interface Settings for Monitoring" on page 416 • "Node Settings for Monitoring" on page 443 <p>Tip: Setting both the High Duration and High Duration Window to zero disables the High threshold.</p>
High Duration Window	<p>Designate the window of time within which the High Duration criteria must be met.</p> <p>The value must be greater than 0 (zero) and can be the same as or greater than the High Duration value. NNMi uses a sliding window, meaning that each time the High Window Duration is reached, NNMi drops the oldest polling interval and adds the most recent.</p>

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>Tip: Setting both the High Duration and High Duration Window to zero disables the High threshold.</p>
	<p>A Low Threshold situation occurs when:</p> <p>The <i>Monitored Attribute</i> is lower than the <i>Low Value</i> for at least the time specified in <i>Low Duration</i> within the <i>Low Duration Window</i>.</p> <p>When these criteria are met, NNMi does the following:</p> <ul style="list-style-type: none"> • Updates the Threshold's state value to  Low for the appropriate Interface. • Generates the related incident (if one is Enabled <input checked="" type="checkbox"/>). If an incident is generated, NNMi closes that incident when the Threshold criteria are no longer met.
Low Value	<p>Designate the value that below which becomes a threshold situation. Use one of the following:</p> <ul style="list-style-type: none"> • Designate a percentage between 0.00 and 100.00. <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> ■ 0.000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. ■ 99.99999999999999 for the highest value less than one hundred. • Designate any appropriate integer value (for example, a Management Address ICMP Response Time of 0 or greater milliseconds). <p>The Low Value must be less than or equal to the designated High Value.</p> <p>Note: If you use the minimum possible value, the Low threshold is disabled because it cannot be <i>crossed</i>.</p>
Low Value Rearm	<p>The Low Value Rearm designates the upper boundary of the Low Threshold <i>range of values</i>.</p> <p>After entering a Low threshold situation, when a returned value is above the specified Low Value Rearm, the following happens (for Time-Based Thresholds):</p> <ul style="list-style-type: none"> • The current polling interval does not contribute toward Low Duration. • The criteria for Low Duration and Low Duration Window determine when Low Threshold ends.

Basic Time-Based Threshold Settings, continued

Attribute	Description
	<p>Note: The Low Value Rearm must be greater than or equal to the Low Value and less than or equal to the High Value Rearm.</p>
Low Duration	<p>Designate the minimum time within which the value must remain in the Low range before the threshold state changes to Low and (optionally) an incident is generated.</p> <p>The Low Duration should be equal to or greater than which ever currently configured <i>Fault Polling Interval</i> or <i>Performance Polling Interval</i> setting is influencing the Monitored Attribute you chose, because that is how often NNMi provides a data point. See the tables in "About Threshold Settings Provided by NNMi" on page 405 for details. See the following topics for instructions about finding the current polling interval setting:</p> <ul style="list-style-type: none">• "Default Settings for Monitoring" on page 393• "Interface Settings for Monitoring" on page 416• "Node Settings for Monitoring" on page 443 <p>Tip: Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p>
Low Duration Window	<p>Designate the window of time within which the Low Duration criteria must be met.</p> <p>The value must be greater than 0 (zero) and can be the same as or greater than the Low Duration value. NNMi uses a sliding window, meaning that each time the Low Window Duration is reached, NNMi drops the oldest polling interval and adds the most recent.</p> <p>Tip: Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p>

Configure Baseline Settings for Nodes

Use the **Baseline Settings** form to configure both of the following:





- NNMi
 - If you set baseline ranges, you can configure NNMi to generate an Incident when any value is outside of the baseline range.
- NNM iSPI Performance for Metrics

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

The following are affected by the Baseline Settings:




- Triple Exponential Smoothing technique to predict the baseline values of a monitored attribute. See "Integrating with Other iSPIs" in the NNM iSPI Performance for Metrics Online Help for more information about how baseline data is collected.
- Exception reports that track the frequency of threshold breaches. You can open these reports with **Actions** → **HP NNM iSPI Performance** → **Reporting - Report Menu** in the incident, node, or interface views and forms. (See [NNM iSPI Performance for Metrics Actions](#).)

To establish baseline settings for the Nodes in a Node Group:

1. Navigate to the **Node Settings** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select **Monitoring Configuration**.
 - d. Navigate to the **Node Settings** tab.
 - e. Do one of the following:
 - To create an Node Settings definition, click the  New icon.
 - To edit an Node Settings definition, select a row and click the  Open icon.
2. Navigate to the **Baseline Settings** tab.
3. Do one of the following:
 - To create an Baseline Settings definition, click the  New icon.
 - To edit an Baseline Settings definition, select a row and click the  Open icon.
4. Establish the baseline settings (see the [Baseline Settings](#) table).
5. Navigate to the **Baseline Deviations Settings** tab.
6. Establish the baseline range for monitoring this Node Group (see the [Baseline Deviation Settings](#) table).

7. By default, NNMi monitors only interfaces that are connected to other interfaces. When SNMP polling is enabled, NNMi automatically detects most connections. See ["Add or Delete a Layer 2 Connection" on page 314](#) for information about manual overrides.

Optional. If you want to expand monitoring behavior for this group to include unconnected Interfaces, indicate your choices in the [Extend the Scope of Polling Beyond Connected Interfaces](#) group box.

8. Click  **Save and Close** to return to the Node Settings form.
9. Click  **Save and Close** to return to the Monitoring Configuration form.
10. Click  **Save and Close**. NNMi applies your changes. The next regularly scheduled monitoring cycle uses the new settings.

Caution: When you establish monitoring configuration settings, NNMi must recalculate the settings for all affected objects. This can take some time and slow down your system. Consider making this change during a slow time in your network environment

11. *Optional.* Customize the node monitoring behavior. See ["Node Settings for Monitoring" on page 443](#). Also see ["Detect Interface Changes" on page 311](#).
12. See also ["Find Threshold Results" on page 472](#).

Baseline Settings for this Node Group Setting

Attribute	Description
Monitored Attribute	<p>NNMi gathers data to calculate thresholds. See "About Threshold Settings Provided by NNMi" on page 405 for information about which attributes apply here.</p> <div> <p>Tip: You may see attributes in the selection list that do not apply here.</p> </div>
Threshold Enabled	<p>Use this attribute to temporarily disable the threshold:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Duration	<p>Designate the minimum time within which the value must remain out of the configured Baseline Range before the state changes to Abnormal Range and (optionally) an incident is generated. Use the Baseline Deviation Settings tab to set the upper and lower limits of the baseline range.</p> <p>Note the following:</p> <ul style="list-style-type: none"> If you do not configure a Baseline Range, NNMi uses the default value of 3 standard deviations.

Baseline Settings for this Node Group Setting, continued

Attribute	Description
	<ul style="list-style-type: none"> The Polling Interval should be less than or equal to the Duration.
Duration Window	<p>Designate the window of time in which the Upper Baseline Limit or Lower Baseline Limit criteria must be met.</p> <p>Note: The value must be greater than 0 (zero) and can be the same as the Duration value. NNMi uses a sliding window, meaning that each time the Duration is reached, NNMi drops the oldest polling interval and adds the most recent. See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.</p>

Baseline Deviation Settings for this Node Group Setting

Attribute	Description
Upper Baseline Limit Enabled	<p>If <input checked="" type="checkbox"/> enabled, NNMi uses the Upper Baseline Limit attribute value to determine the number of standard deviations above the average that defines the upper baseline limit.</p> <p>If <input type="checkbox"/> disabled: NNMi does not define the upper baseline limit.</p>
Upper Baseline Limit	Enter the number of standard deviations above the average values that NNMi should use to determine the upper baseline limit.
Lower Baseline Limit Enabled	<p>If <input checked="" type="checkbox"/> enabled, NNMi uses the Lower Baseline Limit attribute value to determine the number of standard deviations below the average that defines the lower baseline limit.</p> <p>If <input type="checkbox"/> disabled: NNMi does not define the lower baseline limit.</p>
Lower Baseline Limit	Enter the number of standard deviations below the average values that NNMi should use to determine the lower baseline limit.

Troubleshooting Monitoring Configuration

For help with troubleshooting NNMi, see the following topics:

Determine Reasonable Threshold Settings	471
Find Threshold Results	472
Threshold Monitoring Behavior After a System Restart or Configuration Change	473
Monitor Router Redundancy Groups (NNMi Advanced)	474
Current Health of the State Poller Service	474

Verify the Monitoring Settings	474
Monitor Status Distribution for Network Objects	478

Determine Reasonable Threshold Settings

You must decide how to define normal behavior for devices in the associated Node Group or Interface Group. You can then set reasonable thresholds for the group and avoid Threshold Incident storms. See ["Examples of Count-Based Threshold Monitoring" on page 378](#) and ["Examples of Time-Based Threshold Monitoring" on page 382](#).

Access the NNM iSPI Performance for Metrics Headline report:

1. **Prerequisites:**

- a. Create a Node Group or Interface Group filter that includes the devices you want to monitor. See ["Creating Groups of Nodes or Interfaces" on page 325](#).
- b. Export the Node Group or Interface Group filter to NNM iSPI Performance for Metrics.

Tip: (*NNM iSPI Performance for Metrics only*) NNMi automatically synchronizes Interface Group and Node Group configuration changes between NNMi and NNM iSPI Performance. However, in some cases, additional configuration changes that affect Node Group or Interface Group membership might take longer to synchronize. If you do not see one or more nodes in an NNM iSPI Performance report that are visible in NNMi, use the **Actions** → **HP NNM iSPI Performance** → **Sync Interface and Node Groups** with NNMi option. This option forces NNMi to synchronize the Interface and Node Group information between NNMi and NNM iSPI Performance more quickly than the default time frame.

- c. Enable Performance Monitoring for the Node Group or Interface Group. See ["Node Settings for Monitoring" on page 443](#) or ["Interface Settings for Monitoring" on page 416](#).
 - d. Wait a minimum of 24 hours before following the steps below.
2. In the NNMi console, click **Actions** → **HP NNM iSPI Performance** → **Reporting - Report Menu**.
 3. Click the link for **Headline**. The Headline report displays data from the past 24 hours from the time you request the report. So if you run the report at 5.03 p.m., the report includes data since 5.03 p.m. yesterday. Click the **Help** link in the report if you need information about how to use this report.
 4. Open the **Topology Filters** panel and restrict your view to the network elements for which you are determining thresholds.
 5. Click **Confirm Selection** to return to the report.

6. Open the **Time Controls** panel and select a start time and interval.
7. Click **Confirm Selection**.
8. The report appears using the filters you specified.
9. Study the Range & Exceptions graphs to guide your decision about what constitutes reasonable threshold settings. See online help for this report for information about how to read this report.

Find Threshold Results

The results of your threshold monitoring provide data in the following locations:

- NNM iSPI Performance for Metrics reports. See the NNM iSPI Performance for Metrics documentation.
- NNMi's **Monitoring** workspace → **Interface Performance** table view (Requires *HP Network Node Manager iSPI Performance for Metrics Software*) – [click here for more information](#).
- NNMi's **Node** form:
 - [Node Sensors tab](#) — Displays a list of node health issues associated with the selected node. Open threshold issues can influence the Status of nodesensors.
 - [Custom Polled Instances tab](#) — Open [Custom Poller](#) threshold issues can influence results shown here.
 - [Conclusions tab](#) — Open threshold issues can influence conclusion calculations.
- NNMi's **Node Sensor** form:
 - [Monitored Attributes tab](#) — Displays a list of all related monitored attributes. The threshold results can influence the State of monitored attributes.
 - [Conclusions tab](#) — Open threshold issues can influence conclusion calculations.
- NNMi's **Chassis** form:
 - [Physical Sensors tab](#) — Displays a list of health issues associated with the selected chassis. Open threshold issues can influence the Status of physical sensors.
 - [Conclusions tab](#) — Open threshold issues can influence conclusion calculations.
- NNMi's **Physical Sensor** form:
 - [Monitored Attributes tab](#) — Displays a list of all related monitored attributes. The threshold results can influence the State of monitored attributes.

- [Conclusions tab](#)— Open threshold issues can influence conclusion calculations.
- NNMi's **Interface** form:
 - [Performance tab](#) — Displays a list of currently configured thresholds related to the selected interface.

Tip: This information is also visible in the Monitoring workspace, Interface Performance view.

- [Conclusions tab](#) — Open threshold issues can influence conclusion calculations.
- NNMi's **Layer 2 Connection** form:
 - [Conclusions tab](#) — Open threshold issues can influence conclusion calculations.

Confirm Threshold Configuration Settings

To view the threshold settings that produced the threshold state values above:

- Select an Interface, Node Sensor, or Node, click **Actions** → **Configuration Details** → **Monitoring Settings**, and then scroll down to the Count-Based Threshold Settings table and Time-Based Threshold Settings table.

Tip: These tables do not appear if the selected Interface, Node Sensor, or Node is not a member of any Interface Group or Node Group with configured thresholds.

Threshold Monitoring Behavior After a System Restart or Configuration Change

After a network device is restarted, NNMi does the following:

- NNMi retains the device's former State value and updates the State value as soon as the new State is positively identified based on current configuration settings for Discovery and Monitoring.
- If the prior State value were **Not Polled**, NNMi changes the State to **Nominal** before determining the new State.

After a Threshold setting is re-configured, NNMi can positively identify the current device State when any the following criteria are met:

- For Count-Based Thresholds, High Trigger Count or Low Trigger Count is reached.
- For Time-Based Thresholds:

- High Window Duration or Low Window Duration is reached.
- NNMi receives enough data samples to identify the State. For example, if the Threshold definition setting is monitoring a value for 20 out of 30 minutes and the threshold is crossed within the first 20 minutes, then NNMi can update the State after 20 minutes has passed.

Monitor Router Redundancy Groups (NNMi Advanced)

NNMi monitors state and priority information for any discovered objects in the network. These objects include Router Redundancy Members and Tracked Objects. See [Router Redundancy Group View](#) for more information about Router Redundancy Groups and the objects associated with them.

The polling interval used is the Fault Polling Interval that is set for the node associated with the Router Redundancy Member or Tracked Object.

If you do not want these objects polled:

- Set the Management Mode for each node to **Not Managed** or **Out of Service**. See [Stop or Start Managing an Object](#) for more information about Management Mode.
- Disable all Router Redundancy Group monitoring. See [Set Global Monitoring](#).

NNMi Advanced also uses Router Redundancy Group objects when calculating a Path View between two nodes that have IPv4 addresses. See [Path View with NNMi Advanced](#) for more information.

Current Health of the State Poller Service

At any time, you can check the current health statistics about the State Poller Service.

To see a report of the health of the State Poller Service, click **Help** → **System Information** and navigate to the **State Poller** tab. For more information see [System Information: State Poller tab](#).

The State Poller Service contributes towards discovery and ongoing monitoring. See ["About Each NNMi Service" on page 88](#).

Verify the Monitoring Settings

After the NNMi administrators configure the monitoring settings, configuration for particular objects can be verified to ensure that everything is working correctly. Examples of objects that have Monitoring Settings reports include Nodes, Interfaces, IP addresses, Router Redundancy Groups, Tracked Objects, Node Sensors, and Physical Sensors. Open the object's form and use the **Actions** → **Configuration Details** → **Monitoring Settings** menu item to display the report.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

(*NNMi Advanced*) If the Global Network Management feature is enabled and you are signed into a Global Manager:

- Node managed by the Global Manager = **Actions** → **Configuration Details** → **Monitoring Settings** opens a report, provided by the Global Manager (NNMi management server).
- Node managed by a Regional Manager = **Actions** → **Configuration Details** → **Monitoring Settings** accesses that Regional Manager (NNMi management server) and requests the report.

Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

To verify the monitoring configuration for a Node (SNMP Agent), Interface, IP address, or Card:

1. Navigate to the view for that object (for example, **Inventory** workspace, **Nodes**) view.
2. Select the row representing the object information.
3. Select **Actions** → **Configuration Details** → **Monitoring Settings**.

NNMi displays the monitoring configuration settings for the selected object.

Note: This menu item also is available on any object's form.

To verify the monitoring configuration for a Router Redundancy Member:

1. Navigate to a Router Redundancy Group view (for example, **Inventory** workspace, **Router Redundancy Groups** view).
2. Double-click the row representing the Router Redundancy Group configuration you want to see.
3. From the Router Redundancy Members tab, double-click the row representing the Router Redundancy Member configuration you want to see.
4. Select **Actions** → **Configuration Details** → **Monitoring Settings**.

NNMi displays the monitoring configuration settings for the selected object.

To verify the monitoring configuration for a Tracked Object:

1. Navigate to a Router Redundancy view (for example, **Inventory** workspace, **Router Redundancy Groups** view).

2. Double-click the row representing the Router Redundancy Group.
3. From the Router Redundancy Members tab, double-click the row representing the Router Redundancy Group Member.
4. From the Tracked Objects tab, double-click the row representing the Tracked Object.
5. Select **Actions** → **Configuration Details** → **Monitoring Settings**.

NNMi displays the monitoring configuration settings for the selected object.

To verify the monitoring configuration for a Node Sensor or Physical Sensor:



1. Navigate to the view for that object (for example, **Inventory** workspace's **Node Sensors** view or **Physical Sensors** view).
2. Double-click the row representing the Node Sensor or Physical Sensor Configuration.
3. Select **Actions** → **Configuration Details** → **Monitoring Settings**.

NNMi displays the monitoring configuration settings for the selected object.

Check status and connectivity of important interfaces.

1. Open a Layer 2 Neighbor View map of each important interface's parent device. See [Viewing Maps \(Network Connectivity\)](#).
2. Each connected interface has a little square symbol around the edge of the parent device's map symbol. For example:




3. Hover your mouse over the square to verify the identify of your important interface on the map.
4. Verify that the status color of each important interface is not  Unknown or  **Unmanaged**¹ (see [About Status Colors](#)). For example:



¹Indicates the Management Mode is "Not Managed" or "Out of Service".

- By default, NNMi only monitors the health of connected interfaces. A line appears on the map between interfaces when they are connected. For example:




- To add a connection, see ["Add or Delete a Layer 2 Connection" on page 314](#).



Check status and connectivity of important addresses.

- Open a Layer 3 Neighbor View map of each important parent device. See [Viewing Maps \(Network Connectivity\)](#).
- Each address that is connected to another address in the same subnet has a little hexagon symbol around the edge of the parent device's map symbol. For example:



- Hover your mouse over the hexagon to verify the identify of your important address on the map.
- NNMi monitors the health of addresses only if you enable [ICMP Address Monitoring](#). A line appears on the map between addresses when they are connected. The line represents the subnet. For example:



5. If ICMP Address Monitoring is enabled, verify that the status color of each important address is not  Unknown or  Unmanaged¹ (see [About Status Colors](#)). For example:



6. To add a connection, see ["Add or Delete a Layer 2 Connection" on page 314](#).

See ["Configure NNMi Monitoring Behavior" on page 387](#) for information about establishing monitoring behavior.

Monitor Status Distribution for Network Objects

NNMi enables you to view the overall health of your network by providing Stacked Area Graphs that display the distribution of Node, Interface, and IP Address Status information over time.

To view Status Distribution Graphs:

1. Select **Tools** → **Status Distribution Graphs**.
2. Select the object type for which you want to display Status distribution. For example, **Node Status**.

NNMi displays a Stacked Area Graph of the distribution of the object's Status over time.

See **Help** → **Using Stacked Area Graphs** from the Graph's menu bar for more information about using Stacked Area Graphs.

Tip: If you do not want to display unpolled objects (No Status), use the graph's **File** → **Select Area** menu item and clear the **No Status** check box.

See ["Configure NNMi Monitoring Behavior" on page 387](#) for information about establishing monitoring behavior.

Create Custom Polling Configurations

Tip: Check to see if the threshold you want is already defined. See ["About Threshold Settings Provided by NNMi" on page 405](#).

The Custom Poller feature enables you to take a proactive approach to network management by using SNMP MIB Expressions to specify additional information that NNMi should poll. You can also specify States that should be assigned to polled MIB Expression values, including any thresholds that should be set and monitored.

¹Indicates the Management Mode is "Not Managed" or "Out of Service".

For example, if you have the HOST-RESOURCES-MIB loaded on your NNMi management server, you might want to monitor additional information using a single MIB variable, such as `hrDeviceStatus`, so that you can monitor information about a COM (communication) port, Loopback interface, or Ethernet Adapter Status. You might also want to monitor additional information using multiple MIB variables.

For example, disk utilization could be calculated and polled using a MIB Expression similar to the following: $(hrStorageUsed / hrStorageSize)$

Tip: To view the list of MIB Variables supported for a particular node, use the **Tools** → **MIB Browser** menu option. See [Run SNMP Walk Commands \(MIB Browser\)](#).

Note the following:

- The MIB variables included in the MIB Expression that you want NNMi to poll must be loaded on the NNMi management server.
- A Custom Poller Policy is applied to the selected node or all the nodes in its specified Node Group as follows:
 - At the time the Policy Active State attribute is set to **Active**. See ["Create a Policy" on page 516](#) for more information.
 - Each time the network is rediscovered as specified by the **Rediscovery Interval**. See ["Adjust the Rediscovery Interval" on page 231](#) for more information.
 - Each time you select **Actions** → **Polling** → **Configuration Poll** from the NNMi console.
- You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller configuration.

When using [nnmcustompollerconfig.ovpl](#) to create Custom Poller Policies, you must first create the Node Group to which you want to gather the additional information.

When using [nnmcustompollerconfig.ovpl](#), each MIB included in the MIB Expression does NOT need to be loaded on the NNMi management server.

Use [nnmcustompollerconfig.ovpl](#) to also enable, disable, configure, list, update, and delete Custom Poller configurations.

As an Administrator, to configure Custom Polling you want to perform the following tasks:

1. *Prerequisite:* Install the MIB files needed for SNMP communication with the devices in your network environment:
 - a. ["Load MIBs" on page 1492](#)
 - b. ["Unload MIBs" on page 1496](#)
2. ["Enable or Disable Custom Poller" on the next page](#)

3. ["Create a Custom Poller Collection" on the next page](#)
 - a. ["Configure Basic Settings for a Custom Poller Collection" on page 484](#)
 - b. ["Specify the MIB Variable Information for a Custom Poller Collection" on page 493](#)
 - c. ["Configure Threshold Information for a Custom Poller Collection" on page 507](#)
 - d. ["Configure Comparison Maps for a Custom Poller Collection" on page 513](#)
4. ["Create a Policy" on page 516](#)
5. ["Create a Report Group \(NNM iSPI Performance for Metrics\)" on page 520](#)




Enable or Disable Custom Poller

The Custom Poller Configuration form enables you to enable or disable your Custom Poller Collections. You can also view the Custom Poller Collections and Policies that have been created.

Note: Custom Poller is not enabled by default. When Custom Polling is disabled, the State of Polled Instances retain the most recent value before Custom Poller was disabled.


Tip: You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller configuration. When using [nnmcustompollerconfig.ovpl](#) to create Custom Poller Policies, you must first create the Node Group to which you want to gather the additional information. Use [nnmcustompollerconfig.ovpl](#) to also enable, disable, configure, list, update, and delete Custom Poller configurations.


To enable Custom Poller:

1. Navigate to the  **Configuration** workspace.
2. Expand the **Monitoring** folder.
3. Select **Custom Poller Configuration**.
4. Click **Enable Custom Poller** .
5. Click the  **Save** icon.

To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help** → **System Information**.

To disable Custom Poller:

1. Navigate to the  **Configuration** workspace.
2. Expand the **Monitoring** folder.

3. Select **Custom Poller Configuration**.
4. Click to clear **Enable Custom Poller** ☐.
5. Click the  **Save** icon.

To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help** → **System Information**.

The Custom Poller Collections tab enables you to create a Custom Poller Collection. See ["Create a Custom Poller Collection" below](#) for more information.

The Policies tab enables you to create one or more policies for a Collection. See ["Create a Policy" on page 516](#) for more information.

Create a Custom Poller Collection

A Custom Poller Collection defines the information you want to gather (poll) as well as how NNMi reacts to the gathered data. For example, by default, you can specify whether you want to do either of the following:

Tip: These features require that the Custom Poller Collection Type is **Instance**. See ["Configure Basic Settings for a Custom Poller Collection" on page 484](#) for more information.

- Configure Thresholds or Comparison Maps that map polled MIB Expression values to States and optionally causes incidents to be generated.
- Include State changes in calculations for the source Node's Status.

Each Custom Poller Collection can have one or more Policies. Each Policy specifies the Node Group from which you want to gather the additional information.

Instance Custom Poller Collection Type only. The first time a MIB Expression is validated with discovery information, the results appear in a Custom Polled Instance object. The Polled Instance object is updated whenever a change in State occurs and includes the most recent polled value that caused the State to change.

Tip: You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller configuration. When using [nnmcustompollerconfig.ovpl](#) to create Custom Poller Policies, you must first create the Node Group to which you want to gather the additional information. Use [nnmcustompollerconfig.ovpl](#) to also enable, disable, configure, list, update, and delete Custom Poller configurations.

[Click here](#) for a diagram that describes Custom Poller Collections and their associated Policies:

The screenshot shows a software interface for configuring network monitoring. It is divided into two main sections: **Custom Poller Configuration** and **Custom Poller Collections**.

Custom Poller Configuration

- Policies**
 - Define **"Where (which Node Group)"**
 - NNMI gathers this extra information.
 - Define the logic of **"When"** NNMI collects this extra information.
 - When the information matches a configured MIB Filter?
 - Each time a defined Polling Interval (time period) is exceeded?

Important Nodes (Node Group)

Switch_9 SwitchRouter_3

Custom Poller Collections

- Basics**
 - Define **"How"** NNMI reacts to the gathered data.
 - Generate Incidents that alert operators to certain situations?
 - Include State changes in calculations for the source Node's Status?
 - Map a MIB Filter Variable (if necessary)
- MIB Variables**
 - Define **"What information"** you want to gather.
 - Click to select one OID or click to define a MIB Expression
 - Set thresholds?
 - Map polled values to States by defining comparison maps?


To create a Custom Poller Collection, do the following:

1. Navigate to the **Custom Poller Collections** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.
 - d. Select the **Custom Poller Collections** tab.
 - e. Do one of the following:
 - To create a Custom Poller Collection, click the **New** icon.
 - To edit a Custom Poller Collection, double-click the row representing the configuration you want to edit.
2. Make your configuration choices (see [table](#)).
3. Click **Save and Close**.

Note: When you save a Collection configuration, each Policy for that Collection changes to **Active State Suspended**. When you are finished making your Custom Poller Configuration changes, set the Active State to **Active** for each of the policies in the Custom Poller Collection that you want to be in use. To make a Policy active, access the Custom Poller Configuration: Policy tab, open each associated Policy, and change the Active State to **Active**. See ["Create a Policy" on page 516](#) for more information.

To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help → System Information**.

Custom Poller Collection Configuration Tasks

Task	How
"Configure Basic Settings for a Custom Poller Collection" on the next page	Provide the basic information for a Custom Poller Collection configuration.
"Specify the MIB Variable Information for a Custom Poller Collection" on page 493	You specify the MIB Expression you want to poll. Use the MIB Expression editor to specify the MIB Variable and any constant or arithmetic operator you want to use in the MIB Expression. Navigate the  MIB Tree to select each MIB OID you need to define your MIB Variable.
"Configure Threshold Information for a Custom Poller Collection" on page 507	<i>Optional. Instance Custom Poller Collection Type only.</i> Specify minimum and maximum threshold values for the MIB Expression results and assign these thresholds to States.
"Configure Comparison Maps for a Custom Poller Collection" on page 513	<i>Optional. Instance Custom Poller Collection Type only.</i> Use Comparison Maps to assign a State value to a potential polled value of a MIB Expression.

Note: Thresholds and Comparison Maps contribute to State calculations. If you configure both Thresholds and Comparison Maps, NNMi first checks Threshold settings to determine State values. If the Threshold evaluates to non-Normal, NNMi uses the Threshold settings to determine State values. If the Threshold evaluates to Normal, NNMi checks for a non-Normal State using any Comparison Maps configuration.




Configure Basic Settings for a Custom Poller Collection

The Basic settings for a Custom Poller Collection include the Name and Collection Type of the Custom Poller Collection, as well as whether to have this Collection affect a Node's Status or generate incidents under specified conditions. You also use the Basic settings to configure whether NNMi exports Custom Poller Collection metrics to a comma-separated values (CSV) file for use in other applications.

Note: If you are an NNMi administrator, you can change the maximum amount of disk space that NNMi uses when exporting data to `<collection_name>.csv` files. See the "Maintaining NNMi" chapter in the HP Network Node Manager i Software Deployment Reference for more information.

Tip: You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller Collection or to list or update Custom Poller Collections. When using [nnmcustompollerconfig.ovpl](#), each MIB included in the MIB Expression does NOT need to be loaded on the NNMi management server.

To configure the Basic settings for a Custom Poller Collection:









1. Navigate to the **Custom Poller Collection** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** view.
 - d. Select the **Custom Poller Collections** tab.
 - e. Do one of the following:
 - To create a Collection, click the  **New** icon.
 - To edit a Collection, double-click the row representing the configuration you want to edit.
2. Provide the required basic settings (see the [Basics for this Custom Poller Collection](#) table).
3. Complete the configuration for this Custom Poller Collection configuration, if you have not already done so:
4. Click  **Save and Close** to return to the **Custom Poller Configuration** form.

To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help** → **System Information**.

Basics for this Custom Poller Collection

Attribute	Description
Name	<p>The name for the Custom Poller Collection configuration.</p> <p>The name can be up to 50 alphanumeric characters. Spaces are permitted. The following special characters (<, >, ", ', &, /, \, #) are not permitted.</p> <div data-bbox="427 464 1370 611"> <p>Note: The Custom Poller Collection name appears in any incidents generated as a result of the collection. Specify a name that will help you to identify the MIB information being polled.</p> </div>
Collection Type	<p>Enables you to specify the method you want Custom Poller to use to collect MIB information.</p> <div data-bbox="427 720 1370 831"> <p>Tip: You can switch between the Bulk and Instance Collection Type as needed.</p> </div> <ul style="list-style-type: none"> • Select Instance when you want to collect information for a small number of MIB instances or do any of the following: <ul style="list-style-type: none"> ■ Configure Thresholds or Comparison Maps that map polled MIB Expression values to States and optionally causes incidents to be generated. ■ Include State changes in calculations for the source Node's Status. ■ Include Status for the associated Custom Node Collections. ■ Monitor Custom Polled Instances for the MIB information collected. • Select Bulk when you want to collect information for a large number of MIB instances. This method is useful for generating large amounts of data that can be exported to comma-separated values (CSV) files for customized reports or for use with NNM iSPI Performance for Metrics. <div data-bbox="461 1415 1370 1661"> <p>Note: NNMi bypasses Custom Polled Instance discovery and simply polls all instances of the configured MIB Variables for the nodes specified in the Custom Poller policies that use a Bulk Custom Poller Collection. This means that NNMi does not create Custom Polled Instances for the MIB information collected. Also see "Create a Policy" on page 516 see for more information.</p> </div> <div data-bbox="461 1694 1370 1841"> <p>Tip: The MIB Expression value can be either a MIB Expression or a MIB OID. Use the Variables tab to specify each MIB Expression or MIB OID from which you want to collect information.</p> </div>

Basics for this Custom Poller Collection, continued

Attribute	Description															
Affect Node Status	<p>Instance Custom Poller Collection Type only.</p> <p>If enabled <input checked="" type="checkbox"/>, NNMi uses the Status of a Custom Node Collection to affect the associated topology Node's Status.</p> <p>To understand how the topology Node Status is affected, you must understand the relationship between a Custom Node Collection and a topology Node. Click here for more information:</p> <p>As shown in the following diagram, a Custom Node Collection identifies each topology node that has at least one associated Custom Poller Collection and Custom Poller Policy pair.</p> <div><div><div>Custom Poller Configuration</div><div><div>Custom Poller Policy</div><div>Node Group = "Important Nodes"</div></div><div><div>Custom Poller Collection</div><div>with Threshold Settings and/or Comparison Maps + <input checked="" type="checkbox"/> Affect Node Status</div><div>Results of Collection:</div></div></div><div><div>Important Nodes (Node Group)</div><div><div> Switch_9</div><div> SwitchRouter_3</div></div></div><div>Custom Node Collection "Status" Affects Node "Status"</div></div> <div><div>Monitoring</div><div><div>Custom Node Collections</div><div><div>Custom Node Collections</div><table><tr><th>Status</th><th>Node</th><th>Active State</th><th>Status</th><th>Last Modified</th></tr><tr><td></td><td>Switch_9</td><td>Active</td><td></td><td>Jun 2, 2011 4:17:10 PM</td></tr><tr><td></td><td>SwitchRouter_3</td><td>Active</td><td></td><td>Jun 2, 2011 4:16:34 PM</td></tr></table></div></div></div>	Status	Node	Active State	Status	Last Modified		Switch_9	Active		Jun 2, 2011 4:17:10 PM		SwitchRouter_3	Active		Jun 2, 2011 4:16:34 PM
Status	Node	Active State	Status	Last Modified												
	Switch_9	Active		Jun 2, 2011 4:17:10 PM												
	SwitchRouter_3	Active		Jun 2, 2011 4:16:34 PM												
Export Custom Poller Collection	<p>If enabled <input checked="" type="checkbox"/>, NNMi exports the Custom Poller Collection to a comma-separated values (CSV) file that is written to the following directory (see "About Environment Variables" on page 86):</p> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\databases\custompoller\export\final</pre> <p>Linux:<pre>\$NnmDataDir/shared/nnm/databases/custompoller/export/final</pre><p>When exporting Custom Poller Collections, note the following:</p><ul style="list-style-type: none">NNMi includes the following information in the CSV file:<ul style="list-style-type: none">Node UUID</p>															


Basics for this Custom Poller Collection, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ IP address ■ Node Name (Host Name of the Node) ■ The MIB expression or the numeric Object Identifier of the MIB variable ■ Time stamp (in milliseconds) ■ Poll interval (in milliseconds) ■ MIB Instance (number used to identify the row in the MIB table) ■ Metric value ■ Display Attribute (See "MIB Expressions Form (Custom Poller)" on page 495 for more information) ■ Filter Value (See "MIB Expressions Form (Custom Poller)" on page 495 for more information) <ul style="list-style-type: none"> • By default, NNMi accumulates the data and writes the metrics to the CSV file, one metric per Custom Poller Collection instance, every 5 minutes. • NNMi names each CSV file using the Custom Poller Collection name, appended with the timestamp (yyyymmddHHmmssSSS). • NNMi monitors the <code>custompoller</code> directory to ensure that the Custom Poller metrics do not fill the disk. By default, after the <code>custompoller</code> directory has consumed more than one gigabyte of disk space, NNMi removes the oldest metric files as it writes new files to the disk. • See the HP Network Node Manager i Software Deployment Reference for information about how to change default values, including the directory name, disk size, and the interval at which NNMi accumulates the data before writing the metric files to the disk. • If you have a High Availability (HA) environment, NNMi places the CSV files on the shared disk. • If you are using Application Failover, NNMi replicates these files to the failover system. <p>See the HP Network Node Manager i Software Deployment Reference for more information about HA and Application Failover.</p> <ul style="list-style-type: none"> • <i>Export to Network Performance Server (NPS) only.</i> If you change the name of a Custom Poller Collection or one of the MIB Variables associated with a Custom Poller Collection, NPS removes all of the historical reporting data related to the

Basics for this Custom Poller Collection, continued

Attribute	Description						
	<p>change as follows:</p> <table border="1"> <thead> <tr> <th>Name Change</th><th>Historical Data Removed</th></tr> </thead> <tbody> <tr> <td>Custom Poller Collection</td><td>All of the data associated with the original Custom Poller Collection</td></tr> <tr> <td>MIB Variable</td><td>All of the data associated with the original MIB Variable name</td></tr> </tbody> </table> <p>If disabled <input type="checkbox"/>, NNMi does not export the Custom Poller Collection information.</p>	Name Change	Historical Data Removed	Custom Poller Collection	All of the data associated with the original Custom Poller Collection	MIB Variable	All of the data associated with the original MIB Variable name
Name Change	Historical Data Removed						
Custom Poller Collection	All of the data associated with the original Custom Poller Collection						
MIB Variable	All of the data associated with the original MIB Variable name						
Compress Export File	<p>If enabled <input checked="" type="checkbox"/>, NNMi exports the Custom Poller Collection in compressed format and appends *.gz to the *.csv file suffix.</p> <p>If you have more than one Custom Poller Collection with the same name, note the following:</p> <ul style="list-style-type: none"> • If at least one of those Custom Poller Collections has Compress Export File enabled, NNMi compresses all of the exported Custom Poller Collections with the same name. • NNMi writes the Custom Poller Collection information to the same CSV file. <p>If Disabled <input type="checkbox"/>, NNMi does not compress the CSV file.</p>						
Generate Incident	<p><i>Instance Custom Poller Collection Type only.</i></p> <p>If Enabled <input checked="" type="checkbox"/>, NNMi generates an incident when a Threshold (defined on the Thresholds tab) is reached or exceeded, or when a specified MIB returns a value that causes the Node's <i>State</i> to be other than Normal (defined on the Comparison Maps tab).</p> <p>To generate incidents for the Custom Node Collection, select Custom Node Collection.</p> <p>To generate incidents for Custom Polled Instances, select Custom Polled Instance.</p> <p>If disabled <input type="checkbox"/>, NNMi does not generate any incidents for Custom Node Collections or Custom Polled Instances.</p> <p>To understand how Custom Node Collection incidents are generated, it is important to understand the relationship between a Custom Poller Policy and a Custom Poller Collection. Click here for more information:</p> <ul style="list-style-type: none"> • Each Custom Poller Collection is associated with a Custom Poller Policy that identifies the Node Group to which the policy and collection apply. 						

Basics for this Custom Poller Collection, continued

Attribute	Description																											
	<ul style="list-style-type: none">The results of each Custom Poller Collection and Custom Poller Policy pair appear in one row of the Monitoring workspace's Custom Node Collection view. A Custom Node Collection identifies each topology node that has at least one associated Custom Poller Collection and Custom Poller Policy pair. <p>Multiple Custom Poller Collection and Custom Poller Policy pairs can be associated with the same Node Group. Results appear as multiple rows for each Node Group member in the Custom Node Collection view.</p> <ul style="list-style-type: none">Click here to view a diagram of this relationship.  <p>Incident Visible in Node form's "Incident" tab</p> <table><tr><th colspan="2">Management Event Configurations</th></tr><tr><th>Name</th><th>SNMP Object ID</th></tr><tr><td>CustomPollCritical</td><td>.1.3.6.1.4.1.11.2.17.19.2.0.10</td></tr><tr><td>CustomPollMajor</td><td>.1.3.6.1.4.1.11.2.17.19.2.0.11</td></tr><tr><td>CustomPollMinor</td><td>.1.3.6.1.4.1.11.2.17.19.2.0.12</td></tr><tr><td>CustomPollWarning</td><td>.1.3.6.1.4.1.11.2.17.19.2.0.13</td></tr></table> <p>Incident Visible in Custom Node Collection form's "Incident" tab</p> <table><tr><th>Status</th><th>Node</th><th>Active State</th><th>Status</th><th>Last Modified</th></tr><tr><td>🟡</td><td>Switch_9</td><td>Active</td><td>Jun 2, 2011 4:17:10 PM</td><td></td></tr><tr><td>🔴</td><td>SwitchRouter_3</td><td>Active</td><td>Jun 2, 2011 4:16:34 PM</td><td></td></tr></table>	Management Event Configurations		Name	SNMP Object ID	CustomPollCritical	.1.3.6.1.4.1.11.2.17.19.2.0.10	CustomPollMajor	.1.3.6.1.4.1.11.2.17.19.2.0.11	CustomPollMinor	.1.3.6.1.4.1.11.2.17.19.2.0.12	CustomPollWarning	.1.3.6.1.4.1.11.2.17.19.2.0.13	Status	Node	Active State	Status	Last Modified	🟡	Switch_9	Active	Jun 2, 2011 4:17:10 PM		🔴	SwitchRouter_3	Active	Jun 2, 2011 4:16:34 PM	
Management Event Configurations																												
Name	SNMP Object ID																											
CustomPollCritical	.1.3.6.1.4.1.11.2.17.19.2.0.10																											
CustomPollMajor	.1.3.6.1.4.1.11.2.17.19.2.0.11																											
CustomPollMinor	.1.3.6.1.4.1.11.2.17.19.2.0.12																											
CustomPollWarning	.1.3.6.1.4.1.11.2.17.19.2.0.13																											
Status	Node	Active State	Status	Last Modified																								
🟡	Switch_9	Active	Jun 2, 2011 4:17:10 PM																									
🔴	SwitchRouter_3	Active	Jun 2, 2011 4:16:34 PM																									
	<p>When generating incidents for Custom Node Collections, note the following:</p> <ul style="list-style-type: none">If a Custom Node Collection meets or exceeds a configured threshold, an incident is generated for the associated Custom Node Collection.NNMi generates only one incident per Custom Node Collection. This means if multiple instances within the Custom Node Collection have a Status other than Normal, NNMi generates only one incident using the details for the highest severity instance.If multiple instances within the Custom Node Collection have a Status other than Normal and more than one of them has the highest severity, NNMi selects one of the Custom Node Collection instances to generate the incident.																											

Basics for this Custom Poller Collection, continued

Attribute	Description
	<ul style="list-style-type: none">• The most severe incident status is then propagated from the Custom Node Collection to the corresponding node object.• If the Custom Node Collection with the most severe status returns to normal, NNMi closes the corresponding incident. If another instance in the Custom Poller Collection has a status other than normal, NNMi generates a new incident using the next highest severity. <p>To understand how Custom Polled Instance incidents are generated, it is important to understand how Custom Polled Instances are generated. Click here for more information:</p> <ul style="list-style-type: none">• The first time a MIB Expression is validated with discovery information, the results appear in a Custom Polled Instance object. A Custom Polled Instance represents the results of a MIB expression when it is evaluated against a node. The Custom Polled Instance is updated whenever a change in State occurs and includes the most recent polled value that caused the State to change.• A node can be associated with multiple Custom Polled Instances when its associated MIB expression includes MIBs that have multiple instances per node. For example, the associated MIB expression might perform a calculation using the ifInOctets and ifOutOctets MIB values. Using the MIB Filter and MIB Filter Variable specified, NNMi calculates these values for each interface that meets the filter criteria and that is associated with a node in the Custom Poller Collection.• Click here to view a diagram of this relationship.



Basics for this Custom Poller Collection, continued

Attribute	Description																						
	<div><div><div><div><div>Custom Poller Configuration</div><div><div>Custom Poller Policy</div><div>Node Group = "Important Nodes"</div></div><div><div>Custom Poller Collection</div><div>with Threshold Settings and/or Comparison Maps</div><div><div><div><div><div>+</div><div><input checked="" type="checkbox"/> Generate Incident</div></div><div>Incident Source Object: Custom Polled Instance</div></div></div></div></div></div><div>Results of Collection:</div><div><div>Management Event Configurations</div><table><thead><tr><th>Name</th><th>SHMP Object ID</th></tr></thead><tbody><tr><td>CustomPolledInstanceOutOfRange</td><td>.1.3.6.1.4.1.11.2.17.19.2.0.9999</td></tr></tbody></table></div><div>Monitoring</div><div>Custom Polled Instances</div><div><table><thead><tr><th>Status</th><th>Sta</th><th>Last State Chang</th><th>MIB Expression</th><th>MIB</th><th>Filt</th></tr></thead><tbody><tr><td></td><td></td><td>0.00000091483428</td><td>If%util</td><td>.21</td><td>21</td></tr><tr><td></td><td></td><td>0.0</td><td>If%util</td><td>.9</td><td>9</td></tr></tbody></table></div></div><div><div>Important Nodes (Node Group)</div><div><div></div>Switch_9</div><div><div></div>SwitchRouter_3</div></div><div>Incident Visible in Node form's "Incident" tab</div><div>Incident Visible in Custom Node Instance form's "Incident" tab</div></div></div>	Name	SHMP Object ID	CustomPolledInstanceOutOfRange	.1.3.6.1.4.1.11.2.17.19.2.0.9999	Status	Sta	Last State Chang	MIB Expression	MIB	Filt			0.00000091483428	If%util	.21	21			0.0	If%util	.9	9
Name	SHMP Object ID																						
CustomPolledInstanceOutOfRange	.1.3.6.1.4.1.11.2.17.19.2.0.9999																						
Status	Sta	Last State Chang	MIB Expression	MIB	Filt																		
		0.00000091483428	If%util	.21	21																		
		0.0	If%util	.9	9																		
	<p>When generating incidents for Custom Polled Instances, note the following:</p> <ul style="list-style-type: none">• The Source Object is the Custom Polled Instance and the Source Node is the Node associated with the specified Custom Node Collection.• If the Status of the Custom Polled Instance incident changes from Critical to Major, Minor, or Warning, NNMi cancels the Critical incident and replaces it with the incident that has a Status of Major, Minor, or Warning• If the Status of the Custom Polled Instance Incident changes from Major, Minor, or Warning to Critical, the current incident is canceled and replaced by the incident that has a Critical Status.• When the Status of the Custom Polled Instance changes to Normal, the Custom Polled Incident is Closed.• If a Custom Poller Policy's Active State becomes Inactive, NNMi deletes any Custom Polled Instances associated with the Custom Poller Policy and Closes any associated Custom Polled Instance incidents.																						
Incident Source	Applies only if Generate Incident is <input checked="" type="checkbox"/> Enabled .																						

Basics for this Custom Poller Collection, continued

Attribute	Description
Object	<p>Specifies the Source Object for the incident.</p> <ul style="list-style-type: none"> • Select Custom Node Collection to identify the Custom Node Collection as the Source Object for which the incident is generated. <div data-bbox="462 485 1370 814"> <p>Tip: NNMi generates one of the following incidents:</p> <ul style="list-style-type: none"> ▪ CustomPollCritical ▪ CustomPollMajor ▪ CustomPollMinor ▪ CustomPollWarning </div> <ul style="list-style-type: none"> • Select Custom Polled Instance to identify the Custom Polled Instance as the Source Object from which the incident is generated. <div data-bbox="462 947 1370 1020"> <p>Tip: NNMi generates a CustomPolledInstanceOutOfRange incident.</p> </div>
MIB Filter Variable	<p>The MIB Filter Variable is the MIB variable value you want to use as a filter to determine which instances of the MIB expression to Custom Poll. If you specify a MIB Filter Variable, you must also specify a MIB Filter (value). For example, because a node can have multiple interfaces, MIB expressions containing interface information have multiple instances and require you to use a MIB Filter Variable and MIB Filter (value) to specify which interfaces you want NNMi to poll. You might use a MIB Filter Variable of <code>ifIndex</code> and a MIB Filter (value) of 1. In this example, NNMi creates a Polled Instance for each interface with an (interface index) <code>ifIndex</code> value of 1 in the Node Group or Interface Group specified by the associated Custom Poller Policy. See "Create a Policy" for more information about Custom Poller Policies.</p> <p>Valid types for MIB Filter Variables include the following:</p> <ul style="list-style-type: none"> • Integer • Unsigned Integer • Gauge • Octet String • IpAddress (IPv4 only) • INTEGER • UNSIGNED INTEGER

Basics for this Custom Poller Collection, continued


Attribute	Description
	<ul style="list-style-type: none">• GAUGE• OCTET STRING• IpAddress (IPv4 only) <div>Note: The MIB Filter Variable must be a MIB variable that has multiple instances (Table Entry MIB) and that can be applied to all of the MIB variables used in the Custom Poller Collection.</div> <p>Click the  icon to open the MIB Tree and select the MIB OID you want to use as this filter variable.</p> <p>When using MIB Filter Variables, note the following:</p> <ul style="list-style-type: none">• If you do not see a MIB that you recently loaded, close the Custom Poller Collection form, wait 1 minute for NNMi to cache the new MIB information. Then open the  MIB Tree again.• To remove an unwanted MIB Filter Variable:<ul style="list-style-type: none">a. Delete any MIB Filter Values from all Policies associated with the Custom Poller Collection.b. Edit the Custom Poller Collection to remove the MIB Filter Variable.

See ["Specify the MIB Variable Information for a Custom Poller Collection"](#) below for information about the Variable attributes.





See ["Configure Threshold Information for a Custom Poller Collection"](#) on page 507 for information about configuring Thresholds.

Specify the MIB Variable Information for a Custom Poller Collection

When specifying the MIB variable information, note the following:

- You navigate the  MIB Tree to select a MIB OID to include in a MIB Expression.
- Each MIB Variable can be associated with a single MIB OID or a MIB Expression.
- A Custom Poller Collection can be associated with one or more MIB Variables.
- Each Custom Polled Instance is associated with only one MIB Variable.

Variable Attributes

Attribute	Description
Name	<p>The name you want to use for the MIB variable information. Each Name value must be unique within the same Custom Poller Collection.</p> <p>Type a maximum of 50 characters. Alpha-numeric and special characters (~ ! @ \$ % ^ * () _ +) are permitted. No spaces are permitted</p>
MIB Expression	<p>You create a MIB Expression by selecting a MIB OID value from the list or using the MIB Expression form. If your NNMi Security configuration permits, to access the MIB Expression form, click the  Lookup icon and do one of the following:</p> <ul style="list-style-type: none"> • Select  Quick Find to select an existing MIB expression. • Select  Open to edit the current MIB expression. • Select  New to create a MIB expression. <p>See "MIB Expressions Form (Custom Poller)" on the next page for more information.</p>
Report Data Type	<div> <p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) -- click here for more information.</p> </div> <p>Determines how NNM iSPI Performance for Metrics interprets the metrics to be displayed. Possible values include:</p> <ul style="list-style-type: none"> • Integer - Represents metrics as non-decimal numerical values. • Gauge – Represents single non-cumulative values. Examples of Gauge data types include Response Time, Bit Rate, and Temperature. <p>When Gauge data types are aggregated, NNM iSPI Performance for Metrics calculates the minimum, maximum, and average values.</p> <ul style="list-style-type: none"> • Percent – Represents single non-cumulative values that are formatted with a percent sign (%) and two decimal places. Examples of Percent data types include Utilization and Discard Rate. <p>When Percent data types are aggregated, NNM iSPI Performance for Metrics calculates the minimum, maximum, and average values..</p> <ul style="list-style-type: none"> • Counter – Represents incremental values. Examples of Counter data types include byte counts, packet counts, and flow counts. <p>When Counter data types are aggregated, NNM iSPI Performance for Metrics</p>



Variable Attributes, continued

Attribute	Description
	<p>calculates the sum.</p> <ul style="list-style-type: none">• String - Represents the metrics as a sequence of characters. <div>Tip: The String Data Type is most useful for filtering the report information rather than for reporting results.</div> <ul style="list-style-type: none">• Unset - Default. Indicates you do not plan to export the data to the NNM iSPI Performance for Metrics Network Performance Server (NPS).

To specify Threshold information for the Custom Poller Collection, see ["Configure Threshold Information for a Custom Poller Collection" on page 507](#).

MIB Expressions Form (Custom Poller)

You can access the MIB Expression form in the following ways:


- From the  **Configuration** workspace > **MIBs** folder > **MIB Expressions** view.
- From the  **Configuration** workspace > **Monitoring** folder > **Custom Poller Configuration** form
- From the **MIB Specification** form. (Used when configuring SNMP Graph actions.)







When you want to create a MIB Expression to be used in Graphs, use the **MIB Expressions** view. See ["MIB Expression Form \(Line Graph\)" on page 1500](#) for more information.

When you want to create a MIB Expression to be used in a Custom Poll, use the **Custom Poller Configuration** form.

Note: You can re-use any MIB Expression that you create for NNMi graphs or for Custom Poller. Use ["MIB Expressions View" on page 1500](#) to see a list of the available MIB Expressions. Use the ["Loaded MIBs View" on page 1499](#) to see a list of the MIBs loaded on the NNMi management server.

To create a MIB Expression using the Custom Poller Configuration form:

1. Navigate to the **Custom Poller Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.

- d. Select the **Custom Poller Collections** tab.
 - e. Do one of the following:
 - To create a Collection, click the  **New** icon.
 - To edit a Collection, double-click the row representing the configuration you want to edit.
 2. In the MIB Expression attribute, click the  **Lookup** icon and do one of the following:
 - Select  **Quick Find** to select and edit an existing MIB expression.
 - Select  **Open** to edit the current MIB expression.
 - Select  **New** to create a MIB expression.
 3. Provide the required basic settings (see the [MIB Expression Basic Attributes](#) table).
 4. Click  **Save and Close** to return to the **Custom Poller Configuration** form.
- You must save the MIB Expression before you use **Actions** → **Graph MIB Expression**.
5. To test your MIB Expression, select **Actions** → **Graph MIB Expression**. See ["Test a MIB Expression \(Custom Poller\)" on page 500](#) for more information.






Tip: You can right-click any object in a table or map view to access the **Actions** menu.

The NNMi administrator determines the label that is used to identify the data instances that are displayed in Line Graphs using the Instance Display Configuration (see the [Instance Display Configuration](#) table). If the Instance Display Configuration is not set, NNMi identifies each instance that appears in a Line Graph using the Node's short DNS Name followed by the MIB Instance value in the format: `<node_name> -<MIB_instance_value>`. This value also appears as the Display Attribute in the Custom Polled Instance View.

MIB Expression Basic Attributes

Attribute	Description
Unique Key	Used as a unique identifier when exporting and importing MIB Expression definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following example: <code>com.<your_company_name>.nnm.mibexp.<mib_expression_name></code> The maximum length is 80 characters.

MIB Expression Basic Attributes, continued

Attribute	Description
	<p>Note: Unlike the Unique Key attributes associated with other objects, you can change the MIB Expression configuration's Unique Key value at any time.</p>
Name	<p>The name you want to use for the MIB information being polled. This name can be the same name as a MIB OID used in the MIB Expression, or you can enter a name of your choice.</p> <p>Type a maximum of 50 characters. Alpha-numeric and special characters (~ ! @ \$ % ^ * () _ +) are permitted. No spaces are permitted.</p>
Author	<p>Indicates who created or last modified the MIB Expression.</p> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value.
Expression	<p>Click the  button to access the MIB Expression editor. See "Use the MIB Expression Editor (Custom Poller)" on page 501 for information about using the MIB Expression editor.</p> <p>Valid types for the MIB variables that can be included in a MIB expression for Custom Poller include the following:</p> <ul style="list-style-type: none"> Integer Unsigned Integer Gauge Counter Counter64 TimeTicks Octet String <p>Note the following:</p> <ul style="list-style-type: none"> The MIB containing the variable must be loaded on the NNMi management

MIB Expression Basic Attributes, continued

Attribute	Description
	<p>server.</p> <ul style="list-style-type: none"> • If a MIB Expression includes more than one MIB Variable that has multiple instances (Table Entry MIB), select a MIB Filter and MIB Filter Variable that can be consistently applied to each Table Entry MIB in the expression. • Although it is strongly discouraged, to configure Custom Polling for all instances of a repeating MIB, you can use the same MIB variable for both the MIB Expression and the MIB Filter Variable. • If your MIB Expression contains an invalid MIB Variable, NNMi is not able to create an associated Polled Instance. If Polled Instances are not created as expected, check the Custom Node Collection view for Discovery State and Discovery State Information values. • If Polled Instances are created, but errors occur while processing the MIB Expression data from a device's SNMP Agent, information is logged to the analysis.0.0.log file. Examples of possible errors include divide by zero (0) or data unavailable. See "Verify that NNMi Services are Running" on page 91 for more information about log files. • When evaluating MIB expressions that include MIB variables of type Counter, Counter64 or Time_Ticks, NNMi evaluates the MIB Variable using the difference in value between the most recent poll and the poll before it. If you want NNMi to calculate a rate over time in seconds, divide the MIB Expression by sysUptime. For example: $(((ifInOctets+ifOutOctets)*8/ifSpeed)*100)/sysUpTime*0.01$ <div data-bbox="477 1276 1370 1419" style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: The sysUpTime variable is a value of hundredths of a second. When you want the rate in seconds, use <code>sysUpTime*0.01</code> in the MIB expression as shown in the previous example.</p> </div> • If you use a MIB variable of type Counter, Counter64 or Time_Ticks in the MIB Expression, NNMi automatically collects sysUpTime values if sysUpTime is not already in the MIB Expression. NNMi uses the sysUptime value to detect a system reboot. Any time a system reboot is detected, NNMi cannot determine the difference in values between polls for any Counter MIB variable and therefore does not calculate the MIB Expression for that poll.
Display numeric MIB OIDs in the Expression	<p>Enables you to display the MIB object identifier (OID) rather than the MIB variable name in the MIB Expression.</p> <p>Select Display numeric MIB OIDs in the Expression <input checked="" type="checkbox"/> to replace any MIB variable name with the MIB OID value in the MIB Expression.</p>

MIB Expression Basic Attributes, continued

Attribute	Description
	Clear Display numeric MIB OIDs in the Expression <input type="checkbox"/> to display the MIB variable names rather than the MIB OIDs within the MIB Expression.
Description	<p>NNMi provides the Description attribute to help you further identify the current MIB Expression configuration.</p> <p>Use the description field to provide additional information that you would like to store about the current MIB expression configuration.</p> <p>Type a maximum of 2000 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Instance Display Configuration

Attribute	Description
Conversion Algorithm	<p>Used to determine the format in which the value contained in the Display Variable appears in the NNMi console.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: NNMi applies the Display Filter to each Display Variable to determine the value to display.</p> </div> <p>Possible Conversion Algorithms are:</p> <ul style="list-style-type: none"> • Numeric - Use this option to display the instance number returned by the SNMP query. This format is useful when no meaningful name is available in the MIB. For example, you might use this format to display CPU information. • MIB Variable - Use this option to display the value that is stored in the MIB variable you specify. To obtain each MIB variable value, NNMi appends the instance number to the MIB variable specified. The result from the SNMP query is converted to a text string and displayed. • Alphabetic - Use this option to display information for legacy Cisco Arrow Point load balancers. When using this algorithm, each instance number returned by the SNMP query is treated as a set of ASCII characters instead of numbers. For example, the instance 101.120.97.109.112.108.101 would be displayed as 'example'. • Interface Name - Use this option to display the interface name (ifName, if any). If the SNMP agent responds to an ifName request with null, the ifIndex value is queried and used instead. • Interface Name Indirect - Use this option to display the Interface Name value obtained from an indirect reference in the MIB table. For example, if the MIB variable you specify resides in an RMON MIB table, use this algorithm. If the SNMP agent responds to an ifName request with null, the ifIndex value is queried and used instead.

Instance Display Configuration, continued

Attribute	Description
Display Variable	<p>Select the MIB variable you want to display.</p> <p>Note: When you define multiple MIB Variables for a Custom Poller Collection, you must specify the same Display Attribute for each MIB Variable in the Custom Poller Collection.</p> <p>NNMi uses the Conversion Algorithm you specify to determine how to obtain the Display Variable's value.</p>
Display Filter	<p>The value that NNMi displays for the Display Variable is determined by the criteria you provide here. This value is indicated as Display Attribute in the NNMi console.</p> <p>Enter a valid regular expression that specifies the pattern you want NNMi to match when determining the values to display.</p> <p>Note: NNMi uses the syntax defined for java regular expressions (java.util.regex Pattern class).</p> <p>NNMi finds the first character sequence that matches the Display Filter expression. If NNMi does not find a match for the Display Filter, it returns the Display Variable name.</p> <p>For example, if you have several interfaces with an ifDescr set to "FastEthernet" followed by a unique set of numbers for each interface (such as FastEthernet0/1, FastEthernet0/2, FastEthernet0/3, and so on), you can use the following Display Filter to display "Ethernet" followed by the unique set of numbers:</p> <pre>(Ethernet.*[0-9]+){1}</pre> <p>In the example, the following matches occur:</p> <ul style="list-style-type: none">• Ethernet matches Ethernet• The .* matches 0/• The [0-9]+ matches any sequence of numbers• The {1} specifies to match the expression exactly one time <p>In this example, possible Display Values include FastEthernet0/1, FastEthernet0/2, and FastEthernet0/3.</p>


Test a MIB Expression (Custom Poller)

The Actions menu enables you to test the results of a MIB Expression using a Line Graph.

You must save the MIB Expression before you use **Actions** → **Graph MIB Expression**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.



To graph the results for a MIB Expression:

1. Navigate to the **MIB Expression** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **MIBs** folder.
 - c. Select the **MIB Expressions** view.

Note: You can also access the MIB Expressions form when creating Line Graphs and when creating Custom Poller Collections. See "[MIB Expression Form \(Line Graph\)](#)" on [page 1500](#) and "[MIB Expressions Form \(Custom Poller\)](#)" on [page 495](#) for more information.

2. Select the row representing the MIB Expression you want to graph.
3. Select **Actions** → **Graph MIB Expression**.

The dialog for selecting a node appears.

4. Click the  **Lookup** icon and select  **Quick Find**.
5. Select the node you want to use to test your MIB Expression results.


NNMi displays a Line Graph using the selected node and calculating the results for the MIB Expression you selected.

Note the following:

- *Line Graphs Only.* When evaluating MIB Expressions that include MIB variables of type Counter or Counter64, NNMi requests both the high capacity and low capacity counter variable for any interface instance. If the high capacity Counter64 is enabled for any given interface instance, NNMi uses the high capacity counter.
- *Custom Poller Only.* When evaluating MIB Expressions that include MIB variables of type Counter, NNMi requests only the low capacity counter information for any interface instance.

Use the MIB Expression Editor (Custom Poller)

Use the MIB Expression Editor to specify MIB Variables and any Constant values or arithmetic operators in your MIB Expression.

- For a description of each MIB Expression Editor option, see the [table below](#).
- Before you start, review the MIB Expression Editor guidelines, [click here](#).
 - As a general guideline, begin by writing out the MIB Expression. Then in the MIB Expression Editor, begin creating your MIB Expression by selecting your arithmetic operators (+, -, *, or /) from the outermost parenthesis to the innermost parenthesis. Each time you specify an arithmetic operator (+, -, *, or /), NNMi creates a set of parenthesis to specify the ordering of the mathematical calculation.
 - When adding arithmetic operators (+, -, *, or /) to a MIB Expression, first click to select the location in the MIB Expression at which you want to add the arithmetic operator.
 - Click to select the arithmetic operator (for example +) in the MIB Expression, before selecting the MIB variable or Constant value that you want to add, subtract, multiply or divide.
 - NNMi inserts arithmetic operators, MIB Expressions, and Constant values from the left to right.
 - To replace an arithmetic operator use the  (Change Operator) button (see [table](#)).
 - To replace a MIB Variable or Constant value, click to select the existing value in the MIB Expression and then select the new MIB variable or enter the new Constant value.

Note: You can replace a MIB Variable with another MIB Variable or with a Constant value. You can replace a Constant value with a MIB Variable or Constant value.

- You can drag any of the following items to a new location in the MIB Expression:
 - MIB variable
 - Constant value
 - An operation, such as **(IfInOctets + IfOutOctets)**
- For information about moving items to a new location within your MIB Expression, [click here](#).
 - To move an arithmetic operation (for example, **(IfInOctets + IfOutOctets)**), click the arithmetic operator before dragging it to a new location.
 - To move a MIB Variable or Constant Value, click the MIB Variable or Constant Value you want to move before dragging it to a new location.
 - If you are moving the selected item to the right, NNMi places the item to the right of the new location.
 - If you are moving the selected item to the left, NNMi places the item to the left of the new location.
 - As you drag a selected item, an underline indicates the current target location.

- If you drag a selected item past the outermost parenthesis, it is deleted. If desired, you can re-enter the value in the new location.



MIB Expression Example

To poll or graph a MIB Expression that calculates the percentage of available bandwidth on a half-duplex interface, create the following MIB Expression:

$$(((\text{ifInOctets} + \text{ifOutOctets}) * 8) / \text{ifSpeed}) * 100)$$

For step-by-step instructions about creating this MIB Expression, [click here](#).

To create the expression above, begin by specifying each arithmetic operator from the outermost parenthesis to the innermost parenthesis.

1. Click  (multiply).
2. Click  (divide).

Now that you have multiple entries in your MIB Expression, click to select the location in the MIB Expression to which you want to add each remaining arithmetic operators.

3. In the MIB Expression, click / (divide).

The divide (/) arithmetic operator and its surrounding parenthesis should appear highlighted. Because NNMi inserts arithmetic operators, MIB variables, and Constant values from left to right, selecting / (divide) places the next arithmetic operator to the left of the divide arithmetic operator.

4. Click  (multiply).

The multiply (*) arithmetic operator and its parenthesis should appear to the left of the divide arithmetic operator you previously selected.

5. In the MIB Expression, click the leftmost * (multiply).

The multiply (*) arithmetic operator and its surrounding parenthesis should appear highlighted.


6. Click  (add).

The add (+) arithmetic operator and its parenthesis should appear to the left of the multiply (*) arithmetic operator you previously selected.


Now that you have specified the arithmetic operators, you are ready to add the MIB variables and Constant values. Begin by selecting the arithmetic operator in the MIB Expression to which you will add MIB variables, Constant values, or both. We will begin with the leftmost arithmetic operation.

Note: As you add your MIB variables or Constant values, make sure you first select the

corresponding arithmetic operator within the MIB Expression.

7. In the MIB Expression attribute, click + (add).
8. Select the IfInOctets MIB Variable:
 - a. Click  to open the MIB Tree (showing the combined structure of all installed MIB files).
 - b. Navigate to **ifInOctets**.
 - c. Select **ifInOctets**.
 - d. Click **OK**.

The ifInOctets MIB variable should appear to the left of the add (+) arithmetic operator.


9. Select the IfOutOctets MIB Variable:
 - a. Click  to open the MIB Tree (showing the combined structure of all installed MIB files).
 - b. Navigate to **ifOutOctets**.
 - c. Select **ifOutOctets**.
 - d. Click **OK**.

The ifOutOctets MIB variable should appear to the right of the add (+) arithmetic operator.

You are ready to specify the Constant value 8 that corresponds with the leftmost multiply (*) arithmetic operator.

10. Click the leftmost * multiply.
11. In the Constant attribute, enter 8 and click Enter.

The value 8 should appear to the right of the multiply (*) arithmetic operator that you previously selected.



12. In the MIB Expression, click divide (/).
13. Select the IfSpeed MIB Variable:
 - a. Click  to open the MIB Tree (showing the combined structure of all installed MIB files).
 - b. Navigate to ifSpeed.
 - c. Double-click ifSpeed.
 - d. Click **OK**.

The ifSpeed MIB Variable name should appear to the right of the divide (/) arithmetic operator you previously selected.








14. Click the rightmost * (multiply)
15. In the Constant attribute, enter 100 and then click Enter.
16. The Constant value 100 should appear to the right of the divide (/) arithmetic operator you previously selected.
17. Click **OK** to save your MIB Expression.

The following table describes each of the MIB Expression Editor options.

MIB Expression Editor Options

Attribute	Description
MIB Expression	<p>Displays the MIB Expression as it is created.</p> <p>You can place the cursor in the MIB Expression field to specify where you want to add or replace an entry.</p>
MIB Variable	<p>You must select a MIB Variable using the MIB Tree. Click the  icon to access the MIB Tree and navigate to the MIB OID of interest.</p> <div><p>Note: If you do not find a MIB file that you recently loaded, wait 1 minute for NNMi to cache the new MIB information, and then open the  MIB Tree again.</p></div> <p>After you select a MIB OID, NNMi displays the MIB Variable's name.</p> <p>If you choose a MIB Variable that has multiple instances, you MUST specify a MIB Filter Variable and MIB Filter. For example, because a node can have multiple interfaces, MIB Variables containing interface information have multiple instances, one for each interface. You are required to provide a MIB Filter value to select the interfaces you want NNMi to poll. If you do not specify a MIB Filter Variable and MIB Filter, NNMi assumes the MIB variable is non-repeating.</p> <p>For example, if you want to always gather additional HOST-RESOURCES-MIB status information about COM (communication) port devices, you would define the following:</p> <ul style="list-style-type: none">• MIB Expression: hrDeviceStatus• MIB Filter Variable: hrDeviceDescr• MIB Filter: COM* <p>See "Create a Policy" on page 516 for more information about the MIB Filter.</p>

MIB Expression Editor Options, continued

Attribute	Description
Constant Value	A numeric value to be used in the calculation for the MIB Expression. For example, you might want to include 100 as a constant when calculating percentages.
Enter	Includes the Constant Value in the MIB Expression.
	Adds the results.
	Subtracts the results.
	Multiplies the results.
	Divides the results.
	<p>Changes the selected operator (+, -, *, and /) to the operator that appears next in sequence (from left to right) in the MIB Expression Editor. (The example below shows the operator sequence in the MIB Expression Editor.)</p> <p>For example, if you place your cursor at an add (+) operator in the MIB Expression, the MIB Expression Editor changes the add (+) operator to the minus (-) operator. If you place your cursor at the divide (/) operator in the MIB Expression as shown in the example below, the MIB Expression Editor changes the operator to the add (+) operator.</p>  <p>When using the  (Change Operator) button, note the following:</p> <ul style="list-style-type: none"> You must select an operator in the MIB Expression before using the Change Operator (<>) button. You can replace a MIB Variable with another MIB Variable or with a Constant. You can replace a Constant value with a MIB Variable or Constant.
Delete	Deletes the entry that is selected. If no entry is selected, NNMI deletes the last entry in the MIB Expression.
OK	Closes the MIB Expression Editor and saves your changes.

MIB Expression Editor Options, continued

Attribute	Description
Clear	Removes any entries in the MIB Expression.
Cancel	Closes the MIB Expression Editor without saving your changes.

Configure Threshold Information for a Custom Poller Collection

Note: The Threshold Configuration feature applies to only **Instance** Custom Poller Collection Types.


Thresholds specify the high and low values from the MIB Expression results that indicate a High Threshold situation or Low Threshold situation. NNMi administrators can configure NNMi to change the associated High State and Low State for the Custom Polled Instance and generate an incident based on the Custom Polled Instance's State.





Tip: Check to see if the threshold you want is already defined. See ["About Threshold Settings Provided by NNMi" on page 405](#).

When configuring Threshold settings, note the following:

- If a polled value is between the high range and the low range, the Polled Instance state is Normal.
- You can configure Comparison Maps, which also contribute to State calculations. If you configure both Thresholds and Comparison Maps, NNMi first checks the Threshold settings to determine State values. If the threshold evaluates to non-Normal, NNMi uses the Threshold settings to determine State values. If the Threshold evaluates to Normal, NNMi checks for a non-Normal State using any Comparison Map configuration. See ["Configure Comparison Maps for a Custom Poller Collection" on page 513](#) for more information about configuring Comparison Maps.
- The MIB Expression must evaluate to a numeric type. (OCTET STRING type is not supported.)
- When evaluating Threshold configurations with MIB Expressions that include one or more MIB Variables of type Counter or Counter64, NNMi evaluates the MIB Variable value using the difference in value between the most recent poll and the poll before it.

To configure thresholds for a MIB Variable:

1. *Prerequisite:* You must specify the MIB Expression you want to poll. See ["Specify the MIB Variable Information for a Custom Poller Collection" on page 493](#) for more information. Navigate to the Custom Poller Collection form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.

- b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.
 - d. Navigate to the **Custom Poller Collections** tab.
 - e. Do one of the following to open the **Custom Poller Collection** form:
 - To create a collection, click the  New icon.
 - To edit a collection, double-click the row representing the configuration you want to edit.
 - f. Navigate to the **MIB Variables** tab.
 - g. Do one of the following to open the **MIB Variable** form:
 - To create a collection, click the  New icon.
 - To edit a collection, double-click the row representing the configuration you want to edit.
 - h. Locate the **Threshold** tab.
2. Make your configuration choices (see [table](#)).
 3. Click  **Save and Close** to close the **Custom Poller Collection** form.
 4. Complete the configuration for this Custom Poller Collection configuration, if you have not already done so:
 5. Click  **Save and Close** to close the **Custom Poller Configuration** form.

High Threshold Attributes for a Custom Polled Instance

Monitored Attribute	Description
Threshold Setting Type	<p>Select one of the following:</p> <ul style="list-style-type: none">• Count to configure count-based thresholds. Count-based threshold settings enable you to determine as soon as a threshold is crossed (for example, the results of polling the MIB Expression are above 90 percent for 4 consecutive polls). See "Examples of Count-Based Threshold Monitoring" on page 378 for more information.• Time to configure time-based thresholds. Time-based threshold settings enable you to determine whether a threshold is crossed within a particular duration of time (for example, the results of polling the MIB Expression are above 90 percent for 20 out of 30 minutes). See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.

High Threshold Attributes for a Custom Polled Instance, continued

Monitored Attribute	Description
High State	<p>The Custom Polled Instance's State when the results of polling the MIB Expression exceed the specified High Value for the specified Count or Duration. Possible values are:</p> <ul style="list-style-type: none"> • Normal • Warning • Minor • Major • Critical
High Value	<p>Designate the value that above which becomes a threshold situation. The appropriate value depends on the MIB Expression definition (see "Specify the MIB Variable Information for a Custom Poller Collection" on page 493).</p> <p>For special situations, the following values can be used:</p> <ul style="list-style-type: none"> • 0.0000000000000001 (or 1E-15 in Scientific Notation) for the smallest value greater than zero. • 99.99999999999999 for the highest value less than one hundred. <p>Note: If you use the maximum possible value, the High threshold is disabled because it cannot be <i>crossed</i>.</p>
High Value Rarm	<p>The High Value Rarm designates the lower boundary of the High Threshold <i>range of values</i>. Designate a numeric value appropriate for the MIB Expression definition.</p> <p>After entering a High threshold situation, when a returned value is below the specified High Value Rarm, the following happens:</p> <ul style="list-style-type: none"> • For Time-Based Thresholds: <ul style="list-style-type: none"> ■ The current polling interval does not contribute toward High Duration. ■ The criteria for High Duration and High Duration Window determine when the High Threshold situation ends. • For Count-Based Thresholds: After entering a High threshold situation, when a returned value is below the specified High Value Rarm, the High Threshold situation ends.

High Threshold Attributes for a Custom Polled Instance, continued

Monitored Attribute	Description
	<p>Note: The High Value Rarm must be less than or equal to the High Value and greater than or equal to the Low Value Rarm (if any).</p>
If you chose Threshold Setting Type = Count configure the following:	
High Trigger Count	Designate the number of consecutive polling intervals the returned value must be greater than the specified High Value to meet the High Threshold criteria. The default value is 1.
If you chose Threshold Setting Type = Time configure the following (setting both of these to zero disables the High Threshold):	
High Duration	<p>Designate the minimum time within which the value must remain in the High range before the threshold state changes to High and (optionally) an incident is generated.</p> <p>The High Duration should be equal to or greater than the associated Polling Policy's Polling Interval setting, because that is how often NNMi provides a data point.</p> <p>Note: The polling interval should be less than or equal to the High Duration. The High Duration should be a multiple of the polling interval. For example, if the polling interval is 5 minutes, use multiples of 5 (10, 15, or 20).</p> <p>Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p>
High Duration Window	<p>Designate the window of time within which the High Duration criteria must be met.</p> <p>Note: Setting both the High Duration and High Duration Window to zero disables the High threshold.</p> <p>To enable this setting, the value must be:</p> <ul style="list-style-type: none"> greater than 0 (zero) the same as or greater than the High Duration value <p>NNMi uses a sliding window. Each time the High Window Duration is reached, NNMi drops the oldest polling interval and adds the most recent. See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.</p>

Low Threshold Attributes for a Custom Polled Instance

Monitored Attribute	Description
Threshold Setting Type	<p>Select one of the following:</p> <ul style="list-style-type: none"> • Count to configure count-based thresholds. Count-based threshold settings enable you to determine as soon as a threshold is crossed (for example, the results of polling the MIB Expression are above 90 percent for 4 consecutive polls). See "Examples of Count-Based Threshold Monitoring" on page 378 for more information. • Time to configure time-based thresholds. Time-based threshold settings enable you to determine whether a threshold is crossed within a particular duration of time (for example, the results of polling the MIB Expression are above 90 percent for 20 out of 30 minutes). See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.
Low State	<p>The Custom Polled Instance's State when the results of polling the MIB Expression are below the specified Low Value for the specified Count or Duration. Possible values are:</p> <ul style="list-style-type: none"> • Normal • Warning • Minor • Major • Critical
Low Value	<p>Specify the value that <i>below which</i> indicates entering the Low range. The appropriate value depends on the MIB Expression definition (see "Specify the MIB Variable Information for a Custom Poller Collection" on page 493).</p> <p>The Low Value must be less than or equal any specified High Value.</p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: If you use the minimum possible value, the threshold is disabled because it cannot be <i>crossed</i>.</p> </div>
Low Value Rearm	<p>The Low Value Rearm designates the upper boundary of the Low Threshold <i>range of values</i>. Designate a numeric value appropriate for the MIB Expression definition.</p> <p>After entering a Low threshold situation, when a returned value is above the specified Low Value Rearm, the following happens:</p> <ul style="list-style-type: none"> • For Time-Based Thresholds:

Low Threshold Attributes for a Custom Polled Instance, continued

Monitored Attribute	Description
	<ul style="list-style-type: none"> ■ The current polling interval does not contribute toward Low Duration. ■ The criteria for Low Duration and Low Duration Window determine when the Low Threshold situation ends. ● For Count-Based Thresholds: After entering a Low threshold situation, when a returned value is above the specified Low Value Rarm, the Low Threshold situation ends. <p>Note: The Low Value Rarm must be greater than or equal to the Low Value and less than or equal to the High Value Rarm (if any).</p>
If you chose Threshold Setting Type = Count configure the following:	
Low Trigger Count	Designate the number of consecutive polling interval the returned value must be less than the specified Low Value to meet the Low Threshold criteria. The default value is 1.
If you chose Threshold Setting Type = Time configure the following (setting both of these to zero disables the Low Threshold):	
Low Duration	<p>Designate the minimum time within which the value must remain in the Low range before the threshold state changes to Low and (optionally) an incident is generated.</p> <p>Note: The polling interval should be less than or equal to the Low Duration. The Low Duration should be a multiple of the polling interval. For example, if the polling interval is 5 minutes, use multiples of 5 (10, 15, or 20).</p>
Low Duration Window	<p>Designate the window of time within which the Low Duration criteria must be met.</p> <p>Note: Setting both the Low Duration and Low Duration Window to zero disables the Low threshold.</p> <p>To enable this setting, the value must be:</p> <ul style="list-style-type: none"> ● greater than 0 (zero) ● the same as or greater than the Low Duration value <p>NNMi uses a sliding window. Each time the High Window Duration is reached, NNMi drops the oldest polling interval and adds the most</p>

Low Threshold Attributes for a Custom Polled Instance, continued

Monitored Attribute	Description
	recent. See "Examples of Time-Based Threshold Monitoring" on page 382 for more information.

Configure Comparison Maps for a Custom Poller Collection


Prerequisite: .You must know the valid values that might be returned when the MIB Expression is polled. The Comparison Map feature applies to only **Instance** Customer Poller Collection Types.





Custom Poller enables you to map the returned value of a MIB Expression to a Custom Polled Instance *State*. These values are used to determine the High State and Low State of the Custom Polled Instance. NNMi administrators can configure NNMi to generate an incident when the Custom Polled Instance's State changes. For example, you might want the hrDeviceStatus value of **5** (or lower) to be mapped to a **Critical** State. This means that NNMi changes the State of the Polled Collection Instance to **Critical** each time the hrDeviceStatus returns a value of **5** when polled.

When configuring Comparison Maps, note the following:

- NNMi applies the Comparison Maps according to the Ordering number defined. The first comparison criteria met defines the State for the Polled Instance.
- You can configure Thresholds, which also contribute to State calculations. If you configure both Thresholds and Comparison Maps, NNMi first checks the Threshold settings to determine State values. If the threshold evaluates to non-Normal, NNMi uses the Threshold settings to determine State values. If the Threshold evaluates to Normal, NNMi checks for a non-Normal State using any Comparison Map configuration. See ["Configure Threshold Information for a Custom Poller Collection" on page 507](#) for more information about configuring thresholds.
- When evaluating Threshold configurations with MIB Expressions that include one or more MIB Variables of type Counter or Counter64, NNMi evaluates the MIB Variable value using the difference in value between the most recent poll and the poll before it.

To configure Comparison Maps for a MIB Expression:

1. *Prerequisite:* You must specify the MIB Expression you want to poll. See ["Specify the MIB Variable Information for a Custom Poller Collection" on page 493](#) for more information.
2. [Navigate to the Custom Poller Collection form.](#)
 - a. From the workspace navigation panel, select the  **Configuration** workspace.






- b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.
 - d. Select the **Custom Poller Collections** tab.
 - e. Do one of the following:
 - To create a collection, click the  New icon.
 - To edit a collection, double-click the row representing the configuration you want to edit.
3. Locate the **Comparison Maps** tab.
4. Do one of the following:
 - To create a Comparison Map, click the  New icon.
 - To edit a Comparison Map, double-click the row representing the configuration you want to edit.
5. Make your configuration choices (see [table](#)).
6. Click  **Save and Close** to close the **Custom Poller Collection** form.
7. Complete the configuration for this Custom Poller Collection configuration, if you have not already done so:
8. Click  **Save and Close** to close the **Custom Poller Configuration** form.

Note: Each time you save a Comparison Maps configuration, NNMi suspends Custom Polling for the Custom Poller Collection. When you finish making your Comparison Mapping changes, set the [Active State](#) to **Active** for each of the policies in the Custom Poller Collection that you want to be in use. See "[Create a Policy](#)" on page 516 for more information.

State Mapping Attributes

Attribute	Description
Ordering	<p>The order in which the State mapping (Comparison Maps) operations should be performed.</p> <div><p>Note: NNMi uses the Ordering value to determine which State mapping to use. The lower the number, the higher the priority. For example, 1 is the highest priority.</p></div>
Comparison	Operator used to evaluate the Comparison Value and subsequently determine its

State Mapping Attributes, continued

Attribute	Description
Operator	<p>State. For example, the < (less than) Comparison Operator indicates the polled value must be less than the Comparison Value specified to change the Custom Poller Polled Instance to the specified State value.</p> <p>Possible Comparison Operator values are:</p> <ul style="list-style-type: none"> • < (Less than) • <= (Less than or equal to) • = (Equal to) • != (Not equal to) • > (Greater than) • >= (Greater than or equal to) • is null (Null or unavailable) • is not null (Contains a value) • default (Sets the State when no matches are found using the other Comparison Operators) <p>Note: Ordering for the default Comparison Operator must be the last.</p>
Comparison Value	<p>The value returned when the MIB Expression is evaluated when polled.</p>
State Mapping	<p>The State to assign to the Custom Poller Polled Instance when the polled value is returned. For example, each time the value 3 (warning) is returned when NNMI polls hrDeviceStatus, you can specify that you want NNMI to change the State of the Polled Instance to Warning.</p> <p>Possible State values for a <i>Polled Instance</i> (Threshold = High State/Low State; or Comparison Map = State Mapping) are:</p> <ul style="list-style-type: none">  Normal  Warning  Minor  Major  Critical

Create a Policy

Prerequisite: Make sure that the Node Group has been created to which you want to apply the Custom Polling Policy. See [Define Node Groups](#) for more information about creating Node Groups.

Tip: You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller configuration. When using [nnmcustompollerconfig.ovpl](#) to create Custom Poller Policies, you must first create the Node Group to which you want to gather the additional information. Use [nnmcustompollerconfig.ovpl](#) to also enable, disable, configure, list, update, and delete Custom Poller configurations.

You can create one or more policies for a Custom Poller Collection. When configuring a Custom Poller Policy, you define which MIB variable or variables NNMi gathers from members of a specific Node Group.

If you configure more than one Policy per Collection, each Policy must be for a different Node Group.


The Management Mode setting for the node is used to determine whether NNMi collects Custom Poller information for the node regardless of the Management Mode for any associated interfaces. See [Management Mode and Custom Poller](#) for example scenarios.



Note: These scenarios assume that the Custom Poller MIB Expression is configured to access MIBs from the Interface table.

Management Mode and Custom Poller




Node Management Mode	Interface Management Mode	Access Node MIBs	Access Interface MIBs
Not Managed or Out of Service	Not Managed or Out of Service	No	No
Not Managed or Out of Service	Managed	No	No
Managed	Not Managed or Out of Service	Yes	Yes

To configure a Custom Poller Policy:

1. Navigate to the Custom Poller Policies form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** view.

- d. Locate the **Policies** tab.
 - e. Do one of the following:
 - To create a policy, click the New  icon.
 - To edit a policy, double-click the row representing the configuration you want to edit.
 2. Make your configuration choices (see [table](#)).
 3. Click  **Save and Close** to return to the **Custom Poller Configuration** form.
- To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help** → **System Information**.

Custom Poller Policy Attributes

Attribute	Description
Name	<p>The Name of the Policy configuration. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No spaces are permitted.</p> <div> <p>Note: The Policy name appears in any incidents generated as a result of the Collection. Specify a name that will help you to indicate the types of nodes that are polled with this policy.</p> </div>
Ordering	<p>The order in which the Policy should be considered for nodes that appear in multiple Node Groups and therefore might have conflicting Policies. For example, Ordering is used in the following scenario:</p> <ul style="list-style-type: none"> • Two Policies associated with the same Custom Poller Collection specify ifOperStatus as the MIB Expression. • One Policy uses the Routers Node Group and the second Policy uses the Switches Node Group. • Each Policy has a different Polling Interval. <p>In the example scenario above, if a device was in both the Routers Node Group and the Switches Node Group, NNMi would poll the device only one time according to the Policy with the lowest Ordering number.</p>
Collection	<p>Click the  Lookup icon and select  Show Analysis or  Open to display more information about the Custom Poller Collection.</p>
Active State	<p>Use the Active State setting to specify which Custom Poller Policies you want to enable or temporarily disable.</p> <p>The Active State for the associated Custom Collect Policy. Possible values are described below:</p>

Custom Poller Policy Attributes, continued

Attribute	Description
	<p>Active - Indicates the Custom Poller Policy is in use.</p> <div data-bbox="427 380 1369 520" style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: At the time the Active State attribute is set to Active, NNMi applies the Custom Poller Policy to the nodes in the specified Node Group to determine which instances should be polled.</p> </div> <p>Inactive - Indicates the Custom Poller Policy is not in use. NNMi removes all Polled Instances associated with the Policy.</p> <p>Suspended - Indicates someone on your team changed this Custom Poller Policy's <i>Active State</i> to Suspended, or the NNMi administrator disabled Custom Poller in the <i>Global Control</i> settings of Configuration workspace, Custom Poller Configuration form. NNMi suspends polling and retains the most recent State value from before the Policy was suspended.</p>
Node Group	The Node Group to which the Custom Poller Policy applies.
MIB Filter	<p>The MIB Filter value to be used as the filter for determining the Polling Instances.</p> <p>When using a MIB Filter, note the following:</p> <ul style="list-style-type: none"> • The MIB Filter value must match the return type of your filter variable. For example, because hrDeviceDescr is of type String, to poll only those MIBs associated with each node that includes the description for a COM (communication) port, COM* would be the MIB Filter for the example MIB Filter Variable hrDeviceDescr. • If your MIB Expression includes a MIB Variable that has multiple instances, you MUST specify a MIB Filter Variable and MIB Filter. For example, because a node can have multiple interfaces, MIB variables containing interface information have repeating instances and require you to use a MIB Filter to specify which interfaces you want NNMi to poll. • If your MIB Expression contains more than one MIB Variable with multiple instances, the MIB Filter must apply to each of these MIB Variables. • Valid types for MIB Filter Variables include the following: <ul style="list-style-type: none"> ■ INTEGER ■ UNSIGNED INTEGER ■ GAUGE ■ OCTET STRING ■ IpAddress (IPv4 only)

Custom Poller Policy Attributes, continued

Attribute	Description
	<p>Note: The MIB Filter Variable must be a MIB variable that has multiple instances (Table Entry MIB) and that can be applied to all of the MIB variables used in the Custom Poller Collection.</p> <p>Click here for information about valid values for the MIB Filter Expression.</p> <p>Valid values for MIB Filter include the following:</p> <ul style="list-style-type: none"> For numeric values only, you can specify a range using a dash (-). For example 1-6. For string values only, you can use the wildcard character (*) at either the beginning or end of a string value. For example: *vlan, vlan*, and *vlan*. <p>To match all instances, specify *.</p> <ul style="list-style-type: none"> For either numeric or sting values, you can use the Not operator (!) at the beginning of the MIB Filter expression. For example: !1-3, !*vlan, and !vlan. <p>When using MIB Filters, note the following:</p> <ul style="list-style-type: none"> NNMi uses exact matches for string comparisons. String comparisons are case insensitive. NNMi ignores leading and trailing white spaces. You can specify multiple MIB Filter expressions by separating each MIB Filter using a comma (,). When you enter multiple MIB Filter expressions, NNMi combines them using the OR operator. When you enter multiple MIB Filter expressions, they are all evaluated. Evaluation does not stop after the first positive match, for example: <ul style="list-style-type: none"> A*,D*,E* includes any text string beginning with A, D, or E !A*,!D*,!E* excludes any text string beginning with A, D, or E If the value of the MIB Filter Variable matches an expression using the Not operator (!) the result for that value is always “does not match”. To include the dash (-), asterisk (*), or exclamation (!), backslash (\), or comma (,) in your search, use a leading backslash (\) before the special character.
Polling Interval	The interval in which to perform the Custom Poll.

Create a Report Group (NNM iSPI Performance for Metrics)




Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).


Report Groups enable you to define which Custom Poller Collections are reported to NNM iSPI Performance for Metrics. Each Report Group you configure represents a tab in the NNM iSPI Performance for Metrics Report Menu.

Tip: You can also use [nnmcustompollerconfig.ovpl](#) to create a Custom Poller configuration. When using [nnmcustompollerconfig.ovpl](#) to create Custom Poller Policies, you must first create the Node Group to which you want to gather the additional information. Use [nnmcustompollerconfig.ovpl](#) to also enable, disable, configure, list, update, and delete Custom Poller configurations.

Caution: If you delete a Report Group, NNM iSPI Performance for Metrics removes all historical reporting data associated with that Report Group. To retain the historical reporting data, change the Active State of the associated Custom Poller policy to **Suspend**. See ["Create a Policy" on page 516](#) for more information.

To configure a Report Group:

1. Navigate to the **Report Group** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.
 - d. Select the **Report Groups** tab.
 - e. Do one of the following:
 - To create a Report Group, click the New  icon, and continue.
 - To edit a Report Group, double-click the row representing the configuration you want to edit, and continue.
 - To delete a Report Group, select a row, and click the  Delete icon.
2. Make your configuration choices (see [table](#)).

3. Click  **Save and Close** to return to the **Custom Poller Configuration** form.
4. Create a Report Collection to associate one or more Custom Poller Collections with this Report Group. See "[Create a Report Collection \(NNM iSPI Performance for Metrics\)](#)" below for more information.

To view the Report Collection configuration associated with a selected Report Group, from the **Custom Poller Collections** or **Report Groups** tab, select **Actions** → **HP NNM iSPI Performance** → **Show Report Configuration**. NNMi displays the following information:

Note: NNMi displays the **Show Report Configuration** menu option only if you have an HP Network Node Manager iSPI Performance for Metrics Software license key installed on the NNMi management server.

- Report Configuration file name
- Report Group unique identifier (UUID)
- Name of the metrics collected by this report configuration

Custom Poller Report Group Attributes

Attribute	Description
Name	Enter the name that you want to appear in the tab in the NNM iSPI Performance for Metrics Report Menu for this Report Group. The name can be up to 255 alphanumeric characters. Spaces are permitted. The following special characters (<, >, ", ', &, /, \, #) are not permitted.





Create a Report Collection (NNM iSPI Performance for Metrics)

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

Report Collections enable you to specify a Custom Poller Collection to be associated with a Report Group as well as the type of data that is being collected. You can create one or more Report Collections for a Report Group.

Caution: If you delete a Report Collection, NNM iSPI Performance for Metrics removes all historical reporting data for that Report Collection.

To configure a Report Collection:

1. Navigate to the **Report Collection** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Monitoring** folder.
 - c. Select the **Custom Poller Configuration** form.
 - d. Locate the **Report Groups** tab.
 - e. Do one of the following:
 - To create a Report Group, click the New  icon.
 - To edit a Report Group, double-click the row representing the configuration you want to edit.
2. Select the **Report Collections** tab.
3. Do one of the following:
 - To create a Report Collection, click the New  icon.
 - To edit a Report Collection, double-click the row representing the configuration you want to edit.
 - Make your configuration choices (see [table](#)).
4. Click  **Save and Close** to return to the **Custom Poller Configuration** form.

To verify that Custom Poller is working as expected, see the report on the Custom Poller tab in **Help** → **System Information**.

To view the Report Collection configuration associated with the selected Report Collection, from the **Custom Poller Collections** or **Report Groups** tab, select **Actions** → **HP NNM iSPI Performance** → **Show Report Configuration**. NNMi displays the following information:





Note: NNMi displays the **Show Report Configuration** menu option only if you have an HP Network Node Manager iSPI Performance for Metrics Software license key installed on the NNMi management server.

- Report Configuration file name
- Report Group unique identifier (UUID)
- Name of the metrics collected by this report configuration

Note: If the Report Collection displays data as a different type than expected, check the

MIB OID Types table in the **Configuration** workspace. The NNMi administrator can override the MIB OID Type values generated by Custom Poller. See ["Override MIB OID Types" on page 1512](#) for more information.

Custom PollerReport Collection Attributes

Attribute	Description
Custom Poller Collection	<p>Specifies a Custom Poller Collection that should be associated with the Report Group you are configuring.</p> <p>Click the  Lookup icon, and do one of the following:</p> <ul style="list-style-type: none"> To specify a Custom Poller Collection, select  Quick Find . In the Quick Find dialog, select the Custom PollerCollection of interest. To create a Custom Poller Collection, click the New  icon. To edit a Custom Poller Collection, select a row, click the  Open icon. <p>When specifying a Custom PollerCollection, note the following:</p> <ul style="list-style-type: none"> A Custom Poller Collection can be associated with only one Report Group. If you associate more than one Custom Poller Collection with the same Report Group, make sure the combination of Collections will generate a meaningful report. Use the following general guidelines: <ul style="list-style-type: none"> Select Collections with MIB Variables that are indexed in the same MIB table. For example, you might group a collection that includes power supply information, such as UPS line voltage (upsInputVoltage and upsOutputVoltage), UPS line current (upsInputCurrent and upsOutputCurrent) and UPS line power (upsInputPower and upsOutputPower). Select Collections with MIB Variables that are stored in different MIBs, but that would be useful to visualize together at an aggregate level. For example, you might choose to group power supply line load (upsOutputPercentLoad) and power supply battery temperature (upsBatteryTemperature). Select Collections representing the same index value or similar data across Custom Poller Collections. For example, you might want to examine environment sensor information (such as temperature, humidity, dew point, airflow, and audible sounds such as alarms), in the same report even though this information comes from different MIBs. As soon as the Report Collection is saved, NNMi updates the information in the NNM iSPI Performance for Metrics Report Menu.

Chapter 10: Configuring the NNMi User Interface


NNMi enables an NNMi administrator to configure the following global user interface features:

- The console timeout interval
- The initial view to display in the NNMi console
- Whether NNMi displays unlicensed features that require a special license, such as NNMi Advanced

For information about the additional user interface configurations available, including configuring Node Group map settings, setting the default values for maps and Line Graphs, and configuring menus and menu items:

Note: If you are using multiple tenants, you might want to remove the Nodes Group view from the NNMi console. See the "NNMi Console" chapter of the *HP Network Node Manager i Software Deployment Reference* for more information.

To configure user interface features, do the following:

1. Navigate to the **User Interface Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **User Interface Configuration**.
2. Make your Global Control configuration choices (see the [Global Control Attributes](#) table).
3. Make your additional configuration choices. Click here for a list of choices .
4. Click  **Save and Close** to apply your changes.
5. To apply your Console Timeout or Initial View configuration changes, sign out of the NNMi console. After restarting the console, your changes should take effect.

Global Control Attributes for User Interface Configuration

Attribute	Description
Console Timeout	NNMi's default session inactivity timeout value is 18 hours. Use this attribute to change the timeout interval in days, hours, and minutes. <div>Note: The minimum timeout value is 1 minute.</div>

Global Control Attributes for User Interface Configuration, continued

Attribute	Description
	<p>After this period, if no mouse movement occurs, the consoles locks and the user is prompted to sign in again.</p> <div data-bbox="483 430 1369 611"> <p>Tip: If your network operation center (NOC) has a large screen where a map of the most important nodes is continuously displayed, use a launched view. See "Launch a Troubleshooting Workspace View" on page 1550. The map automatically updates every 30 seconds. (If you are using Mozilla Firefox, also see Configure Mozilla Firefox Timeout Interval.)</p> </div>
Initial View	<p>Use this attribute to specify the initial view to be automatically displayed in the NNMi console by default.</p> <p>When selecting a view from the drop-down menu list, note the following:</p> <ul style="list-style-type: none"> • Use the value None (blank) to specify that you do not want a default view automatically displayed by default. • If the Node Group you select has been removed, NNMi uses None (blank view). • To select a Node Group map you have created: <ul style="list-style-type: none"> ■ <i>Prerequisite.</i> Use the Node Group Map Settings configuration workspace to create a Node Group map and enter a Quick Access Map Ordering number that lists the Node Group map as the first or last map in the Quick Access Maps folder. See "Configure Basic Settings for a Node Group Map" on page 552 for more information. ■ For the Initial View attribute: <ul style="list-style-type: none"> ○ If you placed the Node Group map as the first entry in the Quick Access Maps folder, select First Node Group in Quick Access Maps folder. ○ If you placed the Node Group map as the last entry in the Quick Access Maps folder, select Last Node Group in Quick Access Maps folder.
Default Author	<p>The Default Author attribute specifies the Author attribute NNMi should use by default when you create a new instance of an object in NNMi. For example you might create a new incident configuration.</p> <p>The Author attribute identifies who provided that instance of an object. The Author attribute value is also useful for filtering objects in certain views and when using the NNMi Export/Import feature.</p> <p>Either keep the Default Author value of Customer or enter an Author attribute value representing you or your organization.</p> <p>The Default Author value you specify then appears in the Author selection list in any appropriate form and appears by default as the Author value when you create</p>

Global Control Attributes for User Interface Configuration, continued

Attribute	Description
	<p>a new instance of an object.</p> <p>See Author form for important information.</p>
Enable URL Redirect	<p>Before enabling URL Redirect, verify that the NNMi management server's official Fully Qualified Domain Name (FQDN) is set correctly and the DNS name is resolvable from any remote systems that need to access the NNMi management server. If the official FQDN does not meet these requirements, users will view errors when trying to access the NNMi console. To view the NNMi management server's official FQDN, do one of the following:</p> <ul style="list-style-type: none"> • Select Help → System Information and click the Server tab. • Use the nnmhealth.ovpl command line tool. • Use the nnmofficialfqdn.ovpl command line tool. <p>Tip: To change the official FQDN, use the nnmsetofficialfqdn.ovpl command line tool.</p> <p>When <input checked="" type="checkbox"/> URL Redirect is enabled, a user can sign into the NNMi console using any hostname (<i>not case-sensitive</i>) or IP address that is valid for the NNMi management server.</p> <p>(<i>NNMi Advanced's Global Network Management feature or HP Network Node Manager i Software Smart Plug-ins (iSPIs)</i>) For environments configured with Single Sign-On (SSO) among multiple servers (which normally requires users to provide the official Fully Qualified Domain Name (FQDN) that was configured during NNMi installation), this attribute enables NNMi to redirect URLs that contain the IP address or any hostname associated with the NNMi management server to the official FQDN. For more information, see the "Using Single Sign-On with NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> (available at: http://h20230.www2.hp.com/selfsolve/manuals).</p> <p>Note: All NNMi management servers participating in Global Network Management or Single Sign-On (SSO) must have synchronized time stamps.</p>
Show Unlicensed Features	<p>By default, NNMi displays menus, views, and workspaces that require an additional license. If you do not have the required license, NNMi labels these features as Unlicensed or Evaluation. Evaluation indicates the License Type is Instant-On or Temporary.</p> <p>To determine which Unlicensed or Evaluation features could be displayed in your NNMi console, click here for more information.</p>

Global Control Attributes for User Interface Configuration, continued

Attribute	Description
	<ul style="list-style-type: none">• Access Help → Documentation Library → Release Notes and click the Licensing link.• Access Help → System Information and click the Extension tab.• Access Help → System Information and click the Product tab and click the View Licensing Information button. <p>See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 for more information about possible HP Smart Plug-ins.</p> <p>To hide Unlicensed or Evaluation features from the NNMi console, clear the Show Unlicensed Features <input type="checkbox"/> check box. (Recommended if you do not plan to install a permanent license for these features.)</p> <p>To display Unlicensed or Evaluation features in the NNMi console, select the Show Unlicensed Features <input checked="" type="checkbox"/> check box.</p>
Enable Table Row Shading	<p>If enabled <input checked="" type="checkbox"/>, NNMi color-codes each row of an incident view according to the incident status. See About Status Color for more information about status color.</p> <p>If disabled <input type="checkbox"/>, incident views are not color-coded.</p>

Registration Attributes for User Interface Configuration

Attribute	Description
Last Modified	Indicates the last date and time that any of the user interface attributes were modified.

NNMi also enables you to configure features specific to Node Group Maps. See ["Define Node Group Map Settings"](#) on page 550 for more information.



Define Default Map Settings

Default Map Settings define settings for all of your Node Group Maps.

Note: You can override Default Map Setting using the **Node Group Map Settings** Configuration workspace. See ["Configure Basic Settings for a Node Group Map"](#) on page 552 for more information.

To configure Default Map Settings, do the following:



1. Navigate to the **User Interface 'Configuration'** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace:

- b. Click to expand **User Interface**.
 - c. Select **User Interface Configuration**.
2. Navigate to the **Default Map Settings** tab.
3. Make your configuration choices (see the [Default Map Settings Attributes](#) table).
4. Click  **Save and Close** to return to the **User Interface Configuration** form.
5. Click  **Save and Close** to save and apply your changes.

Default Map Settings Attributes

Attribute	Description
Map Refresh Interval	Specifies the refresh interval for Status Refresh.
Maximum Number of Displayed Nodes	<p>Use this attribute to change the maximum number of nodes to be displayed on a map.</p> <p>Note the following:</p> <ul style="list-style-type: none">• If you change the default value to display a large number of nodes at one time, you might need to re-adjust this number if maps are taking longer than expected to display.• In Layer 2 and Layer 3 Neighbor views, NNMi adds nodes one hop at a time. If NNMi finds a large number of nodes in a single hop, the number of nodes might exceed the maximum number specified.• The Initial Discovery Progress map provided by NNMi displays a maximum number of 100 nodes. The Maximum Number of Displayed Nodes that you specify does not change the maximum number of nodes for this map.• The Network Overview map provided by NNMi displays a maximum of 250 nodes by default. The Maximum Number of Displayed Nodes that you specify does not change the maximum number of nodes for this map. However, the NNMi administrator can change the maximum number of nodes displayed using a configuration file. See the "NNMi Console" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> for more information. <p>Note: This number applies to the total number of nodes within the Node Group, including the nodes in any Child Node Groups displayed on the map.</p>

Default Map Settings Attributes , continued

Attribute	Description
Maximum Number of Displayed End Points	<p>Use this attribute to change the maximum number of end points to be displayed on a map.</p> <p>Note: If you change the default value to display a large number of end points at one time, you might need to re-adjust this number if maps are taking longer than expected to display.</p> <p>For troubleshooting issues, see also the nnmtopoquery.ovpl Reference Page. Use this command-line tool to list all connected neighbor interfaces for a specified node.</p>
Multiconnection Threshold	<p>Use this attribute to change the number of connections that must exist between two objects before NNMi displays the connections as one thick line on a map (known as a multiconnection).</p> <p>When this number of connections is reached, NNMi displays the connections as one thick line on all maps except Path View maps.</p> <p>Note: To display the Interface objects and each connection, double-click the line representing the multiconnection.</p>
Indicate Key Incidents	<p>In the Node Group map, NNMi can enlarge the map symbol of any node associated with a Key Incident¹.</p> <p>Users can click the Indicate Key Incidents button in the map view toolbar to toggle this feature on and off (see Using the View Toolbars: Node Group Map Toolbar Icons):</p> <p> (on) = When the this Node Group map opens, NNMi enlarges any objects on a Node Group map that are Source Objects for a Key Incident². (For example, when viewing the Node Group map, NNMi enlarges any node on a Node Group map that has an open root cause incident associated with it.)</p> <p> (off) = When the this Node Group map opens, NNMi does not indicate the objects on a Node Group map that are Source Objects for a Key Incident³.</p> <p>NNMi administrators can override this default setting for a particular Node</p>

¹Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

²Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

³Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

Default Map Settings Attributes , continued



Attribute	Description
	Group map, when you "Configure Basic Settings for a Node Group Map" on page 552 . See Node Group Maps and Key Incident Views for more information.

Configure Default Settings for Line Graph

NNMi enables you to configure default settings for Line Graphs displayed through the Actions menu.

Note: NNMi provides a set of Line Graphs for node and interface objects that are accessible from the Actions menu. As an NNMi administrator you can configure additional Line Graphs using the **Menu Items** option of the **User Interface** workspace. See ["Configure SNMP Line Graph Actions" on page 1477](#) for more information.

To configure default settings for Line Graphs:

1. Navigate to the **Default Line Graph Settings** tab of the **User Interface Configuration** form.
 - a. Navigate to the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **User Interface Configuration**.
 - d. Navigate to the **Default Line Graph Settings** tab.
2. Provide the default settings for all Line Graphs (see the [Default Line Graph Settings](#) table).
3. Click  **Save and Close** to the **User Interface Configuration** form.
4. Click  **Save and Close** to save and apply your changes.

Default Line Graph Settings

Attribute	Description
Default Number of Lines	<p>The Default Number of Lines determines the initial number of lines that are displayed on each Line Graph.</p> <div><p>Note: If more lines than this initial number are available, the user can choose to display additional lines while viewing the graph.</p></div> <p>You can override this number for an individual graph. See "Configure SNMP Line Graph Actions" on page 1477 for more information.</p>
Default	The maximum time period in hours in which to retain the Line Graph data point sets.

Default Line Graph Settings, continued


Attribute	Description
Default Number of Lines	<p>The Default Number of Lines determines the initial number of lines that are displayed on each Line Graph.</p> <p>Note: If more lines than this initial number are available, the user can choose to display additional lines while viewing the graph.</p> <p>You can override this number for an individual graph. See "Configure SNMP Line Graph Actions" on page 1477 for more information.</p>
Maximum Time Range (Hours)	<p>When the Maximum Time Range number is reached, NNMi discards the oldest data point sets so that it can display the most recent data for the time range you specify. For example, if you enter 24 hours, when 24 hours has passed, NNMi removes data starting with the initial data point set so that it can display data for the most recent 24-hour interval.</p> <p>Enter a decimal number indicating the maximum number of hours in which to retain the data.</p> <p>If you do not specify a Maximum Time Range or if you specify 0 (zero), NNMi determines the best setting for the Maximum Time Range based on the Polling Interval specified.</p> <p>If you do not specify a Default Maximum Time Range or set the Default Maximum Time Range to 0 (zero), and you do not specify a Default Polling Interval, NNMi determines the best settings for each so the data fits into the Line Graph displayed.</p> <p>You can override this number for an individual graph. See "Configure SNMP Line Graph Actions" on page 1477 for more information.</p>
Default Update Interval (Seconds)	<p>The Default Update Interval determines how often the NNMi management server polls for the most recent set of data points to be displayed in a Line Graph.</p> <p>Note: This Default Polling Interval does not affect the polling intervals set for the NNMi State Poller.</p> <p>Enter the number of seconds in which NNMi should poll for graph data.</p> <p>If you do not specify an Polling Interval, NNMi determines the best setting for the Polling Interval based on the Maximum Time Range specified.</p> <p>If you do not specify an Polling Interval and you do not specify a Maximum Time Range or if you set the Maximum Time Range to 0 (zero), NNMi determines the best setting for each so the data fits into the Line Graph displayed.</p> <p>When viewing a Line Graph, the user can temporarily change the Polling Interval in a Line Graph. After a graph is re-opened, the Polling Interval returns to this default value.</p> <p>At each Polling Interval, the NNMi management server performs an ad-hoc</p>

Default Line Graph Settings, continued

Attribute	Description
Default Number of Lines	<p>The Default Number of Lines determines the initial number of lines that are displayed on each Line Graph.</p> <p>Note: If more lines than this initial number are available, the user can choose to display additional lines while viewing the graph.</p> <p>You can override this number for an individual graph. See "Configure SNMP Line Graph Actions" on page 1477 for more information.</p>
	SNMP query to obtain the most current data.

Customize Device Profile Icons

NNMi enables you to customize the icons associated with a Device Profile or specific Nodes. These icons appear in table views, menu items, and as foreground images on an NNMi topology map.

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
 - The icon's graphic file does not exist.
-
- ["Add Device Profile Icons" below](#)
 - ["View the Device Profile Icons Available" on page 535](#)
 - ["Change the Image for a Specified Icon" on page 536](#)
 - ["Configure Device Family Icons" on page 539](#)
 - ["Configure Device Vendor Icons" on page 540](#)
 - ["Configure Device Category Icons" on page 542](#)
 - ["Configure the Device Profile Icon for Specified Nodes" on page 538](#)


Add Device Profile Icons

NNMi enables the NNMi administrator to customize the icons associated with a Device Profile or specific Nodes. These icons appear in table views, menu items, and as foreground images on an NNMi topology map.



You can specify icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon to use in the following order of precedence:

- [Specified Node Icons](#)
- [Device Family Icons](#)
- [Device Vendor Icons](#)
- [Device Category Icons](#)





Tip: You can use a command line tool to list, create, update, and delete the icons that you load into the NNMi database. See [nnmicons.ovpl](#).

If you delete an icon from the NNMi database, the icon *Name* remains associated with any [Device Profile](#)'s Device Family, Device Category, or Device Vendor attribute to which that icon was previously assigned. NNMi displays the missing_image  icon for the affected items until the NNMi administrator updates the specification to an existing icon.

To add icons to the NNMi database:

1. Navigate to the **Icons** option under the **User Interface** folder.
 - a. Navigate to the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Icons**.
2. Provide settings for the icons listed. (see the [Device Profile Icons](#) table).
3. Click  **Save and Close** to the **Icon** form.
4. Click  **Save and Close** to save and apply your changes.
5. If you change your mind, see "[Change the Image for a Specified Icon](#)" on page 536.

Device Profile Icons

Attribute	Description
Name	<p>Enter a unique name that identifies the icon.</p> <p>Type a maximum of 64 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. Spaces are not permitted.</p> <p>Note: To enable you to filter the Icons table view by vendor, include the vendor name and the Device Profile attribute for which the icon will be used.</p> <p>For example, for a Device Family icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-family <p>For example, for a Device Vendor icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-vendor <p>For example, for a Device Category icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-category <p>Tip: See the Name drop-down menu for example names of icons provided by HP.</p>
Description	<p>Provide additional information that you want to store about the icon.</p> <p>Type a maximum of 2048 characters. Alpha-numeric, spaces, colons (:), and special characters (~ ! @ # \$ % ^ & * () _ +) are permitted.</p>
Author	<p>See Author form for important information.</p> <p>Caution: It is recommended that you create new icon objects rather than modify icons provided by HP. If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future. Also see: "Export/Import Behavior and Dependencies" on page 1610</p> <p>Click the  Lookup icon and select  Show Analysis to display details about the currently selected Author, select  Quick Find to access the list of existing Author values, or click  New to create one.</p>
Image-(16 pixels)	<p>File name of the 16 pixel image. NNMi supports .jpg, .jpeg, .gif, and .png file types.</p> <p>Click Browse to navigate to the image file to be used for this icon.</p> <p>Tip: As you browse for the image file, NNMi displays the image and its size (for example 16x16).</p>


Device Profile Icons, continued

Attribute	Description
Name	<p>Enter a unique name that identifies the icon.</p> <p>Type a maximum of 64 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. Spaces are not permitted.</p> <p>Note: To enable you to filter the Icons table view by vendor, include the vendor name and the Device Profile attribute for which the icon will be used.</p> <p>For example, for a Device Family icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-family <p>For example, for a Device Vendor icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-vendor <p>For example, for a Device Category icon, you might use the following format:</p> <ul style="list-style-type: none"> <unique_information>-<vendor_name>-category <p>Tip: See the Name drop-down menu for example names of icons provided by HP.</p>
	<p>Note: Ensure that the image background is transparent.</p> <p>After you select the image file, click Open.</p>
Image-(32 pixels)	<p>File name of the 32 pixel image. NNMi supports .jpg, .jpeg, .gif, and .png file types.</p> <p>Click Browse to navigate to the image file to be used for this icon.</p> <p>Tip: As you browse for the image file, NNMi displays the image and its size (for example 32x32).</p> <p>Note: Ensure that the image background is transparent.</p> <p>After you select the image file, click Open.</p>

View the Device Profile Icons Available

NNMi enables you to customize the icons associated with a Device Profile or specific nodes. These icons appear in views, menu items, and as foreground images on an NNMi topology map.

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see ["Add Device Profile Icons" on page 532](#).

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.

To view the device profile icons available for use:

Navigate to the **Icons** option under the **User Interface** folder

1. Navigate to the **Configuration** workspace.
2. Click to expand **User Interface**.
3. Select **Icons**.

For each icon, NNMi displays the image (in 16 pixels), the name of the image, and the author.

Note: Images must be provided in 16 pixels. You can also specify the same image in 32 pixels. To determine whether a 32 pixel image has been added to the NNMi database, examine the Analysis Pane information for the selected icon.

To modify or delete an icon using the command line, see [nnmicons.ovpl](#).

To modify or delete an icon using the NNMi console, see ["Customize Device Profile Icons" on page 532](#).


Change the Image for a Specified Icon

NNMi enables you to customize the icons associated with a Device Profile or specific Nodes. These icons appear in views, menu items, and as foreground images on an NNMi topology map.

You can specify icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon to use in the following order of precedence:



- [Specified Node Icons](#)
- [Device Family Icons](#)
- [Device Vendor Icons](#)
- [Device Category Icons](#)

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see ["Add Device Profile Icons" on page 532](#)



Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.



To change the image for a specified icon:

1. Navigate to the **Icons** option under the **User Interface** folder.
 - a. Navigate to the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Icons**.
2. Select the icon image that you want to change.
3. Provide settings for the selected icon. (see the [Device Profile Icon Images](#) table).
4. Click  **Save and Close** to the **Icon** form.
5. Click  **Save and Close** to save and apply your changes.

Device Profile Icon Images

Attribute	Description
Name	The unique name that identifies the icon.
Description	Provide additional information that you want to store about the icon. Type a maximum of 2048 characters. Alpha-numeric, spaces, colons (:), and special characters (~ ! @ # \$ % ^ & * () _ +) are permitted.
Author	The name of the Author who created the icon object. See Author form for important information. <div>Caution: It is recommended that you create new icon objects rather than modify icons provided by HP. If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future. Also see: "Export/Import Behavior and Dependencies" on page 1610</div> Click the  Lookup icon and select  Show Analysis to display details about

Device Profile Icon Images, continued

Attribute	Description
Name	The unique name that identifies the icon.
	the currently selected Author, select  Quick Find to access the list of existing Author values, or click  New to create one.
Image-(16 pixels)	<p>File name of the 16 pixel image. NNMi supports .jpg, .jpeg, .gif. and .png file types.</p> <p>Click Browse to navigate to the image file to be used for this icon.</p> <div>Tip: As you browse for the image file, NNMi displays the image and its size (for example 16x16).</div> <div>Note: Ensure that the image background is transparent.</div> <p>After you select the image file, click Open.</p>
Image-(32 pixels)	<p><i>Optional.</i> File name of the 32 pixel image. NNMi supports .jpg, .jpeg, .gif. and .png file types.</p> <p>Click Browse to navigate to the image file to be used for this icon.</p> <div>Tip: As you browse for the image file, NNMi displays the image and its size (for example 32x32).</div> <div>Note: Ensure that the image background is transparent.</div> <p>After you select the image file, click Open.</p>


Configure the Device Profile Icon for Specified Nodes

NNMi enables you to customize the icons associated with a device profile. These icons appear in views, menu items, and as foreground images on an NNMi topology map.

You can specify image icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon image to user per node in the following order of precedence:

- Specified Node Icons
- [Device Family Icons](#)
- [Device Vendor Icons](#)
- [Device Category Icons](#)

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see "[Add Device Profile Icons](#)" on page 532

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.

To configure the Device Profile Icon for specified Nodes:

1. Navigate to the Nodes view (for example **Inventory > Nodes**).
2. Use Ctrl-Click to select each node.

Tip: You can also select Nodes from a map view.

3. Select **Actions > Custom Attributes > Add**.
4. In the **Name** drop-down menu, select **NNM_ICON**.
5. In the **Value** attribute, enter the Name of the icon you want to use for the selected nodes prepended with **NNM**.

Note: The Value *must* begin with NNM: For example: NNM:1400-procurve-vendor.

Tip: To view the device profile icons available, see "[View the Device Profile Icons Available](#)" on page 535.

Configure Device Family Icons

NNMi enables you to customize the icons associated with a Device Profile or specific Nodes. These icons appear in views, menu items, and as foreground images on an NNMi topology map.








You can specify image icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon image to user per node in the following order of precedence:


- [Specified Node Icons](#)
- Device Family Icons

- [Device Vendor Icons](#)
- [Device Category Icons](#)

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see "[Add Device Profile Icons](#)" on page 532

To configure a Device Family icon:

1. Navigate to the **Device Profile** option in the  **Configuration** workspace.
 - a. Navigate to the  **Configuration** workspace..
 - b. Select **Device Profiles**.
2. Navigate to the **Device Family** attribute.
3. Click the  **Lookup** icon, and select  **Open**.
4. Navigate to the **Icon** attribute.
5. Do one of the following:
 - a. Select the Name of the icon you want to use.
 - b. Click the  **Lookup** icon, and select  **New**. See "[Add Device Profile Icons](#)" on page 532 for more information.
6. Click  **Save and Close** to save and apply your changes.
7. Verify that the icon specified displays in the appropriate places.

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.

Configure Device Vendor Icons








NNMi enables you to customize the icons associated with a Device Profile or specific Nodes. These icons appear in views, menu items, and as foreground images on an NNMi topology map.


You can specify image icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon image to user per node in the following order of precedence:

- [Specified Node Icons](#)
- [Device Family Icons](#)
- Device Vendor Icons
- [Device Category Icons](#)

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see "[Add Device Profile Icons](#)" on page 532

To configure a Device Vendor icon:

1. Navigate to the **Device Profile** option in the  **Configuration** workspace.
 - a. Navigate to the  **Configuration** workspace..
 - b. Select **Device Profiles**.
2. Navigate to the **Device Vendor** attribute.
3. Click the  ▾ Lookup icon, and select  **Open**.
4. Navigate to the **Icon** attribute.
5. Do one of the following:
 - a. Select the Name of the icon you want to use.
 - b. Click the  ▾ **Lookup** icon, and select  **New**. See "[Add Device Profile Icons](#)" on page 532 for more information.
6. Select the Name of the icon you want to use.
7. Click  **Save and Close** to save and apply your changes.
8. Verify that the icon specified displays in the appropriate places.

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.

Configure Device Category Icons








NNMi enables you to customize the icons associated with a Device Profile or specific Nodes. These icons appear in views, menu items, and as foreground images on an NNMi topology map.


You can specify icons for a specific Node, Device Family, Device Vendor, or Device Category. NNMi determines the icon to use in the following order of precedence:

- ["Configure the Device Profile Icon for Specified Nodes" on page 538](#)
- ["Configure Device Family Icons" on page 539](#)
- ["Configure Device Vendor Icons" on page 540](#)

Tip: To use the command line to load the icon images to the NNMi database so they are available for use, see [nnmicons.ovpl](#). To use the NNMi console to load images, see ["Add Device Profile Icons" on page 532](#)

To configure a Device Category icon:

1. Navigate to the **Device Profile** option in the  **Configuration** workspace.
 - a. Navigate to the  **Configuration** workspace..
 - b. Select **Device Profiles**.
2. Navigate to the **Device Category** attribute.
3. Click the  ▾ Lookup icon, and select  **Open**.
4. Navigate to the **Icon** attribute.
5. Do one of the following:
 - a. Select the Name of the icon you want to use.
 - b. Click the  ▾ **Lookup** icon, and select  **New**. See ["Add Device Profile Icons" on page 532](#) for more information.
6. Select the Name of the icon you want to use.
7. Click  **Save and Close** to save and apply your changes.
8. Verify that the icon specified displays in the appropriate places.

Note: NNMi provides a *missing* icon () to indicate a Device Profile icon is not available. The reasons that NNMi displays the *missing* icon include the following:

- The icon's graphic file has been deleted.
- The icon's graphic file does not exist.

Customize Object Attributes

NNMi enables you to customize the Custom Attributes associated with a node, chassis, interface or card.

For details about configuring Custom Attributes, see the following:

Add a Custom Attribute to One Object	543
Add Custom Attributes to Multiple Objects	546
Remove Custom Attributes from Objects	548

Note: Be cautious of associating one Custom Attribute name with multiple object types.

Add a Custom Attribute to One Object

If you determine that you want to keep track of additional information about a Node, Chassis, Interface, or Card, you can add Custom Attributes to these objects. For example, you might determine that you want to track the owner of your nodes on the network. You might also want to track the serial number for each node. The Custom Attribute value appears in the object's table view and on the object form's Custom Attributes tab. For more information:

Tip: (*NNMi Advanced - Global Network Management feature*) If you are a Regional Manager's NNMi administrator and are adding a Custom Attribute, remember to notify your Global Manager's NNMi administrator about that new Custom Attribute name. See ["Global Manager: Configure Custom Attribute Replication"](#) on page 115.


To add Custom Attributes to a map Node or Chassis object:

1. Navigate to a map view:
2. Select one or more map icons.
3. Right-click and select Custom Attributes > Add.
 - Enter or select a Name.
 - Type a Value.
4. Click **OK** to return to the main Node form or Chassis Form.

To add Custom Attributes to a Node object:

1. **Navigate to the Node form: Custom Attributes tab:**
 - a. From the workspace navigation panel, select a workspace that contains a Node view. For example, the **Inventory** workspace.
 - b. Double-click the row representing the node with settings you want to edit.



Tip: You can also select Nodes from a map view.

- c. Select the **Custom Attributes** tab.
2. Click the  New icon to create a Custom Attribute.
3. Enter a Name and Value.

For more information, see:

[Custom Node Attributes Form](#)




[Custom Node Attributes Samples](#)

4. Click  **Save and Close** to return to the main Node Form.
5. Click  **Save and Close** to save your changes.

To add Custom Attributes to a Chassis object:

1. **Navigate to the Chassis form: Custom Attributes tab:**
 - a. From the workspace navigation panel, select a workspace that contains a Chassis view. For example, the **Inventory** workspace.
 - b. Double-click the row representing the Chassis with settings you want to edit.


Tip: You can also select Chassis from a map view.

- c. Select the **Custom Attributes** tab.
2. Click the  New icon to create a Custom Attribute.
3. Enter a Name and Value. See [Physical Component Custom Attribute Form \(Chassis\)](#) for more information.
4. Click  **Save and Close** to return to the main Chassis Form.
5. Click  **Save and Close** to save your changes.

To add Custom Attributes to an Interface object:

1. **Navigate to the Interface form: Custom Attributes tab:**
 - a. From the workspace navigation panel, select a workspace that contains an Interfaces view. For example, the **Inventory** workspace.
 - b. Double-click the row representing the interface with settings you want to edit.



Tip: You can also select Interfaces from a map view.

- c. Select the **Custom Attributes** tab.
2. Click the  New icon to create a Custom Attribute.
 3. Enter a Name and Value. See [Custom Interface Attributes Form](#) for more information.




For more information, see:

[Custom Interface Attributes Form](#)

[Custom Interface Attributes Samples](#)

4. Click  **Save and Close** to return to the main Interface Form.
5. Click  **Save and Close** to save your changes.

To add Custom Attributes to a Card object:

1. **Navigate to the Card form: Custom Attributes tab:**
 - a. From the workspace navigation panel, select a workspace that contains a Card view. For example, the **Inventory** workspace.
 - b. Double-click the row representing the Card with settings you want to edit.
 - c. Select the **Custom Attributes** tab.
2. Click the  New icon to create a Custom Attribute.
3. Enter a Name and Value. See [Physical Component Custom Attribute Form \(Card\)](#) for more information.
4. Click  **Save and Close** to return to the main Card Form.
5. Click  **Save and Close** to save your changes.

Related Topics

["Add Custom Attributes to Multiple Objects" on the next page](#)

[nnmloadattributes.ovpl](#) Reference Page

["Global Manager: Configure Custom Attribute Replication" on page 115](#)

Add Custom Attributes to Multiple Objects

Custom attributes can be added to multiple Nodes, Chassis, Interfaces, or Cards in several ways:

- ["Add Custom Attributes Using the Actions Menu" below](#). (Use the **Actions** → **Custom Attributes** option.)
- ["Add Custom Attributes Using the Command Line" on the next page](#) (Use the `nnmloadattributes.ovpl` command line.)
- Add Custom Attributes to a map object:
 - a. Navigate to a map view:
 - b. Select one or more map Node or Chassis icons.
 - c. Right-click and select **Custom Attributes > Add**.
 - Enter or select a Name.
 - Enter a Value.
 - d. Click **OK** to return to the main Card Form.

The Custom Attribute value appears in the object's table view and on the object form's Custom Attributes tab. For more information:

Add Custom Attributes Using the Actions Menu

For examples, see:

- [Custom Node Attributes Samples](#)
- [Custom Interface Attributes Samples](#)

Tip: (*NNMi Advanced - Global Network Management feature*) If you are a Regional Manager's NNMi administrator and are adding a Custom Attribute, remember to notify your Global Manager's NNMi administrator about that new Custom Attribute name. See ["Global Manager: Configure Custom Attribute Replication" on page 115](#).

To add a Custom Attribute to multiple nodes, chassis, interfaces, or cards using the Actions menu (if your role permits you to do this):

1. Navigate to a Nodes, Chassis, Interfaces, or Cards inventory view.
 - a. From the workspace navigation panel, select the **Inventory** workspace.
 - b. Select the view of interest (for example, **Nodes** view).

Tip: You can also select Nodes or Interfaces from a map view. See ["Customize Object Attributes" on page 543](#).

2. Use Ctrl-Click to select each object to which you want to add to a Custom Attribute.
3. Select **Actions** → **Custom Attributes** → **Add**.
4. In the **Custom Attributes** dialog, box, enter the following:

Name	<p>Do one of the following:</p> <ul style="list-style-type: none"> ■ Select a previously established entry from the drop-down list. For example: <ul style="list-style-type: none"> ○ NNM_ICON (to customize the Device Profile icon, see "Configure the Device Profile Icon for Specified Nodes" on page 538) ○ NPS Annotation (to enhance NNM iSPI Performance for Metrics reports, see "Annotate NNM iSPI Performance for Metrics Reports" on page 1517) ■ Type any value directly into the drop-down list to created a new one: <p>Maximum of 50 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -)</p>
Value	<p>Type the value you want to assign to the Custom Attribute:</p> <p>Maximum of 2000 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -)</p>

5. Click **OK**.

The Custom Attribute value appears in the object's table view and on the object form's Custom Attributes tab. For more information:

Add Custom Attributes Using the Command Line

The [nnmloadattributes.ovpl](#) command line tool enables you to load Custom Attributes by configuring a comma-separated values (CVS) file. This feature is useful if you have information about a large number of nodes, chassis, interfaces, or cards defined in an external data storage, and you would like to load that information into the NNMi database as Custom Attributes. The Custom Attribute value appears in the object's table view and on the object form's Custom Attributes tab. For more information:

For example:

- Node location information in a Microsoft Excel spreadsheet where you track the location of each node: You can save this information as a .csv file. Use the `nnmloadattributes.ovpl` command to define **BldgLocation** as a Custom Attribute and load the location values for each node into the NNMi database. You can then create a Node Group with an Additional Filters specification using **BldgLocation** as the `customAttrName` and the location of interest, such as **Building Five Upper** as the `customAttrValue`.

For additional examples, see [Custom Node Attributes Samples](#).

- Interface information in a comma-separated value file where you track the name of customers assigned to each interface: Use the `nnmloadattributes.ovpl` command to define **Customer** as a Custom Attribute and load the name values for each customer into the NNMi database. You can then create an Interface Group with an Additional Filters specification using **Customer** as the `customAttrName` and a customer name, such as **Hewlett Packard** as the `customAttrValue`.

For additional examples, see [Custom Interface Attributes Samples](#).

Tip: (NNMi Advanced - Global Network Management feature) If you are a Regional Manager's NNMi administrator and are adding a Custom Attribute, remember to notify your Global Manager's NNMi administrator about that new Custom Attribute name. See "[Global Manager: Configure Custom Attribute Replication](#)" on page 115.

To load Custom Attributes for Nodes, Chassis, Interfaces, or Cards using a comma-separated file:

See the [nnmloadattributes.ovpl](#) Reference Page for more information about the `nnmloadattributes.ovpl` command, including requirements for the CSV file. You must provide a CSV file with a specific syntax and order. Each column in the CSV file has a pre-defined meaning. See the Reference Page for an explanation of each of the following:

```
nnmdeleteattributes.ovpl [-?] -t <type> (-f <path & filename of csv file>) | (-s  
<"csv formatted line">) [-u <username> -p <password>] [-jndiHost <hostName>  
Default: localhost] [-jndiPort <port> Default: 1099]
```

Remove Custom Attributes from Objects

NNMi administrators can add Custom Attributes to Node, Chassis, Interface, or Card objects. The Custom Attribute value appears in the object's table view and on the object form's Custom Attributes tab. For more information:

Caution: When you remove a Custom Attribute name using these procedures, NNMi removes matching name/value pairs from all objects in your NNMi database. This means both Custom Attributes that were manually added or Replicated are removed.

To remove a Custom Attribute from an object using the Actions menu (if your role permits you to do this):

1. Navigate to a Nodes, Chassis, Interfaces, or Cards inventory view.
 - a. From the workspace navigation panel, select the **Inventory** workspace.
 - b. Select the view of interest (for example, **Nodes** view).

Tip: You can also select Nodes or Interfaces from a map view.

2. Use Ctrl-Click to select each object from which you want to remove all Custom Attributes.
3. Select **Actions** → **Custom Attributes** → **Remove**.
4. Click **OK**.

To remove a Custom Attribute from an object using the command line (if your role permits you to do this):

The `nnmdeleteattributes.ovpl` command line tool enables you to delete Custom Attributes by configuring a comma-separated values (CVS) file.

See the `nnmloadattributes.ovpl` Reference Page for more information about the `nnmloadattributes.ovpl` command, including requirements for the CSV file. You must provide a CSV file with a specific syntax and order. Each column in the CSV file has a pre-defined meaning. See the Reference Page for an explanation of each of the following:

```
nnmdeleteattributes.ovpl [-?] -t <type> (-f <path & filename of csv file>) | (-s  
<"csv formatted line">) [-u <username> -p <password>] [-jndiHost <hostName>  
Default: localhost] [-jndiPort <port> Default: 1099]
```

Configure Maps

NNMi enables you to configure the following maps:

- Node Group Map views
- Path View Maps

Note: The Node Group Overview map provided by NNMi is not configurable.

When configuring Node Group maps, you can do the following:

- Include only the nodes that are important to you.
- Specify which Node Group maps appear in the **Quick Access Maps** folder.
- Specify refresh information.

- View node groups in the context of a relevant background image, such as a map illustrating node locations.
- View node groups in a customized arrangement.

When configuring Node Group map views, you can also specify the role level required to save maps in a customized arrangement. See ["Define Node Group Map Settings" below](#) for more information.

When configuring Path View maps you specify undiscovered regions of your network by creating a `PathConnections.xml` file that defines the path between the undiscovered nodes. See ["Configure a Path View Map" on page 563](#) for more information.

You can also specify the maximum number of nodes to display on a map. See ["Define Default Map Settings" on page 527](#) for more information.

Related Topics

["Node Group Map Settings Form" on the next page](#)

[Node Group Map View](#)

[Position Nodes in a Node Group Map](#)

Define Node Group Map Settings

Node Group Map settings specify the node group and background image to be used in a Node Group map. Map settings include the following:

- Node group name
- **Quick Access Maps** folder ordering
- Minimum role for saving edited locations for each node in the map
- Refresh interval
- The maximum number of map nodes
- Node connectivity information
- Node Group connectivity information
- Background image information

Tip: To configure Node Group Map settings from the command line, see the [nnmnodegroupmapsettings.ovpl](#) Reference Page.

Node Group Map views are used for a variety of purposes in NNMi:

- Viewing groups of only the nodes that are important to you.
- Viewing Node Groups in the context of a relevant background image.
- Viewing Node Groups in a customized arrangement.

To define Node Group Map Settings, use the ["Node Group Map Settings Form"](#) below.

To view a Node Group Map, do one of the following:

- Use the **Actions** menu from the NNMi main toolbar from either a Node Group or Node Group Map Settings form. See [Node Group Map](#) for more information.



Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

- Use the **Topology Maps** workspace. See [About Workspaces](#) for more information.

To view more information about the Node Group from a Node Group map, use the **File** → **Open Node Group for Map** option to open the Node Group form for the selected Node Group.

Node Group Map Settings Form

Use the Node Group Map Settings form to configure maps based on currently defined Node Groups. Items you configure include the background image and type of connectivity (for example, Layer 2) to be displayed on the map.



Note: NNMi displays the list of Node Group Map Settings that have default configuration changes. If NNMi does not display a list of Node Group Map Settings, this means that NNMi is using the default settings for each Node Group Map. To change the default settings for a Node Group Map, either reposition the nodes on the map of interest and select  **Save Map** from the Node Group Map toolbar or use the Node Group Map Settings form to create a Node Group Map Settings configuration as described below. See [Position Nodes on a Node Group Map](#) for more information about using  **Save Map**.

To configure Node Group Map Settings, do the following:

1. Navigate to the **Node Group Map Settings** view.

Note: You can also access the Node Group Map Settings form from any Node Group Map by using the **File** → **Open Node Group Map Settings** option.

- a. From the workspace navigation panel, select the **Configuration** workspace.
- b. Click to expand **User Interface**.

- c. Select **Node Group Map Settings**.
- d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, double-click the row representing the Node Group Map Settings definition you want to edit.
2. Make your configuration choices (see [table](#)).
3. Click  **Save and Close** to save and apply your changes.

Tasks for Configuring Node Group Map Settings

Task	How
"Configure Basic Settings for a Node Group Map" below	<p>Use the Basics Settings pane to configure Node Group, Topology Maps, and Refresh Interval information.</p> <div> <p>Note: To apply your Topology Maps Ordering configuration changes, such as reordering a Node Group map or adding a Node Group map to the workspace, refresh the web browser using the F5 key on your keyboard (by default, NNMi turns off the web browser's menu bar).</p> </div>
"Configure the Connectivity to be Displayed for a Node Group Map" on page 556	Use the Connectivity tab to configure the level of node connectivity to be displayed on the Node Group Map. Use this tab to also specify the Node Group connectivity to be displayed and maximum connections to be included on the Node Group map.
"Configure Background Image Information for a Node Group Map" on page 559	Use the Background Image tab to configure information about the Background Image to use on the Node Group map.




Configure Basic Settings for a Node Group Map

The Basic Settings configuration determines general information about the Node Group map.

To establish Basic Settings for a Node Group Map:


1. Navigate to the **Node Group Map Settings** view.

Note: You can also access the Node Group Map Settings form from any Node Group Map by using the **File** → **Open Node Group Map Settings** option.

- a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Node Group Map Settings**.
 - d. Do one of the following:
 - To create a Node Group Map Settings definition, click the  New icon.
 - To edit a Node Group Map Settings definition, double-click the row that represents the Node Group Map Settings definition you want to edit.
 - To delete a Node Group Map Settings definition, select a row and click the  Delete button.
2. Establish the appropriate settings to identify Node Group and Refresh Settings information (see [table](#)).
 3. Click  **Save and Close** to save and apply your changes.

Note: Use the web browser's refresh feature (F5 key on your keyboard) to immediately display changes made to Node Group Map Settings (for example, to update the Topology Maps workspace).

Basic Attributes

Attribute	Description
Node Group	<p>Specifies which parent node group to display in the Node Group Map view. The contents of the parent node group include any nodes and Child Node Groups associated with it.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: NNMi displays any Child Node Groups of the selected parent Node Group as a hexagon on the map.</p> </div> <p>The Expand Child in Parent Node Group Map attribute determines how a Child Node Group appears on the Node Group Map. Expand Child in Parent Node Group Map is disabled by default.</p> <ul style="list-style-type: none"> If the Child Node Group has the Expand Child in Parent Node Group Map attribute <i>disabled</i>, the Child Node Group appears as a hexagon on the map as shown below: <div style="text-align: center; margin: 10px 0;">  </div> If any Child Node Group has the Expand Child in Parent Node Group

Basic Attributes, continued



Attribute	Description
	<p>Map attribute <i>enabled</i>, NNMi instead recursively displays each of the nodes in that Child Node Group on the map.</p> <p>See Node Group Form: Child Node Groups Tab for more information about configuring Child Node Groups.</p>
Quick Access Maps Ordering	<p>Use this attribute to specify the order in which you want the Node Group map to appear in the Quick Access Maps folder.</p> <div data-bbox="492 600 1370 741"> <p>Note: If you do not want this Node Group map to appear in the Quick Access Maps folder in the Topology Maps workspace, leave the value blank.</p> </div> <p>See Views Available in NNMi for more information about the maps provided in the Topology Maps workspace.</p> <div data-bbox="492 852 1370 1066"> <p>Note: To apply your Quick Access Maps Ordering configuration changes, sign out of the NNMi console. After restarting the console, your changes should take effect. Possible configuration changes include reordering a Node Group map view or adding a new Node Group map view to the Quick Access Maps folder.</p> </div>
Minimum NNMi Role to Save Map	<p>Controls the minimum NNMi User Group required to save the map, for example after repositioning nodes in a Node Group Map. This value also controls the minimum User Group for configuring Node Group Map Settings.</p> <div data-bbox="492 1213 1370 1323"> <p>Note: Only a User Account assigned to the NNMi Administrators User Group can set the Minimum NNMi Role to Save Map value.</p> </div> <p>Possible values include:</p> <ul style="list-style-type: none"> • Administrator • Operator Level 2 • Operator Level 1 (with more limited access privileges than Level 2) <p>The default value is <i>Administrator</i>. See "Determine which NNMi User Group to Assign" on page 619 for more information about NNMi roles.</p> <div data-bbox="492 1688 1370 1850"> <p>Note: A user with any NNMi Role can initially reposition nodes on a Node Group Map view. However, unless your user name is assigned to the required minimum NNMi Role, you cannot save the new node locations on the map. After being saved, these node positions are seen by any user</p> </div>

Basic Attributes, continued

Attribute	Description
	opening this Node Group Map.
Map Refresh Interval	Specify the Refresh Interval you want to use in days, hours, minutes, and seconds. By default, the Refresh Interval is 30 seconds. This interval is used to set the Refresh Status interval for this map if it is used.
Maximum Number of Displayed Nodes	Specifies the maximum number of nodes to be displayed on the Node Group map. Note: This number applies to the total number of nodes within the Node Group, including the nodes in any Child Node Groups displayed on the map.
Maximum Number of Displayed End Points	Specifies the maximum number of end points to be displayed on a map. Note: If maps are taking longer than expected to display, you might need to re-adjust this number.
Multiconnection Threshold	Use this attribute to change the number of connections that must exist between two Node Groups before NNMi displays the connections as one thick line (known as a multiconnection) on a Node Group map. Note the following: <ul style="list-style-type: none"> • The value you enter overrides the Multiconnection Threshold set using the Default Map Settings. • If this setting is blank, NNMi uses the Multiconnection Threshold value configured in Default Map Settings. • When this number of connections is reached, NNMi displays the connections as one thick line. • To display the Interface objects and each connection, double-click the line representing the multiconnection.
Indicate Key Incidents	In the Node Group map, NNMi can enlarge the map symbol of any node associated with a Key Incident ¹ . Users can click the Indicate Key Incidents button in the map view toolbar to toggle this feature on and off (see Using the View Toolbars: Node Group Map Toolbar Icons):

¹Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

Basic Attributes, continued

Attribute	Description
	 (on) = When the this Node Group map opens, NNMi enlarges any objects on a Node Group map that are Source Objects for a Key Incident ¹ . (For example, when viewing the Node Group map, NNMi enlarges any node on a Node Group map that has an open root cause incident associated with it.)  (off) = When the this Node Group map opens, NNMi does not indicate the objects on a Node Group map that are Source Objects for a Key Incident ² .
Include in Visio Export	<p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) – click here for more information.</p> <p>When <input checked="" type="checkbox"/> enabled, NNMi includes this map when exporting all saved Node Group maps using the Tools → Visio Export → Saved Node Group Maps option.</p> <p>When <input type="checkbox"/> disabled, NNMi does not include this map when exporting all saved Node Group maps using the Tools → Visio Export → Saved Node Group Maps option.</p>

Configure the Connectivity to be Displayed for a Node Group Map

The Connectivity Tab of the Node Group Map Settings form enables you to specify the level of connectivity to be displayed on the Node Group map. You also specify the connections that you want to display.




Tip: See also the [nnmtopoquery.ovp1](#) Reference Page. Use this command-line tool to list all connected neighbor interfaces for a specified node.

1. Navigate to the **Connectivity tab** of the **Node Group Map Settings** form.

Note: You can also access the Node Group Map Settings form from any Node Group Map by using the **File** → **Open Node Group Map Settings** option.

¹Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.


²Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

- a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Node Group Map Settings**.
 - d. Do one of the following:
 - To create a Node Group Map Settings definition, click the  New icon.
 - To edit a Node Group Map Settings definition, double-click the row representing the Node Group Map Settings definition you want to edit.
 - To delete a Node Group Map Settings definition, select a row and click the  Delete button
 - e. Navigate to the **Connectivity** tab.
2. Configure the connectivity information for this Node Group Map Settings definition (see [table](#)).
 3. Click  **Save and Close** to save and apply your changes.

Connectivity Attributes

Attribute	Description
Connectivity Type	<p>Connectivity Type determines the type of connectivity to display between nodes in the Node Group Map view.</p> <p>By default, NNMi displays the Layer 2 connectivity between nodes when displaying a Node Group Map view. Possible values include:</p> <ul style="list-style-type: none"> • None - Choose this if you do not want any connectivity displayed on the map. • Layer 2 - Uses Layer 2 connectivity when displaying devices in a Node Group Map view. This connectivity is used by default when positioning node locations on a Node Group Map. • Layer 3 - Uses Layer 3 connectivity when displaying devices on a Node Group Map view. <p>See Position Nodes on a Node Group Map for more information.</p>
Only for Layer 3 or None Connectivity Types (Optional)	
Add L2 Subnet Connections	<p>If you specify Layer 3 or None as the Connectivity Type, this option specifies that you want to include any subnet connections determined by IPv4 Subnet Connections Rules.</p> <p>See "Configure IPv4 Subnet Connection Rules" on page 265 for more information.</p>
Add L2 User	<p>If you specify Layer 3 or None as the Connectivity Type, specifies that you want</p>

Connectivity Attributes, continued

Attribute	Description
Connection Edits	to include any Layer 2 Connections added using the NNMi nrmconnected.ovpl command to add or delete connection data. See " Add or Delete a Layer 2 Connection " on page 314 for more information.
End Points Filter (Optional)	
Interface Group	Use this option, if you want to reduce the connectivity endpoints on the Node Group Map. The Interface Group you select defines the Interface Group to which an interface must belong to be used to connect a Node Group to a Node Group or a Node to a Node Group. NNMi displays Layer 2 endpoints that are interfaces in the group. NNMi displays Layer 3 endpoints that are IP addresses associated with interfaces in the group.
Node Group Connectivity (Optional)	
Nodes to Node Group	Select this check box if you want Node to Node Group connectivity to appear on the Node Group map. Note: By default, this option is not enabled.
Node Groups to Node Groups	Select this check box if you want Node Group to Node Group connectivity to appear on the Node Group map. Note: By default, this option is not enabled.
Node Group Neighbor Connectivity (Optional)	
Show Neighbor Connections	Enabling will add additional selected one hop neighbors that are connected to nodes in the Node Group but are not themselves members of the Node Group. The icons for those one-hop neighbors appear with a gray halo around the icon, for example: 
Node Group Filter	Specify Node Group Neighbor filter to limit which one-hop neighbors display. If the specified Node Group contains Child Node Groups, NNMi ignores members of the Child Node Groups when applying the filter. To review the currently defined Device Filters, navigate to Configuration workspace → Object Groups → Node Groups. Select the appropriate Node Group

Connectivity Attributes, continued




Attribute	Description
	definition and look on the Device Filters tab. Tip: If this attribute value is empty, NNMi uses the direct members of Networking Infrastructure Devices Node Group (not any Child Node Group members).

Configure Background Image Information for a Node Group Map

Use the Background Image tab of the Node Group Map Settings form to configure information about the Background Image to use on the Node Group map.

1. Navigate to the **Background Image** tab of the **Node Group Map Settings** form.

Note: You can also access the Node Group Map Settings form from any Node Group Map by using the **File** → **Open Node Group Map Settings** option.

- a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Node Group Map Settings**.
 - d. Do one of the following:
 - To create a Node Group Map Settings definition, click the  New icon.
 - To edit a Node Group Map Settings definition, double-click the row representing the Node Group Map Settings definition you want to edit.
 - To delete a Node Group Map Settings definition, select a row and click the  Delete button.
2. Establish the appropriate settings to identify the Background Image information (see [table](#)).
 3. Click  **Save and Close** to save and apply your changes.

Background Image Attributes

Attribute	Description
Background Image	Enter the URL for the background image you want to use for this Node Group Map. You can use a background image provided by NNMi or add your own. Note: Click Background Image to view the map.

Background Image Attributes, continued

Attribute	Description
	<p>Use a Background Image Provided by NNMi</p> <p>NNMi provides a set of background images that include maps of many countries. If you want to use one of those images, append the location and file name to the URL at which you access the NNMi console. Use the format: <code>/nnmbg/<file name></code>. For example:</p> <pre>/nnmbg/colorado.gif</pre> <p>To see all of the available images provided by NNMi, browse to:</p> <pre>http://<serverName>:<portNumber>/nnmbg/</pre> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div> <p><code><serverName></code> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the <i>Enable URL Redirect</i> setting in User Interface Configuration, see "Configuring the NNMi User Interface" on page 524)</p> <p><code><portNumber></code> = the NNMi HTTP port number</p> <p>Use a Background Image You Provide</p> <p>You can also provide your own images. See "Background Image Sources in Node Group Maps" on the next page for more information about where to load the background images you want to use.</p> <p>To see a list of all the images added to NNMi, access the following URL:</p> <pre>http://<serverName>:<portNumber>/nnmdocs/images/</pre> <p>To use an image that has been added to NNMi, use the following URL:</p> <pre>/nnmdocs/images/<file name></pre> <p>For example: <code>/nnmdocs/images/myimage.gif</code></p> <p>Note the following:</p> <ul style="list-style-type: none"> • NNMi accepts images that can be loaded by a Web browser. Common file extensions include: .gif, .png and .jpg. • Image names are case sensitive. All background image file names provided by NNMi are lowercase. • Do not use <code>http://<localhost></code> in your URL. This implies the image is on your local machine and is not available from other clients.

Background Image Attributes, continued

Attribute	Description
	<ul style="list-style-type: none">• If using full URLs, all client machines must be able to resolve the DNS hostname of the server on which the images reside.• When you pan and zoom around the map, the background image moves in relation with the other objects on the map. <p>If the image does not display, see "Troubleshoot URLs When Specifying a Background Image" on page 563 for more information.</p>
Background Image Scale	<p>The Background Image Scale attribute applies to the actual background image dimensions when displayed on a Node Group Map.</p> <p>Enter a floating point number greater than zero (0.0) to indicate the ratio at which you want NNMi to scale the background image. For example, the value 1.0 represents a one-to-one ratio, resulting in a background image displayed at actual size. A value of 2.0 represents a two-to-one ratio, resulting in a background image displayed at twice the actual size.</p> <div><p>Note: The default ratio value is 1.0. (This means no scaling is applied.) Use this default value initially. You can adjust it as needed based on the relative size between the image and nodes.</p></div> <p>See "Scale Background Images in Node Group Maps" on the next page for guidelines for scaling the background images you specify.</p>

Background Image Sources in Node Group Maps

When specifying background images to include in Node Group Maps, NNMi enables you to use images provided by NNMi or images that you provide.

The images that NNMi provides include maps of many countries.

To see the available images provided by NNMi:

Browse to: `http://<serverName>:<portNumber>/nnmbg/`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

To use your own background images:

Place your user-supplied images in the following directory (see ["About Environment Variables" on page 86](#) for more information):

Windows:

`%NnmDataDir%/shared/nnm/www/htdocs/images`

Linux:

`$NnmDataDir/shared/nnm/www/htdocs/images`

NNMi accepts images that can be loaded by a Web browser. Common file extensions include: .gif, .png and .jpg.

To see the available images that have been added to NNMi:

Access the following URL: `http://<serverName>:<portNumber>/nnmdocs/images`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

See ["Node Group Map Settings Form" on page 551](#) for more information about how to configure Node Group Maps to use background images.

Scale Background Images in Node Group Maps

Scale a specified background image for a Node Group Map using the Background Image Scale attribute. See ["Define Node Group Map Settings" on page 550](#) for more information.

When you use the maps provided by NNMi, it is recommended that you initially use the default value of 1.0 for the Background Image Scale.

When you use your own images for map backgrounds and you are selecting a scale value, consider the following:

- NNMi renders its nodes 50 by 50 pixels. This means if your image is 500 pixels wide, there is room for 10 nodes across the image.
- To display the image at normal resolution, enter a scale value of 1.0. (This means no scaling occurs.)
- After the image displays on the map, look at the relationship between the node size and the background to determine whether you need to rescale the background image:

- If the nodes look too large compared to the background, enlarge the image using a scale value greater than 1.0.
- If the nodes look too small compared to the background, make the image smaller using a scale value less than 1.0.

Troubleshoot URLs When Specifying a Background Image

This topic contains troubleshooting steps to use if your background image does not display.

If you used a relative URL (beginning with a slash (/) in the Background Image attribute value:

1. Copy and paste the URL to a browser.
2. Insert `http://<serverName>:<portNumber>` in front of the slash (/).

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see "[Configuring the NNMi User Interface](#)" on page 524)

`<portNumber>` = the NNMi HTTP port number

If you used an absolute URL (beginning with http://) in the Background Image attribute value:

Copy and paste the URL to a browser.

Configure a Path View Map

Configuring a Path View map is useful when you have two or more areas of your network which are separated by undiscovered devices, such as service provider nodes. NNMi enables you to configure a Path View map that traverses undiscovered regions of your network. To configure this kind of Path View map, create a `PathConnections.xml` file that defines the following:

- Required. A Start node for each `<CONNECT>` to be included in the Path View map

Note: The Start node specified must be a Router or Switch-Router device that is managed by NNMi.

- *Optional.* A unique identifier for a `<CONNECT>`

- *Optional.* The outbound interface from each Start node per <CONNECT>
- Required. Any number of undiscovered nodes you want to be included in the map between each <CONNECT>
- *Optional.* An End node for a <CONNECT> to be included in the Path View map.

Note: The End node specified must be a Router or Switch-Router device that is managed by NNMi.

- *Optional.* The inbound interface to each End node per <CONNECT> specified.

Each time NNMi determines a node in the Path View, NNMi checks whether the node is specified as a Start node in the PathConnections.xml file. If the node is specified as a Start node in PathConnections.xml, each <CONNECT> configured in PathConnections.xml is inserted in the Path View map.

Note: (NNMi Advanced, plus HP Route Analytics Management System (RAMS) for MPLS WAN) NNMi can use RAMS data to determine router paths. When RAMS data is used to determine the router paths, NNMi ignores the PathConnections.xml file. See [Path View with NNMi Advanced](#) and ["HP RAMS MPLS WAN Configuration \(NNMi Advanced\)" on page 1446](#) for more information.

(NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.

To configure a Path View map:

Using the required format, create a PathConnections.xml file in the following location (see ["About Environment Variables" on page 86](#) for more information):

Windows

```
%NnmDataDir%/shared/nnm/conf/PathConnections.xml
```

Linux

```
$NnmDataDir/shared/nnm/conf/PathConnections.xml
```

The following table describes each of the file elements and its format requirements. (Also see the [sample](#) file)

Note: Each segment of the path that you specify using the <CONNECT> element is directional. If you want to view the path between two nodes in both directions, make sure you include the Start and End nodes for each direction. You should also include the inbound interface for the Start node. If you do not limit the possible routers by including the inbound interface for the Start node, Path View might find additional routers in the path.

Elements for the Path View Configuration File

Element Descriptions
<p><CONNECTIONS></p> <p>Required parent element. The file must include only one <CONNECTIONS> element.</p>
<p><CONNECT></p> <p>Specifies a segment of the path. Each <CONNECT> designates a start and stop location for the <CONNECT>.</p> <p>The file can include more than one <CONNECT> element.</p>
<p><ID></p> <p style="padding-left: 40px;">C1</p> <p></ID></p> <p><i>Optional.</i> Identifies the connection. NNMi uses the ID value you enter when reporting errors for a <CONNECT>.</p> <p>If you do not provide an ID value for the path between a Start and End node, any error message for the <CONNECT> displays Not Applicable rather than the unique identification value.</p>
<p><START></p> <p style="padding-left: 20px;"><IP_OR_DNS>xxx.xx.xxx.x</IP_OR_DNS></p> <p style="padding-left: 20px;"><OUTBOUND_INTERFACE_IFINDEX>x</OUTBOUND_INTERFACE_IFINDEX></p> <p style="padding-left: 20px;"><NEXT_HOPS></p> <p style="padding-left: 40px;"><HOP>xxx.xx.xxx.x</HOP></p> <p style="padding-left: 40px;"><HOP>xxx.xx.xxx.x</HOP></p> <p style="padding-left: 20px;"></NEXT_HOPS></p> <p></START></p> <p>Specifies the node where a segment of the path starts. You provide values for the following elements:</p> <ul style="list-style-type: none"> • <IP_OR_DNS> provides the name or IPv4 address of a node in your network. See "Configure the Node Name Strategy" on page 223 for more information about node names. • <i>Optional.</i> <OUTBOUND_INTERFACE_IFINDEX> designates which of the Start node's interfaces to use for this segment of the path. • <NEXT_HOPS> designates one or more specific IPv4 addresses or nodes that you want to be included in the path.
<p><END></p> <p style="padding-left: 20px;"><IP_OR_DNS>xxx.xx.xxx.x</IP_OR_DNS></p> <p style="padding-left: 20px;"><INBOUND_INTERFACE_IFINDEX>x</INBOUND_INTERFACE_IFINDEX></p> <p></END></p> <p>Specifies the node where the <CONNECT> ends. You provide values for the following elements:</p> <ul style="list-style-type: none"> • <IP_OR_DNS> provides the name or IPv4 address of a node in your network.

Elements for the Path View Configuration File, continued

Element Descriptions
<ul style="list-style-type: none"> <i>Optional.</i> <INBOUND_INTERFACE_IFINDEX> designates which of the End node's interfaces to use for this segment of the path.
<p></CONNECT></p> <p>Required. Designates the end of the XML code that defines one segment of your path view.</p>
<p></CONNECTIONS></p> <p>Required parent element. Designates the end of the XML code that defines your path view.</p>

[Click here](#) to view a sample file:


```
<?xml version="1.0" encoding="UTF-8"?>

<CONNECTIONS>
  <CONNECT>
    <ID>
      C1
    </ID>
    <START>
      <IP_OR_DNS>StartNode.xx.xxx.x</IP_OR_DNS>
      <OUTBOUND_INTERFACE_IFINDEX>3</OUTBOUND_INTERFACE_IFINDEX>
      <NEXT_HOPS>
        <HOP>hop-1.xxx.xx.xxx</HOP>
        <HOP>hop-2.xxx.xx.xxx</HOP>
      </NEXT_HOPS>
    </START>
    <END>
      <IP_OR_DNS>EndNode.xxx.xx.xxx</IP_OR_DNS>
      <INBOUND_INTERFACE_IFINDEX>6</INBOUND_INTERFACE_IFINDEX>
    </END>
  </CONNECT>
</CONNECTIONS>
```

When viewing Path View maps that are configured using the PathConnections.xml file, note the following:

- If the <END> element is not specified, NNMi connects directly to the Destination node to complete the path.
- If the <END> element is specified, then the associated <IP_OR_DNS> specifies a discovered node as the End node of this segment of your Path View.

[Click here](#) to view the sample Path View map generated from the sample file above.





[Click here](#) to view a sample file that includes both directions for the sample Path View map above.

Note: In this example, the path is the same in both directions. In many cases, the path might be different in each direction.

```
<?xml version="1.0" encoding="UTF-8"?>

<CONNECTIONS>
  <CONNECT>
    <ID>
      C1
    </ID>
    <START>
      <IP_OR_DNS>StartNode.xx.xxx.x</IP_OR_DNS>
      <OUTBOUND_INTERFACE_IFINDEX>6</OUTBOUND_INTERFACE_IFINDEX>
      <NEXT_HOPS>
        <HOP>hop-1.xxx.xx.xxx</HOP>
        <HOP>hop-2.xxx.xx.xxx</HOP>
      </NEXT_HOPS>
    </START>
    <END>
      <IP_OR_DNS>EndNode.xxx.xx.xxx</IP_OR_DNS>
      <INBOUND_INTERFACE_IFINDEX>3</INBOUND_INTERFACE_IFINDEX>
    </END>
  </CONNECT>
</CONNECTIONS>
```

[Click here](#) to view the sample Path View map generated from the sample file above after clicking the  **Swap Nodes** button.



Configure Menus


As an NNMi administrator, you configure how menu items are nested in the NNMi console. See ["Create Menu Nesting" on page 1453](#) for more information.

Configure Menu Items

The **Menu Items** tab of the **User Interface Configuration** option enables you to make changes or additions to the items available in the NNMi console menus. For example, you can configure Line Graphs (Graph Action) and additional NNMi actions (Launch Action) menu items that access in-house tools, Web sites, or a variety of other resources. See ["Configure Menu Item Basic Details" on page 1456](#) for more information.

Chapter 11: Configuring Security

NNMi administrators configure security to meet the needs of their user environment.



See ["Determine Your Security Strategy" on page 574](#) for ideas.

Tip: NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See ["Choose a Mode for NNMi Access" on the next page](#).

NNMi enables an NNMi administrator to configure the following access control features:

Basic settings:	"About User Accounts" on page 579 "About User Groups" on page 580 "About User Account Mappings" on page 581
Required only for Operators and Guests: Note: NNMi administrators automatically see all nodes. NNMi users can have access to all nodes if they are a member of User Group: NNMi Global Operators.	"About Security Groups" on page 582 "About Security Group Mappings" on page 583

NNMi administrators can configure security in several ways:

["Using the Security Folder" on page 584](#)

["Using the Security Wizard View" on page 591](#)

[nnmsecurity.ovpl](#) command line tool

The NNMi administrator also needs to understand the following:

["Control Menu Access" on page 649](#)

["Set Up Command Line Access to NNMi" on page 653](#)

["Communicate Console Access Information to Your Team" on page 655](#)

["About Multi-Tenancy and Global Network Management" on page 100](#)

Verify that your NNMi Security configuration is working as expected:

["Troubleshoot NNMi Access" on page 659](#)

Choose a Mode for NNMi Access

Decide how to configure access to NNMi:

- ["NNMi Configuration Settings to Control NNMi Access" on the next page.](#)

NNMi user names, passwords, and User Group membership are defined within the NNMi database.

- ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572.](#)

NNMi administrators have choices about which information NNMi gathers from the directory service:

- a. User Accounts (user names and passwords)
- b. User Accounts (user names and passwords) plus User Groups and User Group Mappings

- ["X.509 Certificates to Control NNMi Access" on page 573.](#)

The X.509 Certificate approach eliminates the need for any passwords.

Tip: NNMi supports Public Key Infrastructure (PKI) user authentication. This includes Smart Cards, such as Common Access Card (CAC) and Personal Identity Verification (PIV).

NNMi administrators have choices about where NNMi gathers User Account Mapping information:

- a. NNMi's database
- b. Lightweight Directory Access Protocol (LDAP)

Caution: You must choose *one* user authentication strategy and configure all NNMi users with the same approach.

User Authentication Strategy

Mode	Which Method for User Authentication?	User Account Definitions in NNMi	User Group Definitions in NNMi	Which Method for Group Membership?
1 - Internal	NNMi Password	yes	yes	NNMi User Account Mappings
2 - Mixed	LDAP Password	yes	yes	NNMi User Account Mappings
	X.509 Certificate	yes	yes	NNMi User Account Mappings
3 - External	LDAP Password	no	yes	LDAP
	X.509 Certificate	no	yes	LDAP

* Assign each NNMi user to one or more User Groups. At a minimum, each NNMi user must belong to one of the following:

- NNMi Administrators
- NNMi Level 1 Operators
- NNMi Level 2 Operators
- Guests

NNMi Configuration Settings to Control NNMi Access

NNMi administrators configure NNMi user names, passwords, and NNMi User Group membership assignments in the NNMi database.

Which Database Stores the Information?

Mode	Using which User Authentication Method?	Are NNMi User Accounts Required?	Where is NNMi User Group Membership Assignment * defined?	Are NNMi User Groups & Mapping Required?
1	NNMi Password	Yes	NNMi	Yes

Caution: NNMi administrators must choose one Mode and configure all NNMi users with the same approach. See also:

- ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on the next page](#)
- ["X.509 Certificates to Control NNMi Access" on page 573](#)

To enable NNMi to store all user information in the NNMi database:

1. ["Configure User Accounts \(User Account Form\)" on page 611.](#)

Tip: NNMi administrators can also add, delete, or modify NNMi user names and passwords with the `nnmsecurity.ovpl` command-line tool.

2. ["Configure User Groups \(User Group Form\)" on page 621.](#)
3. ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624.](#)

NNMi users can belong to more than one User Group.

The NNMi administrator must assign each User Account to a predefined NNMi User Group before that user can access NNMi. See ["User Groups Provided in NNMi" on page 618](#) for more information.

4. ["Configure Security Groups \(Security Group Form\)" on page 632](#)
5. ["Map User Groups to Security Groups \(Security Group Mapping Form\)" on page 638.](#)

Lightweight Directory Access Protocol (LDAP) to Control NNMi Access

NNMi administrators can configure NNMi to rely on your environment's directory service to provide any of the following:

- Mixed: NNMi password
- External: NNMi password plus NNMi User Group membership assignments

Note: If you are using the External LDAP method, you can choose to configure the user display name value to be one or more LDAP properties rather than the name used to sign in to NNMi. If you are an NNMi administrator, see the "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Interactive Installation Guide* for more information.

User Authentication Strategy

Option	Which Method for User Authentication?	User Account Definitions in NNMi	User Group Definitions in NNMi	Which Method for Group Membership?
2 - Mixed	LDAP Password	yes	yes	NNMi User Account Mappings
3 - External	LDAP Password	no	yes	LDAP

Caution: NNMi administrators must choose one Mode and configure all NNMi users with the same approach. See also:

- ["NNMi Configuration Settings to Control NNMi Access" on page 571.](#)
- ["X.509 Certificates to Control NNMi Access" below.](#)

Follow the instructions in the "Integrating NNMi with a Directory Service through LDAP" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
:http://h20230.www2.hp.com/selfsolve/manuals.

X.509 Certificates to Control NNMi Access

The X.509 Certificate service eliminates the need for any NNMi passwords. NNMi administrators have a choice of where to define and store the required NNMi User Group membership assignments:

- Mixed: NNMi defines and stores the User Group assignments.
- External: NNMi uses the Lightweight Directory Access Protocol (LDAP) User Group assignments.

Tip: NNMi supports Public Key Infrastructure (PKI) user authentication. This includes Smart Cards, such as Common Access Card (CAC) and Personal Identity Verification (PIV).

User Authentication Strategy

Option	Which Method for User Authentication?	User Account Definitions in NNMi	User Group Definitions in NNMi	Which Method for Group Membership?
2 - Mixed	X.509 Certificate	yes	yes	NNMi User Account Mappings
3 - External	X.509 Certificate	no	yes	LDAP

Caution: NNMi administrators must choose one Mode and configure all NNMi users with the same approach. See also:

- ["NNMi Configuration Settings to Control NNMi Access" on page 571.](#)
- ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on the previous page.](#)

Follow the instructions in the "Configuring NNMi to Support Public Key Infrastructure User Authentication" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.

Determine Your Security Strategy

Out-of-box, NNMi Security works in the following manner:

- NNMi assigns all nodes to the Default Security Group.
- NNMi operators and guests can see all discovered nodes and all incidents, because of the default Security Group Mappings:



User Group	Security Group	Object Access Privilege
NNMi Guest Users	Default Security Group	Object Guest
NNMi Guest Users	Unresolved Incidents	Object Guest
NNMi Level 1 Operators	Default Security Group	Object Operator Level 1
NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1
NNMi Level 2 Operators	Default Security Group	Object Operator Level 2
NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2

Tip: NNMi administrators always see all nodes and incidents, no Security Group Mappings are required for NNMi administrators.

NNMi administrators can limit access to nodes and incidents by deleting the default (out-of-box) Security Group Mappings. Then no operators or guests can access any nodes until an NNMi administrator explicitly adds new, more restrictive Security Group Mappings. When these out-of-box Security Group Mappings are removed, the predefined [NNMi User Group](#)¹s provide access to the NNMi console only, rather than to the NNMi console and to all nodes. See ["Remove User Groups from Security Group Mappings" on page 640](#) for more information.

Security Group Mappings have three settings:

- [User Group](#) identifies the *NNMi users*.
- [Security Group](#) identifies a *set of nodes* (and indirectly their hosted objects).
- [Object Access Privilege](#) determines the level of access that each User Account in the User Group has to the nodes in the associated Security Group.

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Each node is associated with one and only one Security Group. NNMi operators and guests can view a node only if one of the User Groups to which that NNMi user belongs is associated with that node's Security Group.

When NNMi discovers nodes in your network environment, Tenant and Security Group settings are established in the following manner:

- **Discovery Seeds:** If Nodes are discovered as Discovery seeds, the NNMi administrator specifies a Tenant for each Discovery Seed. See ["Specify Discovery Seeds" on page 287](#). When NNMi administrators define a Tenant, they specify an **Initial Discovery Security Group**. Any newly discovered Node within the defined Tenant is assigned to this Security Group. NNMi administrators can change either the node's Tenant or Security Group assignment or both at any time.

Nodes assigned to the *Default Security Group* are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

Nodes within one Tenant can each be assigned to different Security Groups, and Nodes within one Security Group each be assigned to different Tenants.

- **Auto-Discovery for Default Tenant:** When you configure Auto-Discovery Rules, NNMi assigns any Nodes discovered using those Auto-Discovery Rules to the *Default Tenant* and whichever Security Group is currently configured as the Default Tenant's Initial Discovery Security Group setting (the *Default Security Group* out-of-box). See ["Configure Tenants" on page 213](#).

Global Network Management: Regional Managers forward information about Nodes to the Global Manager. The Global Manager's copy of the Node object has the same Tenant assignment as the Regional Manager's record of that Node.

In a Global Network Management environment, best practice is to have the NNMi administrators for the Global Manager and all Regional Managers agree to a predefined list of Tenant names. Those Tenants would be defined on the Regional Managers, the Tenant definitions exported, and those Tenant definitions imported onto the Global Manager (thus ensuring that the UUID and name value for each Tenant match on both NNMi management servers). The NNMi administrator on the Global Manager update their Tenant definitions to assign Initial Discovery Security Group values that make sense for the Global Manager's team. See ["About Multi-Tenancy and Global Network Management" on page 100](#) for more information.

Note: If a Regional Manager forwards information about a Node to the Global Manager, and that Node is assigned to a Tenant object that does not exist on the Global Manager, NNMi creates a Tenant with the UUID and name from the Regional Manager, but creates a new Security Group with that Tenant name (does not duplicate the Regional Manager's setting for that Tenant's *Initial Discovery Security Group* setting). NNMi maps that new Security Group to the following:

- User Group = NNMi Administrator
- Object Access Privilege = Object Administrator

The Global Manager's NNMi administrator can assign a *different* Initial Discovery Security Group to a Tenant definition at any time. From that point onward, the NNMi Global Manager uses that new Initial Discovery Security Group setting when creating new nodes within that Tenant.

Node revisions: NNMi administrators can change the Node's initial Security Group assignment. See ["Methods for Assigning Nodes to Security Groups" on page 636](#).

Tip: NNMi administrators can use Security Groups in [Node Group definitions](#) that become filters in NNMi views. If a user cannot access any nodes in a particular Node Group, that filter dynamically disappears from the filter selection list in the user's NNMi views. See ["Specify Node Group Additional Filters" on page 330](#) for more information about Node Group filters.

Security influences incidents:

- Network operators and guests can view incidents associated with a node only if that user's User Account is mapped to one of the User Groups that are mapped to the node's Security Group. See ["About Security Groups" on page 582](#) and ["About Security Group Mappings" on page 583](#).
- Any incident that does not have an associated node is assigned to the **Unresolved Incidents** Security Group and NNMi's out-of-box configuration makes these incidents visible to all User Groups. Examples of incidents that are unresolved include unresolved traps, system health, and license violation incidents.
- Operators should only be assigned incidents for nodes they can access.

The following examples present possible Security strategies. Consider printing one or more of the following topics to use as a tutorial about configuring NNMi Security. The [Configure Security Tasks](#) table explains all possible choices.


These strategy examples use the Security views under the Configuration workspace (see ["Using the Security Folder" on page 584](#)):

- ["Configure Security: All Users Access All Nodes" on page 586](#)
- ["Configure Security: Limit Node Access" on page 588](#)

These strategy examples use the Security Wizard under the Configuration workspace (see ["Using the Security Wizard View" on page 591](#)):

- ["Configure Security Example \(Allow a Subset of Users to Access a Subset of Nodes\)" on page 602](#)
- ["Configure Security Example \(Divide Node Access Between Two or More User Groups\)" on page 593](#)

Configure Security Tasks

Task	Description
Determine your Security strategy.	<p>Use the guidelines in this Help topic to understand how to configure Security for your network environment.</p> <p>You must also determine your users, their <i>Object Access Privileges</i>, and the nodes each user should access:</p> <p>"Control Menu Access" on page 649</p> <p>"User Groups Provided in NNMi" on page 618</p> <p>"Determine which NNMi User Group to Assign" on page 619</p>
Remove the Default Security Group Mappings to NNMi User Groups	<p>Out-of-box, NNMi assigns all Nodes to the Default Security Group and all NNMi users can see all Nodes.</p> <p>To ensure that none of your NNMi operators or guests can see nodes assigned to the Default Security Group, remove these out-of-box Security Group Mappings.</p>  <p>Note: Deleting a Security Group Mapping does not delete the associated predefined NNMi User Group nor the <i>Object Access Privilege</i> definition.</p>
Configure User Accounts	<p>You must create a User Account for each NNMi user.</p>
Configure Additional User Groups	<p>The NNMi administrator can create any number of User Groups to meet the needs of your network environment.</p> <p>Examples of when additional User Groups are needed include the following circumstances:</p> <ul style="list-style-type: none"> • When you need a subset of users to access only a subset of nodes. • When you need to divide node access between two or more User Groups (such as multiple shifts or multiple sites that share responsibilities).

Configure Security Tasks, continued


Task	Description
Map User Accounts to the Predefined NNMi User Groups	<p>A particular user cannot access the NNMi console until their User Account is mapped to at least one of the following predefined NNMi User Groups:</p> <ul style="list-style-type: none"> • NNMi Administrators • NNMi Level 2 Operators • NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators) • NNMi Guest Users <p>Note: NNMi provides two additional User Groups:</p> <ul style="list-style-type: none"> • NNMi Global Operators (<i>secondary</i>) <p>Assigning users to this <i>secondary</i> group, in addition to the user's currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment, provides access to all topology objects, but does not change any other aspect of their currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment.</p> <p>Users assigned to the NNMi Administrators User Group do not need any <i>secondary</i> group assignment. These users already can access all topology objects.</p> <ul style="list-style-type: none"> • NNMi Web Services Client <p>Used <i>only to provide access for software</i> that is integrated with NNMi. See "Integrations with HP and Third-Party Products" on page 1519 - for example, "HP RAMS MPLS WAN Configuration (NNMi Advanced)" on page 1446). Do not use any other User Group for software integrations.</p>
Map User Accounts to Additional User Groups	<p>If you created additional User Groups, map the appropriate User Accounts to each User Group you created.</p>
Configure Security Groups	<p>By default, all operators can access all nodes discovered by NNMi. However, the NNMi administrator can limit visibility to a subset of nodes for some or all operators by using User Groups and Security Groups.</p> <p>Note: Each node can be mapped to one and only one Security Group.</p> <p>Examples of when you need to create additional Security Groups to limit node access include the following circumstances:</p>

Configure Security Tasks, continued

Task	Description
	<ul style="list-style-type: none">• When you need a subset of users to access only a subset of nodes.• When you need to divide node access between two or more User Groups
Map Security Groups to User Groups	<p>After creating any additional User Groups, you map each User Group to a Security Group and assign the <i>Object Access Privilege</i> for this Security Group Mapping. The <i>Object Access Privilege</i> determines the level of access that each User Group has to the nodes that are visible.</p> <p>Users can view a node only if one of the User Groups to which they belong is associated with that node's Security Group.</p>
Assign Nodes to Security Groups	<p>Out-of-box, NNMi Security settings allow all NNMi User Groups to access nodes assigned to the Default Security Group.</p> <p>If you create Security Groups to limit node access, you must assign nodes to the appropriate Security Group.</p> <p>Each node is associated with one and only one Security Group.</p>
Verify Your Configuration Changes	<p>NNMi provides a report that includes information about any of the following potential problems:</p> <ul style="list-style-type: none">• Users Accounts that are not mapped to a User Group• User Accounts that are not mapped to an NNMi User Group• User Accounts that have unusual NNMi role combinations• Security Groups that include nodes from multiple tenants• Empty User Groups and Security Groups• Tenants with the same name• Security Groups with the same name

About User Accounts

The NNMi administrator configures User Accounts as part of the Security Configuration that controls who accesses the NNMi console.



Each User Account represents a user.

NNMi administrators can configure User Accounts using the following methods:


- The Configuration Wizard ("[Create and Delete User Accounts Using the Security Wizard](#)" on [page 616](#))
- The User Accounts view ("[Configure User Accounts \(User Account Form\)](#)" on [page 611](#))
- The `nnmsecurity.ovpl` command line tool

NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See "[Choose a Mode for NNMi Access](#)" on [page 570](#).

Next step: "[About User Groups](#)" below

About User Groups

The NNMi administrator configures User Groups as part of the Security Configuration that controls who accesses the NNMi console.



NNMi provides the following predefined User Groups (NNMi users cannot access the NNMi console until their User Account is mapped to at least one of these). The predefined NNMi User Group that the NNMi administrator assigns to each User Account determines which workspaces, views, menus, actions, and object attributes are visible to each user within the NNMi console (see "[User Groups Provided in NNMi](#)" on [page 618](#) for details):

- NNMi Administrators (no Security Group Mapping required)
- NNMi Level 2 Operators

- NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators)
- NNMi Guest Users

NNMi administrators can configure User Accounts using the following methods:

- The Configuration Wizard ("[Create and Delete User Groups Using the Security Wizard](#)" on page 623)
- The User Accounts view ("[Configure User Groups \(User Group Form\)](#)" on page 621)
- The `nnmsecurity.ovpl` command line tool


NNMi administrators can also create additional User Groups to fine tune NNMi access. See "[Determine Your Security Strategy](#)" on page 574.

NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See "[Choose a Mode for NNMi Access](#)" on page 570.

Next step: "[About User Account Mappings](#)" below

About User Account Mappings

User Account Mappings enable the NNMi administrator to assign a User Account to one or more User Groups to control NNMi console access.



At least one predefined NNMi User Group must be mapped to each User Account to determine which workspaces, views, menus, actions, and object attributes are visible to that User Account within the NNMi console. See "[About User Accounts](#)" on page 579 and "[About User Groups](#)" on the previous page and "[User Groups Provided in NNMi](#)" on page 618 for details.

A User Account can be mapped to two or more User Groups. NNMi administrators can create any number of User Groups.

A User Account Mapping is a separate object in the NNMi database. Therefore, when you create or delete a User Account Mapping, you create or delete only the User Account Mapping, not the User Account or User Group.

NNMi administrators can map User Accounts to User Groups using the following methods:

- The Configuration Wizard ("[Map User Accounts and User Groups](#)" on page 628)
- The User Account Mappings view ("[Map User Accounts to User Groups \(User Account Mapping Form\)](#)" on page 624)
- The `nnmsecurity.ovpl` command line tool


NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See "[Choose a Mode for NNMi Access](#)" on page 570.

Next step: "[About Security Groups](#)" below (only for Operator or Guest users)

About Security Groups

Required only for Operator or Guest users:

The NNMi administrator configures Security Groups as part of the Security Configuration that controls which nodes are accessed in the NNMi console. (NNMi administrators automatically see all nodes.)



Security Groups define sets of nodes within your network environment. Each node is assigned to only one Security Group. Your security strategy determines the number of Security Groups required for your network environment. See "[Determine Your Security Strategy](#)" on page 574. Out-of-box, NNMi assigns all nodes to the **Default Security Group** and all NNMi users see those nodes (based on the out-of-box Security Group Mappings).

NNMi administrators can configure Security Groups to limit node access by using the following methods:

- The Configuration Wizard ("[Create and Delete Security Groups Using the Security Wizard](#)" on page 633)
- The Security Accounts view ("[Configure Security Groups \(Security Group Form\)](#)" on page 632)
- The `nnmsecurity.ovpl` command line tool


The NNMi administrator can assign Nodes to Security Groups. See "[Methods for Assigning Nodes to Security Groups](#)" on page 636.

Next step: "[About Security Group Mappings](#)" on the next page (only for Operator or Guest users)

About Security Group Mappings

Required only for Operator or Guest users:

Security Group Mappings control which nodes are visible to NNMi operators and guests, and what NNMi operators and guests can do with those visible nodes. (Security Group Mappings are irrelevant to users assigned to the *NNMi Administrators* User Group. NNMi administrators automatically see all nodes and have full access rights.)



Security Group Mappings have three settings:

1. ["About User Groups" on page 580](#)
2. ["About Security Groups" on the previous page](#)
3. ["Object Access Privileges Provided in NNMi" on page 640](#)

NNMi provides the following *default* Security Group Mappings that allow all NNMi operators and guests to see all Nodes and all incidents that are not associated with any particular node. NNMi administrators can delete these *default* mappings and create new mappings that provide more limited control. (Deleting a Security Group Mapping does not delete the associated User Group or Security Group, so NNMi administrators can then map those User Groups and Security Groups in other ways with more limited control.)

Security Group Mappings		
1 - 11 of 11		
User Group	Security Group	Object Access Privilege
NNMi Guest Users	Default Security Group	Object Guest
NNMi Guest Users	Unresolved Incidents	Object Guest
NNMi Level 1 Operators	Default Security Group	Object Operator Level 1
NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1
NNMi Level 2 Operators	Default Security Group	Object Operator Level 2
NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2

NNMi provides predefined *Object Access Privileges*. The Object Access Privilege determines the level of access that each User Group has to the visible nodes. Level of node access includes the

actions that can be performed on the nodes. See ["Object Access Privileges Provided in NNMi" on page 640](#).

For example, if an NNMi operator is mapped to a User Group with **NNMi Level 2 Operators**, but their Security Group Mapping's *Object Access Privilege* is **Object Operator Level 1** (with more limited access privileges than Level 2), that NNMi operator sees all of the actions available to NNMi Level 2 Operators, but can run only those *actions allowed* for NNMi Level 1 Operators.

If an NNMi operator or guest is assigned to multiple Security Group Mappings


- Multiple predefined [NNMi User Group](#)¹s, the NNMi console displays all the parts of NNMi that are available to the highest User Group.
- Multiple *Object Access Privileges*, actions available for each node are determined by the node's Security Group Mapping. If mapped to the same Security Group multiple times, the highest access level is available.

NNMi administrators can map User Groups to Security Groups using the following methods:

- The Configuration Wizard (["Map User Groups and Security Groups " on page 644](#))
- The Security Accounts view (["Map User Groups to Security Groups \(Security Group Mapping Form\)" on page 638](#))
- The [nnmsecurity.ovpl](#) command line tool


Next step: ["Check Security Configuration" on page 661](#)

Using the Security Folder



NNMi enables an NNMi administrator to configure the following configurations using Security workspace views:


¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users



Tip: Select **Help** → **System Information** to view the User Name, NNMi Role, and User Group for the current NNMi session.

To configure Security using the Security workspace:

1. Determine your Security strategy (see ["Determine Your Security Strategy" on page 574](#)).
2. Navigate to the **Security** workspace.
3. Make your configuration choices using the Security views. Refer to the About the <x> form Help available for each form within the Security views.




NNMi's security model restricts access to the NNMi console based on User Account to User Group mappings. An NNMi administrator can also choose to restrict Node access based on Security Groups and Security Group Mappings (User Group to Security Group).

Two examples are provided. Use these examples as a guideline for configuring security.

- ["Configure Security: All Users Access All Nodes" below](#)
- ["Configure Security: Limit Node Access" on page 588](#)

Note: You can also configure security using the Security Folder in the Configuration workspace. See ["Using the Security Wizard View" on page 591](#) for more information.

4. Click  **Save and Close**.
5. See ["Methods for Assigning Nodes to Security Groups" on page 636](#).


Configure Security: All Users Access All Nodes

If you want all of your NNMi users to access all of the nodes discovered by NNMi, use these guidelines.

Note: You can also use the [nnmsecurity.ovpl](#) command to configure User Accounts, User Groups, Security Groups, and Tenants.

Tip: Select **Help** → **System Information** to view the User Name, NNMi Role, and User Group for the current NNMi session.

To configure Security:

1. Navigate to the **Security** workspace.
2. Make your configuration choices (see [table](#)).
3. Click  **Save and Close**.

Configure Security Tasks (Using the Security workspace)

Task	Description
Determine your users and their NNMi User Group ¹ or Groups	See "Determine Your Security Strategy" on page 574 and the following topics: "Control Menu Access" on page 649 "User Groups Provided in NNMi" on page 618 "Determine which NNMi User Group to Assign" on page 619

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Configure Security Tasks (Using the Security workspace), continued

Task	Description
Configure User Accounts	You must create a User Account for each NNMi user.
Map User Accounts to the Predefined NNMi User Groups	<p>A particular user cannot access the NNMi console until their User Account is mapped to at least one of the following predefined default NNMi User Groups:</p> <ul style="list-style-type: none"> • NNMi Administrators • NNMi Level 2 Operators • NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators) • NNMi Guest Users <p>Note: NNMi provides two additional User Groups:</p> <ul style="list-style-type: none"> • NNMi Global Operators (<i>secondary</i>) <p>Assigning users to this <i>secondary</i> group, in addition to the user's currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment, provides access to all topology objects, but does not change any other aspect of their currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment.</p> <p>Users assigned to the NNMi Administrators User Group do not need any <i>secondary</i> group assignment. These users already can access all topology objects.</p> <ul style="list-style-type: none"> • NNMi Web Services Client <p>Used <i>only to provide access for software</i> that is integrated with NNMi. See "Integrations with HP and Third-Party Products" on page 1519 - for example, "HP RAMS MPLS WAN Configuration (NNMi Advanced)" on page 1446). Do not use any other User Group for software integrations.</p>
Verify Your Configuration Changes	<p>NNMi provides a report that includes information about any of the following potential problems:</p> <ul style="list-style-type: none"> • Users Accounts that are not mapped to a User Group • User Accounts that are not mapped to an NNMi User Group • User Accounts that have unusual NNMi role combinations • Security Groups that include nodes from multiple tenants

Configure Security Tasks (Using the Security workspace), continued

Task	Description
	<ul style="list-style-type: none">• Empty User Groups and Security Groups• Tenants with the same name• Security Groups with the same name

Configure Security: Limit Node Access


To limit node access, use these guidelines. Ways you might limit node access include the following:

- To permit a subset of users to access only a subset of nodes.
- To divide node access between two or more User Groups

Note: You can also use the [nnmsecurity.ovpl](#) command to configure User Accounts, User Groups, Security Groups, and Tenants.

Tip: Select **Help** → **System Information** to view the User Name, NNMi Role, and User Group for the current NNMi session.

To configure Security:

1. Navigate to the **Security** workspace.
2. Make your configuration choices (see [table](#)).
3. Click  **Save and Close**.

Also see:


["Configure Security Example \(Allow a Subset of Users to Access a Subset of Nodes\)" on page 602](#)

["Configure Security Example \(Divide Node Access Between Two or More User Groups\)" on page 593](#)

Configure Security Tasks (Limit Node Access)

Task	Description
Determine your users, their privileges, and the nodes that	See "Determine Your Security Strategy" on page 574 and the following topics: "Control Menu Access" on page 649 "User Groups Provided in NNMi" on page 618 "Determine which NNMi User Group to Assign" on page 619

Configure Security Tasks (Limit Node Access), continued

Task	Description
each user each should access.	
Remove the Default Security Group Mapping to NNMi User Groups	<p>To ensure that none of your NNMi operators or guests can see nodes assigned to the Default Security Group, remove the out-of box Security mappings.</p>  <p>Note: Deleting a Security Group Mapping does not delete the associated predefined NNMi User Group nor the <i>Object Access Privilege</i> definition.</p>
Configure User Accounts	You must create a User Account for each NNMi user.
Configure Additional User Groups	<p>Out-of-box, all operators and guests can access all nodes discovered by NNMi. However, the NNMi administrator can limit visibility to parts of the network for operators and guests with User Groups and Security Groups. Examples of when additional User Groups are needed include the following circumstances:</p> <ul style="list-style-type: none"> • To permit a subset of users to access only a subset of nodes • To divide node access between two or more User Groups
Map User Accounts to the Predefined	<p>A particular user cannot access the NNMi console until their User Account is mapped to at least one predefined NNMi User Group¹:</p> <ul style="list-style-type: none"> • NNMi Administrators

¹ NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users


Configure Security Tasks (Limit Node Access), continued

Task	Description
NNMi User Groups	<ul style="list-style-type: none"> • NNMi Level 2 Operators • NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators) • NNMi Guest Users <p>Note: NNMi provides two additional User Groups:</p> <ul style="list-style-type: none"> • NNMi Global Operators (<i>secondary</i>) <p>Assigning users to this <i>secondary</i> group, in addition to the user's currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment, provides access to all topology objects, but does not change any other aspect of their currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment.</p> <p>Users assigned to the NNMi Administrators User Group do not need any <i>secondary</i> group assignment. These users already can access all topology objects.</p> <ul style="list-style-type: none"> • NNMi Web Services Client <p>Used <i>only to provide access for software</i> that is integrated with NNMi. See "Integrations with HP and Third-Party Products" on page 1519 - for example, "HP RAMS MPLS WAN Configuration (NNMi Advanced)" on page 1446). Do not use any other User Group for software integrations.</p>
Map User Accounts to Additional User Groups	<p>Map the appropriate User Accounts to each User Group that you created.</p>
Configure Security Groups	<p>Configure a Security Group for each set of nodes that requires limited access.</p> <p>Note: Each node can be mapped to one and only one Security Group.</p> <p>For example, if you want to limit access to nodes in a single location, such as Los Angeles, create a Los Angeles Security Group.</p>
Assign Nodes to Security Groups	<p>If you create Security Groups to limit node access, you must assign nodes to the appropriate Security Group.</p> <p>Note: Each node can be mapped to one and only one Security Group.</p>


Configure Security Tasks (Limit Node Access), continued

Task	Description
Map Security Groups to User Groups	<p>Users can view a node only if one of the User Groups to which they belong is associated with that node's Security Group.</p> <p>Map each User Group to one or more Security Groups.</p> <div> <p>Note: When NNMi administrators map a User Group to a Security Group, they assign the Object Access Privilege for this Security Group Mapping. The <i>Object Access Privilege</i> determines the level of access that each User Group has to the nodes that are visible to it.</p> </div>
Verify Your Configuration Changes	<p>NNMi provides a report that includes information about any of the following potential problems:</p> <ul style="list-style-type: none"> • User Accounts that are not mapped to a User Group • User Accounts that are not mapped to an NNMi User Group • User Accounts that have unusual NNMi role combinations • Security Groups that include nodes from multiple tenants • Empty User Groups and Security Groups • Tenants with the same name • Security Groups with the same name

Using the Security Wizard View



These Configuring Security Wizard pages enables NNMi administrators to configure the following access control features. You can access the wizard pages in any order:



- On the Map User Accounts and User Groups page:

- [User Accounts](#)
- [User Groups](#)
- [User Account / Group Mappings](#)

- On the Assign Nodes to Security Groups page:

[Security Groups](#)

- On the Map User Groups and Security Groups:

[Security Group Mappings](#)

To configure Security using the Security wizard:

1. Determine your Security strategy (see [table](#)).
2. Navigate to the **Security Wizard**.
 - a. From the Workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **Security Wizard**.
3. Make your configuration choices. Refer to the links to online Help from within the Discovery Wizard.

NNMi's security model restricts access to the NNMi console based on User Account to User Group mappings. An NNMi administrator can also choose to restrict Node access based on Security Groups and Security Group Mappings (User Group to Security Group).


Two examples of using the Security Wizard are provided.

Tip: Use these examples as a guideline for configuring security.

Select the example that best matches your security configuration requirements:

- ["Configure Security Example \(Allow a Subset of Users to Access a Subset of Nodes\)" on page 602](#)
- ["Configure Security Example \(Divide Node Access Between Two or More User Groups\)" below](#)

Note: You can also configure security using the Security Folder in the Configuration workspace. See ["Using the Security Folder" on page 584](#) for more information.

4. Click  **Save and Close**.
5. See ["Methods for Assigning Nodes to Security Groups" on page 636](#).


Configure Security Example (Divide Node Access Between Two or More User Groups)

This example uses NNMi's security configuration to divide the responsibility for network monitoring based on the following locations:

- Chicago
- Detroit

Each location includes an NNMi Level 1 Operator (with more limited access privileges than Level 2 Operators) and an NNMi Level 2 Operator. Tina, the NNMi Administrator, handles both locations. Kevin is a backup for both Chicago and Detroit and must access the nodes in both Chicago and Detroit.

The following diagram illustrates the security requirements:



The following table lists the NNMi console (NNMi User Group¹) and node access requirements (User Group, Object Access Privilege and Security Group) for each location.

Note: You can place all operators into the NNMi Level 2 Operators if you want all operators to see all menu options, but only have the ability to run them based on their Object Access Privilege.

Example Security Configuration

User Accounts	NNMi User Groups	User Groups	Object Access Privileges	Security Groups
Tina	NNMi	Not Applicable.	Not Applicable. The	Not Applicable.

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Example Security Configuration, continued

User Accounts	NNMi User Groups	User Groups	Object Access Privileges	Security Groups
	Administrator	The NNMi Administrator can access all nodes.	NNMi Administrator has Administrator privileges to all nodes.	The NNMi Administrator can access all nodes.
Kevin	NNMi Level 2 Operators	Chicago Level 2 Detroit Level 2	Object Operator Level 2	Chicago Nodes, Detroit Nodes
Lisa	NNMi Level 2 Operators	Chicago Level 2	Object Operator Level 2	Chicago Nodes
Taylor	NNMi Level 1 Operators	Chicago Level 1	Object Operator Level 1	Chicago Nodes
Mary	NNMi Level 2 Operators	Detroit Level 2	Object Operator Level 2	Detroit Nodes
Tom	NNMi Level 1 Operators	Detroit Level 1	Object Operator Level 1	Detroit Nodes

To set up security for the Chicago and Detroit locations follow these procedures:


- [Remove the Default Security Group Mapping to NNMi User Groups](#): NNMi Level 1 Operators, NNMi Level 2 Operators, and NNMi Guest

Note: The NNMi User Groups are provided for those NNMi administrators who are not concerned with Security configuration. After you remove these Security Group Mappings, the NNMi User Groups provide access to the NNMi console only rather than to the NNMi console and to all nodes.


- [Create the User Accounts](#). (See the [Example Security Configuration](#) table.)
- [Create the Additional User Groups required for the Chicago and Detroit Security Groups](#) (Chicago Level 2, Chicago Level 1, Detroit Level 2, Deteroit Level 1). (See the [Example Security Configuration](#) table.)
- [Map User Accounts to NNMi User Groups](#). (See the [Example Security Configuration](#) table.)
- [Create the Security Groups for each location](#).
- [Map each Security Group to the new User Groups](#). (See the [Example Security Configuration](#) table.)
- [Assign the nodes to the appropriate Security Group](#).
- [View a summary of your configuration changes](#)

Remove the Default Security Group Mapping to NNMi User Groups

1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Navigate to the **Security Group Mappings** table.




User Group	Security Group	Object Access Privilege
NNMi Guest Users	Default Security Group	Object Guest
NNMi Guest Users	Unresolved Incidents	Object Guest
NNMi Level 1 Operators	Default Security Group	Object Operator Level 1
NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1
NNMi Level 2 Operators	Default Security Group	Object Operator Level 2
NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2

3. Click the row representing the **NNMi Level 1 Operators** User Group.
4. Click the  Delete icon to remove the Default Security Group to NNMi Level 1 Operators User Group mapping.
5. Repeat steps 3 and 4 to remove the Default Security Group to **NNMi Level 2 Operator** and the **NNMi Guest** User Group mappings.
6. Continue or, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until after you click **Save and Close** to save your security configuration.

Create User Accounts

1. In the Configuration workspace, select **Security Wizard**
2. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
3. Navigate to the **User Accounts** table.
4. Click  **New**.
5. In the **Create User Account** dialog box, enter the following:

- a. **Name:** Enter the user name **Tina**.
 - b. **Password:** Enter the Password value **Tina**. The Password value can be any amount of alpha-numeric characters, punctuation, spaces, and underline characters.
6. Click **Add**.
 7. Repeat steps 5 and 6 to add each User Account. (See the [Example Security Configuration table](#).)
 8. When you finish creating User Accounts, in the **Create User Account** dialog box, click **Close**

Close


9. Continue or, click the **Save and Close** button to save your security configuration:


Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Create Additional User Groups

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option
2. Navigate to the **User Groups** table.
3. Click *** New**.
4. In the **Create User Group** dialog box, enter the following:
 - a. **Name:** Enter **ChicagoLevel2**. The name can be a maximum of 40 alpha-numeric characters. Spaces are not permitted.
 - b. **Display Name:** Enter **Chicago Level 2**. The Display Name is displayed in the NNMi console to identify this User Group. Enter a maximum of 50 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
 - c. **Directory Service Name:** *Optional*. When Lightweight Directory Access Protocol (LDAP) define this User Group, enter the group's Distinguished Name. See the following topics:
 - ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572](#).
 - ["X.509 Certificates to Control NNMi Access" on page 573](#)
 - d. **Description:** Type a maximum of 2048 characters to describe this User Group. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

5. Click **Add**.
6. Repeat steps 2 and 3 to add each User Group. (See the [Example Security Configuration](#) table.)
7. When you finish creating User Groups, in the **Create User Group** dialog box, click **Close**

8. Continue or, click the **Save and Close** button to save your security configuration:

 Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Map User Accounts to User Groups

Note: A User Account cannot access the NNMi console until it is mapped to one of the NNMi User Groups.

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option
2. Select Tina in the **User Accounts** table.
3. In the **User Groups** table, select the left arrow that precedes the **NNMi Administrators** User Group.

The User Account and User Group names appear in the **User Account Mapping** table.

4. Repeat steps 1 and 2 to assign each User Account to the appropriate User Group. (See the [Example Security Configuration](#) table.)
5. Continue or, click the **Save and Close** button to save your security configuration:

 Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Map Security Groups to User Groups

1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Select **Chicago Nodes** in the **Security Groups** table.
3. In the **Security Group Mappings** drop-down selection box, select **Object Operator Level 2**.

4. In the **User Groups** table, click the  right arrow in the **ChicagoLevel2** row.

The Security Group and User Group names appear in the **Security Group Mapping** table.

5. Repeat steps 2 through 4 to map the following User Groups and Security Groups:

Tip: Be sure to select the appropriate Object Access Privilege in the drop-down selection box under **Security Group Mappings**.

ChicagoLevel1 User Group to the **Chicago Nodes**

DetroitLevel1 User Group to the **Detroit Nodes**

DetroitLevel2 User Group to the **Detroit Nodes**

6. Continue or, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Your Security Group to User Group mappings should look similar to the following:

User Groups		Security Group Mappings		Security Groups	
* X [icon]		X [dropdown]		* X [icon]	
Display Name	User Group	Security Group	Object Access Privilege	Name	
Chicago Level 1	Chicago Level 1	Chicago Nodes	Object Operator Level 1	Chicago Nodes	
Chicago Level 2	Chicago Level 2	Chicago Nodes	Object Operator Level 2	Default Security Group	
Detroit Level 1	Detroit Level 1	Detroit Nodes	Object Operator Level 1	Detroit Nodes	
Detroit Level 2	Detroit Level 2	Detroit Nodes	Object Operator Level 2	Unresolved Incidents	
NNMi Administrators	NNMi Guest Users	Default Security Group	Object Guest		
NNMi Guest Users	NNMi Guest Users	Unresolved Incidents	Object Guest		
NNMi Level 1 Operators	NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1		
NNMi Level 2 Operators	NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2		
NNMi Web Service Clients					

Assign the Nodes to the Appropriate Security Group

1. From the **Security Wizard** main page, select the **Assign Nodes to Security Groups** option.
2. Select a row in the **Security Groups** table.
3. In the **Available Nodes** table, do one of the following:
 - a. Select a Node Group in the Node Group filter drop-down list to specify the nodes to be assigned to the Security Group.
 - b. User Ctrl-Click to select each node you want to assign to the selected Security Group.
4. Click [icon] to specify that you want to assign the selected nodes to the Security Group.

The **Nodes to be Assigned to Selected Group** table displays the list of nodes to be assigned to the selected Security Group.

Note: Out-of-box, NNMi assigns all Nodes the Default Security Group. See "[Methods for Assigning Nodes to Security Groups](#)" on page 636.

5. Repeat steps 2 through 4 to assign nodes to a selected Security Group.
6. Continue or, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click Save and Close to save your security configuration.


View the Summary of Configuration Changes

From the **Security Wizard** main page, select the **View Summary of Changes** option.

NNMi displays a summary of the configuration changes made since you last saved your changes.

Save Your Configuration Changes

When you finish, click the **Save and Close** button to save your security configuration:

A rectangular button with a light blue border and a light blue background, containing the text "Save & Close" in a dark blue font.


Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Configure Security Example (Allow a Subset of Users to Access a Subset of Nodes)

This example uses NNMi's security configuration to allow a subset of users to access only those nodes in Building 5. The remaining users can access all nodes discovered by NNMi.

This location includes an NNMi Level 1 Operator (with more limited access privileges than Level 2 Operators) and an NNMi Level 2 Operator. Jeff is an NNMi Level 2 Operator who can access only the nodes in Building 5.

Note: Be sure to create a User Account that is mapped to the NNMi Administrator User Group so that one person has access to the Configuration workspace and all the nodes in the network. See "[Restore the Administrator NNMi Role](#)" on [page 666](#) for more information.



The following table lists the NNMI console access requirements (NNMi User Group¹) and node access requirements (User Group, Object Access Privilege and Security Group) for each User Account.

Note: You can place all operators into the NNMI Level 2 Operators if you want all operators to see all menu options, but only have the ability to run them based on their Object Access Privilege.

Example Security Configuration

User Accounts	NNMI User Groups	User Groups	Object Access Privileges	Security Groups
Jim	NNMI Level 1 Operators	Lev1Buildings1-4 Lev1Building5	Object Operator Level 1	Default Security Group

¹NNMI User Groups are those User Groups provided by NNMI. Users cannot access the NNMI console until their User Account is mapped to at least one of the following NNMI User Groups: NNMI Administrators, NNMI Level 2 Operators, NNMI Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMI Guest Users

Example Security Configuration, continued

User Accounts	NNMi User Groups	User Groups	Object Access Privileges	Security Groups
Cathy	NNMi Level 2 Operators	Lev2Buildings1-4 Lev2Building5	Object Operator Level 2	Default Security Group
Jeff	NNMi Level 2 Operators	Lev2Building5	Object Operator Level 2	Building 5 Nodes

To set up security for this location follow these procedures:

- [Remove the Default Security Group Mapping to NNMi User Groups](#): NNMi Level 1 Operators, NNMi Level 2 Operators, and NNMi Guest


Note: The [NNMi User Group](#)¹s are provided for those NNMi administrators who are not concerned with Security configuration. After you remove these Security Group Mappings, the NNMi User Groups provide access to the NNMi console only rather than to the NNMi console and to all nodes.

- [Create the User Accounts](#). (See the [Example Security Configuration](#) table.)
- Create Additional User Groups. (See the [Example Security Configuration](#) table.)
- [Map User Accounts to NNMi User Groups](#). (See the [Example Security Configuration](#) table.)
- [Create the Building 5 Security Group](#).
- [Map each Security Group to the new User Groups](#). (See the [Example Security Configuration](#) table.)
- [Assign the nodes to the appropriate Security Group](#).
- [View a summary of your configuration changes](#)

[Remove the Default Security Group Mapping to NNMi User Groups](#)


1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Navigate to the **Security Group Mappings** table.

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users



The screenshot shows a window titled "Security Group Mappings" with a toolbar containing icons for adding, deleting, and refreshing mappings. Below the toolbar is a table with three columns: "User Group", "Security Group", and "Object Access Privilege". The table lists six mappings for NNMi Guest Users, NNMi Level 1 Operators, and NNMi Level 2 Operators, each associated with either the Default Security Group or Unresolved Incidents.


User Group	Security Group	Object Access Privilege
NNMi Guest Users	Default Security Group	Object Guest
NNMi Guest Users	Unresolved Incidents	Object Guest
NNMi Level 1 Operators	Default Security Group	Object Operator Level 1
NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1
NNMi Level 2 Operators	Default Security Group	Object Operator Level 2
NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2


3. Click the row representing the **NNMi Level 1 Operators** User Group.
4. Click the  Delete icon to remove the Default Security Group to NNMi Level 1 Operators User Group mapping.
5. Repeat steps 3 and 4 to remove the Default Security Group to **NNMi Level 2 Operator** and the **NNMi Guest** User Group mappings.
6. Continue or, click the **Save and Close** button to save your security configuration:


Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Create User Accounts

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
2. Navigate to the **User Accounts** table.
3. Click  **New**.
4. In the **Create User Account** dialog box, enter the following:
 - a. **Name:** Enter the user name **Jim**.
 - b. **Password:** Enter the Password value **Jim**. The Password value can be any amount of alpha-numeric characters, punctuation, spaces, and underline characters.
5. Click **Add**.


6. Repeat steps 4 and 5 to add each User Account. (See the [Example Security Configuration table](#).)
7. When you finish creating User Accounts, in the **Create User Account** dialog box, click **Close**

8. Continue or, click the **Save and Close** button to save your security configuration:



Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Create Additional User Groups

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option
 2. Navigate to the **User Groups** table.
 3. Click *** New**.
 4. In the **Create User Group** dialog box, enter the following:
 - a. **Name:** Enter **Lev1Building1-4**. The name can be a maximum of 40 alpha-numeric characters. Spaces are not permitted.
 - b. **Display Name:** Enter **Lev1 Building 1-4**. The Display Name is displayed in the NNMi console to identify this User Group. Enter a maximum of 50 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
- Tip:**
- c. **Directory Service Name:** When a directory service defines this User Group, enter the group's Distinguished Name. This example does not use this option. NNMi communicates with the directory service using Lightweight Directory Access Protocol (LDAP).
 - ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572.](#)
 - ["X.509 Certificates to Control NNMi Access" on page 573](#)
 - d. **Description:** Type a maximum of 2048 characters to describe this User Group. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
5. Click **Add**.

6. Repeat steps 4 and 5 to add the **Lev1Building5**, **Lev2Building1-4**, and **Lev2Building5** User Groups. (See the [Example Security Configuration](#) table.)
7. When you finish creating User Groups, in the **Create User Group** dialog box, click **Close**

8. Continue, or click the **Save and Close** button to save your security configuration:

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration

Map User Accounts to User Groups

Note: A User Account cannot access the NNMi console until after it is mapped to one of the NNMi User Groups.

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option
2. Select **Jim** in the **User Accounts** table.
3. In the **User Groups** table, select the left arrow that precedes the **NNMi Level 1 Operators** User Group.

The User Account and User Group names appear in the **User Account Mapping** table.


4. Repeat steps 2 and 3 to assign each User Account to the appropriate User Group. (See the [Example Security Configuration](#) table.):

Assign **Jim** to the **Lev1Building1-4** and **Lev1Building5** User Group

Assign **Cathy** to the **NNMi Level 2 Operators**, **Lev2Building1-4**, and **Lev2Building5** User Groups








Assign **Jeff** to the **NNMi Level 2 Operators** and **Lev2Building 5** User Groups.

5. Continue or, click the **Save and Close** button to save your security configuration:





Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Your User Account to User Group mappings should look similar to the following:


User Accounts	User Account Mappings	User Groups		
  		  		
Name	User Account	User Group	Name	Display Name
Jeff	Jim	Lev1 Building 1-4	admin	NNMi Administrators
Jim	Jim	Lev1 Building 5	level1	NNMi Level 1 Operators
Cathy	Cathy	Lev2 Building 1-4	level2	NNMi Level 2 Operators
3 User Accounts	Cathy	Lev2 Building 5	client	NNMi Web Service Clients
	Jeff	Lev2 Building 5	guest	NNMi Guest Users
	Jim	NNMi Level 1 Operators	Lev1Building1to	Lev1 Building 1-4
	Cathy	NNMi Level 2 Operators	Lev1Building5	Lev1 Building 5
	Jeff	NNMi Level 2 Operators	Lev2Building5	Lev2 Building 5
			Lev2Building1to	Lev2 Building 1-4

Create the Building 5 Security Group

- From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option
- Navigate to the **Security Groups** table.
- Click  **New**.
- In the **Create Security Group** dialog box, enter the following:
 - Name:** Enter **Building 5 Nodes**. The name must be a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
 - Description:** Type a maximum of 2048 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
- Click **Add**.
- When you finish creating Security Groups, in the **Create Security Group** dialog box, click **Close** .
- Continue, or click the **Save and Close** button to save your security configuration:

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Map User Groups to Security Groups

1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Select **Default Security Group** in the **Security Groups** table.
3. In the **Security Group Mappings** drop-down selection box, select **Object Operator Level 1**.
4. In the **User Groups** table, click the  right arrow in the **Lev1Building1-4** row.

The Security Group and User Group names appear in the **Security Group Mapping** table.

5. Repeat steps 2 through 4 to assign the following Security Group Mappings:

Tip: Be sure to select the appropriate Object Access Privilege in the drop-down selection box under **Security Group Mappings**.

Lev1Building5 User Group to the **Building 5 Nodes**.

Lev2Building1-4 User Group to the **Default Security Group**



Lev2Building5 User Group to the **Building 5 Nodes**.

6. Continue or, click the **Save and Close** button to save your security configuration:


Save & Close

Note: NNMI does not save any configuration changes until you click **Save and Close** to save your security configuration.

Your User Group to Security Group mappings should look similar to the following:

User Groups		Security Group Mappings		Security Groups	
* X 		X <input type="text"/>		* X 	
Display Name	User Group	Security Group	Object Access Privilege	Name	
Lev1 Building 1-4	Lev1 Building 1-4	Default Security Group	Object Operator Level 1	Buildings 1-4 Nodes	
Lev1 Building 5	Lev1 Building 5	Building 5 Nodes	Object Operator Level 1	Building 5 Nodes	
Lev2 Building 1-4	Lev2 Building 1-4	Default Security Group	Object Operator Level 2	Default Security Group	
Lev2 Building 5	Lev2 Building 5	Building 5 Nodes	Object Operator Level 2	RegionalTenant	
NNMi Administrators	NNMi Guest Users	Default Security Group	Object Guest	Unresolved Incidents	
NNMi Guest Users	NNMi Guest Users	Unresolved Incidents	Object Guest		
NNMi Level 1 Operators	NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1		
NNMi Level 2 Operators	NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2		
NNMi Web Service Clients					

Assign the Nodes to the Appropriate Security Group

1. From the **Security Wizard** main page, select the **Assign Nodes to Security Groups** option.
2. Select the **Building 5 Nodes** row in the **Security Groups** table.
3. In the **Available Nodes** table, do one of the following:
 - a. Select a Node Group in the Node Group filter drop-down list to specify the nodes to be assigned to the Security Group.
 - b. User Ctrl-Click to select each node you want to assign to the **Building 5 Nodes**.
4. Click  to specify that you want to assign the selected nodes to the Security Group.

The **Nodes to be Assigned to Selected Group** table displays the list of nodes to be assigned to the selected Security Group.

5. Repeat steps 2 through 4 to assign nodes to a selected Security Group.
6. Continue or, click **Save and Close** to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

View the Summary of Configuration Changes

From the **Security Wizard** main page, select the **View Summary of Changes** option.

NNMi displays a summary of the configuration changes made since you last saved your changes.

Save Your Configuration Changes

When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

User Account Tasks


NNMi administrators can configure User Accounts using the following methods:

- The Configuration Wizard ("[Create and Delete User Accounts Using the Security Wizard](#)" on [page 616](#))

- The User Accounts view ("[Configure User Accounts \(User Account Form\)](#)" below)
- The [nnmsecurity.ovpl](#) command line tool

Configure User Accounts (User Account Form)

NNMi User Account configurations provide NNMi user name and password settings, as well as indicate whether NNMi should use an external resource for password information. See "[About User Accounts](#)" on page 579.




Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See "[Create and Delete User Accounts Using the Security Wizard](#)" on page 616 or [nnmsecurity.ovpl](#).

To configure NNMi user names and passwords use the following instructions:

1. [Navigate to the User Accounts view](#).
 - a. From the workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Accounts**.

Tip: You can filter the User Accounts table view by User Group or Security Group.

2. Do one of the following:
 - To create a new configuration, click the *** New** icon.
 - To edit an existing configuration, double-click the User Account definition you want to edit.
 - To delete a User Account, see "[Delete a User Account](#)" on page 613.
3. Make your configuration choices. See the [User Account Attributes](#) table.
4. Click  **Save and Close** to save your changes and return to the **User Accounts** view.

Note: You must click **Save and Close** to save your changes each time you create a User Account.

5. NNMi users can belong to more than one User Group. You must assign each User Account to a preconfigured User Group provided by NNMi before that user can access NNMi. See ["User Groups Provided in NNMi" on page 618](#) and for more information.

User Account Attributes

Attribute	Description
Name	<p>Enter the user name to be assigned to this user:</p> <ul style="list-style-type: none"> • Up to 40 alpha-numeric characters. • Do not use punctuation, spaces, or underline characters.
Directory Service Account	<p><input type="checkbox"/> = User name and password are stored in the NNMi database. See "NNMi Configuration Settings to Control NNMi Access" on page 571.</p> <p><input checked="" type="checkbox"/> = NNMi uses Lightweight Directory Access Protocol (LDAP) or X509 Certificates such as Public Key Infrastructure (PKI) user authentication. Additional steps are required. See the following topics:</p> <ul style="list-style-type: none"> • "Lightweight Directory Access Protocol (LDAP) to Control NNMi Access" on page 572. • "X.509 Certificates to Control NNMi Access" on page 573
Password	<p>Enter the Password value. Type any amount of alpha-numeric characters, punctuation, spaces, and underline characters.</p> <div> <p>Note: If you enabled Directory Service Account <input checked="" type="checkbox"/>, do not provide a Password.</p> <p>Tip: When NNMi is configured with Directory Service Account <input type="checkbox"/>, NNMi users who are assigned to the following Security Group Mapping can change their NNMi password at any time using File → Change Password.</p> <p><i>Object Access Privilege</i> = one of the following:</p> <ul style="list-style-type: none"> • Object Administrator • Object Operator Level 2 • Object Operator Level 1 (with more limited access privileges than Level 2) </div>
	Re-type the Password value.

Related Topics:

["Delete a User Account" below](#)

["Change Password, Name" on the next page](#)

["Restore the Administrator NNMi Role" on page 666](#)

Delete a User Account


To deny a user's access to the NNMi console, delete their user configuration settings from the NNMi database.

Note: Ignore this topic if NNMi is configured to access LDAP information for user group assignments. When NNMi is configured in that way, to disable a user's access to NNMi, you must use the appropriate process required by your environment's directory service software (see ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572](#) and ["X.509 Certificates to Control NNMi Access" on page 573](#)).

Caution: If you delete the last NNMi user assigned to the NNMi Administrators User Group, no one can access the Configuration workspace. See ["Restore the Administrator NNMi Role" on page 666](#) for more information about how to recover from this mistake.

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Create and Delete User Accounts Using the Security Wizard" on page 616](#) or [nnmsecurity.ovpl](#).

To deny a user's access to NNMi:

1. Navigate to the **User Accounts** view.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Accounts**.
2. Select the row containing the User Account you want to delete.
3. Click the  Delete icon.

The user's configuration is automatically removed from the User Accounts view.

Note: If you remove the User Account for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

Tip: Access the Incident Browsing workspace. Open the All Incidents view. Sort this view using the Assigned To (AT) column. Reassign all Incidents associated with any user you deleted (see [Assign an Incident](#)).

Change Password, Name

Only NNMi administrators can add and delete accounts and change NNMi User Accounts and User Groups.

- If configuring NNMi to store user names and passwords in the NNMi database, use the following instructions.
- If configuring NNMi to use an external User Authentication Method (passwords stored outside of the NNMi database), see ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572](#) or ["X.509 Certificates to Control NNMi Access" on page 573](#).


Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Create and Delete User Accounts Using the Security Wizard" on page 616](#) or [nmmsecurity.ovpl](#).

To change an NNMi user name:

You must ["Delete a User Account" on the previous page](#), and then recreate the account mapping (see ["NNMi Configuration Settings to Control NNMi Access" on page 571](#)).




To change an NNMi password:

Note: If you are not using Lightweight Directory Access Protocol (LDAP) or X.509 Certificates to manage NNMi users, User Accounts assigned to the following User Groups can change their password using **File** → **Change Password**: NNMi Administrators, NNMi Level 2 Operators, and NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators). See [Change Your Password](#) for more information.







1. Navigate to the **User Accounts** view.
 - a. From the Workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Accounts**.
2. Double-click the row representing the account you want to edit.
3. Locate the **Password** attribute and edit the **Password** value. Type up to 40 alpha-numeric characters, punctuation, spaces, and underline characters.
4. Retype the new password.
5. Click  **Save and Close**. NNMi immediately implements your changes.

To change an NNMi User Group to User Account assignment:

Note: To change a User Group to User Account assignment, you first delete the User Account mapping. If you change the User Account or User Group configuration for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

1. Navigate to the **User Account Mappings** view.
 - a. From the Workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Account Mappings**.
2. Select the row representing the User Account mapping you want to change.
3. Delete the User Account mapping by clicking the  Delete icon.
4. Select the  **New** icon to configure the new User Account mapping.
5. Make your configuration choices. (See the [User Account Mapping Attributes](#) table.)
6. Click  **Save and Close**.

User Account Mapping Attributes

Attribute	Description
User Group	<p>In the User Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none">■ To create new User Group, click the  New icon and provide the required information. (See "Configure User Groups (User Group Form)" on page 621 for more information.)■ To select an NNMi User Group configuration, click the  Quick Find icon and make a selection.
User Account	<p>In the User Account attribute, click the  Lookup icon.</p> <ul style="list-style-type: none">■ To create new User Account, click the  New icon and provide the required information. See "Configure User Accounts (User Account Form)" on page 611 for more information.)■ To select an NNMi User Group configuration, click the  Quick Find icon and make a selection.

User Account Mapping Attributes, continued


Attribute	Description
	Note: If you map a User Account to two or more NNMi User Groups, NNMi gives the User Account the privileges associated with each mapped NNMi User Group.

Create and Delete User Accounts Using the Security Wizard

For more information about User Accounts, see ["About User Accounts" on page 579](#).

Tip: NNMi administrators can also use the User Accounts view or command line to complete this task. See ["Configure User Accounts \(User Account Form\)" on page 611](#) or [nnmsecurity.ovpl](#).

To create a User Account:

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
2. Navigate to the **User Accounts** table.
3. Click  **New**.
4. In the **Create User Account** dialog box, enter the following:
 - a. **Username:** Enter the user name to be assigned to this user:
 - Up to 40 alpha-numeric characters.
 - Do not use punctuation, spaces, or underline characters.
 - b. **Password:** Enter the Password value. Type any amount of alpha-numeric characters, punctuation, spaces, and underline characters.

Note: The Security Wizard is unable to create accounts for use with LDAP or PKI user authentication. These accounts may be created using the User Accounts Form or the [nnmsecurity.ovpl](#) command. See ["Configure User Accounts \(User Account Form\)" on page 611](#).

5. Click **Add**.
6. Repeat Step 4 and 5 to add each User Account.


7. When you finish adding User Accounts in the **Create User Account** dialog box, click **Close**




8. When you finish your security configuration, click **Save and Close** to save your security configuration.

To modify a User Account: see ["Change Password, Name" on page 614](#).

To delete a User Account:

1. Select a row in the **User Accounts** table.
2. Click  **Delete**.
3. When you finish, click the **Save and Close** button to save your security configuration:



Caution: If you remove the User Account for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

Access the Incident Browsing workspace. Open the All Incidents view. Sort this view using the Assigned To (AT) column. Reassign all Incidents associated with any user you deleted (see [Assign an Incident](#)).

NNMi User Accounts can be assigned to one or more User Groups. You must assign each User Account to one of the following NNMi User Groups so users can access the NNMi console:

- NNMi Administrators
- NNMi Level 2 Operators
- NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators)
- NNMi Guest Users

See ["Assign User Accounts to User Groups Using the Security Wizard Page" on page 630](#) for more information.

User Group Tasks

NNMi administrators can configure User Groups using the following methods:

- The Configuration Wizard ("[Create and Delete User Groups Using the Security Wizard](#)" on page 623)
- The User Accounts view ("[Configure User Groups \(User Group Form\)](#)" on page 621)
- The `nnmsecurity.ovpl` command line tool

User Groups Provided in NNMi

When the NNMi administrator configures NNMi Security, each User Account must be mapped to one or more User Group.

The following predefined [NNMi User Group](#)¹s determine the NNMi user's access to the NNMi console workspaces, forms, and actions. Each User Account must be mapped to one of these predefined NNMi User Groups before users can access the NNMi console:

- NNMi Administrators
- NNMi Level 2 Operators
- NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators)
- NNMi Guest Users

Note: NNMi provides two additional User Groups:

- NNMi Global Operators (*secondary*)

Assigning users to this *secondary* group, in addition to the user's currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment, provides access to all topology objects, but does not change any other aspect of their currently assigned NNMi Guest User, NNMi Level 1 Operator, or NNMi Level 2 Operator assignment.

Users assigned to the NNMi Administrators User Group do not need any *secondary* group assignment. These users already can access all topology objects.

- NNMi Web Services Client

Used *only to provide access for software* that is integrated with NNMi. See "[Integrations with HP and Third-Party Products](#)" on page 1519 - for example, "[HP RAMS MPLS WAN Configuration \(NNMi Advanced\)](#)" on page 1446). Do not use any other User Group for software integrations.

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

You cannot delete these predefined NNMi User Groups.

If you map a User Account to two or more NNMi User Groups, NNMi gives the User Account the privileges associated with each User Group to which the User Account is assigned.

Note: NNMi administrators can also create User Groups. Creating User Groups enables you to fine tune User Group access when using Security Groups. For example, you might want one User Group to have Level 2 Operator access to the nodes in one Security Group and Level 1 Operator access to nodes in another Security Group. See "[Configure User Groups \(User Group Form\)](#)" on page 621 and "[Configure Security Groups \(Security Group Form\)](#)" on page 632 for more information.

For details about User Groups, see the following topics:

- "[Determine which NNMi User Group to Assign](#)" below (controls access to views and forms)
- "[Control Menu Access](#)" on page 649 (NNMi administrators control which User Groups can access a subset of Action menu items)
- "[Configure Basic Settings for a Node Group Map](#)" on page 552 (For each Node Group Map, the **Minimum NNMi Role for Saving Map Layout** attribute setting controls the minimum [NNMi Role](#)¹ required for saving the layout after the user repositions nodes on the map. The NNMi Role is assigned to a User Account through the NNMi User Group.)

Determine which NNMi User Group to Assign

Before configuring NNMi sign-in access for your team, determine which predefined [NNMi User Group](#)² is appropriate for each team member. The User Groups are hierarchical, meaning the higher level User Groups include all privileges of the lower level User Groups in the hierarchy (Administrator is highest, Guest is lowest).

Note: NNMi provides a special `Web Services Client` User Group used *only to provide access for software* that is integrated with NNMi. For example, see "[HP RAMS MPLS WAN Configuration \(NNMi Advanced\)](#)" on page 1446. Do not use any other User Group for software integrations.

As NNMi administrator, you can change the following aspects of User Group definitions:

¹Determined by your membership in one of four special NNMi User Groups (NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators, or NNMi Guest Users). This membership determines what you can see and do within the NNMi console.

²NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

- ["Control Menu Access" on page 649](#) (restrict access to certain NNMi Actions menu items and Tools menu items - provide tighter security than those enforced by the default settings.) See also ["Configure Launch Actions" on page 1462](#) for more information about adding options to the NNMi Actions menu.
- ["Configure Basic Settings for a Node Group Map" on page 552](#). (For each Node Group Map, the **Minimum NNMi Role for Saving Map Layout** attribute setting controls the minimum User Group required for saving the layout after the user repositions nodes on the map. The [NNMi Role¹](#) is assigned to a User Account through the NNMi User Group.
- ["Set Up Command Line Access to NNMi" on page 653](#) (Use to control access to NNMi command line commands.)

The following table lists the User Group required to access NNMi workspaces. You cannot modify User Group settings for workspaces. See [About Workspaces](#) for more information about workspaces. See [Views Available in NNMi](#) for more information about the views provided in each workspace.

Access to Workspaces

Workspaces	NNMi Guest Users	NNMi Level 1 Operators	NNMi Level 2 Operators	NNMi Administrators
All views in the Incident workspaces	Yes	Yes	Yes	Yes
All views in the Topology workspace	Yes	Yes	Yes	Yes
All views in the Monitoring workspace	Yes	Yes	Yes	Yes
All views in the Troubleshooting workspace	Yes	Yes	Yes	Yes
All views in the Inventory workspace	Yes	Yes	Yes	Yes
All views in the Management Mode workspace			Yes	Yes
All views in the Configuration workspace				Yes

The following table provides some examples of how NNMi User Groups control permission for modifications to certain forms. You cannot modify User Group settings for forms.


¹Determined by your membership in one of four special NNMi User Groups (NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators, or NNMi Guest Users). This membership determines what you can see and do within the NNMi console.

Access to Forms (some examples)

Forms	NNMi Guest Users	NNMi Level 1 Operators	NNMi Level 2 Operators	NNMi Administrators
Node forms	Read-Only	Read-Write except Management Mode field which is Read-Only	Read-Write	Read-Write
Interface forms	Read-Only	Read-Write except Management Mode field which is Read-Only	Read-Write	Read-Write
IP Address forms	Read-Only	Read-Write except Management Mode field which is Read-Only	Read-Write	Read-Write
IP Subnet forms	Read-Only	Read-Write except Management Mode field which is Read-Only	Read-Write	Read-Write
Incident forms	Read-Only	Read-Write	Read-Write	Read-Write
Node Group forms	Read-Only	Read-Only	Read-Only	Read-Write
MIB forms			Read-Only	Read-Only
Configuration Forms				Read-Write

Configure User Groups (User Group Form)

Use this User Group form to establish any User Groups required for your NNMi Security strategy. See ["Determine Your Security Strategy" on page 574](#).



Each NNMi user must belong to at least one predefined [NNMi User Group](#)¹. See ["User Groups Provided in NNMi" on page 618](#) and ["Determine which NNMi User Group to Assign" on page 619](#). These predefined NNMi User Groups cannot be deleted.

¹ NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users




Each NNMi user can belong to one or more User Groups that the NNMi administrators create. See ["About User Groups" on page 580](#).

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Create and Delete User Groups Using the Security Wizard" on the next page](#) or [nnmsecurity.ovpl](#).

To configure a User Group, do the following:

1. [Navigate to the User Groups view](#).
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Groups**.

Tip: You can filter the User Groups table view by Security Group.

2. Do one of the following:
 - To create a new configuration, click the  **New** icon.
 - To edit an existing configuration, double-click the User Groups definition you want to edit.
 - To delete an existing configuration, click the  **Delete** icon.
3. Make your configuration choices. (See the [User Group Attributes](#) table.)
4. Make your additional configuration choices. Click [here](#) for a list of choices .
5. Click  **Save and Close** to apply your changes.

User Group Attributes

Attribute	Description
Name	Enter the name that uniquely identifies the User Group. Enter a maximum of 40 alpha-numeric characters. Spaces are not permitted.
Display Name	Enter the name that should be displayed in the NNMi console to identify this User Group. Enter a maximum of 50 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
Directory Service Name	<i>Optional.</i> When Lightweight Directory Access Protocol (LDAP) defines this User Group, enter the group's Distinguished Name. See the following topics: <ul style="list-style-type: none">• "Lightweight Directory Access Protocol (LDAP) to Control NNMi Access" on page 572.• "X.509 Certificates to Control NNMi Access" on page 573

User Group Attributes, continued

Attribute	Description
Description	Type a maximum of 2048 characters to describe this User Group. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Create and Delete User Groups Using the Security Wizard

For more information about User Accounts, see ["About User Groups" on page 580](#).

Tip: NNMi administrators can also use the User Groups view or command line to complete this task. See ["Configure User Groups \(User Group Form\)" on page 621](#) or [nnmsecurity.ovpl](#).

To create User Groups:

1. From the **Security Wizard** page, do one of the following:
 - a. Select the **Map User Accounts and Security Groups** option.
 - b. Select the **Map User Groups and Security Groups** option.
2. Navigate to the **User Groups** table.
3. Click *** New**.
4. In the **Create User Group** dialog box, enter the following:
 - a. **Name:** Enter the name that uniquely identifies the User Group. Enter a maximum of 40 alpha-numeric characters. Spaces are not allowed.
 - b. **Display Name:** Enter the name that should be displayed in the NNMi console to identify this User Group. Enter a maximum of 50 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
 - c. **Directory Service Name:** Optional. When a directory service defines this User Group, enter the group's Distinguished Name. NNMi communicates with the directory service using Lightweight Directory Access Protocol (LDAP). See one of the following topics:
 - ["Lightweight Directory Access Protocol \(LDAP\) to Control NNMi Access" on page 572](#).
 - ["X.509 Certificates to Control NNMi Access" on page 573](#)
 - d. **Description:** Type a maximum of 2048 characters to describe this User Group. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
5. Click **Add**.

6. Repeat Step 4 and 5 to add each User Group.
7. When you finish adding User Groups, in the **Create User Group** dialog box, click **Close**
8. When you finish, click the **Save and Close** button to save your security configuration:

Close

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

To delete User Groups:

1. Select a row in the **User Groups** table.
2. Click **Delete**.
3. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.


User Account Mapping Tasks

NNMi administrators can map User Accounts to User Groups using the following methods:

- The Configuration Wizard ("[Map User Accounts and User Groups](#)" on page 628)
- The User Account Mappings view ("[Map User Accounts to User Groups \(User Account Mapping Form\)](#)" below)
- The [nnmsecurity.ovpl](#) command line tool

Map User Accounts to User Groups (User Account Mapping Form)

To assign User Accounts to User Groups use the following instructions. See "[About User Account Mappings](#)" on page 581.




The NNMi administrator must assign each User Account to a predefined NNMi User Group before that user can access NNMi. See ["User Groups Provided in NNMi" on page 618](#) for more information.

Tip: NNMi administrators can also use the Security Wizard and to complete this task. See ["Map User Accounts and User Groups" on page 628](#).

To assign a User Account to a User Group:

1. [Navigate to the User Accounts Mappings view:](#)
 - a. From the workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Account Mappings**.
2. Do one of the following:
 - To create a new configuration, click the *** New** icon, and continue.
 - To edit an existing configuration, double-click the Mappings definition you want to edit, and continue.
 - To delete a Mapping, see ["Delete a User Account" on page 613](#).
3. Make your configuration choices. See the [User Account Mapping Attributes](#) table.







Tip: NNMi can be configured to use the Lightweight Directory Access Protocol (LDAP) and X.509 Certificates such as Public Key Infrastructure (PKI) user authentication for NNMi user names, passwords, and User Group Membership assignments. Additional steps are required. See ["Choose a Mode for NNMi Access" on page 570](#).

4. Click the  **Save and Close** icon to save your changes and return to the **User Accounts Mappings** view.

Note: If you create a User Account to User Group mapping for an NNMi user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed

out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

User Account Mapping Attributes

Attribute	Description
User Group	<p>In the User Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none">• To create new User Group, click the  New icon and provide the required information. (See "Configure User Groups (User Group Form)" on page 621 for more information.)• To select an NNMi User Group configuration, click the  Quick Find icon and make a selection.
User Account	<p>In the User Account attribute, click the  Lookup icon.</p> <ul style="list-style-type: none">• To create new User Account, click the  New icon and provide the required information. See "Configure User Accounts (User Account Form)" on page 611 for more information.)• To select an NNMi User Group configuration, click the  Quick Find icon and make a selection. <p>Note: If you map a User Account to two or more NNMi User Groups, NNMi gives the User Account the privileges associated with each mapped NNMi User Group.</p>



Remove a User from a User Group (User Account Mapping)

Only NNMi administrators can add and delete accounts and change NNMi User Accounts and User Groups. See ["About User Account Mappings" on page 581](#).

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Create and Delete User Accounts Using the Security Wizard" on page 616](#) or [nnmsecurity.ovpl](#).

To remove a user from an NNMi User Group:

Note: Removing a user from a User Group does not delete the User Account or User Group.

1. Navigate to the **User Account Mappings** view.
 - a. From the Workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **User Account Mappings**.
2. Select the row representing the User Account mapping you want to change.
3. Delete the User Account mapping by clicking the  Delete icon.
4. Click  **Save and Close**.


Note: If you change the User Account mapping for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

Remove User Accounts from User Groups

Tip: NNMi administrators can also use the User Account Mappings view or command line to complete this task. See ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624](#) or [nnmsecurity.ovpl](#).

To remove a User Account mapping from a User Group:

Note: When you remove a User Account from a User Group, you are only deleting the mapping between the two. You are not deleting the User Account or User Group from the NNMi database. See ["About User Account Mappings" on page 581](#) for more information.

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
2. Navigate to the **User Account Mapping** table.
3. Select the row that contains the User Account and User Group mapping you want to delete.
4. Click  **Delete**.
5. Repeat steps 3 and 4 to delete each mapping.
6. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Map User Accounts and User Groups

You can map User Accounts and User Groups using either the Security Wizard main page or using a pop-up dialog box.

- Use the Security Wizard main page:

["Assign User Accounts to User Groups Using the Security Wizard Page" on page 630](#)

["Assign User Groups to User Accounts Using the Security Wizard Page" below](#)

- Use the  pop-up dialog box:


["Assign User Accounts to User Groups Using the Security Wizard Dialog Box" on page 631](#)

["Assign User Groups to User Accounts Using the Security Wizard Dialog Box" on the next page](#)

Assign User Groups to User Accounts Using the Security Wizard Page

Tip: You can also use the Security Wizard pop-up dialog box to complete this task. See ["Assign User Groups to User Accounts Using the Security Wizard Dialog Box" on the next page](#) for more information.

When using the wizard main page to assign User Groups to User Accounts, note the following (see ["About User Account Mappings" on page 581](#) for more information):


- The **User Account Mapping** table displays the mapping that applies to the selected User Account or User Group.
- Double-click a row or select a row and click  to use the **Assign User Groups to User Accounts** dialog box instead of the Wizard main page.
- Your configuration changes are not saved until you click the **Save and Close** button:

Save & Close

Tip: NNMi administrators can also use the User Account Mappings view or command line to complete this task. See ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624](#) or [nnmsecurity.ovpl](#).

To assign User Groups to User Accounts using the wizard main page:

To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
2. Select a row in the **User Accounts** table.
3. In the **User Groups** table, click the  left arrow in the row of the User Account you want to assign to the selected User Group.

The selected User Group and User Account names appear in the **User Account Mapping** table.

4. Repeat steps 2 and 3 to assign each User Group you want to the User Account.
5. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign User Groups to User Accounts Using the Security Wizard Dialog Box

Tip: You can also use the Security Wizard main page to complete this task. See ["Assign User Groups to User Accounts Using the Security Wizard Page" on the previous page](#) for more information.


Note the following (see ["About User Account Mappings" on page 581](#) for more information):

- When you select a row in the **User Groups** table, NNMi filters the **User Accounts** table to display only those User Accounts that are not assigned to the selected User Group.
- When you select a row in the **User Accounts** table, NNMi filters the **User Groups** table to display only those User Groups to which the selected User Account has not been assigned.

Tip: NNMi administrators can also use the User Account Mappings view or command line to complete this task. See ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624](#) or [nnmsecurity.ovpl](#).

To assign User Groups to User Accounts using the wizard pop-up dialog box:


To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** page, select the **Map User Accounts and User Groups** option.
2. In the **User Accounts** table in the wizard page, double-click the User Account to which you want to assign User Groups or select a row and click  to use the **Assign User Groups to User Accounts** dialog instead of the Wizard page.
3. In the wizard dialog box, select a row in the **Available User Groups** table.


4. Click the  right arrow.

The selected User Group Name appears in the **Assigned to User Groups** table.

5. Repeat steps 3 and 4 to assign each User Group you want to the selected User Account.

6. Click **Close**  to close the dialog box.

7. When you finish, click the **Save and Close** button to save your security configuration:




Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign User Accounts to User Groups Using the Security Wizard Page

Tip: You can also use the Security Wizard pop-up dialog box to complete this task. See ["Assign User Accounts to User Groups Using the Security Wizard Dialog Box" on the next page](#) for more information.

When using the wizard main page to assign User Accounts to User Groups, note the following (see ["About User Account Mappings" on page 581](#) for more information):

- The **User Account Mapping** table displays the mapping that applies to the selected User Account or User Group.
- Double-click a row or select a row and click  to use the **Assign User Accounts to User Groups** dialog instead of the Wizard page.
- Your configuration changes are not saved until you click **Save and Close**.

For more information about User Accounts, see ["About User Account Mappings" on page 581](#).

Tip: NNMi administrators can also use the User Account Mappings view or command line to

complete this task. See ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624](#) or [nnmsecurity.ovpl](#).

To assign User Accounts to User Groups using the wizard main page:

To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** page, select the **Map User Accounts and User Groups** option.
2. Select a row in the **User Accounts** table.

3. In the **User Groups** table, click the  left arrow in the row of the User Group you want to assign to the selected User Account.

The User Account and User Group names appear in the **User Account Mappings** table.

4. Repeat steps 2 and 3 to assign each User Account you want to a User Group.
5. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign User Accounts to User Groups Using the Security Wizard Dialog Box

Tip: You can also use the Security Wizard main page to complete this task. See ["Assign User Accounts to User Groups Using the Security Wizard Page" on the previous page](#) for more information.


Note the following (see ["About User Account Mappings" on page 581](#) for more information):

- When you select a row in the **User Accounts** table, NNMi filters the **User Groups** table to display only those User Groups to which the selected User Account has not been assigned.
- When you select a row in the **User Groups** table, NNMi filters the **User Accounts** table to display only those User Accounts that are not assigned to the selected User Group.

Tip: NNMi administrators can also use the User Account Mappings view or command line to complete this task. See ["Map User Accounts to User Groups \(User Account Mapping Form\)" on page 624](#) or [nnmsecurity.ovpl](#).

To assign User Accounts to User Groups using the wizard pop-up dialog box:

To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** main page, select the **Map User Accounts and User Groups** option.
2. In the **User Groups** table in the wizard main page, double-click the User Group to which you want to assign User Accounts or select a row and click  to use the **Assign User Accounts to User Groups** dialog instead of the Wizard page.
3. Select a row in the **Available User Accounts** table.

4. Click the  right arrow.

The selected User Account name appears in the **Assigned to User Accounts** table.

5. Repeat steps 2 through 4 to assign each User Account you want to the User Group.
6. Click **Close** to close the dialog box.
7. In the wizard main page, when you finish your security configuration, click **Save and Close** to save your configuration changes.

Security Group Tasks

NNMi administrators can configure Security Groups to limit node access by using the following methods:

- The Configuration Wizard ("[Create and Delete Security Groups Using the Security Wizard](#)" on [the next page](#))
- The Security Accounts view ("[Configure Security Groups \(Security Group Form\)](#)" below)
- The [nnmsecurity.ovpl](#) command line tool

Configure Security Groups (Security Group Form)

Required only for Operator or Guest users:

Security Groups enable NNMi administrators to identify groups of nodes that require the same access level. See "[About Security Groups](#)" on [page 582](#) for more information.



Use the **Security Groups** form to create, edit, or delete a Security Group.

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See "[Create and Delete Security Groups Using the Security Wizard](#)" on [the next page](#) or [nnmsecurity.ovpl](#).

To configure a Security Group, do the following:

1. [Navigate to the Security Groups view.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **Security Groups**.

Tip: You can filter the Security Groups table view by User Group.

2. Do one of the following:
 - To create a new configuration, click the  **New** icon.
 - To edit an existing configuration, double-click the Security Groups definition you want to edit.
3. Make your configuration choices. (See the [Security Group Attributes](#) table.)
4. Click  **Save and Close** to apply your changes.
5. See ["Methods for Assigning Nodes to Security Groups" on page 636](#).

Security Group Attributes

Attribute	Description
Name	Enter the name that uniquely identifies this Security Group. Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
UUID	NNMi assigns a Universally Unique Object Identifier to the Security Group. This UUID is unique across all databases.
Description	Type a maximum of 2048 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Related Topics

["Configure Tenants" on page 213](#)

["About Multi-Tenancy and Global Network Management" on page 100](#)



Create and Delete Security Groups Using the Security Wizard


Required only for Operator or Guest users:

See ["About Security Groups" on page 582](#) for more information.

Tip: NNMi administrators can also use the Security Groups view or command line to complete this task. See ["Configure Security Groups \(Security Group Form\)" on page 632](#), or [nrmsecurity.ovpl](#).


To create Security Groups:

1. From the **Security Wizard** main page, do one of the following:
 - a. Select the **Map User Groups and Security Groups** option.
 - b. Select the **Assign Nodes to Security Groups** option.
2. Navigate to the **Security Groups** table.
3. Click  **New**.
4. In the **Create Security Group** dialog box, enter the following:
 - a. **Name:** Enter the name that uniquely identifies this Security Group. Type a maximum of 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
 - b. **Description:** Type a maximum of 2048 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
5. Click **Add**.
6. Repeat Step 4 and 5 to add each Security Group.
7. When you finish adding Security Groups, in the **Create Security Group** dialog box, click **Close** .
8. When you finish, click the **Save and Close** button to save your security configuration:



Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

To delete Security Groups:

1. Select a row in the **Security Groups** table.
2. Click  **Delete**.
3. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign Nodes to Security Groups

Required only for Operator or Guest users:

When assigning nodes to Security Groups, note the following (see ["About Security Groups" on page 582](#) for more information):

- When you select a row in the **Security Groups** table, NNMi filters the **Nodes Assigned to Security Group** table to display only those nodes that are assigned to the selected Security Group.
- Your configuration changes are not saved until you click **Save and Close**.

Tip: NNMi administrators can also use other methods to complete this task. See ["Methods for Assigning Nodes to Security Groups" on the next page](#) including [nnmsecurity.ovpl](#).

To assign nodes to a Security Group:

1. From the **Security Wizard** main page, select the **Assign Nodes to Security Groups** option.
2. Select a row in the **Security Groups** table.
3. In the **Available Nodes** table, do one of the following:
 - a. Select a Node Group in the Node Group filter drop-down list or select a column filter to specify the nodes to be assigned to the Security Group.
 - b. User Ctrl-Click to select each node you want to assign to the selected Security Group.

4. Click  to specify that you want to assign the selected nodes to the Security Group.

The **Nodes to be Assigned to Selected Group** table displays the list of nodes to be assigned to the selected Security Group.

5. Repeat steps 2 through 4 to assign nodes to a selected Security Group.
6. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Methods for Assigning Nodes to Security Groups

When NNMi discovers nodes in your network environment, Tenant and Security Group settings are established in the following manner:

- **Discovery Seeds:** If Nodes are discovered as Discovery seeds, the NNMi administrator specifies a Tenant for each Discovery Seed. See ["Specify Discovery Seeds" on page 287](#). When NNMi administrators define a Tenant, they specify an **Initial Discovery Security Group**. Any newly discovered Node within the defined Tenant is assigned to this Security Group. NNMi administrators can change either the node's Tenant or Security Group assignment or both at any time.

Nodes assigned to the *Default Security Group* are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

Nodes within one Tenant can each be assigned to different Security Groups, and Nodes within one Security Group each be assigned to different Tenants.

- **Auto-Discovery for Default Tenant:** When you configure Auto-Discovery Rules, NNMi assigns any Nodes discovered using those Auto-Discovery Rules to the *Default Tenant* and whichever Security Group is currently configured as the Default Tenant's Initial Discovery Security Group setting (the *Default Security Group* out-of-box). See ["Configure Tenants" on page 213](#).

Global Network Management: Regional Managers forward information about Nodes to the Global Manager. The Global Manager's copy of the Node object has the same Tenant assignment as the Regional Manager's record of that Node.

In a Global Network Management environment, best practice is to have the NNMi administrators for the Global Manager and all Regional Managers agree to a predefined list of Tenant names. Those Tenants would be defined on the Regional Managers, the Tenant definitions exported, and those Tenant definitions imported onto the Global Manager (thus ensuring that the UUID and name value for each Tenant match on both NNMi management servers). The NNMi administrator on the Global Manager update their Tenant definitions to assign Initial Discovery Security Group values that make sense for the Global Manager's team. See ["About Multi-Tenancy and Global Network Management" on page 100](#) for more information.

Note: If a Regional Manager forwards information about a Node to the Global Manager, and that Node is assigned to a Tenant object that does not exist on the Global Manager, NNMi creates a Tenant with the UUID and name from the Regional Manager, but creates a new Security Group with that Tenant name (does not duplicate the Regional Manager's setting for that Tenant's *Initial Discovery Security Group* setting). NNMi maps that new Security Group to the following:

- User Group = NNMi Administrator
- Object Access Privilege = Object Administrator

The Global Manager's NNMi administrator can assign a *different* Initial Discovery Security Group to a Tenant definition at any time. From that point onward, the NNMi Global Manager uses that new Initial Discovery Security Group setting when creating new nodes within that Tenant.

NNMi administrators can change the Security Group assignment for Node objects using the following methods:

- Use the Security Wizard, ["Assign Nodes to Security Groups"](#) on page 635.
- Use the [nnmsecurity.ovpl](#) command line tool.
- Use the Node form. However, until an NNMi Administrator defines at least one Security Group in addition to those provided out-of-box by NNMi:
 - The Security Group attribute does not appear on any Node form.
 - The Security Group column does not appear in the [Nodes \(All Attributes\) view](#).

The screenshot shows the 'Nodes' window with the 'Node' tab selected. The 'Basics' section contains the following fields:

Name	node-name
Hostname	10.2.0.30
Management Address	10.2.0.30
Status	Major
* Node Management Mode	Managed
Device Profile	hpRouter
* Tenant	Default Tenant
* Security Group	Default Security Group

The 'Security Group' field is highlighted with a red rectangle. Each field with an asterisk has a dropdown arrow icon to its right.

Tip: NNMi administrators can use Security Groups in [Node Group definitions](#) that become filters in NNMi views. If an NNMi user cannot access any nodes in a particular Node Group, that filter dynamically disappears from the filter selection list in the NNMi views.

Security Group Mapping Tasks

NNMi administrators can map User Groups to Security Groups using the following methods:

- The Configuration Wizard ("[Map User Groups and Security Groups](#) " on page 644)
- The Security Accounts view ("[Map User Groups to Security Groups \(Security Group Mapping Form\)](#)" below)
- The [nnmsecurity.ovpl](#) command line tool


Map User Groups to Security Groups (Security Group Mapping Form)

Required only for Operator or Guest users:







See "[About Security Group Mappings](#)" on page 583 for more information.

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See "[Map User Groups and Security Groups](#) " on page 644 and [nnmsecurity.ovpl](#).

To assign a User Group to a Security Group :

1. Navigate to the **Security Group Mappings** view.
 - a. From the workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **Security Group Mappings**.
 - d. Double-click the row representing the Security Group mapping you want to edit.
2. Make your configuration choices. (See the [Security Group Mapping Attributes](#) table.)
3. Click  **Save and Close** to save your changes and return to the **Security Group Mappings** view.

Security Group Mapping Attributes

Attribute	Description
User Group	<p>Specify the User Group to be assigned to the Security Group.</p> <p>In the User Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none"> To create new User Group, click the  New icon and provide the required information. (See "Configure User Groups (User Group Form)" on page 621 for more information.) To select an NNMi User Group configuration, click the  Quick Find icon and make a selection.
Security Group	<p>Specify the Security Group to be assigned to the User Group.</p> <p>In the Security Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none"> To create new Security Group, click the  New icon and provide the required information. See "Configure Security Groups (Security Group Form)" on page 632 for more information. To select an Security Group configuration, click the  Quick Find icon and make a selection.
Object Access Privilege	<p>Determines the level of access each User Account in the User Group has to the nodes assigned to its Security Group.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>For example:</p> <ul style="list-style-type: none"> With <i>Object Operator Level 2</i> access, users can run the MIB Browser's SNMP Walk commands. With <i>Object Administrator</i> access, users can also run the MIB Browser's SNMP Set commands. </div> <p>In the Object Access Privilege attribute, select a privilege level from the drop-down list. NNMi provides the following privileges:</p> <ul style="list-style-type: none"> Object Administrator Object Operator Level 2 Object Operator Level 1 (with more limited access privileges than Level 2) Object Guest <p>See "Object Access Privileges Provided in NNMi" on the next page for more information.</p>

Object Access Privileges Provided in NNMi

As an NNMi administrator, when you map User Groups to Security Groups, you also determine the Object Access Privilege.

The Object Access Privilege determines the level of access each User Account in the User Group has to the nodes associated with the assigned Security Group. See ["Control Menu Access" on page 649](#) and ["Actions Provided by NNMi" on page 41](#) for more information.

NNMi provides the following Object Access Privileges. Each can be used in any number of Security Group Mappings:

- Object Administrator
- Object Operator Level 2
- Object Operator Level 1 (with more limited access privileges than Level 2)
- Object Guest

You cannot change the Object Access Privileges definitions that NNMi provides.

For more information about access control, see the following topics:

- ["About Security Group Mappings" on page 583](#)
- ["Determine which NNMi User Group to Assign" on page 619](#) (Use to control access to views and forms.)
- ["Control Menu Access" on page 649](#) (NNMi administrators control which roles can access a small subset of Action menu items. The [NNMi Role](#)¹ is assigned to a User Account through the NNMi User Group.
- ["Configure Basic Settings for a Node Group Map" on page 552](#) (For each Node Group Map, the **Minimum NNMi Role for Saving Map Layout** attribute setting controls the minimum user role required for saving the layout after the user repositions nodes on the map.)

Remove User Groups from Security Group Mappings

Only NNMi administrators can change Security Group mappings. See ["About Security Group Mappings" on page 583](#).

Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Remove User Groups from Security Group Mappings " on page 648](#) or [nmmsecurity.ovpl](#).



¹Determined by your membership in one of four special NNMi User Groups (NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators, or NNMi Guest Users). This membership determines what you can see and do within the NNMi console.

To remove a User Group from a Security Group Mapping:

Note: Removing the User Group from a Security Group deletes the mapping between the two (not the User Group or Security Group from the NNMi database).

1. Navigate to the **Security Group Mappings** view.
 - a. From the Workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **Security Group Mappings**.
2. Select the row representing the Security Group mapping you want to change.

Note: By default, all users assigned to the predefined [NNMi User Group](#)¹s see all nodes discovered by NNMi (see ["User Groups Provided in NNMi" on page 618](#)). To prevent this, delete the Security Group Mapping for NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), NNMi Level 2 Operators, and NNMi Guest. Then, create one or more Security Groups and remap those User Groups to the appropriate Security Group.

3. To delete the Security Group mapping, click the  Delete icon.
4. Click  **Save and Close**.

Note: If you change the Security Group mapping for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#).

Change the User Group to Security Group Assignment

Required only for Operator or Guest users:

Only NNMi administrators can change Security Group mappings. See ["About Security Group Mappings" on page 583](#).




Tip: NNMi administrators can also use the Security Wizard or command line to complete this task. See ["Remove User Groups from Security Group Mappings" on page 648](#) or

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

nnmsecurity.ovpl.







To change the User Group to Security Groups assignment use the following instructions:

Note: To change a User Group to Security Group assignment, you first delete the existing Security Group mapping.

1. Navigate to the **Security Group Mappings** view.
 - a. From the workspaces navigation panel, select the **Configuration** workspace.
 - b. Expand **Security**.
 - c. Select **Security Group Mappings**.
2. Select the row representing the Security Group mapping you want to change.
3. Delete the Security Group mapping by clicking the  Delete icon.
4. Select the  New icon to configure the new Security Group mapping.
5. Make your configuration choices. (See the [Security Group Mapping Attributes](#) table.)
6. Click  **Save and Close** to save your changes and return to the **Security Group Mappings** view.

Note: If you change the User Group to Security Group mapping for a user who is currently signed into the NNMi console, the change does not take effect until the next time the user signs in. By default, the NNMi timeout limit is 18 hours. If a user has not signed out within 18 hours, NNMi forces the user to sign out. To change the Console Timeout value, see ["Configuring the NNMi User Interface" on page 524](#)

Security Group Mapping Attributes

Attribute	Description
User Group	<p>Specify the User Group to be assigned to the Security Group.</p> <p>In the User Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none"> To create new User Group, click the  New icon and provide the required information. (See "Configure User Groups (User Group Form)" on page 621 for more information.) To select an User Group configuration, click the  Quick Find icon and make a selection.
Security Group	<p>Specify the Security Group to be assigned to the User Group.</p> <p>In the Security Group attribute, click the  Lookup icon.</p> <ul style="list-style-type: none"> To create new Security Group, click the  New icon and provide the required information. See "Configure Security Groups (Security Group Form)" on page 632 for more information. To select an NNMi Security Group configuration, click the  Quick Find icon and make a selection.
Object Access Privilege	<p>Determines the level of access each User Account in the User Group has to the nodes assigned to its Security Group.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>For example:</p> <ul style="list-style-type: none"> With <i>Object Operator Level 2</i> access, users can run the MIB Browser's SNMP Walk commands. With <i>Object Administrator</i> access, users can also run the MIB Browser's SNMP Set commands. </div> <p>In the Object Access Privilege attribute, select a privilege from the drop-down list. NNMi provides the following privileges:</p> <ul style="list-style-type: none"> Object Administrator Object Operator Level 2 Object Operator Level 1 (with more limited access privileges than Level 2) Object Guest <p>See "Object Access Privileges Provided in NNMi" on page 640 for more information.</p>

Map User Groups and Security Groups

Required only for Operator or Guest users:

You can map User Groups and Security Groups using either the Security Wizard main page or using a pop-up dialog box.

- Use the Security Wizard main page:

["Assign User Groups to Security Groups Using the Security Wizard Page" on page 646](#)

["Assign Security Groups to User Groups Using the Security Wizard Page" below](#)

- Use the  pop-up dialog box:

["Assign User Groups to Security Groups Using the Security Wizard Dialog Box" on page 647](#)


["Assign Security Groups to User Groups Using the Security Wizard Dialog Box" on the next page](#)

Assign Security Groups to User Groups Using the Security Wizard Page

Required only for Operator or Guest users:

Tip: You can also use the Security Wizard pop-up dialog box to complete this task. See ["Assign Security Groups to User Groups Using the Security Wizard Dialog Box" on the next page](#) for more information.

When using the wizard main page to assign Security Groups to User Groups, note the following (see ["About Security Group Mappings" on page 583](#) for more information):


- The **Security Group Mapping** table displays the mapping that applies to the selected User Group or Security Group.
- Double-click a row or select a row and click  to use the **Assign Security Groups to User Groups** dialog instead of the Wizard page.
- Your configuration changes are not saved until you click the **Save and Close** button:

Save & Close

Tip: NNMi administrators can also use the Security Group Mappings view or command line to complete this task. See ["Map User Groups to Security Groups \(Security Group Mapping Form\)" on page 638](#) or [nnmsecurity.ovpl](#).

To assign Security Groups to User Groups using the wizard main page:

To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** page, select the **Map User Groups and Security Groups** option.
2. Select a row in the **Security Groups** table.
3. In the **User Groups** table, click the  right arrow in the row of the User Group you want to assign to the selected Security Group.

The Security Group and User Group names appear in the **Security Group Mapping** table.

4. Repeat steps 2 and 3 to assign each Security Group you want to a User Group.
5. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign Security Groups to User Groups Using the Security Wizard Dialog Box

Required only for Operator or Guest users:


Tip: You can also use the Security Wizard main page to complete this task. See "[Assign Security Groups to User Groups Using the Security Wizard Page](#)" on the previous page for more information.

See "[About Security Group Mappings](#)" on page 583 for more information.

Tip: NNMi administrators can also use the Security Group Mappings view or command line to complete this task. See "[Map User Groups to Security Groups \(Security Group Mapping Form\)](#)" on page 638 or [nnmsecurity.ovpl](#).

To assign Security Groups to User Groups using the wizard pop-up dialog box:

To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** page, select the **Map User Groups and Security Groups** option.
2. In the **User Groups** table in the wizard main page, double-click the User Group to which you want to assign Security Groups or select a row and click  to use the **Assign Security Groups to User Groups** dialog instead of the Wizard page.
3. In the wizard dialog box, select a row in the **Available Security Groups** table.

4. Click the  right arrow.

The selected Security Group Name appears in the **Assigned to Security Groups** table.

5. Repeat steps 2 through 4 to assign each Security Group you want to the User Group.
6. Click **Close** to close the dialog box.
7. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close


Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign User Groups to Security Groups Using the Security Wizard Page

Required only for Operator or Guest users:

Tip: You can also use the Security Wizard pop-up dialog box to complete this task. See ["Assign User Groups to Security Groups Using the Security Wizard Dialog Box" on the next page](#) for more information.

When using the wizard main page to assign User Groups to Security Groups, note the following (see ["About Security Group Mappings" on page 583](#) for more information):


- The **Security Group Mapping** table displays the mapping that applies to the selected User Group or Security Group.
- Double-click a row or select a row and click  to use the **Assign User Groups to Security Groups** dialog instead of the wizard main page.
- Your configuration changes are not saved until you click the **Save and Close** button:

Save & Close

Tip: NNMi administrators can also use the Security Group Mappings view or command line to complete this task. See ["Map User Groups to Security Groups \(Security Group Mapping Form\)" on page 638](#) or [nnmsecurity.ovpl](#).

To assign User Groups to Security Groups using the wizard main page:

Tip: To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Select a row in the **User Groups** table.
3. In the **Security Groups** table, select the  left arrow in the row of the Security Group you want to assign to the selected User Group.

The User Group and Security Group names appear in the **Security Group Mapping** table.

4. Repeat steps 2 and 3 to assign each User Account you want to a User Group.
5. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Assign User Groups to Security Groups Using the Security Wizard Dialog Box

Required only for Operator or Guest users:

Tip: You can also use the main Security Wizard page to complete this task. See ["Assign User Groups to Security Groups Using the Security Wizard Page" on the previous page](#) for more information.



See ["About Security Group Mappings" on page 583](#) for more information.

Tip: NNMi administrators can also use the Security Group Mappings view or command line to complete this task. See ["Map User Groups to Security Groups \(Security Group Mapping Form\)" on page 638](#) or [nnmsecurity.ovpl](#).

To assign User Groups to Security Groups using the wizard pop-up dialog box:

Tip: To select multiple rows, use Ctrl-Click.

1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.

2. In the **Security Groups** table in the wizard page, double-click the Security Group to which you want to assign User Groups or select a row and click  to use the **Assign User Groups to Security Groups** dialog instead of the Wizard page.
3. In the wizard dialog box, select a row in the **Available User Groups** table.
4. Click the  right arrow.

The selected User Group Name appears in the **Assigned to User Groups** table.
5. Repeat steps 3 and 4 to assign each User Group you want to the Security Group.
6. Click **Close** to close the dialog box.
7. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close


Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Remove User Groups from Security Group Mappings

Tip: NNMi administrators can also use the Security Group Mappings view or the command line to complete this task. See ["Remove User Groups from Security Group Mappings" on page 640](#) or [nnmsecurity.ovpl](#).

When the NNMi administrator removes a User Group from a Security Group Mapping, NNMi only deletes the mapping between the two (not the User Group or Security Group from the NNMi database). See ["About Security Groups" on page 582](#) for more information.

To remove a User Group from a Security Group Mapping:


1. From the **Security Wizard** main page, select the **Map User Groups and Security Groups** option.
2. Navigate to the **Security Group Mapping** table.
3. Select the row that contains the User Group and Security Group mapping you want to delete.
4. Click  **Delete**.
5. Repeat steps 3 and 4 to delete each mapping.
6. When you finish, click the **Save and Close** button to save your security configuration:

Save & Close

Note: NNMi does not save any configuration changes until you click **Save and Close** to save your security configuration.

Control Menu Access

Access to the [Tools](#) and [Actions](#) menu items is controlled by Security Group Mapping configuration settings: User Group, Security Group, and *Object Access Privilege*



See ["Determine which NNMi User Group to Assign" on page 619](#) for additional information about User Group limitations. See ["Object Access Privileges Provided in NNMi" on page 640](#) and ["Actions Provided by NNMi" on page 41](#) for additional information about *Object Access Privileges*.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Note the following:

- User Groups determine access to NNMi console workspaces, views and forms. User Groups also determine the Tools and Actions that the users in the User Group can access.
- You MUST assign each User Account to one of the predefined [NNMi User Group](#)¹s before that user can access NNMi. See ["User Groups Provided in NNMi" on page 618](#) for more information.
- If you map a User Account to two or more NNMi User Groups, NNMi gives the User Account the privileges associated with each User Group to which the User Account is assigned.
- Security Groups are optional and control (through User Groups) which Users can access a node and its hosted objects, such as an interface. Each node is associated with only one Security

¹ NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Group.

Note: Users see only those members of an object group (for example, Node Group or Router Redundancy Group) for which they have access. If a user cannot access any nodes in the group, the group is not visible to that user.

- Object Access Privileges are associated only with Security Groups and their associated User Groups. Object Access Privileges determine the Tools and Actions that the User Group can access for the nodes they are permitted to view.
 - If a User Account is assigned an NNMi User Group with *more privileges* than the Object Access Privilege, the user sees all of the actions available for the User Group (not restricted because of the Object Access Privilege setting). For example, if a User Account is assigned to the User Group **NNMi Level 2 Operators** and has an Object Access Privilege of **Object Operator Level 1** (with more limited access privileges than Level 2 Operators) for a set of nodes, the operator sees all actions available to Level 2 Operators.
 - If a User Account is assigned an NNMi User Group with *less privileges* than the Object Access Privilege, the user will not see all of the actions available for the Object Access Privilege. For example, if a User Account is assigned to the User Group **NNMi Level 1 Operators** (with more limited access privileges than Level 2 Operators) and has an Object Access Privilege of **Object Operator Level 2** for a set of nodes, the operator will see only those actions available to Level 1 Operators. As an NNMi administrator, you must do either of the following:
 - Configure the **Menu Item Context Basic Details** to change the **Required NNMi Role** for the menu item
 - Assign the operator User Account to the **NNMi Level 2 Operators** User Group.
- All menu items are visible to users with a role that can use the items, but an *Access Denied* message displays when any user with insufficient Object Access privileges tries to use a menu item. For example, both Level 1 or Level 2 Operators are denied access to the Communication Settings action.
- You can restrict access to certain Launch Actions (provide tighter security than those enforced by the default settings). See ["Configure Menu Item Context Basic Details" on page 1459](#) for more information about configuring actions.
- If the menu item does not require node access, (for example, **Status Details** for a Node Group) NNMi uses the privileges assigned to the NNMi User Group that is mapped to the User Account.

User Group and Object Access Privilege Required for the Tools Menu:

Access to the NNMi Tools menu items is determined by User Group and the Security Group Object Access Privilege that is set for the node. Also see ["Actions Provided by NNMi" on page 41](#). [Click here](#) for information about Tools Menu Access Limitations.

NNMi Tools Menu Access Limitation

Tools Menu Item	NNMi User Group	Object Access Privilege
Find Node	NNMi Guest Users	Object Guest
Find Attached Switch Port	NNMi Level 2 Operators	Object Operator Level 2
Incident Actions Log	NNMi Administrators	Object Administrator
Load /Unload MIB	NNMi Administrators	Object Administrator
MIB Browser	NNMi Level 2 Operators	Object Operator Level 2 for SNMP Walk Object Administrator for SNMP Set
NNMi Audit Log	NNMi Administrators	Object Administrator
NNMi Self-Monitoring Graphs	NNMi Administrators	Object Administrator
NNMi Status	NNMi Level 1 Operators	Object Operator Level 1
Restore All Default View Settings	NNMi Guest Users	Object Guest
Security Reports	NNMi Administrators	Object Administrator
Status Distribution Graphs	NNMi Level 2 Operators	Object Operator Level 2
Trap Analytics	NNMi Administrators	Object Administrator
Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information .		

NNMi Tools Menu Access Limitation, continued

Tools Menu Item	NNMi User Group	Object Access Privilege
Upload Local MIB File	NNMi Administrators	Object Administrator
Visio Export Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) – click here for more information .	NNMi Level 2 Operators	Object Operator Level 2

User Group and Object Access Privilege Required for the Actions Menu:

Access to the NNMi Actions menu is determined by User Group and the Security Group Object Access Privilege that is set for the node. [Click here](#) for more information about URL Action Access Limitations.

URL Action Access Limitations

Action Menu Item	Submenu Item	NNMi User Group	Object Access Privilege
Configuration Details	Communication Settings	NNMi Administrators	Object Administrator
Configuration Details	Monitoring Settings	NNMi Level 1 Operators	Object Operator Level 1
Custom Attributes		NNMi Administrators	Object Administrator
Graphs		NNMi Level 1 Operators	Object Operator Level 1
Management Mode		NNMi Level 2 Operators	Object Operator Level 2
MIB Information	MIB Browser	NNMi Level 2 Operators	Object Operator Level 2 for SNMP Walk Object Administrator for SNMP Set
MIB Information	List Supported MIBs	NNMi Level 2 Operators	Object Operator Level 2
Node Access	Ping (from server)	NNMi Level 1 Operators	Object Operator Level 1
Node Access	Secure Shell (from client)	NNMi Level 2	Object Operator Level 2

URL Action Access Limitations, continued

Action Menu Item	Submenu Item	NNMi User Group	Object Access Privilege
		Operators	
Node Access	Traceroute (from server)	NNMi Level 1 Operators	Object Operator Level 1
Node Access	Telnet...(from client)	NNMi Level 2 Operators	Object Operator Level 2
Node Group Details	Show All Incidents	NNMi Level 1 Operators	Object Operator Level 1
Node Group Details	Show Members (Include Child Groups)	NNMi Level 1 Operators	Object Operator Level 1
Node Group Details	Preview Members (Current Group Only)	NNMi Level 1 Operators	Object Operator Level 1
Node Group Details	Status Details	NNMi Level 1 Operators	Object Operator Level 1
Node Group Details	Show All Open Incidents	NNMi Level 1 Operators	Object Operator Level 1
Node Group Membership		NNMi Administrators	Object Administrator
Polling	Configuration Poll	NNMi Level 2 Operators	Object Operator Level 2
Polling	Status Poll	NNMi Level 2 Operators	Object Operator Level 2
Show Attached End Nodes		NNMi Level 1 Operator	Object Operator Level 1

See [Investigate and Diagnose Network Problems](#) for more information about these actions.

Note: Each Tools and Action menu item provided by NNMi is also associated with a *default NNMi Role*. (To determine the *default NNMi Role* assigned to each Action menu item, see ["Actions Provided by NNMi" on page 41](#).) If you change the setting for a Menu Item provided by NNMi to a Role that is a *lower level Role* than the *default NNMi Role* assigned to the menu item, NNMi ignores that change. Any User Group with the lower level Role than the *default NNMi Role* cannot access the menu item.

Set Up Command Line Access to NNMi

NNMi limits access to Command Line Interface (CLI) commands in one of two ways:

- Method One: Requiring User Name and Password.
- Method Two: Requiring permission to access NNMi as the system user.

See **Help** → **Documentation Library** → **Reference Pages** for a list of command line commands. Check the appropriate Reference Page to determine which method applies.

Method One: Requiring User Name and Password.

There are two strategies for CLI user name and password:

- Providing the appropriate NNMi User Name attribute value and NNMi Password attribute value within the CLI syntax (-u and -p).
- Configuring a valid NNMi User Name attribute value and NNMi Password attribute value using the `nnmsetcmduserpw.ovpl` command. See **Help** → **Documentation Library** → **Reference Pages** for details.

Note: With `nnmsetcmduserpw.ovpl`, the CLI command must then be run on the same machine where the `nnmsetcmduserpw.ovpl` command was executed.

Method Two: Requiring permission to access NNMi as the system user.

During NNMi installation, the first access to the NNMi console requires a special system User Name and Password. Thereafter, only the following situations are appropriate for the system user:

- The CLI you are using runs only when executed by the special NNMi system user.
- If your network environment uses X.509 Certificates such as Public Key Infrastructure (PKI) user authentication, all NNMi CLI commands must be executed by the special NNMi system user. See the “Configuring NNMi to Support Public Key Infrastructure User Authentication” chapter in the *HP Network Node Manager i Software Deployment Reference* for more information, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.
- For Troubleshooting purposes when mistakes were made that result in zero NNMi users being mapped to the [NNMi User Group¹: NNMi Administrators](#). For more information, see ["Restore the Administrator NNMi Role" on page 666](#).

If method two is required, your CLI command must be issued from the NNMi management server and you must have *read* access to the following file on the NNMi management server: `nms-users.properties`

Caution: Any user with *read* access to the `nms-users.properties` file can potentially sign

¹ NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

into the NNMi console and perform Administrator operations.

Note the following for Public Key Infrastructure (PKI) user authentication to provide NNMi User Name and NNMi Password:

- If you are logged into the operating system as root user, NNMi automatically accesses the system User Account and runs the command using the NNMi system user's credentials.
- If you are logged into the operating system with a user name other than root and your user name is not configured for *read* access to the `nms-users.properties` file, NNMi cannot run the CLI command.

Communicate Console Access Information to Your Team

After configuring user passwords and roles, communicate the following information to your team:

- ["Open the NNMi Console" below](#)
- ["Configuring Sign-In to the NNMi Console" on page 657](#)
- ["Sign Out from the Console" on page 658](#)

Open the NNMi Console

Provide each user with the following information:

`http://<serverName>:<portNumber>/nnm/`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

When your NNMi management server has more than one fully-qualified domain name, NNMi chooses one during the installation process. There are two ways to find out which domain name NNMi is using in your network environment:

- Click **Help** → **System Information** and navigate to the **Server** tab. Locate the **Official Fully Qualified Domain Name (FQDN)** attribute value.
- Use the `nnmofficialfqdn.ovpl` command. See the [nnmofficialfqdn.ovpl](#) Reference Page.

To determine the current port number configuration, look at the following lines in the `nms-local.properties` file (see the following table for the location of this file):

- For http, see `nmsas.server.port.web.http`
- For https, see `nmsas.server.port.web.https`

See the [nnm.ports](#) Reference Page and ["About Environment Variables" on page 86](#) for more information.

Determine the NNMi Console Port Number

Operating System	Identify Current Port Number
Windows	<code>%NnmDataDir%\conf\nnm\props\nms-local.properties</code>
Linux	<code>\$NnmDataDir/conf/nnm/props/nms-local.properties</code>

Communicate the following browser requirements for your team to use the NNMi console:

- Pop-ups, cookies, and JavaScript must be enabled.
- Each user's screen resolution must be 1024x768 pixels or higher.
- When using Microsoft Internet Explorer as your browser, you can access multiple browser sessions of NNMi. Use a different user name for each browser session.
- When using Mozilla Firefox as your browser, multiple browser sessions all point to the same window.

Note: Users can bookmark the URL for the NNMi console. Use the URL for the NNMi console rather than the NNMi Welcome page. See [About the NNMi Console](#) for more information about the NNMi console.

To open the console:

1. Type the following URL (Uniform Resource Locator) into your browser navigation bar:

`http://<serverName>:<portNumber>/nnm/`

2. Sign in with the following name and password:

`<name you configured>`

`<password you configured>`

Tip: Tip: You can include name and password in the URL. See ["Launch the Console \(showMain\)" on page 1526](#)

3. Click the **Sign In** button. (See ["Configuring Sign-In to the NNMi Console" below](#) if you need more information.)
4. The console opens in a new window.
5. *Optional.* Close the NNMi Welcome page.

Note: If you do not close the NNMi Welcome page or sign out, you can relaunch the console from the NNMi Welcome Page without signing in again.

To refresh the console window:

Click the  Refresh icon in the tool bar of any NNMi window.

Configuring Sign-In to the NNMi Console


After entering the URL to access the NNMi console (provided by your NNMi administrator), one of the following happens:

- NNMi prompts you to sign into the console:
 - a. At the **User Name** prompt, enter the user name that was provided by your NNMi administrator.
 - b. At the **Password** prompt, enter the password that was provided by your NNMi administrator.
 - c. Click the **Sign In** button.
- If your network environment uses X509 Certificates such as Public Key Infrastructure (PKI) user authentication, the NNMi console opens immediately without requesting a User Name or Password.

Note: The NNMi administrator must configure NNMi to acknowledge your network environment's Public Key Infrastructure (PKI) setup. The PKI configuration maps certificates to NNMi User Accounts. After PKI is configured, NNMi reads the PKI certificate to obtain the NNMi user name information. Steps required to sign in to the NNMi console with certificate validation depend on the user environment. Be sure to communicate these requirements to your team. The NNMi administrator must still define User Accounts within NNMi or configure NNMi to use Lightweight Directory Access Protocol (LDAP), see ["X.509 Certificates to Control NNMi Access" on page 573](#). For more information about PKI configuration, see "Configuring NNMi to Support Public Key Infrastructure User Authentication" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals..>

(*NNMi Advanced*) Single Sign-On (SSO) can be configured to enable access to an NNMi Regional Manager through the NNMi Global Manager. For more information about SSO, see “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*.

After a user accesses the NNMi console, the User Account name and the highest associated object access privilege appear in the upper right corner of the console as shown in the example below:



Sign Out from the Console

To sign out from the console:

1. Select **File** → **Sign Out**.
2. Click **OK**.

Note the following:

- Sign in is not preserved across user sessions. After signing out, each user must sign in again.
- You must sign out of each browser session that is running NNMi. For example, if you have signed in twice with two different browsers, signing out in one browser does not cause you to lose access in the other browser.
- By default, NNMi automatically signs out any user after 18 hours of inactivity. The NNMi administrator can configure this amount of time. See ["Configuring the NNMi User Interface" on page 524](#).

Chapter 12: Troubleshoot NNMi Access


Tip: Select **Help** → **System Information** to view the User Name, NNMi Role, and User Group for the current NNMi session.

NNMi provides several tools to help you troubleshoot and monitor NNMi access:

- ["Check Security Configuration" on page 661](#)
- ["View the Users who are Signed In to NNMi" on page 663](#)
- ["Audit NNMi User Sign-In and Sign-Out Activity" on page 663](#)
- ["Restore the Administrator NNMi Role" on page 666](#)
- ["Restore NNMi Access for the system User" on page 666](#)

Out-of-box, NNMi Security works in the following manner:

- NNMi assigns all nodes to the Default Security Group.
- NNMi operators and guests can see all discovered nodes and all incidents, because of the default Security Group Mappings:



User Group	Security Group	Object Access Privilege
NNMi Guest Users	Default Security Group	Object Guest
NNMi Guest Users	Unresolved Incidents	Object Guest
NNMi Level 1 Operators	Default Security Group	Object Operator Level 1
NNMi Level 1 Operators	Unresolved Incidents	Object Operator Level 1
NNMi Level 2 Operators	Default Security Group	Object Operator Level 2
NNMi Level 2 Operators	Unresolved Incidents	Object Operator Level 2

Tip: NNMi administrators always see all nodes and incidents, no Security Group Mappings are required for NNMi administrators.

NNMi administrators can limit access to nodes and incidents by deleting the default (out-of-box) Security Group Mappings. Then no operators or guests can access any nodes until an NNMi administrator explicitly adds new, more restrictive Security Group Mappings. When these out-of-

box Security Group Mappings are removed, the predefined [NNMi User Group](#)¹s provide access to the NNMi console only, rather than to the NNMi console and to all nodes. See ["Remove User Groups from Security Group Mappings" on page 640](#) for more information.

Security Group Mappings have three settings:

- [User Group](#) identifies the *NNMi users*.
- [Security Group](#) identifies *a set of nodes* (and indirectly their hosted objects).
- [Object Access Privilege](#) determines the level of access that each User Account in the User Group has to the nodes in the associated Security Group.

Each node is associated with one and only one Security Group. NNMi operators and guests can view a node only if one of the User Groups to which that NNMi user belongs is associated with that node's Security Group.

When NNMi discovers nodes in your network environment, Tenant and Security Group settings are established in the following manner:

- **Discovery Seeds:** If Nodes are discovered as Discovery seeds, the NNMi administrator specifies a Tenant for each Discovery Seed. See ["Specify Discovery Seeds" on page 287](#). When NNMi administrators define a Tenant, they specify an **Initial Discovery Security Group**. Any newly discovered Node within the defined Tenant is assigned to this Security Group. NNMi administrators can change either the node's Tenant or Security Group assignment or both at any time.

Nodes assigned to the *Default Security Group* are visible from all views. To control access to a device, assign that device to a Security Group other than Default Security Group.

Nodes within one Tenant can each be assigned to different Security Groups, and Nodes within one Security Group each be assigned to different Tenants.

- **Auto-Discovery for Default Tenant:** When you configure Auto-Discovery Rules, NNMi assigns any Nodes discovered using those Auto-Discovery Rules to the *Default Tenant* and whichever Security Group is currently configured as the Default Tenant's Initial Discovery Security Group setting (the *Default Security Group* out-of-box). See ["Configure Tenants" on page 213](#).

Global Network Management: Regional Managers forward information about Nodes to the Global Manager. The Global Manager's copy of the Node object has the same Tenant assignment as the Regional Manager's record of that Node.

In a Global Network Management environment, best practice is to have the NNMi administrators for the Global Manager and all Regional Managers agree to a predefined list of Tenant names. Those Tenants would be defined on the Regional Managers, the Tenant definitions exported, and those

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Tenant definitions imported onto the Global Manager (thus ensuring that the UUID and name value for each Tenant match on both NNMi management servers). The NNMi administrator on the Global Manager update their Tenant definitions to assign Initial Discovery Security Group values that make sense for the Global Manager's team. See ["About Multi-Tenancy and Global Network Management" on page 100](#) for more information.

Note: If a Regional Manager forwards information about a Node to the Global Manager, and that Node is assigned to a Tenant object that does not exist on the Global Manager, NNMi creates a Tenant with the UUID and name from the Regional Manager, but creates a new Security Group with that Tenant name (does not duplicate the Regional Manager's setting for that Tenant's *Initial Discovery Security Group* setting). NNMi maps that new Security Group to the following:

- User Group = NNMi Administrator
- Object Access Privilege = Object Administrator

The Global Manager's NNMi administrator can assign a *different* Initial Discovery Security Group to a Tenant definition at any time. From that point onward, the NNMi Global Manager uses that new Initial Discovery Security Group setting when creating new nodes within that Tenant.

Node revisions: NNMi administrators can change the Node's initial Security Group assignment. See ["Methods for Assigning Nodes to Security Groups" on page 636](#).

Tip: NNMi administrators can use Security Groups in [Node Group definitions](#) that become filters in NNMi views. If a user cannot access any nodes in a particular Node Group, that filter dynamically disappears from the filter selection list in the user's NNMi views. See ["Specify Node Group Additional Filters" on page 330](#) for more information about Node Group filters.

Security influences incidents:

- Network operators and guests can view incidents associated with a node only if that user's User Account is mapped to one of the User Groups that are mapped to the node's Security Group. See ["About Security Groups" on page 582](#) and ["About Security Group Mappings" on page 583](#).
- Any incident that does not have an associated node is assigned to the **Unresolved Incidents** Security Group and NNMi's out-of-box configuration makes these incidents visible to all User Groups. Examples of incidents that are unresolved include unresolved traps, system health, and license violation incidents.
- Operators should only be assigned incidents for nodes they can access.

Check Security Configuration

Each NNMi user can be assigned to multiple Security Group Mappings. The *Object Access Privilege* determines what NNMi users can do with a node object. For example, if their User Group is **NNMi Level 2 Operators**, but the Object Access Privilege is **Object Operator Level 1** (with

more limited access privileges than Level 2), each user assigned to the Security Group Mapping sees all of the actions available to a Level 2 Operator, but can run only those *actions allowed* for Level 1 Operators. If an NNMi user is assigned to multiple Security Group Mappings, that user sees all the parts of NNMi that are provided to the highest User Group setting and access for each node is determined by the node's Security Group Mapping.

NNMi administrators can generate a report of possible Security configuration problems:

- Users Accounts that are not mapped to a User Group
- User Accounts that are not mapped to an NNMi User Group
- User Accounts that have unusual NNMi role combinations
- Security Groups that include nodes from multiple tenants
- Empty User Groups and Security Groups
- Tenants with the same name
- Security Groups with the same name

Generate the report using any of the following methods:

- **Tools → Security Report**
- The [nnmsecurity.ovpl](#) command

You can also use the [View Summary of Changes](#) option in the Security Wizard to view a report based on only your latest configuration changes.

View Summary of Changes in the Security Wizard

Use the Security Wizard **View Summary of Changes** option to view your recent configuration changes, including the following:

- The User Accounts created.
- The User Groups created.
- The Security Groups created.
- The User Accounts and User Groups mappings.
- The User Groups and Security Groups mappings.
- The Security Groups that have new nodes assigned to them.

To view the summary of security configuration changes:

From the **Security Wizard** main page, select the **View Summary of Changes** option.

NNMi displays a summary of the configuration changes made since you last saved your changes.

View the Users who are Signed In to NNMi

Use the **Tools** → **Signed in Users** menu option to view a list of the NNMi users who are currently signed in to NNMi. This tool is useful when you want to determine which users and systems are available. For example, you might want to view the users who are signed in before shutting down a system.

To see the list of users who are currently signed in to NNMi:

Select **Tools** → **Signed In Users**.

NNMi displays the number of users currently signed in to NNMi as well as each user name, IP address of the client that is running the NNMi console, and the time in which the user signed in to NNMi.

Audit NNMi User Sign-In and Sign-Out Activity

NNMi tracks a history of sign-in and sign-out activity for each NNMi user.

NNMi stores the sign-in/sign-out log files in the following directory (see ["About Environment Variables" on page 86](#)):

Windows

`%NnmDataDir%\log\nnm`

Linux

`$NnmDataDir/log/nnm`

NNMi names these log files `signin.log`. Any archived log file has a number appended to the end of the file name, for example `signin.log.%g`.

- *signin* is the log file base name
- *%g* represents the archive number of the archived log file

The highest appended archive number represents the oldest file. A log file can become an archived log file after the size of the log file exceeds the configured limit. After a log file exceeds the configured limit, the last active log file is archived. For example, after NNMi archives the `nnm.log` file as the `nnm.log.1` file, NNMi begins logging to a new `nnm.log` file. Each archive file's name is incremented by one each time a new archive becomes the `nnm.log.1`.

To see the most recent sign-in audit report:

1. A tool is available to NNMi administrators. In the console menu bar, select **Tools** → **Sign In/Out Audit Log**.

Note: If you do not see the **Tools** → **Sign In/Out Audit Log** option, you must enable the log file.

2. The log provides a variety of information about recent account activity. For example:

```
Sign In/Sign Out Audit Log
Jun 14, 2007 10:53:01.926 AM [ThreadID:719]com.hp.ov.nms.ui.framework...

SignInOutAuditLog logSignIn:

INFO: Successful Sign In
User Account: system
NNMi Role: Administrator (ADMIN)
Remote Host: <node IP address>
Remote Port: 1549
Locale: en_US
Sign In/Out Audit Since 6/14/07 9:33 AM
=====
Currently Signed In:
#1: system <node IP address> 6/14/07 10:53 AM (last access 6/14/07 10:53 AM)
No users currently signed out.
```

To enable the audit log files:

Tip: When making file changes under HA, you must make the changes on both nodes in the cluster. For NNMi using HA configurations, if the change requires you to stop and restart the NNMi management server, you must put the nodes in maintenance mode before running the ovstop and ovstart commands.

1. In a text editor, open the nnm-logging.properties file (see ["About Environment Variables" on page 86](#)):
 - **Windows:**
%NnmDataDir%\shared\nnm\conf\props\nnm-logging.properties
 - **Linux:**
\$NnmDataDir/shared/nnm/conf/props/nnm-logging.properties
2. Search for the text block containing the following line:

com.hp.ov.nnm.log.signin.level = OFF.
3. Modify the line to read as follows:


com.hp.ov.nnm.log.signin.level = INFO
4. *Optional:* Add the following two configuration settings if they do not already exist:
 - Set the total number of audit log files, for example 4:
com.hp.ov.nnm.log.signin.count = <count value>

- Set the maximum size for the audit log files, for example 20M (20 megabytes):
`com.hp.ov.nnm.log.signin.size = <file size value>`
- 5. Save and close the `nnm-logging.properties` file.
- 6. From the command line, use the `ovstop` command to stop NNMi.
- 7. From the command line, use the `ovstart` command to restart NNMi.

Audit NNMi User Actions

Tip: See ["Audit NNMi User Sign-In and Sign-Out Activity" on page 663](#) for information about auditing user sign-in and sign-out activity.

By default, NNMi audits user actions that result in changes to the NNMi database. These kinds of user actions include, but are not limited to, the following:

- Changes to NNMi topology objects (for example, nodes, node groups, interfaces, and interface groups) . Examples include creating or deleting Node Groups or Interface Groups, and changing filters or membership in a Node Groups or Interface Groups.
- Changes to incident lifecycle information. Examples include changing an incident's owner or state.
- Changes to user and access information. Example include changing passwords, adding or deleting a user account or user group, and creating tenants.
- Configuration changes made using the NNMi console  **Configuration** workspace or a command line tool. Example include modifications to SNMP settings, discovery settings, and monitoring configuration.
- User actions from the NNMi console **Actions** menu. Examples include Configuration Poll and Status Poll.

The auditing log files reside in the following directory (see ["About Environment Variables" on page 86](#)):

Tip: As an NNMi administrator you can also view the most current audit log from the NNMi console **Tools > NNMi Audit Log** menu option.

- **Windows:**
`%NnmDataDir%\nmsas\NNM\log\audit-<date>.log`
- **Linux:**
`$NnmDataDir/nmsas/NNM/log/audit-<date>.log`

Note: NNMi auditing is enabled by default.

See "NNMi Auditing" in the *HP Network Node Manager i Software Deployment Reference* at <http://h20230.www2.hp.com/selfsolve/manuals> for more information.

Restore the Administrator NNMi Role

If you have accidentally configured NNMi so that zero NNMi users are mapped to the [NNMi User Group](#)¹: NNMi Administrators (preventing anyone from being able to access the Configuration workspaces), access the NNMi console as the system user to correct the problem.

Sign into the console using the password that was configured for the system user when NNMi was first installed.

If you do not remember the password assigned to the system user, use the [nnmchangesyspw.ovpl](#) command to reset the system user's password.

Note: If you are still unable to sign into the console, verify that the `nms-roles.properties` file is in good working order. See ["Restore NNMi Access for the system User"](#) below for more information.

Restore NNMi Access for the system User

NNMi provides an `nms-roles.properties` file that stores part of the system user configuration. This file is located in the following directory:

- **Windows:**
`%NmInstallDir%\nmsas\NNM\conf\props\nms-roles.properties`
- **Linux:**
`$NmInstallDir/nmsas/NNM/conf/props/nms-roles.properties`

You should not need to ever modify this file.

To verify the contents of this file:

1. With a text editor, open the `nms-roles.properties` file.
2. Verify that the following required line is present:

```
system = system,admin
```

3. Save and close the file.

¹NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Chapter 13: Configuring Incidents

Incidents are information that NNMi considers important to bring to your attention regarding your network. See ["How NNMi Gathers Incidents" on the next page](#) for more information.

NNMi provides a set of incident configurations for the following:

- Traps generated from an SNMP agent (SNMPv1, SNMPv2c, or SNMPv3)
- Syslog Messages
- Management incidents that are generated by NNMi

See ["Incident Configurations Provided by NNMi" on page 688](#) for more information about the configurations provided.

Note: If a node is deleted, only an NNMi administrator can view the incidents associated with that node.

NNMi provides one centralized location, the incident views, where the management events, SNMP traps, and Syslog Message Incidents are visible to your team. You control which SNMP traps and Syslog Messages are considered important enough to show up as incidents. You can also configure how incidents that are generated by NNMi are displayed. You and your team can easily monitor the incidents and take appropriate action to preserve the health of your network.

You can modify the incident configurations provided by NNMi or create new incident configurations. To do so, see the following topics:

Tip: See ["Configure a Correlation Rule" on page 771](#) and ["Configure a Causal Rule" on page 808](#) for information about creating incidents for use in Custom Correlations.

- ["Configure SNMP Trap Incidents" on page 886](#)
- ["Configure Syslog Message Incidents \(HP ArcSight\)" on page 1068](#)
- ["Configure Management Events" on page 1236](#)
- Using the Pairwise Configuration form, you can configure pairwise correlations. See ["About Pairwise Configurations" on page 746](#) for more information.

Caution: If you make changes to an incident configuration provided by NNMi, those changes are at risk of being overwritten in the future. See [Author form](#) for important information.

You can also use the Incident Configuration form to define relationships between multiple incidents by creating deduplication and rate configurations. See ["Manage the Number of Incoming Incidents" on page 739](#), ["Correlate Duplicate Incidents \(Deduplication Configuration\)" on page 745](#), and ["Track Incident Frequency \(Rate: Time Period and Count\)" on page 746](#), for more information.

You can use the Incident Configuration form to control how NNMi handles incoming SNMP traps. See ["Handle Unresolved Incoming Traps" on page 878](#) and ["Control which Incoming Traps Are Visible in Incident Views" on page 877](#) for more information.

Note: Each time you stop and restart ovjboss, any incidents that have not yet been correlated or persisted are lost. This means that after a restart of ovjboss, an incoming incident might not be correlated as expected. For example, after a restart of ovjboss, a duplicate incident might not be correlated under its original parent incident. Instead, a new parent incident might be generated. See ["Stop or Start an NNMi Process" on page 87](#) for more information about starting and stopping the ovjboss process.

Manage Incidents Using Incident Configurations

NNMi enables you to control the incidents that are generated and how they are displayed. To help you manage your incidents and incident configurations, you want to understand the following:

- ["How NNMi Gathers Incidents" below](#)
- ["How NNMi Closes Incidents" on page 687](#)
- ["Incident Configurations Provided by NNMi" on page 688](#)

When managing your incidents using Incident Configurations, you can perform the following tasks:

- ["Manage the Number of Incoming Incidents" on page 739](#)
- ["Track Incident Frequency \(Rate: Time Period and Count\)" on page 746](#)
- ["Configure an Action for an Incident" on page 847](#)
- ["Configure Diagnostics for an Incident" on page 857](#)

How NNMi Gathers Incidents

Incidents are information that NNMi considers important to bring to your attention regarding your network.


The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an **Origin** of **NNMi** in your incident views. See [Using the Incident Form](#) for more information about incident attributes.

NNMi gathers information from the sources described in the following table.

Incidents Collected by NNMi

Information Source	Description
State Poller	Tracks changes in State for an object. See Accessing Device Details for more information about possible States per object.
SNMP Traps	Traps are unsolicited SNMP notifications that come from your network devices. The NNMi Causal Engine uses this information as symptoms during its analysis. SNMP traps can also appear as incidents if configured to do so, using the NNMi incident configuration feature. See "Configure SNMP Trap Incidents" on page 886 for more information.
Conclusions	Every Conclusion has a Severity associated with it. The Status reported for an object is the most severe of all outstanding Conclusions. In addition, Conclusions inform the user of the underlying cause (or reason) for an object's Status. A Conclusion generates an associated Incident if it is determined to be the root cause of a problem.

[Click here](#) to view a diagram of the relationship among Conclusions, States (from State Poller), and Incidents.



See ["The NNMi Causal Engine and Incidents" on the next page](#) for an overview of what the NNMi Causal Engine does with the information collected. See ["About the Event Pipeline" on page 685](#) for an overview of the event pipeline path each trap or NNMi event takes before NNMi creates an incident. This chronological path guarantees that the data is analyzed in chronological order.

Note: The Causal Engine also sends incident information that it generates through the event pipeline to guarantee the chronological order for determining its root cause incidents.

By default, NNMi includes preconfigured definitions for SNMP traps, Syslog Messages and the incidents generated by the NNMi Causal Engine. See [Incident Views Provided by NNMi](#) for more information.

Related Topics

["Configure SNMP Trap Incidents" on page 886](#)

["Configure Syslog Message Incidents \(HP ArcSight\)" on page 1068](#)

["Configure Management Events" on page 1236](#)

["Incident Configurations Provided by NNMi" on page 688](#)


["Manage the Number of Incoming Incidents" on page 739](#)

The NNMi Causal Engine and Incidents

The Causal Engine extensively evaluates network issues and determines the root cause for you, whenever possible, sending incidents to notify you of problems.

The NNMi Causal Engine defines root cause in terms of symptoms. To do so, it uses a set of rules to define relationships for fault and performance (thresholding) symptoms and root causes. Sources of symptom information include SNMP traps and the monitoring information from the State Poller, which includes an object's State. See ["The NNMi Causal Engine and Object Status" on page 672](#) and ["How NNMi Gathers Incidents" on page 668](#) for more information.


[Click here](#) to view a diagram of the relationship among Incidents, Conclusions, States, and Status.



The NNMi Causal Engine performs the following tasks:

- Generates notifications about problems.
- Generates conclusions that relate to the root cause of the problem.

- Determines whether the incident should be correlated or suppressed.

Tip: An incident that is correlated with a Root Cause Parent Incident has a Correlation Nature of  **Secondary Root Cause**. These incidents can be examined using the **All Incidents** view, but do not appear as Key Incidents or Root Cause incidents. See [Incident Views Provided by NNMi](#) for more information.

Incident *correlation* scenario ([click here](#))

The NodeDown incident correlates the InterfaceDown incident from one-hop neighbor interfaces, according to the following scenario:

When an interface goes down, a NodeDown episode begins for the neighboring node, which exists for the duration of 300 seconds.

Within that duration, if the node goes down, the InterfaceDown incident is correlated with the NodeDown incident.

The InterfaceDown incidents from all one-hop neighbors are correlated with the NodeDown incident. The network operator can review the InterfaceDown incidents as supporting evidence for the NodeDown incident.

Incident *suppression* scenario ([click here](#))

The AddressNotResponding incident is suppressed by the InterfaceDown incident, according to the following scenario:

When an IPv4 address stops responding to ICMP, an episode begins, which exists for the duration of 60 seconds.

Within that duration, if the interface associated with that IPv4 address goes down, the Causal Engine concludes that the interface down condition caused the IPv4 address to stop responding.

Therefore, the AddressNotResponding incident is not generated. Only the InterfaceDown incident is generated.

To ensure that the InterfaceDown incident is detected within the duration, the Causal Engine issues a named poll for that interface. The incident enables the network engineer to fix the root cause of the problem which, in this case, is the interface.

If the interface does not go down during the episode, the Causal Engine generates an AddressNotResponding incident. If the interface goes down after the episode, NNMi generates the InterfaceDown incident. In this case, the network engineer has to treat the two problems separately.

- Closes incidents that are no longer valid (for example, when a "Cold Start" trap is received a short time after a "Node Down" incident was generated because a device was recently rebooted).

- Creates a parent-child relationship between incidents that are all related to one problem (for example, a "Node Down" incident contains a child "Interface Down" incident for each neighboring interface of the node).
- Creates parent-child relationships between incidents that are correlated using the Custom Correlation configuration. NNMi's Custom Correlation feature enables administrators to add customized rules for when and how to correlate incidents. See ["Configure Custom Correlations" on page 769](#) for more information.

The Causal Engine actively solicits symptoms during analysis and reacts dynamically to topology changes. The Causal Engine uses the following three stages to help determine and display root cause incidents and their related conclusions.

NNMi Causal Engine Stages

Causal Engine Stages	Description
Condition Listener	Collects symptoms from NNMi processes and services.
Hypothesis engine	Analyzes these symptoms to determine relationships until a root cause is reached.
Blackboard	Based on the information sent by the hypothesis engine, the blackboard updates a device's status and posts any related incidents.

The NNMi Causal Engine analyzes the health of your network and provides the ongoing health Status reading for each object it monitors. See ["The NNMi Causal Engine and Object Status" below](#) and ["The NNMi Causal Engine and Monitoring" on page 390](#) for more information.

Related Topics


["The NNMi Causal Engine and Object Status" below](#)

The NNMi Causal Engine and Object Status

The Causal Engine sets the Status on relevant network objects. Status indicates the overall health of an object and is determined from the outstanding Conclusions. Every Conclusion has a Severity associated with it. The Status reported is the most severe of all outstanding Conclusions. In addition, Conclusions inform the user of the underlying cause (or reason) for an object's Status.

See the Conclusion Tab information for each object form in [Accessing Device Details](#) for information about possible Conclusions for each NNMi object.

[Click here](#) to view a diagram of the relationship among Incidents, Conclusions, States, and Status.



The Causal Engine uses the following Status categories in decreasing order of severity:

- Unknown
- Disabled
- Critical
- Major
- Minor
- Warning
- Normal
- No Status

To determine why an object is not polled (No Status), do the following:

- Select the object from the table or map view and access **Actions** → **Configuration Details** → **Monitoring Settings**.
- Select the node of interest or the node that is hosting the object of interest from the table or map view and access **Actions** → **Configuration Details** → **Communication Settings**.






NNMi analyzes a variety of network objects using either the SNMP protocol or ping to retrieve information about the network object. The following list shows the network objects that NNMi monitors and analyzes. Click each object for more information.

- [Aggregator Interface \(NNMi Advanced\)](#)

An Aggregator Interfaces is a set of interfaces on a switch that are linked together, usually for

the purpose of creating a trunk (high bandwidth) connection to another device. Aggregator Interfaces have designated Aggregation Member Interfaces.

NNMi reports that Status of an Aggregator Interface as follows:


 Unknown	The Status of all Aggregation Members of the Aggregator Interface are Unknown.
 Critical	The Aggregator Interface, or all of the Aggregation Members, or both are operationally down. This means ifOperStatus is down.
 Minor	Some Aggregation Members (but not all Aggregation Members) of the Aggregator Interface are operationally down. This means the ifOperStatus is down.
 Normal	All Aggregation Members of the Aggregator Interface are operationally up. This means ifOperStatus is up.
 No Status	All Aggregation Members of the Aggregator Interface are not polled.

- **Aggregator Layer 2 Connection (NNMi Advanced)**

An Aggregator Layer 2 Connection is a connection with endpoints that are Aggregator Interfaces. These are usually high-bandwidth connections that link switches. Aggregator Layer 2 Connections have Aggregator Interfaces and Aggregation Members.


[Click here](#) to see example Link Aggregations.

On a Layer 2 map, a thick line with a superimposed ellipse represents a [Link Aggregation](#)¹ or [Split Link Aggregation](#)² (group of multiple Layer 2 Connections that are functioning as one). The icon representing an Interface at either end of the thick line is an Aggregator Interface (a *logical* interface comprised of many physical interfaces that are functioning as one).



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.



NNMi reports the Status of an Aggregator Layer 2 Connection as follows:





Unknown	The Status of any Aggregation Member of the Aggregator Layer 2 Connection is Unknown.
Critical	The Aggregator Interface, the Aggregation Member, or both are operationally down. This means ifOperStatus is down.
Minor	Some Aggregation Members, but not all, are operationally down. This means ifOperStatus is down.
Normal	All Aggregation Members of the Aggregator Layer 2 Connection are operationally up. This means ifOperStatus is up.
No Status	All Aggregation Members of the Aggregator Layer 2 Connection are not polled.

- Card**

A card is a physical component on a device which generally has physical ports that contain one or more interfaces used to connect to other devices. A card can also contain sub-cards. The card containing another card is known in NNMi as the Parent Card. The sub-card is known as a Daughter Card. NNMi supports Daughter cards one level deep.

NNMi reports the status of a Card as follows:







Unknown	Indicates the SNMP Agent associated with the Card does not respond to SNMP queries.
Disabled	The Card or Child Card is administratively down or disabled. This means the cardAdminStatus is down.

 Critical	The Card is operationally down. This means the cardOperStatus is down.
 Minor	The Card is neither up nor down. This means the cardOperStatus is unknown or other.
 Normal	The Card is operationally up. This means the cardOperStatus is up.
 No Status	The Card is not polled.

- **Card Redundancy Group**

A Card Redundancy Group is a set of card modules that are configured to provide card redundancy on the device. These cards are management modules on Cisco and HP Procurve platforms. The number of cards supported in a group on both platforms is two. The Card Redundancy Group has one card acting as the primary member, the other acting as the secondary. If the primary card fails, the secondary card takes over as the primary card.








NNMi reports the Status of Card Redundancy Groups as follows:

 Unknown	All cards in the Card Redundancy Group have an Unknown Status.
 Critical	Indicates either of the following: <ul style="list-style-type: none"> ◦ No Card is acting as the Primary member of the Card Redundancy Group. ◦ Both Cards are acting as the Primary member of the Card Redundancy Group.
 Major	At least one card in the group is reporting a state that indicates it is neither the Primary nor Secondary card.
 Warning	The Card Redundancy Group has no Secondary member.
 Normal	The Card Redundancy Group is functioning correctly.
 No Status	No Status - The Card Redundancy Group has not yet been discovered or is not being polled.

- **Chassis**

A Chassis is a physical component on a device into which other objects are plugged, such as cards. A Chassis can also contain sub-chassis. The Chassis containing another Chassis is known in NNMi as the Parent Chassis. The sub-chassis is known as the Child Chassis. A Child Chassis can be one-level deep. NNMi supports the following scenarios: A single node running on one chassis Multiple nodes running on one chassis A single node running on multiple chassis Chassis are connected by Inter Switch Links (ISL). A port used for the Inter Switch Link is designated with the Type **IRF physical port** and is associated with the card or chassis on which it resides.

NNMi reports the status of a Chassis as follows:




 Unknown	Indicates the SNMP Agent associated with the Chassis does not respond to SNMP queries.
 Critical	The Chassis is operationally down. This means the operStatus is down.
 Major	The Chassis operStatus is not down, and all cards in the chassis have the cardOperStatus of down.
 Minor	The Chassis operStatus is not down, and more than one card but not all cards have the cardOperStatus of down
 Warning	The Chassis operStatus is not down, and one card in the chassis has the cardOperStatus of down.
 Normal	The operStatus of the chassis is up, and all cards in the chassis have the cardOperStatus of up.
 No Status	The chassis and all of its cards are not polled.



- **Chassis Redundancy Group**

A Chassis Redundancy Group is a set of chassis that are configured to provide redundancy (for example, for switches). Each redundancy group member is discovered as a Chassis managed by a node. Each Chassis Redundancy Group member has one of the following roles:

- Master - Indicates the chassis is the master member of the Chassis Redundancy Group.
- Slave - Indicates the chassis is a slave member of the Chassis Redundancy Group.

NNMi reports the status of Chassis Redundancy Groups as follows:








 Major	No Chassis in the Chassis Redundancy Group has a standby State value of SLAVE.
 Minor	Indicates either of the following: <ul style="list-style-type: none"> ■ At least one of the Inter Switch Links (ISL) between the Chassis in the Chassis Redundancy Group is down. ■ NNMi determined the following: <ul style="list-style-type: none"> ○ One Chassis has a MASTER State ○ One Chassis has a SLAVE State ○ Other Chassis in the group are not in SLAVE State
 Warning	At least one of the Inter Switch Links (ISL) between the Chassis in the Chassis Redundancy Group is degraded.

 Normal	The Chassis Redundancy Group is functioning correctly.
 No Status	The Chassis Redundancy Group is not being polled.

- **Connections**

Connections are Layer 2 physical connections and Layer 3 network connections. NNMi discovers connection information by reading forwarding database (FDB) tables from network devices and gathering data from a variety of Layer 2 *discovery protocols* (see the list of Topology Source protocols in [Layer 2 Connection Form](#)).

NNMi reports the Status of Layer 2 physical connections as follows:

 Unknown	All endpoints of the connection have unknown status.
 Disabled	Any one endpoint of the connection is disabled.
 Critical	All endpoints are operationally down.
 Minor	Any one endpoint is down.
 Warning	Endpoints have unknown and non-critical Status.
 Normal	All endpoints are operationally up.
 No Status	All endpoints are not polled.


Note:






- Pseudo interfaces do not affect Connection Status. See [Interfaces \(All Attributes\) View \(Inventory\)](#) for more information about pseudo interfaces.
- Connections on Layer 3 maps never have status.

- **Field Replaceable Units (FRU Card)**

A Field-Replaceable-Unit (FRU) card is a card that can be replaced on a device that is operationally active (not powered down). When an FRU card is removed from or added to the device, NNMi reports the occurrence with an incident. If an FRU card is not recognized by the device, NNMi reports the unrecognized card with an incident.

NNMi reports the Status of an FRU Card as follows:

 Unknown	Indicates either of the following: <ul style="list-style-type: none">■ The SNMP Agent associated with the card does not respond to SNMP queries.
---	--

	<ul style="list-style-type: none"> ■ NNMi cannot determine the cardOperStatus or cardAdminStatus values.
 Disabled	The Card is administratively down. This means the cardAdminStatus is down.
 Critical	The Card is operationally down. This means the cardOperStatus is down.
 Minor	The Card is neither up nor down. This means the cardOperStatus is either unknown or other.
 Normal	The Card is operationally up. This means the cardOperStatus is up.
 No Status	The Card is not being polled.






• Interface

An interface is a logical object that might or might not be associated with a physical port. Interfaces are used to identify connections between nodes. Multiple interfaces can be associated with a single physical port. NNMi identifies interfaces using either of the following values:

- ifName
- ifAlias
- ifType[ifIndex] (for example, ethernetCsmacd[17])

Each physical port managed by NNMi is associated with one or more interfaces. NNMi identifies ports using the *<Card-number / Port-number>* value.





NNMi reports the Status of Interfaces as follows:

 Unknown	<p>Indicates either of the following:</p> <ul style="list-style-type: none"> ■ The SNMP Agent associated with the interface does not respond to SNMP queries. ■ NNMi cannot determine the health because ifAdminStatus and ifOperStatus cannot be measured.
 Disabled	Interface is administratively down. This means ifAdminStatus is down.
 Critical	Interface is operationally down. This means ifOperStatus is down.
 Normal	Interface is operationally up. This means ifOperStatus is up.
 No Status	Interface is not polled.

- **IP Address**

An IP address is a routable address that responds to ICMP. IP addresses are typically associated with nodes.

NNMi reports the status of a IP Addresses as follows:

 Disabled	The interface associated with this IP address is administratively down or disabled.
 Critical	IP address does not respond to ICMP queries (ping the device).
 Normal	IP address responds to ICMP queries.
 No Status	IP address is not polled.

- **Node**




A node is a device that NNMi finds as a result of the Spiral Discovery process. A node can contain interfaces, boards, and ports. You can separate nodes into two categories:




- Network nodes, which are active devices such as switches, routers, bridges, and hubs



Note: These nodes can be physical or virtual and can represent one or more additional objects, such as a switch stack.

- End nodes, such as Linux or Windows servers

NNMi typically manages network nodes, reporting Status as follows:

 Unknown	Indicates SNMP node is unresponsive due to either of the following circumstances: <ul style="list-style-type: none">■ The SNMP Agent associated with the node does not respond to SNMP queries and the polled IP addresses do not respond to ICMP queries■ The polled IP addresses associated with the non-SNMP node does not respond to ICMP queries
 Disabled	Indicates a neighbor interface has been disabled, causing the node to be unreachable.
 Critical	Indicates any one of the following: <ul style="list-style-type: none">■ The node is down as determined by neighbor analysis.■ The node is marked as important and is unresponsive (NNMi cannot access the node from the NNMi management server).








	<ul style="list-style-type: none"> ■ The node is unconnected (it has no neighbors) and, therefore, is unresponsive. ■ NNMi cannot determine if the node is down or if the incoming connection is down. ■ At least one Custom Polled Instance associated with the node has a Status of Critical and Custom Polled Instances are configured to affect Node Status.
 Minor	<p>A managed object in the Node has any of the following problems:</p> <ul style="list-style-type: none"> ■ The SNMP Agent associated with the Node does not respond to SNMP queries. ■ The management address on the Node is not responding to ICMP. ■ One or more interfaces on the Node are operationally down. This means <code>ifOperStatus</code> is down. ■ One or more IP addresses on the Node do not respond to ICMP. ■ NNMi is unable to measure the Status of one or more Cards on the Node. This means the <code>cardOperStatus</code> is either unknown or other. ■ At least one Interface on the Node has a threshold outside the range specified for the device. ■ At least one Custom Polled Instance associated with the Node has a Status of Minor and Custom Polled Instances are configured to affect Node Status. ■ One or more cards in the Node are operationally down. This means <code>cardOperStatus</code> is down.
 Warning	<p>A managed object on the Node has any of the following problems:</p> <ul style="list-style-type: none"> ■ At least one Card in a Card Redundancy Group associated with the Node is malfunctioning. ■ At least one Custom Polled Instance associated with the Node has a Status of Warning and Custom Polled Instances are configured to affect Node Status.
 Major	<p>Indicates NNMi detected any of the following:</p> <ul style="list-style-type: none"> ■ A fan (Physical Sensor) failure

	<ul style="list-style-type: none"> ■ A power supply (Physical Sensor) failure ■ A backplane (Physical Sensor) failure ■ A memory (Node Sensor) failure ■ At least one Custom Polled Instance associated with the Node has a Status of Major and Custom Polled Instances are configured to affect Node Status.
 Normal	All objects associated with the node are operationally up.
 No Status	The SNMP Agent, all interfaces, and all IP addresses of the node are not polled.

- **Node Groups**

A Node Group is a logical collection of nodes created by an NNMi administrator.




An NNMi administrator can also configure Node Group Status calculations. The out-of-the-box configuration propagates the most severe Status as follows:

 Critical	At least one node in the Node Group has Critical Status.
 Major	No nodes have a Critical Status, and at least one node in the Node Group has Major Status.
 Minor	No nodes in the Node Group have Critical or Major Status, and at least one Node in the Node Group has Minor Status.
 Warning	No nodes in the Node Group have Critical, Major, or Minor Status, and at least one Node in the Node Group has Warning Status.
 Normal	No nodes in the Node Group have Critical, Major, Minor, or Warning status, and at least one Node in the Node Group has Normal Status.
 Unknown	No nodes in the Node Group have Critical, Major, Minor, Warning, or Normal Status, and at least one Node in the Node Group has Unknown Status.
 No Status	All nodes in the group have No Status.

- **Node Sensor**

Some network devices enable SNMP Agents to monitor certain aspects of ongoing usage such as buffers, CPU utilization, disk utilization, and memory utilization. NNMi administrators can monitor the health of these by configuring node sensors to alert their team members when any of these aspects of operation are marginal or failing.




NNMi reports the status of Node Sensors as follows:

 Critical	The monitored node health attribute is not functioning properly.
 Normal	The monitored node health attribute is operating properly.
 No Status	The node health attribute is not currently being polled.

- **Physical Sensor**

Some network devices enable SNMP Agents to monitor internal components such as backplane, fan, power supply, temperature guage, and voltage regulator. NNMi administrators can monitor the health of these components by configuring physical sensors to alert their team members when any of these components operate marginally or fail.

NNMi reports the status as follows:

 Critical	The monitored Physical Component is not functioning properly.
 Normal	The monitored Physical Component is operating properly.
 No Status	The Physical Component is not currently being polled.





- **Router Redundancy Groups** (*NNMi Advanced*)



A Router Redundancy Group is a set of routers that are configured to provide redundancy in the network. Such groups use the following two types of protocols:

- Hot standby router protocol (HSRP)
- Virtual router redundancy protocol (VRRP)

Router Redundancy Groups usually have a single device acting as the primary, a single device acting as a secondary, and any number of standby devices. If the primary device fails, the secondary device should take over as primary, and one of the standby devices should become secondary. The router groups employ either the HSRP or VRRP protocol to designate the primary, secondary, and standby routers.

NNMi reports the Status of Router Redundancy Groups as follows:






 Critical	The Router Redundancy Group has no acting Primary router.
 Major	The Router Redundancy Group's Primary device is not properly configured (for example, multiple Primary routers exist).
 Minor	The Router Redundancy Group' Secondary device is not properly configured (for example, no acting Secondary router exists).
 Warning	The Router Redundancy Group is functioning, but is in some way degraded.

 Normal	The Router Redundancy Group is functioning properly.
 No Status	The Router Redundancy Group is not yet fully discovered or populated.

- **SNMP Agent**

An SNMP agent is a process interacting with the managed node and providing management functions. The SNMP agent is responsible for SNMP communications with the managed node. An SNMP Agent can be associated with one or more nodes.

NNMi reports the Status of SNMP Agents as follows:

 Critical	SNMP Agent does not respond to SNMP queries.
 Minor	The address associated with the SNMP Agent is not responding to ping.
 Warning	A high or abnormal ICMP response time from the NNMi management server to the selected node is reported.
 Normal	SNMP Agent responds to SNMP queries.
 No Status	SNMP Agent is not polled.

Related Topics

["The NNMi Causal Engine and Incidents" on page 670](#)

About the Trap Service Stages

Any trap information that appears in the NNMi console or in an NNMi log file is first processed through the NNMi Trap Service. The NNMi Trap Service guarantees that the trap data is analyzed in chronological order.

The following table describes the NNMi Trap Service stages.

NNMi Trap Service Stages

Trap Service Stages	Description
TrapListener	Receives traps from the configured "Listen" interface. No filtering takes place at this stage.
MessageProcessor	Parses raw traps and records traps for audit purposes. If Trap Logging is enabled, the MessageProcessor writes all traps to the trap log. Note: Traps configured in <code>trapFilter.conf</code> file are not written to the log file.
TrapServerConfiguration	Handles configuration updates.

NNMi Trap Service Stages, continued

Trap Service Stages	Description
NarrowTrapAnalysis	<p>Handles Hosted Object Trap Storm detection and suppression.</p> <p>Note: This stage is disabled by default. To enable this state use: <code>nnmtrapconfig.ovpl -setProp hostedObjectTrapstorm true -persist</code>. See nnmtrapconfig.ovpl for more information.</p> <p>See Hosted Object Trap Storm for more information about Hosted Object Trap Storm incidents.</p>
WideTrapAnalysis	<p>Handles Trap Storm detection and suppression.</p> <p>Note: This stage is enabled by default.</p> <p>See Trap Storm for more information about Trap Storm incidents.</p>
TrapFilter	<p>Drops all traps that are older than 10 minutes or blocked by IPAddress and OID.</p> <p>Note: Use nnmtrapd.conf to configure trap filters.</p> <p>This filter only passes traps that are configured and enabled in the SNMP Trap Incident Configuration workspace.</p> <p><i>SNMPv1 generic traps only.</i> NNMi uses implicit OID matching when checking for existing SNMP Trap Configurations.</p>
TrapServerConfiguration	<p>Forwards traps to the Events Pipeline. This stage also handles Hosted Trap Storm and Trap Storm incident generation. See Hosted Object Trap Storm and Trap Storm for more information.</p>
ForwardingStage	<p>Forwards traps to another destination, if specified. For example, traps might be forwarded to another instance of NNMi or to other integrated software.</p>


About the Event Pipeline

Any incident information that appears in your incident views first travels through the event pipeline. The event pipeline guarantees that the incident data is analyzed in chronological order.

Note: Not all information that travels through the pipeline results in an incident.

If an incident does not meet the criteria for an event pipeline stage, it is ignored and passed to the next stage in the pipeline. The following table describes the event pipeline stages.

NNMi Event Pipeline Stages

Event PipelineStages	Description
SNMP Trap Receiver	<p>Accepts all SNMP traps.</p> <p>Tip: See "About the Trap Service Stages" on page 684 for information about Trap Service stages that occur before the Event Pipeline stages begin.</p>
Incident Receiver	<p>Accepts all incident information that comes from the NNMi Causal Engine. See "The NNMi Causal Engine and Incidents" on page 670.</p> <p>Note: The incident information that is received includes any Custom Correlation configurations.</p>
Geo Incident Receiver	Accepts all incident information that comes from Global or Regional Managers.
Type Enforcer	<p>Determines if a configuration exists for this trap, event, or incident.</p> <p>If the incident configuration exists, the type enforcer begins to populate the incident fields according to the configuration. Examples of the incident fields that are populated include Severity, Origin, Category, and Correlation Nature. If an incident configuration is disabled or does not exist for the incident, NNMi drops the incident.</p>
Resolver	<p>Drops the trap if the Source Object or Source Node is not in the topology, unless the "Discard Unresolved SNMP Traps and Syslog Messages" check box is unchecked.</p>  <p>Determines if the incident's Source Node or Source Object (such as interface or card) matches an object in the NNMi database.</p> <p>If available, the Resolver populates the incident with the most current Source Node and Source Object attribute values.</p>
Customization	Checks for any of the following incident configurations in the order listed:

NNMi Event Pipeline Stages, continued

Event PipelineStages	Description
	<ul style="list-style-type: none">• Suppression• Enrichment• Dampening
Store Bulk	Collects incidents and stores them. NNMi stores this information in bulk, using a pre-defined time period or number of incidents, whichever occurs first. The default time period is 3 seconds. The default number of incidents is 300. If you send a trap and subsequent traps do not occur on the network for a period of time after the trap is sent, NNMi waits up to 30 seconds before persisting new incident or trap information.
Notification	Notifies other process and services about a new incident.
Pairwise	Checks for any current pairwise configurations for the incident.
Rate	Checks for any current rate configurations for the incident.
Dedup	Checks for any current deduplication configurations for the incident.
Relate	Performs any additional Causal Engine correlations, including Custom Correlations, and cancels the incident when applicable.
Actions	Performs any automatic actions that the NNMi administrator has configured to be run for one or more incidents. See Using Actions to Perform Tasks for more information.
Rba	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – click here for more information.</div> <p>The NNM iSPI NET Diagnostics stage checks whether Diagnostics should be run on the current incident and submits a execution request to run the Diagnostics report on the device. See RbaManager.</p>

How NNMi Closes Incidents

NNMi closes incidents under the following circumstances:

- The incident's configuration is a Pairwise Configuration and both incidents specified in the pair occurred in the order specified. See ["About Pairwise Configurations" on page 746](#) for more information.
- NNMi determines that the problem that generated the incident is resolved. For example, NNMi closes a Down incident when a Conclusion indicates the node or device is available for use and

has returned to a normal state for a specified threshold of time.

See ["Incident Configurations Provided by NNMi" below](#) for the incident configurations that NNMi provides.

An NNMi administrator can also manually change the incident Lifecycle State to Closed. An operator might also be able to change the incident Lifecycle State to Closed if the NNMi administrator chooses to make this Action available to operators.

Note the following:

- If a node is deleted, NNMi closes the incident.
- The NNMi Causal Engine does not generate Conclusions during initial discovery.
- NNMi only Closes incidents for those objects that have one or more outstanding Conclusions as indicated in the object form's Conclusions tab.

Incident Configurations Provided by NNMi

NNMi provides several incident configurations out-of-the-box. You can review these configurations or modify these configurations to better meet your needs. For example, you might want to customize the message that appears with a particular type of incident, including adding information to the message displayed.

You might also choose to create your own configurations for additional SNMP traps that are important to you.

These out-of-the-box configurations are organized according to the following categories:

["SNMP Trap Incident Configurations Provided by NNMi" on page 695](#)

["Syslog Message Incident Configurations Provided by NNMi" on page 708](#)

["Management Event Configurations Provided by NNMi" on page 716](#)

["Incident Pair \(Pairwise\) Configurations Provided by NNMi" on page 748](#)

Caution: If you make changes to an incident configuration provided by NNMi, those changes are at risk of being overwritten in the future. See [Author form](#) for important information.

Custom Incident Attributes Provided by NNMi (Information for Administrators)

NNMi uses custom incident attributes to attach additional information to incidents.

A subset of CIAs is available for any particular incident. Any relevant CIAs are displayed in the [Incident form](#), on the Custom Attributes tab. There are two categories of possible CIAs:

1. Custom incident attributes

- Provided by NNMi
- Provided for [NNM iSPI Performance for Metrics](#).

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

2. SNMP trap varbinds

Identified by the Abstract Syntax Notation value (ASN.1). Varbinds are defined in MIB files that you can load into NNMi. See "[Load SNMP Trap Incident Configurations](#)" on page 873.

The following tables explain the custom incident attributes provided by NNMi.

Custom Incident Attributes Provided by NNMi

Name	Description
cia.address	<p>This attribute value is determined by the <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property defined in the following file (see "About Environment Variables" on page 86 for more information):</p> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\conf\props\nms-jboss.properties</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/conf/props/nms-jboss.properties</pre> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=true</code>, the <code>cia.address</code> value is the User Datagram Protocol (UDP) header IP Address.</p> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=false</code>, both the <code>cia.address</code> and <code>cia.originaladdress</code> values contain the SNMP Agent IP Address. The <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property is false by default.</p> <p>See the "Maintaining NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
cia.originaladdress	<p>This attribute value is determined by the <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property defined in the following file (see "About Environment Variables" on page 86 for more information):</p> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\conf\props\nms-jboss.properties</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/conf/props/nms-jboss.properties</pre> <p>This Custom Incident Attribute enables you to access both the User Datagram Protocol (UDP) header IP Address and the SNMP Agent IP Address of the managed device.</p> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=true</code>, <code>cia.originaladdress</code> is the value of the SNMP Agent IP Address and the <code>cia.address</code> value is the User Datagram Protocol (UDP) header IP Address.</p> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=false</code>, both <code>cia.originaladdress</code> and <code>cia.address</code> values contain the SNMP Agent IP Address. The <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property is false by default.</p> <p>See the "Maintaining NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>
cia.agentAddress	The IP Address that is stored in the SNMPv1 trap data for the SNMP Agent that generated the trap.
cia.custompoller.mibInstance	<p>Instance number used to identify the row in the MIB table that contains the MIB value.</p> <div> <p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p> </div>
cia.custompoller.instanceDisplayValue	<p>Value that results from the Instance Display Configuration.</p> <div> <p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p> </div> <p>See "MIB Expressions Form (Custom Poller)" on page 495</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
	for more information.
cia.custompoller.instanceFilterValue	<p>The instance of the MIB Variable after the MIB Filter is applied to the nodes in the specified Node Group.</p> <p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p> <p>The MIB Filter Variable is specified when configuring a Custom Poller Collection. The MIB Filter is specified when configuring a Custom Poller Policy for the collection. See "Create a Custom Poller Collection" on page 481 and "Create a Policy" on page 516 for more information.</p>
cia.cardsRemoved	Comma-separated list of removed card names used for formatting the Card Removed incident message.
cia.cardsInserted	Comma-separated list of the inserted card names used for formatting the Card Inserted incident message.
cia.custompoller.collection	The Name of the associated Custom Poller Collection.
cia.custompoller.lastValue	The last polled value that caused a state change which generated the incident.
cia.custompoller.policy	The Name of the associated Custom Poller Policy.
cia.custompoller.variable.description	The description of the MIB expression being polled.
cia.custompoller.variable.expression	The MIB expression that was collected and the computed value that caused the incident.
cia.custompoller.variable.name	The Name of the MIB expression variable that caused the incident.
cia.custompoller.state	The state of the Custom Polled Instance for this incident.
cia.incidentDurationMs	<p>The time measured in milliseconds between when NNMi detected a problem with one or more network devices to the time the problem was resolved.</p> <p>Use this CIA to track the total time a particular object in the network was down or unavailable.</p> <p>Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
	<p>network operator), NNMi does not include <code>cia.incidentDuration</code>.</p>
cia.internalAddress	<p>If <i>static</i> Network Address Translation (NAT) is part of your network management domain, and the NNMi management server is outside of that static NAT domain, the NNMi administrator can configure this attribute to show the internal IP address that is mapped to the external management address of the selected incident's Source Node.</p> <p>Note: The external management IP addresss (public address) must be mapped to this internal address (such as private IPv4 address) using the Overlapping IP Address Mapping Form. See "Overlapping Address Mapping Form" on page 211 for more information. For more information about Overlapping IP Addresses in an NNMi network see "Overlapping Address Mapping" on page 210.</p>
cia.island.name	<p>Name NNMi uses to identify the nodes contained in the island.</p> <p>NNMi administrators can use this cia value in Launch Actions to display the associated table view or topology map.</p> <p>To launch the associated topology map, use the following syntax for the Launch Action Full URL attribute value:</p> <pre>http://<serverName>:<portNumber>/nnm/launch?cmd=showNodeGroup&name=\${cias[name=cia.island.name].value}</pre> <p>To launch the associated table view, use the following syntax for the Launch Action Full URL attribute value:</p> <pre>http://<serverName>:<portNumber>/nnm/launch?cmd=showView&view=allNodesTableView&-nodegroup=\${cias[name=cia.island.name].value}</pre> <p>See "Configure Launch Actions" on page 1462 and "Attributes per Object Type for Full URLs" on page 1467 for more information.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
cia.island.numberOfNodes	Number of nodes contained in the island. Use this number to determine the effect of the associated Island Down incident. See Island Group Down for more information.
cia.reasonClosed	<p>The Conclusion information identifying the reason NNMi changed the incident's Lifecycle State to Closed. For example, NNMi might include an Interface Up Conclusion as the reason an Interface Down incident was closed.</p> <p>Note: This CIA is used when NNMi's Causal Engine has analyzed and Closed the incident. Software that is integrated with NNMi might also provide values for cia.reasonClosed. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.reasonClosed.</p>
cia.remotemgr	Hostname or IP address of the (<i>NNMi Advanced - Global Network Management feature</i>) NNMi Regional Manager that is forwarding the event
cia.securityGroup.name	<p>Name value for the Security Group. See "Configure Security Groups (Security Group Form)" on page 632 for more information.</p> <p>Note: This CIA does not appear if the node is assigned to the Default Security Group provided by NNMi.</p>
cia.securityGroup.uuid	<p>UUID value for the Security Group. See "Configure Security Groups (Security Group Form)" on page 632 for more information.</p> <p>Note: This CIA does not appear if the node is assigned to the Default Security Group provided by NNMi.</p>
cia.snmpoid	SNMP trap object identifier.
cia.sourceNodeLongName	Fully qualified DNS name for the incident's Source Node.
cia.tenant.name	<p>Name value for the Tenant. See "Use the Tenant Form" on page 215 for more information.</p> <p>Note: This CIA does not appear if the node is assigned to the Default Tenant provided by NNMi.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
cia.tenant.uuid	UUID value for the Tenant. See "Use the Tenant Form" on page 215 for more information. Note: This CIA does not appear if the node is assigned to the Default Tenant provided by NNMi.
cia.timeIncidentDetectedMs	The timestamp in milliseconds when NNMi first detected the problem associated with an incident. Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.timeIncidentDetected.
cia.timeIncidentResolvedMs	The time when NNMi determines the problem associated with the incident is resolved. Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.timeIncidentResolved.

NNM iSPI Performance for Metrics Custom Incident Attributes

(*NNM iSPI Performance for Metrics*) For network performance monitoring, additional custom incident attributes are provided for your use. [Click here for more information.](#)

Many incidents are candidates for these custom incident attributes:

Information about configuring thresholds is in the following topics:

- ["Configure Threshold Monitoring for Node Groups" on page 458](#)
- ["Configure Threshold Monitoring for Interface Groups" on page 426](#)
- ["Configure Threshold Information for a Custom Poller Collection" on page 507](#)

Custom Incident Attributes Provided for Thresholding

Name	Description
cia.thresholdParameter	The Monitored Attribute that is being measured in the threshold's configuration settings. For example, Input Utilization .

Custom Incident Attributes Provided for Thresholding, continued

Name	Description
<code>cia.thresholdLowerBound</code>	The configured value that when <i>crossed</i> indicates a low threshold situation.
<code>cia.thresholdUpperBound</code>	The configured value that when <i>crossed</i> indicates a high threshold situation.
<code>cia.thresholdPreviousValue</code>	Threshold results from the previous Polling Interval. For example, the threshold results might change from Nominal to High , based on a change in the <code>cia.thresholdMeasuredValue</code> . See Interface Form: Performance tab for a list of additional example Threshold result values.
<code>cia.thresholdCurrentValue</code>	Threshold results from the most recent Polling Interval. For example, High .
<code>cia.thresholdMeasuredValue</code>	The most recent value of the Measured Attribute being monitored according to this threshold's criteria settings. This measurement is the average of all measurements taken during the last polling interval (determined by the NNMi State Poller).
<code>cia.thresholdMeasurementTime</code>	The time at which the threshold was <i>crossed</i> . The time appears in ISO 8601 format.

These CIAs are used in a variety of ways:

- In SNMP trap configurations. See ["Configure SNMP Trap Incidents" on page 886](#).
- In management events. See ["Configure Management Events" on page 1236](#).
- In automatic actions. See ["Configure an Action for an Incident" on page 847](#).
- In correlation configurations. See ["Manage the Number of Incoming Incidents" on page 739](#).
- In Launch Action definitions (access through the Actions menu). See ["Control the NNMi Console Menus" on page 1452](#).

SNMP Trap Incident Configurations Provided by NNMi

Caution: If an SNMP Trap Incident configuration's **Author** value is **HP Network Node Manager**, it can be overwritten by NNMi. See [Author form](#) for important information.

NNMi provides the SNMP trap incident configurations described in the following table.

You might also choose to create your own configurations for additional SNMP traps that are important to you.

SNMP Trap Configurations Provided by NNMI

Incident Configuration Name	Description
BGPBackward Transition	Generated when the BGP Finite State Machine moves from a higher numbered state to a lower numbered state.
BGPEstablished	Generated when the BGP Finite State Machine enters the ESTABLISHED state.
CempMemBufferNotify	Signifies that a cempMemBufferPeak object has been updated in the buffer pool.
CiscoChassisAlarmOff	Signifies that the agent entity has detected the chassisTempAlarm, chassisMinorAlarm, or chassisMajorAlarm object in this MIB has transitioned to the off(1) state.
CiscoChassisAlarmOn	Signifies that the agent entity has detected the chassisTempAlarm, chassisMinorAlarm, or chassisMajorAlarm object in this MIB has transitioned to the on(2) state.
CiscoChassisChangeNotification	Agent detects any hot-swap Physical Component change or changes in the chassis.
CiscoColdStart	Occurs when a Cisco Agent is powered up.
CiscoDemand NeighborLayer2Change	Sent to the manager whenever the D-channel of an interface changes state.
CiscoEnvMonFanNotification	Physical Sensor object incident: Indicates at least one of the fans in the fan array has failed.
CiscoEnvMonFanStatusChangeNotif	Physical Sensor object incident: Indicates a state change for a device being monitored by ciscoEnvMonFanState.
CiscoEnvMonRedundantSupplyNotification	Physical Sensor object incident: Physical Sensor object incident: Indicates the redundant power supply failed.
CiscoEnvMonSuppStatusChangeNotification	Physical Sensor object incident: Indicates a change in the state of a device being monitored by ciscoEnvMonSupplyState.
CiscoEnvMonTemperatureNotification	Physical Sensor object incident: Indicates the temperature measured at a given testpoint is outside the normal range for the testpoint, For example, it is at the warning, critical, or

SNMP Trap Configurations Provided by NNMI, continued

Incident Configuration Name	Description
	shutdown stage.
CiscoEnvMonTempStatusChangeNotification	Physical Sensor object incident: Indicates a change in the state of a device being monitored by ciscoEnvMonTemperatureState.
CiscoEnvMonVoltageNotification	Physical Sensor object incident: Indicates the voltage measured at a given testpoint is outside the normal range for the testpoint. For example, it is at the warning, critical, or shutdown stage.
CiscoEnvMonVoltStatusChangeNotification	Physical Sensor object incident: Indicates a change in the state of a device being monitored by ciscoEnvMonVoltageState.
CiscoFRUInserted	Indicates a Field Replaceable Unit (FRU) was inserted into the source node.
CiscoFRURemoved	Indicates a Field Replaceable Unit (FRU) was removed from the source node.
CiscoLinkDown	Occurs when the Cisco agent detects an interface has gone down.
CiscoLinkUp	Occurs when the Cisco agent detects an interface has come back up.
CiscoModuleDown	Signifies that the SNMP Agent has detected that the card has gone down.
CiscoModuleStatusChange	Indicates the Operational State of the card has changed.
CiscoModuleUp	Signifies that the SNMP Agent has detected that the card has come back up.
CiscoRFProgressionNotif	Notification sent by the active Card (for example Card Active), whenever its Redundancy Framework (RF) state changes or the RF state of the second card in the Card Redundancy Group changes.
CiscoRFSwacNotif	Sent by the newly Active Card (for example Card Active). Indicates that a card state has been switched to a different state.
CiscoUnrecognizedFRU	Indicates the Field Replaceable Unit (FRU) has a product identification that is not recognized.
CiscoVlanPortStatusChange	Generated by a device when the value of

SNMP Trap Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	vlanTrunkPortDynamicStatus object has been changed.
CiscoWarmStart	Occurs when an Cisco agent is reconfigured.
HSRPStateChange	Sent when an HSRP interface transitions to or from an Active or Standby state in a particular HSRP Group.
IetfVrrpStateChange	Sent when a standard VRRP interface transitions to or from a Master State in a particular VRRP Group. This trap is used by the standard VRRP protocol. It corresponds to the vrrpTrapNewMaster trap name.
OSPFIfStateChange	Signifies that there has been a change in the state of a nonvirtual OSPF interface.
OSPFNbrStateChange	Signifies that there has been a change in the state of a nonvirtual OSPF neighbor.
OSPFVirtIfStateChange	Signifies that there has been a change in the state of an OSPF virtual interface.
RMONFallingAlarm	Sent when an RMON device falls below a preconfigured threshold.
Rc2kTemperature	Physical Sensor object incident: Signifies the SNMPv2c entity acting as an SNMP agent, has detected the chassis is overheating.
RcAggLinkDown	(<i>NNMi Advanced</i>) Signifies the operational state of the Multi-Link Trunk (MLT) Aggregator changed from Up to Down. (Link Aggregation ¹ or Split Link Aggregation ²)

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

SNMP Trap Configurations Provided by NNMi, continued

Incident Configuration Name	Description
RcAggLinkUp	(<i>NNMi Advanced</i>) Signifies the operational state of the Multi-Link Trunk (MLT) Aggregator changed from Down to Up. (Link Aggregation ¹ or Split Link Aggregation ²)
RcChasFanDown	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasFanOperStatus object for one of its power supply units is about to transition to the Down state.
RcChasFanUp	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasFanOperStatus object for one of its power supply units is about to transition to the Up state.
RcChasPowerSupplyDown	Physical Sensor object incident: Signifies the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition to the Down state.
RcChasPowerSupplyUp	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP Agent, has detected that the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition to the Up state.
Rcn2kTemperature	Physical Sensor object incident: Signifies that the SNMPv2c entity, acting as an SNMP agent, has detected the chassis is overheating.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

SNMP Trap Configurations Provided by NNMi, continued

Incident Configuration Name	Description
RcnAggLinkDown	(<i>NNMi Advanced</i>) Signifies the operational state of the Multi-Link Trunk (MLT) Aggregator Link changed from Up to Down. (Link Aggregation ¹ or Split Link Aggregation ²)
RcnAggLinkUp	(<i>NNMi Advanced</i>) Signifies the operational state of the Multi-Link Trunk (MLT) Aggregator Interface has changed from Down to Up. (Link Aggregation ³ or Split Link Aggregation ⁴)
RcnChasFanDown	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasFanOperStatus object for one of its power supply units is about to transition into the Down state.
RcnChasFanUp	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasFanOperStatus object for one of its power supply units is about to transition into the Up state.
RcnPowerSupplyDown	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition into the Up state.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

³Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

⁴Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

SNMP Trap Configurations Provided by NNMi, continued

Incident Configuration Name	Description
RcnPowerSupplyUp	Physical Sensor object incident: Signifies the SNMPv2c entity, acting as an SNMP agent, has detected that the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition into the Up state.
RcnSmltIsLinkDown	Signifies the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition into the Down state.
RcnSmltIsLinkUp	Signifies the rcChasPowerSupplyOperStatus object for one of its power supply units is about to transition into the Up state.
RcSmltIsLinkDown	(<i>NNMi Advanced</i>) Signifies the operational state of the Split Multi-Link Trunk (SMLT) Aggregator Link is transitioning from Up to Down. (Link Aggregation ¹ or Split Link Aggregation ²)
RcSmltIsLinkUp	(<i>NNMi Advanced</i>) Signifies the operational state of the Split Multi-Link Trunk (SMLT) Aggregator Link is transitioning from Down to Up. (Link Aggregation)
RcVrrpStateChange	Sent when a Rapid City (RC) Nortel interface transitions to or from a Master state in a particular VRRP Group. This trap is used by the Rapid City (RC) Nortel proprietary VRRP protocol. It corresponds to the rcVrrpTrapNewMaster trap name.
RMONFallingAlarm	Sent when an RMON device falls below a preconfigured threshold.
RMONRiseAlarm	Sent when an RMON device exceeds a preconfigured threshold.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

SNMP Trap Configurations Provided by NNMI, continued

Incident Configuration Name	Description
SNMPColdStart	Signifies that the sending protocol entity is reinitializing itself. Therefore, the agent's configuration or protocol might change.
SNMPLinkDown	Signifies that the sending protocol entity recognizes a failure in one of the communication links represented in the agent's configuration.
SNMPLinkUp	Signifies that the sending protocol entity recognizes that one of the communication links represented in the agent's configuration has come up.
SNMPWarmStart	Signifies that the sending protocol entity is reinitializing itself such that neither the agent configuration nor the protocol entity implementation is altered.
STPNewRoot	Indicates that the sending agent has become the new root of the Spanning Tree.
STPTopologyChange	Sent by a node when any of its configured ports transitions from the Learning state to the Forwarding state, or from the Forwarding state to the Blocking state.

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS)

Incident Configuration Name	Description
RexAdjStateDown	Signifies the adjacency went down.
RexAdjStateFlap	Signifies the adjacency's flap count (rexEventCount) in the duration given by rexCountDuration has become greater than or equal to rexEventThreshold. Both adjacency up and adjacency down count as flaps. For example: An adjacency going down and coming up increments the flap count by two.
RexAdjStateUp	Signifies the adjacency came up.
RexASPathChange	Signifies the AS path to a route has changed.
RexBgpRedundChange	Signifies a change in the number of next hops available for reaching a prefix

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
RexBgpVpnReachByCustGain	<p>Signifies the routes in the Customer announced by Provider Edge (PE¹) that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Customer that are up and not baselined • The percentage of participating routes in the Customer that are up and not baselined
RexBgpVpnReachByCustLoss	<p>Signifies the routes in the Customer announced by PE that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Customer that are down and not baselined • The percentage of participating routes in the Customer that are down and not baselined
RexBgpVpnReachByRtGain	<p>Signifies the routes in the Route Target announced by PE that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Route Target that are up and not baselined • The percentage of participating routes in the Route Target that are up and not baselined
RexBgpVpnReachByRtLoss	<p>Signifies the routes in the Route Target announced by PE that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Route Target that are down and not baselined • The percentage of participating routes in the Route Target that are down and not baselined

¹Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
RexPathChange	Indicates the a path attributes such as metric, number of hops, intermediate hops from a source router to a IP prefix or NSAP address have changed.
RexPeeringStateDown	Indicates a peering between a router and RAMS has gone down
RexPeeringStateFlap	Indicates a peering between a router and RAMS has gone down.
RexPeeringStateUp	Indicates a peering between a router and RAMS has come up.
RexPrefixDrought	Signifies a particular BGP Peer Rib has decreased significantly from the Baseline Size as a percentage of the baseline
RexPrefixFlood	Signifies a particular BGP Peer Rib has increased significantly from the Baseline Size as a percentage of the baseline.
RexPrefixStateDown	Indicates the prefix(rexDstPrfx,rexDstMask) announced by Router(rexSrcRtrSysID, rexSrcRtrIP, rexSrcRtrName) has gone down.
RexPrefixStateFlap	Indicates the prefix (rexDstPrfx,rexDstMask) flap count (rexEventCount) in the duration given by rexCountDuration becomes greater than or equal to rexEventThreshold. Both prefix up and prefix down count as flaps. For example: A prefix going down and coming up increments the flap count by two.
RexPrefixStateUp	Indicates the prefix(rexDstPrfx,rexDstMask) announced by Router(rexSrcRtrSysID, rexSrcRtrIP, rexSrcRtrName) has come up.
RexRtrConnected	Indicates the first adjacency of a router becomes full duplex. This means the neighbor sends an LSA and the previously isolated router sends an LSA across that adjacency.
RexRtrIsolated	Signifies a router has become isolated from the rest of the topology as all of its duplex connections it has to other routers which are not overloaded with respect to a particular routing protocol have gone down.

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
RexRtrStateFlap	Signifies the router's flap count (rexEventCount) in the duration given by rexCountDuration has become greater than or equal to rexEventThreshold. Both router isolation and router connection count as flaps. For example: A router getting isolated and then connected increments the flap count by two.
RexTest	This trap is sent for test purposes
RexVpnPEParticipationByCustGain	Signifies the Provider Edges (PEs) participating in the Customer that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following: <ul style="list-style-type: none"> • The number of PEs that are up and not baselined • The percentage of participating PEs that are up and not baselined
RexVpnPEParticipationByCustLoss	Signifies the Provider Edges (PEs) participating in the Customer that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following: <ul style="list-style-type: none"> • The number of PEs that are down and not baselined • The percentage of participating PEs that are down and not baselined
RexBgpVpnReachByRtGain	Signifies the routes in the Route Target announced by PE that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following: <ul style="list-style-type: none"> • The number of routes in the Route Target that are up and not baselined • The percentage of participating routes in the Route Target that are up and not baselined
RexVpnPEParticipationByRtLoss	Signifies the PEs participating in the Route Target (RT) that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following: <ul style="list-style-type: none"> • The number of PEs that are down and not baselined

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
	<ul style="list-style-type: none"> • The percentage of participating PEs that are down and not baselined
RexVpnReachByCustPEGain	<p>Signifies the routes in the Customer announced by PE that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Customer that are up and not baselined • The percentage of participating routes in the Customer that are up and not baselined
RexVpnReachByCustPELoss	<p>Signifies the routes in the Customer announced by PE that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Customer that are down and not baselined • The percentage of participating routes in the Customer that are down and not baselined
RexVpnReachByCustPrefixDown	Signifies that the prefix has become unreachable in Customer.
RexVpnReachByCustPrefixUp	Signifies that the prefix has become reachable in Customer.
RexVpnReachByRtPEGain	<p>Signifies the routes in the Route Target announced by PE that are up and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p> <ul style="list-style-type: none"> • The number of routes in the Route Target that are up and not baselined • The percentage of participating routes in the Route Target that are up and not baselined
RexVpnReachByRtPELoss	<p>Signifies the routes in the Route Target announced by PE that are down and not baselined as compared to the threshold value. The deviation is represented as either of the following:</p>



SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
	<ul style="list-style-type: none"> The number of routes in the Route Target that are down and not baselined The percentage of participating routes in the Route Target that are down and not baselined
RexVpnReachByRtPrefixDown	Signifies the prefix has become unreachable in RT.
RexVpnReachByRtPrefixUp	Signifies that the prefix has become reachable in RT.
RexVpnSiteExpectedAnncdPfxLoss	Signifies that there is a decrease in the number of prefixes announced by the Vpn/Site pair.
RexVpnSiteExpectedRcvdPfxLoss	Signifies that there is a decrease in the number of prefixes received by the Vpn/Site pair.
RexVpnSitePrefixStateDown	Signifies the prefix(rexDstPrfx,rexDstMask) announced by Router(rexSrcRtrSysID, rexSrcRtrIP, rexSrcRtrName) in VPN(rexVpnName) and site (rexSiteName), has gone down.
RexVpnSitePrefixStateFlap	<p>Signifies the prefix (rexDstPrfx,rexDstMask) flap count (rexEventCount) in the duration given by rexCountDuration becomes greater than or equal to rexEventThreshold.</p> <p>The prefix is announced by Router (rexSrcRtrSysID, rexSrcRtrIP, rexSrcRtrName) in VPN (rexVpnName) and site (rexSiteName).</p> <p>Both prefix up and prefix down count as flaps. For example: A prefix going down and coming up increments the flap count by two.</p>
RexVpnSitePrefixStateUp	<p>Signifies the prefix (rexDstPrfx,rexDstMask) has come up.</p> <p>The prefix is announced by Router (rexSrcRtrSysID, rexSrcRtrIP, rexSrcRtrName) in VPN (rexVpnName) and site (rexSiteName).</p>
RexVpnSiteUnexpectedAnncdPfxGain	Signifies there is an increase in the number of prefixes announced by the Vpn/Site pair.
RexVpnSiteUnexpectedRcvdPfxGain	Signifies there is an increase in the number of prefixes received by the Vpn/Site pair.
TrafficHighLinkUtilization	Indicates the traffic volume has exceeded a specified threshold on a link. Specify the threshold as an

SNMP Trap Incident Configurations for HP Route Analytics Management System (RAMS), continued

Incident Configuration Name	Description
	absolute number in kilobytes per second or in terms of percentage of link capacity.
TrafficLinkCoSUtilization	Indicates the traffic volume has exceeded a specified threshold for a CoS queue on a link. Specify the threshold as an absolute number in kilobytes per second or in terms of a percentage of link capacity.
TrafficLowLinkUtilization	Indicates the traffic volume has fallen below a specified threshold on a link. Specify the threshold as an absolute number in kilobytes per second or in terms of percentage of link capacity.
TrafficQuantityAlert	A generic trap for all non-link related traffic alerts. Specify the threshold as an absolute number in kilobytes per second or in terms of percentage of link capacity.

To see or modify these SNMP trap incident configurations:

1. Navigate to the **SNMP Trap Configuration** form.
 - a. In the Workspace navigation panel, select the **Configuration** workspace.
 - b. Select **SNMP Trap Configurations**
2. Select a row and click the  Open icon.
3. When you finish, click  **Save and Close**.

Syslog Message Incident Configurations Provided by NNMi

Caution: If a Syslog Message Incident configuration's **Author** value is **HP Network Node Manager**, it can be overwritten by NNMi. See [Author form](#) for important information.

NNMi provides the Syslog Message incident configurations described in the following tables. Each of the tables is organized by vendor.

You might also choose to create your own configurations for additional Syslog Messages that are important to you.

Syslog Message Configurations Provided by NNMi - CISCO

Syslog Message Configurations Provided by NNMi - CISCO

Incident Configuration Name	Description
BGP-5-ADJCHANGE	Indicates a Border Gateway Protocol (BGP) neighbor has either come up or gone down. This informational message normally appears as routers and BGP neighbors go up or down. However, unexpected neighbor loss might indicate high error rates or high packet loss in the network and should be investigated.
CDP-4-DUPLEX_MISMATCH	Indicates that Cisco Discovery Protocol (CDP) has discovered a mismatch of duplex configuration. The recommended action is to configure the interfaces to the same duplex (full or half).
DTP-3-NONTRUNKPORTFAIL	Indicates that the port failed to become nontrunked.
DTP-3-TRUNKPORTFAIL	Indicates that the port failed to become trunked.
DTP-5-NONTRUNKPORTON	Indicates that the port is nontrunked.
DTP-5-TRUNKPORTCHG	Indicates that the encapsulation type of the trunk has changed.
DTP-5-TRUNKPORTON	Indicates that the port is trunked.
FR-5-DLCICHANGE	Indicates that a Frame-Relay Data Link Connection Identifier (DLCI) changes state. For states other than ACTIVE, such as INACTIVE and DELETED, check the Frame-Relay switch configuration to make sure its configuration matches the configuration of the router acting as the Frame-Relay Data Terminal Equipment device.
LINEPROTO-5-UPDOWN	Indicates the data link level line protocol changed state.
LINK-3-UPDOWN	Indicates the interface hardware went either up or down. The recommended action is to confirm the configuration settings for the interface, if the state change was unexpected.
LINK-4-ERROR	Indicates excessive errors have occurred on the interface. The recommended action is to check for duplex mismatches between both ends of the link.
OSPF-5-ADJCHG	Indicates an Open Shortest Path First (OSPF) neighbor has changed state.
PAGP-5-	The switch has detected a loss of a link on a switch port, indicating

Syslog Message Configurations Provided by NNMi - CISCO, continued

Incident Configuration Name	Description
PORTFROMSTP	the removal of a port from the Spanning Tree (via Spanning-Tree Protocol).
PAGP-5-PORTTOSTP	The switch has detected a link on a switch port, indicating the addition of a port to the Spanning Tree (via Spanning-Tree Protocol).
PORT_SECURITY-2-PSECURE_VIOLATION_VLAN	An unauthorized device attempted to connect on a secure trunk port.
SNMP-5-MODULETRAP	Indicates the SNMP agent has sent the Module Up or Module Down trap to the engine ID of the remote agent (or SNMP manager) because the corresponding module is up or down.
SPANTREE-5-PORTLISTEN	Indicates that the specified port in the VLAN state has changed to listening.
SPANTREE-5-ROOTCHANGE	Indicates that a new root port or a new root bridge has been selected for a specified Spanning Tree instance (via Spanning-Tree Protocol).
SPANTREE-6-PORTFWD	Indicates the port state in the VLAN changed to forwarding.
SPANTREE-6-PORTLISTEN	Indicates the port state in the VLAN changed to listening.
STACKMGR-6-MASTER_ELECTED	Indicates that the specified switch has been selected as the active switch.
STACKMGR-6-MASTER_READY	Indicates that the active switch is ready for use.
STACKMGR-6-STACK_LINK_CHANGE	Indicates that the status of the specified stack port has changed to active or inactive (up or down).
STANDBY-3-DUPADDR	Indicates that the router has received a Hot Standby Router Protocol (HSRP) message on the interface. The IP address in the HSRP message is the same as the IP address of the router. This condition may be caused by a network loop, a misconfiguration, or a malfunctioning switch.
STANDBY-6-STATECHANGE	Indicates that the Hot Standby Router Protocol (HSRP) state is changed.
SYS-3-MOD_CFGMISMATCH1	Indicates that a module was inserted into a slot that has been configured for another module type.

Syslog Message Configurations Provided by NNMi - CISCO, continued

Incident Configuration Name	Description
SYS-3-MOD_CFGMISMATCH2	Indicates that a module was inserted into a slot that has been configured for another module type.
SYS-3-MOD_CFGMISMATCH3	Indicates that a module was inserted into a slot that has been configured for another module type.
SYS-3-MOD_CFGMISMATCH4	Indicates that a module was inserted into a slot that has been configured for another module type.
SYS-3-PKTBUFBAD	Indicates that the packet buffer test detected a corrupted packet buffer on a module port.
SYS-3-PORT_COLL	Indicates that excessive or late collisions on the port are being logged.
SYS-3-PORT_COLLDIS	Indicates that the threshold values for late or excessive collisions on a port have been exceeded.
SYS-3-PORT_IN_ERRORS	Indicates that a port has experienced an input packet error.
SYS-3-PORT_RUNTS	Indicates that the switch has detected a runt frame (a frame that is less than 64 bytes). These errors are typically caused by physical layer issues or a speed/duplex mode mismatch with the remote device.
SYS-4-SYS_LCPERR4	Indicates a transient Application-Specific Integrated Circuit (ASIC) packet buffer problem.
SYS-5-MOD_INSERT	Indicates that the module was inserted.
SYS-5-MOD_OK	Indicates that the module passed diagnostic self-test and is online.
SYS-5-MOD_REMOVE	Indicates that module was removed.
SYS-5-MOD_RESET	Indicates that the system was reset from the specified console number or IP address.
SYS-5-RELOAD	Indicates that a reload was requested.
SYS-5-RESTART	Indicates that a restart was requested.
SYS-5-SYS_LCPERR5	Indicate an error or a significant condition for a specified port.

Syslog Message Configurations Provided by NNMi - HC3

Syslog Message Configurations Provided by NNMi - HC3

Incident Configuration Name	Description
ARP/3/ROUTECONFLICT	Indicates that the device returned a route conflict when an Address Resolution Protocol (ARP) entry was added to the device.
ARP/5/ARP_DUPVRRPIP	Indicates that a virtual IP address in a Router Redundancy Group using the Virtual Router Redundancy Protocol (VRRP) conflict was detected.
BFD/5/BFD_CHANGE_FSM	Indicates that the finite state machine (FSM) of a Brute Force Detection (BFD) session has been changed.
BGP/5/BGP_RECHED_THRESHOLD	Indicates that the warning threshold of prefixes that can be received from a peer or peer group has been reached.
CFM/5/CFM_SAVECONFIG_SUCCESSFULLY	Indicates that the save configuration was successful.
DEV/4/BOARD_LOADING	Indicates that the specified board is loading a file.
DEV/4/FAN_FAILED	Indicates that the fan failed to run.
DEV/4/FAN_RECOVERED	Indicates that the fan state changed from failed or absent to normal.
DEV/4/LOAD_FINISHED	Indicates that the board has finished loading a file.
DEV/4/POWER_ABSENT	Indicates that the power has been removed.
DEV/4/POWER_FAILED	Indicates that the power state changed to failed.
DEV/4/POWER_RECOVERED	Indicates that the power state changed from failed or absent to normal.
DEV/4/SYSTEM_REBOOT	Indicates that the system is rebooting.
DEVM/2/BOARD_STATE_FAULT	Indicates that an Input/Output or slave boards state changed to fault.
DEVM/2/POWER_FAILED	Indicates that the power state changed to failed.
DEVM/3/BOARD_REMOVED	Indicates that an Input/Output or slave board has been removed from a slot.
DEVM/3/RPS_ABSENT	Indicates that the redundant power system (RPS) is removed.

Syslog Message Configurations Provided by NNMi - HC3, continued

Incident Configuration Name	Description
DEVM/5/POWER_RECOVERED	Indicates that the power state changed from failed or absent to OK .
DEVM/5/RPS_NORMAL	Indicates that the Redundant Power System (RPS) state changed to normal.
DEVM/5/SYSTEM_REBOOT	Indicates that the system is rebooting.
LDP/5/LDP_SESSION_DOWN	Indicates that the sessions state changed to down.
MSTP/5/MSTP_BPDU_RECEIVE_EXPIRY	Indicates that a non-designated port did not receive a Bridge Protocol Data Unit (BPDU) within the <code>rcvdInfoWhile</code> interval, thus aging out the information of the port.
NTP/5/NTP_SOURCE_LOST	Indicates that there was a system synchronization source lost.
OPTMOD/3/TYPE_ERR	Indicates that the transceiver type is not supported by the port hardware.
OPTMOD/4/MODULE_IN	Indicates that the module on this port is plugged in to the interface.
OPTMOD/4/MODULE_OUT	Indicates that the module on this port is not plugged in.
OPTMOD/5/CHKSUM_ERR	Indicates that the checksum of transceiver information is bad.
OPTMOD/5/IO_ERR	Indicates that the transceiver information Input/Output failed.
OPTMOD/5/MOD_ALM_OFF	Indicates that a module fault is gone, and the module on the port has recovered to normal.
OPTMOD/5/MOD_ALM_ON	Indicates that a module not ready fault of the module is detected, and the module on the port has some fault.
OSPF/5/OSPF_NBR_CHG	Indicates that an important neighbor state change event has occurred.
OSPF/6/OSPF_LAST_NBR_DOWN	Indicates a record of the last Open Shortest Path First (OSPF) neighbor down event.
PIM/5/PIM_NBR_DOWN	Indicates that a Protocol Independent Multicast (PIM) neighbor state changed to down.
STM/3/STM_LINK_STATUS_DOWN	Indicates that the link status of an Intelligent Resilient Framework (IRF) port is down.

Syslog Message Configurations Provided by NNMi - HC3, continued

Incident Configuration Name	Description
STM/4/LINK_STATUS_CHANGE	Indicates that the link status of an Intelligent Resilient Framework (IRF) port changed to up or down.
STM/6/STM_LINK_STATUS_UP	Indicates that the link status of an Intelligent Resilient Framework (IRF) port is up.
VRRP/6/VRRP_STATUS_CHANGE	Indicates that the status of the virtual router has changed.

Syslog Message Configurations Provided by NNMi - HP Procurve



Syslog Message Configurations Provided by NNMi - HP Procurve

Incident Configuration Name	Description
ProCurve-RMON_BOOT_CRASH_RECORD0	Indicates that the specified management module was rebooted.
ProCurve-RMON_BOOT_CRASH_RECORD1	Indicates a text message was generated explaining the reasons for a system failure, which may include the type of failure (out of resources or bus error), task name, file name and line number (bus address).
ProCurve-RMON_BOOT_NO_CRASH_RECORD	Indicates that the specified management module failed without saving a failure record.
ProCurve-RMON_BOOT_SELFTEST_FAILURE	Indicates that the Self test failed while the switch was booting up.
ProCurve-RMON_CHASSIS_FAN_STATUS	A fan has failed or a failed fan is no longer failing. The fan state is indicated by failure or OK . The number of times that the fan failed is also displayed.
ProCurve-RMON_CHASSIS_HEARTBEAT_FAILURE	Indicates that communication with the specified slot was lost.
ProCurve-RMON_CHASSIS_POWER_STATUS	Indicates that the one of the following power conditions exists: <ul style="list-style-type: none"> The Redundant Power-Supply (RPS) is failing The RPS is operational but the main power supply is failing

Syslog Message Configurations Provided by NNMi - HP Procurve, continued

Incident Configuration Name	Description
	<ul style="list-style-type: none"> A failed power supply is no longer failing. <p>The state of the main or RPS power supply is indicated as failure or OK. The number of times that the power supply failed is also displayed.</p>
ProCurve-RMON_LACP_DYNAMIC_TRUNK_OFF_LINE	Indicates that the trunk is now off-line.
ProCurve-RMON_LACP_DYNAMIC_TRUNK_ON_LINE	Indicates that the trunk is now online.
ProCurve-RMON_LACP_ERROR_CONDITION_BLOCK	Indicates that an error condition occurred on the specified trunk port and that the port is blocked.
ProCurve-RMON_PMGR_PORT_UP	Indicates that the specified port is now online.
ProCurve-RMON_POEMGR_INTERNAL_50V_FAULT	Indicates that the internal power supply has faulted or a faulted power supply is now operational. The power supply state is indicated as faulted or OK .
ProCurve-RMON_POEMGR_PD_DENIED_POWER	Indicates that there is insufficient power available to power the Powered Device (PD) on the port and the port does not have sufficient PoE priority to take power from another active PoE port.
ProCurve-RMON_POEMGR_PD_OVERCURRENT	Indicates that the Powered Device (PD) connected to the port has requested more than 15.4 watts of power. This may indicate a short-circuit or other problem in the PD.
ProCurve-RMON_SSH_DISABLED	Indicates that the Secure Shell (SSH) server has been disabled.
ProCurve-RMON_SSH_ENABLED	Indicates that the Secure Shell (SSH) server has been enabled.
ProCurve-RMON_STP_NEW_ROOT	Indicates that the Spanning-Tree Protocol (STP) root MAC address has changed for the specified STP priority level.

To see or modify these Syslog Message Incident configurations:

1. Navigate to the **Syslog Message Configurations** form.
 - a. In the Workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**
2. Select a row and click the  Open icon.
3. When you finish, click  **Save and Close**.


Management Event Configurations Provided by NNMi

Caution: If a Management Event configuration's **Author** value is **HP Network Node Manager**, it can be overwritten by NNMi. See [Author form](#) for important information.

Deduplication is not configured for out-of-the-box management events. See "[Correlate Duplicate Incidents \(Deduplication Configuration\)](#)" on page 745 for information about how to configure deduplication.

NNMi provides the incident configurations for management events. Click here for more information.

To see or modify these management event incident configurations:

1. Navigate to the **Management Event Configurations** view.
 - a. In the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
2. Double-click the row representing the configuration you want to see or modify:
 - [Management Event Configurations Provided by NNMi](#)
 - [Additional Management Event Configurations \(NNM iSPI Performance for Metrics\)](#)
3. When you finish, click  **Save and Close**.

Management Event Configurations Provided by NNMi

Incident Configuration Name	Description
AddressNotResponding	Indicate an address is not responding to ICMP. Reasons an address might not respond include:

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	<ul style="list-style-type: none"> • Its node is down • A device, such as a router, has been mis-configured so that some addresses cannot be reached
AggregatorDegraded	(<i>NNMi Advanced</i>) Indicates one or more (but not all) physical interfaces that are part of the Aggregator Interface are not operational. (Link Aggregation ¹ or Split Link Aggregation ²)
AggregatorDown	(<i>NNMi Advanced</i>) Indicates the operational status of the Aggregator Interface is down (if monitored), or all of the corresponding physical interfaces are Down. (Link Aggregation ³ or Split Link Aggregation ⁴)

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

³Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

⁴Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
AggregatorLinkDegraded	(NNMi Advanced) Indicates any Aggregation Member Interface is operationally down on either node, when there is a connection between two Aggregator Interfaces. (Link Aggregation ¹ or Split Link Aggregation ²)
AggregatorLinkDown	(NNMi Advanced) Indicates the Aggregator Interface on either side of an Aggregator Layer 2 Connection is down. (Link Aggregation ³ or Split Link Aggregation ⁴)
BufferOutOfRangeOrMalfunctioning	Indicates the buffer pool is exhausted or cannot meet demand.
CardDisabled	Indicates that the card has been disabled by the device administrator.
CardDown	Indicates the card is not responding to polls.
CardRemoved	Indicates the card was removed from a device.
CardInserted	Indicates a card was inserted into a device.
CardUndeterminedState	Indicates the card reported a non-normal

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

³Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

⁴Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	state for some unspecified reason.
ConnectionDown	Indicate that both (or all) ends of a connection are not responding to SNMP queries.
CpuOutOfRangeOrMalfunctioning	Indicates any of 5 second, 1 minute, or 5 minute utilization averages is too high.
CrgFailover	Indicates the primary card (for example, Card Active) has moved from one card to the other in a Card Redundancy Group. The Card Redundancy Group is routing packets properly.
CrgMultiplePrimary	Indicates NNMi has identified multiple primary cards (for example, Card Active) in the Card Redundancy Group. This typically indicates the communication between the cards in the group is malfunctioning.
CrgNoPrimary	Indicates NNMi is unable to identify a primary card (for example, Card Active) in the Card Redundancy Group. This typically indicates one of the following: <ul style="list-style-type: none"> • One card, or both cards, are down • NNMi has identified only secondary cards (for example Standby cards) in the group • Communication between cards in the group is malfunctioning.
CrgNoSecondary	Indicates NNMi cannot identify a secondard card (for example Card Standby) in the Card Redundancy Group. This typically indicates the following: <ul style="list-style-type: none"> • One of the two cards in the group is down. • NNMi has identified the other card as primary (for example, Card Active). • The Card Redundancy Group is

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	functioning properly
CustomPollCritical	Indicates that a Polling Instance associated with the Custom Poller Collection is in a Critical State.
CustomPolledInstanceOutOfRange	Indicates that a Custom Polled Instance has reached or exceeded a Comparison Map value or Threshold configured for the associated Custom Node Collection.
CustomPollMajor	Indicates that a Polling Instance associated with the Custom Poller Collection is in a Major State.
CustomPollMinor	Indicates that a Polling Instance associated with the Custom Poller Collection is in a Minor State.
CustomPollWarning	Indicates that a Polling Instance associated with the Custom Poller Collection is in a Warning State.
DuplicateCorrelation	<p>Provided as a template for configuring deduplication for an incident to specify which attribute values NNMi must match to verify that an incident is a duplicate</p> <p>Note: The DuplicateCorrelation incident configuration does not support Suppression, Enrichment or Dampening.</p>
FanOutOfRangeOrMalfunctioning	Physical Sensor object incident: Indicates the specified fan is not operating correctly.
ForwardIncidentRateExceeded	(NNMi Advanced) Indicates that the volume of messages entering a Regional Manager's Global Network Management message queue has exceeded the configured rate limits.
HostedObjectTrapStorm	Indicates the trap rate threshold for a hosted object has been exceeded.
InterfaceDisabled	Indicates the interface has been explicitly disabled by the device administrator.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
InterfaceDown	Indicates that the operational status of the interface is down.
IpSubnetContainsIpWithNewMac	Indicates the MAC Address corresponding to a particular IP Address has changed. Possible causes include a duplicate IP Address on this subnet.
IslandGroupDown	Indicates all nodes in a group of Layer 2 connected nodes do not respond to monitoring polls (for example, ICMP or SNMP). These groups are automatically discovered and contain all of the nodes that can be connected through NNMi topology. Typically, these are groups on one side of a WAN (wide area network) connection.
LicenseExpired	Indicates that the expiration date has passed for an instant-on or temporary NNMi license key. See "Extend a Licensed Capacity" on page 1605 .
LicenseMismatch	Indicates that the licensed capacity for NNMi does not match the licensed capacity for one of the i Smart Plug in products in your network environment. See "Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515 . Note: The licensed capacity count is cumulative for each licensed product (across all installed license keys for that licensed product). See "Extend a Licensed Capacity" on page 1605 .
LicenseNodeCountExceeded	Indicates that the number of discovered nodes exceeds the licensed capacity for managed node count. See "Extend a Licensed Capacity" on page 1605 .

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
ManagementAddressICMPResponseTimeAbnormal	Indicates an abnormal Internet Control Message Protocol (ICMP) response time from the NNMi management server to the selected node. ICMP messages are typically used for diagnostic or routing purposes for determining whether a host or router could not be reached. The incident is generated when NNMi detects a higher than configured ICMP response time between the NNMi management server and the selected node.
ManagementAddressICMPResponseTimeHigh	Indicates a high Internet Control Message Protocol (ICMP) response time from the management server to the selected node. ICMP messages are typically used for diagnostic or routing purposes for determining whether a host or router could not be reached. The incident is generated when NNMi detects a higher than configured ICMP response time between the NNMi management server and the selected node.
MemoryQueueIncidentRateExceeded	<i>(NNMi Advanced)</i> Indicates the rate at which NNMi forwards incidents to the Global Manager has exceeded the maximum allowed. NNMi no longer forwards incidents generated from SNMP traps.
MessageQueueSizeExceeded	Indicates one of the queues connecting the stages for the Event Pipeline is above the configured limits. NNMi determines queue size limits based on memory size.
ModifiedConnectionDown	Indicates a connection has been disconnected, moved, or both and is not responding to SNMP queries.
NnmClusterFailover	Indicates the NNMi cluster detected a failure of the active server. NNMi services were started on the standby server.
NnmClusterLostStandby	Indicates the NNMi cluster active server lost its communication to the standby server.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
NnmClusterStartUp	Indicates the NNMi cluster was started in a state where no active server was already present. Therefore the server was started in the active state.
NnmClusterTransfer	Indicates the system administrator moved the active state from one server to another. The NNMi services will then start on the new active server.
NodeDeleted	Indicates that the specified node was deleted from the NNMi topology.
NodeDown	Indicates that the NNMi Causal Engine has determined the node is down based on the following analysis: 100% of the addresses assigned to this node are unreachable. NNMi is communicating with at least two of the neighboring devices. And at least two neighboring devices report problems with connectivity to this node.
NodeOrConnectionDown	Indicate a node is not responding to an ICMP or SNMP query. It also indicates that only one neighbor is down so that the NNMi Causal Engine cannot determine whether the node or the connection is down.
PowerSupplyOutOfRangeOrMalfunctioning	Physical Sensor object incident: Indicates a power supply for the Source Node is not operating correctly.
RateCorrelation	Provided as a template to measure the number of incoming incidents within a defined time period. Note: The rateCorrelation incident configuration does not support Suppression, Enrichment, or Dampening.
RrgDegraded	This incident occurs only in Router Redundancy Groups with more than two routers.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	<p>Indicates the following:</p> <ul style="list-style-type: none"> • The Router Redundancy Group still has a primary and secondary device. • The remaining devices in the group are down or in an unexpected protocol-specific state. For example, in HSRP other devices should be in Listen state. <p>Typically, the protocol-specific communication between routers is malfunctioning. However, the group is routing packets properly.</p>
RrgFailover	<p>Indicates a primary role moved from one device to another in a Router Redundancy Group (for example, HSRP Active or VRRP Master).</p> <p>Reasons for this incident include one or more of the following:</p> <ul style="list-style-type: none"> • A router or interface in the Router Redundancy Group has gone down. • A tracked object (interface or IP address) in the Router Redundancy Group has gone down. <p>Even though a fail-over occurred, the group is routing packets properly.</p>
RrgMultiplePrimary	<p>Indicates that multiple primary devices are identified in a Router Redundancy Group (for example, HSRP Active or VRRP Master).</p> <p>Typically, the protocol-specific communication between routers in the group is malfunctioning.</p>
RrgMultipleSecondary	<p>Indicates that more than one secondary device is identified in a Router Redundancy Group (for example, HSRP Standby).</p>

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	<p>Note: This incident applies only to Router Redundancy Groups that allow only one secondary member. Typically, the protocol-specific communication between routers in the group is malfunctioning.</p> <p>Typically, the protocol-specific communication between routers in the group is malfunctioning.</p>
RrgNoPrimary	<p>Indicates that no primary device is identified in a Router Redundancy group (for example, HSRP Active or VRRP Master) .</p> <p>This incident typically indicates one of the following:</p> <ul style="list-style-type: none"> • Too many routers are down. • Protocol-specific communication between routers in the group is malfunctioning.
RrgNoSecondary	<p>Indicates that no secondary device is identified in a Router Redundancy Group (for example, HSRP Standby or VRRP Backup).</p> <p>This incident typically indicates the following:</p> <ul style="list-style-type: none"> • Protocol-specific communication between routers in the group is malfunctioning. • The group is routing packets properly because a single primary device has been identified.
SNMPAgentNotResponding	The SNMP agent is not responding to SNMP queries on the selected Node.
SNMPTrapLimitCritical	Indicates the number of SNMP traps persisted in the NNMi database is approaching the maximum allowed limit.

Management Event Configurations Provided by NNMi, continued

Incident Configuration Name	Description
	After the maximum allowed limit is reached, NNM no longer accepts SNMP traps until the number of SNMP traps within the database is reduced using the nnmtrimincidents.ovpl command.
SNMPTrapLimitMajor	Indicates the number of SNMP traps persisted in the NNMi database has reached or exceeded 95% of the maximum limit. After the maximum limit is reached, NNMi only accepts traps required for Causal Engine analysis until the number of SNMP traps within the database has been reduced using the nnmtrimincidents.ovpl command.
SNMPTrapLimitWarning	Indicates the number of SNMP traps persisted in the NNMi database has reached or exceeded 90% of the maximum limit. After the maximum limit is reached, NNMi no longer accepts SNMP traps until the number of SNMP traps within the database is reduced using the nnmtrimincidents.ovpl command.
TemperatureOutOfRangeOrMalfunctioning	Physical Sensor object incident: Indicates the specified temperature sensor on the Source Node is too hot or too cold.
TrapStorm	Indicates a trap storm has occurred.
VoltageOutOfRangeOrMalfunctioning	Physical Sensor object incident: Indicates the specified voltage on one of the Source Node's power supplies is out of range.

(*NNM iSPI Performance for Metrics*) For network performance monitoring, the HP Network Node Manager iSPI Performance for Metrics Software provides additional management event configurations. [Click here for more information.](#)

The Node Sensor performance threshold events have a Category value of **Performance** a Family value of **Node Sensor**, and a Nature of **Root Cause**.

The Interface performance threshold events have a Category value of **Performance** a Family value of **Interface**, and a Nature of **Root Cause**.

Additional Management Event Configurations (NNM iSPI Performance for Metrics)

Incident Configuration Name	Description
<p>Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the <i>optional</i> Network Performance Server (NPS) – click here for more information.</p>	
BackplaneAbnormal	Indicates the backplane utilization is abnormal based on the computed baseline.
BackplaneOutOfRange	Indicates the backplane utilization has gone above or below a threshold setting.
BufferAbnormal	Indicates the buffer utilization is abnormal based on the computed baseline.
CpuAbnormal	<p>Indicates the CPU utilization is abnormal based on the computed baseline for one of the following:</p> <ul style="list-style-type: none"> • CPU 5 second utilization • CPU 1 minute utilization • CPU 5 minute utilization
DiskSpaceAbnormal	Indicates disk space utilization is abnormal based on the computed baseline.
DiskSpaceOutOfRange	Indicates disk space utilization has gone above or below a threshold setting.
InterfaceFCSLANErrorRateHigh	<p><i>Local Area Network</i>. Indicates a Frame Check Sequence (FCS) error rate on the interface has gone above a threshold setting. The error rate is based on the number of frames that were received with a bad checksum (CRC¹ value).</p> <p>Possible causes include collisions at half-duplex, a duplex mismatch, bad hardware (NIC², cable, or port), or a connected device generating frames with bad FCS.</p>
InterfaceFCSWLANErrorRateHigh	<i>Wireless Local Area Network</i> . Indicates a Frame Check Sequence (FCS) error rate on the interface has

¹Cyclic Redundancy Check

²Network Interface Controller

**Additional Management Event Configurations (NNM iSPI Performance for Metrics),
continued**

Incident Configuration Name	Description
	gone above a threshold setting. The error rate is based on the number of frames that were received with a bad checksum (CRC ¹ value). Possible causes include collisions at half-duplex, a duplex mismatch, bad hardware (NIC, cable, or port), or a connected device generating frames with bad FCS.
InterfaceInputDiscardRateHigh	Indicates the input discard rate on the interface has exceeded a threshold setting. This rate is based on the reported change in the number of input packets on the interface and the discarded packet count.
InterfaceInputErrorRateAbnormal	Indicates the input error rate on the interface is abnormal based on the computed baseline. This range is based on the reported change in the number of input packets on the interface and the packet error count. Possible causes include include bad packet checksums, incorrect header information, and small packets.
InterfaceInputErrorRateHigh	Indicates the input error rate on the interface <i>crossed</i> a High threshold setting. This rate is based on the reported change in the number of input packets on the interface and the packet error count.
InterfaceInputQueueDropsHigh	Indicates the number of input queue drops on the interface <i>crossed</i> a High threshold setting. This range is based on the number of packets dropped because of a full queue. Possible causes include that the number of packet buffers allocated to the interface is exhausted or has reached its maximum threshold.
InterfaceInputUtilizationAbnormal	Indicates the input utilization on the interface is abnormal based on the computed baseline. This range is based on the interface speed and the reported change in the number of input bytes on the interface.
InterfaceInputUtilizationHigh	Indicates the input utilization on the interface <i>crossed</i> a High threshold setting. This percentage is based on

¹Cyclic Redundancy Check

**Additional Management Event Configurations (NNM iSPI Performance for Metrics),
continued**

Incident Configuration Name	Description
	the interface speed and the reported change in the number of input bytes on the interface.
InterfaceInputUtilizationLow	Indicates the input utilization on the interface <i>crossed</i> a Low threshold setting. This percentage is based on the interface speed and the reported change in the number of input bytes on the interface.
InterfaceInputUtilizationNone	Indicates there is no input utilization on the interface. This value is based on the interface speed and the reported change in the number of input bytes on the interface.
InterfaceOutputDiscardRateHigh	Indicates the output discard rate on the interface <i>crossed</i> a High threshold setting. This rate is based on the reported change in the number of input packets on the interface and the discarded packet count.
InterfaceOutputErrorRateHigh	Indicates the output error rate on the interface <i>crossed</i> a High threshold setting. This rate is based on the reported change in the number of output packets on the interface and the packet error count.
InterfaceOutputQueueDropsHigh	Indicates the number of output queue drops on the interface <i>crossed</i> a High threshold setting. This number is based on the number of packets dropped because of a full queue. Possible causes include a congested interface.
InterfaceOutputUtilizationAbnormal	Indicates the output utilization on the interface is abnormal based on the computed baseline. This range is based on the interface speed, and the reported change in the number of output bytes on the interface.
InterfaceOutputUtilizationHigh	Indicates the output utilization on the interface <i>crossed</i> a High threshold setting. This percentage is based on the interface speed and the reported change in the number of output bytes on the interface.
InterfaceOutputUtilizationLow	Indicates the output utilization on the interface <i>crossed</i> a Low threshold setting. This percentage is based on the interface speed and the reported change in the number of output bytes on the interface.
InterfaceOutputUtilizationNone	Indicates there is no output utilization on the interface. This value is based on the interface speed and the

**Additional Management Event Configurations (NNM iSPI Performance for Metrics),
continued**

Incident Configuration Name	Description
	reported change in the number of output bytes on the interface.
InterfacePerformanceCritical	Indicates the interface performance has reached a Critical severity.
InterfacePerformanceWarning	Indicates that the interface performance has reached a Warning severity.
MemoryOutOfRangeOrMalfunctioning	Indicates the Source Node's memory pool is exhausted or cannot meet the demand for use.
MemoryAbnormal	Indicates the memory utilization is abnormal based on the computed baseline.

Incident Pair (Pairwise) Configurations Provided by NNMi

NNMi provides the pairwise configurations described in the following table.

Pairwise Configurations Provided by NNMi

Name	Description
CiscoLinkDownUpPair	Cancels a CiscoLinkDown incident with a CiscoLinkUp incident on the same interface for the same SNMP agent address. This configuration is used for known Cisco devices.
CiscoModuleDownUpPair	Cancels a Cisco Module Down incident with a Cisco Module Up incident from the same module and SNMP agent address.
RcAggLinkDownUpPair	(<i>NNMi Advanced</i>) Cancels an RcAggLinkDown incident with an RcAggLinkUp incident from the same Multi-Link Trunk (MLT) Aggregator ID (from the MIB) and SNMP agent address. (Link Aggregation ¹ or Split Link)

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

Pairwise Configurations Provided by NNMI, continued

Name	Description
	Aggregation ¹⁾
RcChasFanDownUpPair	Physical Sensor object incident: Cancels an RcChasFanDown incident with an RcChasFanUp incident from the same fan ID (from the MIB) and SNMP agent address.
RcChasPowerSupplyDownUpPair	Physical Sensor object incident: Cancels an RcChasPowerSupplyDown incident with an RcChasPowerSupplyUp incident from the same power supply ID (from the MIB) and SNMP agent address.
RcSmltIsLinkDownUpPair	Cancels an RcSmltIsLinkDown incident with an RcSmltIsLinkUp incident from the same SNMP agent address.
RcnAggLinkDownUpPair	(<i>NNMi Advanced</i>) Cancels an RcnAggLinkDown incident with an RcnAggLinkUp incident from the same Multi-Link Trunk (MLT) Aggregator Link ID (from the MIB) and SNMP agent address. (Link Aggregation ² or Split Link Aggregation ³)
RcnChasFanDownUpPair	Physical Sensor object incident: Cancels an RcnChasFanDown incident with an RcnChasFanUp incident from the same fan ID (from the MIB) and SNMP agent address.
RcnChasPowerSupplyDownUpPair	Physical Sensor object incident: cancels a RcnChasPowerSupplyDown incident with an RcnChasPowerSupplyUp incident from the same power supply ID (from the MIB) and SNMP agent address.
RcnSmltIsLinkDownUpPair	Cancels an RcnSmltIsLinkDown incident with an RcnSmltIsLinkUp incident from the same SNMP agent address.

¹Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

²Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

³Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Pairwise Configurations Provided by NNMi, continued

Name	Description
SnmpLinkDownUpPair	Cancels an SNMPLinkDown incident with an SNMPLinkUp incident on the same interface for the same SNMP agent address.

To see or modify these incident pair configurations:

1. Navigate to the **Pairwise Configurations** view.
 - a. In the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Pairwise Configurations**.
2. Double-click the row representing the configuration you want to see or modify.

See ["Pairwise Configuration Form \(Correlate Pairs of Incidents\)" on page 752](#) for more information.

3. When you are finished, click  **Save and Close** to save your changes.

About Custom Incident Attributes for an Incident

The Custom Incident Attributes (CIAs) form enables you to specify additional CIAs to be saved with an incoming incident. You can then use this information to enhance the incident. For example, the information might be added to the incident message or used to customize a severity for a particular CIA value.

When creating a CIA for an incident configuration, you can specify any of the following values:

- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

You can provide the required information within the following contexts:

["Configure Custom Incident Attributes to Enrich an Incident Configuration \(Interface Settings\) \(SNMP Trap Incidents\)" on page 928](#)

["Configure Custom Incident Attributes to Enrich an Incident Configuration \(Interface Settings\) \(Management Events\)" on page 1272](#)

["Configure Custom Incident Attributes to Enrich an Incident Configuration \(Interface Settings\) \(Syslog Message\)\(HP ArcSight\)" on page 1104](#)

Custom Incident Attributes Provided by NNMi (Information for Administrators)

NNMi uses custom incident attributes to attach additional information to incidents.

A subset of CIAs is available for any particular incident. Any relevant CIAs are displayed in the [Incident form](#), on the Custom Attributes tab. There are two categories of possible CIAs:

1. Custom incident attributes

- Provided by NNMi
- Provided for [NNM iSPI Performance for Metrics](#).

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

2. SNMP trap varbinds

Identified by the Abstract Syntax Notation value (ASN.1). Varbinds are defined in MIB files that you can load into NNMi. See "[Load SNMP Trap Incident Configurations](#)" on page 873.

The following tables explain the custom incident attributes provided by NNMi.

Custom Incident Attributes Provided by NNMi

Name	Description
cia.address	<p>This attribute value is determined by the <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property defined in the following file (see "About Environment Variables" on page 86 for more information):</p> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\conf\props\nms-jboss.properties</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/conf/props/nms-jboss.properties</pre> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=true</code>, the <code>cia.address</code> value is the User Datagram Protocol (UDP) header IP Address.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
	<p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=false</code>, both the <code>cia.address</code> and <code>cia.originaladdress</code> values contain the SNMP Agent IP Address. The <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property is false by default.</p> <p>See the "Maintaining NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>
cia.originaladdress	<p>This attribute value is determined by the <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property defined in the following file (see "About Environment Variables" on page 86 for more information):</p> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\conf\props\nms-jboss.properties</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/conf/props/nms-jboss.properties</pre> <p>This Custom Incident Attribute enables you to access both the User Datagram Protocol (UDP) header IP Address and the SNMP Agent IP Address of the managed device.</p> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=true</code>, <code>cia.originaladdress</code> is the value of the SNMP Agent IP Address and the <code>cia.address</code> value is the User Datagram Protocol (UDP) header IP Address.</p> <p>When <code>com.hp.nnm.trapd.useUdpHeaderIpAddress=false</code>, both <code>cia.originaladdress</code> and <code>cia.address</code> values contain the SNMP Agent IP Address. The <code>com.hp.nnm.trapd.useUdpHeaderIpAddress</code> property is false by default.</p> <p>See the "Maintaining NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i> for more information.</p>
cia.agentAddress	<p>The IP Address that is stored in the SNMPv1 trap data for the SNMP Agent that generated the trap.</p>
cia.custompoller.mibInstance	<p>Instance number used to identify the row in the MIB table that contains the MIB value.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
	<p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p>
cia.custompoller.instanceDisplayValue	<p>Value that results from the Instance Display Configuration.</p> <p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p> <p>See "MIB Expressions Form (Custom Poller)" on page 495 for more information.</p>
cia.custompoller.instanceFilterValue	<p>The instance of the MIB Variable after the MIB Filter is applied to the nodes in the specified Node Group.</p> <p>Tip: You can use this CIA in the Message Format for a Custom Poller incident.</p> <p>The MIB Filter Variable is specified when configuring a Custom Poller Collection. The MIB Filter is specified when configuring a Custom Poller Policy for the collection. See "Create a Custom Poller Collection" on page 481 and "Create a Policy" on page 516 for more information.</p>
cia.cardsRemoved	Comma-separated list of removed card names used for formatting the Card Removed incident message.
cia.cardsInserted	Comma-separated list of the inserted card names used for formatting the Card Inserted incident message.
cia.custompoller.collection	The Name of the associated Custom Poller Collection.
cia.custompoller.lastValue	The last polled value that caused a state change which generated the incident.
cia.custompoller.policy	The Name of the associated Custom Poller Policy.
cia.custompoller.variable.description	The description of the MIB expression being polled.
cia.custompoller.variable.expression	The MIB expression that was collected and the computed value that caused the incident.
cia.custompoller.variable.name	The Name of the MIB expression variable that caused the incident.
cia.custompoller.state	The state of the Custom Polled Instance for this incident.

Custom Incident Attributes Provided by NNMi, continued

Name	Description
cia.incidentDurationMs	<p>The time measured in milliseconds between when NNMi detected a problem with one or more network devices to the time the problem was resolved.</p> <p>Use this CIA to track the total time a particular object in the network was down or unavailable.</p> <div data-bbox="688 533 1370 743"> <p>Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.incidentDuration.</p> </div>
cia.internalAddress	<p>If <i>static</i> Network Address Translation (NAT) is part of your network management domain, and the NNMi management server is outside of that static NAT domain, the NNMi administrator can configure this attribute to show the internal IP address that is mapped to the external management address of the selected incident's Source Node.</p> <div data-bbox="688 995 1370 1310"> <p>Note: The external management IP addresss (public address) must be mapped to this internal address (such as private IPv4 address) using the Overlapping IP Address Mapping Form. See "Overlapping Address Mapping Form" on page 211 for more information. For more information about Overlapping IP Addresses in an NNMi network see "Overlapping Address Mapping" on page 210.</p> </div>
cia.island.name	<p>Name NNMi uses to identify the nodes contained in the island.</p> <p>NNMi administrators can use this cia value in Launch Actions to display the associated table view or topology map.</p> <p>To launch the associated topology map, use the following syntax for the Launch Action Full URL attribute value:</p> <pre>http://< serverName >:< portNumber >/nnm/launch?cmd=showNodeGroup&name=\${cias [name=cia.island.name].value</pre> <p>To launch the associated table view, use the following syntax for the Launch Action Full URL attribute value:</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
	<p><code>http://<serverName>:<portNumber>/nnm/launch?cmd=showView&view=allNodesTableView&-nodegroup=\${cias[name=cia.island.name].value}</code></p> <p>See "Configure Launch Actions" on page 1462 and "Attributes per Object Type for Full URLs" on page 1467 for more information.</p>
<code>cia.island.numberOfNodes</code>	<p>Number of nodes contained in the island. Use this number to determine the effect of the associated Island Down incident. See Island Group Down for more information.</p>
<code>cia.reasonClosed</code>	<p>The Conclusion information identifying the reason NNMi changed the incident's Lifecycle State to Closed. For example, NNMi might include an Interface Up Conclusion as the reason an Interface Down incident was closed.</p> <div> <p>Note: This CIA is used when NNMi's Causal Engine has analyzed and Closed the incident. Software that is integrated with NNMi might also provide values for <code>cia.reasonClosed</code>. Any time an incident is closed manually (for example, by the network operator), NNMi does not include <code>cia.reasonClosed</code>.</p> </div>
<code>cia.remotemgr</code>	<p>Hostname or IP address of the (<i>NNMi Advanced - Global Network Management feature</i>) NNMi Regional Manager that is forwarding the event</p>
<code>cia.securityGroup.name</code>	<p>Name value for the Security Group. See "Configure Security Groups (Security Group Form)" on page 632 for more information.</p> <div> <p>Note: This CIA does not appear if the node is assigned to the Default Security Group provided by NNMi.</p> </div>
<code>cia.securityGroup.uuid</code>	<p>UUID value for the Security Group. See "Configure Security Groups (Security Group Form)" on page 632 for more information.</p> <div> <p>Note: This CIA does not appear if the node is assigned to the Default Security Group provided by NNMi.</p> </div>
<code>cia.snmpoid</code>	<p>SNMP trap object identifier.</p>
<code>cia.sourceNodeLongName</code>	<p>Fully qualified DNS name for the incident's Source Node.</p>

Custom Incident Attributes Provided by NNMi, continued

Name	Description
cia.tenant.name	Name value for the Tenant. See "Use the Tenant Form" on page 215 for more information. Note: This CIA does not appear if the node is assigned to the Default Tenant provided by NNMi.
cia.tenant.uuid	UUID value for the Tenant. See "Use the Tenant Form" on page 215 for more information. Note: This CIA does not appear if the node is assigned to the Default Tenant provided by NNMi.
cia.timeIncidentDetectedMs	The timestamp in milliseconds when NNMi first detected the problem associated with an incident. Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.timeIncidentDetected.
cia.timeIncidentResolvedMs	The time when NNMi determines the problem associated with the incident is resolved. Note: This CIA is used only when NNMi's Causal Engine has analyzed and Closed the incident. Any time an incident is closed manually (for example, by the network operator), NNMi does not include cia.timeIncidentResolved.

NNM iSPI Performance for Metrics Custom Incident Attributes

(*NNM iSPI Performance for Metrics*) For network performance monitoring, additional custom incident attributes are provided for your use. [Click here for more information.](#)

Many incidents are candidates for these custom incident attributes:

Information about configuring thresholds is in the following topics:

- ["Configure Threshold Monitoring for Node Groups" on page 458](#)
- ["Configure Threshold Monitoring for Interface Groups" on page 426](#)
- ["Configure Threshold Information for a Custom Poller Collection" on page 507](#)

Custom Incident Attributes Provided for Thresholding

Name	Description
<code>cia.thresholdParameter</code>	The Monitored Attribute that is being measured in the threshold's configuration settings. For example, Input Utilization .
<code>cia.thresholdLowerBound</code>	The configured value that when <i>crossed</i> indicates a low threshold situation.
<code>cia.thresholdUpperBound</code>	The configured value that when <i>crossed</i> indicates a high threshold situation.
<code>cia.thresholdPreviousValue</code>	Threshold results from the previous Polling Interval. For example, the threshold results might change from Nominal to High , based on a change in the <code>cia.thresholdMeasuredValue</code> . See Interface Form: Performance tab for a list of additional example Threshold result values.
<code>cia.thresholdCurrentValue</code>	Threshold results from the most recent Polling Interval. For example, High .
<code>cia.thresholdMeasuredValue</code>	The most recent value of the Measured Attribute being monitored according to this threshold's criteria settings. This measurement is the average of all measurements taken during the last polling interval (determined by the NNMi State Poller).
<code>cia.thresholdMeasurementTime</code>	The time at which the threshold was <i>crossed</i> . The time appears in ISO 8601 format.

These CIAs are used in a variety of ways:

- In SNMP trap configurations. See ["Configure SNMP Trap Incidents" on page 886](#).
- In management events. See ["Configure Management Events" on page 1236](#).
- In automatic actions. See ["Configure an Action for an Incident" on page 847](#).
- In correlation configurations. See ["Manage the Number of Incoming Incidents" below](#).
- In Launch Action definitions (access through the Actions menu). See ["Control the NNMi Console Menus" on page 1452](#).

Manage the Number of Incoming Incidents

NNMi's Causal Engine reduces the number of incidents by extensively evaluating problems and determining the root cause for you, whenever possible.

To help simplify the diagnosis of network faults, you can configure NNMi to manage the number of incidents that are displayed. To do so, use any of the following methods:

- **Disable the Incident configuration.** In the **Basics** group of the SNMP Trap Configuration, Management Event Configuration or Syslog Messages Configuration form, verify that **Enabled** ☐ is cleared for each configuration for which you do not want NNMi to generate an Incident.
- **Use NNMi's Scheduled Outage feature to set the Management Mode of the network object to Out of Service.** NNMi discards any incoming traps during the Scheduled Outage. See [Scheduling Outages for Nodes or Node Groups](#) for more information.
- **Use NNMi's Management Mode feature to set the Management Mode of the network object to Not Managed or Out of Service.** NNMi discards any incoming traps if the trap source is [Unmanaged](#)¹. See [Stop or Start Managing an Object](#) for more information about Management Mode.
- **Use the Monitoring Configuration to specify that you do not want NNMi to monitor the network object.** NNMi discards most incoming traps if the source object is not monitored. See ["Configure NNMi Monitoring Behavior" on page 387](#) for more information.
- **Identify additional criteria for or relationships between incoming incidents.** When these criteria or relationships occur, NNMi modifies the flow of incidents by recognizing the criteria or patterns of incoming management events or SNMP traps and nesting related incidents as correlated children.

These strategies can dramatically reduce the number of incidents and improve the value of the incidents displayed. For example, instead of displaying an entire incident storm typically generated by equipment and link failures, use the deduplication configuration to specify only the most meaningful incidents, and correlate the rest as children. Then it is faster and easier to identify the network problem. See ["Establish Criteria or Relationships for Incoming Incidents" below](#) for more information.

Related Topics

["Configure Management Events" on page 1236](#)

["Configure SNMP Trap Incidents" on page 886](#)

["Configure Syslog Message Incidents \(HP ArcSight\)" on page 1068](#)

Establish Criteria or Relationships for Incoming Incidents

Using NNMi, you can establish the criteria or relationships for the incoming incidents using any of the incident configurations shown in the following diagram. You can choose to use them as is, edit them, or create your own configurations.

Incident Configuration Tabs

¹Indicates the Management Mode is "Not Managed" or "Out of Service".



Click [here](#) for a description and example of each configuration option.


Overview of Incident Configuration Tabs

	Configuration Option	When to Use	Example
1	Interface Settings	Select this tab to specify that you want to configure Suppression, Enrichment, Dampening, and Actions for a specified Interface Group.	Change the Severity and Message of an incident configuration for a specified Interface Group. Dampen an Interface Down incident only for the interfaces in a specified Interface Group that you know will be intermittently unavailable.
2	Node Settings	Select this tab to specify that you want to configure Suppression, Enrichment, Dampening, Actions, and Diagnostic Selections for a specified Node Group.	Change the Severity and Message of an incident configuration for the nodes in a specified Node Group.
3	Suppression	Select this tab when you want to discard an incident before it appears in an incident view.	Discard an incident if it is in response to a particular status change notification trap.


Overview of Incident Configuration Tabs, continued

	Configuration Option	When to Use	Example
4	Enrichment	<p>Select this tab when you want to fine tune any of the following for a selected incident configuration:</p> <ul style="list-style-type: none"> • Category • Family • Severity • Priority • Correlation Nature • Message • Assigned To • Add a node or interface Custom Attribute to an incident 	Change the Severity and Message of an incident configuration.
5	Dampening	<p>Select this tab to delay (dampen) the following for an incident configuration:</p> <ul style="list-style-type: none"> • Appearance within Incident views in the NNMi Console • Execution of Incident Actions • Execution of Diagnostics <div> <p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – click here for more information.</p> </div>	<p>Lengthen the Dampen Interval for the Interface Down incident Configuration provided by NNMi.</p> <p>Disable Dampening for the Interface Down Incident Configuration provided by NNMi.</p>
6	Deduplication	<p>Select this tab to correlate incidents that are identified as duplicates based on one or more Custom Incident Attribute (CIA) or SNMP trap varbind values.</p> <p>To help your operators understand the magnitude or significance of the problem, NNMi tracks the number of duplicates generated. This value is captured as the Duplicate Count attribute. It is incremented on the Duplicate Correlation incident. Its Correlation Nature</p>	Identify any CiscoLinkDown incidents as duplicates if the cia_address value is the same for the incident's Source Object.

Overview of Incident Configuration Tabs, continued

	Configuration Option	When to Use	Example
		<p>attribute value is  Dedup Stream Correlation.</p> <p>NNMi also records the following information related to duplicate incidents:</p> <p>First Occurrence Time: Indicates the timestamp of the first occurrence of a duplicate incident.</p> <p>Last Occurrence Time: Indicates the timestamp of the latest notification for a set of duplicate incidents.</p> <p>Count: Specifies the number of duplicate incidents for the current configuration that NNMi stores at one time. For example, if the Count is 10, after NNMi receives 10 duplicate incidents, NNMi deletes the first (oldest) duplicate incident and keeps the eleventh. (NNMi stores ten maximum.)</p> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: A Duplicate Correlation incident inherits the Dampening settings of its Correlated Children. If the Correlated Children are Closed while Dampened, and therefore deleted, NNMi retains the parent Duplicate Correlation incident. See "Dampening Incident Configurations" on page 769 for more information about Dampening an Incident Configuration.</p> </div>	
7	Rate	<p>Select this tab to measure the rate of incoming incidents within a defined time period and correlate any incidents that occur within the specified time period.</p> <p>NNMi stores the following information related to rate:</p> <p>Count: Indicates the rate at which the incident must occur within the specified timeframe.</p> <p>Hours, Minutes, and Seconds: Used to measure the time within the rate must occur</p> <p>First Occurrence Time: Indicates the time at which the measured rate was reached.</p> <p>Last Occurrence Time: Indicates the last time which the incident occurred.</p> <p>NNMi updates the Correlation Notes with the number of incidents that have occurred within the specified time</p>	<p>If a connection is intermittently down three times within 30 minutes; correlate the Connection Down incidents.</p>

Overview of Incident Configuration Tabs, continued


	Configuration Option	When to Use	Example
		<p>period. For example, 5 in 5 minutes.</p> <p>Note: An incident with a Correlation Nature attribute value of  Rate Stream Correlation inherits the Dampening settings of its Correlated Children. If the Correlated Children are Closed while Dampened, and therefore deleted, NNMi retains the parent Rate Correlation incident. See "Dampening Incident Configurations" on page 769 for more information about Dampening an Incident Configuration.</p>	
8	Actions	Select this tab to configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (Registered).	<p>When an incident is generated (Registered), open a trouble ticket.</p> <p>After the incident is Closed, close the trouble ticket.</p>
9	Forward to Global Managers	(<i>NNMi Advanced - Global Network Management feature</i>) Select the Global Manager Forwarding tab when you want to forward specific SNMP traps from your NNMi management server (a Regional Manager) to all Global Managers in your Global Network Management environment.	Forward all CiscoLinkDown incidents to the Global Manager.

You can also create Pairwise Configurations and your own Custom Correlations as described in the table below. See ["About Pairwise Configurations" on page 746](#) and ["Configure Custom Correlations" on page 769](#) for more information.

Additional Configuration Options

	Configuration Option	When to Use	Example
	Pairwise Configurations	<p>Select the Pairwise Configurations view under the Incidents folder to pair the first occurrence of an incident to another subsequent incident.</p> <p>Note: NNMi provides Correlation Notes information only when the Causal Engine has analyzed and Closed the incident. Software that is integrated with NNMi might</p>	Correlate a CiscoLinkDown incident as the Child Incident for a CiscoLinkUp incident.

Additional Configuration Options, continued

Configuration Option	When to Use	Example
	also provide information identifying the reason an incident was Closed. Any time an incident is Closed manually (for example, by the network operator), NNMi does not provide Correlation Notes information.	
Custom Correlations	<p>Select the Custom Correlation Configuration view under the Incidents folder of the  Configuration workspace to correlate incidents using regular expressions to define the relationships between Parent and Child Incidents. This feature is useful when you want to define a relationship between a number of incidents potentially from different network objects that form a logical set to identify a problem. The set of correlations is considered complete if all of the incidents arrive within a specified time window.</p> <p>When configuring a Custom Correlation, you select the Parent and Child Incident configurations, the time window, and the regular expression that defines the relationship requirements that must be met before the incidents are correlated.</p>	Correlate Interface Down incidents that occur for subinterfaces under the Interface Down incident generated for the main interface

See ["Configuring Incidents" on page 667](#) for more information about the Incident Configuration options. See ["Load SNMP Trap Incident Configurations" on page 873](#) for more information about how to specify which SNMP traps you want to receive by automatically creating or updating an incident configuration for an SNMP trap using a MIB file.

Related Topics

["Configure Management Events" on page 1236](#)

["Configure SNMP Trap Incidents" on page 886](#)

["Configure Syslog Message Incidents \(HP ArcSight\)" on page 1068](#)

Correlate Duplicate Incidents (Deduplication Configuration)

The deduplication configuration determines what values NNMi should match to detect when an SNMP Trap Incident, Management Event Incident, or Syslog Message Incident is a duplicate.

You can provide the required information within the following contexts:

["Deduplication Comparison Parameters Form \(SNMP Trap Incident\)" on page 1036](#)

["Deduplication Comparison Parameters Form \(Syslog Message\) \(HP ArcSight\)" on page 1211](#)

["Deduplication Comparison Parameters Form \(Management Events\)" on page 1379](#)

Deduplication Comparison Parameters Form

Custom Incident Attributes (CIAs) are used as parameter values. Parameter values enable accurate identification of duplicate incidents. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

You can provide the required information within the following contexts:

- ["Deduplication Comparison Parameters Form \(SNMP Trap Incident\)" on page 1036](#)
- ["Configure Deduplication for a Syslog Message Incident \(HP ArcSight\)" on page 1204](#)
- ["Deduplication Comparison Parameters Form \(Management Events\)" on page 1379](#)

Track Incident Frequency (Rate: Time Period and Count)

Use Rate Configuration to track incident patterns *based on the number of incident reoccurrences within a specified time period*. After the count within the specified time period is reached, NNMi emits a Rate Correlation incident and continues to update the Correlation Notes with the number of occurrences within that rate.

You can provide the required information within the following contexts:

- ["Configure Rate \(Time Period and Count\) for an SNMP Trap Incident" on page 1038](#)
- ["Configure Rate \(Time Period and Count\) for a Syslog Message Incident \(HP ArcSight\)" on page 1213](#)
- ["Configure Rate \(Time Period and Count\) for a Management Event Incident" on page 1380](#)

About Pairwise Configurations

Often two incidents have a logical relationship to each other, for example, CiscoLinkDown followed by CiscoLinkUp. There is no need for both incidents to take up room in your Incident view. Nesting the two together helps you do your job quickly and efficiently.

Use the Pairwise Configuration to pair up the occurrence of one incident with another subsequent incident. When the second incident in the pair occurs, the first incident becomes a correlated child incident within the parent incident. See ["Incident Pair \(Pairwise\) Configurations Provided by NNMi" on page 748](#) for ideas.

When using Pairwise Configurations, note the following:

- You can use Payload Filters (for example, with trap varbinds) to identify the first and second incidents in a Pairwise Configuration.
- You can specify the same incident (for example, the same trap OID) as both the first and second incident configuration for a Pairwise Configuration.
- Using the Payload Filter to distinguish the first and second incidents (the first could represent a non-normal state and the second a normal state), different instances of the same incident configuration can cancel one another.
- You can also set up the Payload Filters such that the same incident instance cancels itself.
- You can use the same incident configuration in multiple Pairwise Configurations. For example:
 - Incident configuration A cancels both incident configuration B and incident configuration C
 - Incident configuration A cancels incident configuration B and incident configuration B cancels incident configuration C.
- Single incident instance can cancel multiple incident instances (for example, one Link Up trap cancels multiple instances of a Link Down trap).

Note: If multiple Link Up/Link Down trap pairs are received within a 30 seconds, NNMi investigates only once (generates SNMP traffic).

- Use the Duration time to specify the time in which the second incident configuration cancels the first incident configuration. This Duration is calculated from the `originOccurrenceTime` of the second incident backwards in time, canceling any number of first incidents within the Duration specified.
- You can also specify whether to delete any incidents that were canceled according to the Pairwise Configuration and that occurred within the time period specified by the Duration attribute.
- When matching incidents, NNMi automatically takes into account the following values:
 - **SNMP Trap incidents.** NNMi takes into account from which device the trap originated using the `cia.address` value of the source address of the trap.
 - **Management Event incidents.** NNMi takes into account the name of the incident's Source Object and Source Node.

Tip: NNMi displays the Name value used to identify the Source Node and Source Object in the **Source Node** and **Source Object** attribute for each incident in the Incident form.

- **Syslog Message incidents.** NNMi does not automatically use any matching criteria.

Tip: When configuring the Matching Criteria, you do not need to specify any of the `cia` Names that NNMI automatically takes into account. See ["Matching Criteria Configuration Form \(Identify Incident Pairs\)" on page 762](#) for more information.

Some incident pairs require extensive details to verify an accurate match. If both incidents have custom incident attributes, you can refine the match criteria beyond the values that NNMI automatically takes into account. See ["Matching Criteria Configuration Form \(Identify Incident Pairs\)" on page 762](#) and ["Configure a Payload Filter to Enrich a Pairwise Incident Configuration" on page 755](#) for more information.

Related Topics:

["Prerequisites for Pairwise Configurations" on page 750](#)

["Pairwise Configuration Form \(Correlate Pairs of Incidents\)" on page 752](#)

Incident Pair (Pairwise) Configurations Provided by NNMI

NNMI provides the pairwise configurations described in the following table.

Pairwise Configurations Provided by NNMI

Name	Description
CiscoLinkDownUpPair	Cancels a CiscoLinkDown incident with a CiscoLinkUp incident on the same interface for the same SNMP agent address. This configuration is used for known Cisco devices.
CiscoModuleDownUpPair	Cancels a Cisco Module Down incident with a Cisco Module Up incident from the same module and SNMP agent address.
RcAggLinkDownUpPair	(<i>NNMI Advanced</i>) Cancels an RcAggLinkDown incident with an RcAggLinkUp incident from the same Multi-Link Trunk (MLT) Aggregator ID (from the MIB) and SNMP agent address. (Link Aggregation ¹ or Split Link Aggregation ²)
RcChasFanDownUpPair	Physical Sensor object incident: Cancels an

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Pairwise Configurations Provided by NNMi, continued


Name	Description
	RcChasFanDown incident with an RcChasFanUp incident from the same fan ID (from the MIB) and SNMP agent address.
RcChasPowerSupplyDownUpPair	Physical Sensor object incident: Cancels an RcChasPowerSupplyDown incident with an RcChasPowerSupplyUp incident from the same power supply ID (from the MIB) and SNMP agent address.
RcSmltIsLinkDownUpPair	Cancels an RcSmltIsLinkDown incident with an RcSmltIsLinkUp incident from the same SNMP agent address.
RcnAggLinkDownUpPair	(<i>NNMi Advanced</i>) Cancels an RcnAggLinkDown incident with an RcnAggLinkUp incident from the same Multi-Link Trunk (MLT) Aggregator Link ID (from the MIB) and SNMP agent address. (Link Aggregation¹ or Split Link Aggregation²)
RcnChasFanDownUpPair	Physical Sensor object incident: Cancels an RcnChasFanDown incident with an RcnChasFanUp incident from the same fan ID (from the MIB) and SNMP agent address.
RcnChasPowerSupplyDownUpPair	Physical Sensor object incident: cancels a RcnChasPowerSupplyDown incident with an RcnChasPowerSupplyUp incident from the same power supply ID (from the MIB) and SNMP agent address.
RcnSmltIsLinkDownUpPair	Cancels an RcnSmltIsLinkDown incident with an RcnSmltIsLinkUp incident from the same SNMP agent address.
SnmpLinkDownUpPair	Cancels an SNMPLinkDown incident with an SNMPLinkUp incident on the same interface for the same SNMP agent address.

To see or modify these incident pair configurations:

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

1. Navigate to the **Pairwise Configurations** view.
 - a. In the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Pairwise Configurations**.
2. Double-click the row representing the configuration you want to see or modify.

See ["Pairwise Configuration Form \(Correlate Pairs of Incidents\)" on page 752](#) for more information.
3. When you are finished, click  **Save and Close** to save your changes.

Configure Pairwise Configurations

Use the Pairwise Configuration to pair the occurrence of one incident with another subsequent incident. See ["About Pairwise Configurations" on page 746](#) for more information.

When configuring Pairwise Configurations you perform the following tasks:

- [Use the Basics Pane of the Pairwise Configuration Form to Correlate Pairs of Incidents](#)
- [Optional. Configure the First and Second Incident Payload Filters](#)
- [Optional. Configure the Matching Criteria](#)

Prerequisites for Pairwise Configurations

Tip: When configuring the Matching Criteria, you do not need to specify any of the `ciaNames` that NNMi automatically takes into account. See ["Matching Criteria Configuration Form \(Identify Incident Pairs\)" on page 762](#) for more information.

When matching incidents, NNMi automatically takes into account the following values:

- **SNMP Trap incidents.** NNMi takes into account from which device the trap originated using the `cia.address` value of the source address of the trap.
- **Management Event incidents.** NNMi takes into account the name of the incident's Source Object and Source Node.

Tip: NNMi displays the Name value used to identify the Source Node and Source Object in the **Source Node** and **Source Object** attribute for each incident in the Incident form.

- **Syslog Message incidents.** NNMi does not automatically use any matching criteria.

If you must provide more details to accurately identify the logical pair of incidents (from among all possible incidents related to that source node), complete the Optional step 6 below.

Complete the following steps before attempting to set up a Pairwise Configuration:

1. Identify the incidents or SNMP traps that consist of the logical relationship that makes the pair.

Note: The incident configurations you select can be the same or different for each pair.

2. Configure those two incidents or traps within NNMi, if they are not already configured:
 - See ["Incident Configurations Provided by NNMi" on page 688](#).
 - See ["Configure SNMP Trap Incidents" on page 886](#).
3. Generate one of each of the incidents or SNMP traps so you can see an example of each in one of the NNMi Incident views. See [Views Available in NNMi](#).
4. To display the Incident form, double-click the row representing the first sample incident for the pair .

Navigate to the Custom Attributes tab. These are the custom incident attributes available to use in step 6, below. See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#) for more information about Custom Attributes.

The screenshot displays the HP Network Node Manager i Software interface. At the top, there's a navigation bar with 'Open Root Cause Incidents' and 'Incidents'. A dropdown menu is open, showing 'InterfaceDown'. Below this is a toolbar with icons for 'Save and Close', 'Delete Incident', and a search icon. The main area is divided into two panes. The left pane, titled 'Basics', contains fields for 'Message' (Interface Down), 'Severity' (Critical), 'Priority' (None), 'Lifecycle State' (Registered), 'Source Node' (CH-KVM), 'Source Object' (Se0/0/2), and 'Assigned To'. The right pane, titled 'Custom Attributes', shows a table with two rows of attributes. A dropdown menu is open, showing options like 'General', 'Correlated Parents', 'Correlated Children', 'Custom Attributes', 'Diagnostics', and 'Registration'. The table has columns for 'Name', 'Type', and 'Value'. The first row is 'com.hp.ov.nms.apa.symptom' with type 'String' and value 'IfOperStatusDown'. The second row is 'com.hp.ov.nms.apa.symptom_1' with type 'String' and value 'InterfaceAdminUpC'. At the bottom, there's a status bar showing 'Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF'.

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF




5. Repeat the previous step with the second sample incident for the pair.
6. *Optional.* If both Pairwise incidents have custom attributes, you can refine the match criteria beyond what NNMi automatically uses to determine a match. Some incident pairs require extensive details to verify an accurate match. See ["Pairwise Configuration Form \(Correlate Pairs of Incidents\)"](#) below.

Pairwise Configuration Form (Correlate Pairs of Incidents)

Use the Pairwise Configuration to pair the occurrence of one incident with another subsequent incident. See ["About Pairwise Configurations"](#) on page 746 for more information.

To configure incident pairs:

1. Complete the steps in ["Prerequisites for Pairwise Configurations"](#) on page 750 so you know exactly which two incidents or traps belong to this logical pair.
2. Navigate to the **Pairwise Configurations** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.

- c. Select **Pairwise Configurations**.
- d. Do one of the following:
 - To create a new pair configuration, click the  New icon, and continue.
 - To edit an existing pair configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete a pair configuration, select a row and click the  Delete icon.
3. Provide the basic definition of the pair of incidents for this correlation (see [table](#)).
4. When matching incidents, NNMi automatically takes into account the following values:
 - **SNMP Trap incidents.** NNMi takes into account from which device the trap originated using the `cia.address` value of the source address of the trap.
 - **Management Event incidents.** NNMi takes into account the name of the incident's Source Object and Source Node.

Tip: NNMi displays the Name value used to identify the Source Node and Source Object in the **Source Node** and **Source Object** attribute for each incident in the Incident form.


- **Syslog Message incidents.** NNMi does not automatically use any matching criteria.

Some incident pairs require additional details to verify an accurate match. If both incidents have custom incident attributes, you can refine the match criteria.

Optional. Navigate to the **First Incident Payload Filter** and **Second Incident Payload Filter** tabs, and specify the payload filter to use when identifying a valid pair of incidents. See ["Configure a Payload Filter to Enrich a Pairwise Incident Configuration" on page 755](#).









Optional. Navigate to the **Matching Criteria** tab, and provide one or more custom incident attribute sets for NNMi to use as a filter when identifying a valid pair of incidents. See ["Matching Criteria Configuration Form \(Identify Incident Pairs\)" on page 762](#).

Tip: When configuring the Matching Criteria, you do not need to specify any of the `ciaNames` that NNMi automatically takes into account. See ["Matching Criteria Configuration Form \(Identify Incident Pairs\)" on page 762](#) for more information.

Then, click  **Save and Close** to save your changes and return to the previous configuration form.

The next time the two incidents in this pair are generated, the first one becomes a Child Incident of the second one. See ["About Pairwise Configurations" on page 746](#) for an example.

Pairwise Configuration Definition

Attribute	Description
Name	<p>The name is used to identify the pairwise configuration and must be unique. Use a name that will help you to remember the purpose for this pairwise configuration.</p> <p>Maximum length is 64 characters. Alpha-numeric characters are permitted. No spaces are permitted.</p>
Enabled	In the Basics group, verify that Enabled <input checked="" type="checkbox"/> is selected.
First Incident Configuration	<p>Identify the incident in the pair that would occur first in the logical sequence. Click the  ▾ Lookup icon and select  Quick Find. Choose the name of one of the predefined incident configurations. If you cannot find it, see "Incident Configurations Provided by NNMi" on page 688.</p> <p>This First Incident becomes the Child Incident when the Second (Parent) Incident occurs. For example, in the CiscoLinkDownUp Pairwise configuration, if a Cisco Link Up (Second Incident) occurs after a Cisco Link Down (First Incident), the Cisco Link Down is cancelled and correlated as a Child Incident under the Cisco Link Up.</p>
Second Incident Configuration	<p>Identify the incident in the pair that would occur second in the logical sequence. Click the  ▾ Lookup icon and select  Quick Find. Choose the name of one of the predefined incident configurations. If you cannot find it, see "Incident Configurations Provided by NNMi" on page 688.</p> <p>This Second Incident becomes the Parent Incident if it occurs after the First Incident. For example, in the CiscoLinkDownUp Pairwise configuration, if a Cisco Link Up (Second Incident) occurs after a Cisco Link Down (First Incident), the Cisco Link Down is cancelled and correlated as a Child Incident under the Cisco Link Up.</p>
Description	<p><i>Optional.</i> Explain the purpose of your pairwise configuration for future reference.</p> <p>Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>
Author	<p>Indicates who created or last modified the Correlation Rule.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> </div> <ul style="list-style-type: none"> Click  ▾ Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value.
Duration	NNMi uses the value you enter to determine the duration window in which it




Pairwise Configuration Definition , continued


Attribute	Description
	<p>correlates the Pairwise incidents you specify. During the timeframe specified, NNMi enables a single (parent) incident to cancel multiple (child) incidents.</p> <p>The Duration is calculated from the <code>originOccurrenceTime</code> of the parent incident backwards in time, canceling any child incidents within the Duration specified.</p> <p>Note the following:</p> <ul style="list-style-type: none">• By default, the Duration value is 0 (zero). <p>When the Duration value is 0, NNMi finds the most recently occurring incident that matches the First Incident specified in the Pairwise configuration, regardless of time. See First Incident Configuration for more information.</p> <ul style="list-style-type: none">• The maximum duration value is 365 days.
Delete when Canceled	<p>When enabled <input checked="" type="checkbox"/>, after the Duration is reached, NNMi deletes any incidents that were canceled according to the Pairwise configuration and that occurred within the timeframe specified by the Duration attribute.</p> <p>When disabled, NNMi cancels the pairwise incidents as configured, but does not delete them.</p>

Configure a Payload Filter to Enrich a Pairwise Incident Configuration

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be correlated in the Pairwise configuration. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression for a Pairwise Incident configuration:

1. Navigate to the **Pairwise Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Pairwise Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.

2. Select the **First Incident Payload Filter** or **Second Incident Payload Filter** tab.
3. Do one of the following:
 - a. To create a new configuration, click the * New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue..
8. Define your Payload Filter (see [table](#)). Also see [Guidelines for Creating a Payload Filter](#). For more information about Payload Filters, [click here](#).

A Payload Filter enables you to further define the filters to be used for selecting the incidents to participate in the Pairwise Configuration. A Payload Filter selects incoming incidents based on Custom Incident Attribute names (ciaName) and values (ciaValue).


- a. Plan out the logic needed for your Filter String.
- b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:



The screenshot shows the **Filter Editor** interface. At the top, there are three fields: **Attribute** (set to 'ciaName'), **Operator** (set to '='), and **Value** (set to '.1.3.6.1.4.1.9.9.13.1.2.1.7'). To the right of these fields are three buttons: **Append**, **Insert** (highlighted with a red box), and **Replace**. Below these fields is a logic flow diagram. It shows a tree structure with **AND** and **NOT** operators. A red arrow points from the **Insert** button to the logic flow diagram, with the text "Highlight the location in the logic flow, then click Insert to define the filter requirement". At the bottom, there is a **Filter String** field containing the text "(() AND NOT ())". A red arrow points from the **Insert** button to the first set of parentheses in the filter string.

9. Click  **Save and Close**.

10. Click  **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • <code>ciaName</code> • <code>ciaValue</code>
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 436"> <p>The screenshot shows a table with two columns: 'Operator' and 'Value'. Under 'Operator', the word 'between' is selected in a dropdown menu. Under 'Value', the numbers '1' and '4' are entered on separate lines.</p> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="467 590 1320 653"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <div data-bbox="451 915 837 1050"> <p>The screenshot shows a table with two columns: 'Operator' and 'Value'. Under 'Operator', the word 'in' is selected in a dropdown menu. Under 'Value', the numbers '4' and '5' are entered on separate lines.</p> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="467 1173 1320 1236"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.

Payload Filter Editor Settings, continued

Attribute	Description				
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: ciaValue not in <div data-bbox="446 1197 875 1331" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>not in</td> <td>1 2</td> </tr> </tbody> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. 	Operator	Value	not in	1 2
Operator	Value				
not in	1 2				

Payload Filter Editor Settings, continued

Attribute	Description
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<<i>literal_value</i>>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.

Additional Filters Editor Buttons, continued

Button	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Matching Criteria Configuration Form (Identify Incident Pairs)

Tip: When configuring the Matching Criteria, you do not need to specify any of the `ciaNames` that NNMi automatically takes into account .

When matching incidents, NNMi automatically takes into account the following values:

- **SNMP Trap incidents.** NNMi takes into account from which device the trap originated using the `cia.address` value of the source address of the trap.
- **Management Event incidents.** NNMi takes into account the name of the incident's Source Object and Source Node.

Tip: NNMi displays the Name value used to identify the Source Node and Source Object in the **Source Node** and **Source Object** attribute for each incident in the Incident form.

- **Syslog Message incidents.** NNMi does not automatically use any matching criteria.


Some incident pairs require additional details to verify an accurate match. If both Pairwise incidents have custom incident attributes, you can use the Matching Criteria Configuration form to refine the matching criteria beyond what NNMi includes automatically.


Tip: You can also use Payload Filters to define incident pairs. See ["Configure a Payload Filter to Enrich a Pairwise Incident Configuration"](#) on page 755 for more information.

Specify one or more values for NNMi to use as a filter when identifying a valid pair of incidents.

You can use any Custom Incident Attributes (CIAs) displayed on the [Incident form](#) of the two incidents you are associating into a logical pair. The group of available CIAs depends on which incidents you select. There are two categories of possible CIAs:

- SNMP trap varbinds identified by the Abstract Syntax Notation value (ASN.1) or position. For example, a varbind OID of .1.3.6.1.2.1.2.2.1.1 or a position number of 25.
- Custom attributes provided by NNMi (Name = cia_*). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.






The screenshot displays the HP Network Node Manager i Software interface. At the top, a blue header bar contains the text 'Open Root Cause Incidents' and 'Incident'. Below this, a toolbar includes icons for 'Save and Close' and 'Delete Incident'. The main window is divided into two panes. The left pane, titled 'Basics', contains a 'Message' field with the text 'Interface Down', and three dropdown menus for 'Severity' (set to 'Critical'), 'Priority' (set to 'None'), and 'Lifecycle State' (set to 'Registered'). Below these are fields for 'Source Node' (CH-KVI), 'Source Object' (Se0/0/2), and 'Assigned To'. The right pane, titled 'Custom Attributes', shows a table with two columns: 'Name' and 'Value'. The table contains two rows: 'com.hp.ov.nms.apa.symptom' with value 'IfOperStatusDown', and 'com.hp.ov.nms.apa.symptom_1' with value 'InterfaceAdminUpC'. A status bar at the bottom of the right pane indicates 'Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF'. A footer bar at the bottom of the entire window displays 'Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R'.

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

For example:

- If you specify a First Incident Criteria and Second Incident Criteria of .1.3.6.1.2.1.2.2.1.1, the first incident's varbind value for the specified OID must match the second incident's varbind value for the specified OID to confirm a match.
- If you specify two custom attribute sets (one with both First Incident Criteria and Second Incident Criteria set to position 7, and one with both First Incident Criteria and Second Incident Criteria set to position 25), then the values for both custom attributes (varbind position 7 and varbind position 25) in both Incidents must match to confirm the logical pair.

To configure which attributes NNMi uses to verify incident identity:

1. Complete the steps in ["Prerequisites for Pairwise Configurations" on page 750](#) so your choices for this Item Pair configuration are displayed in the NNMi console. (Two Incident forms should be open before you proceed to step 2.)
2. Navigate to the **Matching Criteria Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Pairwise Configurations**.
 - d. Do one of the following:
 - To create a new pairwise configuration, click the  New icon.
 - To edit a pairwise configuration, double-click the row representing the configuration you want to edit.
 - e. Navigate to the **Matching Criteria** tab.
 - f. Do one of the following:
 - i. To create a new matching criteria configuration, click the  New icon.
 - ii. To edit a matching criteria configuration, double-click the row representing the configuration you want to edit.
3. Specify the Object Identifier (OID) or trap varbind position number you want NNMi to use to confirm the identity of the pair of incidents (see [table](#)).
4. Click  **Save and Close** to save your changes and return to the previous form.
5. Repeat steps 1-3 any number of times. The incidents must pass all Matching Criteria, plus have identical Source Node and Source Object attribute values.

Matching Criteria Configuration

Attribute	Description
First Incident Criterion	<p>Type the specification required to confirm the identify of the first incident in this logical pair of incidents. Provide one of the following:</p> <ul style="list-style-type: none">• The SNMP trap varbind Abstract Syntax Notation value - ASN.1 (OID)• The SNMP trap varbind position number <div>Caution: The varbind position numbers are not visible in the table on the Incident form's Custom Attributes tab. And the rows in that table are sorted by the visible column headings and are not in varbind position order. You must access the vendor-supplied information in the underlying MIB file to determine the appropriate position number for any particular varbind.</div> <ul style="list-style-type: none">• The Custom Attribute Name value (see "Custom Incident Attributes Provided by NNMi (Information for Administrators)" on page 733 or the Name column in the table on the Incident Form: Custom Attributes Tab of the Incident you are configuring as a member of this logical pair).
Second Incident Criterion	<p>Type the specification required to confirm the identify of the second incident in this logical pair of incidents. Provide one of the following:</p> <ul style="list-style-type: none">• The SNMP trap varbind Abstract Syntax Notation value - ASN.1 (OID)• The SNMP trap varbind position number <div>Caution: The varbind position numbers are not visible in the table on the Incident form's Custom Attributes tab. And the rows in that table are sorted by the visible column headings and are not in varbind position order. You must access the vendor-supplied information in the underlying MIB file to determine the appropriate position number for any particular varbind.</div> <ul style="list-style-type: none">• The Custom Attribute Name value (see "Custom Incident Attributes Provided by NNMi (Information for Administrators)" on page 733 or the Name column in the table on the Incident Form: Custom Attributes Tab of the Incident you are configuring as a member of this logical pair).

Related Topics

["Incident Pair \(Pairwise\) Configurations Provided by NNMi" on page 748](#)

Pairwise Configuration Example

Tip: When configuring the Matching Criteria, you do not need to specify any of the ciaNames

that NNMI automatically takes into account . See "[Matching Criteria Configuration Form \(Identify Incident Pairs\)](#)" on page 762 for more information.

When matching incidents, NNMI automatically takes into account the following values:





- **SNMP Trap incidents.** NNMI takes into account from which device the trap originated using the `cia.address` value.
- **Management Event incidents.** NNMI takes into account the unique name of the incident's Source Object and Source Node.


Tip: NNMI displays the unique name value used to identify the Source Node and Source Object in the **Source Node** and **Source Object** attribute for each incident in the Incident form.

- **Syslog Message incidents.** NNMI takes into account the value of `event.deviceAddress`.

This example correlates the same `ospfIfStateChange` trap in a Pairwise Configuration. This example Pairwise Configuration, specifies that when the `ospfIfState` value changed from 1 (down) to any value other than 1 (down), NNMI correlates the `ospfIfStateChange` incidents. See "[Pairwise Configuration Form \(Correlate Pairs of Incidents\)](#)" on page 752 for more information about how to specify a Pairwise configuration.

To use the same SNMP trap in a Pairwise configuration:

1. Navigate to the **Configuration** workspace.
2. Click to expand the **Incidents** folder.
3. Select **Pairwise Configurations**.
4. Click  (New) to create a Pairwise Configuration.
5. Enter a **Name** that is used to identify the Pairwise Configuration.
6. Make sure **Enabled**  is checked.
7. In the **First Incident Configuration** attribute, select **Quick Find** from the  ▼Lookup menu.
8. Select **OSPFIIfStateChange**.
9. In the **Second Incident Configuration** attribute, select **Quick Find** from the  ▼Lookup menu.
10. Select **OSPFIIfStateChange**.
11. Enter a **Description** for the Pairwise Configuration.

12. Either leave the default value **Customer** or select **New** from the  Lookup menu to specify an Author name.
13. Select **Days** from the **Duration** drop-down menu.
14. Enter the number of days in which NNMi correlates the Pairwise Configuration you specify .
15. If you want NNMi to delete the Pairwise incidents when they are canceled, click **Delete When Canceled** ☒.
16. Navigate to the **First Incident Payload Filter** tab.
17. Use the following expression to indicate you want to use the OSPFIfState value of 1 (down):
`ciaName = 1.3.6.1.2.1.14.7.1.12 AND ciaValue = 1`
18. Navigate to the **Second Incident Payload Filter** tab.
19. Use the following expression to indicate you want to use any OSPFIfState value that is other than 1 (down):
`ciaName = 1.3.6.1.2.1.14.7.1.12 AND ciaValue != 1`

Note: You do not need to specify Matching Criteria. NNMi checks for a match using the value of `cia.address`.

20. Click **Save and Close** to save your changes and return to the Pairwise Configurations view.

Rate Comparison Parameters Form

Custom Incident Attributes (CIAs) are used as parameter values. Parameter values enable accurate identification of duplicate incidents. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = `asn_*`)
- Custom attributes provided by NNMi (Name = `cia.*`, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

You can provide the required information within the following contexts:

["Rate Comparison Parameters Form \(SNMP Trap Incident\)" on page 1041](#)

["Rate Comparison Parameters Form \(Syslog Message\) \(HP ArcSight\)" on page 1216](#)

["Rate Comparison Parameters Form \(Management Events\)" on page 1383](#)

Suppress Incident Configurations

NNMi enables you to suppress incidents based on Interface Group, Node Group, or default Suppression settings. NNMi applies your Suppression settings in the following order. Only the first

match applies.

1. Interface Group (SNMP Trap Configuration Form: Interface Settings tab)
2. Node Group (SNMP Trap Configuration Form: Node Settings tab)
3. Enrich configuration settings without specifying an Interface Group or Node Group (SNMP Trap Configuration Form: Enrichment tab)

You can provide the required information within the following contexts:

["Configure Suppression Settings for an SNMP Trap Incident" on page 1004](#)

["Configure Suppression Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1179](#)

["Configure Suppression Settings for a Management Event Incident" on page 1347](#)

Enrich Incident Configurations

NNMi enables you to fine tune and enhance incidents based on Interface Group, Node Group, or default Enrichment settings. NNMi applies your Enrichment settings in the following order. Only the first match applies:

1. Interface Group (Interface Settings tab)
2. Node Group (Node Settings tab)
3. Enrich configuration settings without specifying an Interface Group or Node Group (Enrichment tab)

The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To

Note: Any configuration you specify for Severity, Priority, or Message overrides those values provided in the Basics information.

You can provide the required information within the following contexts:

["Configure Enrichment Settings for an SNMP Trap Incident" on page 1013](#)

["Configure Enrichment Settings for a Management Event Incident" on page 1356](#)

Dampening Incident Configurations

NNMi enables you to delay (dampen) the following for an incident configuration:

- Appearance within Incident views in the NNMi Console
- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

You can provide the required information within the following contexts:

["Configure Dampening Settings for an SNMP Trap Incident" on page 1018](#)

["Configure Dampening Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1194](#)

["Configure Dampening Settings for a Management Event Incident" on page 1361](#)

Configure Custom Correlations

For information about each Custom Correlation Configuration tab:



NNMi enables you to correlate groups of incidents under a Parent Incident. This feature is useful when you want to define a relationship between a number of incidents potentially from different network objects that form a logical set to identify a problem. The set of correlations is considered complete if all of the incidents arrive within a specified time window.

When configuring a Custom Correlation, you configure one or both of the following:

Rule	Description
Correlation Rule	<p>Tip: Configure a Correlation Rule when you want to correlate only one type of Child incident Configuration with a Parent Incident Configuration that is generated by NNMi.</p> <p>Use a Correlation Rule to specify the following:</p> <ul style="list-style-type: none">• Parent Incident Configuration• Child Incident Configuration• Filters that NNMi should use when selecting the Parent and Child Incident instances for correlation

Rule	Description
	<ul style="list-style-type: none"> The time window within which NNMi begins to correlate the incidents. <p>Note: If the Parent and Child incidents occur within the Correlation Window Duration specified, NNMi begins to correlate the incidents as soon as they occur.</p> <ul style="list-style-type: none"> The regular expression (Correlation Filter) that defines the relationship requirements that must be met before the incidents are correlated <p>The Parent and Child Incident do not have to be the same incident configuration. For example, you can correlate an Address Not Responding incident with an Interface Down incident.</p> <p>See "Correlation Rule Example" on page 804 for a step-by-step example of how the Subinterface Correlation Rule provided by NNMi was created.</p>
Causal Rule	<p>Tip: Configure a Causal Rule when you want to cause NNMi to generate a Parent Incident and you want to correlate one or more Child Incident Configurations under the Parent Incident that you cause to be generated.</p> <p>Use a Causal Rule to specify the following:</p> <ul style="list-style-type: none"> Parent Incident Configuration to be generated One or more Child Incident Configurations to be correlated under the generated Parent Incident Filters that NNMi should use when selecting the Child Incident instances for correlation Source Object and Source Node filters to be used to determine the Source Node and Source Object for the generated Parent Incident The time window that must be met before NNMi correlates the incidents. <p>Note: NNMi waits until the Correlation Window Duration has passed before generating the Parent Incident and correlating its Child Incidents.</p> <p>To establish a relationship between multiple Custom Correlations, configure a Causal Rule to generate a Parent Incident that becomes the Child Incident of another Parent Incident.</p> <p>See "Causal Rule Example" for a step-by-step example of creating a Causal Rule.</p>

To configure a Custom Correlation:

1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. View the configured attributes (see [table](#)).
3. Do one of the following, or both:
 - Configure one or more Correlation Rules. See "[Configure a Correlation Rule](#)" below for more information.
 - Configure one or more Causal Rules. See "[Configure a Causal Rule](#)" on page 808 for more information.
4. Click  **Save and Close** to save your changes and return to the previous form.

Custom Correlation Registration Attribute

Attribute	Description
Last Modified	The date and time the Custom Correlation configuration was last modified.

Configure a Correlation Rule

Tip: Configure a Correlation Rule when you want to correlate a Child incident Configuration under a Parent Incident Configuration that is generated by NNMI.


Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Correlation Rule limitations.





When correlating groups of incidents under an existing Parent incident, use the Correlation Rules tab to specify the Correlation Rule that defines the Parent Incident, the Child Incident, and the relationship requirements that must be met before the incidents are correlated.

See "[Correlation Rule Example](#)" on page 804 for a step-by-step example of how the Subinterface Custom Correlation Rule provided by NNMI was created.





For information about each Correlation Rules tab:

To configure a Correlation Rule:













1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.

- b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Correlation Rules** tab.
3. From the **Correlation Rules** table toolbar, do one of the following:
 - To create a Correlation Rule, click the  **New** icon, and continue.
 - To edit a Correlation Rule, click the  **Open** icon in the row representing the Correlation Rule you want to edit, and continue.
 - To delete a Correlation Rule, click the  **Delete** icon.
4. Create your Correlation Rule (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the previous form.




Correlation Rule Basic Attributes

Attribute	Description
Name	<p>Type a maximum of 64 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>The name is used to identify the Correlation Rule and must be unique. Use a name that will help you to remember the purpose of the Correlation Rule.</p>
Author	<p>Indicates who created or last modified the Correlation Rule.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> </div> <ul style="list-style-type: none"> • Click  Lookup and select  Show Analysis to display details about the currently selected Author. • Click  Quick Find to access the list of existing Author values. • Click  New to create an Author value.
Enabled	<p>If <input checked="" type="checkbox"/> enabled, the NNMi Causal Engine uses the Correlation Rule when evaluating incidents.</p> <p>If <input type="checkbox"/> disabled, the Correlation Rule is ignored.</p>
Parent Incident	Specifies the incident configuration that should be used as the Parent Incident for the Correlation Rule.

Correlation Rule Basic Attributes, continued

Attribute	Description
	<p>Note: If you want to create a rule to <i>generate</i> a Parent Incident configure a Causal Rule. See "Configure a Causal Rule" on page 808 for more information.</p> <p>To specify a Parent Incident configuration:</p> <ol style="list-style-type: none"> Click the  Lookup icon, and do one of the following: <ul style="list-style-type: none"> To display Analysis Pane information, select  Show Analysis. (See Use the Analysis Pane for more information about the Analysis Pane.) To display the list of possible incidents, select  Quick Find. In the Quick Find dialog, select the Incident of interest. To create a Parent Incident, select one of the following: <ul style="list-style-type: none">  New Management Event Configuration  New Remote NNM Event Configuration  New SNMP Trap Configuration To modify a Parent Incident, select  Open. <i>Optional.</i> To create or modify a Parent Incident, enter or modify the attribute values for the selected Incident configuration. See "Configuring Incidents" on page 667 for more information about the Incident Configuration form. Click  Save and Close to save your changes and return to the previous form.
Child Incident	<p>Specifies the incident configuration that must match an incoming incident and that should be correlated as the Child Incident for the Custom Correlation.</p> <p>To specify a Child Incident configuration:</p> <ol style="list-style-type: none"> Click the  Lookup icon, and do one of the following: <ul style="list-style-type: none"> To display Analysis Pane information, in the Quick Find dialog, select  Show Analysis. (See Use the Analysis Pane for more information about the Analysis Pane.) To create a Child Incident, select one of the following: <ul style="list-style-type: none">  New Management Event Configuration  New Remote NNM Event Configuration

Correlation Rule Basic Attributes, continued

Attribute	Description
	<ul style="list-style-type: none"> ◦  New SNMP Trap Configuration ▪ To modify a Child Incident, select  Open. <ol style="list-style-type: none"> 2. <i>Optional.</i> To create or modify a Child Incident, enter or modify the attribute values for the selected Incident configuration. See "Configuring Incidents" on page 667 for more information about the Incident Configuration form. 3. Click  Save and Close to save your changes and return to the previous form.
Correlation Window Duration	<p>The time window within which NNMi begins to correlate the incidents. Enter a number for Days, Hours, Minutes, and Seconds.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • If the Parent and Child incidents occur within the Correlation Window Duration specified, NNMi begins to correlate the incidents as soon as they occur. • If you are relating multiple Custom Correlations, make sure the Correlation Window Duration allows enough time for all of the Parent and Child incidents to be generated. For example, when correlating a trap and an Interface Down incident on an interface that is polled every 5 minutes, use a 6-minute Correlation Duration Window to guarantee that the trap on the Interface Down occurs in the same Correlation Window Duration. This is because it might take up to 5 minutes for the associated Interfaced Down incident to occur <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: This example assumes that if the Interface Down occurs before the trap, the trap is sent within 6 minutes of the Interface Down Incident.</p> </div> <ul style="list-style-type: none"> • A lengthy Correlation Window Duration can increase memory usage and subsequently affect NNMi performance. When using a long duration window, the more often the incident occurs, the greater the affect on memory. To avoid possible performance issues, use a shorter duration for incidents that occur more frequently.
Description	<p>Use the description field to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.</p> <p>Type a maximum of 2048 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ +) are permitted.</p>

Configure a Parent Incident Filter for a Correlation Rule

Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Parent Incident Filter limitations.

Tip: The Parent Incident Filter is optional, but recommended. Use of a Parent Incident Filter improves NNMi performance by reducing the set of incidents that NNMi processes.

When correlating groups of incidents under a Parent Incident, you can define the requirements for the Parent Incident. The Parent Incident tab enables you to use the Filter Editor to define these requirements. For example, you might want to specify that the Source Node of the Parent Incident be a specific node Name pattern. See [Valid Operators](#) in the table that follows for examples of valid Parent Incident Filters.

When specifying the **like** or **not like** operator, use the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at :
<http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html>

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor for Custom Correlations:

- You can use Custom Incident Attributes, attributes for an incident's Source Node or Source Object, or both to define how matching incidents should be considered for the Correlation Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For example, if the Attribute type is numeric, NNMi does a numeric comparison. If the Attribute type is textual, NNMi does a lexicographical string comparison. In all cases, when you use the **like** or **not like** operator, NNMi uses a lexicographical string comparison. [Click here](#) for more information about Attribute types:
 - `ifIndex` and `ifSpeed` are numeric Attributes.
 - Any Attribute name that begins with "is" (`isSnmInterface`, `isSnmNode`, `isNnmSystemLocal`) represents a Boolean Attribute.
 - All other Attributes are textual.
- Each set of expressions associated with a Boolean Operator (for example, AND) is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions.

- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.

Filter Editor Buttons and Drag and Drop Feature





Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none"> ■ Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS ■ Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none"> ■ Click the item you want to move before dragging it to a new location. ■ As you drag a selected item, an underline indicates the target location.

Filter Editor Buttons and Drag and Drop Feature, continued

Button or Feature	Description
	<ul style="list-style-type: none">■ If you are moving the selection up, NNMi places the item above the target location.■ If you are moving the selection down, NNMi places the item below the target location.■ If you attempt to move the selection to an invalid target location, NNMi displays an error message.

See ["Correlation Rule Example" on page 804](#) for a step-by-step example of how the Subinterface Correlation Rule provided by NNMi was created.


To configure a Parent Incident Filter:

1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Correlation Rules** tab.
3. From the **Correlation Rules** table toolbar, do one of the following:
 - To create a Correlation Rule, click the  New icon, and continue.
 - To edit a Correlation Rule, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete a Correlation Rule, click the  Delete icon.
4. Navigate to the **Parent Incident Filter** tab.

5. Create your Parent Incident Filter (see [Filter Editor Settings](#)).

Filter Editor Settings



Setting	Description
Attribute	The Attribute on which NNMI searches. See Valid Attributes below for a description of valid Attributes.
Operator	Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.
Expression	Use the Expression to complete the criteria for the Parent Incident configuration. See Valid Expressions below for more information.

6. Click  **Save and Close** to save your changes and return to the previous form.

Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMI searches. Valid attributes other than Source Node attributes depend on the Incident's Source Object. NNMI checks the Source Node as well as the Source Object for any Capability value.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none">• Boolean Attributes begin with "is" and must contain the value true or false.• Use the following syntax to specify a Custom Incident Attribute (CIA): <code>valueOfCia(<CIA_Name>)</code><ul style="list-style-type: none">■ Check the appropriate Incident form for any valid CIA Names provided by NNMI. For example: <code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)}= 5</code>■ When specifying the <CIA_Name>, you can use the syntax defined for Java regular expressions. For example, use the following syntax to specify that you want to include any CIA Name that begins with .1.3.6.1.2.1.31.1.1.1.1.: <code>\${valueOfCia(\Q.1.3.6.1.2.1.31.1.1.1.1.\E.*)}</code>■ Enclose all CIA names using the \Q and \E characters so that NNMI correctly interprets the period character. For example: <code>\${child.valueOfCia(\Qcia.address\E)}</code> <p>For more information, see the Pattern (Java Platform SE6) API documentation at http://download.oracle.com/javase/6/docs/api/java/util/regex/Patt-</p>

Valid Attributes , continued

Attribute	Description
	<p>ern.html</p> <ul style="list-style-type: none"> • If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter. • When using attributes for a Source Object, note the following: <ul style="list-style-type: none"> ▪ When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the hostedOn attribute and the Source Object is not an interface, the correlation does not occur. <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> <ul style="list-style-type: none"> ▪ <i>SNMP Trap incidents only.</i> NNMi does not find a match when the value for a Source Object is None. A Source Object attribute value of None indicates that NNMi cannot resolve the Source Object. If you want to match the incident, use one or more Source Node attributes. • If the incident does not have a Source Object, a Source Node, or both (for example, the node is not stored in the NNMi database), you must use CIAs in your filter rather than Source Object or Source Node attributes. <p>Tip: To check whether the Source Object or Source Node is stored in the NNMi database, open the incident and then select  Open from the Lookup menu for the Source Node or Source Object displayed. If a form does not open for the selected object or node, this means the source is not stored in the NNMi database.</p> <ul style="list-style-type: none"> • When specifying a Correlation Filter, precede the attribute name with either parent. or child. to specify from which incident the attribute value should be compared. For example, you might specify \${parent.hostedOn} or \${child.ifDesc}. <p>Possible Source Object choices are as follows:</p> <ul style="list-style-type: none"> • Card [click here for a list of attribute values] <p>Unique Keys from the Card Form: Capabilities Tab:</p>

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) • Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: valueOfInterfaceCa(<CA_Name>) For example: <code>\${child.valueOfInterfaceCA(Role)} = WAN Connection</code> <p>Values from the Basics Attributes listed on the Interface Form:</p> <ul style="list-style-type: none"> ■ hostedOn (Hosted On Node) You must use the full DNS name for the hostedOn value. <p>Values from the Interface Form: General Tab:</p> <ul style="list-style-type: none"> ■ ifName (name configured for the interface) ■ ifAlias (alias configured for the interface) ■ ifDesc (description configured for the interface) ■ ifIndex (index assigned to the interface) ■ ifSpeed (speed configured for the interface) When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps. <p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <=. <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the parent Node Form:</p> <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled) <p>Values from the parent Node Form: General Tab:</p>

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorInterface (Device Vendor) ■ devFamilyInterface (Device Family) <ul style="list-style-type: none"> • IP Address [click here for a list of attribute values] <p>Unique Keys from the IP Address Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <ul style="list-style-type: none"> • Node [click here for a list of attribute values] <p>Use the following syntax to specify a Custom Attribute for a Node:</p> <p>valueOfNodeCa(<CA_Name>)</p> <p>For example: \${valueOfNodeCa(Location)} = USA</p> <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>) ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p>

Valid Attributes , continued

Attribute	Description
	<p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server). See "Global Manager: Connect to a Regional Manager" on page 110.</p>

Valid Operator Values

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} = 5</pre> <p>Match any incident with the Source Object's Capability equal to com.hp.nnm.capability.card.fru</p> <pre>\$(capability) = com.hp.nnm.capability.card.fru</pre>
!=	<p>Finds all values not equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with Device Vendor for the interface (Source Object) not equal to Cisco:</p> <pre>\${devVendorInterface} != Cisco</pre>
<	<p>Finds all values less than the value specified.</p> <p>Click here for an example.</p>

Valid Operator Values, continued

Operator	Description
	<p>Match any incident with a CIA value of less than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} < 5</pre>
<=	<p>Finds all values less than or equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of less than or equal to 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} <= 5</pre>
>	<p>Finds all values greater than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value of greater than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} > 5</pre>
>=	<p>Finds all values greater than or equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface speed) ifSpeed value of 10Mbps:</p> <pre>\${ifSpeed} >= 10000000</pre>
is not null	<p>Finds all non-blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that contains a value:</p> <pre>\${ifName} is not null</pre>
is null	<p>Finds all blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that does not contain a value:</p> <pre>\${ifName} is null</pre>
like	<p>Finds matches using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p>

Valid Operator Values, continued

Operator	Description
	<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface description) ifDesc attribute that includes Serial followed by one or more digits:</p> <pre>{ifDesc} like Serial\d+</pre> <p>Match any incident with a Source Object's (interface alias) ifAlias attribute that contains EtherChannel (for example, PAgPEtherChannel Group 1).</p> <p>Note: The . (period) indicates any alphanumeric character.</p> <pre>{ifAlias} like .*EtherChannel.*</pre> <p>Match any incident with a CIA attribute value of Chassis Fan Tray followed by a digit and Object Identifier (OID) of .1.3.6.1.4.1.9.9.13.1.4.1.3</p> <p>Note: To include literal strings in the value, enclose the string value in \Q<literal_value>\E as shown in the following example.</p> <pre>{valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.3\E)} like Chassis Fan Tray \d</pre>
not like	<p>Finds all matches that do not have the values specified using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p>

Valid Operator Values, continued

Operator	Description
	Match any incident with a Source Object's (interface name) ifName value that does not include rtr: <code>\${ifName} not like .*rtr.*</code>

Valid Expressions

Attribute	Description
Expression	The value or pattern for which you want NNMi to search. Note the following: <ul style="list-style-type: none">• The expression can include a valid Attribute.• The value or pattern you want to match is case sensitive.• When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.

Configure a Child Incident Filter for a Correlation Rule

Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Child Incident Filter limitations.

Tip: The Child Incident Filter is optional, but recommended. Use of a Child Incident Filter improves NNMi performance by reducing the set of incidents that NNMi processes.

When correlating groups of incidents under a Parent incident, you must specify the requirements for the Child Incident. The Child Incident tab enables you to use the Filter Editor to define these requirements. For example, you might want to specify that the Source Node of the Child Incident be a specific Node Name pattern. See [Valid Operators](#) in the table that follows for examples of valid Child Incident Filters.

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor for Custom Correlations:

- You can use Custom Incident Attributes, attributes for an incident's Source Node or Source Object, or both to define how matching incidents should be considered for the Correlation Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For

example, if the Attribute type is numeric, NNMI does a numeric comparison. If the Attribute type is textual, NNMI does a lexicographical string comparison. In all cases, when you use the **like** or **not like** operator, NNMI uses a lexicographical string comparison. [Click here](#) for more information about Attribute types:

- ifIndex and ifSpeed are numeric Attributes.
 - Any Attribute name that begins with "is" (isSnmInterface, isSnmNode, isNnmSystemLocal) represents a Boolean Attribute.
 - All other Attributes are textual.
- Each set of expressions associated with a Boolean Operator (for example, AND) is treated as if it were enclosed in parentheses and evaluated together.
 - View the expression displayed under **Filter String** to see the logic of the expression as it is created.
 - The AND and OR Boolean Operators must contain at least two expressions.
 - The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
 - The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.

Filter Editor Buttons and Drag and Drop Feature


Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.
AND	Inserts the AND Boolean Operator in the selected cursor location. Note: View the expression displayed under Filter String to see the logic of the expression as it is created.
OR	Inserts the OR Boolean Operator in the current cursor location.




Filter Editor Buttons and Drag and Drop Feature, continued

Button or Feature	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none"> Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none"> Click the item you want to move before dragging it to a new location. As you drag a selected item, an underline indicates the target location. If you are moving the selection up, NNMi places the item above the target location. If you are moving the selection down, NNMi places the item below the target location. If you attempt to move the selection to an invalid target location, NNMi displays an error message.

See ["Correlation Rule Example" on page 804](#) for a step-by-step example of how the Subinterface Correlation Rule provided by NNMi was created.


To configure a Child Incident Filter:

- Navigate to the **Custom Correlation Configuration** form:
 - From the workspace navigation pane, select the  **Configuration** workspace.
 - Expand the **Incidents** folder.
 - Select **Custom Correlation Configuration**.
- Navigate to the **Correlation Rules** tab.
- From the **Correlation Rules** table toolbar, do one of the following:

- To create a Correlation Rule, click the  New icon, and continue.
 - To edit a Correlation Rule, click the  Open icon in the row representing the Correlation Rule you want to edit, and continue.
 - To delete a Correlation Rule, click the  Delete icon.
4. Navigate to the **Child Incident Filter** tab.
 5. Create your Child Incident Filter (see the [Filter Editor Settings](#) below).

Filter Editor Settings


Setting	Description
Attribute	The Attribute on which NNMI searches. See Valid Attributes below for a description of valid Attributes.
Operator	<p>Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.</p> <div style="background-color: #f0f0f0; padding: 10px; border: 1px solid #ccc;"> <p>Note: When specifying the like or not like operator, you must use the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> </div>
Expression	Use the Expression to complete the criteria for the Child Incident configurations. See Valid Expressions below for more information.

6. Click  **Save and Close** to save your changes and return to the previous form.


Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMI searches. Valid attributes other than Source Node attributes depend on the Incident's Source Object. NNMI checks the Source Node as well as the Source Object for any Capability value.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none"> Boolean Attributes begin with "is" and must contain the value true or false. Use the following syntax to specify a Custom Incident Attribute (CIA): <pre>valueOfCia(<CIA_Name>)</pre>

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ Check the appropriate Incident form for any valid CIA Names provided by NNMi. For example: <code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)}= 5</code> ■ When specifying the <code><CIA_Name></code>, you can use the syntax defined for Java regular expressions. For example, use the following syntax to specify that you want to include any CIA Name that begins with <code>.1.3.6.1.2.1.31.1.1.1.1.:</code> <code>\${valueOfCia(\Q.1.3.6.1.2.1.31.1.1.1.1.\E.*)}</code> ■ Enclose all CIA names using the <code>\Q</code> and <code>\E</code> characters so that NNMi correctly interprets the period character. For example: <code>\${child.valueOfCia(\Qcia.address\E)}</code> For more information, see the Pattern (Java Platform SE6) API documentation at http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html <ul style="list-style-type: none"> ● If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter. ● When using attributes for a Source Object, note the following: <ul style="list-style-type: none"> ■ When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the <code>hostedOn</code> attribute and the Source Object is not an interface, the correlation does not occur. <div style="border: 1px solid #ccc; background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> </div> ■ <i>SNMP Trap incidents only.</i> NNMi does not find a match when the value for a Source Object is None. A Source Object attribute value of None indicates that NNMi cannot resolve the Source Object. If you want to match the incident, use one or more Source Node attributes. <ul style="list-style-type: none"> ● If the incident does not have a Source Object, a Source Node, or both (for example, the node is not stored in the NNMi database), you must use CIAs in your filter rather than Source Object or Source Node attributes.

Valid Attributes , continued

Attribute	Description
	<div data-bbox="440 359 1370 569"> <p>Tip: To check whether the Source Object or Source Node is stored in the NNMI database, open the incident and then select  Open from the Lookup menu for the Source Node or Source Object displayed. If a form does not open for the selected object or node, this means the source is not stored in the NNMI database.</p> </div> <ul style="list-style-type: none"> When specifying a Correlation Filter, precede the attribute name with either <code>parent.</code> or <code>child.</code> to specify from which incident the attribute value should be compared. For example, you might specify <code>\${parent.hostedOn}</code> or <code>\${child.ifDesc}</code>. <p>Possible Source Object choices are as follows:</p> <ul style="list-style-type: none"> Card [click here for a list of attribute values] Unique Keys from the Card Form: Capabilities Tab: <ul style="list-style-type: none"> capability (Unique Key of the Capability) Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: <code>valueOfInterfaceCa(<CA_Name>)</code> For example: <code>\${child.valueOfInterfaceCA(Role)} = WAN Connection</code> Values from the Basics Attributes listed on the Interface Form: <ul style="list-style-type: none"> hostedOn (Hosted On Node) You must use the full DNS name for the hostedOn value. Values from the Interface Form: General Tab: <ul style="list-style-type: none"> ifName (name configured for the interface) ifAlias (alias configured for the interface) ifDesc (description configured for the interface) ifIndex (index assigned to the interface) ifSpeed (speed configured for the interface) <p>When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.</p>

Valid Attributes , continued

Attribute	Description
	<p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <=.</p> <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the parent Node Form:</p> <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled) <p>Values from the parent Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorInterface (Device Vendor) ■ devFamilyInterface (Device Family) <ul style="list-style-type: none"> • IP Address [click here for a list of attribute values] <p>Unique Keys from the IP Address Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <ul style="list-style-type: none"> • Node [click here for a list of attribute values] <p>Use the following syntax to specify a Custom Attribute for a Node:</p> <pre>valueOfNodeCa(<CA_Name>)</pre> <p>For example: <code>\${valueOfNodeCa(Location)} = USA</code></p> <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>) ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server)

Valid Attributes , continued

Attribute	Description
	<p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p> <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server). See "Global Manager: Connect to a Regional Manager" on page 110.</p>

Valid Operator Values

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p>

Valid Operator Values, continued

Operator	Description
	<p><code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} = 5</code></p> <p>Match any incident with the Source Object's Capability equal to <code>com.hp.nnm.capability.card.fru</code></p> <p><code>\$(capability) = com.hp.nnm.capability.card.fru</code></p>
!=	<p>Finds all values not equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with Device Vendor for the interface (Source Object) not equal to Cisco:</p> <p><code>\${devVendorInterface} != Cisco</code></p>
<	<p>Finds all values less than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value of less than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} < 5</code></p>
<=	<p>Finds all values less than or equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of less than or equal to 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} <= 5</code></p>
>	<p>Finds all values greater than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value of greater than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} > 5</code></p>
>=	<p>Finds all values greater than or equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface speed) ifSpeed value of 10Mbps:</p> <p><code>\${ifSpeed} >= 10000000</code></p>
is not null	<p>Finds all non-blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that</p>

Valid Operator Values, continued

Operator	Description
	contains a value: <code>\${ifName} is not null</code>
is null	<p>Finds all blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that does not contain a value:</p> <p><code>\${ifName} is null</code></p>
like	<p>Finds matches using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code>.</p> </div> <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface description) ifDesc attribute that includes Serial followed by one or more digits:</p> <p><code>\${ifDesc} like Serial\d+</code></p> <p>Match any incident with a Source Object's (interface alias) ifAlias attribute that contains EtherChannel (for example, PAgPEtherChannel Group 1).</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The . (period) indicates any alphanumeric character.</p> </div> <p><code>\${ifAlias} like .*EtherChannel.*</code></p> <p>Match any incident with a CIA attribute value of Chassis Fan Tray followed by a digit and Object Identifier (OID) of .1.3.6.1.4.1.9.9.13.1.4.1.3</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal strings in the value, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the following example.</p> </div> <p><code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.3\E)} like Chassis Fan Tray \d</code></p>

Valid Operator Values, continued

Operator	Description
not like	<p>Finds all matches that do not have the values specified using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> <div><p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p></div> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName value that does not include rtr:</p> <pre>\${ifName} not like .*rtr.*</pre>

Valid Expressions

Attribute	Description
Expression	<p>The value or pattern for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The expression can include a valid Attribute.• The value or pattern you want to match is case sensitive.• When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.

Configure a Correlation Filter

Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Correlation Filter limitations.

When correlating groups of incidents under a Parent incident, you must specify the Correlation Filter that defines the relationship requirements that must be met before the incidents are correlated. The Correlation Filter tab enables you to use the Filter Editor to define these relationship requirements. See [Valid Operators](#) in the table that follows for examples of valid Correlation Filters.

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor for Custom Correlations:

- You can use Custom Incident Attributes, attributes for an incident's Source Node or Source Object, or both to define how matching incidents should be considered for the Correlation Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For example, if the Attribute type is numeric, NNMi does a numeric comparison. If the Attribute type is textual, NNMi does a lexicographical string comparison. In all cases, when you use the **like** or **not like** operator, NNMi uses a lexicographical string comparison. [Click here](#) for more information about Attribute types:
 - `ifIndex` and `ifSpeed` are numeric Attributes.
 - Any Attribute name that begins with "is" (`isSnmInterface`, `isSnmNode`, `isNnmSystemLocal`) represents a Boolean Attribute.
 - All other Attributes are textual.
- Each set of expressions associated with a Boolean Operator (for example, AND) is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions.
- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.

Filter Editor Buttons and Drag and Drop Feature





Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.

Filter Editor Buttons and Drag and Drop Feature, continued

Button or Feature	Description
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none">■ Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS■ Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none">■ Click the item you want to move before dragging it to a new location.■ As you drag a selected item, an underline indicates the target location.■ If you are moving the selection up, NNMi places the item above the target location.■ If you are moving the selection down, NNMi places the item below the target location.■ If you attempt to move the selection to an invalid target location, NNMi displays an error message.


See ["Correlation Rule Example" on page 804](#) for a step-by-step example of how the Subinterface Custom Correlation Rule provided by NNMi was created.

To configure a Correlation Filter:

1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Correlation Rules** tab.
3. From the **Correlation Rules** table toolbar, do one of the following:
 - To create a Correlation Rule, click the  New icon, and continue.
 - To edit a Correlation Rule, click the  Open icon in the row representing the Correlation Rule you want to edit, and continue.
 - To delete a Correlation Rule, click the  Delete icon.
4. Navigate to the **Correlation Filter** tab.
5. Create your Correlation Filter (see [Filter Editor Settings](#)).

Filter Editor Settings


Setting	Description
Attribute	The Attribute on which NNMi searches. See Valid Attributes below for a description of valid Attributes.
Operator	Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.
Expression	Use the Expression to complete the criteria for the required relationship between the parent and child incident configurations. See Valid Expressions below for more information.

6. Click  **Save and Close** to save your changes and return to the previous form.


Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMi searches. Valid attributes other than Source Node attributes depend on the Incident's Source Object. NNMi checks the Source Node as well as the Source Object for any Capability value.</p> <p>Note the following when specifying Attributes:</p>

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> Boolean Attributes begin with "is" and must contain the value true or false. Use the following syntax to specify a Custom Incident Attribute (CIA): <code>valueOfCia(<CIA_Name>)</code> <ul style="list-style-type: none"> Check the appropriate Incident form for any valid CIA Names provided by NNMi. For example: <code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)}= 5</code> When specifying the <CIA_Name>, you can use the syntax defined for Java regular expressions. For example, use the following syntax to specify that you want to include any CIA Name that begins with .1.3.6.1.2.1.31.1.1.1.1.: <code>\${valueOfCia(\Q.1.3.6.1.2.1.31.1.1.1.1.\E.*)}</code> Enclose all CIA names using the \Q and \E characters so that NNMi correctly interprets the period character. For example: <code>\${child.valueOfCia(\Qcia.address\E)}</code> For more information, see the Pattern (Java Platform SE6) API documentation at http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter. When using attributes for a Source Object, note the following: <ul style="list-style-type: none"> When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the <code>hostedOn</code> attribute and the Source Object is not an interface, the correlation does not occur. <div data-bbox="472 1528 1370 1675" style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> </div> <ul style="list-style-type: none"> <i>SNMP Trap incidents only.</i> NNMi does not find a match when the value for a Source Object is None. A Source Object attribute value of None indicates that NNMi cannot resolve the Source Object. If you want to match the incident, use one or more Source Node attributes.

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> If the incident does not have a Source Object, a Source Node, or both (for example, the node is not stored in the NNMi database), you must use CIAs in your filter rather than Source Object or Source Node attributes. <div data-bbox="440 489 1370 703" style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: To check whether the Source Object or Source Node is stored in the NNMi database, open the incident and then select  Open from the Lookup menu for the Source Node or Source Object displayed. If a form does not open for the selected object or node, this means the source is not stored in the NNMi database.</p> </div> <ul style="list-style-type: none"> When specifying a Correlation Filter, precede the attribute name with either <code>parent.</code> or <code>child.</code> to specify from which incident the attribute value should be compared. For example, you might specify <code>\${parent.hostedOn}</code> or <code>\${child.ifDesc}</code>. <p>Possible Source Object choices are as follows:</p> <ul style="list-style-type: none"> Card [click here for a list of attribute values] Unique Keys from the Card Form: Capabilities Tab: <ul style="list-style-type: none"> ■ <code>capability</code> (Unique Key of the Capability) Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: <code>valueOfInterfaceCa(<CA_Name>)</code> For example: <code>\${child.valueOfInterfaceCA(Role)} = WAN Connection</code> Values from the Basics Attributes listed on the Interface Form: <ul style="list-style-type: none"> ■ <code>hostedOn</code> (Hosted On Node) You must use the full DNS name for the hostedOn value. Values from the Interface Form: General Tab: <ul style="list-style-type: none"> ■ <code>ifName</code> (name configured for the interface) ■ <code>ifAlias</code> (alias configured for the interface) ■ <code>ifDesc</code> (description configured for the interface) ■ <code>ifIndex</code> (index assigned to the interface)

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ ifSpeed (speed configured for the interface) When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps. <p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <=. <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the parent Node Form:</p> <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled) <p>Values from the parent Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorInterface (Device Vendor) ■ devFamilyInterface (Device Family) <ul style="list-style-type: none"> • IP Address [click here for a list of attribute values] <p>Unique Keys from the IP Address Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <ul style="list-style-type: none"> • Node [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for a Node: valueOfNodeCa(<CA_Name>) For example: \${valueOfNodeCa(Location)} = USA <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>)

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p> <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server). See "Global Manager: Connect to a Regional Manager" on page 110.</p>

Valid Operators

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for an example.</p> <p>Correlate the incidents if the hostedOn value for the Source Object of the Child Incident is equal to the hostedOn value for the Source Object in the Parent Incident.</p> <pre>\${child.hostedOn} = \${parent.hostedOn}</pre>
!=	<p>Finds all values not equal to the value specified.</p> <p>Click here for an example.</p> <p>Correlate the incidents if the hostedOn value for the Source Object of the Child Incident is not equal to the hostedOn value for the Source Object in the Parent Incident.</p> <pre>\${child.hostedOn} != \${parent.hostedOn}</pre>
<	Finds all values less than the value specified.
<=	Finds all values less than or equal to the value specified.
>	Finds all values greater than the value specified.
>=	Finds all values greater than or equal to the value specified.
is not null	Finds all non-blank values.
is null	Finds all blank values.
like	<p>Finds matches using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> </div> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p>
not like	<p>Finds all matches that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> </div>

Valid Operators, continued

Operator	Description
	The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i> .
	The period (.) character means <i>any single character of any type at this location</i> .

Valid Expressions

Attribute	Description
Expression	<p>The value or pattern for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The expression can include a valid Attribute.• The value or pattern you want to match is case sensitive.• When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.

Correlation Rule Example


Tip: Use these steps as a guideline for creating your own Correlation Rules.



This example uses the Subinterface Correlation Rule to describe the steps for creating a Correlation Rule. The Subinterface Correlation Rule specifies that Interface Down incidents that occur for subinterfaces should be correlated under the Interface Down incident generated for the main interface. [Click here](#) for more information about Custom Correlations.

The NNMi Custom Correlation feature enables you to correlate groups of incidents under a Parent Incident. This feature is useful when you want to define a relationship between a number of incidents potentially from different network objects that form a logical set to identify a problem. The set of correlations is considered complete if all of the incidents arrive within a specified time window. You can correlate incidents under an existing Incident Configuration (Correlation Rule) or create a new Incident Configuration (Causal Rule).

This example uses an existing Incident Configuration as the Parent Incident. See "[Causal Rule Example](#)" on page 842 for an example that generates a new Incident Configuration as the Parent Incident.

To configure the Subinterface Correlation Rule Basics information:

1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.

- c. Select **Custom Correlation Configuration**.
2. Navigate to the **Correlation Rules** tab.
3. From the **Correlation Rules** table toolbar, click the  New icon.
4. In the **Name** attribute, enter a unique name that will help you to identify the Correlation Rule. In this example, the Correlation Rule Name is **Subinterface**.
5. In the **Author** attribute, enter a name that identifies the person who is creating the Correlation Rule. In this example, **HP Network Node Manager** is the Author name to identify this Correlation Rule as one that NNMi provides.
6. Make sure **Enabled** ☒ is checked to indicate the NNMi Causal Engine should use this Correlation Rule when evaluating incidents.
7. To use an existing Parent Incident, do the following:
 - a. In the **Parent Incident** Lookup Field, select  Quick Find to select from the list of existing incident configurations.
 - b. In the Subinterface Correlation Rule, the **InterfaceDown** incident configuration was selected as the Parent Incident.
8. Select the Incident Configuration that must match an incoming incident and that should be correlated as the Child Incident for the Custom Correlation.

In the Subinterface Correlation Rule, the **InterfaceDown** incident configuration was also selected as the Child Incident.
9. In the **Correlation Window Duration** attribute, enter the time limit (in days, hours, minutes, and seconds) that must be reached before the incoming incident are correlated. The Subinterface Correlation Rule specifies a Correlation Window Duration of 6 minutes.
10. Use the **Description** attribute to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.

The Subinterface Correlation Rule includes the following description: **Correlates sub-interfaces down incidents under the main interface down.**

To configure the Parent Incident Filter:

1. In the Correlation Rule form, navigate to the **Parent Incident Filter** tab.
2. The following Parent Incident Filter specifies that the Correlation Rule applies only to Cisco devices:

```
${devVendorInterface} = Cisco
```

3. The following Parent Incident Filter specifies that the `ifDesc` value must contain the string `Serial` followed by one or more digits and then a forward slash, followed by zero or more digits:

```
${ifDesc} like Serial\d+/*\d*
```

4. As shown in the following Filter String, the Parent Incident Filters use the Boolean operator **AND** so that both criteria must be met for the Incident to be selected as a Parent:

```
{{devVendorInterface}} = Cisco AND ${ifDesc} like Serial\d+/*\d*)
```

To create this Parent Incident Filter, in the Filter Editor:

- a. Click **And**.
- b. In the **Attribute** field, enter `{{devVendorInterface}}`.
- c. In the **Operator** field, select `=` from the drop-down menu.
- d. In the **Expression** field, enter **Cisco**.
- e. Click **Append**.
- f. In the **Attribute** field, enter `${ifDesc}`.
- g. In the **Operator** field, select `like` from the drop-down menu.
- h. In the **Expression** field, enter `Serial\d+/*\d*`.
- i. Click **Add**.

To configure the Child Incident Filter:

1. In the Correlation Rule form, navigate to the **Child Incident Filter** tab.
2. The following Child Incident Filter specifies that the Correlation Rule applies only to Cisco devices:

```
${devVendorInterface} = Cisco
```

3. The following Child Incident Filter specifies that the `ifDesc` value must contain the following sequence of values:

The string `Serial` followed by one or more digits, then a forward slash, followed by zero or more digits, and then a period followed by one or more digits:

```
${ifDesc} like Serial\d+/*\d*
```

4. As shown in the following Filter String, the Child Incident Filters use the Boolean operator **AND** so that both criteria must be met for the Incident to be selected as a Child:

```
{{devVendorInterface}} = Cisco AND {{ifDesc}} like Serial\d+/*\d*)
```

To create this Parent Incident Filter, in the Filter Editor:

- a. Click **And**.
- b. In the **Attribute** field, enter `{{devVendorInterface}}`.
- c. In the **Operator** field, select `=` from the drop-down menu.
- d. In the **Expression** field, enter **Cisco**.
- e. Click **Append**.
- f. In the **Attribute** field, enter `{{ifDesc}}`.
- g. In the **Operator** field, select `like` from the drop-down menu.
- h. In the **Expression** field, enter `Serial\d+/*\d*`.
- i. Click **Append**.

To configure the Correlation Filter:

Note: When specifying a Correlation Filter, you must specify whether the attribute is from a Child Incident or Parent Incident using the following syntax: `{{child.<attribute_name>}}` or `{{parent.<attribute_name>}}`.

1. In the Correlation Rule form, navigate to the **Correlation Filter** tab.
2. To ensure that the Interface Down incidents are generated for the same node, the Subinterface Correlation Rules uses `hostedOn` as the attribute for both the Child and Parent Incidents as shown in the following example filter:

```
{{child.hostedOn}}= {{parent.hostedOn}}
```


To ensure that the Interfaces are subinterfaces for the main interface, the filter also matches the `ifDesc` values:

```
{{child.ifDesc}} like {{parent.ifDesc}}.*
```

As shown in the following Filter String, the Correlation Filter uses the Boolean operator **AND** so that both criteria must be met for the Incidents to be correlated:

```
{{child.hostedOn}} = {{parent.hostedOn}} AND {{child.ifDesc}} like  
{{parent.ifDesc}}.*
```

To create the Correlation Rule filter:

- a. Click **And**.
 - b. In the **Attribute** field, enter `${child.hostedOn}`.
 - c. In the **Operator** field, select `=` from the drop-down menu.
 - d. In the **Expression** field, enter `${parent.hostedOn}`.
 - e. Click **Append**.
 - f. In the **Attribute** field, enter `${child.ifDesc}`.
 - g. In the **Operator** field, select `like` from the drop-down menu.
 - h. In the **Expression** field, enter `${parent.ifDesc}.*`.
 - i. Click **Append**.
3. Click  **Save and Close** to save your changes and return to the previous form.

Configure a Causal Rule

Tip: Configure a Causal Rule when you want to cause NNMi to generate a Parent Incident and you want to correlate one or more Child Incident Configurations under the Parent Incident that you cause to be generated.






Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Causal Rule limitations.

When correlating groups of incidents under a Parent incident, use the Causal Rules tab to specify the following.





- Parent Incident Configuration to be generated
- One or more Child Incident Configurations to be correlated with the generated Parent Incident
- Filters that NNMi should use when selecting the Child Incident instances for correlation
- Source Object and Source Node Filter to be used to determine the Source Node and Source Object for the Parent Incident that is generated
- The time window that must be met before NNMi correlates the incidents

For information about each Causal Rules tab:










To configure a Causal Rule:

1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Causal Rules** tab.
3. From the **Causal Rules** table toolbar, do one of the following:
 - To create a Causal Rule, click the  **New** icon, and continue.
 - To edit a Causal Rule, click the  **Open** icon in the row representing the Causal Rule you want to edit, and continue.
 - To delete a Causal Rule, click the  **Delete** icon.
4. Create your Causal Rule (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the previous form.


Cause Rule Basic Attributes

Attribute	Description
Name	<p>Type a maximum of 64 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>The name is used to identify the Causal Rule and must be unique. Use a name that will help you to remember the purpose of the Causal Rule.</p>
Author	<p>Indicates who created or last modified the Causal Rule.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> </div> <ul style="list-style-type: none"> • Click  Lookup and select  Show Analysis to display details about the currently selected Author. • Click  Quick Find to access the list of existing Author values. • Click  New to create an Author value.
Enabled	<p>If <input checked="" type="checkbox"/> enabled, the NNMi Causal Engine uses the Causal Rule when evaluating incidents.</p> <p>If <input type="checkbox"/> disabled, the Causal Rule is ignored.</p>
Parent	Specifies the incident configuration that should be generated as the Parent Incident


Cause Rule Basic Attributes, continued

Attribute	Description
	<p>for the Causal Rule.</p> <p>To specify a Parent Incident configuration:</p> <ol style="list-style-type: none"> Click the  Lookup icon, and do one of the following: <ul style="list-style-type: none"> To display Analysis Pane information, select  Show Analysis. (See Use the Analysis Pane for more information about the Analysis Pane.) To display the list of possible incidents, select  Quick Find. In the Quick Find dialog, select the Incident of interest. To create a Parent Incident, select one of the following: <ul style="list-style-type: none">  New Management Event Configuration  New Remote NNM Event Configuration  New SNMP Trap Configuration To modify a Parent Incident, select  Open. <i>Optional.</i> To create or modify a Parent Incident, enter or modify the attribute values for the selected Incident configuration. See "Configuring Incidents" on page 667 for more information about the Incident Configuration form. Click  Save and Close to save your changes and return to the previous form. <i>Optional.</i> To create or modify a Parent Incident, enter or modify the attribute values for the selected Incident configuration. See "Configuring Incidents" on page 667 for more information about the Incident Configuration form. Click  Save and Close to save your changes and return to the previous form.
Correlation Nature	<p>Select the Correlation Nature that you want to assign to the Parent Incident that is generated. See Incident Form: General Tab for more informaton.</p> <div data-bbox="423 1556 1370 1665"> <p>Note: The Child Incident will have the Correlation Nature of Secondary Root Cause.</p> </div>
Common Child Incident Attribute	<p>Specifies the Incident Attribute that all Child Incidents must have in common for the incident instance to be correlated under the Parent Incident defined for the Causal Rule. For example, if you want to ensure that all child incidents are from the same node, use the <code>\${hostedOn}</code> attribute.</p> <p>Valid attributes other than Source Node attributes depend on the Incident's Source</p>

Cause Rule Basic Attributes, continued

Attribute	Description
	<p>Object. NNMi checks the Source Node as well as the Source Object for any attribute value.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none"> You cannot specify \$(capability) as a Common Child Incident Attribute. Boolean Attributes begin with "is" and must contain the value true or false. Use the following syntax to specify a Custom Incident Attribute (CIA): <pre>valueOfCia(<CIA_Name>)</pre> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Check the appropriate Incident form for any valid CIA Names provided by NNMi.</p> </div> <p>For example: <code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)}</code></p> <ul style="list-style-type: none"> When specifying the <CIA_Name>, you can use the syntax defined for Java regular expressions. For example, use the following syntax to specify that you want to include any CIA Name that begins with .1.3.6.1.2.1.31.1.1.1.1.: <code>\${valueOfCia(\Q.1.3.6.1.2.1.31.1.1.1.1.\E.*)}</code> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Enclose all CIA names using the \Q and \E characters so that NNMi correctly interprets the period character. For example: <code>\$child.valueOfCia(\Qcia.address\E)}</code>.</p> </div> <p>See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information.</p> <ul style="list-style-type: none"> If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter. When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the hostedOn attribute and the Source Object is not an interface, the correlation does not occur. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> </div>

Cause Rule Basic Attributes, continued

Attribute	Description
	<p>A Source Object attribute value of None indicates that NNMi cannot identify the Source Object or the Source Object is a Node. If you want to match the incident, use one or more Source Node attributes.</p> <ul style="list-style-type: none"> • If the incident does not have a Source Object, a Source Node, or both (for example, the node is not stored in the NNMi database), you must use CIAs rather than Source Object or Source Node attributes. <div data-bbox="462 590 1370 800"> <p>Tip: To check whether the Source Object or Source Node is stored in the NNMi database, open the incident and then select  Open from the Lookup menu for the Source Node or Source Object displayed. If a form does not open for the selected object or node, this means the source is not stored in the NNMi database.</p> </div> <p>Possible Source Object choices are as follows:</p> <ul style="list-style-type: none"> • Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: <code>valueOfInterfaceCa(<CA_Name>)</code> For example: <code>\${child.valueOfInterfaceCA(Role)}</code> <p>Values from the Basics Attributes listed on the Interface Form:</p> <ul style="list-style-type: none"> ■ hostedOn (Hosted On Node) <p>Values from the Interface Form: General Tab:</p> <ul style="list-style-type: none"> ■ ifName (name configured for the interface) ■ ifAlias (alias configured for the interface) ■ ifDesc (description configured for the interface) ■ ifIndex (index assigned to the interface) ■ ifSpeed (speed configured for the interface) <p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) <p>Values from the Basics Attributes on the parent Node Form:</p> <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled)

Cause Rule Basic Attributes, continued

Attribute	Description
	<p>Values from the parent Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorInterface (Device Vendor) ■ devFamilyInterface (Device Family) <ul style="list-style-type: none"> • Node [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute (CA) for a Node: valueOfNodeCa(<CA_Name>) For example: \${valueOfNodeCa(Location)} <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>) ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form:</p>

Cause Rule Basic Attributes, continued

Attribute	Description
	<p>Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server). See "Global Manager: Connect to a Regional Manager" on page 110.</p>
Correlation Window Duration	<p>The time window that must be met before NNMi correlates the incidents. Enter a number for Days, Hours, Minutes, and Seconds.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • NNMi waits until the Correlation Window Duration has passed before generating the Parent Incident and correlating its Child Incidents. • If you are relating multiple Custom Correlations, make sure the Correlation Window Duration allows enough time for all of the Parent and Child incidents to be generated. For example, to correlate two or more Interface Down incidents under a new incident on interfaces that are polled every 5 minutes, use a 6-minute Correlation Window Duration. The 6-minute window ensures that the Interface Down incidents, which might occur 5 minutes apart, will be correlated under the new incident.
Description	<p>Use the description field to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.</p> <p>Type a maximum of 2048 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>


Configure a Child Incident for a Causal Rule





The Child Incident tab enables you to specify which Child Incidents should be considered for correlation according to the Causal Rule you are configuring.

For information about each Causal Rules tab:



For information about each Child Incident tab:

To configure a Child Incident for a Causal Rule:






1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.

- c. Select **Custom Correlation Configuration**.
2. Navigate to the **Causal Rules** tab.
3. From the **Causal Rules** table toolbar, do one of the following:
 - To create a Causal Rule, click the  New icon, and continue.
 - To edit a Causal Rule, click the  Open icon in the row representing the Causal Rule you want to edit, and continue.
 - To delete a Causal Rule, click the  Delete icon.
4. Create your Causal Rule. (See ["Configure a Causal Rule" on page 808.](#))
5. Create your Child Incident Configuration (see [table](#)).
6. *Optional.* Configure a Child Incident Filter. (See ["Configure a Child Incident Filter for a Causal Rule" on page 817.](#))
7. *Optional.* Configure a Source Object Filter. (See ["Configure a Source Object Filter for a Causal Rule" on page 827.](#))
8. *Optional.* Configure a Source Node Filter. (See ["Configure a Source Node Filter for a Causal Rule" on page 836.](#))
9. Click  **Save and Close** to save your changes and return to the previous form.

Causal Rule Basic Attributes

Attribute	Description
Name	<p>Type a maximum of 64 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <p>The name is used to identify the Child Incident Configuration and must be unique within each Causal Rule. Use a name that will help you to remember the purpose of the Child Incident Configuration.</p>
Child Incident	<p>Specifies the incident configuration that should be used as the Child Incident when evaluating the Causal Rule.</p> <p>To specify a Child Incident configuration:</p> <ol style="list-style-type: none"> 1. Click the  Lookup icon, and do one of the following: <ul style="list-style-type: none"> ■ To specify a Child Incident without making any changes to the incident configuration, select  Quick Find . In the Quick Find dialog, select the Incident of interest. ■ To create a Child Incident, select one of the following:

Causal Rule Basic Attributes, continued

Attribute	Description
	<ul style="list-style-type: none"> ◦  New Management Event Configuration ◦  New Remote NNM Event Configuration ◦  New SNMP Trap Configuration <ul style="list-style-type: none"> ■ To modify a Child Incident, select  Open. <ol style="list-style-type: none"> 2. <i>Optional.</i> To create or modify a Child Incident, enter or modify the attribute values for the selected Incident configuration. See "Configuring Incidents" on page 667 for more information about the Incident Configuration form. 3. Click  Save and Close to save your changes and return to the previous form.
Forward Child Custom Incident Attributes	Enter a comma-delimited list of the Custom Incident Attributes you want to appear with the generated Parent Incident. NNMi forwards these values from the Child Incidents that you configure for the Causal Rule.
Optional Child Incident	<p>If <input checked="" type="checkbox"/> enabled, the NNMi Causal Engine generates the Parent Incident whether this Child Incident occurs.</p> <p>If <input type="checkbox"/> disabled, the NNMi Causal Engine only generates the Parent Incident if this Child Incident occurs.</p>
Use Child Incident's Source Object for Parent	<p>If <input checked="" type="checkbox"/> enabled, indicates you want NNMi to use the Source Object of the Child Incident as the Source Object for the Parent Incident.</p> <p>Note: If you enable this option, NNMi ignores any Source Object Filter you configured.</p> <p>If <input type="checkbox"/> disabled, indicates you want NNMi to use the Source Object Filter configuration to determine the Parent Incident's Source Node. See "Configure a Source Object Filter for a Causal Rule" on page 827 for more information.</p> <p>If you do not specify the Source Object to use for the Parent Incident, NNMi uses the Source Object of the first Child Incident that occurs.</p>
Use Child Incident's Source Node for Parent	<p>If <input checked="" type="checkbox"/> enabled, indicates you want NNMi to use the Source Node of the Child Incident as the Source Node for the Parent Incident.</p> <p>Note: If you enable this option, NNMi ignores any Source Node Filter you configured.</p> <p>If <input type="checkbox"/> disabled, indicates you want NNMi to use the Source Node Filter</p>

Causal Rule Basic Attributes, continued

Attribute	Description
	configuration to determine the Parent Incident's Source Node. See " Configure a Source Node Filter for a Causal Rule " on page 836 for more information. If you do not specify the Source Node to use for the Parent Incident, NNMi uses the Source Node of the first Child Incident that occurs.

Configure a Child Incident Filter for a Causal Rule

Note: See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** link for Child Incident Filter limitations.

The Child Incident Filter tab enables you to create a filter to specify which Child Incidents should be considered for correlation according to the Causal Rule you are configuring.

For information about each Causal Rules tab:

For information about each Child Incident tab:

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor for Custom Correlations:

- You can use Custom Incident Attributes, attributes for an incident's Source Node or Source Object, or both to define how matching incidents should be considered for the Correlation Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For example, if the Attribute type is numeric, NNMi does a numeric comparison. If the Attribute type is textual, NNMi does a lexicographical string comparison. In all cases, when you use the **like** or **not like** operator, NNMi uses a lexicographical string comparison. [Click here](#) for more information about Attribute types:
 - `ifIndex` and `ifSpeed` are numeric Attributes.
 - Any Attribute name that begins with "is" (`isSnmppInterface`, `isSnmppNode`, `isNnmSystemLocal`) represents a Boolean Attribute.
 - All other Attributes are textual.
- Each set of expressions associated with a Boolean Operator (for example, AND) is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions.

- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.





Filter Editor Buttons and Drag and Drop Feature

Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none">■ Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS■ Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none">■ Click the item you want to move before dragging it to a new location.

Filter Editor Buttons and Drag and Drop Feature, continued

Button or Feature	Description
	<ul style="list-style-type: none">■ As you drag a selected item, an underline indicates the target location.■ If you are moving the selection up, NNMi places the item above the target location.■ If you are moving the selection down, NNMi places the item below the target location.■ If you attempt to move the selection to an invalid target location, NNMi displays an error message.

To configure a Child Incident Filter for a Causal Rule:


1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Causal Rules** tab.
3. From the **Causal Rules** table toolbar, do one of the following:
 - To create a Causal Rule, click the  New icon, and continue.
 - To edit a Causal Rule, click the  Open icon in the row representing the Causal Rule you want to edit, and continue.
 - To delete a Causal Rule, click the  Delete icon.
4. Create your Causal Rule. (See ["Configure a Causal Rule" on page 808.](#))
5. Create your Child Incident Configuration . (See ["Configure a Child Incident for a Causal Rule" on page 814.](#))
6. *Optional.* Configure a Child Incident Filter. (See [Filter Editor Settings](#)).

Filter Editor Settings

Setting	Description
Attribute	The Attribute on which NNMi searches. See Valid Attributes below for a description of valid Attributes.

Filter Editor Settings, continued



Setting	Description
Operator	Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.
Expression	Use the Expression to complete the criteria for the Parent Incident configuration. See Valid Expressions below for more information.

7. *Optional.* Configure a Source Object Filter. (See ["Configure a Source Object Filter for a Causal Rule"](#) on page 827.)
8. *Optional.* Configure a Source Node Filter. (See ["Configure a Source Node Filter for a Causal Rule"](#) on page 836.)
9. Click  **Save and Close** to save your changes and return to the previous form.

Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMI searches. Valid attributes other than Source Node attributes depend on the Incident's Source Object. NNMI checks the Source Node as well as the Source Object for any Capability value.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none"> • Boolean Attributes begin with "is" and must contain the value true or false. • Use the following syntax to specify a Custom Incident Attribute (CIA): <pre>valueOfCia(<CIA_Name>)</pre> <ul style="list-style-type: none"> ■ Check the appropriate Incident form for any valid CIA Names provided by NNMI. <p>For example: <code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)}= 5</code></p> <ul style="list-style-type: none"> ■ When specifying the <CIA_Name>, you can use the syntax defined for Java regular expressions. For example, use the following syntax to specify that you want to include any CIA Name that begins with .1.3.6.1.2.1.31.1.1.1.1.: <pre>\${valueOfCia(\Q.1.3.6.1.2.1.31.1.1.1.1.\E.*)}</pre> <ul style="list-style-type: none"> ■ Enclose all CIA names using the \Q and \E characters so that NNMI correctly interprets the period character. For example: <code>\${child.valueOfCia(\Qcia.address\E)}</code> <p>For more information, see the Pattern (Java Platform SE6) API documentation at</p>

Valid Attributes , continued

Attribute	Description
	<p data-bbox="469 359 1385 422">http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> <ul data-bbox="407 453 1385 1293" style="list-style-type: none"> <li data-bbox="407 453 1385 590">• If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter. <li data-bbox="407 621 1385 1157">• When using attributes for a Source Object, note the following: <ul data-bbox="440 684 1385 1157" style="list-style-type: none"> <li data-bbox="440 684 1385 821">■ When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the <code>hostedOn</code> attribute and the Source Object is not an interface, the correlation does not occur. <div data-bbox="456 852 1369 993"> <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> </div> <li data-bbox="440 1031 1385 1157">■ <i>SNMP Trap incidents only.</i> NNMi does not find a match when the value for a Source Object is <code>None</code>. A Source Object attribute value of <code>None</code> indicates that NNMi cannot resolve the Source Object. If you want to match the incident, use one or more Source Node attributes. <li data-bbox="407 1188 1385 1293">• If the incident does not have a Source Object, a Source Node, or both (for example, the node is not stored in the NNMi database), you must use CIAs in your filter rather than Source Object or Source Node attributes. <div data-bbox="456 1325 1369 1539"> <p>Tip: To check whether the Source Object or Source Node is stored in the NNMi database, open the incident and then select  Open from the Lookup menu for the Source Node or Source Object displayed. If a form does not open for the selected object or node, this means the source is not stored in the NNMi database.</p> </div> <ul data-bbox="407 1570 1385 1707" style="list-style-type: none"> <li data-bbox="407 1570 1385 1707">• When specifying a Correlation Filter, precede the attribute name with either <code>parent.</code> or <code>child.</code> to specify from which incident the attribute value should be compared. For example, you might specify <code>\${parent.hostedOn}</code> or <code>\${child.ifDesc}</code>. <p data-bbox="402 1738 938 1770">Possible Source Object choices are as follows:</p> <ul data-bbox="407 1801 938 1833" style="list-style-type: none"> <li data-bbox="407 1801 938 1833">• Card [click here for a list of attribute values] <p data-bbox="440 1850 1076 1881">Unique Keys from the Card Form: Capabilities Tab:</p>

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) • Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: valueOfInterfaceCa(<CA_Name>) For example: <code>\${child.valueOfInterfaceCA(Role)} = WAN Connection</code> Values from the Basics Attributes listed on the Interface Form: <ul style="list-style-type: none"> ■ hostedOn (Hosted On Node) You must use the full DNS name for the hostedOn value. Values from the Interface Form: General Tab: <ul style="list-style-type: none"> ■ ifName (name configured for the interface) ■ ifAlias (alias configured for the interface) ■ ifDesc (description configured for the interface) ■ ifIndex (index assigned to the interface) ■ ifSpeed (speed configured for the interface) When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps. Addresses from the Interface Form: IP Addresses Tab: <ul style="list-style-type: none"> ■ ipAddress (IP Address associated with the interface) Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <=. Unique Keys from the Interface Form: Capabilities Tab: <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) Values from the Basics Attributes on the parent Node Form: <ul style="list-style-type: none"> ■ isSnmpInterface (Agent Enabled) Values from the parent Node Form: General Tab:

Valid Attributes , continued

Attribute	Description
	<ul style="list-style-type: none"> ■ sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorInterface (Device Vendor) ■ devFamilyInterface (Device Family) <ul style="list-style-type: none"> • IP Address [click here for a list of attribute values] <p>Unique Keys from the IP Address Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <ul style="list-style-type: none"> • Node [click here for a list of attribute values] <p>Use the following syntax to specify a Custom Attribute for a Node:</p> <p>valueOfNodeCa(<CA_Name>)</p> <p>For example: \${valueOfNodeCa(Location)} = USA</p> <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> ■ hostname (Hostname, <i>case-sensitive</i>) ■ mgmtIPAddress (Management Address) ■ isSnmpNode (Agent Enabled) ■ isNnmSystemLocal (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p>

Valid Attributes , continued

Attribute	Description
	<p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server). See "Global Manager: Connect to a Regional Manager" on page 110.</p>

Valid Operator Values

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} = 5</pre> <p>Match any incident with the Source Object's Capability equal to com.hp.nnm.capability.card.fru</p> <pre>\$(capability) = com.hp.nnm.capability.card.fru</pre>
!=	<p>Finds all values not equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with Device Vendor for the interface (Source Object) not equal to Cisco:</p> <pre>\${devVendorInterface} != Cisco</pre>
<	<p>Finds all values less than the value specified.</p> <p>Click here for an example.</p>

Valid Operator Values, continued

Operator	Description
	<p>Match any incident with a CIA value of less than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} < 5</pre>
<=	<p>Finds all values less than or equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of less than or equal to 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} <= 5</pre>
>	<p>Finds all values greater than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value of greater than 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} > 5</pre>
>=	<p>Finds all values greater than or equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface speed) ifSpeed value of 10Mbps:</p> <pre>\${ifSpeed} >= 10000000</pre>
is not null	<p>Finds all non-blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that contains a value:</p> <pre>\${ifName} is not null</pre>
is null	<p>Finds all blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface name) ifName attribute that does not contain a value:</p> <pre>\${ifName} is null</pre>
like	<p>Finds matches using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p>

Valid Operator Values, continued

Operator	Description
	<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object's (interface description) ifDesc attribute that includes Serial followed by one or more digits:</p> <pre>{ifDesc} like Serial\d+</pre> <p>Match any incident with a Source Object's (interface alias) ifAlias attribute that contains EtherChannel (for example, PAgPEtherChannel Group 1).</p> <p>Note: The . (period) indicates any alphanumeric character.</p> <pre>{ifAlias} like .*EtherChannel.*</pre> <p>Match any incident with a CIA attribute value of Chassis Fan Tray followed by a digit and Object Identifier (OID) of .1.3.6.1.4.1.9.9.13.1.4.1.3</p> <p>Note: To include literal strings in the value, enclose the string value in \Q<literal_value>\E as shown in the following example.</p> <pre>{valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.3\E)} like Chassis Fan Tray \d</pre>
not like	<p>Finds all matches that do not have the values specified using the syntax defined for Java regular expressions. For more information, see the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E .</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p>

Valid Operator Values, continued

Operat-or	Description
	Match any incident with a Source Object's (interface name) ifName value that does not include rtr: <code>\${ifName} not like .*rtr.*</code>

Valid Expressions

Attribute	Description
Expression	The value or pattern for which you want NNMi to search. Note the following: <ul style="list-style-type: none">• The expression can include a valid Attribute.• The value or pattern you want to match is case sensitive.• When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.

Configure a Source Object Filter for a Causal Rule

The Source Filter tab enables you to create a filter to specify which Source Object should be used for the Parent Incident that is generated for this Causal Rule.

Note: Create only one Source Object Filter for a Causal Rule. If you select **Use Child Incident's Source Object for Parent** ☒, NNMi ignores any Source Object Filter you configure.

For information about each Causal Rules tab:

For information about each Child Incident tab:

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor for Custom Correlations:

- You can use Custom Incident Attributes, attributes for an incident's Source Node or Source Object, or both to define how matching incidents should be considered for the Correlation Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For example, if the Attribute type is numeric, NNMi does a numeric comparison. If the Attribute type is textual, NNMi does a lexicographical string comparison. In all cases, when you use the **like** or

not like operator, NNMi uses a lexicographical string comparison. [Click here](#) for more information about Attribute types:

- `ifIndex` and `ifSpeed` are numeric Attributes.
 - Any Attribute name that begins with "is" (`isSnmppInterface`, `isSnmppNode`, `isNnmSystemLocal`) represents a Boolean Attribute.
 - All other Attributes are textual.
- Each set of expressions associated with a Boolean Operator (for example, AND) is treated as if it were enclosed in parentheses and evaluated together.
 - View the expression displayed under **Filter String** to see the logic of the expression as it is created.
 - The AND and OR Boolean Operators must contain at least two expressions.
 - The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
 - The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.


Filter Editor Buttons and Drag and Drop Feature




Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.
AND	Inserts the AND Boolean Operator in the selected cursor location. Note: View the expression displayed under Filter String to see the logic of the expression as it is created.
OR	Inserts the OR Boolean Operator in the current cursor location. Note: View the expression displayed under Filter String to see the logic of

Filter Editor Buttons and Drag and Drop Feature, continued

Button or Feature	Description
	the expression as it is created.
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none"> Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none"> Click the item you want to move before dragging it to a new location. As you drag a selected item, an underline indicates the target location. If you are moving the selection up, NNMi places the item above the target location. If you are moving the selection down, NNMi places the item below the target location. If you attempt to move the selection to an invalid target location, NNMi displays an error message.


To configure a Source Object Filter for a Causal Rule:

- Navigate to the **Custom Correlation Configuration** form:
 - From the workspace navigation pane, select the  **Configuration** workspace.
 - Expand the **Incidents** folder.
 - Select **Custom Correlation Configuration**.
- Navigate to the **Causal Rules** tab.
- From the **Causal Rules** table toolbar, do one of the following:

- To create a Causal Rule, click the  New icon, and continue.
 - To edit a Causal Rule, click the  Open icon in the row representing the Causal Rule you want to edit, and continue.
 - To delete a Causal Rule, click the  Delete icon.
4. Create your Causal Rule. (See ["Configure a Causal Rule" on page 808.](#))
 5. Create your Child Incident Configuration . (See ["Configure a Child Incident for a Causal Rule" on page 814.](#))
 6. *Optional.* Configure a Child Incident Filter. (See ["Configure a Child Incident Filter for a Causal Rule" on page 817.](#))
 7. *Optional.* Configure a Source Object Filter. (See the tables that follow, starting with [Filter Editor Settings](#)).

Filter Editor Settings


Setting	Description
Attribute	The Attribute on which NNMi searches. See Valid Attributes below for a description of valid Attributes.
Operator	Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.
Expression	Use the Expression to complete the criteria for the Parent Incident configuration. See Valid Expressions below for more information.

8. *Optional.* Configure a Source Node Filter. (See ["Configure a Source Node Filter for a Causal Rule" on page 836.](#))
9. Click  **Save and Close** to save your changes and return to the previous form.

Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMi searches. Valid attributes other than Source Node attributes depend on the Incident's Source Object. NNMi checks the Source Node as well as the Source Object for any Capability value.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none">• Boolean Attributes begin with "is" and must contain the value true or false.• If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source

Valid Attributes, continued

Attribute	Description
	<p>Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter.</p> <ul style="list-style-type: none"> When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the <code>hostedOn</code> attribute and the Source Object is not an interface, the correlation does not occur. <div data-bbox="456 583 1370 732"> <p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p> </div> <p>A Source Object attribute value of <code>None</code> indicates that NNMi cannot identify the Source Object or the Source Object is a Node. If you want to match the incident, use one or more Source Node attributes.</p> <ul style="list-style-type: none"> Interface [click here for a list of attribute values] Use the following syntax to specify a Custom Attribute for an Interface: <code>valueOfInterfaceCa(<CA_Name>)</code> For example: <code>\${child.valueOfInterfaceCA(Role)} = WAN Connection</code> Values from the Basics Attributes listed on the Interface Form: <ul style="list-style-type: none"> <code>hostedOn</code> (Hosted On Node) <div data-bbox="485 1260 1370 1337"> <p>Note: You must use the full DNS name for the <code>hostedOn</code> value.</p> </div> Values from the Interface Form: General Tab: <ul style="list-style-type: none"> <code>ifName</code> (name configured for the interface) <code>ifAlias</code> (alias configured for the interface) <code>ifDesc</code> (description configured for the interface) <code>ifIndex</code> (index assigned to the interface) <code>ifSpeed</code> (speed configured for the interface) <div data-bbox="485 1751 1370 1858"> <p>Note: When entering the value for <code>ifSpeed</code>, use the actual numeric value for the interface speed. For example, use <code>10000000</code> for <code>ifSpeed</code> 10 Mbps.</p> </div>

Valid Attributes, continued

Attribute	Description
	<p>Addresses from the Interface Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ipAddress (IP Address associated with the interface) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p> <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the parent Node Form:</p> <ul style="list-style-type: none"> isSnmpInterface (Agent Enabled) <p>Values from the parent Node Form: General Tab:</p> <ul style="list-style-type: none"> sysOidInterface (System Object ID) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> devVendorInterface (Device Vendor) devFamilyInterface (Device Family) <ul style="list-style-type: none"> IP Address [click here for a list of attribute values] <p>Unique Keys from the IP Address Form: Capabilities Tab:</p> <ul style="list-style-type: none"> capability (Unique Key of the Capability) <ul style="list-style-type: none"> Node [click here for a list of attribute values] <p>Use the following syntax to specify a Custom Attribute (CA) for a Node:</p> <pre>valueOfNodeCa(<CA_Name>)</pre> <p>For example: <code>\${valueOfNodeCa(Location)} = USA</code></p> <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none"> hostname (Hostname, <i>case-sensitive</i>) mgmtIPAddress (Management Address) isSnmpNode (Agent Enabled) isNnmSystemLocal (NNMi Management Server)

Valid Attributes, continued

Attribute	Description
	<p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> ■ sysName (System Name) ■ sysContact (System Contact) ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <= .</p> <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(<i>NNMi Advanced</i>) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server).</p>

Valid Operator Values

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of 5 and Object Identifier (OID) of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} = 5</pre>
!=	<p>Finds all values not equal to the value specified.</p>

Valid Operator Values, continued

Operator	Description
	<p>Click here for an example.</p> <p>Match any incident with a Source Object value of Interface with Device Vendor value not equal to Cisco:</p> <p><code>\${devVendorInterface} != Cisco</code></p>
<	<p>Finds all values less than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value less than 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} < 5</code></p>
<=	<p>Finds all values less than or equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA attribute value less than or equal to 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} <= 5</code></p>
>	<p>Finds all values greater than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value greater than 5 and Object Identifier (OID) attribute value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <p><code>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} > 5</code></p>
>=	<p>Finds all values greater than or equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object attribute value of Interface that has an (interface speed) ifSpeed of 10Mbps:</p> <p><code>\${ifSpeed} >= 10000000</code></p>
is not null	<p>Finds all non-blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object attribute value of Interface that has an (interface name) ifName value:</p> <p><code>\${ifName} is not null</code></p>
is null	<p>Finds all blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object attribute value of Interface that does not</p>

Valid Operator Values, continued

Operator	Description
	<p>have an (interface name) ifName value:</p> <p><code>\${ifName} is null</code></p>
like	<p>Finds matches using wildcard characters and the question mark.</p> <p>The asterisk (*) character means <i>any number of characters of any type at this location</i>.</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Object attribute value of Interface with a (description) ifDesc that begins with Serial followed by any number of characters:</p> <p><code>\${ifDesc} like Serial*</code></p> <p>Match any incident with a Source Object attribute value of Interface with an (interface alias) ifAlias value that begins with EtherChannel (for example, EtherChannel Group 1).</p> <p><code>\${ifAlias} like EtherChannel*</code></p>
not like	<p>Finds all matches that do not have the values specified.</p> <p>The asterisk (*) characters means <i>any number of characters of any type at this location</i>.</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any with a Source Object attribute value of Interface with an (interface name) ifName value that does not begin with rtr*:</p> <p><code>\${ifName} not like rtr*</code></p>

Valid Expressions

Attribute	Description
Expression	<p>The value or pattern for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The expression can include a valid Attribute. • The value or pattern you want to match is case sensitive. • When entering the value for ifSpeed, use the actual numeric value for the interface speed. For example, use 10000000 for ifSpeed 10 Mbps.

Configure a Source Node Filter for a Causal Rule

The Source Node Filter tab enables you to create a filter to specify which Source Node should be used for the Parent Incident that is generated for this Causal Rule.

Note: Create only one Source Node Filter for a Causal Rule. If you select **Use Child Incident's Source Node for Parent** ☒, NNMi ignores any Source Node Filter you configure.

For information about each Causal Rules tab:

For information about each Child Incident tab:

Use the Filter Editor Buttons to insert Boolean Operators and to append, insert, and replace expressions in the Filter String. Use the Drag and Drop feature to make changes to the placement of the expressions in your Filter String. [Click here](#) for more information about using the Filter Editor:

- You can use Custom Incident Attributes, attributes for an incident's Source Node, or both to define how matching incidents should be considered for the Causal Rule. See [Valid Attributes](#) for more information.
- When specifying Attribute names and values, NNMi uses the type to determine a match. For example, if the Attribute type is Integer, NNMi does a numeric comparison. If the Attribute type is textual, NNMi does a lexicographical string comparison. In all cases, when you use the **like** or **not like** operator, NNMi uses a lexicographical string comparison.
- Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions.
- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.





Filter Editor Buttons and Drag and Drop Feature

Button or Feature	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected

Filter Editor Buttons and Drag and Drop Feature, continued


Button or Feature	Description
	expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed Left or Right Expression.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Drag and Drop	<p>You can drag any of the following items to a new location in the Filter String:</p> <ul style="list-style-type: none"> Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS Filter Expression (Attribute, Operator and Value) <p>When moving items in the Filter String, note the following:</p> <ul style="list-style-type: none"> Click the item you want to move before dragging it to a new location. As you drag a selected item, an underline indicates the target location. If you are moving the selection up, NNMi places the item above the target location. If you are moving the selection down, NNMi places the item below the target location. If you attempt to move the selection to an invalid target location, NNMi displays an error message.

To configure a Source Node Filter for a Causal Rule:


1. Navigate to the **Custom Correlation Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Causal Rules** tab.
3. From the **Causal Rules** table toolbar, do one of the following:
 - To create a Causal Rule, click the  New icon, and continue.
 - To edit a Causal Rule, click the  Open icon in the row representing the Causal Rule you want to edit, and continue.
 - To delete a Causal Rule, click the  Delete icon.
4. Create your Causal Rule. (See ["Configure a Causal Rule" on page 808.](#))
5. Create your Child Incident Configuration . (See ["Configure a Child Incident for a Causal Rule" on page 814.](#))
6. *Optional.* Configure a Child Incident Filter. (See ["Configure a Child Incident Filter for a Causal Rule" on page 817.](#))
7. *Optional.* Configure a Source Object Filter. (See ["Configure a Source Object Filter for a Causal Rule" on page 827.](#))
8. *Optional.* Configure a Source Node Filter. (See the tables that follow, starting with [Filter Editor Settings](#).)

Filter Editor Settings

Setting	Description
Attribute	The Attribute on which NNMI searches. See Valid Attributes below for a description of valid Attributes.
Operator	Use this Operator to establish the relationship between the Attribute and Expression. See Valid Operators in the table below for the description of each valid Operator.
Expression	Use the Expression to complete the criteria for the Parent Incident configuration. See Valid Expressions below for more information.

9. Click  **Save and Close** to save your changes and return to the previous form.

Valid Attributes

Attribute	Description
Attribute	<p>The Attribute on which NNMi searches.</p> <p>Note the following when specifying Attributes:</p> <ul style="list-style-type: none">• Boolean Attributes begin with "is" and must contain the value true or false.• If you use attributes that are valid for the Source Node, NNMi uses the Source Node when comparing values. If you use attributes that are valid for the Source Object, NNMi uses the Source Object when comparing values. You cannot use attributes that are valid for the Source Node and Source Object in the same filter.■ When using attributes for a Source Object, the attribute must be valid for the incident's Source Object or NNMi does not find a match. For example, if you use the <code>hostedOn</code> attribute and the Source Object is not an interface, the correlation does not occur. <div><p>Tip: To check a Source Object for an incident, select the incident of interest, then select  Open from the Lookup menu for the Source Object, and examine the Source Object form.</p></div> <p>A Source Object attribute value of None indicates that NNMi cannot identify the Source Object or the Source Object is a Node. If you want to match the incident, use one or more Source Node attributes.</p> <ul style="list-style-type: none">• Node [click here for a list of attribute values] <p>Use the following syntax to specify a Custom Attribute for a Node:</p> <pre>valueOfNodeCa(<CA_Name>)</pre> <p>For example: <code>\${valueOfNodeCa(Location)} = USA</code></p> <p>Values from the Basics Attributes on the Node Form:</p> <ul style="list-style-type: none">■ <code>hostname</code> (Hostname, <i>case-sensitive</i>)■ <code>mgmtIPAddress</code> (Management Address)■ <code>isSnmpNode</code> (Agent Enabled)■ <code>isNnmSystemLocal</code> (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none">■ <code>sysName</code> (System Name)■ <code>sysContact</code> (System Contact)

Valid Attributes, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ sysLocation (System Location) ■ sysOidNode (System Object ID) <p>Addresses from the Node Form: IP Addresses Tab:</p> <ul style="list-style-type: none"> ■ hostedIPAddress (Address) <p>Because NNMi uses a lexicographical compare when evaluating IP addresses, it is recommended that you use the like and not like operators to specify IP address ranges rather than using the following operators: >, >=, <, or <=.</p> <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> ■ capability (Unique Key of the Capability) <p>Values from the Basics Attributes on the associated Device Profile Form:</p> <ul style="list-style-type: none"> ■ devVendorNode (Device Vendor) ■ devFamilyNode (Device Family) <p>Values from the associated entry on the Regional Manager Form: Connection Tab:</p> <ul style="list-style-type: none"> ■ nnmSystemName (Hostname, <i>case-sensitive</i>) <p>(NNMi Advanced) If the Global Network Management feature is enabled, this attribute value identifies a Regional Manager (NNMi management server).</p>

Valid Operator Values

Operator	Description
=	<p>Finds all values equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value of 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} = 5</pre>
!=	<p>Finds all values not equal to the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Node value that has a Device Vendor value not equal to Cisco:</p> <pre>\${devVendorNode} != Cisco</pre>

Valid Operator Values, continued

Operator	Description
<	<p>Finds all values less than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value less than 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia(\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} < 5</pre>
<=	<p>Finds all values less than or equal to the value specified.</p> <p>Click here for examples.</p> <p>Match any incident with a CIA value less than or equal to 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} <= 5</pre>
>	<p>Finds all values greater than the value specified.</p> <p>Click here for an example.</p> <p>Match any incident with a CIA value greater than 5 and Object Identifier (OID) value of .1.3.6.1.4.1.9.9.106.2.0.1:</p> <pre>\${valueOfCia (\Q.1.3.6.1.4.1.9.9.106.2.0.1\E)} > 5</pre>
>=	<p>Finds all values greater than or equal to the value specified.</p>
is not null	<p>Finds all non-blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Node that has a (system contact name) sysContact value:</p> <pre>\${sysContact} is not null</pre>
is null	<p>Finds all blank values.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Node that does not have a (system contact name) sysContact value:</p> <pre>\${sysContact} is null</pre>
like	<p>Finds matches using wildcard characters and the question mark.</p> <p>The asterisk (*) character means <i>any number of characters of any type at this location.</i></p> <p>The question mark (?) character means <i>any single character of any type at this location.</i></p> <p>Click here for an example.</p>

Valid Operator Values, continued

Operator	Description
	Match any incident with a Source Node that has a (system location) sysLocation value that begins with Bldg5: <code>\${syslocation} like Bldg5*</code>
not like	<p>Finds all matches that do not have the values specified.</p> <p>The asterisk (*) characters means <i>any number of characters of any type at this location</i>.</p> <p>The question mark (?) character means <i>any single character of any type at this location</i>.</p> <p>Click here for an example.</p> <p>Match any incident with a Source Node that has a (system location) sysLocation value that does not begin with Bldg5: <code>\${sysLocation} not like Bldg5*</code></p>

Valid Expressions

Attribute	Description
Expression	<p>The value or pattern for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The expression can include a valid Attribute.• The value or pattern you want to match is case sensitive.

Causal Rule Example

Tip: Use these steps as a guideline for creating your own Causal Rules.

This example creates a Causal Rule that generates a new CardHealthProblem Parent Incident. It uses the traps described in the following table to determine the following:

- Whether there is a temperature problem or diagnostic failure for a Field Replaceable Unit (FRU) Card module
- Whether the source of the problem is a fan, a power supply, or both.

Trap Descriptions

Trap	Description
FruModuleStatusChange	Indicates a temperature problem (14) or diagnostic failure (11) for the Field Replaceable Unit (FRU) card

Trap Descriptions, continued

Trap	Description
	module
CiscoEnvMonFanNotification	Physical Sensor object incident: Indicates the problem is related to a fan. The example Causal Rule uses this trap to obtain the name of the fan.
CiscoEnvMonSuppStatusChangeNotif	Physical Sensor object incident: Indicates the problem is related to the Power Supply.




Using the Causal Rule described in this example, NNMi generates a new CardHealthProblem Parent Incident when NNMi determines the following:




- The Source Object for the Child Incident is a Field Replaceable Unit (FRU) card.


Note: NNMi checks for the **com.hp.nnm.capability.card.fru** capability to determine whether the Source Object is an FRU card.

- The FruModuleStatusChange trap returns a value of either 14 (temperature problem) or 11 (diagnostic failure).



To configure the CardHealth Causal Rule Basics information:

1. Navigate to the **Causal Rule** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Custom Correlation Configuration**.
2. Navigate to the **Causal Rules** tab.
3. From the **Causal Rules** table toolbar, click the  New icon.
4. In the **Name** attribute, enter a unique name that will help you to identify the Causal Rule. In this example, the Causal Rule Name is **Card Health**.
5. In the **Author** attribute, either enter a name that identifies the person who is creating the Causal Rule or keep the default value **Customer**.
6. Make sure **Enabled** ☒ is checked to indicate the NNMi Causal Engine should use this Causal Rule when evaluating incidents.
7. To create a new Incident Configuration for the Parent Incident, in the **Parent Incident** Lookup Field, select  New.

8. In the Management Event Configuration form, enter the **Basics** information as follows:
 - a. In the **Name** attribute, enter **CardHealthProblem** for the Name value.
 - b. Make sure **Enabled** ☒ is checked to indicate the NNMi Causal Engine should use this Causal Rule when evaluating incidents.
 - c. In the **Categories** Lookup Field, select  Quick Find and select **Fault** from the list of incident Categories.
 - d. In the **Family** Lookup Field, select  Quick Find and then **Card** from the list of incident Families.
 - e. In the **Severity** Lookup Field, select  Quick Find and then **Critical** from the list of incident Severities.
 - f. In the Message Format attribute, enter the following: Card
\$.1.3.6.1.2.1.47.1.1.1.1.7.5000 with \$.1.3.6.1.4.1.9.9.13.1.4.1.2 and
Power Supply not functioning

NNMi displays the name of the Card using the Object Identifier (OID) value of
\$.1.3.6.1.2.1.47.1.1.1.1.7.5000. NNMi displays the name of the Fan using the OID value of
\$.1.3.6.1.4.1.9.9.13.1.4.1.2.
 - g. Click **Save and Close** to save your changes and return to the **Causal Rule** form.
9. In the **Correlation Nature** select  **Root Cause** from the drop-down list.
10. In **Common Child Incident Attribute**, enter **\${hostname}**.
11. In the **Correlation Window Duration** attribute, keep the default value of **5** minutes.
12. Use the **Description** attribute to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.

To configure the first Child Incident (CiscoModuleStatusChange):

1. In the **Causal Rule** form, navigate to the **Child Incidents** tab.
2. Click the  New icon to configure the first Child Incident.
3. In the **Name** attribute of the Child Incident Configuration form, enter **FRU Card**.
4. In the **Child Incident** Lookup Field, select  Quick Find and then **CiscoModuleStatusChange** from the list of incident configurations.
5. To forward the Card name to the new Parent Incident, in **Forward Child Custom Incident Attributes**, enter **.1.3.6.1.2.1.47.1.1.1.1.7.5000**.

6. Check to enable **Use Child Incident's Source Object for Parent** ☒.
7. Check to enable **Use Child Incident's Source Node for Parent** ☒.

To configure the first Child Incident Filter:



1. In the **Child Incident Configuration** form, navigate to the **Child Incident Filter** tab.

Next, create the following filter: (capability = com.hp.nnm.capability.card.fru AND $\${valueOfCia(\backslash Q.1.3.6.1.4.1.9.9.117.1.2.1.1.2.5000\backslash E)} = 11$) OR $\${valueOfCia(\backslash Q.1.3.6.1.4.1.9.9.117.1.2.1.1.2.5000\backslash E)} = 14$)

2. In the **Attribute** field, enter **capability**.
3. In the **Operator** field, select = from the drop-down menu.
4. In the **Expression** field, enter **com.hp.nnm.capability.card.fru**.
5. Click **Append**.
6. Select **Insert** from the drop-down menu.
7. Click **AND**.
8. Click to select **AND** in the Child Incident Filter Expression.
9. Select **Append** from the drop-down menu.
10. Click **OR**.
11. Click to select **OR** in the Child Incident Filter Expression.
12. In the **Attribute** field, enter **$\${valueOfCia(\backslash Q.1.3.6.1.4.1.9.9.117.1.2.1.1.2.5000\backslash E)}$** .
13. In the **Operator** field, select = from the drop-down menu.
14. In the **Expression** field, enter **11**.
15. Click **Append**.
16. In the **Attribute** field, enter **$\${valueOfCia(\backslash Q.1.3.6.1.4.1.9.9.117.1.2.1.1.2.5000\backslash E)}$** .
17. In the **Operator** field, select = from the drop-down menu.
18. In the **Expression** field, enter **14**.
19. Click to select **OR** in the Child Incident Filter Expression.
20. Click **Append**.

21. Click **Save and Close** to return to the **Causal Rule** form.

To configure the second Child Incident (CiscoEnvMonFanNotification):


1. In the **Causal Rule** form, navigate to the **Child Incidents** tab.
2. Click the  New icon to configure the second Child Incident.
3. In the **Name** attribute of the **Child Incident Configuration** form, enter **Chassis Fan**.
4. In the **Child Incident** Lookup Field, select  Quick Find and then **CiscoEnvMonFanNotification** from the list of incident configurations.
5. To forward the Fan name to the new Parent Incident, in **Forward Child Custom Incident Attributes**, enter **.1.3.6.1.2.1.47.1.1.1.1.7.5000**.


To configure the second Child Incident Filter:

1. In the **Child Incident Configuration** form, navigate to the **Child Incident Filter** tab.

Next, create the following filter: $\{ \{ \text{valueOfCia}(\backslash \text{Q.1.3.6.1.4.1.9.9.13.1.4.1.2} \backslash \text{E}) \} = \text{Chassis Fan Tray 1 AND } \{ \text{valueOfCia}(\backslash \text{Q.1.3.6.1.4.1.9.9.13.1.4.1.3} \backslash \text{E}) \} = 3 \}$
2. In the **Attribute** field, enter $\{ \text{valueOfCia}(\backslash \text{Q.1.3.6.1.4.1.9.9.13.1.4.1.2} \backslash \text{E}) \}$.
3. In the **Operator** field, select = from the drop-down menu.
4. In the **Expression** field, enter **Chassis Fan Tray 1**.
5. Click **Append**.
6. Select **Insert** from the drop-down menu.
7. Click **AND**.
8. In the **Attribute** field, enter $\{ \text{valueOfCia}(\backslash \text{Q.1.3.6.1.4.1.9.9.13.1.4.1.3} \backslash \text{E}) \}$.
9. In the **Operator** field, select = from the drop-down menu.
10. In the **Expression** field, enter **3**.
11. Click **Append**.
12. Click **Save and Close** to return to the **Causal Rule** form.

To configure the third Child Incident (CiscoEnvMonSuppStatusChangeNotif):

1. In the **Causal Rule** form, navigate to the **Child Incidents** tab.
2. Click the  New icon to configure the third Child Incident.

3. In the **Name** attribute of the **Child Incident Configuration** form, enter **Chassis Power**.
4. In the **Child Incident** Lookup Field, select  Quick Find and then **CiscoEnvMonSuppStatusChangeNotif** from the list of incident configurations.
5. To forward the Fan name to the new Parent Incident, in **Forward Child Custom Incident Attributes**, enter **`${valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.2\E)}`**.

To configure the third Child Incident Filter:

1. In the **Child Incident Configuration** form, navigate to the **Child Incident Filter** tab.

Next, create the following filter: (`${valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.3\E}` = 3}
AND `${valueOfCia(\Q.1.3.6.1.4.1.9.9.117.1.2.1.1.2.5000\E}` = Power Supply 1,
WS-CAC-1300W)

2. In the **Attribute** field, enter **`${valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.3\E)}`**.
3. In the **Operator** field, select = from the drop-down menu.
4. In the **Expression** field, enter **3**.
5. Click **Append**.
6. Select **Insert** from the drop-down menu.
7. Click **AND**.
8. In the **Attribute** field, enter **`${valueOfCia(\Q.1.3.6.1.4.1.9.9.13.1.4.1.2\E)}`**.
9. In the **Operator** field, select = from the drop-down menu.
10. In the **Expression** field, enter **Power Supply 1, WS-CAC-1300W**.
11. Click **Append**.
12. Click **Save and Close** to save your changes and return to the **Causal Rule** form.
13. Click **Save and Close** to save your changes and return to the **Custom Correlation Configuration** form.
14. Click **Save and Close** to save the Custom Correlation Configuration.

See ["Correlation Rule Example" on page 804](#) for an example of creating a Correlation Rule.

Configure an Action for an Incident

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a

trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.

If the NNMi management server is running on a Windows operating system, NNMi runs each action that you configure using the Local System account. If the NNMi management server is running on a Linux operating system, NNMi runs each action that you configure using the bin user name. To change the user account associated with actions, see the "Setting the Action Server Name Parameter" section in the *HP Network Node Manager i Software Deployment Reference*.

You can provide the required information within the following contexts:

["Configure Actions for an SNMP Trap Incident" on page 1042](#)

["Configure Actions for a Management Event Incident" on page 1384](#)

["Configure Actions for a Syslog Message Incident \(HP ArcSight\)" on page 1217](#)

Lifecycle Transition Action Form

Use this form to enter the command you want to run when an incident of the type you are configuring is at a particular [Lifecycle State](#). For example, when an incident is generated (**Registered**), you might want to automatically open a trouble ticket or email or page your network operator.

You can provide the required information within the following contexts:

["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#)

["Lifecycle Transition Action Form \(Management Events\)" on page 1386](#)

["Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)" on page 1219](#)

Valid Parameters for Configuring Incident Actions (Management Events)

When configuring incident actions, consider using incident information as part of the action. NNMi provides the following parameter values. Use these parameters as variables in your Jython or executable files.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See ["Lifecycle Transition Action Form" on the previous page](#) for more information about configuring incident actions.

Valid Parameters Visible From an Incident's Form

Parameter Value	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$severity, \$sev	Value of the Severity attribute of the Incident form.

Valid Parameters Visible from a Node Form

Parameter Value	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the

Valid Parameters Visible from a Node Form, continued

	incident's source Node form: General tab.
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab.

Valid Parameters Visible from an Interface Form

Parameter Value	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.
\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.

Valid Parameters Visible from a Layer 2 Connection Form

Parameter Value	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.

Valid Parameters Visible from a Layer 2 Connection Form, continued

Parameter Value	Description
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

Valid Parameters Visible from a VLAN Form

Parameter Value	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the Global VLAN Name attribute associated with the interface that is the incident's source object. To access this information from a Node form or Interface form, navigate to the VLAN Ports tab. If the node or interface is part of more than one VLAN, this parameter returns a comma-separated list.

Valid Parameters Not Visible From a Form

Parameter Value	Description
\$id	Unique Object Identifier attribute value for the incident (unique across the entire NNMi Database).
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$messageFormat, \$msg	<i>Valid for Incident actions only.</i> Message text displayed for an incident when this parameter is included as an argument to an

Valid Parameters Not Visible From a Form, continued

Parameter Value	Description
	incident action.
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection: The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name> [interface_name]</i>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name 4/1 as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances..
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

Valid Parameters Established in Custom Incident Attributes

Parameter Value	Description
\$<position_number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_name>	Value of the name that is used for the custom incident attribute. For example, \$mycompany.mycia. NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_oid>	Value of the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: \$<CIA_name>:<CIA_value> in which the custom incident attribute name appears followed by the custom incident attribute value.

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the [nnmloadmib.ovpl](#) command.

Functions to Generate Values Within Incident Messages

Function	Description
\$text (\$<position_number>)	The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA. Note: If a text value is not available, NNMi returns the numeric value.
\$text (\$<CIA_oid>)	The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA.

Functions to Generate Values Within Incident Messages, continued

Function	Description
	<p>Note: If a text value is not available, NNMi returns the following message as the value: <CIA <OID> with value <value> was not found within the mib cache</p>

Handling Special Characters in Action Arguments

In some cases, NNMi requires or inserts double quotes or escape characters in arguments that are passed to the Jython file, executable, or shell script using the **Command** attribute.

Note: Shell commands are not permitted in the **Command** attribute. If you use shell commands, place them in a shell script file and reference that file from the **Command** attribute.

The following table describes how to handle special characters included as arguments to your Jython files, executables, or shell scripts.

Handling Special Characters in Arguments

Circumstance	Result
If the following special characters are requested as a single argument to a Jython, executable, shell script, or shell command: , ; & > < (space) =	The argument (containing the special character) must be wrapped in double quotes. For example, "Hello;World" .
Request all available CIA name/value pairs for a particular incident \$*	<p>The \$* argument returns a parsed string. For this example, the available CIA name/value pairs are:</p> <ul style="list-style-type: none">• \$1 = 123• \$com.mycompany.mycia = 012345• \$1.3.6.1.2.1.2.2.1.1 = 1007 <p>Example Command</p> <pre>echoScript.bat \$*</pre> <p>NNMi returns the following string in response to the command:</p> <ul style="list-style-type: none">• Windows: "1: 123, com.mycompany.mycia:012345, .1.3.6.1.2.1.2.2.1.1:1007"

Handling Special Characters in Arguments, continued

Circumstance	Result
	<ul style="list-style-type: none"> • Linux: 1: 123, com.mycompany.mycia:012345, .1.3.6.1.2.1.2.2.1.1:1007
<p>Request specific CIA values as an argument to an action command</p> <p><i>\$<CIA name, position, or OID></i></p>	<p>To request specific CIA values, use the \$ followed by the CIA name</p> <p>Example Command</p> <pre>echoScript.bat \$1 \$com.mycompany.mycia \$.1.3.6.1.2.1.2.2.1.1</pre> <p>For this example, the CIA name/value pairs are:</p> <ul style="list-style-type: none"> • \$1 = 123 • \$com.mycompany.mycia = 012345 • \$.1.3.6.1.2.1.2.2.1.1 = 1007 <p>NNMi returns the following string in response to the command:</p> <ul style="list-style-type: none"> • Windows: 123 012345 1007 • Linux: 123 012345 1007
<p>If an invalid CIA name, position, or OID is requested as an argument to an action command</p>	<p>If the trap or event does not contain one or more of the requested CIAs, NNMi passes error messages as arguments.</p> <p>Linux:</p> <pre>Invalid or unknown cia position 1 Invalid or unknown cia com.mycompany.mycia Invalid or unknown cia .1.3.6.1.2.1.2.2.1.1</pre> <p>Windows: NNMi encloses each CIA value in double quotes.</p> <pre>Invalid or unknown cia "position 1" Invalid or unknown cia "com.mycompany.mycia" Invalid or unknown cia ".1.3.6.1.2.1.2.2.1.1"</pre>
<p>Use \$* in your incident action scripts</p>	<p>Linux:</p> <p>It is recommended that you do not use \$* (shell variable substitution) in your incident action scripts. If you do use \$* within the shell script, specifying \$* expands into the arguments</p>

Handling Special Characters in Arguments, continued

Circumstance	Result
	and are rescanned. This means that blanks in arguments will result in multiple arguments. If you want to use shell variable substitution, use the "\$@" instead so that blanks in arguments are ignored.
Use arguments to Jython methods	Enclose any argument that is not preceded with a "\$" (dollar sign) in double quotes. For example, jythonMethod(\$Severity, "Hello; World").

Example Jython Methods Provided by NNMi

NNMi provides a set of example Jython methods you can use when configuring actions for incidents. These example files reside in the following directory (see ["About Environment Variables" on page 86](#)):

Windows:

```
%NnmInstalLDir%\newconfig\HPOvNmsEvent\actions
```

Linux:

```
$NnmInstalLDir/newconfig/HPOvNmsEvent/actions
```

If you want to use one or more of these example Jython methods, you must first copy the example files to the following directory:

Windows:

```
%NnmDataDir%\shared\nnm\actions
```

<drive> is the drive on which NNMi is installed.

Linux:

```
$NnmDataDir/shared/nnm/actions
```

See ["Lifecycle Transition Action Form" on page 848](#) for more information about creating incident actions.

Note: The argument values, such as *arg1*, and *arg2*, can be any valid parameter as described in ["Valid Parameters for Configuring Incident Actions \(Management Events\)" on page 1397](#).

Example Jython Methods Provided by NNMi

File Name	Method	Description
testPrint.py	testPrint_Registered ()	Displays the incident Lifecycle State specified by the method name.
testPrint.py	testPrint_InProgress	Displays the incident Lifecycle State specified by

Example Jython Methods Provided by NNMi, continued

File Name	Method	Description
	()	the method name.
testPrint.py	testPrint_Completed() ()	Displays the incident Lifecycle State specified by the method name.
testPrint.py	testPrint_Closed()	Displays the incident Lifecycle State specified by the method name.
testPrintArgs.py	testPrintArgs(<i>arg1</i> , <i>arg2</i> , ...)	Displays the specified argument values.
testPrintToFile.py	testPrintToFile(<i>arg1</i>)	Prints the specified argument values to the following file: Windows: <code>%NnmDataDir%\shared\nnm\actions\actionFile</code> <drive> is the drive on which NNMi is installed. Linux: <code>\$NnmDataDir/shared/nnm/actions/actionFile</code>

The output generated from these methods is written to the event action log. You can find the event action log in the following directory:

Windows:

`%NnmDataDir%\log\nnm`

Linux:

`$NnmDataDir/log/nnm/public`

Configure Diagnostics for an Incident

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

NNM iSPI NET provides a set of Diagnostics (Flow Definitions) that can be run on the Source Node each time an incident reaches a specified [Lifecycle State](#) (for example, as soon as an incident becomes Registered).

Note: If you have the licensed HP Operations Orchestration (HP OO) product, you can import HP OO flow definitions into NNMi and then assign these flows to run when NNMi detects certain network incidents. See the "Custom HP OO Flow Management" section of the *HP Network Node Manager iSPI Network Engineering Toolset Software Planning and Installation Guide* and [nnmooflow.ovpl](#) for more information.

These Diagnostics are sets of automated commands specific to one or more device types, including Cisco routers and switches, Cisco switch/routers, and Nortel switches.

See ["Configure Device Profiles" on page 323](#) for more information about device types . See ["Diagnostics \(Flows\) Provided by NNM iSPI NET" on the next page](#) for more information about the Diagnostics provided by NNMi.

Configuring NNMi to automatically gather diagnostic information about the Source Node whenever a specified incident reaches a selected Lifecycle State is a two-step process:

1. Specify the Node Group providing the required information within one of the following contexts:
 - ["Configure Node Settings for an SNMP Trap Incident" on page 957](#)
 - ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#)
 - ["Configure Node Settings for a Management Event Incident" on page 1301](#)
2. Specify the Diagnostics (Flow Definitions) providing the required information within one of the following contexts:
 - ["Configure Diagnostics Selections for a Node Group \(SNMP Trap Incident\)" on page 1001](#)
 - ["Configure Diagnostics Selections for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1177](#)
 - ["Configure Diagnostics Selections for a Node Group \(Management Events\)" on page 1344](#)

D diagnostic Selections Form

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

The Diagnostic Selections form enables you to configure NNMi to automatically gather diagnostic information for the Incident you are configuring. When using this form, you specify the diagnostics you want to run on each applicable node in the specified Node Group.

You can provide the required information within the following contexts:

["Configure Diagnostics Selections for a Node Group \(SNMP Trap Incident\)" on page 1001](#)

["Configure Diagnostics Selections for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1177](#)

["Configure Diagnostics Selections for a Node Group \(Management Events\)" on page 1344](#)

If you have the licensed HP Operations Orchestration (HP OO) product, you can import HP OO flow definitions into NNMi and then assign these flows to run when NNMi detects certain network incidents. See the "Custom HP OO Flow Management" section of the *HP Network Node Manager iSPI Network Engineering Toolset Software Planning and Installation Guide* and [nnmooflow.ovpl](#) for more information.

Diagnostics (Flows) Provided by NNM iSPI NET

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

The Diagnostics (Flows) are sets of automated commands specific to one or more device types. You can associate these Diagnostics with specific incident configurations. After you associate a Diagnostic with an incident configuration and specify the [Lifecycle State](#) for which the Diagnostic should run, the Diagnostic automatically runs on the Source Node for the incident whenever the specified Lifecycle State is reached. See "[Configure Diagnostics for an Incident](#)" on page 857 for more information.

If you have the licensed HP Operations Orchestration (HP OO) product, you can import HP OO flow definitions into NNMi and then assign these flows to run when NNMi detects certain network incidents. See the "Custom HP OO Flow Management" section of the *HP Network Node Manager iSPI Network Engineering Toolset Software Planning and Installation Guide* and [nnmooflow.ovpl](#) for more information.

NNMi also associates these Diagnostics with each node to which the Diagnostics apply. To view the Diagnostics invoked for each node, open the Node form for any node of interest. See [Node Form: Diagnostics Tab](#) for more information.

NNMi provides Diagnostics (Flows) for the following device types:

- [Cisco router](#)
- [Cisco switch](#)
- Cisco switch/router (see [Cisco router](#) and [Cisco switch](#))
- [Nortel switch](#)

Cisco Router Diagnostics (Flow Definitions) Provided by NNMi

Name	Description
Cisco Router Baseline Information	<p>Uses a series of show commands to determine the current configuration of a Cisco router. It first displays the router's and NNMi management server's current times. Next, it invokes a series of commands on the router and formats these results on the summary page. Click here for a list of the commands included in this Diagnostic.</p> <pre>show version show protocol show interface summary show ip route show ip protocol</pre>

Cisco Router Diagnostics (Flow Definitions) Provided by NNMi, continued

Name	Description
	<p>show ip traffic</p> <p>show vlans</p> <p>show cdp</p> <p>show cdp entry</p> <p>show cdp neighbors</p> <p>show log</p> <p>show stacks</p>
Cisco Show IP Route	Obtains routing information using the show ip route command.
Cisco Route To Node Diagnostic	<p>Note: This Diagnostic Flow is not associated with an NNMi incident or node object and can only be run from Operations Orchestration Central's Flow Library. Before the Diagnostic runs, you are prompted for access information for the source router and target device node.</p> <p>Determines failures of either ping or traceroute to a target node. Uses the router to perform a ping and a traceroute to a target node.</p> <p>Click here for a list of commands included in this Diagnostic</p> <p>ping target</p> <p>traceroute target</p>
Cisco Interface Diagnostic	<p>Performs a number of diagnostic checks on a specified interface on the Cisco router. Diagnostics performed include whether the link is Down while the interface is Up. The following error counts are checked:</p> <ul style="list-style-type: none"> • Input errors • CRC¹ errors • Frame errors • Overrun errors • Ignored errors

¹Cyclic Redundancy Check

Cisco Switch Diagnostics (Flow Definitions) Provided by NNMi

Name	Description
Cisco Switch Baseline Information	<p>Uses a series of show commands to determine the current configuration of a Cisco switch. It first displays the switch's and NNMi management server's current times. Next, it invokes a series of commands on the switch and formats these results on the summary page. Click here for a list of the commands included in this Diagnostic.</p> <pre>show version show protocol show interface summary show vlans show cdp show cdp entry show cdp neighbors show log show stacks</pre>
Cisco Switch Spanning Tree Baseline	<p>Gathers Spanning-Tree Protocol and port information from the Cisco switch. The commands run depend on the device's operating system:</p> <p>IOS: show spanning-tree brief</p> <p>CATOS; show spantree</p>

Nortel Switch Diagnostics (Flow Definitions) Provided by NNMi

Name	Description
Nortel Port Diagnostic	<p>Determines statistics, including rate-limit and usage for a specified port on a Nortel switch. This Diagnostic detects rate limit, reception and transmission errors. Similar to Cisco Interface Diagnostic, this flow identifies the following types of errors on the identified port:</p> <ul style="list-style-type: none"> • FCS errors • Undersized packets • Oversized packets • Collisions • Single collisions • Multiple collisions • Excessive collisions

Nortel Switch Diagnostics (Flow Definitions) Provided by NNMi, continued

Name	Description
	<ul style="list-style-type: none">• Deferred packets• Late collisions
Nortel Route to Node Diagnostic	<p>Note: This Diagnostic Flow is not associated with an NNMi incident or node object and can only be run from Operations Orchestration Central's Flow Library. Before the Diagnostic runs, you are prompted for access information for the source router and target device node.</p> <p>Determines failures of either ping or traceroute to a target node.</p> <p>Click here for a list of commands included in this Diagnostic</p> <p>ping target</p> <p>traceroute target</p>
Nortel Switch Baseline	<p>Determines the configuration of a Nortel switch. It first displays the switch's and NNMi management server's current times. Next, it invokes a series of commands on the switch and formats the results on the summary page. Click here for a list of commands included in this Diagnostic</p> <p>show sys-info</p> <p>show interface</p> <p>show logging config</p> <p>show ssh global</p> <p>show stack-info</p> <p>send show rate-limit</p> <p>send show vlan</p>
Nortel Switch Spanning Tree Baseline	<p>Gathers Spanning-Tree Protocol and port information from the Nortel switch. Click here for a list of commands included in this Diagnostic</p> <p>show spanning-tree config</p> <p>show spanning-tree port</p> <p>show spanning-tree vlans</p>


Incident Configurations You Might Want to Enable

NNMi enables you to choose whether you want to generate an Incident for any Incident Configuration that is stored in the NNMi database. To do so you use the **Enable** attribute for each Incident Configuration.

Note: You can use the Actions menu from the NNMi console to Enable or Disable one or more Incident Configurations. See ["Enable or Disable Configurations" on page 36](#) for more information.

By default, not all of the Incident Configurations NNMi provides are enabled.

To determine which Incident Configurations are enabled:

1. Navigate to the **Incidents** folder:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select the incident configuration of interest (**SNMP Trap Incident Configurations**, **Management Event Configurations** or **Syslog Message Incident Configurations**).
3. Click the **Enable** column heading to sort the incident configurations according to the **Enable** configuration setting.

NNMi displays a ✓ check in the Enabled column for each incident configuration that is enabled.

You might want to enable the following incident configurations:

["Generate Interface Disabled Incidents" below](#)

["Generate Card Disabled Incidents" on the next page](#)


["Generate Card Undetermined State Incidents" on the next page](#)

["Generate Performance Threshold Incidents \(NNM iSPI Performance for Metrics\)" on page 865](#)

Generate Interface Disabled Incidents

By default, NNMi *does not generate* an incident for interfaces with **Administrative Status** set to **Down**. If you want NNMi to generate incidents for these disabled interfaces, use the following procedures.



To enable the Interface Disabled Management Event incident configuration:

1. Navigate to the **Incidents** folder.
 - a. In the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **Management Event Configurations**.
3. Double-click the row that represents the Interface Disabled configuration.
4. Click Enable ☒.

Generate Card Disabled Incidents

By default, NNMi *does not generate* an incident for cards with **Administrative Status** set to **Down**. If you want NNMi to generate incidents for these disabled cards, use the following procedures.

To enable the Card Disabled Management Event incident configuration:



1. Navigate to the Incidents folder.
 - a. In the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **Management Event Configurations**.
3. Double-click the row that represents the Card Disabled configuration.
4. Click Enable .

Generate Card Undetermined State Incidents

By default, NNMi *does not generate* an incident for cards that have an undetermined State. (See [Card Undetermined State](#) for more information about these incidents.)

If you want NNMi to generate incidents for these cards, use the following procedures.

To enable the Card Undetermined State Management Event incident configuration:


1. Navigate to the **Incidents** folder.
 - a. In the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **Management Event Configurations**.
3. Double-click the row that represents the Card Undetermined State configuration.
4. Click Enable .

Generate Node Deleted Incidents

By default, NNMi *does not generate* an incident for nodes that have been deleted from the NNMi topology.

If you want NNMi to generate incidents for these nodes, use the following procedures.

To enable the Node Deleted Management Event incident configuration:


1. Navigate to the **Incidents** folder.
 - a. In the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **Management Event Configurations**.
3. Double-click the row that represents the Node Deleted configuration.
4. Click Enable ☒.

Generate Performance Threshold Incidents (NNM iSPI Performance for Metrics)

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

NNMi can generate incidents related to performance thresholds. NNMi does not generate threshold incidents until the NNMi administrator configures the performance thresholds and enables the performance incidents.

To configure NNMi to generate performance threshold incidents:



1. *Prerequisite.* Enable performance polling and configure the performance thresholds. See ["Configure Threshold Monitoring for Interface Groups" on page 426](#) for more information.
2. Navigate to the **Incidents** folder:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
3. Select **Management Event Configurations**.

Tip: NNM iSPI Performance for Metrics threshold incidents are available in Management Event Configurations (not other categories of incident configurations).

4. Double-click the row representing the threshold incident configuration.

For the list of possible values, see [Management Event Configurations Provided by NNMi](#).

5. Enable the threshold incident:

- a. **Management Event Configuration** form
 - b. **Basics** group
 - c. Select **Enable** 
6. Click  **Save and Close** to save your changes.
 7. Repeat steps 4 through 7 for each configuration you want to use.

The NNM iSPI Performance for Metrics now records the number and frequency of threshold related incidents (exceptions). The NNM iSPI Performance for Metrics provides reports to help you establish the root cause of network problems. Access the NNM iSPI Performance for Metrics reports with **Actions** → **HP NNM iSPI Performance** → **Reporting - Report Menu** in the incident, node, or interface views and forms. (See [NNM NNM iSPI Performance for Metrics Actions](#).)

Using the Command Line to Manage Incident Configurations

You can use the [nnmincidentcfgload.ovpl](#) script to generate a file of your Incident Configurations and then load them into the NNMi database.

Incident Configurations are exported in a non-xml format. You can edit the file using the format descriptions provided in [nnmincidentcfg.format](#) and in the following directory (see ["About Environment Variables" on page 86](#) for more information):

Windows:

```
%NnmInstalLDir%/examples/nnm/incidentcfg
```

Linux:

```
$NnmInstalLDir/examples/nnm/incidentcfg
```

See also:

- ["Generate a File of Your Incident Configurations" below](#)
- ["Load Incident Configurations Using the Command Line" on page 869](#)
- ["About Environment Variables" on page 86](#)

Generate a File of Your Incident Configurations

Tip: If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

The NNMi `nnmincidentcfgdump.ovpl` script provides a way for you to create or update an Incident Configuration to subsequently load into the NNMi database using the `nnmincidentcfgload.ovpl` script. The file is generated in a non-xml format.

You can edit the file using the format descriptions provided in the following directory (see ["About Environment Variables" on page 86](#)):

Windows

```
%NmInstallDir%/examples/nnm/incidentcfg
```

Linux

```
$NmInstallDir/examples/nnm/incidentcfg
```

To generate a file of your Incident Configurations, use the following example syntax:

```
nnmincidentcfgdump.ovpl -dump <file_name> -u <NNMadminUsername> -p  
<NNMadminPassword>
```

Note: See `nnmincidentcfgdump.ovpl` for more information, including a complete list of the valid script arguments.

nnmincidentcfg.ovpl Arguments

Argument	Description
-dump <file_name>	<p>Used to create a file of your Incident Configurations.</p> <div> <p>Tip: Incident Configurations can be loaded into the NNMi database using the <code>nnmincidentcfgload.ovpl</code> script.</p> <p>To create an Incident Configuration file without using existing Incident Configurations, start with one of the template files provided in the following directory (see "About Environment Variables" on page 86):</p> <p>Windows</p> <pre>%NmInstallDir%/examples/nnm/incidentcfg</pre> <p>Linux</p> <pre>\$NmInstallDir/examples/nnm/incidentcfg</pre> </div>
-uuid	<p><i>Recommended.</i> Specifies the Universally Unique Object Identifier (UUID) for each configuration entry.</p> <div> <p>Note: Configuration files that do not contain the UUID value take longer to load. See <code>nnmincidentcfgload.ovpl</code> for more information.</p> </div>
-authorKey <author or authors>	<p><i>Optional.</i> Generates an Incident Configuration file that contains the settings created by one or more authors.</p>

nnmincidentcfg.ovpl Arguments, continued

Argument	Description
	<p>Note the following:</p> <ul style="list-style-type: none"> You can include one or more <i><author></i> values. If you do not specify any configuration authors, NNMi includes all of the incident configurations. You cannot use this argument with the <i>-name</i> argument. <p>To find a Unique Key for a particular author using the command line, execute:</p> <pre>nnmincidentcfgdump.ovpl -ListAuthors</pre> <p>To find the Unique Key for a particular Author in the NNMi console:</p> <ol style="list-style-type: none"> Open one of the Incident Configuration workspace in the NNMi console. Select an object created by the Author of interest. Display the Author form, and copy the value of the Unique Key attribute.
-u	<i>Optional.</i> The NNMi user name. This User Account must be assigned to the NNMi Administrators User Group.
-p	<i>Optional.</i> The password associated with the NNMi user name.
-name <name or names>	<p><i>Optional.</i> Specifies the name of each configuration that should be included in the configuration file you are creating.</p> <p>Note the following:</p> <ul style="list-style-type: none"> If you do not specify any configuration Names, NNM includes all of the configurations. You cannot use this argument with the <i>-authorKey</i> argument.
-type <config_ type>	<p><i>Optional.</i> Specifies the type of configurations you want to include. Valid configuration types include:</p> <ul style="list-style-type: none"> MgmtEventConfig PairwiseConfig SnmpTrapConfig SyslogMessageConfig
-mib <module_	Specifies the MIB module or modules that must be contained in an incident configuration to be included in the formatted configuration file. NNMi includes any

nnmincidentcfg.ovpl Arguments, continued

Argument	Description
<i>name</i> > or < <i>module_</i> <i>names</i> >	SNMP Trap Configurations that contain the specified MIB module. Tip: MIB modules are loaded from MIB files using the nnmloadmib.ovpl script. To see what MIB modules are loaded, use the nnmloadmib.ovpl script with the -list option.
-oid < <i>oid_</i> <i>pattern</i> or <i>oid_</i> <i>patterns</i> >	Specifies the Object Identifier (OID) pattern or patterns that must be contained in an incident configuration to be included in the formatted configuration file. NNMi includes any SNMP Trap Configurations that match a specified OID pattern. Each OID pattern can contain one wildcard character (*). See nnmincidentcfgload.ovpl for more information.

Load Incident Configurations Using the Command Line

Tip: If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

The NNMi [nnmincidentcfgload.ovpl](#) script provides a way for you to load Incident Configurations into the NNMi database from a formatted configuration file.

Tip: Use the [nnmincidentcfgdump.ovpl](#) script to create a configuration file of existing Incident Configurations in a non-xml format. You can then edit this file if desired before loading them into the NNMi database.

See the following directory for the required format (see ["About Environment Variables" on page 86](#)):

Windows

%NmInstallDir%/examples/nm/incidentcfg

Linux

\$NmInstallDir/examples/nm/incidentcfg

To validate an Incident Configuration file before it is loaded into the NNMi database, use the following example syntax:

```
nnmincidentcfgload.ovpl -validate <file_name> -u <NNMiadminUsername> -p  
<NNMiadminPassword>
```

To load Incident Configurations, use the following example syntax:

```
nnmincidentcfgload.ovpl -load <file_name> -u <NNMiadminUsername> -p  
<NNMiadminPassword>
```

Note the following:

- NNMi updates all configurations that have matching names or other matching key identifiers.

Caution: NNMi also overwrites the values of any codes associated with these configurations (for example, incident Family).

- NNMi adds all incident configurations with key identifiers that do not exist in the NNMi database.
- NNMi does not change existing incident configurations with key identifiers that do not match any in the exported file.
- NNMi resolves Universally Unique Object Identifiers (UUIDs) if they are not provided in the configuration file.
- If NNMi is unable to resolve a UUID, a UUID is created.

See [nnmincidentcfgload.ovpl](#) for more information, including a complete list of the valid script arguments.

nnmincidentcfg.ovpl Arguments

Argument	Description
-load <file_name>	<p>Use to load the Incident Configurations generated using either the nnmincidentcfgdump.ovpl script or created from a template file provided by NNMi.</p> <p>To create an Incident Configuration file without using existing Incident Configurations, start with one of the template files and required formats provided in the following directory (see "About Environment Variables" on page 86):</p> <p>Windows</p> <p>%NnmInstalLDir%/examples/nnm/incidentcfg</p> <p>Linux</p> <p>\$NnmInstalLDir/examples/nnm/incidentcfg</p>
-validate <file_name>	<p><i>Optional.</i> Use to validate the contents of the Incident Configuration file generated using nnmincidentcfgdump.ovpl.</p>
- expression < expression >	<p>Specifies the filter expression you want to validate.</p>

nnmincidentcfg.ovpl Arguments, continued

Argument	Description
-u	<i>Optional.</i> The NNMi user name. This User Account must be assigned to the NNMi Administrators User Group.
-p	<i>Optional.</i> The password associated with the NNMi user name.

Manage Incoming SNMP Traps

NNMi provides several tools that enable you to manage the SNMP traps that are sent through the Event Pipeline and are configured to appear as incidents in the NNMi console. For more information about NNMi's Event Pipeline, see ["About the Event Pipeline" on page 685](#).

NNMi uses the following criteria to determine whether it *receives or discards incoming* traps:

- If the *incoming* trap's Source Node object or Source Object (such as card or interface) has not yet been discovered, NNMi discards the trap by default.

Note: The NNMi administrator can change this behavior using the **Trap Handling Settings** when configuring incidents. See ["Handle Unresolved Incoming Traps" on page 878](#) for additional information. See also ["Configure Network Devices to Send SNMP Notifications to NNMi" on the next page](#).

- If the Source Node or Source Object of the *incoming* trap has been discovered by NNMi using SNMPv3, NNMi accepts *incoming* traps from SNMPv3, SNMPv2c, or SNMPv1. See [SNMPv3 Settings Form](#) for information about configuring SNMPv3 settings.
- If the Source Node or Source Object of the *incoming* trap has been discovered by NNMi using SNMPv2c or SNMPv1, NNMi discards *incoming* traps from SNMPv3.
- NNMi discards traps that have no incident configuration or with an incident configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap. See ["Configure SNMP Trap Incidents" on page 886](#).
- If either the Source Node or Source Object has *Management Mode* set to **Not Managed** or **Out of Service** in the NNMi database, NNMi always discards the incoming trap. See [Understand the Effects of Setting the Management Mode to Not Managed or Out of Service](#).

NNMi provides the Management Mode workspace so that you can quickly view lists of all nodes, interfaces, IP addresses, chassis, cards, node sensors, and physical sensors that NNMi is not currently discovering or monitoring. For information about these views:

- NNMi discards most incoming traps from network objects that are not monitored. For example, you can configure NNMi to exclude specified interfaces from being monitored. See ["Monitoring Network Health" on page 378](#) for more information.

Note the following:

- If you want the NNMi management server to *forward* traps to other machines in your network environment, see the following topics for additional information and configuration steps:
 - SNMPv2c traps — ["Configure Trap Forwarding" on page 1407](#)
 - SNMPv3 traps — ["Configure NNMi SNMPv3 Security Settings for Trap Forwarding and Inform-Requests" on page 1407](#)
- NNMi administrators can configure thresholds for trap volume within your network. Choices include count-based or time-based thresholds for total volume or for each trap OID. Traps can also be blocked. See the following Reference Pages:
 - [nnmtrapconfig.ovpl](#)
 - [hosted-object-trapstorm.conf](#)

When managing your SNMP Traps consider performing the following tasks:

- ["Configure Network Devices to Send SNMP Notifications to NNMi" below](#)
- ["Load SNMP Trap Incident Configurations" on the next page](#)
- ["Control which Incoming Traps Are Visible in Incident Views" on page 877](#)
- ["Handle Unresolved Incoming Traps" on page 878](#)
- ["Analyze Trap Information" on page 879](#)

Related Topics:

["Configure Trap Forwarding" on page 1407](#)

Configure Network Devices to Send SNMP Notifications to NNMi

An SNMP notification is a message sent from an SNMP agent (SNMPv1, SNMPv2c, or SNMPv3) on a network device to notify a network management system of an event on the network device. For example, an error occurred on the network device and its SNMP agent sent a notification. The notification might be either of the following:

- An acknowledged inform (SNMP InformRequest): An inform is an acknowledged notification sent from one SNMP agent to another with the expectation of a reply from the recipient. If no reply is received, the inform message is resent.
- An unacknowledged trap: A trap is a notification sent from one SNMP agent to another without any expectation of a reply.

Configure SNMP agents in your network environment to send traps to the NNMi management server. Sometimes SNMP agents are configured with a recheck interval, so the trap might be sent to the NNMi management server over and over again until the problem is corrected.

The NNMi Causal Engine analyzes these traps and gathers additional information to determine the root cause. It also provides useful troubleshooting information each time an important SNMP notification is received, including the following information:

- The name or address of the node from which the notification came (Source Node)
- The notification identification (SNMP Object ID)
- Notification-specific variables (varbinds)

When configuring the SNMP agent for each network device, configure the trap-forwarding list (or trap-destination list) to include the NNMi management server's fully-qualified hostname or IP address. Refer to documentation for the SNMP agent for information about how to do this. If the NNMi management server is included on the trap-forwarding list, NNMi receives notice when something goes wrong (even if the device does not show up on your NNMi maps).

Note: For an SNMP notification to be processed by NNMi, it must be configured using the NNMi Incidents folder workspace. Many common SNMP notifications are configured in NNMi by default. See ["Configure SNMP Trap Incidents" on page 886](#) and ["SNMP Trap Incident Configurations Provided by NNMi" on page 695](#) for more information.

Load SNMP Trap Incident Configurations

NNMi enables you to automatically create or update an Incident Configuration for an SNMP trap using a [MIB file](#)¹. To load a trap definition using a MIB file, you can use either the command line or NNMi console:

- ["Load SNMP Trap Incident Configurations from the Command Line" on the next page](#)
- ["Load SNMP Trap Incident Configurations using the Console" on page 876](#)

When loading MIBs to be used for SNMP Trap Incident configurations, NNMi stores TRAP-TYPE or NOTIFICATION-TYPE Macro Definition information from the MIB into the NNMi database. The table below lists field names included in the Macro Definition information.

To see a list of all available Traps provided by MIB Files currently loaded, see Configuration workspace → MIBs → MIB Notifications view.

To see a list of Traps provided by one MIB File, sort the MIB Notifications view by clicking the MIB column heading, or open any [MIB Form](#) and navigate to the [Notifications Tab](#).

¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

Note: If any of the individual field lengths in a TRAP - TYPE or NOTIFICATION - TYPE Macro Definition for a MIB exceeds the limitations for storing this information in the NNMi database, the MIB will not load into NNMi. The most commonly encountered field limitations are listed in the following table.

TRAP-TYPE or NOTIFICATION-TYPE Macro Definition Maximum Field Lengths

Field Name	Maximum Length	Multi-Entry
NAME	80	NO
DESCRIPTION	4000	NO
--#TYPE	255	NO
--#SUMMARY	2000	YES
--#ARGUMENTS	255	NO
--#SEVERITY	255	NO
--#GENERIC	40	NO
--#CATEGORY	80	NO
--#SOURCE_ID	40	NO
--#TIMEINDEX	40	NO
--#HELP	80	NO
--#HELPTAG	40	NO
--#STATE	80	NO

Load SNMP Trap Incident Configurations from the Command Line

Tip: If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

The NNMi [nnmincidentcfg.ovpl](#) script provides a way for you to create or update an Incident Configuration for an SNMP trap using a MIB module that was previously loaded into the NNMi database using the [nnmloadmib.ovpl](#) script with the -load option. To load a MIB module you can use the following syntax:

```
nnmincidentcfg.ovpl -loadTraps <mib_module_name> -disableAllTraps true|false -u  
<NNMiadminUsername> -p <NNMiadminPassword>
```

Note: See [nnmincidentcfg.ovpl](#) for more information, including a complete list of the valid script arguments.

nnmincidentcfg.ovpl Arguments

Argument	Description
-loadTraps <mib_module_name>	<p>Used to load the traps from the specified MIB module you want to use to create or update the incident configuration for an SNMP trap.</p> <p>Tip: MIB modules are loaded from MIB files using the nnmloadmib.ovpl script. To see what MIB modules are loaded, use the nnmloadmib.ovpl script with the <code>-list</code> option.</p> <p>NNMi uses information from the trap definitions (TRAP-TYPES macro) or notification (NOTIFICATION-TYPES macro) in the MIB module for the required incident configuration.</p>
-disableAllTraps	<p>Specifies whether all trap definitions specified using <code>-loadTraps <mib_module_name></code> should be loaded as disabled.</p> <p>Note: The default value is <code>false</code>. This means that by default all trap definitions specified in <code><mib_module_name></code> are loaded as enabled. Set this parameter to <code>true</code> to disable the trap definitions that you are loading.</p>
-u	<p>The NNMi user name. This User Account must be assigned to the NNMi Administrators User Group.</p> <p>Note: The user name might be a Principal object stored in the NNMi database or might be from Lightweight Directory Access Protocol (LDAP) or X.509 Certificates such as Public Key Infrastructure (PKI) user authentication in your environment. See "Choose a Mode for NNMi Access" on page 570.</p>
-p	<p>The password associated with the NNMi account.</p> <p>If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the nnmsetcmduserpw.ovpl command to specify the valid user name and password (instead of <code>-u</code> and <code>-p</code>). The credentials set using the <code>nnmsetcmduserpw.ovpl</code> command are valid for command execution by the same user. See "Set Up Command Line Access to NNMi" on page 653 for more information.</p>

For example, to load the MIB module CISCO-VTP-MIB, you might enter the following:

```
nnmincidentcfg.ovpl -loadTraps "CISCO-VTP-MIB"
```

If the incident is already configured, NNMi performs an update based on the MIB file information. If the incident is not configured, NNMi creates a new incident configuration entry for the SNMP trap. See ["Configure SNMP Trap Incidents" on page 886](#) for information about changing an SNMP trap configuration.

Load SNMP Trap Incident Configurations using the Console

NNMi enables you to load one or more SNMP Trap Incident Configurations from a MIB file using the NNMi console.

Tip: You can display each [MIB file](#)¹ and quickly determine the SNMP Traps provided by that MIB file (if any). See the Notifications tab on any [MIB Form](#).

To load an SNMP Trap Incident Configuration from the NNMi console:

1. Do one of the following:
 - a. Navigate to the MIB view or form. For example, Select **Configuration** → **MIBs** → **Loaded MIBs**.
 - b. Navigate to the MIB Variable view or form. For example, Select **Inventory** → **MIB Variables**.

2. Select **Tools** → **Load/Unload MIB...**

NNMi displays the following information:

- Unloaded MIBs (user provided) that are stored on the NNMi management server and that were provided by the NNMi administrator.
 - Unloaded MIBs (NNMi provided) that NNMi has stored on the NNMi management server during installation.
 - Loaded MIBs that are loaded in the NNMi database.
3. Navigate to the Unloaded MIB view of interest. For example, **Unloaded MIBs (User Provided)**.
 4. In the MIB column, find the MIB that contains the trap incidents you want to load. For example, **FLOWMGREST-MIB**.

Note: The MIB must support the TRAP-TYPE or NOTIFICATION-TYPE macro.

¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

5. To view the MIB before loading, in the Actions column, click **Display**.

NNMi displays the MIB file contents.

6. To load the MIB, in the Actions column, click **Load Incident Configuration**.

NNMi displays the progress of each trap configuration that is loaded, including the following:

- The name and location of the MIB file
- The number of trap incident configurations
- The name and numeric object identification (OID) of each trap configuration
- Whether the trap incident configurations successfully loaded
- Instructions for loading and listing MIB files.

To upload a local MIB file so that it is stored on the NNMi management server and available for loading, see ["Upload MIB Files for NNMi's Use" on page 1491](#).

Control which Incoming Traps Are Visible in Incident Views

You can configure devices in your network environment to send traps to the NNMi management server. To configure how NNMi handles those traps, use the incident configurations provided by NNMi, create your own, or both. See ["Configure SNMP Trap Incidents" on page 886](#) for information about how to configure SNMP traps as incidents. See ["SNMP Trap Incident Configurations Provided by NNMi" on page 695](#) for information about the incident configurations provided by NNMi.

Note:

- To establish this communication flow, the SNMP agent (SNMPv1, SNMPv2c, or SNMPv3) must be intentionally configured by the device administrator to send SNMP traps to your NNMi management server.
- Use the `nnmtrapconfig.ovpl -dumpBlockList` command to view information about the current incident configuration, including SNMP traps that were not passed into the incident pipeline because of non-existent or disabled incident configurations. See [nnmtrapconfig.ovpl](#) for more information.

To determine which SNMP trap incident configurations are Enabled in NNMi:

1. Navigate to the **SNMP Trap Incident Configurations** view:

- a. Expand the **Incidents** folder.
- b. Select **SNMP Trap Incident Configurations**.


2. Click to sort the **Enabled** column.

Each SNMP trap Incident Configuration that is Enabled contains a check mark ✓.

See ["SNMP Trap Incident Configurations Provided by NNMi" on page 695](#) for more information.

Tip: You can configure NNMi to ignore SNMP traps for objects that are not discovered as part of the NNMi topology. See ["Handle Unresolved Incoming Traps" below](#) for more information.

To enable or disable an SNMP trap configuration:

1. Navigate to the Incidents folder.
 - a. In the Workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **SNMP Trap Configurations**.
3. Double-click the row representing the configuration you want to edit.
4. To enable the incident configuration, click Enable ☒.
5. To disable the incident configuration, clear Enable ☐.

Related Topics

["Handle Unresolved Incoming Traps" below](#)

["Manage the Number of Incoming Incidents" on page 739](#)


Handle Unresolved Incoming Traps

Your network environment might be configured to forward SNMP traps to the NNMi management server.

If the trap's source node or source object *cannot be matched with any object in the NNMi database*, that trap is considered to be *unresolved*. Follow the steps in this procedure to specify whether NNMi retains or discards these traps. For example, if you configure NNMi to discover only devices you specifically list as seeds, you can decide if you want NNMi to process or ignore traps from any other devices.

See ["Manage Incoming SNMP Traps" on page 871](#) for more information about the additional criteria NNMi uses to determine when to receive or discard traps.

To control how NNMi handles unresolved incoming SNMP Traps:

1. Navigate to the **Incident Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Incident Configuration....**
2. Navigate to the **NNMi Trap Handling Settings**:
 - If you want NNMi to place unresolved SNMP traps into the NNMi database, clear the **Discard Unresolved SNMP Traps** ☐ check box.

Unresolved traps then appear in incident views, but have missing information. For example, the incident might appear as follows:

 - NNMi displays the Source Node as an IP address.
 - NNMi displays the Source Object as **None**.
 - If you want NNMi to ignore any unresolved traps, select the **Discard Unresolved SNMP Traps** ☒ check box.
3. Select **Save and Close** to save your changes.

Tip: To manage the number of SNMP Traps displayed as incidents, see ["Control which Incoming Traps Are Visible in Incident Views" on page 877](#)

Analyze Trap Information

NNMi measures the rate of incoming SNMP traps regardless of Incident Configuration, including the following:

- Traps from each Node.
- Traps for each SNMP Object Identifier (OID).

NNMi monitors the incoming SNMP traffic flow to determine whether the number of traps received within a certain time period exceeds any set threshold. If a threshold is exceeded, NNMi blocks processing of additional traps until the number of traps is below the threshold set for each time period.

Note: The NNMi administrator configures thresholds for trap volume within your network. Choices include count-based or time-based thresholds for total volume or for each trap OID. You can also block traps. See the following Reference Pages:

- [nnmtrapconfig.ovpl](#)
- [hosted-object-trapstorm.conf](#)

When analyzing traps, NNMi looks at both the most common traps as well as the most common Source Nodes from which the traps are received. NNMi logs this SNMP trap analytics data to the `trapanalytics.0.0.log` file.

(*NNMi SPI NET*) If HP Network Node Manager iSPI Network Engineering Toolset Software is available in your network environment, you can obtain reports about incoming SNMP traps according to the criteria described in the [Trap Analytics Reports](#) table.

Note the following:

- The time interval and number of Nodes or SNMP OIDs included in the reports and Line Graphs is based on the numbers configured using the [nnmtrapconfig.ovpl](#) script. By default, NNMi uses 5 minutes as the time interval and 10 as the top number of Nodes and SNMP OIDs for which information is computed.
- NNMi identifies each trap using its SNMP Object Identifier (OID) number.
- NNMi enables you to open the following graphs, reports, and forms from a Trap Analytics report:
 - Line Graph of the trap rate for all of the Nodes or SNMP OIDs displayed in the report.
 - Line Graph of the trap rate for a selected Node or SNMP OID.
 - SNMP Trap Incident Configuration form, if any, for an SNMP OID.
 - Source IP Address and Node form for a Node.

Note: The Source Node must be stored in the NNMi database for the links to appear.

- MIB Variable form, if any, for the selected SNMP OID.

Note: The MIB Variable must be stored in the NNMi database. To add a MIB Variable by loading a trap, see "[Load SNMP Trap Incident Configurations](#)" on page 873

- When you access a Line Graph from a report, the Line Graph displays an updated real-time data using the Nodes or SNMP OIDs included in the report. Because the trap rate is constantly changing, the data in the Line Graph will not match the historical trap numbers displayed in the report.
- If an SNMP Trap Incident Configuration exists for a trap, NNMi displays the name of the SNMP Trap Incident Configuration as well as whether the SNMP Trap Incident Configuration is disabled. This feature is useful when you want to make changes to the incident configuration. For example, you might want to enable or disable the incident configuration.

- NNMi discards traps that have no incident configuration or with an incident configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap. See ["Configure SNMP Trap Incidents" on page 886](#).

See the [Trap Analytics Reports](#) table for more information about the links available from each report.

To access the Trap Analytics reports:

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

1. Select **Tools** → **Trap Analytics**.
2. Select the graph or report of interest. from the **Trap Analytics** submenu.

NNMi displays the selected report (see [Trap Analytics Reports](#)).

(NNM iSPI NET) Trap Analytics Reports

Report	Description	Links Available from the Report
Recent Top Trap Rate (by Node)	Table view of the Nodes that are most frequently generating traps during the specified time period.	Line Graph of the Nodes that are most frequently generating traps. Recent Top Rate Traps Received (by OID) report Total Traps Received (by Node) Total Traps Received (by OID) Line Graph of the trap rate for the selected Node. Source Node form, if any, for the trap.
Recent	Table view of the traps that are most frequently generated during	Line Graph of the

(NNM iSPI NET) Trap Analytics Reports, continued

Report	Description	Links Available from the Report
Top Trap Rate (by OID)	the specified time period.	<p>traps that are most frequently generated.</p> <p>Recent Top Rate Traps Received (by Node) report</p> <p>Total Traps Received (by Node)</p> <p>Total Traps Received (by OID)</p> <p>Line Graph of the trap rate for the selected SNMP OID.</p> <p>Incident Configuration form, if any, for the selected SNMP OID.</p> <p>MIB variable form, if any, for the MIB variable that is associated with the SNMP OID.</p>
Total Traps Received (by Node)	Table view of the trap totals since NNMi was last started. This report is organized by traps per Node.	<p>Line Graph of the total number of traps received per Node since NNMi was last started.</p> <p>Total Traps Received (by OID) report</p> <p>Recent Top Trap Rate (by Node)</p> <p>Recent Top Trap</p>

(NNM iSPI NET) Trap Analytics Reports, continued

Report	Description	Links Available from the Report
		<p>Rate (by OID)</p> <p>Line Graph of a selected Node's total traps in real time.</p> <p>Source Node form, if any, for the selected trap.</p>
Total Traps Received (by OID)	Table view of the trap totals since NNMi was last started. This report is organized by traps per SNMP OIDs.	<p>Line Graph of the total number of traps received since NNMi was last started.</p> <p>Total Traps Received (by Node) report</p> <p>Recent Top Trap Rate (by Node)</p> <p>Recent Top Trap Rate (by OID)</p> <p>Line Graph of the selected SNMP OID's total traps in real time.</p> <p>Incident Configuration form, if any, for the selected SNMP OID.</p> <p>MIB variable form, if any, for the MIB variable that is associated with the SNMP OID.</p>
Trap Analysis Log	<p>Log file listing trap information organized by the following criteria:</p> <ul style="list-style-type: none"> Trap rate in number of traps per second 	

(NNMi iSPI NET) Trap Analytics Reports, continued

Report	Description	Links Available from the Report
	<ul style="list-style-type: none">• The top 10 addresses that are generating traps• The top 10 traps that are being generated <p>This information is recomputed every 5 minutes as configured in nnmtrapconfig.ovpl. Scroll to the bottom to see the latest entry.</p> <div>Note: The NNMi administrator can configure threshold values using the nnmtrapconfig.ovpl script.</div> <p>You can also use the <code>nnmtrapdump.ovpl</code> command to extract the data in which you are most interested from the <code>trapanalytics.0.0.log</code> file. See the nnmtrapdump.ovpl Reference Page for more information (Help → Documentation Library → Reference Pages, in the <i>User Commands</i> category).</p>	

Control the Times within which NNMi Causal Engine Accepts SNMP Traps

When large areas of a network are unavailable at regular and predictable hours, NNMi enables you to moderate Causal Engine analysis load by inhibiting the delivery of traps to the Causal Engine. To inhibit the delivery of traps, as an NNMi administrator, you configure times that the NNMi Causal Engine stops accepting traps from the event system.

Note: This feature does not interfere with traps delivered to the NNMi console.

Traps that are delivered to the Causal Engine are used to trigger State Poller to poll a node sooner than the schedule dictated by the State Poller Polling Policy. When you inhibit the delivery of traps, NNMi must wait until the scheduled polling interval before obtaining updated information from State Poller. In all cases, the NNMi Causal Engine reaches the same conclusion with or without traps by using state flows from the NNMi State Poller.

See the "Maintaining NNMi" chapter in the HP Network Node Manager i Software Deployment Reference for more information.

Configure Incident Logging

NNMi enables you to configure incident logging so that incoming incident information is written to the `incident.csv` file. This feature is useful when you want to track and archive your incident history.

Tip: You can also use the [nnmtrimincidents.ovpl](#) command to configure incident logging.

The `incident.csv` is located in the following directories (see ["About Environment Variables" on page 86](#)):



Windows

`%NnmDataDir%\log\nnm`

Linux

`$NnmDataDir/log/nnm`

To configure incident logging:

1. Navigate to the **Incidents** folder.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **Incident Configuration**.
3. Navigate to the **Incident Logging Configuration** tab.
4. Provide the required information (see [General Configuration](#) and [Log File Configuration](#)).
5. Click  **Save and Close** to save your changes.

If **Enable Incident Logging** ☒, the next time an incident arrives, NNMi logs the information to the `incident.csv` file.

Note: See [nnmtrimincidents.ovpl](#) for a description of the incident information that is written to the `incident.csv` file.

General Configuration

Attribute	Description
Enable Incident Logging	If enabled <input checked="" type="checkbox"/> , NNMi logs incoming incident information to the <code>incident.csv</code> file. If disabled <input type="checkbox"/> , incident information is not logged.

Log File Configuration

Attribute	Description
Enable Compression	If enabled <input checked="" type="checkbox"/> , NNMi saves the <code>incident.csv</code> file in compressed (.gz) format. If disabled <input type="checkbox"/> , incident information is not saved in the compressed (.gz) format.
Maximum File Size (MB)	Specify the maximum amount of disk space in megabyte that NNMi should use for the <code>incident.csv</code> file. The default value is 128 megabytes.

Log File Configuration, continued

Attribute	Description
	Note: After the maximum file size is reached, the log file is renamed to <code>incident.csv.<gz>.old</code> and a new <code>incident.csv</code> file is created. If an <code>incident.csv.<gz>.old</code> exists, it is overwritten.
Logging Interval (ms)	<p>Specify the time interval in which NNMi should log incident information. The default value is 6 seconds (6000 milliseconds).</p> <p>Tip: To optimize performance, use a less frequent Logging Interval with a larger Maximum Number of Incidents.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The minimum value is 0.01 second (10 milliseconds).• The maximum value is 1 minute (60000 milliseconds).
Maximum Number of Incidents per Logging Interval	<p>Specify the number of incidents to be logged to the <code>incident.csv</code> file per the Logging Interval specified. The default value is 1024.</p> <p>Tip: To optimize performance, use a less frequent Logging Interval with a larger Maximum Number of Incidents.</p> <p>The minimum value is 32.</p>

Configure SNMP Trap Incidents

Configure incidents that originate from an SNMP trap.

Create one Trap Incident configuration for each trap (separate configurations for an SNMPv2 trap number and a similar SNMPv1 trap number). For example:





- .1.3.6.1.4.1.11.15.1.4.1 (SiteScopeAlertEventv2)
- .1.3.6.1.4.1.11.15.1.4.0.1 (SiteScopeAlertEventv1)

NNMi discards traps that have no Incident Configuration or with an Incident Configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap.

Tip: You can manage the number of SNMP Traps using either of the following methods: 1) ["Manage the Number of Incoming Incidents" on page 739](#) and 2) ["Handle Unresolved Incoming Traps" on page 878](#).

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure incidents originating from SNMP traps:

1. Navigate to the **Incidents** folder.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **SNMP Trap Configurations** .
3. Do one of the following:
 - To create an SNMP trap configuration, click the  New icon, and continue.
 - To edit an SNMP trap configuration, double-click the row representing the configuration you want to edit, and continue.
 - To delete an SNMP trap configuration, select a row, click the  Delete icon.
4. In the [SNMP Traps form](#), provide the required information.
5. Click  **Save and Close** to save your changes.

The next time that a trap of this type arrives, NNMi creates an associated incident to display in the appropriate incident views.


SNMP Trap Configuration Form

Create one Trap Incident configuration for each trap (separate configurations for an SNMPv2 trap number and a similar SNMPv1 trap number). For example:

- .1.3.6.1.4.1.11.15.1.4.1 (SiteScopeAlertEventv2)
- .1.3.6.1.4.1.11.15.1.4.0.1 (SiteScopeAlertEventv1)



Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure incidents originating from SNMP traps:


1. Navigate to the **Incidents** folder:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Select **SNMP Trap Configurations** .

3. Do one of the following:

Note: If you want to add or edit an SNMP trap configuration, verify that **Enabled**  is selected.

- To add an SNMP trap configuration, click the  New icon, and continue.
- To edit an SNMP trap configuration, double-click the row representing the configuration you want to edit, and continue.
- To delete an SNMP trap configuration, select a row, and click the  Delete icon.

4. Make your configuration choices (see [table](#)).

5. Click  **Save and Close** to save your changes and return to the previous form.

Tasks for SNMP Trap Configuration

Task	How
"Configure Basic Settings for an SNMP Trap Incident" on the next page	Use the Basics pane of the SNMP Trap Configuration form.
"Configure Interface Settings for an SNMP Trap Incident" on page 913	Use the Interface Settings tab of the SNMP Trap Configuration form.
"Configure Node Settings for an SNMP Trap Incident" on page 957	Use the Node Settings tab of the SNMP Trap Configuration form.
"Configure Suppression Settings for an SNMP Trap Incident" on page 1004	Use the Suppression tab of the SNMP Trap Configuration form.
"Configure Enrichment Settings for an SNMP Trap Incident" on page 1013	Use the Enrichment tab of the SNMP Trap Configuration form.
"Configure Dampening Settings for an SNMP Trap Incident" on page 1018	Use the Dampen tab of the SNMP Trap Configuration form.
"Configure Deduplication for an SNMP Trap Incident" on page 1029	Use the Deduplication tab of the SNMP Trap Configuration form.
"Configure Rate (Time Period and Count) for an SNMP Trap Incident" on page 1038	Use the Rate tab of the SNMP Trap Configuration form.
"Configure Actions for an SNMP Trap Incident" on page 1042	Use the Actions tab of the SNMP Trap Configuration form.
"Configure Forward to Global Manager Settings for an SNMP Trap Incident (NMMi Advanced)" on page 1059	Use the Forward to Global Managers tab of the SNMP Trap Configuration form.

Configure Basic Settings for an SNMP Trap Incident




The Basics settings for an SNMP Trap Incident specifies general information for an incident configuration, including the name, severity, and message.


Note the following:

- NNMi discards traps that have no Incident Configuration or with an Incident Configuration set to Disabled. To ensure that NNMi retains all received Trap instances when your network environment includes SNMP agents using a variety of SNMPv1, SNMPv2c, and SNMPv3 protocol, you must configure two Incidents: one for the SNMPv1 version and one for the SNMPv2c/3 version of that trap.
- When configuring SNMP Trap incidents, if you are using SNMPv3 protocol:
 - You must also configure SNMPv3 communication using the Communication Configuration workspace. For more information,
 - If you configured SNMPv3 communication, use the **Actions** → **Configuration Settings** → **Communication Settings** to determine the SNMPv3 user name that NNMi will use for any node from which you want to receive SNMP Trap incidents. Make sure the node is configured with this user name when configuring SNMP trap incidents. See ["Troubleshooting Communication Settings" on page 187](#) for more information.
 - If you configured SNMPv1 or SNMPv2c communication, NNMi does not authenticate the community string for any node from which you want to receive SNMP Trap incidents.
- In the **Basics** group of the **SNMP Trap Configuration** form, verify that **Enable** ☒ is selected for each configuration you want to use.



For information about each SNMP Traps tab:

To configure Basic settings for an SNMP Trap incident:



1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.

2. Configure the required Basic settings (see [table](#)).
3. Click  **Save and Close** to save your changes.

Basics Attributes for SNMP Trap Configuration

Task	How
"Specify the Incident Configuration Name (SNMP Trap Incident)" on the next page	Use the Basics pane of the SNMP Trap Configuration form. Specify a name that helps you to identify the configuration for subsequent use.
"Specify the SNMP Object ID" on page 892	Use the Basics pane of the SNMP Trap Configuration form. NNMi supports SNMPv3, SNMPv2c and SNMPv1 formats.
Specify whether you want to enable this configuration.	In the Basics group of the SNMP Trap Configuration form, verify that Enable  is selected for each configuration you want to use.
"Display an SNMP Trap as a Root Cause Incident" on page 897	Use the Basics pane of the SNMP Trap Configuration form.
"Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898	Use the Basics pane of the SNMP Trap Configuration form. You can organize your incidents using Category and Family.
"Specify the Incident Severity (SNMP Trap Incident)" on page 903	Use the Basics pane of the SNMP Trap Configuration form. Possible Severity values include: Normal , Warning , Minor , Major , and Critical .
"Specify Your Incident Message Format (SNMP Trap Incident)" on page 904	Use the Basics pane of the SNMP Trap Configuration form. The message format determines the message to be displayed for the incident.
"Specify a Description for Your Incident Configuration (SNMP Trap Incident)" on page 912	Use the Basics pane of the SNMP Trap Configuration form. Provide a meaningful description.
Specify an Author for Your Incident Configuration (SNMP Trap Incident)	<p>Use the Basics pane of the SNMP Trap Configuration form to indicate who created or last modified the trap.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> </div> <ul style="list-style-type: none"> • Click  Lookup and select  Show

Basics Attributes for SNMP Trap Configuration, continued

Task	How
	<p>Analysis to display details about the currently selected Author.</p> <ul style="list-style-type: none">Click  Quick Find to access the list of existing Author values.Click  New to create an Author value.

After you complete the Basic Configuration for the SNMP trap, you can also choose to configure the information described in the following table.

Additional Incident Configurations

Task	How
"Configure Interface Settings for an SNMP Trap Incident" on page 913	Select the Interface Settings tab to specify an Interface Group to which you want your incident configuration to apply.
"Configure Node Settings for an SNMP Trap Incident" on page 957	Select the Node Settings tab to specify a Node Group to which you want your incident configuration to apply.
"Configure Suppression Settings for an SNMP Trap Incident" on page 1004	Select the Suppression tab to specify the criteria for discarding incidents that match the selected incident configuration.
"Configure Enrichment Settings for an SNMP Trap Incident" on page 1013	Select the Enrichment tab to specify enhancements for the selected incident configuration.
"Configure Dampening Settings for an SNMP Trap Incident" on page 1018	Select the Dampen tab to specify the time interval that must be met before the incident appears in an Incident view.
"Correlate Duplicate Incidents (Deduplication Configuration)" on page 745	Select the Deduplication tab to specify duplicate incidents that you want to be suppressed.
"Track Incident Frequency (Rate: Time Period and Count)" on page 746	Select the Rate tab to specify a rate for duplicate incidents. After the rate limit is reached, NNMi generates an Incident to notify you of the problem.
"Configure an Action for an Incident" on page 847	Select the Actions tab to specify actions that should occur automatically when an incident changes its Lifecycle State .

Specify the Incident Configuration Name (SNMP Trap Incident)

When providing the Name for an incident configuration, use the following guidelines:

Name

The name is used to identify the incident configuration and must be unique. Use a name that will help you to remember the purpose or kind of Management Event, SNMP Trap, or Syslog Message for which you are configuring this incident. Name is also used to identify your Pairwise configurations.

Specify the SNMP Object ID

When configuring incidents for an SNMP trap, you are asked to provide the SNMP Object ID values that you want to use to assist you in identifying the trap.

Note:

- The value you enter for an SNMP Object ID (OID) must be unique.
- When checking whether an SNMP Trap Incident Configuration exists, NNMi's TrapFilter uses only implicit matching when checking generic SNMPv1 traps OIDs. See ["About the Trap Service Stages" on page 684](#) for more information about TrapFilter.
- *SNMPv2c, SNMPv3, and Specific SNMPv1 traps only.* NNMi enables you to use a wildcard character (*) in the SNMP Object ID attribute to create an SNMP Trap Incident configuration for multiple OIDs. This feature enables you to use the same SNMP Trap Incident Configuration for similar traps. For example, you might have a device class for which you might want to capture a particular kind of trap as an SNMP Trap Incident and ignore the rest.

The SNMP Object IDs must be entered in a format that is recognized by NNMi. Select the type of SNMP trap you want to configure from the list below to learn about the required NNMi format.

- ["SNMP Object ID Format for SNMPv2c\SNMPv3 Traps" below](#)
- ["SNMP Object ID Format for SNMPv1 Generic Traps" on page 894](#)
- ["SNMP Object ID Format for a Specific SNMPv1 Trap" on page 895](#)

SNMPv1 generic traps are standard traps that are commonly used across vendors. The SNMPv1 enterprise specific traps are those traps that are generated by a particular vendor's device. The vendor is also known as the enterprise. Both include a vendor name as part of the set of information stored with each trap.

SNMP Object ID Format for SNMPv2c\SNMPv3 Traps

NNMi requires that all SNMP traps have an object identifier (SNMP Object ID).

To specify an SNMP trap object ID (OID), open the MIB definition file for the device of interest to look up the correct ID. The MIB file includes object identifiers for all of the traps that the configured SNMP agent (SNMPv1, SNMPv2c, or SNMPv3) generates for a particular device.

In the **SNMP Object ID** attribute of the **SNMP Trap Incident Configuration** form, enter the **SNMP Object ID** attribute value for the SNMP trap that you want to see in the console incident views.

Note: You can use a wildcard character (*) in the SNMP Object ID attribute to create an SNMP Trap Incident configuration for multiple OIDs. This feature enables you to use the same SNMP Trap Incident Configuration for similar traps. For example, you might have a device class for which you might want to capture a particular kind of trap as an SNMP Trap Incident and ignore the rest.

When using the wildcard (*) character in the SNMP Object ID (OID) attribute, note the following:

- The OID must be unique.
- Only one wildcard character is permitted within the SNMP OID attribute.
- The wildcard must appear at the end of an OID. For example .1.3.6.1.4.1.* is valid; however, .1.3.6.1.4.*.2 is NOT valid.
- NNMi permits wildcards only in OIDs beginning with .1.3.6.1.4 (private MIBs).
- The wildcard character is not valid for an SNMPv1 generic trap because these traps do not begin with .1.3.6.1.4.
- When checking whether an SNMP Trap Incident Configuration exists, NNMi's TrapFilter uses only implicit matching when checking generic SNMPv1 traps OIDs. See ["About the Trap Service Stages" on page 684](#) for more information about TrapFilter.
- NNMi matches the OID value using the longest match. Specific OID matches take precedence over an OID that is matched using the wildcard character. [Click here for an example:](#)

The following table provides an example of precedence between a specific OID and one that includes a wildcard. This example also illustrates how NNMi uses the longest match.

Example of Matching Incoming SNMP Traps Using Specific and Longest Match Criteria

SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria
.1.3.6.1.4.1.2.3	.1.3.6.1.4.1.2.3	Specific OID takes precedence over the wildcard OID configuration.
.1.3.6.1.4.1.*	.1.3.6.1.4.1.2	The wildcard OID takes precedence because it is the longest match.
.1.3.6.1.4.*	Using the specific OID and longest match	See above.

Example of Matching Incoming SNMP Traps Using Specific and Longest Match Criteria, continued

SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria
	criteria, this configuration is not the best match for these incoming traps.	

- NNMi handles each OID as if it contains an implicit wildcard. For example, when NNMi receives a trap whose OID is .1.3.6.1.6.3.1.1.5.4.100, NNMi logs the trap as SnmpLinkUp (.1.3.6.1.6.3.1.1.5.4) and generates an SNMPLinkUp incident.
- If a trap's OID matches both an implicit and explicit wildcard, the longer one is used. If the length is the same, NNMi uses the implicit OID. [Click here for an example:](#)

The following table provides an example of precedence between implicit and explicit wildcards.

Example of Matching Incoming SNMP Traps Using Implicit and Explicit Wildcard Criteria

SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria
.1.3.6.1.4.1.2.3.*	.1.3.6.1.4.1.2.3.4	The longest OID takes precedence.
.1.3.6.1.4.1.2	.1.3.6.1.4.1.2.3	The implicit OID takes precedence.
.1.3.6.1.4.1.*	Using the length and implicit criteria, this configuration is not the best match for these incoming traps.	See above.

SNMP Object ID Format for SNMPv1 Generic Traps

NNMi requires that SNMPv1 traps have object IDs. The object IDs are created according to the specifications in Request for Comments (RFC) document 2576: *Coexistence between Version 1, Version 2, and Version 3 of the Internet-standard Network Management Framework*.

When using SNMPv1 format, you can specify either generic or vendor specific traps. SNMPv1 generic traps are standard traps that are commonly used across vendors. The SNMPv1 enterprise specific traps are those traps that are generated by a particular vendor's device. The vendor is also known as the enterprise. Both include a vendor name as part of the set of information stored with each trap.

Note:

- The value you enter for an SNMP Object ID (OID) must be unique.
- When checking whether an SNMP Trap Incident Configuration exists, NNMI's TrapFilter uses only implicit matching when checking generic SNMPv1 traps OIDs. See ["About the Trap Service Stages" on page 684](#) for more information about TrapFilter.
- The wildcard character is not valid for an SNMPv1 generic trap because these traps do not begin with .1.3.6.1.4.

The six SNMPv1 generic traps have the following SNMP object identifiers that are recognized by SNMPv2c:

1.3.6.1.6.3.1.1.5.1 (coldStart)

1.3.6.1.6.3.1.1.5.2 (warmStart)

1.3.6.1.6.3.1.1.5.3 (linkDown)

1.3.6.1.6.3.1.1.5.4 (linkUp)

1.3.6.1.6.3.1.1.5.5 (authenticationFailure)

1.3.6.1.6.3.1.1.5.6 (egpNeighborLoss)

To configure an SNMP object identifier (SNMP OID) for a generic SNMPv1 trap, specify the SNMP object ID as described in RFC 2576. You also need to include the object identifier for the vendor name (<VendorEnterprise>) as shown below:

<SNMPv2c generic trap OID>.<VendorEnterprise>

The <vendorEnterprise> is the object identifier for the vendor that is included with the varbind trap information.

For example, the SNMP object identifier for Cisco warmStart trap would be:

.1.3.6.1.6.3.1.1.5.2.1.3.6.1.4.1.9

Note: Cisco's Vendor enterprise object identifier in this example is .1.3.6.1.4.1.9

SNMP Object ID Format for a Specific SNMPv1 Trap

NNMI requires that SNMPv1 traps have object identifiers. The object IDs are created according to the specifications in RFC 2576: *Coexistence between Version 1, Version 2, and Version 3 of the Internet-standard Network Management Framework*.

When using SNMPv1 format, you can specify either generic or vendor specific traps. SNMPv1 generic traps are standard traps that are commonly used across vendors. The SNMPv1 enterprise specific traps are those traps that are generated by a particular vendor's device. The vendor is also known as the enterprise. Both include a vendor name as part of the set of information stored with each trap.

When specifying the SNMP object ID for an SNMPv1 specific trap, include the SNMP object ID for the vendor name and for the trap that you want to see in the console incident views.

The value you enter must be in the format:

<VendorEnterprise>.0.<SpecificTrapNumber>

The *<VendorEnterprise>* is the object identifier for the vendor that is included in the SNMPv1 trap. The *<SpecificTrapNumber>* is the SNMPv1 specific trap identification number that is provided by the vendor.

For example, for an SNMPv1 vendor object id 1.3.6.1.3.1.12.9 and specific trap number 12234, the SNMP object ID would be:

1.3.6.1.3.1.12.9.0.12234

Note: You can use a wildcard character (*) in the SNMP Object ID attribute to create an SNMP Trap Incident configuration for multiple OIDs. This feature enables you to use the same SNMP Trap Incident Configuration for similar traps. For example, you might have a device class for which you might want to capture a particular kind of trap as an SNMP Trap Incident and ignore the rest.

When using the wildcard (*) character in the SNMP Object ID (OID) attribute, note the following:

- The OID must be unique.
- Only one wildcard character is permitted within the SNMP OID attribute.
- The wildcard must appear at the end of an OID. For example .1.3.6.1.4.1.* is valid; however, .1.3.6.1.4.*.2 is NOT valid.
- NNMi permits wildcards only in OIDs beginning with .1.3.6.1.4 (private MIBs).
- The wildcard character is not valid for an SNMPv1 generic trap because these traps do not begin with .1.3.6.1.4.
- When checking whether an SNMP Trap Incident Configuration exists, NNMi's TrapFilter uses only implicit matching when checking generic SNMPv1 traps OIDs. See ["About the Trap Service Stages" on page 684](#) for more information about TrapFilter.
- NNMi matches the OID value using the longest match. Specific OID matches take precedence over an OID that is matched using the wildcard character. [Click here for an example:](#)

The following table provides an example of precedence between a specific OID and one that includes a wildcard. This example also illustrates how NNMi uses the longest match.

Example of Matching Incoming SNMP Traps Using Specific and Longest Match Criteria

SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria
.1.3.6.1.4.1.2.3	.1.3.6.1.4.1.2.3	Specific OID takes precedence over the wildcard OID configuration.
.1.3.6.1.4.1.*	.1.3.6.1.4.1.2	The wildcard OID takes precedence because it is the longest match.
.1.3.6.1.4.*	Using the specific OID and longest match criteria, this configuration is not the best match for these incoming traps.	See above.

- NNMi handles each OID as if it contains an implicit wildcard. For example, when NNMi receives a trap whose OID is .1.3.6.1.6.3.1.1.5.4.100, NNMi logs the trap as SnmpLinkUp (.1.3.6.1.6.3.1.1.5.4) and generates an SNMPLinkUp incident.
- If a trap's OID matches both an implicit and explicit wildcard, the longer one is used. If the length is the same, NNMi uses the implicit OID. [Click here for an example:](#)

The following table provides an example of precedence between implicit and explicit wildcards.


Example of Matching Incoming SNMP Traps Using Implicit and Explicit Wildcard Criteria



SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria
.1.3.6.1.4.1.2.3.*	.1.3.6.1.4.1.2.3.4	The longest OID takes precedence.
.1.3.6.1.4.1.2	.1.3.6.1.4.1.2.3	The implicit OID takes precedence.
.1.3.6.1.4.1.*	Using the length and implicit criteria, this configuration is not the best match for these incoming traps.	See above.

Display an SNMP Trap as a Root Cause Incident

SNMP traps normally appear as symptoms rather than as root cause incidents. However, there might be times when you want an SNMP trap to appear as a root cause incident. For example, you


might want an HSRP state change (cHsrpStateChange, 1.3.6.1.4.1.9.9.106.2.0.1) trap to be listed as a root cause. This trap might occur when the hot standby has gone down indicating the system is at risk if there is a failover.

Note: To reduce "noise" associated with duplicate incidents, NNMI changes the incident Correlation Nature to  **Symptom** for any user-defined Root Cause (User Root Cause) incidents that exceed the rate or de-duplication threshold:

-  **Root Cause** value = determined by NNMI's Causal Engine
-  **User Root Cause** = your NNMI administrator configured NNMI to always treat this Incident as Correlation Nature: Root Cause

To display an SNMP Trap Incident as a Root Cause incident:

Select **Root Cause** ☒ in the **SNMP Trap Incident Configuration** form.

The next time the incident occurs, the Correlation Nature attribute value changes to  **Root Cause**.

To no longer display an SNMP Trap Incident as a Root Cause incident:

Clear **Root Cause** ☐ in the **SNMP Trap Incident Configuration** form.

The next time the incident occurs, the Correlation Nature attribute value changes to  **Symptom**.

Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)

When configuring incidents, NNMI provides the Category and Family attributes to help you organize your incidents.

Preconfigured Categories

The Category attribute helps you organize your incidents. Select the category that you want to be associated with this type of incident when it appears in an incident view. Each of the possible Category values is described in the following table.

Incident Categories Provided by NNMI

Category	Description
Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMI with default configurations, but it is available for incidents you define.
Application Status	Indicates there is a problem with the health of the NNMI software. Examples of these kinds of events include license expiration (see "Track Your NNMI Licenses" on page 1604 or "Extend a Licensed Capacity" on page 1605) or that a certain NNMI process or service lost connection to the Process Status Manager (see "Stop or Start an NNMI Process" on page 87 and "Stop or Start

Incident Categories Provided by NNMi, continued

Category	Description
	NNMi Services" on page 93).
Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.
Fault	Indicates a problem with the network, for example Node Down.
Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .
Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.
Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.

Note: You can add your own Category entries to NNMi. See ["Create an Incident Category \(SNMP Trap Incident\)" on page 901](#) for more information.

You can use Family values to further categorize the types of incidents that might be generated. Each of the possible Family values are described in the following table.

Incident Family Attribute Values Provided by NNMi

Family	Description
Address	Indicates the incident is related to an address problem.
Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .
BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.
Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Chassis	Indicates the incident is related to a chassis problem.
Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.
Connection	Indicates the incident is related to a problem with one or more connections.
Correlation	Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.
Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.
HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).
Interface	Indicates the incident is related to a problem with one or more interfaces.
IP Subnet	Indicates the incident is related to a problem with the IP Subnet.
License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .
NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.
Node	Indicates the incident is related to a node problem.
OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RAMS	Indicates the incident is related to a Router Analytics Management System problem.
RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.
STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents

¹Hot Standby Router Protocol

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
	you define.
Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.
System and Applications	Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.
Trap Analysis	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</div> <div>Indicates the incident is related to an SNMP trap storm.</div>
VLAN	Indicates the incident is related to a problem with a virtual local area network.
VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP ¹).

Note: You can add your own Family entries to NNMi. See "[Create an Incident Family \(SNMP Trap Incident\)](#)" on the next page for more information.





Create an Incident Category (SNMP Trap Incident)

The Category attribute helps you organize your incidents. Create any Category that makes sense to you and your team. For a list of the Category codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(SNMP Trap Incident\)](#)" on page 898.


To create a new incident Category:

1. Navigate to the **Incident Category** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:

¹Virtual Router Redundancy Protocol

- To create an incident configuration, click the  New icon.
 - To edit an incident configuration, double-click the row representing the configuration you want to edit.
- e. In the configuration form, locate the **Category** attribute.
- f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the previous form.

Category Code Attributes





Name	Description
Label	Incident category name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Alpha-numeric, spaces, and underline characters are permitted.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trap_conf.category.<category_Label> com.<your_company_name>.nnm.event_conf.category.<category_Label> com.<your_company_name>.nnm.inci_conf.category.<category_Label></pre> <p>The maximum length is 80 characters. Alpha-numeric characters and periods are permitted. Spaces are not permitted.</p>

Create an Incident Family (SNMP Trap Incident)


The Family attribute helps you organize your incidents. Create any Family that makes sense to you and your team. For a list of the Family codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(SNMP Trap Incident\)](#)" on page 898.

To create a new incident Family:

1. Navigate to the **Incident Family** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.

- c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - To create an incident configuration, click the  New icon.
 - To edit an incident configuration, double-click the row representing the configuration you want to edit.
 - e. In the configuration form, locate the **Family** attribute.
 - f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
 3. Click  **Save and Close** to save your changes and return to the previous form.

Family Attributes

Name	Description
Label	Family name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Any character type is valid.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trapConf.family.<family_label> com.<your_company_name>.nnm.eventConf.family.<family_label> com.<your_company_name>.nnm.inciConf.family.<family_label></pre> <p>The maximum length is 80 alpha-numeric characters, periods allowed, no spaces allowed.</p>

Specify the Incident Severity (SNMP Trap Incident)

The incident severity represents the seriousness calculated for the incident. Use the severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described in the following table.

Incident Severity Values

Attribute	Description
Normal	Indicates there are no known problems related to the associated object. This severity

Incident Severity Values, continued

Attribute	Description
	is meant to be informational. Generally, no action is needed for these incidents.
Warning	Indicates there might be a problem related to the associated object.
Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.
Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.
Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.

See ["Monitor Incidents for Problems"](#) for more information about these severity values.

Specify Your Incident Message Format (SNMP Trap Incident)

When configuring an incident, specify the information you want NNMi to include in the incident's Message attribute value. You can use any combination of valid parameter strings and Custom Incident attributes to configure the Message.

Note: The incident Message limit is 1024 characters. If the returned values exceed this limit, NNMi truncates the value starting from the end of the returned text string.

["Valid Parameters for Configuring Incident Messages \(SNMP Trap Incident\)"](#) below

["Include Custom Incident Attributes in Your Message Format \(SNMP Trap Incident\)"](#) on page 911

Valid Parameters for Configuring Incident Messages (SNMP Trap Incident)

When configuring incident messages, consider using incident information as part of the message. NNMi provides the following parameter values. Use these parameters as variables when formatting an incident message.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See ["Specify Your Incident Message Format \(SNMP Trap Incident\)"](#) above for more information about configuring messages.

Parameter strings are available for the following:

Note: See the following tables to view the valid parameters for incidents generated from Custom Polled Instances: [Parameter Strings for all Incidents \(Attributes from an Incident form\)](#), [Parameter Strings for Node Source Objects \(Attributes from a Node form\)](#), and the [Parameter Strings for all Incidents \(Attributes not Visible from any form\)](#).

- Parameter strings for all incidents (Incident form attributes) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Incident form attributes)

Parameter String	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$sev, \$severity	Value of the Severity attribute of the Incident form.

- Parameter Strings for Node Source Objects (Node form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Node Source Objects (Node form attributes)

Parameter String	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the

Parameter Strings for Node Source Objects (Node form attributes) , continued

Parameter String	Description
	value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

- Parameter Strings for Interface Source Objects (Interface form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Interface Source Objects (Interface form attributes)

Parameter String	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.

Parameter Strings for Interface Source Objects (Interface form attributes) , continued

Parameter String	Description
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.
\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.

- Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes)

Parameter String	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

- Parameter strings for VLAN Source Objects (VLAN form attributes) ([Click here for a list of choices.](#))

Parameter Strings for VLAN Source Objects (VLAN form attributes)

Parameter String	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the VLAN Name attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Ports tab of the Interface form. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.

- Parameter Strings for all incidents (Additional information that is not visible in any form) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Attributes not visible in any form)

Parameter String	Description
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	<p>If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection:</p> <p>The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name>[interface_name]</i></p>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source

Parameter Strings for all Incidents (Attributes not visible in any form), continued

Parameter String	Description
	node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name 4/1 as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances.
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

- Information established in Custom Incident Attributes ([Click here for a list of choices.](#))

Parameter Strings for Attributes Established in Custom Incident Attributes

Parameter String	Description
\$<position _number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_ name>	Value of the name that is used for the custom incident attribute. For example, <code>\$mycompany.mycia</code> . NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_ _	Value of the object identifier for any custom incident attribute that originated as a

Parameter Strings for Attributes Established in Custom Incident Attributes, continued

Parameter String	Description
oid>	varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: <code><CIA_name>:<CIA_value></code> in which the custom incident attribute name appears followed by the custom incident attribute value.

- Functions to generate values ([Click here for a list of choices.](#))

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the `nnmloadmib.ovpl` command.

Functions to Generate Values Within the Incident Message

Function	Description
\$oidtext (\$<position_ number>)	<p>A <code><position_number></code> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, <code>\$oidtext(\$2)</code>.</p> <div style="border: 1px solid black; padding: 5px; margin: 10px 0;"> <p>Note: The position number you enter must represent a CIA that contains an Object Identifier (OID) value.</p> </div> <p>NNMi returns the textual value of the OID for the CIA specified.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ If the MIB is not loaded, NNMi returns the numeric OID value. ■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$oidtext (\$<CIA_ oid>)	<p>The <code><CIA_oid></code> argument specifies the Object Identifier (OID) for any custom incident attribute that originated as a varbind. For example, <code>\$oidtext (\$.1.3.6.1.6.3.1.1.5.1.)</code> Use this argument to the <code>\$oidtext()</code> function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the textual value of the OID you specify.</p>

Functions to Generate Values Within the Incident Message, continued

Function	Description
	<p>Note the following:</p> <ul style="list-style-type: none">■ If the MIB is not loaded, NNMi returns the numeric OID value.■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$text (\$<position_ number>)	<p>The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>
\$text (\$<CIA_ oid>)	<p>The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>

Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)

NNMi includes two categories of CIAs:

- SNMP trap varbinds identified by the Abstract Syntax Notation value (ASN.1). NNMi turns varbinds into CIAs and maintains each varbind's position number. See ["Load SNMP Trap Incident Configurations" on page 873](#).
- Custom incident attributes provided by NNMi. See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

You cannot create Custom Incident Attributes.

You can use CIAs in your message format to extend the amount of information presented. To determine which CIAs are available for any particular incident type, open an Incident view, locate the incident and open the [Incident form](#). Navigate to the **Custom Attributes** tab. A complete list of available CIAs (for that incident type) appears in the table.

To include a CIA in your message format, type the dollar-sign character (\$) plus any of the following:

- Varbind position number or asterisk (*) to include all varbind values
- Name of the CIA
- Object identifier (oid) of the CIA (useful when the varbind position number is not consistent among vendors)

Note: A single incident cannot include two CIAs with the same name. However, two incidents can contain CIAs having the same names and values.

The following table presents some example formats with the subsequent output.

Example Incident Message Formats

Example Message Format	Output in Incident View
Possible trouble with \$3	Possible trouble with <varbind 3>
Possible trouble with \$11	Possible trouble with <varbind 11>
Possible trouble with \$77 (where the varbind position 77 does not exist)	Possible trouble with <Invalid or unknown cia> 77
Possible trouble with \$*	Possible trouble with <cia1_name: cia_value>, <cia2_name: cia_value>, <cia3_name: cia_value>
Possible trouble with \$3x	Possible trouble with <varbind 3>x
Possible trouble with \$1.2.3.4.5	Possible trouble with <value of the CIA with oid of 1.2.3.4.5>
Possible trouble with \$cia.sourceObject.Ucmdbld	Possible trouble with <value of the CIA with name of cia.sourceObject.Ucmdbld>

Tip: NNMi provides an error message when a CIA cannot be found. For example, if you enter an unavailable varbind position, name, or object identifier (oid), NNMi returns an "Invalid or unknown cia" error message.

Specify a Description for Your Incident Configuration (SNMP Trap Incident)

NNMi provides the Description attribute to help you further identify the current incident configuration.

Description

Use the description field to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.

Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure Interface Settings for an SNMP Trap Incident

NNMi enables you to apply a Suppression, Enrichment, Dampen, or Actions incident configuration to a Source Object based on the Source Object's participation in an Interface Group.







Note: Interface Settings override any other Suppression, Enrichment, Dampen, or Actions configuration settings for this incident, including those configured on the Node Settings tab.

Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.



For information about each Interface Settings tab:

For information about each SNMP Traps tab:

To apply an incident configuration to a Source Object based on the Source Object's Interface Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, click the  Open icon in the row representing the configuration you want to edit.
4. Configure the desired Interface Settings (see [table](#)).
5. Configure any Suppression, Dampen, or Enrichment settings for this Interface Group.
6. Click  **Save and Close** to save your changes and return to the previous form.

Interface Group Attributes

Name	Description
Interface Group	Click the  Lookup icon and select  Quick Find to select the Interface Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those interfaces that appear in multiple Interface Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If an interface is in multiple Interface Groups and more than one of those Interface Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the interface.
Enable	Use this attribute to temporarily disable an incident's configuration settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Related Topics

["Configure Node Settings for an SNMP Trap Incident" on page 957](#)

Configure Incident Suppression Settings for an Interface Group (SNMP Trap Incident)

Note: Interface Settings override any other Suppression settings for this incident, including those from the Node Settings tab.

NNMi enables you to suppress a specified incident configuration based on the Source Object's participation in an Interface Group. When an incident is suppressed:

- It is not stored in the NNMi database
- It does not appear in an incident view in the NNMi console







You can also suppress the incident configuration based on either of the following:

- Source Node's participation in a Node Group. See ["Configure Incident Suppression Settings for a Node Group \(SNMP Trap Incident\)" on page 959](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Suppression Settings for an SNMP Trap Incident" on page 1004](#) for more information.

Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.

For information about each Interface Settings tab:

To suppress an incident configuration based on an Interface Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Navigate to the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, and click the  Open icon.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Suppression** tab.
6. Configure the desired Suppression behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings for the specified Interface Group:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p>

Interface Settings Suppression Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (java.util.regex Pattern class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression <code>\Q.1.3.6.1.4.1.9.9\E.*</code> and has a value of 25. ■ Contain a varbind whose OID matches the regular expression <code>\Q.1.3.6.1.2.1.2.2.1.1.3\E.*</code> and has a value of 3.

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Settings <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. 						




Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. 				

Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribut- e	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribut- e	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Suppression Attributes , continued

Name	Description														
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribute	Description	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 										
Attribute	Description														
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 														
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> <p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>OR</td><td> <p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT</td><td> <p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p> </td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>
Button	Description														
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.														
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.														
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.														
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>														
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>														
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>														

Interface Settings Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Enrichment Settings for an Interface Group (SNMP Trap Incident)

Note: Interface Settings override any other Enrichment settings for this incident, including those from the Node Settings tab.

NNMi enables you to fine tune and enhance a specified incident configuration based on the Source Object's participation in an Interface Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Severity
- Priority
- Category
- Family
- Correlation Nature
- Message
- Assigned To

You can also enrich the incident configuration based on either of the following:




- The incident configuration based on the Source Node's participation in a Node Group. See ["Configure Incident Enrichment Settings for a Node Group \(SNMP Trap Incident\)" on page 968](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Enrichment Settings for an SNMP Trap Incident" on page 1013](#) for more information.







Tip: See [Create Interface Groups](#) for more information about Interface Groups.

For information about each Interface Settings tab:

For information about each Enrichment tab:

To enrich an incident configuration based on an Interface Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Enrich Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p>

















Interface Settings Enrich Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Address • Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.) • Card • Connection • Correlation • Interface • Node
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p>



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Interface Settings Enrich Configuration Attributes , continued

Name	Description
	<p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMI's Causal Engine  User Root Cause = your NNMI administrator configured NNMI to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p>

Interface Settings Enrich Configuration Attributes , continued

Name	Description
	<p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (SNMP Trap Incident)" on page 904</p> <p>"Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)" on page 911</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (SNMP Trap Incidents)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.











When creating a CIA for an incident configuration, you can specify any of the following values:

- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
5. Make sure the Enrichment settings are configure. See ["Configure Incident Enrichment Settings for an Interface Group \(SNMP Trap Incident\)" on page 923](#) for more information.
8. Navigate to the **Custom Incident Attributes** tab.
9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.
 - c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.

10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).

11. Click  **Save and Close** to save your changes and return to the previous form.


Custom Incident Attribute








Name	Description
Type	Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are: <ul style="list-style-type: none">• Node Custom Attribute• Interface Custom Attribute
Custom Attribute Name	Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following: <ul style="list-style-type: none">• Name of the Custom Attribute on the source node• Name of the Custom Attribute on the interface (source object)
Custom Incident Attribute Name	Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (SNMP Trap Incidents)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.

- ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue..
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure the Enrichment settings are configured. See ["Configure Incident Enrichment Settings for an Interface Group \(SNMP Trap Incident\)" on page 923](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())
 - c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: Operator:

Append Insert Replace

AND AND NOT

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String: (AND NOT ())



Insert AND OR NOT EXISTS NOT EXISTS Delete

10. Click **Save and Close**.
11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an


Payload Filter Editor Settings, continued

Attribute	Description
	<p>example.</p> <p>Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6.</p> <ul style="list-style-type: none">• > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4.• >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.• between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. Note: As shown in the example, each value must be entered on a separate line.• in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. Note: As shown in the example, each value must be entered on a separate line.

Payload Filter Editor Settings, continued

Attribute	Description
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="451 552 1370 663"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1380 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 825 1341 890" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 905 1364 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1001 1344 1033">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="451 1064 1370 1176"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1207 561 1239">Example:</p> <p data-bbox="451 1270 1299 1335">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1367 1364 1432">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1461 938 1493">The value for which you want NNMi to search.</p> <div data-bbox="418 1514 1370 1885"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. • The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for an Interface Group (SNMP Trap Incident)

Note: Interface Settings override any other Dampening settings for this incident, including those from the Node Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Object's participation in an Interface Group:

- Execution of Incident Actions
- Execution of Diagnostics (*HP Network Node Manager iSPI Network Engineering Toolset Software \ NNM iSPI NET*)
- Appearance within Incident views in the NNMi Console

You can configure the Dampening settings based on either of the following:

- The Source Node's participation in a Node Group. See ["Configure Incident Dampening Settings for a Node Group \(SNMP Trap Incident\)" on page 982](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Dampening Settings for an SNMP Trap Incident" on page 1018](#) for more information.


Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.






For information about each Interface Settings tab:

After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure Dampening settings based on an Interface Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.

- ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Dampening** tab.
6. Configure the desired Dampening behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Dampening Configuration Attributes

Name	Description
Enable	Use this attribute to temporarily disable an incident's dampening settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	Specifies the number of minutes to be used for the dampen interval. Note: The maximum dampen interval is 60 minutes.
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none">• Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class).• You must use a <code>ciaName</code> that already exists in the trap or event you are configuring.

Interface Settings Dampening Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none"> Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. View the expression displayed under Filter String to see the logic of the expression as it is created. The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <p>AND</p> <pre>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ■ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3.

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings	
Attribute	Description
Attribute	<p>The attribute name on which NNMI searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.




Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. 				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribute	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="555 453 984 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="573 743 1320 808"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="573 1425 1334 1522"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="555 453 984 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="573 743 1320 808"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="573 1425 1334 1522"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="555 453 984 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="573 743 1320 808"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="573 1425 1334 1522"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
Value	<p>The value for which you want NNMI to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMI displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMI should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMI includes interfaces with (interface description) ifDesc containing</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Actions for an Interface Group (SNMP Trap Incident)

Note: Interface Settings override any other Actions settings for this incident, including those from the Node Settings tab.


For information about each Interface Settings tab:

NNMi enables you to configure incident actions based on a Source Object's participation in an Interface Group.

You can also configure incident actions based on either of the following:

- The Source Node's participation in a Node Group. See ["Configure Incident Actions for a Node Group \(SNMP Trap Incident\)" on page 992](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Actions for an SNMP Trap Incident" on page 1042](#) for more information.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.



Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.







You can configure actions for incidents generated from SNMP Traps and the NNMi management events. Any time an incident configuration changes, the action directory is rescanned and any executable or script files (for example, Jython) are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#) for more information about the actions directory.

Tip: Copy any required executable or script files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:

1. Navigate to the **SNMP Trap Configuration** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Interface Settings** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure the basic Interface Setting behavior is configured. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Actions** tab.
6. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row and click the  Delete icon.
7. In the ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#), provide the required information.
8. Click  **Save and Close** to save your changes.









The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type .

Configure a Payload Filter for an Incident Action (Interface Settings) (SNMP Trap Incidents)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select the **SNMP Traps** tab.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue..
 - iii. To delete an incident configuration, select the row and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for an SNMP Trap Incident" on page 913](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:
 - a. To create an Action configuration, click the  New icon, and continue.
 - b. To edit an Action configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Action configuration, select a row and click the  Delete icon.
7. Make sure you configure the Action Configuration settings. See ["Configure Incident Actions for an Interface Group \(SNMP Trap Incident\)" on page 947](#) for more information.
- h. Select the **Payload Filter** tab.
 - i. Define your Payload Filter (see [table](#)).
 - i. Plan out the logic needed for your Filter String.
 - ii. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())
 - iii. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, NOT

Filter String: AND NOT ()

Operator List: Insert, AND, OR, NOT, EXISTS, NOT EXISTS, Delete

Annotation: Highlight the location in the logic flow, then click Insert to define the filter requirement



j. Click **Save and Close**.

k. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMI searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. ■ != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than .1.3.6.1.4.1.9.9.13.1.2.1.7. ■ < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than


Payload Filter Editor Settings, continued

Attribute	Description
	<p>6.</p> <ul style="list-style-type: none"> ■ <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. ■ > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. ■ >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. ■ between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code>  <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> ■ in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 

Payload Filter Editor Settings, continued

Attribute	Description
	<p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. ■ is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. ■ like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.

Payload Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> not in Finds all values except those included in the list of values. Click here for an example. Example: ciaValue not in  matches any incident that contains a varbind with values other than 1 and 2. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below. </div> Example: ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9. ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.
Value	The value for which you want NNMi to search. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> Note: </div>

Payload Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. ■ The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <i>ifDesc</i> containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) <i>ifName</i> value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Node Settings for an SNMP Trap Incident

NNMi enables you to apply a Suppression, Enrichment, Dampen, Actions, or Diagnostics Selections incident configuration to a Source Node based on the Source Node's participation in a Node Group.







Note: Node Settings override any other Suppression, Enrichment, Dampen, Actions, or Diagnostics Selections configuration settings for this incident, except those configured on the Interface Settings tab.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.



For information about each Node Settings tab:

For information about each SNMP Traps tab:

To apply an incident configuration to a Source Node based on the Source Node's Node Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Configure the desired Node Settings (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the previous form.

Node Group Attributes

Name	Description
Node Group	Click the  Lookup icon and select  Quick Find to select the Node Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those nodes that appear in multiple Node Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If a node is in multiple Node Groups and more than one of those Node Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the node.
Enable	Use this attribute to temporarily disable an incident's suppression settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Configure Incident Suppression Settings for a Node Group (SNMP Trap Incident)

Note: Node Settings override any other Suppression settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to suppress a specified incident configuration based on the Source Node's participation in a Node Group. When an incident is suppressed:

- It is not stored in the NNMi database
- It does not appear in an incident view in the NNMi console




You can also suppress the incident configuration based on either of the following:




- The Source Object's participation in an Interface Group. See ["Configure Incident Suppression Settings for an Interface Group \(SNMP Trap Incident\)" on page 914](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Suppression Settings for an SNMP Trap Incident" on page 1004](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

To suppress an incident configuration based on a Node Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, and click the  Open icon.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Suppression** tab.
6. Configure the desired Suppression behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (java.util.regex Pattern class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre> AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5 </pre>




Node Settings Suppression Attributes , continued

Name	Description						
	<p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <h4>Payload Filter Editor Settings</h4> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p>
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p>						

Node Settings Suppression Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4
Attribut- e	Description										
	<ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>.
Attribut- e	Description				
	<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. 				

Node Settings Suppression Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="550 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> </td></tr> </table>	Attribute	Description		<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="550 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p>	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>
Attribute	Description								
	<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="550 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p>	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>				
Operator	Value								
not in	<div> <div>1</div> <div>2</div> </div>								

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut-e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribut-e	Description		<ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.
Attribut-e	Description						
	<ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 						

Node Settings Suppression Attributes , continued

Name	Description																
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>OR</td><td> Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>NOT</td><td> Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>EXISTS</td><td> Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div> </td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div>
Button	Description																
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.																
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.																
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.																
AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div>																

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> </td></tr> </table>	Button	Description		<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>
Button	Description						
	<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>						

Node Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued						
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server))) Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</td></tr><tr><td>Delete</td><td>Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</td></tr></table>	Button	Description		(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server))) Note: View the expression displayed under Filter String to see the logic of the expression as it is created.	Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.
Button	Description						
	(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server))) Note: View the expression displayed under Filter String to see the logic of the expression as it is created.						
Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.						

Configure Incident Enrichment Settings for a Node Group (SNMP Trap Incident)

Note: Node Settings override any other Enrichment configuration for this incident, except those configured on the Interface Settings tab.

NNMi enables you to enhanced a specified incident configuration based on the Source Node's participation in a Node Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To

You can also enrich the incident configuration based on either of the following:










- The Source Object's participation in an Interface Group. See ["Configure Incident Enrichment Settings for an Interface Group \(SNMP Trap Incident\)" on page 923](#) for more information.

- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Enrichment Settings for an SNMP Trap Incident" on page 1013](#) for more information.

For information about each Node Settings tab:

For information about each Enrichment tab:

To configure enrichment settings for a Node Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure the basic Node Setting behavior is configured. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.










Node Settings Enrich Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none">• Address• Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.)• Card• Connection• Correlation• Interface• Node










¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Node Settings Enrich Configuration Attributes , continued

Name	Description
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine

Node Settings Enrich Configuration Attributes , continued

Name	Description
	<div data-bbox="479 321 1370 436"> <ul style="list-style-type: none">  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <div data-bbox="441 1054 1370 1163"> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> </div> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (SNMP Trap Incident)" on page 904</p> <p>"Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)" on page 911</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <div data-bbox="441 1528 1370 1638"> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p> </div>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (SNMP Trap Incidents)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.







When creating a CIA for an incident configuration, you can specify any of the following values:








- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 - c. To delete an existing configuration, select a row and click the  Delete icon.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:

- a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure the Enrichment settings are configured. See ["Configure Incident Enrichment Settings for a Node Group \(SNMP Trap Incident\)" on page 968](#) for more information.
 8. Navigate to the **Custom Incident Attributes** tab.
 9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.
 - c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.
 10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).
 11. Click  **Save and Close** to save your changes and return to the previous form.










Custom Incident Attribute

Name	Description
Type	Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are: <ul style="list-style-type: none"> • Node Custom Attribute • Interface Custom Attribute
Custom Attribute Name	Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following: <ul style="list-style-type: none"> • Name of the Custom Attribute on the source node • Name of the Custom Attribute on the interface (source object)
Custom Incident Attribute Name	Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (SNMP Trap Incidents)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 - c. To delete an existing configuration, select a row and click the  Delete icon.
4. Make sure the basic Node Setting behavior is configured. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.

7. Make sure the Enrichment settings are configured. See "[Configure Incident Enrichment Settings for a Node Group \(SNMP Trap Incident\)](#)" on page 968 for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: Operator:

Buttons: Append, **Insert**, Replace

Logic Flow: AND, AND, NOT

Filter String: (() AND NOT ())

Highlight the location in the logic flow, then click Insert to define the filter requirement

10. Click **Save and Close**.
11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	The attribute name on which NNMi searches. Filterable attributes include the

Payload Filter Editor Settings, continued

Attribute	Description
	<p>following:</p> <ul style="list-style-type: none"> • <code>ciaName</code> • <code>ciaValue</code>
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value other than .1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="449 1604 881 1722"> <p>The screenshot shows a UI element for the 'between' operator. It consists of a label 'Operator' and a dropdown menu currently showing 'between'. To the right of the dropdown are two input fields. The top input field contains the number '1' and the bottom input field contains the number '4'.</p> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p>

Payload Filter Editor Settings, continued

Attribute	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="448 667 841 804" data-label="Form"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>in</td><td>4 5</td></tr> </tbody> </table> </div> matches any incident with a varbind value of either 4 or 5. <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p>	Operator	Value	in	4 5
Operator	Value				
in	4 5				

Payload Filter Editor Settings, continued

Attribute	Description				
	<p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code> <div data-bbox="446 924 872 1058" data-label="Form"> <table border="1"> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>not in</td> <td>1 2</td> </tr> </tbody> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="464 1182 1320 1247" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="464 1696 1341 1764" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the Examples listed below.</p> </div> <p>Example:</p> 	Operator	Value	not in	1 2
Operator	Value				
not in	1 2				

Payload Filter Editor Settings, continued

Attribute	Description
	<p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <div> <p>Note:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the <code>between</code> Operator causes two value fields to be displayed. The <code>between</code>, <code>in</code> and <code>not in</code> operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.

Additional Filters Editor Buttons, continued

Button	Description
	<p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for a Node Group (SNMP Trap Incident)

Note: Node Settings override any other Dampening settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Node's participation in a Node Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

- Appearance within Incident views in the NNMi Console

You can also configure Dampening settings based on either of the following:

- The Source Object's participation in an Interface Group. See ["Configure Incident Dampening Settings for an Interface Group \(SNMP Trap Incident\)" on page 938](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Dampening Settings for an SNMP Trap Incident" on page 1018](#) for more information.








Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure Dampening settings based on a Node Group:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 - c. To delete an existing configuration, select a row and click the  Delete icon.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Dampen** tab.
6. Configure the desired Dampen behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Dampen Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's Dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	<p>Specifies the number of minutes to be used for the dampen interval.</p> <p>Note: The maximum dampen interval is 60 minutes.</p>
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p>




Node Settings Dampen Attributes , continued

Name	Description
	<ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3.
Payload Filter Editor Settings	
Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.

Node Settings Dampen Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 	Operator	Value	between	1		4
Attribute	Description										
	<ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Dampen Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1333 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the Examples listed below.</p> </div> </td></tr> </table>	Attribute	Description		<div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1333 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the Examples listed below.</p> </div>
Attribute	Description				
	<div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1333 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the Examples listed below.</p> </div>				

Node Settings Dampen Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div> <div>not in</div> <div> <div>1</div> <div>2</div> </div> </div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re- </td></tr> </table>	Attribute	Description		<p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div> <div>not in</div> <div> <div>1</div> <div>2</div> </div> </div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re-
Attribute	Description				
	<p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div> <div>not in</div> <div> <div>1</div> <div>2</div> </div> </div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re- 				

Node Settings Dampen Attributes , continued

Name	Description												
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table> <p>Payload Filter Editor Buttons</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front</td></tr> </table>	Attribute	Description		<p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front
Attribute	Description												
	<p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>												
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 												
Button	Description												
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.												
Insert	Inserts the current expression (Attribute, Operator, and Value) in front												

Node Settings Dampen Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Node Settings Dampen Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> </td></tr> </table>	Button	Description		<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre>
Button	Description						
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre>						

Node Settings Dampen Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued						
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</td></tr><tr><td>Delete</td><td>Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</td></tr></table>	Button	Description		Note: View the expression displayed under Filter String to see the logic of the expression as it is created.	Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.
Button	Description						
	Note: View the expression displayed under Filter String to see the logic of the expression as it is created.						
Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.						

Configure Incident Actions for a Node Group (SNMP Trap Incident)

For information about each Node Settings tab:

Note: Node Settings override any other Actions settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to configure incident actions based on a Source Node's participation in a Node Group.

You can also configure incident actions based on either of the following:

- The Source Object's participation in an Interface Group. See ["Configure Incident Actions for an Interface Group \(SNMP Trap Incident\)" on page 947](#) for more information.
- Incident configuration default settings without specifying a Node or Interface Group. See ["Configure Actions for an SNMP Trap Incident" on page 1042](#) for more information.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.








You can configure actions for incidents generated from SNMP traps and NNMi management events. Any time an incident configuration changes, the action directory is rescanned and any executable or script files (for example, Jython) are reloaded to the NNMi database. See ["Lifecycle](#)


[Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#) for more information about the actions directory.

Tip: Copy any required executable or script files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:

1. Navigate to the **SNMP Trap Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 - c. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
4. Select the **Actions** tab.
5. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row and click the  Delete icon.
3. In the ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on page 1044](#), provide the required information.







4. Click  **Save and Close** to save your changes and return to the **SNMP Trap Configuration** form.

The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type .

Configure a Payload Filter for an Incident Action (Node Settings) (SNMP Trap Incidents)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 - c. To delete an existing configuration, select a row and click the  Delete icon.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for an SNMP Trap Incident" on page 957](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:

- a. To create an Action configuration, click the * New icon, and continue.
 - b. To edit an Action configuration, select a row, click the 📄 Open icon, and continue.
 - c. To delete an Action configuration, select a row and click the ✖ Delete icon.
7. Make sure the Action Configuration settings are configured. See ["Configure Incident Actions for a Node Group \(SNMP Trap Incident\)" on page 992](#) for more information.
 8. Select the **Payload Filter** tab.
 9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

The screenshot shows the **Filter Editor** interface. At the top, there are three input fields: **Attribute** (containing 'ciaName'), **Operator** (containing '='), and **Value** (containing '.1.3.6.1.4.1.9.9.13.1.2.1.7'). To the right of these fields are three buttons: **Append**, **Insert** (highlighted with a red circle), and **Replace**. Below these fields is a logic flow diagram. It shows a tree structure with **AND** and **NOT** operators. A red arrow points from the **Insert** button to the logic flow diagram, with a text box that says "Highlight the location in the logic flow, then click Insert to define the filter requirement". At the bottom, there is a **Filter String** field containing the text "(() AND NOT ())". A red arrow points from the first set of parentheses in the filter string to the **Insert** button.

10. Click  **Save and Close**.

11. Click  **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • <code>ciaName</code> • <code>ciaValue</code>
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code>

Payload Filter Editor Settings, continued

Attribute	Description												
	<div><div><table><thead><tr><th>Operator</th><th>Value</th></tr></thead><tbody><tr><td>between</td><td>1</td></tr><tr><td></td><td>4</td></tr></tbody></table></div><p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p><div>Note: As shown in the example, each value must be entered on a separate line.</div><ul style="list-style-type: none">• in Finds any match to at least one value in a list of values. Click here for an example. Example: <pre>ciaValue in</pre><div><div><table><thead><tr><th>Operator</th><th>Value</th></tr></thead><tbody><tr><td>in</td><td>4</td></tr><tr><td></td><td>5</td></tr></tbody></table></div><p>matches any incident with a varbind value of either 4 or 5.</p><div>Note: As shown in the example, each value must be entered on a separate line.</div><p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p></div>• is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value.• is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value.• like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</div>	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description				
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: ciaValue not in <div data-bbox="451 1201 878 1335"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>not in</td><td>1 2</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. 	Operator	Value	not in	1 2
Operator	Value				
not in	1 2				

Payload Filter Editor Settings, continued

Attribute	Description
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <p>Note:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	Appends, Inserts, or replaces the OR Boolean Operator in the current cursor

Additional Filters Editor Buttons, continued

Button	Description
	<p>location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Diagnostics Selections for a Node Group (SNMP Trap Incident)










For information about each Node Settings tab: .

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

Note: Node Settings override any other Diagnostics Selections settings for this incident, except those configured on the Interface Settings tab.

The Diagnostic Selections form enables you to configure NNMi to automatically gather NNM iSPI NET diagnostic information for the Incident you are configuring. When using this form, you specify the diagnostics you want to run on each applicable node in the specified Node Group.

To configure Diagnostics to run on a Source Node for an incident:

1. Navigate to the **Diagnostics Selection** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - To create an Incident configuration, click the  New icon.
 - To edit an Incident configuration, select a row, click the  Open icon, and continue.
 - e. Navigate to **Node Settings** tab, and do one of the following:
 - To create a Node Settings configuration, click the  New icon.
 - To edit a Node Settings configuration, select a row, click the  Open icon, and continue.
 - To delete a Node Settings configuration, select the Node setting, and click the  Delete icon.
 - f. Navigate to the **Diagnostic Selection** tab, and do one of the following:
 - To create a Diagnostic Selection setting, click the  New icon, and continue.
 - To edit a Diagnostic Selection setting, select a row, click the  Open icon, and continue.
 - To delete a Diagnostic Selection setting, select a row and click the  Delete icon.
2. Provide the required information (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the **Node Settings** form.

After you configure the Diagnostic for the incident and Node Group, the Diagnostic must match the following criteria before the Diagnostic runs:

- The Source Node must be in the specified Node Group.
- The Diagnostic must be valid for the Source Node. (For example, only Nortel switch Diagnostics are run on Nortel switches.)
- The incident's current lifecycle state must match a lifecycle state for which it was configured. (For example, if you configure the Incident to run a specified Diagnostic when the incident is Closed, then if the current Incident's Lifecycle State is Closed, NNMi runs that Diagnostic.)

Note: If a Source Node is in more than one Node Group, the Diagnostic is only run on the node the first time NNMi finds a match for that Source Node based on the configuration Ordering field.




If these criteria are met, NNM iSPI NET runs the Diagnostics and generates Diagnostic reports to help you solve the problem on the Source Node.

After you configure Diagnostics for an incident, you can also run Diagnostics and access the Diagnostics reports on demand, using **Actions** → **Run Diagnostics** in the Incident form. The same criteria apply (see the [criteria](#) above). See [Incident Form:Diagnostics Tab](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

You can also run and access Diagnostics reports from a Node form. See [Node Form: Diagnostics Tab](#) for more information.

Diagnostic Settings Attributes

Attribute	Description
Flow Definition	<p>Select the Diagnostic (Flow Definition) you want to use for the specified Node Group.</p> <p>Click the  Lookup icon and choose one of the following options:</p> <ul style="list-style-type: none"> Show Analysis to display Analysis Pane information for Diagnostic (Flow Definition). (See Use the Analysis Pane for more information about the Analysis Pane.) Quick Find to view the list of possible diagnostic Flow Definitions. <p>NNMi provides diagnostics for the following types of devices:</p> <ul style="list-style-type: none">Cisco switchCisco routerCisco switch/routerNortel switch <p>See "Diagnostics (Flows) Provided by NNM iSPI NET" on page 859 for more information about the diagnostics provided and the devices to which they apply.</p>
Lifecycle State	<p>Incident Lifecycle State of the target Incident.</p> <p>If the incident's Lifecycle State matches the value specified here, the Diagnostic runs.</p> <p>The Diagnostic automatically runs on each applicable Source Node in the specified</p>

Diagnostic Settings Attributes, continued

Attribute	Description
	Node Group if the incident has the Lifecycle State currently configured in this attribute of the Diagnostic (Flow Definition - set of automated commands).
Enable	Use this attribute to temporarily disable an incident's Diagnostics settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Configure Suppression Settings for an SNMP Trap Incident

For information about each SNMP Trap tab:

NNMi enables you to suppress incidents based on Interface Group, Node Group, or default Suppression settings. NNMi applies your Suppression settings in the following order. Only the first match applies.

1. Interface Group (SNMP Trap Configuration Form: Interface Settings tab)
2. Node Group (SNMP Trap Configuration Form: Node Settings tab)
3. Suppression configuration settings without specifying an Interface Group or Node Group (SNMP Trap Configuration Form: Suppression tab)

A Payload Filter enables you to use the data that is included with any of the following items before they are stored as incidents in NNMi:





- Traps generated from an SNMP agent
- Syslog Messages.
- Management incidents that are generated by NNMi.

Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as CIA (Custom Incident Attribute) names and values. For example, you might want NNMi to suppress a particular status change notification trap for a specified Node Group or Interface Group. To do so, you could include the name of the trap varbind that stores this information as well as the particular status change value string the traps that you want to suppress should contain.

See ["Configure Incident Suppression Settings for an Interface Group \(SNMP Trap Incident\)" on page 914](#) for information about how to suppress an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Suppression Settings for a Node Group \(SNMP Trap Incident\)" on page 959](#) for more information about how to suppress an incident for a Node Group with or without a Payload Filter.

To configure suppression for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand **Incidents**.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - iii. To delete an incident configuration, click the  Delete icon.
2. Select the **Suppression** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none">• Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class).• You must use a <code>ciaName</code> that already exists in the trap or event you are configuring.• Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.• View the expression displayed under Filter String to see the logic of the expression

Suppression Attributes , continued

Name	Description				
	<p>as it is created.</p> <ul style="list-style-type: none"> The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <p>AND</p> <pre>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <h4>Payload Filter Editor Settings</h4> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName
Attribute	Description				
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName 				

Suppression Attributes , continued

Name	Description
	Payload Filter Editor Settings, continued
Attribut- e	Description
	<ul style="list-style-type: none"> • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between

Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p> <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> </td></tr> </table>	Attribut- e	Description		<div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p> <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p>
Attribut- e	Description				
	<div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p> <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p>				

Suppression Attributes , continued

Name	Description								
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i> The period (.) character means <i>any single character of any type at this location.</i> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> </div> not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 . not in Finds all values except those included in the list of values. Click here for an example. Example: <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i> The period (.) character means <i>any single character of any type at this location.</i> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> </div> not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 . not in Finds all values except those included in the list of values. Click here for an example. Example: <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> 	not in	1		2
Attribute	Description								
	<ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i> The period (.) character means <i>any single character of any type at this location.</i> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> </div> not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 . not in Finds all values except those included in the list of values. Click here for an example. Example: <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> 	not in	1		2				
not in	1								
	2								

Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. </td></tr> </table>	Attribut- e	Description		<p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive.
Attribut- e	Description						
	<p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. 						

Suppression Attributes , continued

Name	Description														
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 										
Attribute	Description														
	<ul style="list-style-type: none"> NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 														
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>OR</td><td> Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>NOT</td><td> Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> </td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre>
Button	Description														
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.														
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.														
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.														
AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>														
OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>														
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre>														

Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that</p>

Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Enrichment Settings for an SNMP Trap Incident

For information about each **SNMP Traps** tab:

For information about each **Enrichment** tab:

NNMi enables you to fine tune and enhance incidents based on Interface Group, Node Group, or default Enrichment settings. NNMi applies your Enrichment settings in the following order. Only the first match applies:

1. Interface Group (SNMP Trap Configuration Form: Interface Settings tab)
2. Node Group (SNMP Trap Configuration Form: Node Settings tab)

3. Enrich configuration settings without specifying an Interface Group or Node Group (SNMP Trap Configuration Form: Enrichment tab)

The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To

Note: Any configuration you specify for Severity, Priority, or Message overrides those values provided in the SNMP Trap Configuration Form: Basics information.

You can also add a Custom Incident Attribute that is provided by NNMI to the incoming incident.

Note: You cannot create Custom Incident Attributes.

When configuring Interface Settings, Node Settings, or other Suppress Configuration, Enrich Configuration, or Dampening configuration settings for an incident, you can specify a Payload Filter. Payload Filters enables you to use the data that is included with any of the following items before they are stored as incidents in NNMI:







- Traps generated from an SNMP agent
- Syslog Messages
- Management incidents that are generated by NNMI

Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as Management Event CIA (Custom Incident Attribute) names and values. For example, you might want NNMI to enrich an incident based on a particular status change notification trap and participation within a specified Node Group or Interface Group. To do so, you would first specify participation in the Node Group or Interface Group for the trap you want to enrich. You would also specify a Payload Filter that includes the name of the trap varbind that stores the status information as well as the status change value string of interest.

See ["Configure Incident Enrichment Settings for an Interface Group \(SNMP Trap Incident\)" on page 923](#) for information about how to enrich an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Enrichment Settings for a Node Group \(SNMP Trap Incident\)" on page 968](#) for more information about how to enrich an incident for a Node Group with or without a Payload Filter.

To configure Enrichment settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Enrichment** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Provide the required information (see [table](#))
5. Click  **Save and Close** to save your changes and return to the previous form.

Enrichment Attributes

Name	Description
Category	Use the Category attribute to customize the category for this incident configuration. Possible values include: <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security

















Enrichment Attributes , continued

Name	Description
	<ul style="list-style-type: none"> Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none"> Address Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.) Card Connection Correlation Interface Node
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p>



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Enrichment Attributes , continued

Name	Description
	<p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation

Enrichment Attributes , continued

Name	Description
	See Incident Form: General Tab for more information.
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (SNMP Trap Incident)" on page 904</p> <p>"Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)" on page 911</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Dampening Settings for an SNMP Trap Incident

For information about each SNMP Traps tab:

NNMi enables you to delay (dampen) the following for an incident configuration:

- Appearance within Incident views in the NNMi Console
- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

You can configure Dampening settings based on Interface Group, Node Group, or default Dampening settings. NNMi applies your Dampening settings in the following order. Only the first match applies.

1. Interface Group (SNMP Trap Configuration Form: Interface Settings tab)
2. Node Group (SNMP Trap Configuration Form: Node Settings tab)
3. Dampening configuration settings without specifying an Interface Group or Node Group (SNMP Trap Configuration Form: Dampening tab)

When using Dampening configuration, note the following:

- For all Incident Configurations except Deduplication and Rate Incidents, if the dampened Incident is Closed before the Dampen Interval has passed, NNMi deletes the Incident. If the Incident is the Root Cause Incident, NNMi also deletes any Child Incidents

Note: NNMi administrators can view the number of incidents Closed and deleted while dampened. Access the **Help** → **System Information** → **Health** tab, click the View Detailed Health Report button, and search for the word dampened.

- For all Incident Configurations except Deduplication and Rate Incidents, if the dampened Incident is Closed before the Dampen Interval has passed, NNMi deletes the Incident. If the Incident is the Root Cause Incident, NNMi also deletes any Child Incidents.
- NNMi always retains the Parent Deduplication or Rate Incident even If its Child Incidents are Closed within the Dampen Interval and subsequently deleted. See "[Correlate Duplicate Incidents \(Deduplication Configuration\)](#)" on page 745 and "[Track Incident Frequency \(Rate: Time Period and Count\)](#)" on page 746 for more information about Duplicate and Rate Correlation incidents.
- Any Deduplication and Incidents that have Child Incidents inherit the Dampening settings from their Correlated Children.
- If an incident is a Root Cause Incident and a Child Incident's Dampen Interval is less than the Parent Incident's Dampen Interval, NNMi holds any Child Incidents until the Dampen Interval for the Parent Incident has passed or until the Parent Incident is Closed and subsequently deleted.
- To make sure NNMi handles both Incidents in a Pairwise Configuration the same, configure the same Dampen Interval for each Incident in a Pairwise Incident Configuration.
- After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

- You can use a Payload Filter to fine tune the incidents you want to dampen.

When configuring Interface Settings, Node Settings, or other Suppress Configuration, Enrich Configuration, or Dampening configuration settings for an incident, you can specify a Payload

Filter. Payload Filters enables you to use the data that is included with any of the following items before they are stored as incidents in NNMI:





- Traps generated from an SNMP agent
- Syslog Messages
- Management incidents that are generated by NNMI

Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as Management Event CIA (Custom Incident Attribute) names and values. For example, you might want NNMI to dampen an incident based on a particular status change notification trap and participation within a specified Node Group or Interface Group. To do so, you would first specify participation in the Node Group or Interface Group for the trap you want to dampen. You would also specify a Payload Filter that includes the name of the trap varbind that stores the status information as well as the status change value string of interest.

See ["Configure Incident Dampening Settings for an Interface Group \(SNMP Trap Incident\)" on page 938](#) for information about how to configure Dampening settings for an Interface Group with or without a Payload Filter.

See ["Configure Incident Dampening Settings for a Node Group \(SNMP Trap Incident\)" on page 982](#) for more information about how to configure Dampening for a Node Group with or without a Payload Filter.

To configure Dampening settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create a configuration, click the  New icon, and continue.
 - ii. To edit configuration, select a row, click the  Open icon, and continue.
 - iii. To delete a configuration, select a row and click the  Delete icon.
2. Select the **Dampening** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Dampening Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's Dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the Dampen Interval.
Minutes	Specifies the number of minutes to be used for the Dampen Interval.
Seconds	Specifies the number of seconds to be used for the Dampen Interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> ■ Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). ■ You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. ■ Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. ■ View the expression displayed under Filter String to see the logic of the expression as it is created. ■ The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of</p>




Dampening Attributes , continued

Name	Description						
	<p>5.</p> <ul style="list-style-type: none"> ■ The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. ■ The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. ■ You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ○ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ○ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an 						

Dampening Attributes , continued

Name	Description										
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribute	Description		<p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4
Attribute	Description										
	<p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Dampening Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>. </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.
Attribute	Description				
	<ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>. 				

Dampening Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </td></tr> </table>	Attribute	Description		<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p>	Operator	Value	not in	1 2
Attribute	Description								
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p>	Operator	Value	not in	1 2				
Operator	Value								
not in	1 2								

Dampening Attributes , continued

Name	Description						
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. </td></tr> </table>	Attribute	Description		<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.
Attribute	Description						
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. 						

Dampening Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
	<ul style="list-style-type: none"> The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMI should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMI includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>

Dampening Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from</p> </div>

Dampening Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Deduplication for an SNMP Trap Incident

For information about each SNMP Traps tab:



The deduplication configuration determines what values NNMi should match to detect when an SNMP Trap Incident, Syslog Message Incident or Management Event Incident is a duplicate.

Note the following:



- Suppression, Enrichment, and Dampening are not supported for Deduplication incidents.
- NNMi applies only one deduplication configuration per incident. If NNMi generates an incident using a specified deduplication configuration, NNMi continues to correlate duplicate incidents using the original configuration. To use a different deduplication configuration for an incident, first delete the current deduplication incident (created using the original deduplication configuration). NNMi generates the next deduplication incident according to the new deduplication configuration settings.
- NNMi continues to update the duplicate count regardless of an incident's lifecycle state. For example, if an incident's **Lifecycle State** is set to **Closed**, the duplicate count continues to be incremented. See [About the Incident Lifecycle](#) for more information. This behavior helps you identify situations in which the incident is not yet fixed. Take note if the Duplicate Count is incremented after a lengthy time period has elapsed, which might indicate there is a new problem with the node, interface, or address.
- Each time you stop and restart ovjboss, any incidents that have not yet been correlated or persisted are lost. This means that after a restart of ovjboss, an incoming incident might not be correlated as expected. For example, after a restart of ovjboss, a duplicate incident might not be correlated under its original parent incident. Instead, a new parent incident might be generated. See ["Stop or Start an NNMi Process" on page 87](#) for more information about starting and stopping the ovjboss process.
- If a Duplicate Correlation Incident is dampened, note the following:
 - Duplicate Correlation Incidents inherit the Dampening settings from its Correlated Children.
 - NNMi always retains the Parent Duplicate Correlation incident, even if its Child Incidents are Closed and subsequently deleted.

See ["Dampening Incident Configurations" on page 769](#) for more information about Dampening an incident configuration.

To specify or delete a deduplication configuration:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create a deduplication configuration, click the  New icon, and continue.
 - ii. To edit a deduplication configuration, select a row, click the  Open icon, and

continue.

- iii. To delete a deduplication configuration, select a row and click the  Delete icon.
2. Select the **Deduplication** tab.
3. Provide the required information (see "Deduplication Attributes" table).
4. Click  **Save and Close** to save your changes and return to the previous form.

Deduplication Attributes

Name	Description
Enabled	<p>Use this attribute to temporarily disable an incident's deduplication configuration:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p> <div><p>Note: After a deduplication configuration is enabled, NNMi increments the Duplicate Count for an associated incident regardless of the Lifecycle State value. For example, if an incident's Lifecycle State is set to Closed, the duplicate count continues to be incremented. See About the Incident Lifecycle for more information.</p></div>
Count	<p>Specifies the number of duplicate incidents for the current configuration that NNMi stores at one time. For example, if the Count is 10, after NNMi receives 10 duplicate incidents, NNMi deletes the first (oldest) duplicate incident and keeps the eleventh. (NNMi stores ten maximum.)</p>
Hours	<p>Used with the Minute and Second Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Hour Interval value is 1, and no Minute or Second Intervals are specified, and the duplicate incident is not generated within one hour, NNMi generates a new duplicate incident the next time it occurs.</p>
Minutes	<p>Used with the Hour and Second interval to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Minute Interval is 30 and no Hour or Second Intervals are specified, and the duplicate incident is not generated within 30 minutes, NNMi generates a new duplicate incident the next time it occurs.</p>
Seconds	<p>Used with the Hour and Minute Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Second Interval is 120 and no Hour or Minute Intervals are specified, and the duplicate incident is not generated within 120 seconds, NNMi generates a new duplicate incident the next time it occurs.</p>
Parent Incident	<p>Used to specify the Incident Configuration that will be the Parent Incident for the</p>

Deduplication Attributes, continued

Name	Description
	<p>incident you are configuring. For example, you might have created a Management Event Incident Configuration that could be used as the Parent Incident for SNMP Trap Incidents.</p> <p>When specifying the Parent Incident, you have the following options:</p> <ul style="list-style-type: none"> When you want to use a configuration that NNMi provides, use the default Duplicate Correlation incident configuration . If you select this option, the incident message for the Parent Incident begins as follows: <p style="margin-left: 40px;">Duplicate Correlation for <incident_configuration_name></p> <p>For example if you are configuring a Node Down incident and select Duplicate Correlation as the Parent Incident, the Parent Incident message begins with: Duplicate Correlation for Node Down. Each Node Down incident that is a duplicate then appears correlated under the Duplicate Correlation for Node Down incident.</p> <ul style="list-style-type: none"> NNMi also enables you to customize the Parent Incident for a given deduplication scenario. If you have created a Management Event Incident Configuration to use for this deduplication scenario, select the Management Event Incident Configuration that you have created.
Comparison Criteria	<p>Specify the attribute values that must match before the incident is identified as a duplicate. The possible attributes consist of the following choices.</p> <ul style="list-style-type: none"> Name - The Name attribute value from the Incident form: General tab. CIA - Represents any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> SourceNode - The Source Node attribute value from the Basics attributes listed on the Incident form. The Source Node value is the IP Address or Name of the node for which the incident was generated. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The Source Node must be stored in the NNMi database.</p> </div> <ul style="list-style-type: none"> Source Object - The Source Object attribute value from the Basics

Deduplication Attributes, continued

Name	Description						
	<p>attributes listed on the Incident form.</p> <p>Note: The Source Object must be stored in the NNMi database.</p> <p>Caution: Each attribute value in the option you select must match before the incident is identified as a duplicate. For example, if you select Name, only the Incident Name value must match. If you select Name SourceNode SourceObject CIA, the Incident Name, Source Node, Source Object, and all Custom Incident Attribute values that you configure as a Parameter Value must match before NNMi identifies the incident as a duplicate.</p> <p>Selecting an option that includes CIA enables you to further refine the deduplication criteria. For example, you might want to configure deduplication for incidents with CIA values that specify the same State attribute value for a particular network object.</p> <p>For a description of each Comparison Criteria option, click here.</p> <table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td>Name</td><td>Value of the Name attribute from the Incident form: General tab must match.</td></tr> <tr> <td>Name CIA</td><td> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> </table>	Comparison Criteria	Description	Name	Value of the Name attribute from the Incident form: General tab must match.	Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>
Comparison Criteria	Description						
Name	Value of the Name attribute from the Incident form: General tab must match.						
Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>						

Deduplication Attributes, continued

Name	Description								
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td>Name SourceNode</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form </td></tr> <tr> <td>Name SourceNode CIA</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> <tr> <td>Name SourceObject</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> </td></tr> </table>	Comparison Criteria	Description	Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form 	Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 	Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p>
Comparison Criteria	Description								
Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form 								
Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 								
Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p>								

Deduplication Attributes, continued

Name	Description								
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. </td></tr> <tr> <td>Name SourceObject CIA</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> <tr> <td>Name SourceNode SourceObject</td><td> <p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics </td></tr> </table>	Comparison Criteria	Description		<ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 	Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>	Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics
Comparison Criteria	Description								
	<ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 								
Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>								
Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics 								


Deduplication Attributes, continued

Name	Description						
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td>attributes listed on the Incident form</td></tr> <tr> <td>Name SourceNode SourceObject CIA</td><td> <p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> </table>	Comparison Criteria	Description		attributes listed on the Incident form	Name SourceNode SourceObject CIA	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>
Comparison Criteria	Description						
	attributes listed on the Incident form						
Name SourceNode SourceObject CIA	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>						
Deduplication Comparison Parameters	<i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must populate one or more rows in this table. See " Deduplication Comparison Parameters Form " on page 746.						


Deduplication Comparison Parameters Form (SNMP Trap Incident)

Comparison Parameter values enable accurate identification of duplicate incidents. Custom Incident Attributes (CIAs) are used as Comparison Parameter values. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Deduplication (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.



Open Root Cause Incidents Incident **InterfaceDown**

Save and Close Delete Incident

Basics

Message
Interface Down

* Severity Critical

* Priority None

* Lifecycle State Registered

Source Node CH-KVI

Source Object Se0/0/2

Assigned To

Correlated Children Custom Attributes Diagnostics Re

General
Correlated Parents
Correlated Children
Custom Attributes
Diagnostics
Registration

1 - 2 of 2







Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To specify a CIA to use in the identification criteria for duplicate incidents:

1. Navigate to the **Deduplication Comparison Params** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.

- d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit a configuration, select a row, click the  Open icon, and continue.
- e. On the form that opens, navigate to the **Deduplication** tab.
- f. Locate the **Deduplication Comparison Parameters** table.
- g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
 - To delete an existing Custom Incident Attribute parameter, select a row and click the  Delete icon..
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Rate (Time Period and Count) for an SNMP Trap Incident

For information about each SNMP Traps tab:

Use Rate configuration to track incident patterns *based on the number of incident reoccurrences within a specified time period*. After the count within the specified time period is reached, NNMi emits a Rate Correlation incident and continues to update the Correlation Notes with the number of occurrences within that rate.

Note: Suppression, Enrichment, and Dampening are not supported for Rate incidents.

As long as your defined criteria (Count and Hours, Minutes, Seconds) is sustained, the following information is updated in the Correlation Notes of the Rate Correlation incident:

- the actual number of occurrences of incidents for that sustained rate (Count)
- the sustained time interval (Hours, Minutes, Seconds)

For example, you can set a Rate configuration to track when a link is intermittently down at least three times in 30 minutes. NNMi shows the first occurrence of the rate incident in the incident view and uses Correlation Notes to update the number of incidents and time interval to reflect all the incremental incident occurrences and time periods. To continue the example, if the rate of three times in 30 minutes is sustained for 90 minutes, NNMi updates the Correlation Notes to specify that 9 incidents occurred in 90 minutes.




NNMi provides preconfigured Rate correlations. You can add new Rate correlations.


When you open the Incident form of the newest instance:

- On the General tab, two fields notify you that the Rate correlation is working:
 - **Correlation Nature:** Rate Stream Correlation
 - **Count:** x
- On the **Correlated Children** tab, each incident is listed in the table.
- If a Rate Correlation Incident is dampened, note the following:
 - Rate Correlation Incidents inherit the Dampening configuration settings from its Correlated Children.
 - NNMi always retains the Parent Rate Correlation Incident, even if its Child Incidents are Closed and subsequently deleted.



See [Dampening Incident Configurations](#) for more information about Dampening an incident configuration.

To establish a rate correlation within an incident configuration:

1. Navigate to the **Rate** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - To delete an existing configuration, select a row and click the  Delete icon.
 - e. On the form that opens, locate the **Rate** tab.
2. Provide the definition for this Rate configuration (see the "Rate Configuration Definition" table).

3. *Optional.* If your [Comparison Criteria](#) includes custom incident attributes (CIA) to identify one specific incident, use the Comparison Parameter List table to define each CIA. See ["Rate Comparison Parameters Form" on page 767](#).
4. Click  **Save and Close** to save your changes and return to the previous form.


Rate Configuration Definition

Attribute	Description
Enable	<p>Use this attribute to temporarily disable an incident's rate settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p> <p>If enabled, NNMi actively tracks any reoccurrences of the designated incident within the time period you specify, and generates a Rate incident.</p>
Count	Specify the number of reoccurrences required before your Rate Configuration starts working.
Hours	Used with the Minutes and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Minutes	Used with the Hours and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Seconds	Used with the Hours and Minutes attributes to specify the time duration within which the reoccurrences are measured.
Parent Incident	Click the  icon and select  Quick Find. Select Rate Correlation from the list.
Comparison Criteria	<p>Specify which group of attributes must match before the incident is identified as a duplicate. The possible groups of attributes consist of the following choices.</p> <p>Name value of the Incident (from the General tab on the Incident form).</p> <p>Source Node value (from the Basics group on the Incident form). Address or name of the node for which the incident was generated.</p> <p>Source Object value (from the Basics group on the Incident form). For example, the Source Object for a LinkDown incident is interface.</p> <p>CIA custom incident attribute values (select from the list displayed on the Custom Attributes tab on the Incident form). If you want to use CIA as part of your comparison criteria, see "Rate Comparison Parameters Form (SNMP Trap Incident)" on the next page.</p>
Rate Comparison Parameters	<i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must populate one or more rows in this table. See "Rate Comparison Parameters Form (SNMP Trap Incident)" on the next page .


Rate Comparison Parameters Form (SNMP Trap Incident)

Custom Incident Attributes (CIAs) are used as parameter values. Parameter values enable accurate identification of duplicate incidents. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Rate (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.









The screenshot shows the HP Network Node Manager i Software interface for configuring an incident. The incident type is 'InterfaceDown'. The 'Custom Attributes' tab is selected, showing a table of attributes.

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To specify a CIA to use in the identification criteria for duplicate incidents:

1. Navigate to the **Rate Comparison Params** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, navigate to the **Rate** tab.
 - f. Locate the **Rate Comparison Parameters** table.
 - g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
 - To delete Custom Incident Attribute parameter specification, select a row and click the  Delete icon.
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Actions for an SNMP Trap Incident

For information about each SNMP Traps tab:

For information about each Actions tab:

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.

If the NNMi management server is running on a Windows operating system, NNMi runs each action that you configure using the Local System account. If the NNMi management server is running on a Linux operating system, NNMi runs each action that you configure using the bin user name. To change the user account associated with actions, see the "Setting the Action Server Name Parameter" section in the *HP Network Node Manager i Software Deployment Reference*.

You can also configure incident actions based on either of the following:

- The Source Node's participation in a Node Group. See ["Configure Incident Actions for a Node Group \(SNMP Trap Incident\)" on page 992](#) for more information.
- The Source Object's participation in an Interface Group. See ["Configure Incident Actions for an Interface Group \(SNMP Trap Incident\)" on page 947](#) for more information.

You can configure actions for incidents generated from SNMP traps, Syslog Messages, and the NNMi management events. Any time an incident configuration changes, the action directory is rescanned and any executable or script files (for example, Jython) are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on the next page](#) for more information about the actions directory.

Tip: Copy any required executable or script files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(SNMP Trap Incidents\)" on the next page](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. To view the contents of the Actions log, use the **Tools** → **Incident Actions Log** menu option.

See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.








NNMi sets the default values described in the following table.

See the "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for information about changing the default values for Action Server Properties.

Action Server Properties

Property	Description	Value
numProcess	Number of actions that can be run at one time.	10
numJythonThreads	Number of threads the action server uses to run Jython scripts	10
userName	User name under which the action server runs.	bin

To configure an automatic action for an incident:


1. Navigate to the **Actions** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row and click the  Delete icon.
 - e. Select the **Actions** tab.
2. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row and click the  Delete icon.
3. In the "[Lifecycle Transition Action Form \(SNMP Trap Incidents\)](#)" below, provide the required information.
4. Click  **Save and Close** to save your changes and return to the previous form.

The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.




Lifecycle Transition Action Form (SNMP Trap Incidents)

For information about each Action tab:


Use this form to enter the command you want to run when an incident of the type you are configuring is at a particular [Lifecycle State](#). For example, when an incident is generated (**Registered**), you might want to automatically open a trouble ticket or email or page your network operator.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.

To configure an action for an incidents:

1. Navigate to the **Lifecycle Transition Actions** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Click to expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Select the **Actions** tab.
 - e. From the **Lifecycle Transition Action** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row and click the  Delete icon.
2. Make your configuration choices (see [table](#)).

Note: NNMi reloads the configuration information anytime the incident configuration is changed.

3. Click  **Save and Close** to save your changes and return to the previous form.

Create Action Attributes

Attribute	Description
Lifecycle State	Select a Lifecycle State from the drop-down menu.
Command Type	If you provided a Jython command, select Jython ¹ from the drop-down list. If you are using an executable or bat file, select ScriptOrExecutable from the drop-down list.
Command	Enter one of the following: <ul style="list-style-type: none">• A Jython method with the required parameters• Executable command for the current operating system with the required parameters. When entering a Command value, note the following: <ul style="list-style-type: none">• Left or right bracket ([]) and backtick (` Unicode character: 0060 hex = 96 dec)

¹Jython is a programming language (successor of JPython) uses Java class, instead of Python modules.




Create Action Attributes, continued

Attribute	Description
	<p>characters are not permitted in the Command attribute. If you need these characters in your shell script, place them in a shell script file and reference that file from the Command attribute.</p> <ul style="list-style-type: none">• Windows only: Shell commands are not permitted in the Command attribute. To use shell commands, place them in a shell script file and reference that file from the Command attribute.• Use absolute paths to executables instead of relying on the PATH variable as it might not be set correctly.• Verify that you do not have two Jython methods with the same name. Otherwise, NNMi is not able to tell which is the correct method to load.• You can use the same Jython method for more than one incident configuration.• Jython (.py) files must reside in the following directory (see "About Environment Variables" on page 86): <div><p>Note: All the functions defined in the Jython files that reside in this directory are also accessible by NNMi. The files are also executed by NNMi on startup.</p></div> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\actions</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/actions</pre> <ul style="list-style-type: none">• When using executable files, specify the absolute path to the executable command or make sure the directory in which the executable file resides is in your PATH environment variable.• NNMi provides a set of parameters that can pass attribute values from an incident configuration. See "Valid Parameters for Configuring Incident Actions (Management Events)" on page 1397 for more information.

Configure a Payload Filter for an Action (SNMP Trap Incidents)



The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.

2. Select the **Actions** tab.

3. Do one of the following:

- a. To create a new configuration, click the  New icon.
- b. To edit an existing configuration, select a row, click the  Open icon, and continue.

4. Select the **Payload Filter** tab.

5. Define your Payload Filter (see [table](#)). Also see [Guidelines for Creating a Payload Filter](#).

- a. Plan out the logic needed for your Filter String.
- b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: Operator:

Append Insert Replace

AND AND NOT

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String: (AND NOT ())

Insert AND OR NOT EXISTS NOT EXISTS Delete

6. Click **Save and Close**.
7. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind value less than 6.


Payload Filter Editor Settings, continued

Attribute	Description												
	<ul style="list-style-type: none"> • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="449 957 878 1075" data-label="Form"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="466 1230 1320 1293" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <div data-bbox="449 1556 841 1690" data-label="Form"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value of either 4 or 5.</p> <div data-bbox="466 1814 1320 1845" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate</p> </div> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with varbind values. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1317 520">matches any incident that contains a varbind with values other than 1 and 2 .</p> <div data-bbox="469 573 1317 638"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 890" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1360 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1341 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1087 1338 1155"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1274 1308 1337">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1371 1360 1434">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1465 938 1497">The value for which you want NNMi to search.</p> <p data-bbox="418 1518 630 1549">Note the following:</p> <ul data-bbox="418 1581 1357 1843" style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Valid Parameters for Configuring Incident Actions (SNMP Trap Incident)

When configuring incident actions, consider using incident information as part of the action. NNMi provides the following parameter values. Use these parameters as variables in your Jython or executable files.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See "[Lifecycle Transition Action Form](#)" on page 848 for more information about configuring incident actions.

Valid Parameters Visible From an Incident's Form

Parameter Value	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$severity, \$sev	Value of the Severity attribute of the Incident form.

Valid Parameters Visible from a Node Form

Parameter Value	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

Valid Parameters Visible from an Interface Form

Parameter Value	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.

Valid Parameters Visible from an Interface Form , continued

\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.
-----------------	---

Valid Parameters Visible from a Layer 2 Connection Form

Parameter Value	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

Valid Parameters Visible from a VLAN Form

Parameter Value	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the Global VLAN Name attribute associated with the interface that is the incident's source object. To access this information from a Node form or Interface form, navigate to the VLAN Ports tab. If the node or interface is part of more than one VLAN, this parameter returns a comma-separated list.

Valid Parameters Not Visible From a Form

Parameter Value	Description
\$id	Unique Object Identifier attribute value for the incident (unique across the entire NNMi Database).
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$messageFormat, \$msg	<i>Valid for Incident actions only.</i> Message text displayed for an incident when this parameter is included as an argument to an incident action.
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection: The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name> [interface_name]</i>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name <code>4/1</code> as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source

Valid Parameters Not Visible From a Form, continued

Parameter Value	Description
	object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances..
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

Valid Parameters Established in Custom Incident Attributes

Parameter Value	Description
\$<position_number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_name>	Value of the name that is used for the custom incident attribute. For example, \$mycompany.mycia. NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_oid>	Value of the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: \$<CIA_name>:<CIA_value> in which the custom incident attribute name appears followed by the custom incident attribute value.

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the [nnmloadmib.ovpl](#) command.

Functions to Generate Values Within Incident Messages

Function	Description
\$text (\$<position_number>)	The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1. After the function runs, NNMi replaces the numeric value with the text value

Functions to Generate Values Within Incident Messages, continued

Function	Description
	stored in the CIA. Note: If a text value is not available, NNMi returns the numeric value.
\$text (\$<CIA_oid>)	The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA. Note: If a text value is not available, NNMi returns the following message as the value: <CIA <OID> with value <value> was not found within the mib cache

Configure Forward to Global Manager Settings for an SNMP Trap Incident (NNMi Advanced)

For information about each **SNMP Traps** tab:

(*NNMi Advanced - Global Network Management feature*) The NNMi Global Network Management feature enables multiple NNMi management servers to work together while managing different geographic areas of your network. See [NNMi's Global Network Management Feature \(NNMi Advanced\)](#) for more information. The Global Manager combines topology information from multiple Regional Managers, but maintains *a separate set of incidents about those nodes*.

Use the Global Manager Forwarding tab when you want to forward specific SNMP traps from your NNMi management server (a Regional Manager) to all Global Managers in your Global Network Management environment.





Caution: The Global Manager must have an incident configuration for that SNMP trap, otherwise the incoming trap is dropped. See ["Export and Import Configuration Settings" on page 1610](#) for ideas about sharing incident configurations among NNMi management servers.

When you configure Forward to Global Managers, you can specify an optional Payload Filter for NNMi to use when determining *which occurrences* should be forwarded to Global Managers. Payload Filters enable you to use the data that is included with an occurrence of an incident configuration before it is stored as an incident in the NNMi database.

Examples of the type of data that can be used as a Payload Filter include Custom Incident Attribute names (ciaName) and values (ciaValue). For example, you might want NNMi to forward an incident based on a particular status change notification trap. To do so, you would specify a Payload Filter that includes the name of the Custom Incident Attribute that stores the status information as well as the status change value string of interest.

Tip: See also "[Configure Trap Forwarding Destinations](#)" on page 1413.

To configure Forwarding to Global Managers:

1. Navigate to the **SNMP Trap Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **SNMP Trap Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row and click the  Delete icon.
2. Select the **Forward to Global Managers** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Forwarding Configuration Attributes

Name	Description
Enable	<p>Use this attribute to enable or temporarily disable an incident's Forward to Global Managers settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that NNMi forwards to other servers. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none">• Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class).• You must use a <code>ciaName</code> that already exists in the trap or event you are configuring.• Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.

Forwarding Configuration Attributes , continued

Name	Description						
	<ul style="list-style-type: none"> View the expression displayed under Filter String to see the logic of the expression as it is created. The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind value of .1.3.6.1.4.1.9.9.13.1.2.1.7 and CIA value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. <h4>Payload Filter Editor Settings</h4> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an 						

Forwarding Configuration Attributes , continued

Name	Description										
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>example.</p> <p>Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. <p>Example: ciaValue < 6 matches any incident that with a varbind value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: ciaValue <= 6 matches any incident that with a varbind value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: ciaValue > 4 matches any incident that with a varbind value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: ciaValue between</p> <div> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </div> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribute	Description		<p>example.</p> <p>Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. <p>Example: ciaValue < 6 matches any incident that with a varbind value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: ciaValue <= 6 matches any incident that with a varbind value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: ciaValue > 4 matches any incident that with a varbind value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: ciaValue between</p> <div> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </div> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4
Attribute	Description										
	<p>example.</p> <p>Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. <p>Example: ciaValue < 6 matches any incident that with a varbind value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: ciaValue <= 6 matches any incident that with a varbind value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: ciaValue > 4 matches any incident that with a varbind value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: ciaValue between</p> <div> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </div> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Forwarding Configuration Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="583 627 971 762" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4 5</td></tr> </table> </div> matches any incident that with a varbind value of either 4 or 5. <div data-bbox="599 884 1328 951" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="599 1753 1317 1818" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the</p> </div> </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="583 627 971 762" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4 5</td></tr> </table> </div> matches any incident that with a varbind value of either 4 or 5. <div data-bbox="599 884 1328 951" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="599 1753 1317 1818" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the</p> </div> 	Operator	Value	in	4 5
Attribute	Description								
	<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="583 627 971 762" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4 5</td></tr> </table> </div> matches any incident that with a varbind value of either 4 or 5. <div data-bbox="599 884 1328 951" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="599 1753 1317 1818" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the</p> </div> 	Operator	Value	in	4 5				
Operator	Value								
in	4 5								

Forwarding Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Examples listed below.</p> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div>not in</div> <div>1 2</div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. </td></tr> </table>	Attribute	Description		<p>Examples listed below.</p> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div>not in</div> <div>1 2</div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example.
Attribute	Description				
	<p>Examples listed below.</p> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div> <div>Operator</div> <div>Value</div> <div>not in</div> <div>1 2</div> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. 				

Forwarding Configuration Attributes , continued

Name	Description														
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table> <p>Payload Filter Editor Buttons</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in</td></tr> </table>	Attribute	Description		<p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in
Attribute	Description														
	<p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>														
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 														
Button	Description														
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.														
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.														
Replace	Replaces the selected expression with the expression displayed in														

Forwarding Configuration Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) <code>ifName</code> value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass</p>

Forwarding Configuration Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> </table>	Button	Description		<p>other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Button	Description						
	<p>other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						

Forwarding Configuration Attributes , continued

Name	Description	
	Payload Filter Editor Buttons, continued	
	Button	Description
	Delete	<div>Deletes the selected expression.</div> <div>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</div>




Configure Syslog Message Incidents (HP ArcSight)


The HP NNMi–ArcSight integration adds syslog message information to NNMi, so that NNMi users can view these syslog messages and investigate potential problems. After the ArcSight integration is enabled, NNMi receives ArcSightEvent traps that contain syslog message data. NNMi then maps this syslog information to a Syslog Message incident configuration and treats it as a syslog message in NNMi. See the *HP Network Node Manager i Software-HP ArcSight Logger Integration Guide* for more information.

You can configure how you want these incidents to be displayed in the incident views provided by NNMi. The types of things you configure include name, category, and the message format.

Note: When the Source Object for a Syslog Message Incident is a Port object, NNMi resolves the Source Object to the associated Interface. Because ArcSight does not store Interface data, these incidents do not appear in the ArcSight user interface. See the *HP Network Node Manager i Software-HP ArcSight Logger Integration Guide* for more information about best practices for viewing these incidents.

To configure a Syslog Message incident:


1. Navigate to the **Syslog Message Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
2. Do one of the following:
 - a. To create a Syslog Message incident configuration, click the  New icon, and continue.
 - b. To edit a Syslog Message incident configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a Syslog Message configuration, select a row, and click the  Delete icon.


3. In the [Syslog Message Configuration form](#), provide the required information.
4. Click  **Save and Close** to save your changes and return to the **Incident Configuration** form.




The next time that a syslog message event of this type arrives into the database, NNMi creates an associated incident to display in the appropriate console incident views.

Syslog Message Configuration Form (HP ArcSight)


To configure incidents originating from syslog messages:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
2. Make your configuration choices (see [table](#)).





Note: If you want to add or edit a Syslog Message incident configuration, verify that **Enabled**  is selected.

- a. To add a Syslog Message incident configuration, click the  **New** icon, and continue.
 - b. To edit a Syslog Message incident configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a Syslog Message incident configuration, click the  **Delete** icon.
3. Click  **Save and Close** to save your changes and return to the previous form.

Tasks for Syslog Message Incident Configuration

Task	How
"Specify the Incident Configuration Name (Syslog Messages) (HP ArcSight)" on page 1074	Use the Basics group of the Syslog Message Configuration form. Specify a name that helps you to identify the configuration for subsequent use.
Specify whether you want to enable this configuration.	In the Basics group of the Syslog Message Configuration form, verify that Enable  is selected for each configuration you want to use.
"Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page	Use the Basics group of the Syslog Message Configuration form. You can organize your incidents using Category and Family.

Tasks for Syslog Message Incident Configuration, continued

Task	How
1074	
"Specify the Incident Severity (Syslog Message) (HP ArcSight)" on page 1079	Use the Basics group of the Syslog Message Configuration form. Possible Severity values include: Normal , Warning , Minor , Major , and Critical .
"Specify Your Incident Message Format (Syslog Message) (HP ArcSight)" on page 1080	Use the Basics group of the Syslog Message Configuration form. The message format determines the message to be displayed for the incident.
"Specify a Description for Your Incident Configuration (Syslog Messages)(HP ArcSight)" on page 1088	Use the Basics group of the Syslog Message Configuration form. Provide a meaningful description.
Specify an Author for Your Incident Configuration (Management Events)	<p>Use the Basics pane of the Syslog Message Configuration form to indicate who created or last modified the event.</p> <div> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value. </div>

After you complete the Basic Configuration for the Syslog Message incident, you can also choose to configure the information described in the following table.

Additional Configurations

Task	How
"Correlate Duplicate Incidents (Deduplication Configuration)" on page 745	Select the Deduplication tab to specify duplicate incidents that you want to be suppressed.
"Track Incident Frequency (Rate: Time Period and Count)" on	Select the Rate tab to specify a rate for duplicate incidents. After the rate limit is reached, NNMI generates an Incident to notify you of the problem.

Additional Configurations , continued

Task	How
page 746	
"Configure an Action for an Incident" on page 847	Select the Actions tab to specify actions that should occur automatically when an incident changes its Lifecycle State .
"Configure Diagnostics for an Incident" on page 857	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- click here for more information.</div> <div>Select the Node Settings tab to specify diagnostic actions that should occur automatically when an incident reaches a selected Lifecycle State for a node that belongs to a particular Node Group.</div>

Configure Basic Settings for a Syslog Message Incident (HP ArcSight)




The Basics settings for a Syslog Message incident specifies general information for an incident configuration, including the name, severity, and message.


Note: In the **Basics** group of the **Syslog Message Configuration** form, verify that **Enable** ☒ is selected for each configuration you want to use.

For information about each Syslog Messages tab:

To configure Basic settings for a Syslog Message incident:

Navigate to the **Syslog Message Configuration** form:





1. From the workspace navigation panel, select the **Configuration** workspace.
2. Expand the **Incidents** folder.
3. Select **Syslog Message Configurations**.
4. Do one of the following:
 - a. To create an incident configuration, click the  New icon, and continue.
 - b. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - c. To delete an incident configuration, select a row, and click the  Delete icon.
5. Configure the required Basic settings (see the [Basic Attributes](#) table).

6. Click  **Save and Close** to save your changes and return to the previous form. NNMi uses the SNMP Object ID to enable forwarding of Management Events as SNMP traps. NNMi automatically assigns a unique SNMP Object ID to all Management Events provided by NNMi.

Basic Attributes for Syslog Message Configuration

Task	How
"Specify the Incident Configuration Name (Syslog Messages) (HP ArcSight)" on page 1074	<p>Use the Basics pane of the Syslog Message Configuration form.</p> <p>Specify the value of the AdditionalDataValue mnemonic for the undefined trap as the Syslog Message name.</p> <p>In the following example LINK-3-UPDOWN is the AdditionalDataValue mnemonic value for the trap:</p> <pre>additionalDataValue.1 .1.3.6.1.4.1.11937.1.42.1.3.1 LINK-3-UPDOWN</pre> <p>Alpha-numeric, spaces, and the following special characters are permitted: - (dash), _ (underscore), : (colon), and / (slash).</p> <p>If the mnemonic value includes non-supported characters, replace each character with an underscore character (_) or space.</p> <p>See the <i>HP Network Node Manager i Software-HP ArcSight Logger Integration Guide</i> for more information.</p>
Specify whether you want to enable this configuration.	In the Basics group of the Syslog Message Configuration form, verify that Enable <input checked="" type="checkbox"/> is selected for each configuration you want to use.
"Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074	Use the Basics pane of the Syslog Message Configuration form. You can organize your incidents using Category and Family.
"Specify the Incident Severity (Syslog Message) (HP ArcSight)" on page 1079	Use the Basics pane of the Syslog Message Configuration form. Possible Severity values include: Normal , Warning , Minor , Major , and Critical .
"Specify Your Incident Message Format (Syslog Message) (HP ArcSight)" on page 1080	Use the Basics pane of the Syslog Message Configuration form. The message format determines the message to be displayed for the incident.

Basic Attributes for Syslog Message Configuration, continued

Task	How
"Specify a Description for Your Incident Configuration (Syslog Messages)(HP ArcSight)" on page 1088	Use the Basics pane of the Syslog Message Configuration form. Provide a meaningful description.
Specify an Author for Your Incident Configuration (Management Events)	<p>Use the Basics pane of the Syslog Message Configuration form to indicate who created or last modified the event.</p> <div> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value. </div>

After you complete the Basic Configuration, you can also choose to configure the information described in the following table.

Additional Incident Configurations

Task	How
"Configure Interface Settings for a Syslog Message Incident (HP ArcSight)" on page 1089	Select the Interface Settings tab to specify an Interface Group to which you want your incident configuration to apply.
"Configure Node Settings for a Syslog Message Incident (HP ArcSight)" on page 1133	Select the Node Settings tab to specify a Node Group to which you want your incident configuration to apply.
"Configure Suppression Settings for a Syslog Message Incident (HP ArcSight)" on page 1179	Select the Suppression tab to specify the criteria for discarding incidents that match the selected incident configuration.
"Configure Enrichment Settings for a Syslog Message Incident (HP ArcSight)" on page 1189	Select the Enrichment tab to specify enhancements for the selected incident configuration.
"Configure Dampening Settings for a Syslog Message Incident (HP ArcSight)" on page 1194	Select the Dampening tab to specify the time interval that must be met before the incident appears in an Incident view.

Additional Incident Configurations, continued

Task	How
"Configure Deduplication for a Syslog Message Incident (HP ArcSight)" on page 1204	Select the Deduplication tab to specify duplicate incidents that you want to be suppressed.
"Configure Rate (Time Period and Count) for a Syslog Message Incident (HP ArcSight)" on page 1213	Select the Rate tab to specify a rate for duplicate incidents. After the rate limit is reached, NNMi generates an Incident to notify you of the problem.
"Configure Actions for a Syslog Message Incident (HP ArcSight)" on page 1217	Select the Actions tab to specify actions that should occur automatically when an incident changes its Lifecycle State .

Specify the Incident Configuration Name (Syslog Messages) (HP ArcSight)

Specify the value of the AdditionalDataValue mnemonic as the Syslog Message name.

In the following example LINK-3-UPDOWN is the AdditionalDataValue mnemonic value for the trap:

```
additionalDataValue.1 .1.3.6.1.4.1.11937.1.42.1.3.1 LINK-3-UPDOWN
```

Valid characters include alphanumeric, dash (-), slash (/), colon (:), and underscore(_).

See the HP Network Node Manager i Software-HP ArcSight Logger Integration Guide for more information.

Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)

When configuring incidents, NNMi provides the Category and Family attributes to help you organize your incidents.

Preconfigured Categories

The Category attribute helps you organize your incidents. Select the category that you want to be associated with this type of incident when it appears in an incident view. Each of the possible Category values is described in the following table.

Incident Categories Provided by NNMi

Category	Description
Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.
Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Track Your NNMi

Incident Categories Provided by NNMi, continued

Category	Description
	Licenses" on page 1604 or "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).
Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.
Fault	Indicates a problem with the network, for example Node Down.
Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .
Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.
Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.

Note: You can add your own Category entries to NNMi. See ["Create an Incident Category \(Management Events\)" on page 1245](#) for more information.

You can use **Family** attribute values to further categorize the types of incidents that might be generated. Each of the possible values are described in the following table.

Incident Family Attribute Values Provided by NNMi

Family	Description
Address	Indicates the incident is related to an address problem.
Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .
BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Chassis	Indicates the incident is related to a chassis problem.
Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.
Connection	Indicates the incident is related to a problem with one or more connections.
Correlation	Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.
Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.
HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).
Interface	Indicates the incident is related to a problem with one or more interfaces.
IP Subnet	Indicates the incident is related to a problem with the IP Subnet.
License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .
NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.
Node	Indicates the incident is related to a node problem.
OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RAMS	Indicates the incident is related to a Router Analytics Management System problem.
RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.

¹Hot Standby Router Protocol

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.
System and Applications	Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.
Trap Analysis	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</div> <div>Indicates the incident is related to an SNMP trap storm.</div>
VLAN	Indicates the incident is related to a problem with a virtual local area network.
VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).

Note: You can add your own Family entries to NNMi. See "[Create an Incident Family \(Syslog Message\) \(HP ArcSight\)](#)" on the [next page](#) for more information.







Create an Incident Category (Syslog Message) (HP ArcSight)

The Category attribute helps you organize your incidents. Create any Category that makes sense to you and your team. For a list of the Category codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(Syslog Message\) \(HP ArcSight\)](#)" on page 1074.


To create a new incident Category:

1. Navigate to the **Incident Category** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:

¹Virtual Router Redundancy Protocol

- To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
- e. In the configuration form, locate the **Category** attribute.
- f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the previous form.

Category Code Attributes







Name	Description
Label	Incident category name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Alpha-numeric, spaces, and underline characters are permitted.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trapConf.category.<category_Label> com.<your_company_name>.nnm.eventConf.category.<category_Label> com.<your_company_name>.nnm.inciConf.category.<category_Label></pre> <p>The maximum length is 80 characters. Alpha-numeric characters and periods are permitted. Spaces are not permitted.</p>

Create an Incident Family (Syslog Message) (HP ArcSight)


The Family attribute helps you organize your incidents. Create any Family that makes sense to you and your team. For a list of the Family codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(Syslog Message\) \(HP ArcSight\)](#)" on page 1074.

To create a new incident Family:

1. Navigate to the **Incident Family** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.

- b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
 - e. In the configuration form, locate the **Family** attribute.
 - f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
 3. Click  **Save and Close** to save your changes and return to the previous form.

Family Attributes

Name	Description
Label	Family name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Any character type is valid.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trapConf.family.<family_label> com.<your_company_name>.nnm.eventConf.family.<family_label> com.<your_company_name>.nnm.inciConf.family.<family_label></pre> <p>The maximum length is 80 alpha-numeric characters, periods allowed, no spaces allowed.</p>

Specify the Incident Severity (Syslog Message) (HP ArcSight)

The incident severity represents the seriousness calculated for the incident. Use the severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described in the following table.

Incident Severity Values

Attribute	Description
Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.
Warning	Indicates there might be a problem related to the associated object.
Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.
Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.
Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.

See ["Monitor Incidents for Problems"](#) for more information about these severity values.

Specify Your Incident Message Format (Syslog Message) (HP ArcSight)

When configuring an incident, specify the information you want NNMi to include in the incident's Message attribute value. You can use any combination of valid parameter strings and Custom Incident attributes to configure the Message.

Note: The incident Message limit is 1024 characters. If the returned values exceed this limit, NNMi truncates the value starting from the end of the returned text string.

["Valid Parameters for Configuring Incident Messages \(Syslog Message\) \(HP ArcSight\)"](#) below

["Include Custom Incident Attributes in Your Message Format \(Syslog Message\) \(HP ArcSight\)"](#) on page 1087

Valid Parameters for Configuring Incident Messages (Syslog Message) (HP ArcSight)

When configuring incident messages, consider using incident information as part of the message. NNMi provides the following parameter values. Use these parameters as variables when formatting an incident message.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See "[Specify Your Incident Message Format \(Syslog Message\) \(HP ArcSight\)](#)" on the previous page for more information about configuring messages.

Parameter strings are available for the following:

Note: See the following tables to view the valid parameters for incidents generated from Custom Polled Instances: [Parameter Strings for all Incidents \(Attributes from an Incident form\)](#), [Parameter Strings for Node Source Objects \(Attributes from a Node form\)](#), and the [Parameter Strings for all Incidents \(Attributes not Visible from any form\)](#).

- Parameter strings for all incidents (Incident form attributes) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Incident form attributes)

Parameter String	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$sev, \$severity	Value of the Severity attribute of the Incident form.

- Parameter Strings for Node Source Objects (Node form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Node Source Objects (Node form attributes)

Parameter String	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's

Parameter Strings for Node Source Objects (Node form attributes) , continued

Parameter String	Description
	form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

- Parameter Strings for Interface Source Objects (Interface form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Interface Source Objects (Interface form attributes)

Parameter String	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.

Parameter Strings for Interface Source Objects (Interface form attributes) , continued

Parameter String	Description
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.
\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.

- Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes)

Parameter String	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

- Parameter strings for VLAN Source Objects (VLAN form attributes) ([Click here for a list of choices.](#))

Parameter Strings for VLAN Source Objects (VLAN form attributes)

Parameter String	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the VLAN Name attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Ports tab of the Interface form. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.

- Parameter Strings for all incidents (Additional information that is not visible in any form) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Attributes not visible in any form)

Parameter String	Description
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	<p>If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection:</p> <p>The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name>[interface_name]</i></p>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source

Parameter Strings for all Incidents (Attributes not visible in any form), continued

Parameter String	Description
	node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name <code>4/1</code> as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances.
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

- Information established in Custom Incident Attributes ([Click here for a list of choices.](#))

Parameter Strings for Attributes Established in Custom Incident Attributes

Parameter String	Description
\$<position _number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: <code>\$1</code> NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_ name>	Value of the name that is used for the custom incident attribute. For example, <code>\$mycompany.mycia</code> . NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_ _	Value of the object identifier for any custom incident attribute that originated as a

Parameter Strings for Attributes Established in Custom Incident Attributes, continued

Parameter String	Description
oid>	varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: <code><CIA_name>:<CIA_value></code> in which the custom incident attribute name appears followed by the custom incident attribute value.

- Functions to generate values ([Click here for a list of choices.](#))

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the `nnmloadmib.ovpl` command.

Functions to Generate Values Within the Incident Message

Function	Description
\$oidtext (\$<position_ number>)	<p>A <code><position_number></code> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, <code>\$oidtext(\$2)</code>.</p> <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: The position number you enter must represent a CIA that contains an Object Identifier (OID) value.</p> </div> <p>NNMi returns the textual value of the OID for the CIA specified.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ If the MIB is not loaded, NNMi returns the numeric OID value. ■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$oidtext (\$<CIA_ oid>)	<p>The <code><CIA_oid></code> argument specifies the Object Identifier (OID) for any custom incident attribute that originated as a varbind. For example, <code>\$oidtext (\$.1.3.6.1.6.3.1.1.5.1.)</code> Use this argument to the <code>\$oidtext()</code> function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the textual value of the OID you specify.</p>

Functions to Generate Values Within the Incident Message, continued

Function	Description
	<p>Note the following:</p> <ul style="list-style-type: none">■ If the MIB is not loaded, NNMi returns the numeric OID value.■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$text (\$<position_ number>)	<p>The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>
\$text (\$<CIA_ oid>)	<p>The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>

Include Custom Incident Attributes in Your Message Format (Syslog Message) (HP ArcSight)

NNMi includes two categories of CIAs:

- SNMP trap varbinds identified by the Abstract Syntax Notation value (ASN.1). NNMi turns varbinds into CIAs and maintains each varbind's position number. See ["Load SNMP Trap Incident Configurations" on page 873](#).
- Custom incident attributes provided by NNMi. See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

You cannot create Custom Incident Attributes.

You can use CIAs in your message format to extend the amount of information presented. To determine which CIAs are available for any particular incident type, open an Incident view, locate the incident and open the [Incident form](#). Navigate to the **Custom Attributes** tab. A complete list of available CIAs (for that incident type) appears in the table.

To include a CIA in your message format, type the dollar-sign character (\$) plus any of the following:

- Varbind position number or asterisk (*) to include all varbind values
- Name of the CIA
- Object identifier (oid) of the CIA (useful when the varbind position number is not consistent among vendors)

Note: A single incident cannot include two CIAs with the same name. However, two incidents can contain CIAs having the same names and values.

The following table presents some example formats with the subsequent output.

Example Incident Message Formats

Example Message Format	Output in Incident View
Possible trouble with \$3	Possible trouble with <varbind 3>
Possible trouble with \$11	Possible trouble with <varbind 11>
Possible trouble with \$77 (where the varbind position 77 does not exist)	Possible trouble with <Invalid or unknown cia> 77
Possible trouble with \$*	Possible trouble with <cia1_name: cia_value>, <cia2_name: cia_value>, <cia3_name: cia_value>
Possible trouble with \$3x	Possible trouble with <varbind 3>x
Possible trouble with \$1.2.3.4.5	Possible trouble with <value of the CIA with oid of 1.2.3.4.5>
Possible trouble with \$cia.sourceObject.Ucmdbld	Possible trouble with <value of the CIA with name of cia.sourceObject.Ucmdbld>

Tip: NNMi provides an error message when a CIA cannot be found. For example, if you enter an unavailable varbind position, name, or object identifier (oid), NNMi returns an "Invalid or unknown cia" error message.

Specify a Description for Your Incident Configuration (Syslog Messages)(HP ArcSight)

NNMi provides the Description attribute to help you further identify the current incident configuration.

Description

Use the description field to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.

Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure Interface Settings for a Syslog Message Incident (HP ArcSight)

Note: Interface Settings override any other Suppression, Enrichment, Dampen, or Actions settings for this incident, including those configured on the Node Settings tab.





NNMi enables you to apply an incident configuration to a Source Object based on the Source Object's participation in an Interface Group. If the Source Object is not a member of the Interface Group specified, the incident is neither displayed nor stored in the NNMi database


Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.

For information about each Interface Settings tab:



For information about each Syslog Message tab:

To apply an incident configuration to a Source Object based on the Source Object's Interface Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Configure the desired Interface Settings (see [table](#)).

5. Configure any Suppression, Dampen, or Enrichment settings for this Interface Group.
6. Click  **Save and Close** to save your changes and return to the previous form.

Interface Group Attributes

Name	Description
Interface Group	Click the  ▾ Lookup icon and select  Quick Find to select the Interface Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those interfaces that appear in multiple Interface Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If an interface is in multiple Interface Groups and more than one of those Interface Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the interface.
Enable	Use this attribute to temporarily disable an incident's configuration settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Related Topics

["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#)

Configure Incident Suppression Settings for an Interface Group (Syslog Message)(HP ArcSight)

Note: Interface Settings override any other Suppression settings for this incident, including those from the Node Settings tab.






NNMi enables you to suppress a specified incident configuration based on the Source Object's participation in an Interface Group.

Note: You can also suppress the incident configuration based on the Source Node's participation in a Node Group. See ["Configure Incident Suppression Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1134](#) for more information.

Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.

For information about each Interface Settings tab:

To suppress an incident configuration based on an Interface Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit a configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See "[Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)](#)" on page 1089 for more information.
5. Select the **Suppression** tab.
6. Configure the desired Suppression behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings for the specified Interface Group:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p>







Interface Settings Suppression Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression <code>\Q.1.3.6.1.4.1.9.9\E.*</code> and has a value of 25. ■ Contain a varbind whose OID matches the regular expression <code>\Q.1.3.6.1.2.1.2.2.1.1.3\E.*</code> and has a value of 3.

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Settings <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. 						




Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. 				

Interface Settings Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribut- e	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribut- e	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="548 453 974 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="565 743 1318 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="565 1425 1331 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Suppression Attributes , continued

Name	Description																		
	<div>Payload Filter Editor Settings, continued</div> <table><tr><th>Attribut- e</th><th>Description</th></tr><tr><td>Value</td><td><p>The value for which you want NNMi to search.</p><p>Note the following:</p><ul style="list-style-type: none">• The values you enter are case sensitive.• NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.• The between, in and not in operators require that each value be entered on a separate line.</td></tr></table> <div>Payload Filter Editor Buttons</div> <table><tr><th>Button</th><th>Description</th></tr><tr><td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr><tr><td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr><tr><td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr><tr><td>AND</td><td><p>Inserts the AND Boolean Operator in the selected cursor location.</p><div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div></td></tr><tr><td>OR</td><td><p>Inserts the OR Boolean Operator in the current cursor location.</p><div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div></td></tr><tr><td>NOT</td><td><p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p><p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p></td></tr></table>	Attribut- e	Description	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The values you enter are case sensitive.• NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.• The between, in and not in operators require that each value be entered on a separate line.	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>	OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>	NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>
Attribut- e	Description																		
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none">• The values you enter are case sensitive.• NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.• The between, in and not in operators require that each value be entered on a separate line.																		
Button	Description																		
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.																		
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.																		
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.																		
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>																		
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>																		
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>																		

Interface Settings Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Enrichment Settings for an Interface Group (Syslog Message)(HP ArcSight)

Note: Interface Settings override any other Enrichment settings for this incident, including those from the Node Settings tab.

NNMi enables you to fine tune and enhance a specified incident configuration based on the Source Object's participation in an Interface Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To




Note: You can also enhance the incident configuration based on the Source Node's participation in a Node Group. See ["Configure Incident Enrichment Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1143](#) for more information.






Tip: See [Create Interface Groups](#) for more information about Interface Groups.

For information about each Interface Settings tab:

For information about each Enrichment tab:

To enrich an incident configuration based on an Interface Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Enrichment Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p>

















Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Address • Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.) • Card • Connection • Correlation • Interface • Node <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.</p>
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<p>the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in</p>

Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<p>an incident view.</p> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (Syslog Message) (HP ArcSight)" on page 1080</p> <p>"Include Custom Incident Attributes in Your Message Format (Syslog Message) (HP ArcSight)" on page 1087</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (Syslog Message)(HP ArcSight)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.










When creating a CIA for an incident configuration, you can specify any of the following values:



- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select **Interface Settings**.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure you configure the Enrichment settings. See ["Configure Incident Enrichment Settings for an Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1099](#) for more information.
8. Navigate to the **Custom Incident Attributes** tab.
9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.

- c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.
10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).
11. Click  **Save and Close** to save your changes and return to the previous form.

Custom Incident Attribute








Name	Description
Custom Incident Attribute Name	Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
Type	Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are: <ul style="list-style-type: none">• Node Custom Attribute• Interface Custom Attribute
Custom Attribute Name	Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following: <ul style="list-style-type: none">• Name of the Custom Attribute on the source node• Name of the Custom Attribute on the interface (source object)

Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (Syslog Message) (HP ArcSight)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure you configure the Enrichment settings. See ["Configure Incident Enrichment Settings for an Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1099](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())
 - c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, AND, NOT

Filter String: (AND NOT ())

Options: Insert, AND, OR, NOT, EXISTS, NOT EXISTS, Delete

Highlight the location in the logic flow, then click Insert to define the filter requirement

10. Click **Save and Close**.

11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6.


Payload Filter Editor Settings, continued

Attribute	Description												
	<ul style="list-style-type: none"> • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between <div data-bbox="449 957 878 1075" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="466 1228 1320 1291" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="449 1554 839 1690" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </table> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="466 1812 1320 1843" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate</p> </div> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="469 573 1318 638"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 892" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1362 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1344 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1087 1339 1155"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1276 1295 1339">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1373 1362 1436">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1463 938 1495">The value for which you want NNMi to search.</p> <div data-bbox="435 1539 1369 1885"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for an Interface Group (Syslog Message) (HP ArcSight)

Note: Interface Settings override any other Dampening settings for this incident, including those from the Node Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Object's participation in an Interface Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

- Appearance within Incident views in the NNMi Console

Note: You can also configure the Dampening settings based on the Source Node's participation in a Node Group. See "[Configure Incident Dampening Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)](#)" on page 1157 for more information.

Tip: See "[Create Interface Groups](#)" on page 356 for more information about Interface Groups.

For information about each Interface Settings tab:







When using the Dampening configuration, note the following:

- NNMi initially assigns incidents with Dampening settings configured a Lifecycle State of DAMPENED.
- After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure the Dampening settings based on an Interface Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
 3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
 4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.
 5. Select the **Dampening** tab.
 6. Configure the desired Dampening behavior (see [table](#)).
 7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Dampening Configuration Attributes

Name	Description
Enable	Use this attribute to temporarily disable an incident's dampening settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	Specifies the number of minutes to be used for the dampen interval. Note: The maximum dampen interval is 60 minutes.
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class).

Interface Settings Dampening Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none"> You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. View the expression displayed under Filter String to see the logic of the expression as it is created. The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression <code>\Q.1.3.6.1.4.1.9.9\E.*</code> and has a value of 25. Contain a varbind whose OID matches the regular expression <code>\Q.1.3.6.1.2.1.2.2.1.1.3\E.*</code> and has a value of 3.

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings	
Attribute	Description
Attribute	<p>The attribute name on which NNMI searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.




Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. 				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribute	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="553 453 977 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="553 453 977 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="553 453 977 588">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
Value	<p>The value for which you want NNMI to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMI displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMI should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMI includes interfaces with (interface description) ifDesc containing</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						


Configure Incident Actions for an Interface Group (Syslog Message) (HP ArcSight)

Note: Interface Settings override any other Actions settings for this incident, including those from the Node Settings tab.

For information about each Interface Settings tab:

NNMi enables you to configure incident actions based on a Source Object's participation in an Interface Group.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.





Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.





You can configure actions for incidents generated from SNMP traps, Syslog Messages (HP ArcSightonly), and the NNMi Management Events. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See ["Configure Actions for a Syslog Message Incident \(HP ArcSight\)" on page 1217](#) for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)" on page 1219](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:

1. Navigate to the **Syslog Message Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.




5. Select the **Actions** tab.
6. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
7. In the "[Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)](#)" on page 1219, provide the required information.
8. Click  **Save and Close** to save your changes and return to the previous form.




The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Configure a Payload Filter for an Incident Action (Interface Settings) (Syslog Message) (HP ArcSight)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:

- a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1089](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:
 - a. To create an Action configuration, click the  New icon, and continue.
 - b. To edit an Action configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete an Action configuration, select a row, and click the  Delete icon.
7. Make sure the Action settings are configured. See ["Configure Incident Actions for an Interface Group \(Syslog Message\) \(HP ArcSight\)" on page 1123](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, NOT

Filter String: AND NOT ()

Operator List: Insert, AND, OR, NOT, EXISTS, NOT EXISTS, Delete

Annotation: Highlight the location in the logic flow, then click Insert to define the filter requirement

10. Click **Save and Close**.

11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an


Payload Filter Editor Settings, continued

Attribute	Description												
	<p>example.</p> <p>Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between <div data-bbox="446 919 873 1039" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>between</td> <td>1</td> </tr> <tr> <td></td> <td>4</td> </tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="462 1192 1320 1260" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="446 1518 836 1654" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>in</td> <td>4</td> </tr> <tr> <td></td> <td>5</td> </tr> </tbody> </table> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="462 1774 1320 1841" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="469 573 1318 638"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 892" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1362 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1343 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1089 1341 1155"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1276 1295 1339">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1373 1362 1436">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1463 938 1495">The value for which you want NNMi to search.</p> <div data-bbox="435 1539 1352 1885"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. • The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Node Settings for a Syslog Message Incident (HP ArcSight)

Note: Node Settings override any other Suppression, Enrichment, Dampen, Action, or Diagnostics Selections configuration settings, except those configured on the Interface Settings tab.






NNMi enables you to apply an incident configuration to a Source Node based on the Source Node's participation in a Node Group. If the Source Node is not a member of the Node Group specified, the incident is neither displayed nor stored in the NNMi database.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.



For information about each Node Settings tab:

For information about each Syslog Message tab:

To apply an incident configuration to a Source Node based on the Source Node's Node Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Configure the desired Node Settings (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the previous form.

Node Group Attributes

Name	Description
Node Group	Click the  Lookup icon and select  Quick Find to select the Node Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those nodes that appear in multiple Node Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If a node is in multiple Node Groups and more than one of those Node Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the node.
Enable	Use this attribute to temporarily disable an incident's suppression settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Configure Incident Suppression Settings for a Node Group (Syslog Message) (HP ArcSight)

Note: Node Settings override any other Suppression settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to suppress a specified incident configuration based on the Source Node's participation in a Node Group.





Note: You can also suppress the incident configuration based on the Source Object's participation in an Interface Group. See ["Configure Incident Suppression Settings for an Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1090](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

To suppress an incident configuration based on a Node Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
 3. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#) for more information.
 5. Select the **Suppression** tab.
 6. Configure the desired Suppression behavior (see [table](#)).
 7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <p>AND</p>




Node Settings Suppression Attributes , continued

Name	Description						
	<p>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</p> <p>NNMi evaluates the expression above as follows:</p> <p>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</p> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <p>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</p> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. 						

Node Settings Suppression Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="550 1614 979 1730"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="550 1614 979 1730"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4
Attribute	Description										
	<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="550 1614 979 1730"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of</i></p> </td></tr> </table>	Attribut- e	Description		<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of</i></p>
Attribut- e	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of</i></p>				

Node Settings Suppression Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribut- e	Description		<p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	not in	1		2
Attribut- e	Description								
	<p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	not in	1		2				
not in	1								
	2								

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribut- e	Description		<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.
Attribut- e	Description						
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 						

Node Settings Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component</p>

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> </td></tr> </table>	Button	Description		<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>
Button	Description						
	<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>						

Node Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued						
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td><div>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</div><div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div></td></tr><tr><td>Delete</td><td><div>Deletes the selected expression.</div><div>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</div></td></tr></table>	Button	Description		<div>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</div> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>	Delete	<div>Deletes the selected expression.</div> <div>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</div>
	Button	Description					
	<div>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</div> <div>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</div>						
Delete	<div>Deletes the selected expression.</div> <div>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</div>						

Configure Incident Enrichment Settings for a Node Group (Syslog Message) (HP ArcSight)

Note: Node Settings override any other Enrichment settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to enhanced a specified incident configuration based on the Source Node's participation in a Node Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To

Note: You can also enhance the incident configuration based on the Source Object's participation in an Interface Group. See ["Configure Incident Enrichment Settings for an](#)










[Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1099](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

For information about each Enrichment tab:

To configure Enrichment settings for a Node Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.









Node Settings Enrichment Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none">• Address• Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.)• Card• Connection• Correlation• Interface• Node











¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Node Settings Enrichment Configuration Attributes , continued

Name	Description
	See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <p>Tip: When using Incident views:</p>

Node Settings Enrichment Configuration Attributes , continued

Name	Description
	<div> <ul style="list-style-type: none"> ■  Root Cause value = determined by NNMi's Causal Engine ■  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none"> •  Secondary Root Cause •  Symptom •  Stream Correlation •  Service Impact •  Dedup Stream Correlation •  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <div> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> </div> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (Syslog Message) (HP ArcSight)" on page 1080</p> <p>"Include Custom Incident Attributes in Your Message Format (Syslog Message) (HP ArcSight)" on page 1087</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <div> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p> </div>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p>

Node Settings Enrichment Configuration Attributes , continued

Name	Description
	Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (Syslog Message) (HP ArcSight)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.






When creating a CIA for an incident configuration, you can specify any of the following values:








- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#) for more information.

5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure the Enrichment settings are configure. See ["Configure Incident Enrichment Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1143](#) for more information.
8. Navigate to the **Custom Incident Attributes** tab.
9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.
 - c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.
10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).
11. Click  **Save and Close** to save your changes and return to the previous form.

Custom Incident Attribute

Name	Description
Custom Incident Attribute Name	<p>Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <div>Note: Make sure to note this name if you plan to filter on the value using the Payload Filter tab. See "Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (Syslog Message) (HP ArcSight)" on the next page for more information.</div>
Type	<p>Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are:</p> <ul style="list-style-type: none">• Node Custom Attribute• Interface Custom Attribute
Custom Attribute Name	<p>Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following:</p>






Custom Incident Attribute , continued




Name	Description
	<ul style="list-style-type: none">• Name of the Custom Attribute on the source node• Name of the Custom Attribute on the interface (source object)

Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (Syslog Message) (HP ArcSight)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  **New** icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  **Open** icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  **Delete** icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  **New** icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Node Setting behavior. See "[Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)](#)" on page 1133 for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:


- a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure you configure the Enrichment settings. See ["Configure Incident Enrichment Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1143](#) for more information.
 8. Select the **Payload Filter** tab.
 9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:



The screenshot shows the **Filter Editor** interface. At the top, there are three input fields: **Attribute** (containing 'ciaName'), **Operator** (containing '='), and **Value** (containing '.1.3.6.1.4.1.9.9.13.1.2.1.7'). To the right of these fields are three buttons: **Append**, **Insert** (highlighted with a red box), and **Replace**. Below these fields is a logic flow diagram. It starts with a blue box labeled **AND**, followed by a bracketed section containing **AND** and **NOT**. A red arrow points from the **Insert** button to the first opening parenthesis in the **Filter String** at the bottom, which is **((AND NOT ())**. Another red arrow points from the text 'Highlight the location in the logic flow, then click Insert to define the filter requirement' to the first opening parenthesis. To the right of the logic flow diagram is a vertical list of buttons: **Insert** (with a dropdown arrow), **AND**, **OR**, **NOT**, **EXISTS**, **NOT EXISTS**, and **Delete**.

10. Click  **Save and Close**.

11. Click  **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • <code>ciaName</code> • <code>ciaValue</code>
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 436"> <p>The screenshot shows a table with two columns: 'Operator' and 'Value'. Under 'Operator', the word 'between' is selected in a dropdown menu. Under 'Value', the numbers '1' and '4' are entered on separate lines.</p> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="467 590 1320 653"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <div data-bbox="451 915 839 1050"> <p>The screenshot shows a table with two columns: 'Operator' and 'Value'. Under 'Operator', the word 'in' is selected in a dropdown menu. Under 'Value', the numbers '4' and '5' are entered on separate lines.</p> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="467 1173 1320 1236"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.

Payload Filter Editor Settings, continued

Attribute	Description				
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: ciaValue not in <div data-bbox="446 1197 873 1331" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>not in</td> <td>1 2</td> </tr> </tbody> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. 	Operator	Value	not in	1 2
Operator	Value				
not in	1 2				

Payload Filter Editor Settings, continued

Attribute	Description
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <p>Note:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	Appends, Inserts, or replaces the OR Boolean Operator in the current cursor

Additional Filters Editor Buttons, continued

Button	Description
	<p>location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for a Node Group (Syslog Message) (HP ArcSight)

Note: Node Settings override any other Dampening settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Node's participation in a Node Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

- Appearance within Incident views in the NNMi Console

Note: You can configure the Dampening settings based on the Source Object's participation in an Interface Group. See "[Configure Incident Dampening Settings for an Interface Group \(Syslog Message\) \(HP ArcSight\)](#)" on page 1114 for more information.

Tip: See "[Create Node Groups](#)" on page 326 for more information about Node Groups.






For information about each Node Settings tab:


When using the Dampening configuration, note the following:

- NNMi initially assigns incidents with Dampening settings configured a Lifecycle State of DAMPENED.
- After the dampen interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure the Dampening settings based on a Node Group:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.

4. Make sure you configure the basic Node Setting behavior. See "[Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)](#)" on page 1133 for more information.
5. Select the **Dampen** tab.
6. Configure the desired Dampen behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Dampen Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's Dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	<p>Specifies the number of minutes to be used for the dampen interval.</p> <p>Note: The maximum dampen interval is 60 minutes.</p>
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p>




Node Settings Dampen Attributes , continued

Name	Description						
	<p>AND</p> <p>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</p> <p>ciaValue = 5</p> <p>NNMi evaluates the expression above as follows:</p> <p>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</p> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ■ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. 						

Node Settings Dampen Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> • < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> • < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4
Attribute	Description										
	<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> • < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> • <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> • > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> • >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> • between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Dampen Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. </td></tr> </table>	Attribute	Description		<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information.
Attribute	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. 				

Node Settings Dampen Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a</p> </div> </td></tr> </table>	Attribute	Description		<p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a</p> </div>	not in	1		2
Attribute	Description								
	<p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a</p> </div>	not in	1		2				
not in	1								
	2								

Node Settings Dampen Attributes , continued

Name	Description						
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. </td></tr> </table>	Attribute	Description		<p>separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.
Attribute	Description						
	<p>separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. 						

Node Settings Dampen Attributes , continued

Name	Description																
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> The between, in and not in operators require that each value be entered on a separate line. 												
Attribute	Description																
	<ul style="list-style-type: none"> The between, in and not in operators require that each value be entered on a separate line. 																
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>OR</td><td> Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>NOT</td><td> Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>EXISTS</td><td>Used for filters that include Capabilities or Custom Attribute names</td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	EXISTS	Used for filters that include Capabilities or Custom Attribute names
Button	Description																
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.																
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.																
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.																
AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
EXISTS	Used for filters that include Capabilities or Custom Attribute names																

Node Settings Dampen Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> </div> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are</p> </div> </td></tr> </table>	Button	Description		<p>and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> </div> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are</p> </div>
Button	Description						
	<p>and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> </div> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are</p> </div>						

Node Settings Dampen Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Actions for a Node Group (Syslog Message) (HP ArcSight)

For information about each Node Settings tab:

Note: Node Settings override any other Actions settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to configure incident actions based on a Source Node's participation in a Node Group.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.




Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.




You can configure actions for incidents generated from SNMP traps, Syslog Messages (HP ArcSight only) and the NNMi Management Events. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)" on page 1219](#) for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(Management Events\)" on page 1386](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:

1. Navigate to the **Syslog Message Configuration** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#) for more information.
5. Select the **Actions** tab.
6. From the **Lifecycle Actions** table toolbar, do one of the following:




- To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, double-click the row representing the configuration you want to edit, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
7. In the "[Lifecycle Transition Action Form \(Management Events\)](#)" on page 1386, provide the required information.
 8. Click  **Save and Close** to save your changes and return to the **Syslog Message Configuration** form.






The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Configure a Payload Filter for an Incident Action (Node Settings) (Syslog Message) (HP ArcSight)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:

- a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Syslog Message Incident \(HP ArcSight\)" on page 1133](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:
 - a. To create an Action configuration, click the  New icon, and continue.
 - b. To edit an Action configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Action configuration, select a row, and click the  Delete icon.
7. Make sure the Action settings are configured. See ["Configure Incident Actions for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1167](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: Operator:

Append Insert Replace

AND AND NOT

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String: (AND NOT ())

Insert AND OR NOT EXISTS NOT EXISTS Delete

10. Click **Save and Close**.

11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an


Payload Filter Editor Settings, continued

Attribute	Description												
	<p>example.</p> <p>Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="451 926 878 1041"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="467 1199 1320 1262"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <div data-bbox="451 1524 841 1656"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </tbody> </table> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="467 1780 1320 1843"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="469 573 1318 638" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 890" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1362 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1344 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1087 1339 1155" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1274 1295 1337">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1371 1362 1434">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1461 938 1493">The value for which you want NNMi to search.</p> <div data-bbox="435 1518 1370 1885" style="background-color: #f0f0f0; padding: 10px;"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Diagnostics Selections for a Node Group (Syslog Message) (HP ArcSight)






For information about each Node Settings tab: .





Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

Note: Node Settings override any other Diagnostics Selections settings for this incident, except those configured on the Interface Settings tab.

The Diagnostic Selections form enables you to configure NNMi to automatically gather NNM iSPI NET diagnostic information for the Incident you are configuring. When using this form, you specify the diagnostics you want to run on each applicable node in the specified Node Group.

To configure Diagnostics to run on a Source Node for an incident:

1. Navigate to the **Diagnostics Selection** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - To create an Incident configuration, click the  New icon.
 - To edit an Incident configuration, select a row, click the  Open icon, and continue.
 - e. Navigate to **Node Settings** tab, and do one of the following:
 - To create a Node Settings configuration, click the  New icon.
 - To edit a Node Settings configuration, select a row, click the  Open icon, and continue.
 - To delete a Node Settings configuration, select the Node setting, and click the  Delete icon.
 - f. Navigate to the **Diagnostic Selection** tab, and do one of the following:

- To create a Diagnostic Selection setting, click the  New icon, and continue.
 - To edit a Diagnostic Selection setting, select a row, click the  Open icon, and continue.
 - To delete a Diagnostic Selection setting, select a row, and click the  Delete icon.
2. Provide the required information (see [table](#)).
 3. Click  **Save and Close** to save your changes and return to the previous form.

After you configure the Diagnostic for the incident and Node Group, the Diagnostic must match the following criteria before the Diagnostic runs:

- The Source Node must be in the specified Node Group.
- The Diagnostic must be valid for the Source Node. (For example, only Nortel switch Diagnostics are run on Nortel switches.)
- The incident's current lifecycle state must match a lifecycle state for which it was configured. (For example, if you configure the Incident to run a specified Diagnostic when the incident is Closed, then if the current Incident's Lifecycle State is Closed, NNMi runs that Diagnostic.)

Note: If a Source Node is in more than one Node Group, the Diagnostic is only run on the node the first time NNMi finds a match for that Source Node based on the configuration Ordering field.


If these criteria are met, NNM iSPI NET runs the Diagnostics and generates Diagnostic reports to help you solve the problem on the Source Node.

After you configure Diagnostics for an incident, you can also run Diagnostics and access the Diagnostics reports on demand, using **Actions** → **Run Diagnostics** in the Incident form. The same criteria apply (see the [criteria](#) above). See [Incident Form:Diagnostics Tab](#) for more information.



Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

You can also run and access Diagnostics reports from a Node form. See [Node Form: Diagnostics Tab](#) for more information.

Diagnostic Settings Attributes

Attribute	Description
Flow Definition	Select the Diagnostic (Flow Definition) you want to use for the specified Node Group. Click the  Lookup icon and choose one of the following options:

Diagnostic Settings Attributes, continued

Attribute	Description
	<ul style="list-style-type: none">  Show Analysis to display Analysis Pane information for the Flow Definition name displayed. (See Use the Analysis Pane for more information about the Analysis Pane.)  Quick Find to view the list of possible diagnostic Flow Definitions. <p>NNMi provides diagnostics for the following types of devices:</p> <ul style="list-style-type: none"> ■ Cisco switch ■ Cisco router ■ Cisco switch/router ■ Nortel switch <p>See "Diagnostics (Flows) Provided by NNM iSPI NET" on page 859 for more information about the diagnostics provided and the devices to which they apply.</p>
Lifecycle State	<p>Incident Lifecycle State of the target Incident.</p> <p>If the incident's Lifecycle State matches the value specified here, the Diagnostic runs.</p> <p>The Diagnostic automatically runs on each applicable Source Node in the specified Node Group if the incident has the Lifecycle State currently configured in this attribute of the Diagnostic (Flow Definition - set of automated commands).</p>
Enable	<p>Use this attribute to temporarily disable an incident's Diagnostics settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>

Configure Suppression Settings for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message tab:

NNMi enables you to suppress incidents based on Interface Group, Node Group, or default Suppression settings. NNMi applies your Suppression settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)

3. Suppression configuration settings without specifying an Interface Group or Node Group
(Management Event Configuration Form: Suppression tab)

A Payload Filter enables you to use the data that is included with any of the following items before they are stored as incidents in NNMi:





- Traps generated from an SNMP agent
- Syslog messages generated from ArcSightEvent (HP ArcSight only)
- Management incidents that are generated by NNMi

Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as CIA (Custom Incident Attribute) names and values. For example, you might want NNMi to suppress a particular status change notification trap for a specified Node Group or Interface Group. To do so, you could include the name of the trap varbind that stores this information as well as the particular status change value string the traps that you want to suppress should contain.

See ["Configure Incident Suppression Settings for an Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1090](#) for information about how to suppress an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Suppression Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1134](#) for more information about how to suppress an incident for a Node Group with or without a Payload Filter.

To configure suppression for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Suppression** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example:

Suppression Attributes , continued

Name	Description						
	<p>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</p> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ■ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind 						




Suppression Attributes , continued

Name	Description																
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>with a value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </table> <p>matches any incident with a varbind value of either 4 or 5.</p> </td></tr> </table>	Attribut- e	Description		<p>with a value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </table> <p>matches any incident with a varbind value of either 4 or 5.</p> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Attribut- e	Description																
	<p>with a value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </table> <p>matches any incident with a varbind value of either 4 or 5.</p> 	Operator	Value	between	1		4	Operator	Value	in	4		5				
Operator	Value																
between	1																
	4																
Operator	Value																
in	4																
	5																

Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a</p> </td></tr> </table>	Attribut- e	Description		<p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a</p>
Attribut- e	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a</p>				

Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 . • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>  matches any incident that contains a varbind with values other than 1 and 2. <div>Note: As shown in the example, each value must be entered on a separate line.</div><p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. </td></tr> </table>	Attribute	Description		<p>varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 . • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>  matches any incident that contains a varbind with values other than 1 and 2. <div>Note: As shown in the example, each value must be entered on a separate line.</div><p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>.
Attribute	Description				
	<p>varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 . • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>  matches any incident that contains a varbind with values other than 1 and 2. <div>Note: As shown in the example, each value must be entered on a separate line.</div><p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. 				

Suppression Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribute	Description		<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 				
Attribute	Description										
	<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>										
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 										
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td>Inserts the AND Boolean Operator in the selected cursor location.</td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	Inserts the AND Boolean Operator in the selected cursor location.
Button	Description										
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.										
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.										
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.										
AND	Inserts the AND Boolean Operator in the selected cursor location.										

Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi</p>

Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	Deletes the selected expression.

Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Buttons, continued				
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</td></tr></table>	Button	Description		Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.
Button	Description				
	Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.				

Configure Enrichment Settings for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message tab:

NNMi enables you to fine tune and enhance incidents based on Interface Group, Node Group, or default Enrichment settings. NNMi applies your Enrichment settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)
3. Enrich configuration settings without specifying an Interface Group or Node Group (Management Event Configuration Form: Enrichment tab)

The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To

Note: Any configuration you specify for Severity, Priority, or Message overrides those values provided in the Management Event Configuration Form: Basics information.

A Payload Filter enables you to use the data that is included with any of the following items before they are stored as incidents in NNMi:

- Traps generated from an SNMP agent
- Syslog messages generated from ArcSightEvent (HP ArcSight only)
- Management incidents that are generated by NNMi




Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as CIA (Custom Incident Attribute) names and values. For example, you might want NNMi to suppress a particular status change notification trap for a specified Node Group or Interface Group. To do so, you could include the name of the trap varbind that stores this information as well as the particular status change value string the traps that you want to suppress should contain.




Note: The CIA added to an incident must be provided by NNMi. You cannot create CIAs.

See ["Configure Incident Enrichment Settings for an Interface Group \(Syslog Message\)\(HP ArcSight\)" on page 1099](#) for information about how to enrich an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Enrichment Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)" on page 1143](#) for more information about how to enrich an incident for a Node Group with or without a Payload Filter.

To configure Enrichment settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Enrichment** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Provide the required information (see [table](#))
5. Click  **Save and Close** to save your changes and return to the previous form.






Enrichment Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none">• Address• Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation²)












¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.



Enrichment Attributes , continued

Name	Description
	<p>protocol. See Interface Form: Link Aggregation tab.)</p> <ul style="list-style-type: none"> • Card • Connection • Correlation • Interface • Node <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (Syslog Message) (HP ArcSight)" on page 1074 for more information.</p>
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>

Enrichment Attributes , continued

Name	Description
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none"> •  Info •  None •  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none"> ▪  Root Cause value = determined by NNMi's Causal Engine ▪  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none"> •  Secondary Root Cause •  Symptom •  Stream Correlation •  Service Impact •  Dedup Stream Correlation •  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> </div> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (Syslog Message) (HP ArcSight)" on page 1080</p> <p>"Include Custom Incident Attributes in Your Message Format (Syslog Message) (HP ArcSight)" on page 1087</p>
Assigned	Use to specify the owner of any incident generated for this incident configuration.

Enrichment Attributes , continued

Name	Description
To	<p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Dampening Settings for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message tab:

NNMi enables you to delay the following for an incident configuration based on the Source Object's participation in an Interface Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

- Appearance within Incident views in the NNMi Console

You can configure the Dampening settings based on Interface Group, Node Group, or default Dampening settings. NNMi applies your Dampening settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)
3. Dampening configuration settings without specifying an Interface Group or Node Group (Management Event Configuration Form: Dampening tab)

When using the Dampening configuration, note the following:

- Duplicate and Rate Correlation incidents inherit the Dampening settings from their Correlated Children. If the Correlated Children are Closed while Dampened, and therefore deleted, NNMi retains the parent Duplicate or Rate Correlation incident. See "[Correlate Duplicate Incidents \(Deduplication Configuration\)](#)" on page 745 and "[Track Incident Frequency \(Rate: Time Period and Count\)](#)" on page 746 for more information about Duplicate and Rate Correlation incidents.

Note: NNMi administrators can view the number of incidents Closed and deleted while dampened. Access the **Help** → **System Information** → **Health** tab, click the View Detailed Health Report button, and search for the word dampened.




- After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

See "[Configure Incident Dampening Settings for an Interface Group \(Syslog Message\) \(HP ArcSight\)](#)" on page 1114 for information about how to configure Dampening settings for an Interface Group with or without a Payload Filter.

See "[Configure Incident Dampening Settings for a Node Group \(Syslog Message\) \(HP ArcSight\)](#)" on page 1157 for more information about how to configure Dampening settings for a Node Group with or without a Payload Filter.

To configure Dampening settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create a configuration, click the  New icon, and continue.
 - ii. To edit configuration, double-click the row representing the configuration you want to edit, and continue.
 - iii. To delete a configuration, select a row, and click the  Delete icon.
2. Select the **Dampening** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Dampening Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's Dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the Dampen Interval.
Minutes	Specifies the number of minutes to be used for the Dampen Interval.
Seconds	Specifies the number of seconds to be used for the Dampen Interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> ■ Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). ■ You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. ■ Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. ■ View the expression displayed under Filter String to see the logic of the expression as it is created. ■ The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of</p>




Dampening Attributes , continued

Name	Description						
	<p>5.</p> <ul style="list-style-type: none"> ■ The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. ■ The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. ■ You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ○ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ○ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ != Finds all values not equal to the value specified. Click here for an 						

Dampening Attributes , continued

Name	Description										
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribute	Description		<p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4
Attribute	Description										
	<p>example.</p> <p>Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> ■ < Finds all values less than the value specified. Click here for an example. <p>Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6.</p> ■ <= Finds all values less than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6.</p> ■ > Finds all values greater than the value specified. Click here for an example. <p>Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4.</p> ■ >= Finds all values greater than or equal to the value specified. Click here for an example. <p>Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4.</p> ■ between Finds all values equal to and between the two values specified. Click here for an example. <p>Example: <code>ciaValue between</code></p> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Dampening Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>. </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.
Attribute	Description				
	<ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>. 				

Dampening Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </td></tr> </table>	Attribute	Description		<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p>	Operator	Value	not in	1 2
Attribute	Description								
	<p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="581 1436 1015 1570"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td>1 2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p>	Operator	Value	not in	1 2				
Operator	Value								
not in	1 2								

Dampening Attributes , continued

Name	Description						
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. </td></tr> </table>	Attribute	Description		<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed.
Attribute	Description						
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. 						

Dampening Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
	<ul style="list-style-type: none"> The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>

Dampening Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <div> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from</p> </div>

Dampening Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Deduplication for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message tab:



The deduplication configuration determines what values NNMi should match to detect when an SNMP Trap Incident, Syslog Message Incident (HP ArcSightonly), or Management Event is a duplicate.

Note the following:



- Suppression, Enrichment, and Dampening are not supported for Deduplication incidents.
- NNMi applies only one deduplication configuration per incident . If NNMi generates an incident using a specified deduplication configuration, NNMi continues to correlate duplicate incidents using the original configuration. To use a different deduplication configuration for an incident, first delete the current deduplication incident (created using the original deduplication configuration). NNMi generates the next deduplication incident according to the new deduplication configuration settings.
- NNMi continues to update the duplicate count regardless of an incident's lifecycle state. For example, if an incident's **Lifecycle State** is set to **Closed**, the duplicate count continues to be incremented. See [About the Incident Lifecycle](#) for more information. This behavior helps you identify situations in which the incident is not yet fixed. Take note if the Duplicate Count is incremented after a lengthy time period has elapsed, which might indicate there is a new problem with the node, interface, or address.
- Each time you stop and restart ovjboss, any incidents that have not yet been correlated or persisted are lost. This means that after a restart of ovjboss, an incoming incident might not be correlated as expected. For example, after a restart of ovjboss, a duplicate incident might not be correlated under its original parent incident. Instead, a new parent incident might be generated. See ["Stop or Start an NNMi Process" on page 87](#) for more information about starting and stopping the ovjboss process.
- If a Duplicate Correlation Incident is dampened, note the following:
 - Duplicate Correlation Incidents inherit the Dampening settings from its Correlated Children.
 - NNMi always retains the Parent Duplicate Correlation incident, even if its Child Incidents are Closed and subsequently deleted.

See ["Dampening Incident Configurations" on page 769](#) for more information about Dampening an incident configuration.

To specify or delete a deduplication configuration:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - i. To create a deduplication configuration, click the  New icon, and continue.
 - ii. To edit a deduplication configuration, select a row, click the  Open icon, and

continue.

- iii. To delete a deduplication configuration, select a row, and click the  Delete icon.
2. Select the **Deduplication** tab.
3. Provide the required information (see "Deduplication Attributes" table).
4. Click  **Save and Close** to save your changes and return to the previous form.

Deduplication Attributes

Name	Description
Enabled	<p>Use this attribute to temporarily disable an incident's deduplication configuration:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p> <p>Note: After a deduplication configuration is enabled, NNMi increments the Duplicate Count for an associated incident regardless of the Lifecycle State value. For example, if an incident's Lifecycle State is set to Closed, the duplicate count continues to be incremented. See About the Incident Lifecycle for more information.</p>
Count	Specifies the number of duplicate incidents for the current configuration that NNMi stores at one time. For example, if the Count is 10, after NNMi receives 10 duplicate incidents, NNMi deletes the first (oldest) duplicate incident and keeps the eleventh. (NNMi stores ten maximum.)
Hours	Used with the Minute and Second Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Hour Interval value is 1, and no Minute or Second Intervals are specified, and the duplicate incident is not generated within one hour, NNMi generates a new duplicate incident the next time it occurs.
Minutes	Used with the Hour and Second interval to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Minute Interval is 30 and no Hour or Second Intervals are specified, and the duplicate incident is not generated within 30 minutes, NNMi generates a new duplicate incident the next time it occurs.
Seconds	Used with the Hour and Minute Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Second Interval is 120 and no Hour or Minute Intervals are specified, and the duplicate incident is not generated within 120 seconds, NNMi generates a new duplicate incident the next time it occurs.
Parent Incident	Used to specify the Incident Configuration that will be the Parent Incident for the

Deduplication Attributes, continued

Name	Description
	<p>incident you are configuring. For example, you might have created a Management Event Incident Configuration that could be used as the Parent Incident for SNMP Trap Incidents.</p> <p>When specifying the Parent Incident, you have the following options:</p> <ul style="list-style-type: none"> When you want to use a configuration that NNMi provides, use the default Duplicate Correlation incident configuration . If you select this option, the incident message for the Parent Incident begins as follows: <p style="margin-left: 40px;">Duplicate Correlation for <incident_configuration_name></p> <p>For example if you are configuring a Node Down incident and select Duplicate Correlation as the Parent Incident, the Parent Incident message begins with: Duplicate Correlation for Node Down. Each Node Down incident that is a duplicate then appears correlated under the Duplicate Correlation for Node Down incident.</p> <ul style="list-style-type: none"> NNMi also enables you to customize the Parent Incident for a given deduplication scenario. If you have created a Management Event Incident Configuration to use for this deduplication scenario, select the Management Event Incident Configuration that you have created.
Comparison Criteria	<p>Specify the attribute values that must match before the incident is identified as a duplicate. The possible attributes consist of the following choices.</p> <ul style="list-style-type: none"> Name - The Name attribute value from the Incident form: General tab. CIA - Represents any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> SourceNode - The Source Node attribute value from the Basics attributes listed on the Incident form. The Source Node value is the IP Address or Name of the node for which the incident was generated. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The Source Node must be stored in the NNMi database.</p> </div> <ul style="list-style-type: none"> Source Object - The Source Object attribute value from the Basics

Deduplication Attributes, continued

Name	Description						
	<p>attributes listed on the Incident form.</p> <p>Note: The Source Object must be stored in the NNMi database.</p> <p>Caution: Each attribute value in the option you select must match before the incident is identified as a duplicate. For example, if you select Name, only the Incident Name value must match. If you select Name SourceNode SourceObject CIA, the Incident Name, Source Node, Source Object, and all Custom Incident Attribute values that you configure as a Parameter Value must match before NNMi identifies the incident as a duplicate.</p> <p>Selecting an option that includes CIA enables you to further refine the deduplication criteria. For example, you might want to configure deduplication for incidents with CIA values that specify the same State attribute value for a particular network object.</p> <p>For a description of each Comparison Criteria option, click here.</p> <table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td>Name</td><td>Value of the Name attribute from the Incident form: General tab must match.</td></tr> <tr> <td>Name CIA</td><td> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> </table>	Comparison Criteria	Description	Name	Value of the Name attribute from the Incident form: General tab must match.	Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>
Comparison Criteria	Description						
Name	Value of the Name attribute from the Incident form: General tab must match.						
Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>						

Deduplication Attributes, continued

Name	Description								
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td>Name SourceNode</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form </td></tr> <tr> <td>Name SourceNode CIA</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> <tr> <td>Name SourceObject</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> </td></tr> </table>	Comparison Criteria	Description	Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form 	Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 	Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p>
Comparison Criteria	Description								
Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form 								
Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Value attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 								
Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p>								

Deduplication Attributes, continued

Name	Description								
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. </td></tr> <tr> <td>Name SourceObject CIA</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> <tr> <td>Name SourceNode SourceObject</td><td> <p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics </td></tr> </table>	Comparison Criteria	Description		<ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 	Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>	Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics
Comparison Criteria	Description								
	<ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 								
Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>								
Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics 								


Deduplication Attributes, continued

Name	Description						
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td>attributes listed on the Incident form</td></tr> <tr> <td>Name SourceNode SourceObject CIA</td><td> <p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> </table>	Comparison Criteria	Description		attributes listed on the Incident form	Name SourceNode SourceObject CIA	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>
Comparison Criteria	Description						
	attributes listed on the Incident form						
Name SourceNode SourceObject CIA	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>						
Deduplication Comparison Parameters	<p><i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must populate one or more rows in this table.</p> <p>See "Deduplication Comparison Parameters Form " on page 746.</p>						


Deduplication Comparison Parameters Form (Syslog Message) (HP ArcSight)

Comparison Parameter values enable accurate identification of duplicate incidents. Custom Incident Attributes (CIAs) are used as Comparison Parameter values. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Deduplication (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.



The screenshot shows the HP Network Node Manager i Software interface. At the top, there's a navigation bar with 'Open Root Cause Incidents' and 'Incidents'. Below this is a toolbar with icons for 'Save and Close' and 'Delete Incident'. The main window is divided into two panes. The left pane, titled 'Basics', contains a 'Message' field with 'Interface Down', and several dropdown menus for 'Severity' (Critical), 'Priority' (None), 'Lifecycle State' (Registered), 'Source Node' (CH-KVI), 'Source Object' (Se0/0/2), and 'Assigned To'. The right pane, titled 'Custom Attributes', has tabs for 'Correlated Children', 'Custom Attributes', 'Diagnostics', and 'Registration'. The 'Custom Attributes' tab is active, showing a table with two rows of data. The table has columns for 'Name', 'Type', and 'Value'. The first row is 'com.hp.ov.nms.apa.symptom' with Type 'String' and Value 'IfOperStatusDown'. The second row is 'com.hp.ov.nms.apa.symptom_1' with Type 'String' and Value 'InterfaceAdminUpC'. Below the table, it says 'Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF'. At the bottom of the window, there's a status bar that reads 'Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R'.






Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To specify a CIA to use in the identification criteria for duplicate incidents:

1. Navigate to the **Deduplication Comparison Params** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog MessageConfigurations**.

- d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
- e. On the form that opens, navigate to the **Deduplication** tab.
- f. Locate the **Deduplication Comparison Parameters** table.
- g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Rate (Time Period and Count) for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message Configuration tab:

Use Rate configuration to track incident patterns *based on the number of incident reoccurrences within a specified time period*. After the count within the specified time period is reached, NNMi emits a Rate Correlation incident and continues to update the Correlation Notes with the number of occurrences within that rate.

Note: Suppression, Enrichment, and Dampening are not supported for Rate incidents.

As long as your defined criteria (Count and Hours, Minutes, Seconds) is sustained, the following information is updated in the Correlation Notes of the Rate Correlation incident:

- the actual number of occurrences of incidents for that sustained rate (Count)
- the sustained time interval (Hours, Minutes, Seconds)

For example, you can set a Rate configuration to track when a link is intermittently down at least three times in 30 minutes. NNMi shows the first occurrence of the rate incident in the incident view

and uses Correlation Notes to update the number of incidents and time interval to reflect all the incremental incident occurrences and time periods. To continue the example, if the rate of three times in 30 minutes is sustained for 90 minutes, NNMi updates the Correlation Notes to specify that 9 incidents occurred in 90 minutes.



NNMi provides preconfigured Rate correlations. You can add new Rate correlations.

When you open the Incident form of the newest instance:

- On the General tab, two fields notify you that the Rate correlation is working:
 - **Correlation Nature:** Rate Stream Correlation
 - **Count:** x
- On the **Correlated Children** tab, each incident is listed in the table.
- If a Rate Correlation Incident is dampened, note the following:
 - Rate Correlation Incidents inherit the Dampening configuration settings from its Correlated Children.
 - NNMi always retains the Parent Rate Correlation Incident, even if its Child Incidents are Closed and subsequently deleted.

See [Dampening Incident Configurations](#) for more information about Dampening an incident configuration.



To establish a rate correlation within an incident configuration:

1. Navigate to the **Rate** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, locate the **Rate** tab.
2. Provide the definition for this Rate Configuration (see the "Rate Configuration Definition" table).
3. *Optional.* If your [Comparison Criteria](#) includes custom incident attributes (CIA) to identify one specific incident, use the Comparison Parameter List table to define each CIA. See ["Rate](#)

[Comparison Parameters Form" on page 767.](#)

4. Click  **Save and Close** to save your changes and return to the previous form.


Rate Configuration Definition

Attribute	Description
Enabled	<p>Use this attribute to temporarily disable an incident's rate settings: If enabled, NNMI actively tracks any reoccurrences of the designated incident within the time period you specify, and generates a Rate incident.</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Count	Specify the number of reoccurrences required before your Rate Configuration starts working.
Hours	Used with the Minutes and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Minutes	Used with the Hours and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Seconds	Used with the Hours and Minutes attributes to specify the time duration within which the reoccurrences are measured.
Parent Incident	Click the  icon and select  Quick Find. Select Rate Correlation from the list.
Comparison Criteria	<p>Specify which group of attributes must match before the incident is identified as a duplicate. The possible groups of attributes consist of the following choices.</p> <p>Name value of the Incident (from the General tab on the Incident form).</p> <p>Source Node value (from the Basics group on the Incident form). Address or name of the node for which the incident was generated.</p> <p>Source Object value (from the Basics group on the Incident form). For example, the Source Object for a LinkDown incident is interface.</p> <p>CIA custom incident attribute values (select from the list displayed on the Custom Attributes tab on the Incident form). If you want to use CIA as part of your comparison criteria, see "Rate Comparison Parameters Form (Syslog Message) (HP ArcSight)" on the next page.</p>
Rate Comparison Parameters	<i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must populate one or more rows in this table. See " Rate Comparison Parameters Form (Management Events) " on page 1383.


Rate Comparison Parameters Form (Syslog Message) (HP ArcSight)

Custom Incident Attributes (CIAs) are used as parameter values. Parameter values enable accurate identification of duplicate incidents. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Rate (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.








The screenshot shows the HP ArcSight interface for configuring an incident. The incident type is 'InterfaceDown'. The 'Custom Attributes' tab is selected, displaying a table of attributes:

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Below the table, the status bar indicates: Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF.

To specify a CIA to use in the identification criteria for duplicate incidents:

1. Navigate to the **Rate Comparison Parameters** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, navigate to the **Rate** tab.
 - f. Locate the **Rate Comparison Parameters** table.
 - g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Actions for a Syslog Message Incident (HP ArcSight)

For information about each Syslog Message tab:

For information about each Actions tab:

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.

Note: Your actions will not be executed until you enable the Actions configuration by either

clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.

Note: If the NNMi management server is running on a Windows operating system, NNMi runs each action that you configure using the Local System account. If the NNMi management server is running on a Linux operating system, NNMi runs each action that you configure using the bin user name. To change the user account associated with actions, see the "Setting the Action Server Name Parameter" section in the *HP Network Node Manager i Software Deployment Reference*.

You can configure actions for incidents generated from SNMP Traps, Syslog Messages (HP ArcSight only) and the NNMi management events. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)" on the next page](#) for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)" on the next page](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the incidentActions.*.*.log file. To view the contents of the Actions log, use the **Tools** → **Incident Actions Log** menu option.

See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

NNMi sets the default values described in the following table.








See the "Maintaining NNMi" chapter in the HP Network Node Manager i Software Deployment Reference for information about changing the default values for Action Server Properties.

Action Server Properties

Property	Description	Value
numProcess	Number of actions that can be run at one time.	10
numJythonThreads	Number of threads the action server uses to run Jython scripts	10
userName	User name under which the action server runs.	bin

To configure an automatic action for an incident:

1. Navigate to the **Actions** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.


- d. Do one of the following:
 - To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
 - e. Select the **Actions** tab.
2. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
 3. In the "[Lifecycle Transition Action Form \(Syslog Message\) \(HP ArcSight\)](#)" below, provide the required information.
 4. Click  **Save and Close** to save your changes and return to the previous form.

The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Lifecycle Transition Action Form (Syslog Message) (HP ArcSight)




For information about each Actions tab:

Use this form to enter the command you want to run when an incident of the type you are configuring is at a particular [Lifecycle State](#). For example, when an incident is generated (**Registered**), you might want to automatically open a trouble ticket or email or page your network operator.


Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.

To configure an action for an incidents:

1. Navigate to the **Lifecycle Transition Actions** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Select the **Actions** tab.

- e. From the **Lifecycle Transition Action** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
2. Make your configuration choices (see [table](#)).

Note: NNMi reloads the configuration information anytime the incident configuration is changed.

3. Click  **Save and Close** to save your changes and return to the previous form.

Create Action Attributes

Attribute	Description
Lifecycle State	Select a Lifecycle State from the drop-down menu.
Command Type	If you provided a Jython command, select Jython from the drop-down list. If you are using an executable or bat file, select ScriptOrExecutable from the drop-down list.
Command	<p>Enter one of the following:</p> <ul style="list-style-type: none">• A Jython method with the required parameters.• Executable command for the current operating system with the required parameters. <p>When entering a Command value, note the following:</p> <ul style="list-style-type: none">• Left or right bracket ([]) and backtick (` Unicode character: 0060 hex = 96 dec) characters are not permitted in the Command attribute. If you need these characters in your shell script, place them in a shell script file and reference that file from the Command attribute.• Windows only: Shell commands are not permitted in the Command attribute. To use shell commands, place them in a shell script file and reference that file from the Command attribute.• Use absolute paths to executables instead of relying on the PATH variable as it might not be set correctly.• Verify that you do not have two Jython methods with the same name. Otherwise, NNMi is not able to tell which is the correct method to load.

Create Action Attributes, continued






Attribute	Description
	<ul style="list-style-type: none">You can use the same Jython method for more than one incident configuration.Jython (.py) files must reside in the following directory (see "About Environment Variables" on page 86): <div>Note: All the functions defined in the Jython files that reside in this directory are also accessible by NNMi. The files are also executed by NNMi on startup.</div> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\actions</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/actions</pre> <ul style="list-style-type: none">When using executable files, specify the absolute path to the executable command or make sure the directory in which the executable file resides is in your PATH environment variable.NNMi provides a set of parameters that can pass attribute values from an incident configuration. See "Valid Parameters for Configuring Incident Actions (Management Events)" on page 1397 for more information.

Configure a Payload Filter for an Action (Syslog Message) (HP ArcSight)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Syslog Message Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Syslog Message Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Actions** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Select the **Payload Filter** tab.
5. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute	Operator	Value
<input type="text" value="ciaName"/>	<input "="" type="text" value="="/>	<input type="text" value=".1.3.6.1.4.1.9.9.13.1.2.1.7"/>

AND
[AND]
[NOT]

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String
(AND NOT ())

Insert
AND
OR
NOT
EXISTS
NOT EXISTS
Delete

6. Click **Save and Close**.

7. Click **Save and Close** to save your changes and return to the previous form.

When creating a Payload Filter, note the following:

- Payload Filter expressions for the `like` and `not like` operators use the syntax defined for java regular expressions (`java.util.regex Pattern` class)
- You must use a `ciaName` that already exists in the trap or event you are configuring.
- Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions as shown in the example below.

The following example filters incidents on voltage state. Using this Payload Filter, you could then configure the Basics settings of the Enrichment Configuration to set the severity and message format to all incidents that return a state value of 4 or 5.

OR

```
ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7
```

```
ciaValue = 4
```

AND

```
ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7
```

```
ciaValue = 5
```

NNMi evaluates the expression above as follows:

```
(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 4) OR (ciaName =  
.1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)
```

NNMi finds all incidents with a varbind value of `.1.3.6.1.4.1.9.9.13.1.2.1.7` and CIA value of **4** or **5**.

- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators.


Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none">• ciaName• ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none">• = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7.• != Finds all values not equal to the value specified. Click here for an example. Example: ciaName!=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.• < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind value less than 6.• <= Finds all values less than or equal to the value specified. Click here for an


Payload Filter Editor Settings, continued

Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
	<p>example.</p> <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="446 1173 873 1287"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="467 1417 1320 1478"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 	Operator	Value	between	1		4
Operator	Value						
between	1						
	4						

Payload Filter Editor Settings, continued

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
	<div data-bbox="451 537 841 674">  </div> <p>matches any incident that contains a varbind value of either 4 or 5.</p> <div data-bbox="451 772 1370 884"> <p>Note: ;As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with varbind values. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="451 1507 1370 1619"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Examples:</p> <p>ciaName like \Q .1.3.6.1.4.1.9.9\E.* finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p>

Payload Filter Editor Settings, continued

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
	<p>ciaValue like <code>.*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>  matches any incident that contains a varbind with values other than 1 and 2. <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (<code>.*</code>) characters mean <i>any number of characters of any type at this location</i>. The period (<code>.</code>) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string</p>

Payload Filter Editor Settings, continued

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
	<p>value in \Q<<i>literal_value</i>>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. • The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line.

Payload Filter Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	Inserts the AND Boolean Operator in the selected cursor location.

Payload Filter Editor Buttons, continued

Button	Description
	<p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of</p>

Payload Filter Editor Buttons, continued

Button	Description
	<p>the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>

Valid Parameters for Configuring Incident Actions (Syslog Message) (HP ArcSight)

When configuring incident actions, consider using incident information as part of the action. NNMi provides the following parameter values. Use these parameters as variables in your Jython or executable files.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as “null”.

See ["Lifecycle Transition Action Form" on page 848](#) for more information about configuring incident actions.

Valid Parameters Visible From an Incident's Form

Parameter Value	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$severity, \$sev	Value of the Severity attribute of the Incident form.

Valid Parameters Visible from a Node Form

Parameter Value	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in

Valid Parameters Visible from a Node Form, continued

	the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

Valid Parameters Visible from an Interface Form

Parameter Value	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.
\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.

Valid Parameters Visible from a Layer 2 Connection Form

Parameter Value	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.

Valid Parameters Visible from a Layer 2 Connection Form, continued

Parameter Value	Description
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

Valid Parameters Visible from a VLAN Form

Parameter Value	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the Global VLAN Name attribute associated with the interface that is the incident's source object. To access this information from a Node form or Interface form, navigate to the VLAN Ports tab. If the node or interface is part of more than one VLAN, this parameter returns a comma-separated list.

Valid Parameters Not Visible From a Form

Parameter Value	Description
\$id	Unique Object Identifier attribute value for the incident (unique across the entire NNMi Database).
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs,	Value from the Last Occurrence Time attribute in the incident form,

Valid Parameters Not Visible From a Form, continued

Parameter Value	Description
\$lms	converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$messageFormat, \$msg	<i>Valid for Incident actions only.</i> Message text displayed for an incident when this parameter is included as an argument to an incident action.
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection: The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name> [interface_name]</i>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB ifName. Each ifName varies according to the vendor's conventions. Using the name 4/1 as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances..
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

Valid Parameters Established in Custom Incident Attributes

Parameter Value	Description
\$<position_number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_name>	Value of the name that is used for the custom incident attribute. For example, \$mycompany.mycia. NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_oid>	Value of the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: \$<CIA_name>:<CIA_value> in which the custom incident attribute name appears followed by the custom incident attribute value.

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the [nnmloadmib.ovpl](#) command.

Functions to Generate Values Within Incident Messages

Function	Description
\$text (\$<position_number>)	The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA. Note: If a text value is not available, NNMi returns the numeric value.
\$text (\$<CIA_oid>)	The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA.

Functions to Generate Values Within Incident Messages, continued





Function	Description
	<p>Note: If a text value is not available, NNMi returns the following message as the value: <CIA <OID> with value <value> was not found within the mib cache</p>

Configure Management Events

Management events are those events that are generated from the NNMi Causal Engine. You can configure how you want these events to be displayed in the incident views provided by NNMi. The types of things you configure include its name, category, and the format of its message.

Note: Custom created Management Incidents are for use in Custom Correlations. See ["Configure a Correlation Rule" on page 771](#) and ["Configure a Causal Rule" on page 808](#) for more information.


To configure a management event:

1. Navigate to the **Management Events Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
2. Do one of the following:
 - a. To create a management event configuration, click the  New icon, and continue.
 - b. To edit a management event configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a management event configuration, select a row, and click the  Delete icon.
3. In the ["Management Event Form" below](#), provide the required configuration information.
4. Click  **Save and Close** to save your changes and return to the **Incident Configuration** form.




The next time that a management event of this type arrives into the database, NNMi creates an associated incident to display in the appropriate console incident views.

Management Event Form

To configure incidents originating from management events:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
2. Make your configuration choices (see [table](#)).





Note: If you want to add or edit a management event configuration, verify that **Enabled** ☒ is selected.

- a. To add a management event configuration, click the  New icon, and continue.
 - b. To edit a management event configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a management event configuration, click the  Delete icon.
3. Click  **Save and Close** to save your changes and return to the previous form.

Tasks for Management Event Configuration

Task	How
"Specify the Incident Configuration Name (Management Events)" on page 1242	Use the Basics group of the Management Event Configuration form. Specify a name that helps you to identify the configuration for subsequent use.
Specify whether you want to enable this configuration.	In the Basics group of the Management Event Configuration form, verify that Enable <input checked="" type="checkbox"/> is selected for each configuration you want to use.
"Specify Category and Family Attribute Values for Organizing Your Incidents (Management Events)" on page 1242	Use the Basics group of the Management Event Configuration form. You can organize your incidents using Category and Family.
"Specify the Incident Severity (Management Events)" on page 1247	Use the Basics group of the Management Event Configuration form. Possible Severity values include: Normal , Warning , Minor , Major , and Critical .
"Specify Your Incident Message Format (Management Events)" on page 1248	Use the Basics group of the Management Event Configuration form. The message format determines the message to be displayed for the incident.
"Specify a Description for Your Incident Configuration (Management Events)" on page 1256	Use the Basics group of the Management Event Configuration form. Provide a meaningful description.

Tasks for Management Event Configuration, continued

Task	How
Specify an Author for Your Incident Configuration (Management Events)	<p>Use the Basics pane of the Management Event Configuration form to indicate who created or last modified the event.</p> <div> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value. </div>


After you complete the Basic Configuration for the management event, you can also choose to configure the information described in the following table.

Additional Configurations

Task	How
" Correlate Duplicate Incidents (Deduplication Configuration) " on page 745	Select the Deduplication tab to specify duplicate incidents that you want to be suppressed.
" Track Incident Frequency (Rate: Time Period and Count) " on page 746	Select the Rate tab to specify a rate for duplicate incidents. After the rate limit is reached, NNMi generates an Incident to notify you of the problem.
" Configure an Action for an Incident " on page 847	Select the Actions tab to specify actions that should occur automatically when an incident changes its Lifecycle State .
" Configure Diagnostics for an Incident " on page 857	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – click here for more information.</div> <p>Select the Node Settings tab to specify diagnostic actions that should occur automatically when an incident reaches a selected Lifecycle State for a node that belongs to a particular Node Group.</p>

Configure Basic Settings for a Management Event Incident





The Basics settings for a Management Event Incident specifies general information for an incident configuration, including the name, severity, and message.

Note: In the **Basics** group of the **Management Event Configuration** form, verify that **Enable**  is selected for each configuration you want to use.

For information about each Management Events tab:

To configure Basic settings for a Management Event incident:

Navigate to the **Management Event Configuration** form:

1. From the workspace navigation panel, select the **Configuration** workspace.
2. Expand the **Incidents** folder.
3. Select **Management Event Configurations**.
4. Do one of the following:
 - a. To create an incident configuration, click the  New icon, and continue.
 - b. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - c. To delete an incident configuration, select a row, and click the  Delete icon.
5. Configure the required Basic settings (see the [Basic Attributes](#) table).
6. Click  **Save and Close** to save your changes and return to the previous form. NNMi uses the SNMP Object ID to enable forwarding of Management Events as SNMP traps. NNMi automatically assigns a unique SNMP Object ID to all Management Events provided by NNMi.





Basic Attributes for Management Event Configuration

Task	How
"Specify the Incident Configuration Name (Management Events)" on page 1242	Use the Basics pane of the Management Event Configuration form. Specify a name that helps you to identify the configuration for subsequent use.
SNMP Object ID	The SNMP Object ID assigned by NNMi. Note the following about the SNMP Object ID that appears in the Basics settings of the Management Event Configuration form:

Basic Attributes for Management Event Configuration, continued

Task	How
	<ul style="list-style-type: none"> The Management Event SNMP Object ID is used when sending Management Events to another application. For example, you might want to send NNMi Management Event to an event consolidator such as HP Operations Manager. The SNMP Object ID is used to uniquely identify the management event in the application receiving the event. NNMi assigns a unique SNMP Object ID to each Management Event configuration it provides. If you choose to create a new Management Event configuration, NNMi assigns the following "generic" SNMP Object ID to these user-created configurations: .1.3.6.1.4.1.11.2.17.19.2.0.9999 For user-defined Management Events, a combination of the SNMP Object ID and the user-defined event name must be used to uniquely identify the Management Event in an application receiving the event. See the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals for more information. If you choose to create a new Management Event configuration, NNMi automatically assigns the same "generic" SNMP Object ID to all new Management Event configurations.
Specify whether you want to enable this configuration.	In the Basics group of the Management Event Configuration form, verify that Enable <input checked="" type="checkbox"/> is selected for each configuration you want to use.
"Specify Category and Family Attribute Values for Organizing Your Incidents (Management Events)" on page 1242	Use the Basics pane of the Management Event Configuration form. You can organize your incidents using Category and Family.
"Specify the Incident Severity (Management Events)" on page 1247	Use the Basics pane of the Management Event Configuration form. Possible Severity values include: Normal , Warning , Minor , Major , and Critical .
"Specify Your Incident Message Format (Management Events)" on page 1248	Use the Basics pane of the Management Event Configuration form. The message format determines the message to be displayed for the incident.
"Specify a Description	Use the Basics pane of the Management Event Configuration form.

Basic Attributes for Management Event Configuration, continued

Task	How
for Your Incident Configuration (Management Events) " on page 1256	Provide a meaningful description.
Specify an Author for Your Incident Configuration (Management Events)	<p>Use the Basics pane of the Management Event Configuration form to indicate who created or last modified the event.</p> <div> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value. </div>

After you complete the Basic Configuration for the Management Event Incident, you can also choose to configure the information described in the following table.

Additional Incident Configurations

Task	How
"Configure Interface Settings for a Management Event Incident" on page 1257	Select the Interface Settings tab to specify an Interface Group to which you want your incident configuration to apply.
"Configure Node Settings for a Management Event Incident" on page 1301	Select the Node Settings tab to specify a Node Group to which you want your incident configuration to apply.
"Configure Suppression Settings for a Management Event Incident" on page 1347	Select the Suppression tab to specify the criteria for discarding incidents that match the selected incident configuration.
"Configure Enrichment Settings for a Management Event Incident" on page 1356	Select the Enrichment tab to specify enhancements for the selected incident configuration.
"Configure Dampening Settings for a Management Event Incident" on page 1361	Select the Dampen tab to specify the time interval that must be met before the incident appears in an Incident view.
"Configure Deduplication for a Management Event Incident" on page 1372	Select the Deduplication tab to specify duplicate incidents that you want to be suppressed.

Additional Incident Configurations, continued

Task	How
"Configure Rate (Time Period and Count) for a Management Event Incident" on page 1380	Select the Rate tab to specify a rate for duplicate incidents. After the rate limit is reached, NNMi generates an Incident to notify you of the problem.
"Configure Actions for a Management Event Incident" on page 1384	Select the Actions tab to specify actions that should occur automatically when an incident changes its Lifecycle State .

Specify the Incident Configuration Name (Management Events)

When providing the Name for an incident configuration, use the following guidelines:

Name

The name is used to identify the incident configuration and must be unique. Use a name that will help you to remember the purpose or kind of Management Event, Syslog Message or SNMP Trap for which you are configuring an incident. Name is also used to identify your Pairwise configurations.

Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No spaces are permitted.

Specify Category and Family Attribute Values for Organizing Your Incidents (Management Events)

When configuring incidents, NNMi provides the Category and Family attributes to help you organize your incidents.

Preconfigured Categories

The Category attribute helps you organize your incidents. Select the category that you want to be associated with this type of incident when it appears in an incident view. Each of the possible Category values is described in the following table.

Incident Categories Provided by NNMi

Category	Description
Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.
Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Track Your NNMi

Incident Categories Provided by NNMi, continued

Category	Description
	Licenses" on page 1604 or "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).
Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.
Fault	Indicates a problem with the network, for example Node Down.
Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .
Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.
Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.

Note: You can add your own Category entries to NNMi. See ["Create an Incident Category \(Management Events\)" on page 1245](#) for more information.

You can use **Family** attribute values to further categorize the types of incidents that might be generated. Each of the possible values are described in the following table.

Incident Family Attribute Values Provided by NNMi

Family	Description
Address	Indicates the incident is related to an address problem.
Aggregated Port	Indicates the incident is related to a Link Aggregation¹ or Split Link Aggregation² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .
BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Chassis	Indicates the incident is related to a chassis problem.
Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.
Connection	Indicates the incident is related to a problem with one or more connections.
Correlation	Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.
Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.
HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).
Interface	Indicates the incident is related to a problem with one or more interfaces.
IP Subnet	Indicates the incident is related to a problem with the IP Subnet.
License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .
NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.
Node	Indicates the incident is related to a node problem.
OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RAMS	Indicates the incident is related to a Router Analytics Management System problem.
RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.

¹Hot Standby Router Protocol

Incident Family Attribute Values Provided by NNMi, continued

Family	Description
STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.
System and Applications	Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.
Trap Analysis	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</div> <div>Indicates the incident is related to an SNMP trap storm.</div>
VLAN	Indicates the incident is related to a problem with a virtual local area network.
VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).

Note: You can add your own Family entries to NNMi. See "[Create an Incident Family \(Management Events\)](#)" on the next page for more information.







Create an Incident Category (Management Events)

The Category attribute helps you organize your incidents. Create any Category that makes sense to you and your team. For a list of the Category codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(Management Events\)](#)" on page 1242.


To create a new incident Category:

1. Navigate to the **Management Event Configuration Category** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:

¹Virtual Router Redundancy Protocol

- To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
- e. In the configuration form, locate the **Category** attribute.
- f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the previous form.

Category Code Attributes







Name	Description
Label	Incident category name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Alpha-numeric, spaces, and underline characters are permitted.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trapConf.category.<category_Label> com.<your_company_name>.nnm.eventConf.category.<category_Label> com.<your_company_name>.nnm.inciConf.category.<category_Label></pre> <p>The maximum length is 80 characters. Alpha-numeric characters and periods are permitted. Spaces are not permitted.</p>

Create an Incident Family (Management Events)


The Family attribute helps you organize your incidents. Create any Family that makes sense to you and your team. For a list of the Family codes provided by NNMi, "[Specify Category and Family Attribute Values for Organizing Your Incidents \(Management Events\)](#)" on page 1242.

To create a new incident Family:

1. Navigate to the **Incident Family** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.

- b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
 - e. In the configuration form, locate the **Family** attribute.
 - f. Click the  Lookup icon, and select  New.
2. Provide the required information (see [table](#)).
 3. Click  **Save and Close** to save your changes and return to the previous form.

Family Attributes

Name	Description
Label	Family name. For example, Hardware Faults, or Cisco Error. Maximum size is 255 characters. Any character type is valid.
Unique Key	<p>Caution: After you click  Save and Close, this value cannot be changed.</p> <p>Used as a unique identifier when exporting and importing configuration definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following examples:</p> <pre>com.<your_company_name>.nnm.trapConf.family.<family_label> com.<your_company_name>.nnm.eventConf.family.<family_label> com.<your_company_name>.nnm.inciConf.family.<family_label></pre> <p>The maximum length is 80 alpha-numeric characters, periods allowed, no spaces allowed.</p>

Specify the Incident Severity (Management Events)

The incident severity represents the seriousness calculated for the incident. Use the severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described in the following table.

Incident Severity Values

Attribute	Description
Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.
Warning	Indicates there might be a problem related to the associated object.
Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.
Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.
Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.

See ["Monitor Incidents for Problems"](#) for more information about these severity values.

Specify Your Incident Message Format (Management Events)

When configuring an incident, specify the information you want NNMi to include in the incident's Message attribute value. You can use any combination of valid parameter strings and Custom Incident attributes to configure the Message.

Note: The incident Message limit is 1024 characters. If the returned values exceed this limit, NNMi truncates the value starting from the end of the returned text string.

["Valid Parameters for Configuring Incident Messages \(Management Events\)"](#) below

["Include Custom Incident Attributes in Your Message Format \(Management Events\)"](#) on page 1255

Valid Parameters for Configuring Incident Messages (Management Events)

When configuring incident messages, consider using incident information as part of the message. NNMi provides the following parameter values. Use these parameters as variables when formatting an incident message.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See ["Specify Your Incident Message Format \(Management Events\)"](#) above for more information about configuring messages.

Parameter strings are available for the following:

Note: See the following tables to view the valid parameters for incidents generated from Custom Polled Instances: [Parameter Strings for all Incidents \(Attributes from an Incident form\)](#), [Parameter Strings for Node Source Objects \(Attributes from a Node form\)](#), and the [Parameter Strings for all Incidents \(Attributes not Visible from any form\)](#).

- Parameter strings for all incidents (Incident form attributes) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Incident form attributes)

Parameter String	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$sev, \$severity	Value of the Severity attribute of the Incident form.

- Parameter Strings for Node Source Objects (Node form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Node Source Objects (Node form attributes)

Parameter String	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the

Parameter Strings for Node Source Objects (Node form attributes) , continued

Parameter String	Description
	value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

- Parameter Strings for Interface Source Objects (Interface form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Interface Source Objects (Interface form attributes)

Parameter String	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.

Parameter Strings for Interface Source Objects (Interface form attributes) , continued

Parameter String	Description
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.
\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.

- Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Layer 2 Connection Source Objects (Layer 2 Connection form attributes)

Parameter String	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

- Parameter strings for VLAN Source Objects (VLAN form attributes) ([Click here for a list of choices.](#))

Parameter Strings for VLAN Source Objects (VLAN form attributes)

Parameter String	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the VLAN Name attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Ports tab of the Interface form. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.

- Parameter Strings for all incidents (Additional information that is not visible in any form) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Attributes not visible in any form)

Parameter String	Description
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	<p>If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection:</p> <p>The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name>[interface_name]</i></p>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source

Parameter Strings for all Incidents (Attributes not visible in any form), continued

Parameter String	Description
	node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name 4/1 as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances.
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

- Information established in Custom Incident Attributes ([Click here for a list of choices.](#))

Parameter Strings for Attributes Established in Custom Incident Attributes

Parameter String	Description
\$<position _number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_ name>	Value of the name that is used for the custom incident attribute. For example, <code>\$mycompany.mycia</code> . NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_ _	Value of the object identifier for any custom incident attribute that originated as a

Parameter Strings for Attributes Established in Custom Incident Attributes, continued

Parameter String	Description
oid>	varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: <code><CIA_name>:<CIA_value></code> in which the custom incident attribute name appears followed by the custom incident attribute value.

- Functions to generate values ([Click here for a list of choices.](#))

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the `nnmloadmib.ovpl` command.

Functions to Generate Values Within the Incident Message

Function	Description
\$oidtext (\$<position_ number>)	<p>A <code><position_number></code> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, <code>\$oidtext(\$2)</code>.</p> <div style="border: 1px solid #ccc; padding: 10px; margin: 10px 0;"> <p>Note: The position number you enter must represent a CIA that contains an Object Identifier (OID) value.</p> </div> <p>NNMi returns the textual value of the OID for the CIA specified.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ If the MIB is not loaded, NNMi returns the numeric OID value. ■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$oidtext (\$<CIA_ oid>)	<p>The <code><CIA_oid></code> argument specifies the Object Identifier (OID) for any custom incident attribute that originated as a varbind. For example, <code>\$oidtext (\$.1.3.6.1.6.3.1.1.5.1.)</code> Use this argument to the <code>\$oidtext()</code> function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the textual value of the OID you specify.</p>

Functions to Generate Values Within the Incident Message, continued

Function	Description
	<p>Note the following:</p> <ul style="list-style-type: none">■ If the MIB is not loaded, NNMi returns the numeric OID value.■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$text (\$<position_ number>)	<p>The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>
\$text (\$<CIA_ oid>)	<p>The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number.</p> <p>NNMi replaces the numeric value with the text value stored in the CIA.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>

Include Custom Incident Attributes in Your Message Format (Management Events)

NNMi includes two categories of CIAs:

- SNMP trap varbinds identified by the Abstract Syntax Notation value (ASN.1). NNMi turns varbinds into CIAs and maintains each varbind's position number. See ["Load SNMP Trap Incident Configurations" on page 873](#).
- Custom incident attributes provided by NNMi. See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#).

You cannot create Custom Incident Attributes.

You can use CIAs in your message format to extend the amount of information presented. To determine which CIAs are available for any particular incident type, open an Incident view, locate

the incident and open the [Incident form](#). Navigate to the **Custom Attributes** tab. A complete list of available CIAs (for that incident type) appears in the table.

To include a CIA in your message format, type the dollar-sign character (\$) plus any of the following:

- Varbind position number or asterisk (*) to include all varbind values
- Name of the CIA
- Object identifier (oid) of the CIA (useful when the varbind position number is not consistent among vendors)

Note: A single incident cannot include two CIAs with the same name. However, two incidents can contain CIAs having the same names and values.

The following table presents some example formats with the subsequent output.

Example Incident Message Formats

Example Message Format	Output in Incident View
Possible trouble with \$3	Possible trouble with <varbind 3>
Possible trouble with \$11	Possible trouble with <varbind 11>
Possible trouble with \$77 (where the varbind position 77 does not exist)	Possible trouble with <Invalid or unknown cia> 77
Possible trouble with \$*	Possible trouble with <cia1_name: cia_value>, <cia2_name; cia_value>, <cia_n_name: cia_value>
Possible trouble with \$3x	Possible trouble with <varbind 3>x
Possible trouble with \$1.2.3.4.5	Possible trouble with <value of the CIA with oid of 1.2.3.4.5>
Possible trouble with \$cia.sourceObject.UcmdbId	Possible trouble with <value of the CIA with name of cia.sourceObject.UcmdbId>

Tip: NNMi provides an error message when a CIA cannot be found. For example, if you enter an unavailable varbind position, name, or object identifier (oid), NNMi returns an "Invalid or unknown cia" error message.

Specify a Description for Your Incident Configuration (Management Events)

NNMi provides the Description attribute to help you further identify the current incident configuration.

Description

Use the description field to provide additional information that you would like to store about the current incident configuration. This description applies only to the configuration entry.

Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Configure Interface Settings for a Management Event Incident

Note: Interface Settings override any other Suppression, Enrichment, Dampen, or Actions settings for this incident, including those configured on the Node Settings tab.





NNMi enables you to apply an incident configuration to a Source Object based on the Source Object's participation in an Interface Group. If the Source Object is not a member of the Interface Group specified, the incident is neither displayed nor stored in the NNMi database


Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.

For information about each Interface Settings tab:



For information about each Management Events tab:

To apply an incident configuration to a Source Object based on the Source Object's Interface Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Configure the desired Interface Settings (see [table](#)).

5. Configure any Suppression, Dampen, or Enrichment settings for this Interface Group.
6. Click  **Save and Close** to save your changes and return to the previous form.

Interface Group Attributes

Name	Description
Interface Group	Click the  ▾ Lookup icon and select  Quick Find to select the Interface Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those interfaces that appear in multiple Interface Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If an interface is in multiple Interface Groups and more than one of those Interface Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the interface.
Enable	Use this attribute to temporarily disable an incident's configuration settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Related Topics

["Configure Node Settings for a Management Event Incident" on page 1301](#)

Configure Incident Suppression Settings for an Interface Group (Management Events)

Note: Interface Settings override any other Suppression settings for this incident, including those from the Node Settings tab.






NNMi enables you to suppress a specified incident configuration based on the Source Object's participation in an Interface Group.

Note: You can also suppress the incident configuration based on the Source Node's participation in a Node Group. See ["Configure Incident Suppression Settings for a Node Group \(Management Events\)" on page 1302](#) for more information.

Tip: See ["Create Interface Groups" on page 356](#) for more information about Interface Groups.

For information about each Interface Settings tab:

To suppress an incident configuration based on an Interface Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit a configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Suppression** tab.
6. Configure the desired Suppression behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings for the specified Interface Group:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p>







Interface Settings Suppression Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression <code>\Q.1.3.6.1.4.1.9.9\E.*</code> and has a value of 25. ■ Contain a varbind whose OID matches the regular expression <code>\Q.1.3.6.1.2.1.2.2.1.1.3\E.*</code> and has a value of 3.

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Settings <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. 						

Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. Note: As shown in the example, each value must be entered on a separate line. • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. Note: As shown in the example, each value must be entered on a separate line. NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. Note: As shown in the example, each value must be entered on a separate line. • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. Note: As shown in the example, each value must be entered on a separate line. NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> • between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between  matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. Note: As shown in the example, each value must be entered on a separate line. • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. Note: As shown in the example, each value must be entered on a separate line. NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. 				

Interface Settings Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribut- e	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribut- e	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="550 451 974 583" data-label="Form"> <p>The screenshot shows a web interface for configuring a filter. It has two columns: 'Operator' and 'Value'. Under 'Operator', there is a dropdown menu with 'not in' selected. Under 'Value', there is a text area containing the numbers '1' and '2' on separate lines.</p> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="566 741 1317 806" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="566 1423 1330 1522" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="550 451 974 583" data-label="Form"> <p>The screenshot shows a web interface for configuring a filter. It has two columns: 'Operator' and 'Value'. Under 'Operator', there is a dropdown menu with 'not in' selected. Under 'Value', there is a text area containing the numbers '1' and '2' on separate lines.</p> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="566 741 1317 806" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="566 1423 1330 1522" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="550 451 974 583" data-label="Form"> <p>The screenshot shows a web interface for configuring a filter. It has two columns: 'Operator' and 'Value'. Under 'Operator', there is a dropdown menu with 'not in' selected. Under 'Value', there is a text area containing the numbers '1' and '2' on separate lines.</p> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="566 741 1317 806" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="566 1423 1330 1522" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Suppression Attributes , continued

Name	Description																		
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table> <p>Payload Filter Editor Buttons</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> <p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>OR</td><td> <p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT</td><td> <p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p> </td></tr> </table>	Attribute	Description	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>
Attribute	Description																		
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line. 																		
Button	Description																		
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.																		
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.																		
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.																		
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>																		
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>																		
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>																		

Interface Settings Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Enrichment Settings for an Interface Group (Management Events)

Note: Interface Settings override any other Enrichment settings for this incident, including those from the Node Settings tab.

NNMi enables you to fine tune and enhance a specified incident configuration based on the Source Object's participation in an Interface Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To




Note: You can also enhance the incident configuration based on the Source Node's participation in a Node Group. See ["Configure Incident Enrichment Settings for Node Group \(Management Events\)" on page 1311](#) for more information.






Tip: See [Create Interface Groups](#) for more information about Interface Groups.

For information about each Interface Settings tab:

For information about each Enrichment tab:

To enrich an incident configuration based on an Interface Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.

3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Enrichment Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the</p>

















Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<p>values provided by NNMi include:</p> <ul style="list-style-type: none"> • Address • Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.) • Card • Connection • Correlation • Interface • Node
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p>



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p>

Interface Settings Enrichment Configuration Attributes , continued

Name	Description
	<p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (Management Events)" on page 1248</p> <p>"Include Custom Incident Attributes in Your Message Format (Management Events)" on page 1255</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Custom Incident Attributes to Enrich an Incident Configuration (Interface Settings) (Management Events)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.











When creating a CIA for an incident configuration, you can specify any of the following values:

- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select **Interface Settings**.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure you configure the Enrichment settings. See ["Configure Incident Enrichment Settings for an Interface Group \(Management Events\)" on page 1267](#) for more information.
8. Navigate to the **Custom Incident Attributes** tab.
9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.
 - c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.

10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).

11. Click  **Save and Close** to save your changes and return to the previous form.

Custom Incident Attribute








Name	Description
Custom Incident Attribute Name	Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.
Type	Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are: <ul style="list-style-type: none">• Node Custom Attribute• Interface Custom Attribute
Custom Attribute Name	Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following: <ul style="list-style-type: none">• Name of the Custom Attribute on the source node• Name of the Custom Attribute on the interface (source object)

Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (Management Events)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure you configure the Enrichment settings. See ["Configure Incident Enrichment Settings for an Interface Group \(Management Events\)" on page 1267](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())
 - c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, AND, NOT

Filter String: (AND NOT ())

Options: Insert, AND, OR, NOT, EXISTS, NOT EXISTS, Delete

Highlight the location in the logic flow, then click Insert to define the filter requirement

10. Click **Save and Close**.

11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6.


Payload Filter Editor Settings, continued

Attribute	Description												
	<ul style="list-style-type: none"> • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between <div data-bbox="449 957 878 1075" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="466 1230 1320 1293" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="449 1556 841 1690" data-label="Form"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </table> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="466 1814 1320 1845" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate</p> </div> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="469 573 1318 638"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 892" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1362 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1343 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1087 1339 1155"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1274 1295 1339">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1373 1362 1438">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1461 938 1493">The value for which you want NNMi to search.</p> <div data-bbox="435 1539 1369 1885"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for an Interface Group (Management Events)

Note: Interface Settings override any other Dampening settings for this incident, including those from the Node Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Object's participation in an Interface Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

- Appearance within Incident views in the NNMi Console

Note: You can also configure the Dampening settings based on the Source Node's participation in a Node Group. See "[Configure Incident Dampening Settings for a Node Group \(Management Events\)](#)" on page 1325 for more information.

Tip: See "[Create Interface Groups](#)" on page 356 for more information about Interface Groups.

For information about each Interface Settings tab:







When using the Dampening configuration, note the following:

- NNMi initially assigns incidents with Dampening settings configured a Lifecycle State of DAMPENED.
- After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure the Dampening settings based on an Interface Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .

- d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Dampening** tab.
6. Configure the desired Dampening behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Interface Settings Dampening Configuration Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	<p>Specifies the number of minutes to be used for the dampen interval.</p> <p>Note: The maximum dampen interval is 60 minutes.</p>
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p> <ul style="list-style-type: none"> • The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. • The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. • You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ■ Contain a varbind whose Object Identifier (OID) matches the regular expression <code>\Q.1.3.6.1.4.1.9.9\E.*</code> and has a value of 25. ■ Contain a varbind whose OID matches the regular expression <code>\Q.1.3.6.1.2.1.2.2.1.1.3\E.*</code> and has a value of 3.

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings	
Attribute	Description
Attribute	<p>The attribute name on which NNMI searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4.




Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example.
Attribut- e	Description				
	<ul style="list-style-type: none"> between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> matches any incident with a varbind value of either 4 or 5. <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. 				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>
Attribute	Description				
	<p>Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*?) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="553 453 976 585">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="553 453 976 585">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Attribute	Description				
	<div data-bbox="553 453 976 585">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="570 743 1320 810"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="570 1425 1336 1524"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>				

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p>

Interface Settings Dampening Configuration Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>Delete</td><td> <p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p> </td></tr> </table>	Button	Description		<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
Button	Description						
	<p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) <code>ifDesc</code> containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Actions for an Interface Group (Management Events)


Note: Interface Settings override any other Actions settings for this incident, including those from the Node Settings tab.

For information about each Interface Settings tab:

NNMi enables you to configure incident actions based on a Source Object's participation in an Interface Group.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is

generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.





Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.





You can configure actions for incidents generated from SNMP Trap Incidents, Syslog Messages Incidents and the NNMi Management Events Incidents. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(Management Events\)" on page 1386](#) for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(Management Events\)" on page 1386](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the incidentActions.*.*.log file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:

1. Navigate to the **Management Event Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Interface Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Actions** tab.




6. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
7. In the "[Lifecycle Transition Action Form \(Management Events\)](#)" on page 1386, provide the required information.
8. Click  **Save and Close** to save your changes and return to the previous form.




The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Configure a Payload Filter for an Incident Action (Interface Settings) (Management Events)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Interface Settings** tab.
3. Do one of the following:

- a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Interface Setting behavior. See ["Configure Interface Settings for a Management Event Incident" on page 1257](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:
 - a. To create an Action configuration, click the  New icon, and continue.
 - b. To edit an Action configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete an Action configuration, select a row, and click the  Delete icon.
7. Make sure the Action settings are configured. See ["Configure Incident Actions for an Interface Group \(Management Events\)" on page 1291](#) for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute: Operator: Value:

AND
AND
NOT

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String
(AND NOT ())

Insert
AND
OR
NOT
EXISTS
NOT EXISTS
Delete

10. Click **Save and Close**.

11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> • ciaName • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an


Payload Filter Editor Settings, continued

Attribute	Description												
	<p>example.</p> <p>Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between <div data-bbox="449 924 881 1041" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>between</td> <td>1</td> </tr> <tr> <td></td> <td>4</td> </tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="466 1194 1320 1260" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="449 1522 841 1656" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>in</td> <td>4</td> </tr> <tr> <td></td> <td>5</td> </tr> </tbody> </table> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="466 1778 1320 1843" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> 	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Examples:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>

Payload Filter Editor Settings, continued

Attribute	Description
	<div data-bbox="451 317 878 453">  </div> <p data-bbox="451 489 1308 520">matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="469 573 1318 638" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p data-bbox="451 695 1377 793">NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul data-bbox="418 827 1341 890" style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p data-bbox="451 907 1362 970">The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p data-bbox="451 1003 1343 1035">The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="469 1087 1339 1155" style="background-color: #f0f0f0; padding: 5px;"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p data-bbox="451 1209 561 1241">Example:</p> <p data-bbox="451 1274 1295 1337">ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p data-bbox="451 1371 1362 1434">ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p data-bbox="418 1461 938 1493">The value for which you want NNMi to search.</p> <div data-bbox="435 1518 1370 1885" style="background-color: #f0f0f0; padding: 10px;"> <p>Note:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Node Settings for a Management Event Incident

Note: Node Settings override any other Suppression, Enrichment, Dampen, Action, or Diagnostics Selections configuration settings, except those configured on the Interface Settings tab.






NNMi enables you to apply an incident configuration to a Source Node based on the Source Node's participation in a Node Group. If the Source Node is not a member of the Node Group specified, the incident is neither displayed nor stored in the NNMi database.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.



For information about each Node Settings tab:

For information about each Management Events tab:

To apply an incident configuration to a Source Node based on the Source Node's Node Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Configure the desired Node Settings (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the previous form.

Node Group Attributes

Name	Description
Node Group	Click the  Lookup icon and select  Quick Find to select the Node Group you want to use. See "Use the Quick Find Window" on page 38 for more information about using Quick Find.
Ordering	Determines the priority order for those nodes that appear in multiple Node Groups. The lower the number, the higher the priority. For example, 1 is the highest priority. If a node is in multiple Node Groups and more than one of those Node Groups have been specified in an incident configuration, only the incident configuration with the highest priority will be applied to the node.
Enable	Use this attribute to temporarily disable an incident's suppression settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Configure Incident Suppression Settings for a Node Group (Management Events)

Note: Node Settings override any other Suppression settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to suppress a specified incident configuration based on the Source Node's participation in a Node Group.





Note: You can also suppress the incident configuration based on the Source Object's participation in an Interface Group. See ["Configure Incident Suppression Settings for an Interface Group \(Management Events\)" on page 1258](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

To suppress an incident configuration based on a Node Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
 3. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
 5. Select the **Suppression** tab.
 6. Configure the desired Suppression behavior (see [table](#)).
 7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <p>AND</p>




Node Settings Suppression Attributes , continued

Name	Description						
	<p>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</p> <p>NNMi evaluates the expression above as follows:</p> <p>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</p> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <p>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</p> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <p>Payload Filter Editor Settings</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example.
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. 						

Node Settings Suppression Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> </td></tr> </table>	Attribute	Description		<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4
Attribute	Description										
	<p>Example: <code>ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> <ul style="list-style-type: none"> • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> 	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Suppression Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.) characters mean <i>any number of characters of</i></p> </td></tr> </table>	Attribut- e	Description		<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.) characters mean <i>any number of characters of</i></p>
Attribut- e	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. <p>Example:</p> <p>ciaValue in</p>  <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> is not null Finds all non-blank values. Click here for an example. <p>Example: ciaValue is not null matches any incident with a varbind that contains a value.</p> <ul style="list-style-type: none"> is null Finds all blank values. Click here for an example. <p>Example: ciaValue is null matches any incident with a varbind that does not contain a value.</p> <ul style="list-style-type: none"> like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.) characters mean <i>any number of characters of</i></p>				

Node Settings Suppression Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> </td></tr> </table>	Attribut- e	Description		<p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	not in	1		2
Attribut- e	Description								
	<p><i>any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div> <p>Operator Value</p> <table> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	not in	1		2				
not in	1								
	2								

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribut- e	Description		<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.
Attribut- e	Description						
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 						

Node Settings Suppression Attributes , continued

Name	Description																
	Payload Filter Editor Buttons <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.</td></tr> <tr> <td>Replace</td><td>Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.</td></tr> <tr> <td>AND</td><td> Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>OR</td><td> Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>NOT</td><td> Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div> </td></tr> <tr> <td>EXISTS</td><td> Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div> </td></tr> </table>	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.	Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.	AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>	EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div>
Button	Description																
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.																
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.																
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.																
AND	Inserts the AND Boolean Operator in the selected cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
OR	Inserts the OR Boolean Operator in the current cursor location. <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT. <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <div> Note: View the expression displayed under Filter String to see the logic of the expression as it is created. </div>																
EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <div> Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component </div>																

Node Settings Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> </td></tr> </table>	Button	Description		<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>
Button	Description						
	<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>						

Node Settings Suppression Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued						
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td><p>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</p><p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p></td></tr><tr><td>Delete</td><td><p>Deletes the selected expression.</p><p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p></td></tr></table>	Button	Description		<p>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>
	Button	Description					
		<p>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>					
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>						

Configure Incident Enrichment Settings for Node Group (Management Events)

Note: Node Settings override any other Enrichment settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to enhanced a specified incident configuration based on the Source Node's participation in a Node Group. The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature
- Message
- Assigned To










Note: You can also enhance the incident configuration based on the Source Object's participation in an Interface Group. See ["Configure Incident Enrichment Settings for an Interface Group \(Management Events\)" on page 1267](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.

For information about each Node Settings tab:

For information about each Enrichment tab:

To configure Enrichment settings for a Node Group:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  New icon and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Configure the desired Enrichment behavior (see the "Enrich Configuration Attributes" table)
8. Click  **Save and Close** to save your changes and return to the previous form.










Node Settings Enrichment Configuration Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none">• Address• Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.)• Card• Connection• Correlation• Interface• Node










¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Node Settings Enrichment Configuration Attributes , continued

Name	Description
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p> <p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine </div>

Node Settings Enrichment Configuration Attributes , continued

Name	Description
	<ul style="list-style-type: none">  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> <p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (Management Events)" on page 1248</p> <p>"Include Custom Incident Attributes in Your Message Format (Management Events)" on page 1255</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Custom Incident Attributes to Enrich an Incident Configuration (Node Settings) (Management Events)

The Custom Incident Attributes (CIAs) tab enables you to specify additional CIAs to be saved with an incoming incident. The persisted data might then be used as an argument to an action for the incident.






When creating a CIA for an incident configuration, you can specify any of the following values:








- Custom Attribute on the source node
- Custom Attribute on the interface (source object)

You also specify the Custom Incident Attribute name that will store this information.

For information about each Enrichment tab:

To create a Custom Incident Attribute to enrich an incident configuration:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:

- a. To create an Enrichment configuration, click the  New icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  Delete icon.
7. Make sure the Enrichment settings are configure. See ["Configure Incident Enrichment Settings for Node Group \(Management Events\)" on page 1311](#) for more information.
8. Navigate to the **Custom Incident Attributes** tab.
9. Do one of the following:
 - a. To create a Custom Incident Attribute, click the  New icon, and continue.
 - b. To edit a Custom Incident Attribute, select a row, click the  Open icon, and continue.
 - c. To delete a Custom Incident Attribute, select a row and click the  Delete icon.
10. Configure the Custom Incident Attribute (see the "Custom Incident Attribute" table).
11. Click  **Save and Close** to save your changes and return to the previous form.









Custom Incident Attribute

Name	Description
Custom Incident Attribute Name	<p>Name used to identify the Custom Incident Attribute you are configuring. The name limit is 255 characters. Alpha-numeric characters are permitted. No spaces or special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <div>Note: Make sure to note this name if you plan to filter on the value using the Payload Filter tab. See "Configure a Payload Filter to Enrich an Incident Configuration (Interface Settings) (Management Events)" on page 1274 for more information.</div>
Type	<p>Specifies whether you are using a Custom Attribute on a node or a Custom Attribute on an interface. Possible values are:</p> <ul style="list-style-type: none">• Node Custom Attribute• Interface Custom Attribute
Custom Attribute Name	<p>Used to determine the value to be assigned to the Custom Incident Attribute you are configuring. Enter either of the following:</p> <ul style="list-style-type: none">• Name of the Custom Attribute on the source node• Name of the Custom Attribute on the interface (source object)

Configure a Payload Filter to Enrich an Incident Configuration (Node Settings) (Management Events)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be enriched. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Management Events Configuration** form:
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  **New** icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  **Open** icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  **Delete** icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  **New** icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Enrichment** tab.
6. Do one of the following:
 - a. To create an Enrichment configuration, click the  **New** icon, and continue.
 - b. To edit an Enrichment configuration, select a row, click the  **Open** icon, and continue.
 - c. To delete an Enrichment configuration, select a row and click the  **Delete** icon.

7. Make sure you configure the Enrichment settings. See "[Configure Incident Enrichment Settings for Node Group \(Management Events\)](#)" on page 1311 for more information.
8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, AND, NOT

Filter String: (() AND NOT ())

Text: Highlight the location in the logic flow, then click Insert to define the filter requirement

Dropdown: Insert

Buttons: AND, OR, NOT, EXISTS, NOT EXISTS, Delete

10. Click **Save and Close**.
11. Click **Save and Close** to save your changes and return to the previous form.

Payload Filter Editor Settings

Attribute	Description
Attribute	The attribute name on which NNMI searches. Filterable attributes include the


Payload Filter Editor Settings, continued

Attribute	Description
	<p>following:</p> <ul style="list-style-type: none"> • <code>ciaName</code> • <code>ciaValue</code>
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: <code>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="451 1604 878 1719"> <p>The screenshot shows a UI element for the 'between' operator. It consists of a label 'Operator' and a dropdown menu currently showing 'between'. To the right of the dropdown is a 'Value' section with two input fields. The top field contains the number '1' and the bottom field contains the number '4'.</p> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p>

Payload Filter Editor Settings, continued

Attribute	Description				
	<p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div data-bbox="446 667 836 802" data-label="Form"> <table> <thead> <tr> <th>Operator</th> <th>Value</th> </tr> </thead> <tbody> <tr> <td>in</td> <td>4 5</td> </tr> </tbody> </table> </div> matches any incident with a varbind value of either 4 or 5. <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not have a value. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p>	Operator	Value	in	4 5
Operator	Value				
in	4 5				

Payload Filter Editor Settings, continued

Attribute	Description
	<p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code>  <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in <code>\Q<literal_value>\E</code> as shown in the Examples listed below.</p> <p>Example:</p>

Payload Filter Editor Settings, continued

Attribute	Description
	<p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <div> <p>Note:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the <code>between</code> Operator causes two value fields to be displayed. The <code>between</code>, <code>in</code> and <code>not in</code> operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
NOT	Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.

Additional Filters Editor Buttons, continued

Button	Description
	<p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Incident Dampening Settings for a Node Group (Management Events)

Note: Node Settings override any other Dampening settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to delay the following for an incident configuration based on the Source Node's participation in a Node Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server -- [click here for more information](#).

- Appearance within Incident views in the NNMi Console

Note: You can configure the Dampening settings based on the Source Object's participation in

an Interface Group. See ["Configure Incident Dampening Settings for an Interface Group \(Management Events\)" on page 1282](#) for more information.

Tip: See ["Create Node Groups" on page 326](#) for more information about Node Groups.







For information about each Node Settings tab:

When using the Dampening configuration, note the following:

- NNMi initially assigns incidents with Dampening settings configured a Lifecycle State of DAMPENED.
- After the dampen interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.

To configure the Dampening settings based on a Node Group:

1. Navigate to the **Management Events Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Dampen** tab.
6. Configure the desired Dampen behavior (see [table](#)).
7. Click  **Save and Close** to save your changes and return to the previous form.

Node Settings Dampen Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's Dampening settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Hour	Specifies the number of hours to be used for the dampen interval.
Minutes	<p>Specifies the number of minutes to be used for the dampen interval.</p> <p>Note: The maximum dampen interval is 60 minutes.</p>
Seconds	Specifies the number of seconds to be used for the dampen interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (<code>java.util.regex Pattern</code> class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre>AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind <code>.1.3.6.1.4.1.9.9.13.1.2.1.7</code> value of 5.</p>




Node Settings Dampen Attributes , continued

Name	Description
	<ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3.
Payload Filter Editor Settings	
Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.

Node Settings Dampen Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 	Operator	Value	between	1		4
Attribute	Description										
	<ul style="list-style-type: none"> • < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> 	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Node Settings Dampen Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1334 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> </td></tr> </table>	Attribute	Description		<div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1334 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div>
Attribute	Description				
	<div data-bbox="557 457 948 592">  </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <div data-bbox="573 711 1320 777"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="573 1713 1334 1812"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div>				

Node Settings Dampen Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div data-bbox="555 1129 979 1262"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="555 1402 1356 1509"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re- </td></tr> </table>	Attribute	Description		<p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div data-bbox="555 1129 979 1262"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="555 1402 1356 1509"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re- 	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>
Attribute	Description								
	<p>Example:</p> <p><code>ciaName like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p><code>ciaValue not in</code></p> <div data-bbox="555 1129 979 1262"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="555 1402 1356 1509"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/re- 	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>				
Operator	Value								
not in	<div> <div>1</div> <div>2</div> </div>								

Node Settings Dampen Attributes , continued

Name	Description												
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table> <p>Payload Filter Editor Buttons</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td>Append</td><td>Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.</td></tr> <tr> <td>Insert</td><td>Inserts the current expression (Attribute, Operator, and Value) in front</td></tr> </table>	Attribute	Description		<p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 	Button	Description	Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.	Insert	Inserts the current expression (Attribute, Operator, and Value) in front
Attribute	Description												
	<p>gex/Pattern.html for more information. Click here for an example.</p> <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>												
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 												
Button	Description												
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.												
Insert	Inserts the current expression (Attribute, Operator, and Value) in front												

Node Settings Dampen Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p>

Node Settings Dampen Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> </td></tr> </table>	Button	Description		<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre>
Button	Description						
	<p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre>						

Node Settings Dampen Attributes , continued

Name	Description						
	Payload Filter Editor Buttons, continued						
	<table><tr><th>Button</th><th>Description</th></tr><tr><td></td><td>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</td></tr><tr><td>Delete</td><td>Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</td></tr></table>	Button	Description		Note: View the expression displayed under Filter String to see the logic of the expression as it is created.	Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.
Button	Description						
	Note: View the expression displayed under Filter String to see the logic of the expression as it is created.						
Delete	Deletes the selected expression. Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.						

Configure Incident Actions for a Node Group (Management Events)

For information about each Node Settings tab:

Note: Node Settings override any other Actions settings for this incident, except those configured on the Interface Settings tab.

NNMi enables you to configure incident actions based on a Source Node's participation in a Node Group.

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.







Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable ☒ on the Actions tab or using the **Actions** → **Enable Configuration** option.

You can configure actions for incidents generated from SNMP Trap Incidents, Syslog Messages Incidents and the NNMi Management Events Incidents. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See "[Lifecycle Transition Action Form \(Management Events\)](#)" on page 1386 for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See "[Lifecycle Transition Action Form \(Management Events\)](#)" on page 1386 for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the `incidentActions.*.*.log` file. See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

To configure an automatic action for an incident:









1. Navigate to the **Management Events Configuration** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create a new incident configuration, click the  New icon.
 - ii. To edit an existing incident configuration, select a row, click the  Open icon, and continue.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, double-click the row representing the configuration you want to edit.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Actions** tab.
6. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, double-click the row representing the configuration you want to edit, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
7. In the ["Lifecycle Transition Action Form \(Management Events\)" on page 1386](#), provide the required information.
8. Click  **Save and Close** to save your changes and return to the **Management Event Configuration** form.

The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Configure a Payload Filter for an Incident Action (Node Settings) (Management Events)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Management Events Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Node Settings** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Make sure you configure the basic Node Setting behavior. See ["Configure Node Settings for a Management Event Incident" on page 1301](#) for more information.
5. Select the **Actions** tab.
6. Do one of the following:
 - a. To create an Action configuration, click the  New icon, and continue.
 - b. To edit an Action configuration, select a row, click the  Open icon, and continue.
 - c. To delete an Action configuration, select a row, and click the  Delete icon.
7. Make sure the Action settings are configured. See ["Configure Incident Actions for a Node Group \(Management Events\)" on page 1335](#) for more information.

8. Select the **Payload Filter** tab.
9. Define your Payload Filter (see [table](#)).
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter requirement within those parentheses:

Filter Editor

Attribute: ciaName Operator: = Value: .1.3.6.1.4.1.9.9.13.1.2.1.7

Buttons: Append, Insert, Replace

Logic Flow: AND, AND, NOT

Filter String: (() AND NOT ())

Highlight the location in the logic flow, then click Insert to define the filter requirement

Insert dropdown: Insert, AND, OR, NOT, EXISTS, NOT EXISTS, Delete

10. Click **Save and Close**.
11. Click **Save and Close** to save your changes and return to the previous form.


Payload Filter Editor Settings

Attribute	Description
Attribute	The attribute name on which NNMi searches. Filterable attributes include the following: <ul style="list-style-type: none"> • ciaName

Payload Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> • ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> • = Finds all values equal to the value specified. Click here for an example. Example: ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7. • != Finds all values not equal to the value specified. Click here for an example. Example: ciaName != .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. • < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident with a varbind value less than 6. • <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident with a varbind value less than or equal to 6. • > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident with a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind with a value equal to and between the two values specified. Click here for an example. Example: ciaValue between <div data-bbox="446 1470 872 1587" data-label="Form"> <p>The screenshot shows a web interface for configuring a filter. It has two columns: 'Operator' and 'Value'. Under 'Operator', a dropdown menu is set to 'between'. Under 'Value', there are two input fields. The first field contains the number '1' and the second field contains the number '4'.</p> </div> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <p>Note: As shown in the example, each value must be entered on a separate line.</p>

Payload Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div data-bbox="456 762 1370 873"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not have a value. like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="456 1562 1370 1673"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> Examples: ciaName like \Q.1.3.6.1.4.1.9.9\E.* finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.

Payload Filter Editor Settings, continued

Attribute	Description						
	<p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code> <div data-bbox="446 798 872 928" data-label="Form"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>not in</td><td>1</td></tr> <tr> <td></td><td>2</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="462 1052 1320 1117" data-label="Text"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <div data-bbox="462 1568 1341 1633" data-label="Text"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a</p> 	Operator	Value	not in	1		2
Operator	Value						
not in	1						
	2						

Payload Filter Editor Settings, continued

Attribute	Description
	varbind value that includes the string Chicago .
Value	<p>The value for which you want NNMi to search.</p> <div> <p>Note:</p> <ul style="list-style-type: none"> The values you enter are case sensitive. NNMi displays a variable number of value fields depending on the Operator selected. For example, the <i>between</i> Operator causes two value fields to be displayed. The <i>between</i>, <i>in</i> and <i>not in</i> operators require that each value be entered on a separate line. </div>

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the Filter String.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Appends, inserts, or replaces the AND Boolean Operator in the selected cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
OR	<p>Appends, Inserts, or replaces the OR Boolean Operator in the current cursor location.</p> <div> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </div>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created .</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p>

Additional Filters Editor Buttons, continued

Button	Description
	<p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Diagnostics Selections for a Node Group (Management Events)

For information about each Node Settings tab: .










Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

Note: Node Settings override any other Diagnostics Selections settings for this incident, except those configured on the Interface Settings tab.

The Diagnostic Selections form enables you to configure NNMi to automatically gather NNM iSPI NET diagnostic information for the Incident you are configuring. When using this form, you specify the diagnostics you want to run on each applicable node in the specified Node Group.

To configure Diagnostics to run on a Source Node for an incident:

1. Navigate to the **Diagnostics Selection** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:

- To create an Incident configuration, click the  New icon.
 - To edit an Incident configuration, select a row, click the  Open icon, and continue.
- e. Navigate to **Node Settings** tab, and do one of the following:
- To create a Node Settings configuration, click the  New icon.
 - To edit a Node Settings configuration, select a row, click the  Open icon, and continue.
 - To delete a Node Settings configuration, select the Node setting, and click the  Delete icon.
- f. Navigate to the **Diagnostic Selection** tab, and do one of the following:
- To create a Diagnostic Selection setting, click the  New icon, and continue.
 - To edit a Diagnostic Selection setting, select a row, click the  Open icon, and continue.
 - To delete a Diagnostic Selection setting, select a row, and click the  Delete icon.
2. Provide the required information (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the previous form.

After you configure the Diagnostic for the incident and Node Group, the Diagnostic must match the following criteria before the Diagnostic runs:

- The Source Node must be in the specified Node Group.
- The Diagnostic must be valid for the Source Node. (For example, only Nortel switch Diagnostics are run on Nortel switches.)
- The incident's current lifecycle state must match a lifecycle state for which it was configured. (For example, if you configure the Incident to run a specified Diagnostic when the incident is Closed, then if the current Incident's Lifecycle State is Closed, NNMi runs that Diagnostic.)

Note: If a Source Node is in more than one Node Group, the Diagnostic is only run on the node the first time NNMi finds a match for that Source Node based on the configuration Ordering field.

If these criteria are met, NNM iSPI NET runs the Diagnostics and generates Diagnostic reports to help you solve the problem on the Source Node.




After you configure Diagnostics for an incident, you can also run Diagnostics and access the Diagnostics reports on demand, using **Actions** → **Run Diagnostics** in the Incident form. The

same criteria apply (see the [criteria](#) above). See [Incident Form:Diagnostics Tab](#) for more information.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

You can also run and access Diagnostics reports from a Node form. See [Node Form: Diagnostics Tab](#) for more information.

Diagnostic Settings Attributes

Attribute	Description
Flow Definition	<p>Select the Diagnostic (Flow Definition) you want to use for the specified Node Group.</p> <p>Click the  Lookup icon and choose one of the following options:</p> <ul style="list-style-type: none">  Show Analysis to display Analysis Pane information for the Flow Definition name displayed. (See Use the Analysis Pane for more information about the Analysis Pane.)  Quick Find to view the list of possible diagnostic Flow Definitions. <p>NNMi provides diagnostics for the following types of devices:</p> <ul style="list-style-type: none"> ■ Cisco switch ■ Cisco router ■ Cisco switch/router ■ Nortel switch <p>See "Diagnostics (Flows) Provided by NNM iSPI NET" on page 859 for more information about the diagnostics provided and the devices to which they apply.</p>
Lifecycle State	<p>Incident Lifecycle State of the target Incident.</p> <p>If the incident's Lifecycle State matches the value specified here, the Diagnostic runs.</p> <p>The Diagnostic automatically runs on each applicable Source Node in the specified Node Group if the incident has the Lifecycle State currently configured in this attribute of the Diagnostic (Flow Definition - set of automated commands).</p>
Enable	<p>Use this attribute to temporarily disable an incident's Diagnostics settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>

Configure Suppression Settings for a Management Event Incident

For information about each Management Events tab:

NNMi enables you to suppress incidents based on Interface Group, Node Group, or default Suppression settings. NNMi applies your Suppression settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)
3. Suppression configuration settings without specifying an Interface Group or Node Group (Management Event Configuration Form: Suppression tab)

A Payload Filter enables you to use the data that is included with any of the following items before they are stored as incidents in NNMi:

- Traps generated from an SNMP agent
- Syslog Messages
- Management incidents that are generated by NNMi





Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as CIA (Custom Incident Attribute) names and values. For example, you might want NNMi to suppress a particular status change notification trap for a specified Node Group or Interface Group. To do so, you could include the name of the trap varbind that stores this information as well as the particular status change value string the traps that you want to suppress should contain.

See ["Configure Incident Suppression Settings for an Interface Group \(Management Events\)" on page 1258](#) for information about how to suppress an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Suppression Settings for a Node Group \(Management Events\)" on page 1302](#) for more information about how to suppress an incident for a Node Group with or without a Payload Filter.

To configure suppression for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.

- d. Do one of the following:
 - i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Suppression** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Suppression Attributes

Name	Description
Enable	<p>Use this attribute to temporarily disable an incident's suppression settings:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none"> • Payload Filter expressions for the <code>like</code> and <code>not like</code> operators use the syntax defined for java regular expressions (java.util.regex Pattern class). • You must use a <code>ciaName</code> that already exists in the trap or event you are configuring. • Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. • View the expression displayed under Filter String to see the logic of the expression as it is created. • The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p> <pre> AND ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5 </pre>




Suppression Attributes , continued

Name	Description						
	<p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <h4>Payload Filter Editor Settings</h4> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue </td></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p> </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p>
Attribute	Description						
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ciaName ciaValue 						
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> = Finds all values equal to the value specified. Click here for an example. <p>Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7.</p>						

Suppression Attributes , continued

Name	Description										
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div> </td></tr> </table>	Attribute	Description		<ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div>	Operator	Value	between	1		4
Attribute	Description										
	<ul style="list-style-type: none"> != Finds all values not equal to the value specified. Click here for an example. Example: <code>ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7</code> matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. < Finds all values less than the value specified. Click here for an example. Example: <code>ciaValue < 6</code> matches any incident that contains a varbind with a value less than 6. <= Finds all values less than or equal to the value specified. Click here for an example. Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind with a value less than or equal to 6. > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind with a value greater than 4. >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. between Finds all values equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </table> matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4. <div> Note: As shown in the example, each value must be entered on a separate line. </div>	Operator	Value	between	1		4				
Operator	Value										
between	1										
	4										

Suppression Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>.
Attribut- e	Description				
	<ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in  matches any incident with a varbind value of either 4 or 5. <div> Note: As shown in the example, each value must be entered on a separate line. </div> NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line. • is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. • is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind that does not contain a value. • like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. 				

Suppression Attributes , continued

Name	Description								
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="548 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> </td></tr> </table>	Attribute	Description		<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="548 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p>	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>
Attribute	Description								
	<p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8.</p> <ul style="list-style-type: none"> • not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> <div data-bbox="548 1304 974 1438"> <table> <tr> <th>Operator</th><th>Value</th></tr> <tr> <td>not in</td><td> <div> <div>1</div> <div>2</div> </div> </td></tr> </table> </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p>	Operator	Value	not in	<div> <div>1</div> <div>2</div> </div>				
Operator	Value								
not in	<div> <div>1</div> <div>2</div> </div>								

Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribut- e</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div> </td></tr> <tr> <td>Value</td><td> <p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. </td></tr> </table>	Attribut- e	Description		<ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>	Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.
Attribut- e	Description						
	<ul style="list-style-type: none"> • not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p> </div>						
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line. 						

Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component</p>

Suppression Attributes , continued

Name	Description						
	<p>Payload Filter Editor Buttons, continued</p> <table> <tr> <th>Button</th><th>Description</th></tr> <tr> <td></td><td> <p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p> </td></tr> <tr> <td>NOT EXISTS</td><td> <p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> </td></tr> </table>	Button	Description		<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>	NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>
Button	Description						
	<p>of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>						
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p>						

Suppression Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	Deletes the selected expression. <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Enrichment Settings for a Management Event Incident

For information about each Management Events tab:

NNMi enables you to fine tune and enhance incidents based on Interface Group, Node Group, or default Enrichment settings. NNMi applies your Enrichment settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)
3. Enrich configuration settings without specifying an Interface Group or Node Group (Management Event Configuration Form: Enrichment tab)

The types of items you can fine tune and enhance for a selected incident configuration, include:

- Category
- Family
- Severity
- Priority
- Correlation Nature

- Message
- Assigned To

Note: Any configuration you specify for Severity, Priority, or Message overrides those values provided in the Management Event Configuration Form: Basics information.

A Payload Filter enables you to use the data that is included with any of the following items before they are stored as incidents in NNMi:

- Traps generated from an SNMP agent
- Syslog Messages
- Management incidents that are generated by NNMi

Examples of the type of data that can be used as a Payload Filter include SNMP trap varbind names and values as well as CIA (Custom Incident Attribute) names and values. For example, you might want NNMi to suppress a particular status change notification trap for a specified Node Group or Interface Group. To do so, you could include the name of the trap varbind that stores this information as well as the particular status change value string the traps that you want to suppress should contain.







Note: The CIA added to an incident must be provided by NNMi. You cannot create CIAs.

See ["Configure Incident Enrichment Settings for an Interface Group \(Management Events\)" on page 1267](#) for information about how to enrich an incident for an Interface Group with or without a Payload Filter.

See ["Configure Incident Enrichment Settings for Node Group \(Management Events\)" on page 1311](#) for more information about how to enrich an incident for a Node Group with or without a Payload Filter.

To configure Enrichment settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:


1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations** .
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Enrichment** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Provide the required information (see [table](#))
5. Click  **Save and Close** to save your changes and return to the previous form.

Enrichment Attributes

Name	Description
Category	<p>Use the Category attribute to customize the category for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">• Accounting• Application Status• Configuration• Fault• Performance• Security• Status <p>See "Specify Category and Family Attribute Values for Organizing Your Incidents (SNMP Trap Incident)" on page 898 for more information.</p>
Family	<p>Use the Family attribute to customize the Family for this incident configuration. Select from the drop-down list or create a new value. For example, some of the values provided by NNMi include:</p> <ul style="list-style-type: none">• Address
















Enrichment Attributes , continued

Name	Description
	<ul style="list-style-type: none"> Aggregated Port (Interfaces using Link Aggregation¹ or Split Link Aggregation² protocol. See Interface Form: Link Aggregation tab.) Card Connection Correlation Interface Node
Severity	<p>The incident Severity represents the seriousness calculated for the incident. Use the Severity attribute to specify the severity that should be assigned to the incident you are configuring. Possible values are described below:</p> <p>Normal - Indicates there are no known problems related to the associated object. This Severity is meant to be informational. Generally, no action is needed for these incidents.</p> <p>Warning - Indicates there might be a problem related to the associated object.</p> <p>Minor - Indicates NNMi has detected problems related to the associated object that require further investigation.</p> <p>Major - Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</p> <p>Critical - Indicates NNMi has detected problems related to the associated object that require immediate attention.</p>
Priority	<p>Used to communicate the urgency of resolving the selected incident. You control this value. NNMi sets this value to null by default. The lower the number the higher the priority.</p> <p>Possible values are:</p> <p>5  None</p>



¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Enrichment Attributes , continued

Name	Description
	<p>4  Low</p> <p>3  Medium</p> <p>2  High</p> <p>1  Top</p> <p>Note: The icons are displayed only in table views.</p>
Correlation Nature	<p>Use the Correlation Nature to customize the Correlation Nature for this incident configuration. Possible values include:</p> <ul style="list-style-type: none">  Info  None  Root Cause (or User Root Cause) <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: When using Incident views:</p> <ul style="list-style-type: none">  Root Cause value = determined by NNMi's Causal Engine  User Root Cause = your NNMi administrator configured NNMi to always treat this Incident as Correlation Nature: Root Cause </div> <ul style="list-style-type: none">  Secondary Root Cause  Symptom  Stream Correlation  Service Impact  Dedup Stream Correlation  Rate Stream Correlation <p>See Incident Form: General Tab for more information.</p>
Message Format	<p>When configuring an incident, specify how the incident message appears in the incident view. The string you specify in the Message Format attribute is visible in an incident view.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The incident message limit is 1024 characters. If you exceed this limit, NNMi truncates the value starting from the right.</p> </div>

Enrichment Attributes , continued

Name	Description
	<p>You can use any combination of default and custom attributes:</p> <p>"Valid Parameters for Configuring Incident Messages (SNMP Trap Incident)" on page 904</p> <p>"Include Custom Incident Attributes in Your Message Format (SNMP Trap Incident)" on page 911</p>
Assigned To	<p>Use to specify the owner of any incident generated for this incident configuration.</p> <p>Click the  Lookup icon and select  Quick Find to select a valid user name.</p> <p>Note: You can also begin to type a valid user name and use the auto-complete feature to select the user name of interest.</p>
Description	<p>Use the Description attribute to provide additional information that you want to note about the current enhancement configuration. This description applies only to the enhancement configuration and does not appear when NNMi displays any associated incident.</p> <p>Type a maximum of 1024 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p>

Configure Dampening Settings for a Management Event Incident

For information about each Management Events tab:

NNMi enables you to delay the following for an incident configuration based on the Source Object's participation in an Interface Group:

- Execution of Incident Actions
- Execution of Diagnostics

Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) and requires installation of a Diagnostic Server – [click here for more information](#).

- Appearance within Incident views in the NNMi Console

You can configure the Dampening settings based on Interface Group, Node Group, or default Dampening settings. NNMi applies your Dampening settings in the following order. Only the first match applies.

1. Interface Group (Management Event Configuration Form: Interface Settings tab)
2. Node Group (Management Event Configuration Form: Node Settings tab)
3. Dampening configuration settings without specifying an Interface Group or Node Group (Management Event Configuration Form: Dampening tab)

When using the Dampening configuration, note the following:

- Duplicate and Rate Correlation incidents inherit the Dampening settings from their Correlated Children. If the Correlated Children are Closed while Dampened, and therefore deleted, NNMi retains the parent Duplicate or Rate Correlation incident. See ["Correlate Duplicate Incidents \(Deduplication Configuration\)" on page 745](#) and ["Track Incident Frequency \(Rate: Time Period and Count\)" on page 746](#) for more information about Duplicate and Rate Correlation incidents.

Note: NNMi administrators can view the number of incidents Closed and deleted while dampened. Access the **Help** → **System Information** → **Health** tab, click the View Detailed Health Report button, and search for the word dampened.


- After the Dampen Interval has passed, NNMi changes the Lifecycle State to REGISTERED.

See [About the Incident Lifecycle](#) for more information about Lifecycle State.



See ["Configure Incident Dampening Settings for an Interface Group \(Management Events\)" on page 1282](#) for information about how to configure Dampening settings for an Interface Group with or without a Payload Filter.

See ["Configure Incident Dampening Settings for a Node Group \(Management Events\)" on page 1325](#) for more information about how to configure Dampening settings for a Node Group with or without a Payload Filter.

To configure Dampening settings for an incident using a Payload Filter without an Interface Group or Node Group Filter:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create a configuration, click the  New icon, and continue.
 - ii. To edit configuration, double-click the row representing the configuration you want to

edit, and continue.

- iii. To delete a configuration, select a row, and click the  Delete icon.
2. Select the **Dampening** tab.
3. Provide the required information (see [table](#))
4. Click  **Save and Close** to save your changes and return to the previous form.

Dampening Attributes

Name	Description
Enable	Use this attribute to temporarily disable an incident's Dampening settings: Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.
Hour	Specifies the number of hours to be used for the Dampen Interval.
Minutes	Specifies the number of minutes to be used for the Dampen Interval.
Seconds	Specifies the number of seconds to be used for the Dampen Interval.
Payload Filter	<p>The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents to be suppressed, enriched, or dampened. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.</p> <p>When creating a Payload Filter, note the following:</p> <ul style="list-style-type: none">■ Payload Filter expressions for the like and not like operators use the syntax defined for java regular expressions (java.util.regex Pattern class).■ You must use a ciaName that already exists in the trap or event you are configuring.■ Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.■ View the expression displayed under Filter String to see the logic of the expression as it is created.■ The AND and OR Boolean Operators must contain at least two expressions as shown in the example below. <p>The following example filters incidents on voltage state:</p>

Dampening Attributes , continued

Name	Description				
	<p>AND</p> <pre>ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 ciaValue = 5</pre> <p>NNMi evaluates the expression above as follows:</p> <pre>(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)</pre> <p>NNMi finds all incidents with a varbind .1.3.6.1.4.1.9.9.13.1.2.1.7 value of 5.</p> <ul style="list-style-type: none"> ■ The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected. ■ The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. ■ You can include more than one varbind in the same Payload Filter expression as shown in the following example: <pre>((ciaName like \Q.1.3.6.1.4.1.9.9\E.* AND ciaValue = 25) AND (ciaName like \Q.1.3.6.1.2.1.2.2.1.1.3\E.* AND ciaValue = 3))</pre> <p>In this example, a given trap must meet each of the following criteria:</p> <ul style="list-style-type: none"> ○ Contain a varbind whose Object Identifier (OID) matches the regular expression \Q.1.3.6.1.4.1.9.9\E.* and has a value of 25. ○ Contain a varbind whose OID matches the regular expression \Q.1.3.6.1.2.1.2.2.1.1.3\E.* and has a value of 3. <h4>Payload Filter Editor Settings</h4> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Attribute</td><td> <p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue </td></tr> </table>	Attribute	Description	Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue
Attribute	Description				
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none"> ■ ciaName ■ ciaValue 				

Dampening Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Operator</td><td> <p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. ■ != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. ■ < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. ■ <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. ■ > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. ■ >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. ■ between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between </td></tr> </table>	Attribute	Description	Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. ■ != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. ■ < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. ■ <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. ■ > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. ■ >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. ■ between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between
Attribute	Description				
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none"> ■ = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value of .1.3.6.1.4.1.9.9.13.1.2.1.7. ■ != Finds all values not equal to the value specified. Click here for an example. Example: ciaName! = .1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with a name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7. ■ < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind with a value less than 6. ■ <= Finds all values less than or equal to the value specified. Click here for an example. Example: ciaValue <= 6 matches any incident that contains a varbind with a value less than or equal to 6. ■ > Finds all values greater than the value specified. Click here for an example. Example: ciaValue > 4 matches any incident that contains a varbind with a value greater than 4. ■ >= Finds all values greater than or equal to the value specified. Click here for an example. Example: ciaValue >= 4 matches any incident that contains a varbind with values greater than or equal to 4. ■ between Finds all values equal to and between the two values specified. Click here for an example. Example: ciaValue between 				




Dampening Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> ■ in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. ■ is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind </td></tr> </table>	Attribute	Description		<div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> ■ in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. ■ is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind
Attribute	Description				
	<div> <div>Operator</div> <div>Value</div> <div>between</div> <div>1</div> <div>4</div> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <ul style="list-style-type: none"> ■ in Finds any match to at least one value in a list of values. Click here for an example. Example: ciaValue in <div> <div>Operator</div> <div>Value</div> <div>in</div> <div>4</div> <div>5</div> </div> <p>matches any incident with a varbind value of either 4 or 5.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ is not null Finds all non-blank values. Click here for an example. Example: ciaValue is not null matches any incident with a varbind that contains a value. ■ is null Finds all blank values. Click here for an example. Example: ciaValue is null matches any incident with a varbind 				

Dampening Attributes , continued

Name	Description				
	Payload Filter Editor Settings, continued <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <p>that does not contain a value.</p> <ul style="list-style-type: none"> ■ like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p> </td></tr> </table>	Attribute	Description		<p>that does not contain a value.</p> <ul style="list-style-type: none"> ■ like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p>
Attribute	Description				
	<p>that does not contain a value.</p> <ul style="list-style-type: none"> ■ like Finds matches using the syntax defined for java regular expressions. See the Pattern (Java Platform SE6) API documentation at : http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for more information. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location.</i></p> <p>The period (.) character means <i>any single character of any type at this location.</i></p> <div> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that begins with 1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> <p>ciaValue like .*Chicago.* finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> ■ not between Finds all values except those between the two values specified. Click here for an example. <p>Example: ciaValue not between 5 8 matches an incident that contains a varbind with the values less than 5 or greater than 8 .</p> <ul style="list-style-type: none"> ■ not in Finds all values except those included in the list of values. Click here for an example. <p>Example:</p> <p>ciaValue not in</p>				

Dampening Attributes , continued

Name	Description				
	<p>Payload Filter Editor Settings, continued</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td></td><td> <div data-bbox="583 485 1015 621">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="599 774 1328 840"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="599 1491 1317 1589"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p> </td></tr> </table>	Attribute	Description		<div data-bbox="583 485 1015 621">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="599 774 1328 840"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="599 1491 1317 1589"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p>
Attribute	Description				
	<div data-bbox="583 485 1015 621">  </div> <p>matches any incident that contains a varbind with values other than 1 and 2.</p> <div data-bbox="599 774 1328 840"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> ■ not like Finds all that do not have the values specified using the syntax defined for Java regular expressions. See the Pattern (Java Platform SE6) API documentation at: http://download.oracle.com/javase/6/docs/api/java/util/regex/Pattern.html for more information. Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <div data-bbox="599 1491 1317 1589"> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> </div> <p>Example:</p> <p>ciaName not like \Q.1.3.6.1.4.1.9.9\E.* matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9 and (optionally) ends with any number of characters.</p>				

Dampening Attributes , continued

Name	Description
Payload Filter Editor Settings, continued	
Attribute	Description
	ciaValue not like .*Chicago.* finds all traps or events that do not contain a varbind value that includes the string Chicago .
Value	<p>The value for which you want NNMI to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ The values you enter are case sensitive. ■ NNMI displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. ■ The between, in and not in operators require that each value be entered on a separate line.
Payload Filter Editor Buttons	
Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	Can be used in any part of the Filter String to specify that NNMI

Dampening Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	<p>should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filer String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to</p>

Dampening Attributes , continued

Name	Description
Payload Filter Editor Buttons, continued	
Button	Description
	see the logic of the expression as it is created.
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>

Configure Deduplication for a Management Event Incident

For information about each Management Events tab:

The deduplication configuration determines what values NNMi should match to detect when an SNMP Trap Incident, Syslog Messages Incident or Management Event Incident is a duplicate.





Note the following:

- Suppression, Enrichment, and Dampening are not supported for Deduplication incidents.
- NNMi applies only one deduplication configuration per incident . If NNMi generates an incident using a specified deduplication configuration, NNMi continues to correlate duplicate incidents using the original configuration. To use a different deduplication configuration for an incident, first delete the current deduplication incident (created using the original deduplication configuration). NNMi generates the next deduplication incident according to the new deduplication configuration settings.
- NNMi continues to update the duplicate count regardless of an incident's lifecycle state. For example, if an incident's **Lifecycle State** is set to **Closed**, the duplicate count continues to be incremented. See [About the Incident Lifecycle](#) for more information. This behavior helps you identify situations in which the incident is not yet fixed. Take note if the Duplicate Count is incremented after a lengthy time period has elapsed, which might indicate there is a new problem with the node, interface, or address.
- Each time you stop and restart ovjboss, any incidents that have not yet been correlated or persisted are lost. This means that after a restart of ovjboss, an incoming incident might not be correlated as expected. For example, after a restart of ovjboss, a duplicate incident might not be correlated under its original parent incident. Instead, a new parent incident might be generated. See ["Stop or Start an NNMi Process" on page 87](#) for more information about starting and stopping the ovjboss process.
- If a Duplicate Correlation Incident is dampened, note the following:
 - Duplicate Correlation Incidents inherit the Dampening settings from its Correlated Children.
 - NNMi always retains the Parent Duplicate Correlation incident, even if its Child Incidents are Closed and subsequently deleted.

See ["Dampening Incident Configurations" on page 769](#) for more information about Dampening an incident configuration.

To specify or delete a deduplication configuration:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.

- b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - i. To create a deduplication configuration, click the  New icon, and continue.
 - ii. To edit a deduplication configuration, select a row, click the  Open icon, and continue.
 - iii. To delete a deduplication configuration, select a row, and click the  Delete icon.
2. Select the **Deduplication** tab.
 3. Provide the required information (see "Deduplication Attributes" table).
 4. Click  **Save and Close** to save your changes and return to the previous form.

Deduplication Attributes

Name	Description
Enabled	<p>Use this attribute to temporarily disable an incident's deduplication configuration:</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p> <div><p>Note: After a deduplication configuration is enabled, NNMi increments the Duplicate Count for an associated incident regardless of the Lifecycle State value. For example, if an incident's Lifecycle State is set to Closed, the duplicate count continues to be incremented. See About the Incident Lifecycle for more information.</p></div>
Count	<p>Specifies the number of duplicate incidents for the current configuration that NNMi stores at one time. For example, if the Count is 10, after NNMi receives 10 duplicate incidents, NNMi deletes the first (oldest) duplicate incident and keeps the eleventh. (NNMi stores ten maximum.)</p>
Hours	<p>Used with the Minute and Second Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Hour Interval value is 1, and no Minute or Second Intervals are specified, and the duplicate incident is not generated within one hour, NNMi generates a new duplicate incident the next time it occurs.</p>
Minutes	<p>Used with the Hour and Second interval to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Minute Interval is 30 and no Hour or Second Intervals are specified, and the duplicate incident is not generated within 30 minutes, NNMi</p>

Deduplication Attributes, continued

Name	Description
	generates a new duplicate incident the next time it occurs.
Seconds	Used with the Hour and Minute Intervals to specify the time that must elapse before a new duplicate incident is generated for this incident configuration. For example, if the Second Interval is 120 and no Hour or Minute Intervals are specified, and the duplicate incident is not generated within 120 seconds, NNMi generates a new duplicate incident the next time it occurs.
Parent Incident	<p>Used to specify the Incident Configuration that will be the Parent Incident for the incident you are configuring. For example, you might have created a Management Event Incident Configuration that could be used as the Parent Incident for SNMP Trap Incidents.</p> <p>When specifying the Parent Incident, you have the following options:</p> <ul style="list-style-type: none"> When you want to use a configuration that NNMi provides, use the default Duplicate Correlation incident configuration . If you select this option, the incident message for the Parent Incident begins as follows: <p>Duplicate Correlation for <incident_configuration_name></p> <p>For example if you are configuring a Node Down incident and select Duplicate Correlation as the Parent Incident, the Parent Incident message begins with: Duplicate Correlation for Node Down. Each Node Down incident that is a duplicate then appears correlated under the Duplicate Correlation for Node Down incident.</p> NNMi also enables you to customize the Parent Incident for a given deduplication scenario. If you have created a Management Event Incident Configuration to use for this deduplication scenario, select the Management Event Incident Configuration that you have created.
Comparison Criteria	<p>Specify the attribute values that must match before the incident is identified as a duplicate. The possible attributes consist of the following choices.</p> <ul style="list-style-type: none"> Name - The Name attribute value from the Incident form: General tab. CIA - Represents any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>

Deduplication Attributes, continued

Name	Description						
	<ul style="list-style-type: none"> • SourceNode - The Source Node attribute value from the Basics attributes listed on the Incident form. The Source Node value is the IP Address or Name of the node for which the incident was generated. <p>Note: The Source Node must be stored in the NNMi database.</p> <ul style="list-style-type: none"> • Source Object - The Source Object attribute value from the Basics attributes listed on the Incident form. <p>Note: The Source Object must be stored in the NNMi database.</p> <p>Caution: Each attribute value in the option you select must match before the incident is identified as a duplicate. For example, if you select Name, only the Incident Name value must match. If you select Name SourceNode SourceObject CIA, the Incident Name, Source Node, Source Object, and all Custom Incident Attribute values that you configure as a Parameter Value must match before NNMi identifies the incident as a duplicate.</p> <p>Selecting an option that includes CIA enables you to further refine the deduplication criteria. For example, you might want to configure deduplication for incidents with CIA values that specify the same State attribute value for a particular network object.</p> <p>For a description of each Comparison Criteria option, click here.</p> <table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td>Name</td><td>Value of the Name attribute from the Incident form: General tab must match.</td></tr> <tr> <td>Name CIA</td><td> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) </td></tr> </table>	Comparison Criteria	Description	Name	Value of the Name attribute from the Incident form: General tab must match.	Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.)
Comparison Criteria	Description						
Name	Value of the Name attribute from the Incident form: General tab must match.						
Name CIA	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ Name of a Custom Incident Attribute (CIA) provided by NNMi. (See the Incident form: Custom Attributes tab.) 						

Deduplication Attributes, continued

Name	Description								
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td> <ul style="list-style-type: none"> An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form" on page 746</p> </td></tr> <tr> <td>Name SourceNode</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form </td></tr> <tr> <td>Name SourceNode CIA</td><td> <p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form" on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters</p> </td></tr> </table>	Comparison Criteria	Description		<ul style="list-style-type: none"> An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form" on page 746</p>	Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form 	Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form" on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters</p>
Comparison Criteria	Description								
	<ul style="list-style-type: none"> An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form" on page 746</p>								
Name SourceNode	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form 								
Name SourceNode CIA	<p>Note: Select this option only if the Source Node is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> Name attribute from the Incident form: General tab The Source Node attribute value from the Basics attributes listed on the Incident form CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form" on page 746: <ul style="list-style-type: none"> The Value attribute from the Incident form: Custom Attributes tab An SNMP varbind Object ID An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters</p>								

Deduplication Attributes, continued

Name	Description										
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td>Form " on page 746</td></tr> <tr> <td>Name SourceObject</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. </td></tr> <tr> <td>Name SourceObject CIA</td><td> <p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> <tr> <td>Name SourceNode SourceObject</td><td> <p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p> </td></tr> </table>	Comparison Criteria	Description		Form " on page 746	Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 	Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 	Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p>
Comparison Criteria	Description										
	Form " on page 746										
Name SourceObject	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form. 										
Name SourceObject CIA	<p>Note: Select this option only if the Source Object is stored in the NNMi database.</p> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 										
Name SourceNode SourceObject	<p>Note: Select this option only if the Source Node and Source Object are stored in the NNMi database.</p>										


Deduplication Attributes, continued

Name	Description						
	<table> <tr> <th>Comparison Criteria</th><th>Description</th></tr> <tr> <td></td><td> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form </td></tr> <tr> <td> Name SourceNode SourceObject CIA </td><td> <div> Note: Select this option only if the Source Node and Source Object are stored in the NNMi database. </div> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> </td></tr> </table>	Comparison Criteria	Description		<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form 	Name SourceNode SourceObject CIA	<div> Note: Select this option only if the Source Node and Source Object are stored in the NNMi database. </div> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p>
Comparison Criteria	Description						
	<p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form 						
Name SourceNode SourceObject CIA	<div> Note: Select this option only if the Source Node and Source Object are stored in the NNMi database. </div> <p>Each of the following values must match:</p> <ul style="list-style-type: none"> • Name attribute from the Incident form: General tab • The Source Node attribute value from the Basics attributes listed on the Incident form • The Source Object attribute value from the Basics attributes listed on the Incident form • CIA - Represents the Value associated with any of the following items configured as a Parameter Value using the "Deduplication Comparison Parameters Form " on page 746: <ul style="list-style-type: none"> ■ The Name attribute from the Incident form: Custom Attributes tab ■ An SNMP varbind Object ID ■ An SNMP varbind position number <p>If you want to use CIA as part of your comparison criteria, see "Deduplication Comparison Parameters Form " on page 746</p> 						
Deduplication Comparison Parameters	<p><i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must populate one or more rows in this table.</p> <p>See "Deduplication Comparison Parameters Form " on page 746.</p>						


Deduplication Comparison Parameters Form (Management Events)

Comparison Parameter values enable accurate identification of duplicate incidents. Custom Incident Attributes (CIAs) are used as Comparison Parameter values. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Deduplication (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.








Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To specify a CIA to use in the identification criteria for duplicate incidents:

1. Navigate to the **Deduplication Comparison Params** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, navigate to the **Deduplication** tab.
 - f. Locate the **Deduplication Comparison Parameters** table.
 - g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Rate (Time Period and Count) for a Management Event Incident

For information about each SNMP Traps tab:

Use Rate configuration to track incident patterns *based on the number of incident reoccurrences within a specified time period*. After the count within the specified time period is reached, NNMi emits a Rate Correlation incident and continues to update the Correlation Notes with the number of occurrences within that rate.

Note: Suppression, Enrichment, and Dampening are not supported for Rate incidents.

As long as your defined criteria (Count and Hours, Minutes, Seconds) is sustained, the following information is updated in the Correlation Notes of the Rate Correlation incident:

- the actual number of occurrences of incidents for that sustained rate (Count)
- the sustained time interval (Hours, Minutes, Seconds)

For example, you can set a Rate configuration to track when a link is intermittently down at least three times in 30 minutes. NNMi shows the first occurrence of the rate incident in the incident view and uses Correlation Notes to update the number of incidents and time interval to reflect all the incremental incident occurrences and time periods. To continue the example, if the rate of three times in 30 minutes is sustained for 90 minutes, NNMi updates the Correlation Notes to specify that 9 incidents occurred in 90 minutes.



NNMi provides preconfigured Rate correlations. You can add new Rate correlations.


When you open the Incident form of the newest instance:

- On the General tab, two fields notify you that the Rate correlation is working:
 - **Correlation Nature:** Rate Stream Correlation
 - **Count:** x
- On the **Correlated Children** tab, each incident is listed in the table.
- If a Rate Correlation Incident is dampened, note the following:
 - Rate Correlation Incidents inherit the Dampening configuration settings from its Correlated Children.
 - NNMi always retains the Parent Rate Correlation Incident, even if its Child Incidents are Closed and subsequently deleted.



See [Dampening Incident Configurations](#) for more information about Dampening an incident configuration.

To establish a rate correlation within an incident configuration:

1. Navigate to the **Rate** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, locate the **Rate** tab.

2. Provide the definition for this Rate Configuration (see the "Rate Configuration Definition" table).
3. *Optional.* If your [Comparison Criteria](#) includes custom incident attributes (CIA) to identify one specific incident, use the Comparison Parameter List table to define each CIA. See ["Rate Comparison Parameters Form" on page 767](#).
4. Click  **Save and Close** to save your changes and return to the previous form.

Rate Configuration Definition

Attribute	Description
Enable	<p>Use this attribute to temporarily disable an incident's rate settings: If enabled, NNMi actively tracks any reoccurrences of the designated incident within the time period you specify, and generates a Rate incident.</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>
Count	Specify the number of reoccurrences required before your Rate Configuration starts working.
Hours	Used with the Minutes and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Minutes	Used with the Hours and Seconds attributes to specify the time duration within which the reoccurrences are measured.
Seconds	Used with the Hours and Minutes attributes to specify the time duration within which the reoccurrences are measured.
Parent Incident	Click the  icon and select  Quick Find. Select Rate Correlation from the list.
Comparison Criteria	<p>Specify which group of attributes must match before the incident is identified as a duplicate. The possible groups of attributes consist of the following choices.</p> <p>Name value of the Incident (from the General tab on the Incident form).</p> <p>Source Node value (from the Basics group on the Incident form). Address or name of the node for which the incident was generated.</p> <p>Source Object value (from the Basics group on the Incident form). For example, the Source Object for a LinkDown incident is interface.</p> <p>CIA custom incident attribute values (select from the list displayed on the Custom Attributes tab on the Incident form). If you want to use CIA as part of your comparison criteria, see "Rate Comparison Parameters Form (Management Events)" on the next page.</p>
Rate	<i>Optional.</i> If you selected a Comparison Criteria that includes CIA, you must


Rate Configuration Definition , continued

Attribute	Description
Comparison Parameters	populate one or more rows in this table. See "Rate Comparison Parameters Form (Management Events)" below.


Rate Comparison Parameters Form (Management Events)

Custom Incident Attributes (CIAs) are used as parameter values. Parameter values enable accurate identification of duplicate incidents. There are two categories of CIAs:

- SNMP trap varbind values (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

The group of available CIAs depends on which incident you are configuring for this Rate (for example, CiscoLinkDown). To see which CIAs are available, navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.

Note: You can also use the CIA (varbind) position number.








The screenshot shows the HP Network Node Manager i Software interface. The top menu bar includes 'Open Root Cause Incidents', 'Incident', and 'InterfaceDown'. Below the menu bar is a toolbar with icons for 'Save and Close', 'Delete Incident', and a 'Custom Attributes' tab. The 'Custom Attributes' tab is selected, showing a table of attributes for 'com.hp.ov.nms.apa.symptom' and 'com.hp.ov.nms.apa.symptom_1'. The 'Basics' tab is also visible, showing the message 'Interface Down', severity 'Critical', priority 'None', and lifecycle state 'Registered'. The 'Source Node' is 'CH-KVh' and the 'Source Object' is 'Se0/0/2'. The 'Assigned To' field is empty.

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To specify a CIA to use in the identification criteria for duplicate incidents:


1. Navigate to the **Rate Comparison Params** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, click the  Open icon, and continue.
 - e. On the form that opens, navigate to the **Rate** tab.
 - f. Locate the **Rate Comparison Parameters** table.
 - g. Do one of the following to specify which CIA:
 - To add a Custom Incident Attribute parameter specification, click the  New icon.
 - To edit an existing Custom Incident Attribute parameter specification, select a row, click the  Open icon, and continue.
2. In the Parameter Value field, type (or copy and paste) the exact text string from the Incident form, Custom Attribute tab, **Name** attribute value:
 - NNMi-provided CIA value (see ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)" on page 733](#)).
 - SNMP trap varbind identified by the Abstract Syntax Notation value (ASN.1).
3. Click  **Save and Close** to save your changes and return to the previous configuration form.

Configure Actions for a Management Event Incident

For information about each Management Events tab:

For information about each Actions tab:

You can configure actions to automatically run at any point in the incident lifecycle. For example, you might want to configure an action to occur when an incident of the type you are configuring is generated (**Registered**). When an incident is generated, you might want to automatically open a trouble ticket or send email or page your network operator. After the incident is **Closed**, you might want to automatically close the trouble ticket.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.

Note: If the NNMi management server is running on a Windows operating system, NNMi runs each action that you configure using the Local System account. If the NNMi management server is running on a Linux operating system, NNMi runs each action that you configure using the bin user name. To change the user account associated with actions, see the "Setting the Action Server Name Parameter" section in the *HP Network Node Manager i Software Deployment Reference*.

You can configure actions for incidents generated from SNMP Trap Incidents, Syslog Messages Incidents and the NNMi Management Event Incidents. Any time an incident configuration changes, the action directory is rescanned and any Jython files are reloaded to the NNMi database. See ["Lifecycle Transition Action Form \(Management Events\)" on the next page](#) for more information about the actions directory.

Tip: Copy any required Jython files to the NNMi actions directory before you configure an incident action. New or updated actions are loaded into NNMi only when an incident configuration is updated or created. See ["Lifecycle Transition Action Form \(Management Events\)" on the next page](#) for the location of the NNMi action directory.

When the defined Incident Action runs, output is logged to the incidentActions.*.*.log file. To view the contents of the Actions log, use the **Tools** → **Incident Actions Log** menu option.

See ["Verify that NNMi Services are Running" on page 91](#) for more information about log files and where they are located.

NNMi sets the default values described in the following table.








See the "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference* for information about changing the default values for Action Server Properties.

Action Server Properties

Property	Description	Value
numProcess	Number of actions that can be run at one time.	10
numJythonThreads	Number of threads the action server uses to run Jython scripts.	10
userName	User name under which the action server runs.	bin

To configure an automatic action for an incident:

1. Navigate to the **Actions** tab.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.


- d. Do one of the following:
 - To create an incident configuration, click the  New icon, and continue.
 - To edit an incident configuration, select a row, click the  Open icon, and continue.
 - To delete an incident configuration, select a row, and click the  Delete icon.
 - e. Select the **Actions** tab.
2. From the **Lifecycle Actions** table toolbar, do one of the following:
 - To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
 3. In the "[Lifecycle Transition Action Form \(Management Events\)](#)" below, provide the required information.
 4. Click  **Save and Close** to save your changes and return to the previous form.

The next time the lifecycle changes, NNMi launches the action associated with the lifecycle for the incident of that type.

Lifecycle Transition Action Form (Management Events)




For information about each Actions tab:

Use this form to enter the command you want to run when an incident of the type you are configuring is at a particular [Lifecycle State](#). For example, when an incident is generated (**Registered**), you might want to automatically open a trouble ticket or email or page your network operator.

Note: Your actions will not be executed until you enable the Actions configuration by either clicking Enable  on the Actions tab or using the **Actions** → **Enable Configuration** option.

To configure an action for an incidents:

1. Navigate to the **Lifecycle Transition Actions** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Select the **Actions** tab.

- e. From the **Lifecycle Transition Action** table toolbar, do one of the following:
- To create an Action configuration, click the  New icon, and continue.
 - To edit an Action configuration, select a row, click the  Open icon, and continue.
 - To delete an Action configuration, select a row, and click the  Delete icon.
2. Make your configuration choices (see [table](#)).

Note: NNMi reloads the configuration information anytime the incident configuration is changed.

3. Click  **Save and Close** to save your changes and return to the previous form.

Create Action Attributes

Attribute	Description
Lifecycle State	Select a Lifecycle State from the drop-down menu.
Command Type	If you provided a Jython command, select Jython from the drop-down list. If you are using an executable or bat file, select ScriptOrExecutable from the drop-down list.
Command	<p>Enter one of the following:</p> <ul style="list-style-type: none">• A Jython method with the required parameters.• Executable command for the current operating system with the required parameters. <p>When entering a Command value, note the following:</p> <ul style="list-style-type: none">• Left or right bracket ([]) and backtick (` Unicode character: 0060 hex = 96 dec) characters are not permitted in the Command attribute. If you need these characters in your shell script, place them in a shell script file and reference that file from the Command attribute.• Windows only: Shell commands are not permitted in the Command attribute. To use shell commands, place them in a shell script file and reference that file from the Command attribute.• Use absolute paths to executables instead of relying on the PATH variable as it might not be set correctly.• Verify that you do not have two Jython methods with the same name. Otherwise, NNMi is not able to tell which is the correct method to load.

Create Action Attributes, continued






Attribute	Description
	<ul style="list-style-type: none">You can use the same Jython method for more than one incident configuration.Jython (.py) files must reside in the following directory (see "About Environment Variables" on page 86): <div><p>Note: All the functions defined in the Jython files that reside in this directory are also accessible by NNMi. The files are also executed by NNMi on startup.</p></div> <p>Windows:</p> <pre>%NnmDataDir%\shared\nnm\actions</pre> <p>Linux:</p> <pre>\$NnmDataDir/shared/nnm/actions</pre> <ul style="list-style-type: none">When using executable files, specify the absolute path to the executable command or make sure the directory in which the executable file resides is in your PATH environment variable.NNMi provides a set of parameters that can pass attribute values from an incident configuration. See "Valid Parameters for Configuring Incident Actions (Management Events)" on page 1397 for more information.

Configure a Payload Filter for an Action (Management Events)

The Payload Filter Editor enables you to create expressions that further refine the filters used to select the incidents that cause the configured action to run. Make sure to design any complex Payload Filters offline as a Boolean expression first. This method can help to minimize errors when entering your expressions using the Payload Filter editor.

To create a Payload Filter expression:

1. Navigate to the **Management Event Configuration** form:
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Management Event Configurations**.
 - d. Do one of the following:

- i. To create an incident configuration, click the  New icon, and continue.
 - ii. To edit an incident configuration, select a row, click the  Open icon, and continue.
 - iii. To delete an incident configuration, select a row, and click the  Delete icon.
2. Select the **Actions** tab.
3. Do one of the following:
 - a. To create a new configuration, click the  New icon.
 - b. To edit an existing configuration, select a row, click the  Open icon, and continue.
4. Select the **Payload Filter** tab.
5. Define your Payload Filter (see [table](#)). Also see "[Guidelines for Creating a Payload Filter](#)".
 - a. Plan out the logic needed for your Filter String.
 - b. Use the buttons on the bottom half of the Additional Filters Editor to establish the logic structure.

For example, to establish the following structure, select **Insert**, then click **AND**, then **NOT**, and then **AND** a second time:

(() AND NOT ())

- c. Now place your cursor in a location within the displayed Filter String, and use the top half of the filter editor to define the parameters of the highlighted filter requirement.

For example, select a set of parentheses and use the Insert button to specify the filter

requirement within those parentheses:

Filter Editor

Attribute	Operator	Value
ciaName	=	.1.3.6.1.4.1.9.9.13.1.2.1.7

Append
Insert
Replace

AND
AND
NOT

Highlight the location in the logic flow, then click Insert to define the filter requirement

Filter String
(AND NOT ())

Insert
AND
OR
NOT
EXISTS
NOT EXISTS
Delete

6. Click **Save and Close**.
7. Click **Save and Close** to save your changes and return to the previous form.

When creating a Payload Filter, note the following:

- Payload Filter expressions for the `like` and `not like` operators use the syntax defined for java regular expressions (`java.util.regex Pattern` class)
- You must use a `ciaName` that already exists in the trap or event you are configuring.
- Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together.
- View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND and OR Boolean Operators must contain at least two expressions as shown in the example below.

The following example filters incidents on voltage state. Using this Payload Filter, you could then configure the Basics settings of the Enrichment Configuration to set the severity and message format to all incidents that return a state value of 4 or 5.

OR

```
ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7
```

```
ciaValue = 4
```

AND

```
ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7
```

```
ciaValue = 5
```

NNMi evaluates the expression above as follows:

```
(ciaName = .1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 4) OR (ciaName =  
.1.3.6.1.4.1.9.9.13.1.2.1.7 AND ciaValue = 5)
```

NNMi finds all incidents with a varbind value of `.1.3.6.1.4.1.9.9.13.1.2.1.7` and CIA value of **4** or **5**.

- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Payload Filter Editor. For example, you append to, replace, or change the indentation of the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators.


Payload Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name on which NNMi searches. Filterable attributes include the following:</p> <ul style="list-style-type: none">• ciaName• ciaValue
Operator	<p>Valid operators are described below.</p> <ul style="list-style-type: none">• = Finds all values equal to the value specified. Click here for an example. Example: ciaName=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value .1.3.6.1.4.1.9.9.13.1.2.1.7.• != Finds all values not equal to the value specified. Click here for an example. Example: ciaName!=.1.3.6.1.4.1.9.9.13.1.2.1.7 matches any incident that contains a varbind with the name value other than 1.3.6.1.4.1.9.9.13.1.2.1.7.• < Finds all values less than the value specified. Click here for an example. Example: ciaValue < 6 matches any incident that contains a varbind value less than 6.• <= Finds all values less than or equal to the value specified. Click here for an

Payload Filter Editor Settings, continued

Attribute	Description												
	<p>example.</p> <p>Example: <code>ciaValue <= 6</code> matches any incident that contains a varbind value less than or equal to 6.</p> <ul style="list-style-type: none"> • > Finds all values greater than the value specified. Click here for an example. Example: <code>ciaValue > 4</code> matches any incident that contains a varbind value greater than 4. • >= Finds all values greater than or equal to the value specified. Click here for an example. Example: <code>ciaValue >= 4</code> matches any incident that contains a varbind with values greater than or equal to 4. • between Finds all traps or events that include a varbind value equal to and between the two values specified. Click here for an example. Example: <code>ciaValue between</code> <div data-bbox="451 957 878 1073"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>between</td><td>1</td></tr> <tr> <td></td><td>4</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value equal to or greater than 1 and equal to or less than 4.</p> <div data-bbox="467 1199 1320 1262"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div> <ul style="list-style-type: none"> • in Finds any match to at least one value in a list of values. Click here for an example. Example: <code>ciaValue in</code> <div data-bbox="451 1524 841 1656"> <table> <thead> <tr> <th>Operator</th><th>Value</th></tr> </thead> <tbody> <tr> <td>in</td><td>4</td></tr> <tr> <td></td><td>5</td></tr> </tbody> </table> </div> <p>matches any incident that contains a varbind value of either 4 or 5.</p> <div data-bbox="467 1782 1320 1845"> <p>Note: As shown in the example, each value must be entered on a separate line.</p> </div>	Operator	Value	between	1		4	Operator	Value	in	4		5
Operator	Value												
between	1												
	4												
Operator	Value												
in	4												
	5												

Payload Filter Editor Settings, continued

Attribute	Description
	<p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example (4, 5). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • is not null Finds all non-blank values. Click here for an example. Example: <code>ciaValue is not null</code> matches any incident with varbind values. • is null Finds all blank values. Click here for an example. Example: <code>ciaValue is null</code> matches any incident with no varbind values. • like Finds matches using wildcard characters. Click here for more information about using wildcard characters. The period asterisk (.*?) characters mean <i>any number of characters of any type at this location</i>. The period (.) character means <i>any single character of any type at this location</i>. <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Examples:</p> <p><code>ciaName like \Q .1.3.6.1.4.1.9.9\E.*</code> finds all traps or events that contain varbind names that begin with .1.3.6.1.4.1.9.9 and (optionally) end with any number of characters.</p> <p><code>ciaValue like .*Chicago.*</code> finds all traps or events that contain a varbind value that includes the string Chicago.</p> <ul style="list-style-type: none"> • not between Finds all values except those between the two values specified. Click here for an example. Example: <code>ciaValue not between 5 8</code> matches an incident that contains a varbind with the values less than 5 or greater than 8. • not in Finds all values except those included in the list of values. Click here for an example. Example: <code>ciaValue not in</code> 

Payload Filter Editor Settings, continued

Attribute	Description
	<p>matches any incident that contains a varbind with values other than 1 and 2.</p> <p>Note: As shown in the example, each value must be entered on a separate line.</p> <p>NNMi displays the list of attributes using comma-separated values enclosed in parentheses, for example, (1, 2). However, the comma-separated list is used only for display purposes. The actual delimiter is the new line.</p> <ul style="list-style-type: none"> • not like Finds all that do not have the values specified (using wildcard strings). Click here for an example. <p>The period asterisk (.*) characters mean <i>any number of characters of any type at this location</i>.</p> <p>The period (.) character means <i>any single character of any type at this location</i>.</p> <p>Note: To include literal string values in the Value attribute, enclose the string value in \Q<literal_value>\E as shown in the Examples listed below.</p> <p>Example:</p> <p><code>ciaName not like \Q.1.3.6.1.4.1.9.9\E.*</code> matches any incident that contains a varbind name value that does not begin with .1.3.6.1.4.1.9.9.</p> <p><code>ciaValue not like .*Chicago.*</code> finds all traps or events that do not contain a varbind value that includes the string Chicago.</p>
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. • NNMi displays a variable number of value fields depending on the Operator selected. For example, the between Operator causes two value fields to be displayed. • The between, in and not in operators require that each value be entered on a separate line.

Payload Filter Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.

Payload Filter Editor Buttons, continued

Button	Description
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude interfaces with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have VLAN10 for the (interface name) ifName value:</p> <pre>(ifDesc like VLAN AND NOT (ifName=VLAN10))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String.</p> <p>Indicates that you want NNMi to consider interfaces that have Capabilities or Custom Attributes when evaluating the Filter String.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p>

Payload Filter Editor Buttons, continued

Button	Description
	<p>Note: If you include Capabilities or Custom Attribute names and values in the Filter String, but do not use EXISTS or NOT EXISTS, NNMi excludes from its search interfaces that do not include Capabilities or Custom Attributes.</p> <p>For example, when evaluating the following Filter String, NNMi includes interfaces with (interface description) ifDesc containing VLAN, as well as any Interfaces Custom Attribute Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the interfaces that match the expression that follows the NOT EXISTS.</p> <p>Tip: When creating complex Filter Strings that include customAttrName and customAttrValue pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the customAttrName and customAttrValue pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p> <p>For example, when evaluating the following expression, NNMi includes interfaces with (interface description) ifDesc containing VLAN, and excludes any Interfaces that have the Custom Attribute Role and that Role value is LAN Connection to Oracle Server:</p> <pre>(ifDesc like VLAN OR NOT EXISTS((customAttrName=Role AND customAttrValue=LAN Connection to Oracle Server)))</pre> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Payload Filter Editor deletes all expressions associated with the Boolean Operator.</p>

Valid Parameters for Configuring Incident Actions (Management Events)

When configuring incident actions, consider using incident information as part of the action. NNMi provides the following parameter values. Use these parameters as variables in your Jython or executable files.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

Tip: If a value is not stored for a parameter, it is returned as "null".

See "[Lifecycle Transition Action Form](#)" on page 848 for more information about configuring incident actions.

Valid Parameters Visible From an Incident's Form

Parameter Value	Description
\$category, \$cat	Value of the Category attribute in the Incident form.
\$count, \$cnt	Value representing the number of Custom Incident Attributes that appear in the Incident form.
\$family, \$fam	Value from the Family attribute in the Incident form.
\$firstOccurrenceTime, \$fot	Value from the First Occurrence Time attribute in the incident form.
\$lastOccurrenceTime, \$lot	Value from the Last Occurrence Time attribute in the incident form.
\$lifecycleState, \$lcs	Value from the Lifecycle State attribute in the Incident form.
\$name	Value of the Name attribute from the incident configuration.
\$nature, \$nat	Value from the Nature attribute in the Incident form.
\$origin, \$ori	Value from the Origin attribute in the Incident form.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the incident form.
\$priority, \$pri	Value from the Priority attribute in the Incident form.
\$severity, \$sev	Value of the Severity attribute of the Incident form.

Valid Parameters Visible from a Node Form

Parameter Value	Description
\$managementAddress, \$mga	Value from the Management Address attribute of the incident's source Node's form or SNMP Agent form .
\$otherSideOfConnectionManagementAddress, \$oma	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the value of the Management Address of a node on the other side of the Layer 2 Connection.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name as displayed in the Hostname attribute of the incident's source Node's form .
\$sourceNodeName, \$snn	Value from the Name attribute of the incident's source Node's form .
\$sysContact, \$sct	Value from the System Contact attribute of the incident's source Node form: General tab .
\$sysLocation, \$slc	Value from the System Location attribute of the incident's source Node form: General tab .

Valid Parameters Visible from an Interface Form

Parameter Value	Description
\$ifAlias, \$ifa	Value from the IfAlias attribute for the interface that is the incident's source object.
\$ifConfigDupSetting, \$icd	Configured Duplex Setting on the port associated with the interface that is the incident's source object.
\$ifDesc, \$idc	Value from the ifDesc attribute for the interface that is the incident's source object.
\$ifIndex, \$idx	Value from the ifIndex attribute for the interface that is the incident's source object.
\$ifIpAddr, \$iia	IP Address values associated with the interface that is the incident's source object. If multiple IPAddresses are associated with the interface, this parameter returns a comma-separated list.
\$ifName, \$ifn	Value from the ifName attribute for the interface that is the incident's source object.
\$ifPhysAddr, \$ipa	Value from the Physical Address attribute for the interface that is the incident's source object.
\$ifSpeed, \$isp	Value from the ifSpeed attribute for the interface that is the incident's source object.

Valid Parameters Visible from an Interface Form , continued

\$ifType, \$itp	Value from the ifType attribute for the interface that is the incident's source object.
-----------------	---

Valid Parameters Visible from a Layer 2 Connection Form

Parameter Value	Description
\$otherSideOfConnectionConfigDupSetting, \$ocd	If the incident's source Node is part of a Layer 2 Connection, this parameter contains the Configured Duplex Setting on the port associated with the interface on the other side of the connection.
\$otherSideOfConnectionIfAlias, \$oia	If the incident's Source Node is part of a Layer 2 Connection, this parameter is the value of the ifAlias of one of the interfaces on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfDesc, \$odc	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifDescr attribute value for the interface on the other side of the Layer 2 Connection.
\$otherSideOfConnectionIfIndex, \$odx	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifIndex attribute value for the interface on the other side of the connection.
\$otherSideOfConnectionIfName, \$ofn	If the incident's Source Node is part of a Layer 2 Connection, this parameter contains the ifName attribute value for the interface on the other side of the connection.

Valid Parameters Visible from a VLAN Form

Parameter Value	Description
\$impVlanIds, \$ivi	Value from the VLAN Id attribute associated with the interface that is the incident's source object. To access this information from an interface form, navigate to the VLAN Port tab and open the form for the VLAN of interest. If the interface is part of more than one VLAN, this parameter returns a comma-separated list.
\$impVlanNames, \$ivn	Value from the Global VLAN Name attribute associated with the interface that is the incident's source object. To access this information from a Node form or Interface form, navigate to the VLAN Ports tab. If the node or interface is part of more than one VLAN, this parameter returns a comma-separated list.

Valid Parameters Not Visible From a Form

Parameter Value	Description
\$id	Unique Object Identifier attribute value for the incident (unique across the entire NNMi Database).
\$firstOccurrenceTimeMs, \$fms	Value from the First Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$lastOccurrenceTimeMs, \$lms	Value from the Last Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$messageFormat, \$msg	<i>Valid for Incident actions only.</i> Message text displayed for an incident when this parameter is included as an argument to an incident action.
\$oid	Value of the unique object identifier (oid) for the incident configuration that originated from either an SNMP Trap, Syslog Message or Management Event.
\$otherSideOfConnection, \$osc	If the incident's Source Node is part of a Layer 2 Connection, this attribute is the following combination of values for the node and one of its interfaces on the other side of the Layer 2 Connection: The fully-qualified DNS name of the node appended with the interface Name in the following format: <i><fully-qualified DNS name> [interface_name]</i>
\$originOccurrenceTimeMs, \$oms	Value from the Origin Occurrence Time attribute in the incident form, converted to milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).
\$sourceNodeUuid, \$snu	Universally Unique Object Identifier attribute value of the source node object for the incident (unique across all databases). This identifier distinguishes the source node object instance from all other node objects.
\$sourceObjectClass, \$soc	Value of the object class for the object you want to include. Use this parameter to request more details of a class of objects through a web service. Examples of object classes include: <code>com.hp.ov.nms.model.core.Interface</code> and <code>com.hp.ov.nms.model.snmp.SnmpAgent</code> .
\$sourceObjectName, \$son	Value from the Name attribute of the source object. For example, an interface object is named according to the MIB <code>ifName</code> . Each <code>ifName</code> varies according to the vendor's conventions. Using the name <code>4/1</code> as an example, 4 represents the board number and 1 represents the port number.
\$sourceObjectUuid, \$sou	Universally Unique Object Identifier attribute value of the source

Valid Parameters Not Visible From a Form, continued

Parameter Value	Description
	object for the incident (unique across all databases). This identifier distinguishes the source object instance from all other similar object instances..
\$uuid	Universally Unique Object Identifier attribute value of the incident (unique across all databases). This identifier distinguishes the incident object instance from all other incident objects.

Valid Parameters Established in Custom Incident Attributes

Parameter Value	Description
\$<position_number>	Value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1 NNMi stores varbind values as Custom Incident Attributes. If you know the varbind position number, use this parameter.
\$<CIA_name>	Value of the name that is used for the custom incident attribute. For example, \$mycompany.mycia. NNMi provides CIA values for configuring Management Events. See Custom Incident Attributes Provided by NNMi for more information about custom incident attributes.
\$<CIA_oid>	Value of the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a custom incident attribute (varbind) position number.
\$*	Used to indicate you want all of the custom incident attribute values originating as varbinds, to be passed to the action configuration. Each varbind is returned in the following format: \$<CIA_name>:<CIA_value> in which the custom incident attribute name appears followed by the custom incident attribute value.

The function described in the following table replaces the specified numeric value with the associated text value stored in the CIA.

Note: The associated MIB must have been loaded using the [nnmloadmib.ovpl](#) command.

Functions to Generate Values Within Incident Messages

Function	Description
\$text (\$<position_number>)	The <position_number> argument specifies the numeric value of the custom incident attribute (CIA) position number for any CIA that originated from a varbind or was added by NNMi. For example, to indicate you want to use the varbind in position 1, enter: \$1. After the function runs, NNMi replaces the numeric value with the text value

Functions to Generate Values Within Incident Messages, continued

Function	Description
	stored in the CIA. Note: If a text value is not available, NNMi returns the numeric value.
\$text (\$<CIA_oid>)	The <CIA_oid> argument specifies the object identifier for any custom incident attribute that originated as a varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this argument to the \$text function when you are not certain of a custom incident attribute (varbind) position number. After the function runs, NNMi replaces the numeric value with the text value stored in the CIA. Note: If a text value is not available, NNMi returns the following message as the value: <CIA <OID> with value <value> was not found within the mib cache

Troubleshoot Incident Configurations

The NNMi **Actions** menu enables you to open an Incident Configuration from either an incident or an incident view. This feature is useful when you are monitoring incoming incidents to determine whether incidents are generated as expected. After you make any required changes, you can easily verify your changes the next time the incident occurs.

Note: Your User Account must be assigned to the **NNMi Administrators** User Group to use these actions.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

To open an Incident Configuration form from an incident view:

1. Navigate to the incident view of interest. (For example, select the **Incident Browsing** workspace, **Root Cause Incidents** view.)
2. In the table view, press Ctrl-Click to select each row representing an incident of interest.
3. In the main toolbar, select **Actions** → **Open Incident Configuration Form**.

NNMi opens one Incident Configuration form for each type of incident selected.

To open an Incident Configuration form from an Incident form:

1. Navigate to the incident view of interest. (For example, select the **Incident Browsing** workspace, **Root Cause Incidents** view.)
2. In the table view, press Ctrl-Click to select each row representing the configuration you want to edit.
3. In the main toolbar, select **Actions** → **Open Incident Configuration Form**.

NNMi opens the Incident Configuration form for the current incident.

Note: Any configuration changes you make to an incident apply only to future incidents.

The NNMi **Actions**→ **Incident Configuration Report** menu also enables you to view configuration reports for the following kinds of configurations for an incident:

- Action Results
- Dampen Results
- Enrichments
- Global Manager Forwarding (*NNMi Advanced -Global Network Management*) Available on Regional Managers.
- Suppression Results

See ["View an Incident Configuration Report" below](#) for more information.

View an Incident Configuration Report

The NNMi **Actions** menu enables you to view a report of the following incident configurations:

- Action Results
- Dampen Results
- Enrichment
- Global Manager Forwarding (*NNMi Advanced - Global Network Management feature*)
- Suppression Results

Note: Your User Account must be assigned to the **NNMi Administrators** User Group to use these actions.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

Viewing an incident configuration report helps you determine the following:

- (*NNMi Advanced - Global Network Management feature*). On a Regional Manager, reports whether NNMi forwards occurrences of the selected incident configuration to Global Managers.
- The configuration settings (Interface, Node, or Default) NNMi is using for a selected incident.
- Whether the selected configuration (Suppression, Enrichment, or Dampening) is enabled.
- Whether NNMi found any matches for a Payload Filter for the selected configuration (Suppression, Enrichment, or Dampening).

These reports are useful when you want to change an incident configuration and need to determine which settings have been configured, and therefore which settings you might want to change, for the incident.

To view a configuration report for the selected incident:

1. Select the incident for which you want to view a configuration report.
2. Select **Actions**→ **Incident Configuration Reports**.
3. Select one of the following menu options to indicate the type of configuration report you want to view
 - **Action Results**
 - **Dampen Results**
 - **Report Enrichments**
 - **Global Manager Forwarding** (*NNMi Advanced*)
 - **Suppression Results**

See the [Incident Configuration Actions](#) table for a description of each incident configuration report.

Incident Configuration Actions

Action Menu Option	Information Displayed
Action Results	<ul style="list-style-type: none">• If the Source Object is an interface, the Interface Group, if any, to which the Source Object belongs. If NNMi reports a matching Interface Group, this indicates it is using the Interface configuration settings for the selected incident.• The Node Group, if any, to which the Source Node belongs. If NNMi reports a matching Node Group, this indicates it is using the Node configuration settings for the selected incident.

Incident Configuration Actions, continued

Action Menu Option	Information Displayed
	<div data-bbox="492 411 1370 533" style="background-color: #f0f0f0; padding: 10px; margin-bottom: 10px;"> Note: If no matches for an Interface or Node Group are found, this indicates NNMi is using the Default configuration settings for the selected incident. </div> <ul style="list-style-type: none"> • Whether the Action Configuration is enabled. • The action to be executed. • The Payload Filter, if configured for the incident and whether NNMi found any matches for the Payload Filter.
Dampen Results	<ul style="list-style-type: none"> • If the Source Object is an interface, the Interface Group, if any, to which the Source Object belongs. If NNMi reports a matching Interface Group, this indicates it is using the Interface configuration settings for the selected incident. • The Node Group, if any, to which the Source Node belongs. If NNMi reports a matching Node Group, this indicates it is using the Node configuration settings for the selected incident. <div data-bbox="492 1083 1370 1226" style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> Note: If no matches for an Interface or Node Group are found, this indicates NNMi is using the Default configuration settings for the selected incident. </div> <ul style="list-style-type: none"> • Whether the Dampening configuration is enabled. • The Dampen Interval that is set. • The Payload Filter, if configured for the incident and whether NNMi found any matches for the Payload Filter.
Report Enrichments	<ul style="list-style-type: none"> • If the Source Object is an interface, the Interface Group, if any, to which the Source Object belongs. If NNMi reports a matching Interface Group, this indicates it is using the Interface configuration settings for the selected incident. • The Node Group, if any, to which the Source Node belongs. If NNMi reports a matching Node Group, this indicates it is using the Node configuration settings for the selected incident. <div data-bbox="492 1776 1370 1873" style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> Note: If no matches for an Interface or Node Group are found, this indicates NNMi is using the Default configuration settings for the selected </div>


Incident Configuration Actions, continued

Action Menu Option	Information Displayed
	<p>incident.</p> <ul style="list-style-type: none"> • Whether the Enrichment configuration is enabled. • The Payload Filter, if configured for the incident and whether NNMi found any matches for the Payload Filter. • The current Severity, Priority, Message Format, and Custom Incident Attributes configuration settings for the incident.
Global Manager Forwarding	<p>(<i>NNMi Advanced - Global Network Management feature</i>) Displays the following for each selected incident:</p> <ul style="list-style-type: none"> • Whether the incident is an SNMP Trap Incident, Syslog Message Incident or Management Event Incident Configuration. • The name of the incident configuration. • Whether occurrences of the selected incident configuration will be forwarded to Global Managers in your network environment. • The Payload Filter, if configured for the incident and whether NNMi found any matches for the Payload Filter.
Suppression Results	<ul style="list-style-type: none"> • If the Source Object is an interface, the Interface Group, if any, to which the Source Object belongs. If NNMi reports a matching Interface Group, this indicates it is using the Interface configuration settings for the selected incident. • The Node Group, if any, to which the Source Node belongs. If NNMi reports a matching Node Group, this indicates it is using the Node configuration settings for the selected incident. <p>Note: If no matches for an Interface or Node Group are found, this indicates NNMi is using the Default configuration settings for the selected incident.</p> <ul style="list-style-type: none"> • Whether the Suppress Configuration is enabled. • The Payload Filter, if configured for the incident, and whether NNMi found any matches for the Payload Filter.

Related Topics

["Troubleshoot Incident Configurations" on page 1402](#)

Configure Trap Forwarding

NNMi enables you to configure SNMP trap forwarding using the Trap Forwarding option under the Incidents folder of the  Configuration workspace. This feature is useful when you want to forward traps to a specified destination. For example, you might want to forward certain kinds of traps to one server and forward another set of traps to a different server so they can be managed separately.

When configuring SNMP trap forwarding you perform the following tasks:

- ["Configure NNMi SNMPv3 Security Settings for Trap Forwarding and Inform-Requests" below](#)
- ["Configure Trap Forwarding Filters" on page 1410](#)
- ["Configure Trap Forwarding Destinations" on page 1413](#)

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

(NNMi Advanced - Global Network Management feature) If you want to forward specific SNMP traps from your NNMi management server (a Regional Manager) to all Global Managers in your Global Network management environment, see ["Configure Forward to Global Manager Settings for an SNMP Trap Incident \(NNMi Advanced\)" on page 1059](#)

Configure NNMi SNMPv3 Security Settings for Trap Forwarding and Inform-Requests


Note: If your network environment uses SNMPv2c or SNMPv1 and does not use SNMPv3, skip this task.

If your network environment uses SNMPv3, specify which user-based security model (USM) settings the NNMi management server uses when NNMi acts as an authoritative entity in the following situations:


- Forwarding SNMPv3 traps to other devices in your network environment
- Sending responses to SNMPv3 Inform-Requests

The settings in this form grant permission for NNMi to communicate with the SNMPv3 agent. The SNMPv3 engine identifier and the user-based security settings are required for successful authentication in SNMPv3 protocol. Devices that are sending SNMPv3 informs to NNMi must use these settings.

To configure the NNMi management server as an authoritative entity for SNMPv3:

1. Navigate to the **Trap Forwarding Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
2. Navigate to the **NNMi SNMPv3 Trap Forwarding Security Settings** group.
3. NNMi displays the ID of the engine assigned to the SNMPv3 agent that NNMi uses when forwarding or sending data to other SNMPv3 agents. See the attribute value for [Engine Id](#).

Caution: Devices that are sending SNMPv3 informs to NNMi must use these settings.

4. Provide the USM information that NNMi uses for authentication and privacy when using SNMPv3 protocol for forwarding traps or receiving Inform-Requests from other devices in your network environment (see [table](#)).
5. Click  **Save and Close** to save your changes.

SNMPv3 Engine Assigned to NNMi management server

Attribute	Description
Engine Id	Remote devices must request this SNMPv3 engine ID when sending informs to NNMi. If the SNMPv3 agent sending data to NNMi does not know the correct engine ID, the inform is rejected.

SNMPv3 Settings of the NNMi management server's User-Based Security Model (USM)

Attribute	Description
User Name	The SNMPv3 User Name is the text string used for SNMPv3 requests in your network environment.
Authentication Protocol	The SNMPv3 authentication protocol. Determines whether authentication is required and indicates the type of authentication protocol used. NNMi supports the following protocols: <ul style="list-style-type: none">• HMAC¹-MD5²-96 authentication protocol• HMAC³-SHA⁴-1 authentication protocol

¹Hash-based Message Authentication Code

²Message-Digest algorithm 5

³Hash-based Message Authentication Code

⁴Secure Hash Algorithm

SNMPv3 Settings of the NNMi management server's User-Based Security Model (USM), continued

Attribute	Description
Authentication Passphrase	<p>The SNMPv3 USM authentication passphrase used by the NNMi management server. If required for authentication, provide the appropriate authentication passphrase for the authentication protocol.</p> <p>The length limitations of the authentication passphrase depend on the authentication protocol.</p>
Privacy Protocol	<p>Specify the SNMPv3 USM privacy protocol used by the NNMi management server.</p> <p>The SNMPv3 USM privacy protocol determines whether encryption is required and indicates the type of privacy protocol used. NNMi supports the following privacy protocols:</p> <ul style="list-style-type: none"> • DES¹-CBC² Symmetric Encryption Protocol • TripleDES³ - Triple Data Encryption Algorithm • AES⁴128 - Advanced Encryption Standard 128 Protocol • AES⁵192 - Advanced Encryption Standard 192 Protocol • AES⁶256 - Advanced Encryption Standard 256 Protocol <p>Note: Leaving this attribute empty means SNMP Minimum Security Level = <i>No Privacy</i> for this SNMPv3 configuration.</p>
Privacy Passphrase	<p>Specify the SNMPv3 USM privacy passphrase used by the NNMi management server.</p> <p>If required for privacy, provide the appropriate encryption passphrase for use with the privacy protocol.</p> <p>The length limitations of the privacy passphrase depend on the privacy protocol.</p>

Registration Attributes

Attribute	Description
Last Modified	Date and time the Trap Forwarding Configuration was last modified.

¹Data Encryption Standard

²Cipher Block Chaining

³Data Encryption Standard

⁴Advanced Encryption Standard

⁵Advanced Encryption Standard

⁶Advanced Encryption Standard






Configure Trap Forwarding Filters

Pre-requisite: Make sure you have used the NNMi [nnmincidentcfg.ovpl](#) command line utility to automatically create or update the incident configurations for the SNMP traps you want to include. See ["Load SNMP Trap Incident Configurations" on page 873](#) for more information.

Use the Trap Forwarding Configuration: Trap Forwarding Filters tab to configure a filter expression to specify the SNMP trap Object Identifier (OID) pattern you want to use to determine which SNMP traps NNMi forwards. The traps which pass the filter you specify can then be forwarded to a specified destination using the Trap Forwarding Destinations tab. See ["Configure Trap Forwarding Destinations" on page 1413](#) for more information.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure Trap Forwarding Filters:

1. Navigate to the **Trap Forwarding Configuration** form.
 - a. From the workspace navigation panel, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
2. Select the **Trap Forwarding Filters** tab.
3. Do one of the following:
 - To create an SNMP Trap Forwarding Filter configuration, click the  New icon, and continue.
 - To edit an SNMP Trap Forwarding Filter configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an SNMP Trap Forwarding Filters configuration, click the  Delete icon.
4. In the ["Trap Forwarding Filter Form" on the next page](#) provide the required information.
5. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

The next time that a trap of this type arrives, NNMi uses the filter you specify to determine whether to forward the trap to a specified destination.





Trap Forwarding Filter Form

Pre-requisite: Make sure you have used the NNMi `nnmincidentcfg.ovpl` command line utility to automatically create or update the incident configurations for the SNMP traps you want to include. See ["Load SNMP Trap Incident Configurations" on page 873](#) for more information.

The Trap Forwarding Filters Form enables you to specify the SNMP trap Object Identifier (OID) pattern you want to use to determine which SNMP traps NNMi forwards. The traps which pass the filter you specify can then be forwarded to a specified destination using the Trap Forwarding Destinations tab. See ["Configure Trap Forwarding Destinations" on page 1413](#) for more information.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure Trap Forwarding Filters:

1. Navigate to the **Trap Forwarding Configuration** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
2. Select the **Trap Forwarding Filters** tab.
3. Do one of the following:
 - To add an SNMP Trap Forwarding Filter configuration, click the  New icon, and continue.
 - To edit an SNMP Trap Forwarding Filter configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an SNMP Trap Forwarding Filter configuration, click the  Delete icon.
4. Make your configuration choices (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

SNMP Trap Forwarding Filters Configuration

Attribute	Description
Filter Name	Enter the name you want to use for this SNMP Trap Forwarding Filter configuration. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No

SNMP Trap Forwarding Filters Configuration, continued

Attribute	Description
	spaces are permitted.
"Filter Form" below	Access the Filter Expressions tab to access the Filter form and specify the valid SNMP Object Identifier (OID) pattern to be used for the SNMP trap filter.



Filter Form




Pre-requisite: Make sure you have used the NNMi [nnmincidentcfg.ovpl](#) command line utility to automatically create or update the incident configurations for the SNMP traps you want to include. See ["Load SNMP Trap Incident Configurations" on page 873](#) for more information.

The Filter Form enables you to specify the SNMP trap Object Identifier (OID) pattern you want to use to filter incoming SNMP traps. The traps which pass the filter you specify can then be forwarded to a specified destination using the Trap Forwarding Destinations tab. See ["Configure Trap Forwarding Destinations" on the next page](#) for more information.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure a Trap Forwarding Filter:

1. Navigate to the **Trap Forwarding Filter** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
 - e. Select the **Trap Forwarding Filters** tab.
 - f. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, click the  Open icon in the row representing the configuration you want to edit.
 - g. On the form that opens, navigate to the **Filter Expressions** tab.
 - h. Locate the **Filter Expressions** table.

- i. Do one of the following:
 - To add a Trap Forwarding Filter, click the  New icon.
 - To edit an existing Trap Forwarding Filter, click the  Open icon in the row representing the configuration you want to edit.
2. Make your configuration choices (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

SNMP Trap Forwarding Filter Expression Configuration

Attribute	Description
Trap Object Identifier (OID)	<p>Enter the Trap Object Identifier (OID) pattern you want to use for the SNMP trap filter. Valid values include:</p> <ul style="list-style-type: none">• The entire SNMP trap OID value. For example: .1.3.6.1.6.5.66.7.1225• The SNMP trap OID value that includes a wildcard as a placeholder for the missing values. For example, to specify only the SNMP trap OID matching prefix: .1.3.6.1.6.5.66.7.*

Configure Trap Forwarding Destinations








Pre-requisite: Make sure you have used the NNMi [nnmincidentcfg.ovpl](#) command line utility to automatically create or update the incident configurations for the SNMP traps you want to include. See "[Load SNMP Trap Incident Configurations](#)" on [page 873](#) for more information. You must also create the Trap Forwarding Filters for the SNMP traps you want to forward. See "[Configure Trap Forwarding Filters](#)" on [page 1410](#) for more information.

The Trap Forwarding Destinations tab enables you to specify the servers to which you want to forward SNMP traps. For example, you can configure NNMi to forward traps to a remote server that receives SNMP traps, such as an HP Operations Manager server or another NNMi management server. See "[Forward Traps to a Remote Server Example](#)" on [page 1418](#) for more information. Use this tab to also specify the Trap Forwarding Filters to be used for this destination.

(*NNMi Advanced*) If this NNMi management server is a Regional Manager in your environment, see also "[Configure Forward to Global Manager Settings for an SNMP Trap Incident \(NNMi Advanced\)](#)" on [page 1059](#).

Note: See "[Manage Incoming SNMP Traps](#)" on [page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure Trap Forwarding Destinations:

1. Navigate to the **Trap Forwarding Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
2. Select the **Trap Forwarding Destinations** tab.
3. Do one of the following:
 - To create an SNMP Trap Forwarding Destination configuration, click the  New icon, and continue.
 - To edit an SNMP Trap Forwarding Destination configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an SNMP Trap Forwarding Destination configuration, click the  Delete icon.
4. In the "[Trap Forwarding Destination Form](#)" below, provide the required information.
5. Do one of the following:
 - To create an SNMP Trap Forwarding Filter configuration, click the  New icon, and continue.
 - To edit an SNMP Trap Forwarding Filter configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an SNMP Trap Forwarding Filter configuration, click the  Delete icon.
6. In the "[Destination Filter Form](#)" on page 1416, provide the required information.
7. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

The next time a trap that passes the Trap Forwarding Filter arrives, NNMi forwards the trap to the specified Trap Forwarding Destination.





Trap Forwarding Destination Form

Pre-requisite: Make sure you have used the NNMi [nnmincidentcfg.ovpl](#) command line utility to automatically create or update the incident configurations for the SNMP traps you want to include. See "[Load SNMP Trap Incident Configurations](#)" on page 873 for more information. You must also create the Trap Forwarding Filters for the SNMP traps you want NNMi to forward. See "[Configure Trap Forwarding Filters](#)" on page 1410 for more information.

The Trap Forwarding Destinations form enables you to specify the servers to which you want NNMi to forward SNMP traps.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure a Trap Forwarding Destination:

1. Navigate to the **Trap Forwarding Configuration** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Select **Trap Forwarding Configuration**.
2. Select the **Trap Forwarding Destinations** tab.
3. Do one of the following:
 - To add an SNMP Trap Forwarding Destination configuration, click the  New icon that precedes the configuration you want to edit, and continue.
 - To edit an SNMP Trap Forwarding Destination configuration, click the  Open icon in the row representing the configuration you want to edit, and continue.
 - To delete an SNMP Trap Forwarding Destination configuration, click the  Delete icon.
4. Make your configuration choices (see [table](#)).
5. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

SNMP Trap Forwarding Destination Configuration

Attribute	Description
Destination Name	Enter the name you want to use for this SNMP Trap Forwarding Destination configuration. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted. No spaces are permitted.
Destination Address	Enter the IP address for the destination server. (<i>NNMi Advanced</i>) You can use IPv4 or IPv6 addresses.
Destination Port	Enter the UDP port number for the destination server.
Forwarding Options	<ul style="list-style-type: none">• Default - NNMi processes the trap before forwarding. Click here for more information.

SNMP Trap Forwarding Destination Configuration, continued

Attribute	Description
	<p>NNMi adds two new varbinds to SNMPv2 traps for storing origin address information:</p> <ul style="list-style-type: none"> ■ Origin IP Address ■ Origin IP Address type <p>Tip: NNMi does not add these varbinds to SNMPv1 traps because that information is in each SNMPv1 traps' PDU header IP Address field.</p> <p>See "Trap Varbinds Provided by NNMi" on page 1419 for more information.</p> <ul style="list-style-type: none"> • SNMPv3 to SNMPv2c Conversion - NNMi converts an incoming SNMPv3 trap to SNMPv2c. Click here for more information. <p>When converting SNMPv3 traps to SNMPv2c traps, NNMi does the following:</p> <ul style="list-style-type: none"> ■ Includes a Context Name varbind - Contains the contextName from the original SNMPv3 trap. ■ Creates a Community Name - The Context Engine ID and SNMPv3 User Name of the original SNMPv3 trap are combined as follows: username@contextEngineID. For example, ciscoAdmin@8000000b7f3cbec5632b47455e97070c <p>See "Trap Varbinds Provided by NNMi" on page 1419 for more information.</p> <ul style="list-style-type: none"> • Original Trap (Linux only/IPv4 only) - NNMi forwards the trap without any changes under certain circumstances. Click here for more information. <ul style="list-style-type: none"> ■ Only forwarded from NNMi management servers on Linux operating systems. ■ Only forwards traps received-from IPv4 sources and forwarded-to IPv4 destinations.
Specify the Trap Forwarding Filters to Use	Use the Trap Forwarding Filters form to specify the Trap Forwarding Filters configurations to use. These filters determine which traps NNMi forwards to the destination you specify.

Destination Filter Form





Pre-requisite: Make sure you have used the NNMi [nnmincidentcfg.ovpl](#) command line utility to automatically create or update the incident configurations for the SNMP traps you want to

include. See ["Load SNMP Trap Incident Configurations" on page 873](#) for more information. You must also create the Trap Forwarding Filters for the SNMP traps you want to forward. See ["Configure Trap Forwarding Filters" on page 1410](#) for more information.




The Trap Forwarding Filter Form enables you to specify the Trap Forwarding Filters that you want to apply for the SNMP traps NNMi forwards to the specified Trap Forwarding Destination.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure the Trap Forwarding Filters:

1. Navigate to the **Trap Forwarding Filter** form:
 - a. From the workspace navigation pane, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
 - e. Select the **Trap Forwarding Destinations** tab.
 - f. Do one of the following:
 - To create a new configuration, click the  New icon.
 - To edit an existing configuration, select a row, and click the  Open icon in the row representing the configuration you want to edit.
 - g. On the form that opens, navigate to the **Filter Expressions** tab.
 - h. Locate the **Filter Expressions** table.
 - i. To create a **Filter Expression**, click the  New icon.
2. Make your configuration choices (see [table](#)).
3. Click  **Save and Close** to save your changes and return to the **Trap Forwarding Configuration** form.

SNMP Trap Forwarding Filter






Attribute	Description
Filter	<p>Click the  Lookup icon.</p> <p>Select  Open from the drop-down menu to view information about the selected Filter, if any.</p> <p>Select  Quick Find to select the Trap Forwarding Filter you want to use for the current Trap Forwarding Destination.</p>

Forward Traps to a Remote Server Example


Use this help topic to guide you when you want to forward traps to a remote server that can receive SNMP traps, such as an HP Operations Manager or another NNMi management server.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

To configure NNMi to forward SNMP traps to a remote server:

1. Navigate to the **Trap Forwarding Configuration** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **Incidents** folder.
 - c. Expand the **Trap Server** folder.
 - d. Select **Trap Forwarding Configuration**.
2. Navigate to the **Trap Forwarding Filters** tab.
3. Click the  **New** icon.
4. Enter a filter name; for example, NNMi Remote Server.
5. Navigate to the **Filter Expressions** tab.
6. Click the  **New** icon.
7. In the Trap Object Identifier attribute, enter: .1.3.*
8. Click  **Save and Close** to return to the **Trap Forwarding Filter** form.
9. Click  **Save and Close** to return to the **Trap Forwarding Configuration** form.
10. Navigate to the **Trap Forwarding Destinations** tab.
11. Click the  **New** icon.
12. Provide the following information for the remote server to which SNMP traps will be forwarded:
 - a. Destination Name.
 - b. Destination Address.

- c. Destination Port.
- d. Forwarding Options.

13. Click  **Save and Close** to return to the **Trap Forwarding Configuration** form.

14. Click  **Save and Close** to save your changes.

In this example, Network Node Manager i Software forwards any SNMP traps with the enterprise address .1.3.* to the trap destination you configured.

When forwarding SNMP traps, note the following:

- NNMi appends two varbinds to the original SNMP trap and forwards it to the configured destinations.
- Trap forwarding does not result in any NNMi Incident enrichment to the forwarded SNMP traps.

Trap Varbinds Provided by NNMi

NNMi provides the following varbinds for use when forwarding SNMP traps.

Note: NNMi does not create these varbinds if the Forwarding Options attribute is set to *Original Trap (Linux only)* when configuring trap forwarding destinations. See ["Trap Forwarding Destination Form" on page 1414](#) for more information.

SNMP Trap Varbinds Provided by NNMi

Name	oid	Type	Description
Origin IP address	.1.3.6.1.4.1.11.2.17.2.19.1.1.3	InetAddress	<i>SNMPv2 traps only.</i> Contains the IP address (v4 / v6) of the original SNMP notification that generated the trap. Tip: NNMi does not add this varbind to SNMPv1 traps because that information is in each SNMPv1 traps' PDU header IP Address field.
Origin IP Address type	.1.3.6.1.4.1.11.2.17.2.19.1.1.2	InetAddressType	<i>SNMPv2 traps only.</i> Contains the type of the IP address (v4 / v6) of the Original IP Address varbind. The value "1" indicates IPv4

SNMP Trap Varbinds Provided by NNMi, continued

Name	oid	Type	Description
			and "2" indicates IPv6. Tip: NNMi does not add this varbind to SNMPv1 traps because that information is in each SNMPv1 traps' PDU header IP Address field.
Context Name	.1.3.6.1.4.1.11.2.17.2.19.1.1.1	SnmpAdminString	Contains the contextName present in the original SNMPv3 notification. This varbind is present only when NNMi converts an SNMPv3 notification to an SNMPv2c trap. See "Trap Forwarding Destination Form" on page 1414 and "Configure NNMi SNMPv3 Security Settings for Trap Forwarding and Inform-Requests" on page 1407 for more information.

Configure Trap Logging

NNMi enables you to configure the logging format for SNMP traps that you want to appear in the `trap.log` and `trap.csv` log files. You can also override these trap logging configurations on a Node Group basis. This feature is useful when you want to track your trap history as well as customize a trap's message format and resolve varbind values.

The `trap.log` and `trap.csv` files are located in the following directories (see ["About Environment Variables" on page 86](#)):

Windows

```
%NnmDataDir%\log\nnm
```

Linux

```
$NnmDataDir/log/nnm
```

See the "NNMi Incidents" chapter of the *HP Network Node Manager i Software Deployment Reference* for more information about configuring these file properties.

When configuring trap logging, you perform the following tasks:

- Use the Basics pane of the Configure Trap Logging form to configure Trap Logging.
- Optional. Configure Node Group Trap Configurations to override the Trap Logging Configuration on a Node Group basis.

Note: See ["Manage Incoming SNMP Traps" on page 871](#) for information about the criteria NNMi uses to determine when to receive or discard traps.

Trap Logging Configuration Form

NNMi enables you to configure the logging format for SNMP traps that you want to appear in the `trap.log` and `trap.csv` log files. You can also override these trap logging configurations on a Node Group basis. This feature is useful when you want to track your trap history as well as customize a trap's message format and resolve varbind values.

The `trap.log` and `trap.csv` files are located in the following directories (see ["About Environment Variables" on page 86](#)):

Windows

```
%NmDataDir%\log\nnm
```


Linux




```
$NmDataDir/log/nnm
```

See the "NNMi Incidents" chapter of the *HP Network Node Manager i Software Deployment Reference* for more information about configuring these file properties.

Tip: To display the associated SNMP Trap Incident configuration, if any, use **Actions > Show SNMP Trap Configuration**.

To configure Trap Logging:

1. Navigate to the **Incidents** folder:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Expand the **Trap Server** folder.
3. Select **Trap Logging Configuration**.
4. Do one of the following:

- To add a configuration, click the  New icon, and continue.
 - To edit a configuration, double-click the row representing the configuration you want to edit, and continue.
 - To delete a configuration, select a row, and click the  Delete icon.
5. Make your Basic configuration choices (see [table](#)).
 6. Make your Log Configuration choices (see [table](#)).
 7. Click  **Save and Close** to save your changes and return to the previous form.

Note: See "[Manage Incoming SNMP Traps](#)" on page 871 for information about the criteria NNMi uses to determine when to receive or discard traps.

Trap Logging Basic Configuration

Name	Description
Name	<p>The name is used to identify the logging configuration and must be unique. Use a name that will help you to remember the purpose or kind of SNMP trap for which you are configuring this log information.</p> <p>Valid characters include alphanumeric, dash (-), slash (/), colon (:), and underscore(_).</p>
Trap Object ID	<p>Specify the Object Identifier of the trap you want to log.</p> <p>You can obtain the OID value from the <code>trap.log</code> or <code>trap.csv</code> log file.</p> <div>Note: NNMi automatically logs the OID for any undefined traps to these files.</div> <p>Click here for more information about determining a trap OID for an undefined trap.</p> <ol style="list-style-type: none">1. Export the <code>trap.csv</code> file to an Excel spreadsheet.2. Search for NO TRAP LOGGING CONFIGURATION FMT FOR. <div>Tip: This text should appear in the Formatted Message column.</div> <ol style="list-style-type: none">3. Look for the trap OID value that follows this message. <div>Tip: You can also navigate to the OID column to identify the OID for this trap.</div> <div>Note: You can use a wildcard character (*) in the Trap Object ID attribute to create an SNMP Trap Incident configuration for multiple OIDs. This feature enables you</div>

Trap Logging Basic Configuration, continued

Name	Description									
	<div><p>to use the same SNMP Trap Incident Configuration for similar traps. For example, you might have a device class for which you might want to capture a particular kind of trap as an SNMP Trap Incident and ignore the rest.</p></div> <p>When using the wildcard (*) character in the Trap Object ID (OID) attribute, note the following:</p> <ul style="list-style-type: none">• The OID must be unique.• Only one wildcard character is permitted within the Trap Object ID (OID) attribute.• The wildcard must appear at the end of an OID. For example .1.3.6.1.4.1.* is valid; however, .1.3.6.1.4.*.2 is NOT valid.• NNMi permits wildcards only in OIDs beginning with .1.3.6.1.4 (private MIBs).• The wildcard character is not valid for an SNMPv1 generic trap because these traps do not begin with .1.3.6.1.4.• When checking whether an SNMP Trap Incident Configuration exists, NNMi's TrapFilter uses only implicit matching when checking generic SNMPv1 traps OIDs. See "About the Trap Service Stages" on page 684 for more information about TrapFilter.• NNMi matches the OID value using the longest match. Specific OID matches take precedence over an OID that is matched using the wildcard character. Click here for an example: <p>The following table provides an example of precedence between a specific OID and one that includes a wildcard. This example also illustrates how NNMi uses the longest match.</p> <p>Example of Matching Incoming SNMP Traps Using Specific and Longest Match Criteria</p> <table><tr><th>SNMP OID Attribute Configuration</th><th>Incoming SNMP Trap</th><th>Match Criteria</th></tr><tr><td>.1.3.6.1.4.1.2.3</td><td>.1.3.6.1.4.1.2.3</td><td>Specific OID takes precedence over the wildcard OID configuration.</td></tr><tr><td>.1.3.6.1.4.1.*</td><td>.1.3.6.1.4.1.2</td><td>The wildcard OID takes precedence</td></tr></table>	SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria	.1.3.6.1.4.1.2.3	.1.3.6.1.4.1.2.3	Specific OID takes precedence over the wildcard OID configuration.	.1.3.6.1.4.1.*	.1.3.6.1.4.1.2	The wildcard OID takes precedence
SNMP OID Attribute Configuration	Incoming SNMP Trap	Match Criteria								
.1.3.6.1.4.1.2.3	.1.3.6.1.4.1.2.3	Specific OID takes precedence over the wildcard OID configuration.								
.1.3.6.1.4.1.*	.1.3.6.1.4.1.2	The wildcard OID takes precedence								

Trap Logging Basic Configuration, continued

Name	Description
	If the Disabled option is selected, NNMi does not log the specified SNMP Trap configuration to the <code>trap.log</code> and <code>trap.csv</code> log files in the specified Node Group.

Trap Logging Log Configuration

Name	Description
Log Message Format	<p>Specify the information you want NNMi to include in the SNMP Trap's Message attribute value. You can use any combination of valid parameter strings and Custom Incident attributes to configure the Message.</p> <div>Note: The Log Message limit is 1024 characters. If the returned values exceed this limit, NNMi truncates the value starting from the end of the returned text string.</div> <p>For more information, see:</p> <p>"Valid Parameters for Trap Logging Messages" on page 1438</p> <p>"Include varbinds in Your Log Message Format " on page 1442</p>
Use the SNMP Trap Incident Configuration values	<p>Specifies that you want the values from the associated SNMP Trap Incident Configuration to be used for the following attributes:</p> <ul style="list-style-type: none">• Severity• Category• Family• Incident Message Format <p>If selected <input checked="" type="checkbox"/>, you are not able to provide values for the attributes listed</p>

Trap Logging Log Configuration, continued

Name	Description												
Severity	<p>The Severity represents the seriousness calculated for the SNMP trap. Use the Severity attribute to specify the Severity that should be assigned to the SNMP trap when it appears in the <code>trap.log</code> and <code>trap.csv</code> log files.</p> <p>Possible values are described in the following table.</p> <p>Incident Severity Values</p> <table><tr><th>Attribute</th><th>Description</th></tr><tr><td>Normal</td><td>Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.</td></tr><tr><td>Warning</td><td>Indicates there might be a problem related to the associated object.</td></tr><tr><td>Minor</td><td>Indicates NNMi has detected problems related to the associated object that require further investigation.</td></tr><tr><td>Major</td><td>Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</td></tr><tr><td>Critical</td><td>Indicates NNMi has detected problems related to the associated object that require immediate attention.</td></tr></table>	Attribute	Description	Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.	Warning	Indicates there might be a problem related to the associated object.	Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.	Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.	Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.
Attribute	Description												
Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.												
Warning	Indicates there might be a problem related to the associated object.												
Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.												
Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.												
Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.												
Category	<p>The Category attribute helps you organize your SNMP Traps. Select the category that you want to be associated with this SNMP Trap when it appears in the <code>trap.log</code> and <code>trap.csv</code> log files.</p> <p>Each of the possible Category values is described in the following table.</p>												

Trap Logging Log Configuration, continued

Name	Description																
	<p>Incident Categories Provided by NNMi</p> <table> <tr> <th>Category</th><th>Description</th></tr> <tr> <td>Accounting</td><td>Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Application Status</td><td>Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).</td></tr> <tr> <td>Configuration</td><td>Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.</td></tr> <tr> <td>Fault</td><td>Indicates a problem with the network, for example Node Down.</td></tr> <tr> <td>Performance</td><td>Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .</td></tr> <tr> <td>Security</td><td>Indicates there is a problem related to authentication. For example, an SNMP authentication failure.</td></tr> <tr> <td>Status</td><td>Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.</td></tr> </table>	Category	Description	Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.	Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).	Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.	Fault	Indicates a problem with the network, for example Node Down.	Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .	Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.	Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.
Category	Description																
Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.																
Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).																
Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.																
Fault	Indicates a problem with the network, for example Node Down.																
Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .																
Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.																
Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.																
Family	<p>You can use Family values to further categorize the types of SNMP Traps that might be generated. Select the Family that you want to be associated with this SNMP Trap when it appears in the trap.log and trap.csv log files.</p> <p>Each of the possible Family values are described in the following table.</p>																

Trap Logging Log Configuration, continued

Name	Description																			
	Incident Family Attribute Values Provided by NNMi																			
	<table> <tr> <th>Family</th><th>Description</th></tr> <tr> <td>Address</td><td>Indicates the incident is related to an address problem.</td></tr> <tr> <td>Aggregated Port</td><td>Indicates the incident is related to a Link Aggregation¹ or Split Link Aggregation² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced).</td></tr> <tr> <td>BGP</td><td>Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Board</td><td>Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Card</td><td>Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Chassis</td><td>Indicates the incident is related to a chassis problem.</td></tr> <tr> <td>Component Health</td><td>Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.</td></tr> <tr> <td>Connection</td><td>Indicates the incident is related to a problem with one or more connections.</td></tr> <tr> <td>Correlation</td><td>Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.</td></tr> </table>	Family	Description	Address	Indicates the incident is related to an address problem.	Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .	BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.	Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	Chassis	Indicates the incident is related to a chassis problem.	Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.	Connection	Indicates the incident is related to a problem with one or more connections.	Correlation
Family	Description																			
Address	Indicates the incident is related to an address problem.																			
Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .																			
BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.																			
Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																			
Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																			
Chassis	Indicates the incident is related to a chassis problem.																			
Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.																			
Connection	Indicates the incident is related to a problem with one or more connections.																			
Correlation	Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.																			

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.





²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Trap Logging Log Configuration, continued

Name	Description																													
	Incident Family Attribute Values Provided by NNMi, continued																													
	<table> <tr> <th>Family</th><th>Description</th></tr> <tr> <td>Custom Poller</td><td>Indicates the incident is related to the NNMi Custom Poller feature.</td></tr> <tr> <td>HSRP</td><td>(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).</td></tr> <tr> <td>Interface</td><td>Indicates the incident is related to a problem with one or more interfaces.</td></tr> <tr> <td>IP Subnet</td><td>Indicates the incident is related to a problem with the IP Subnet.</td></tr> <tr> <td>License</td><td>Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604.</td></tr> <tr> <td>NNMi Health</td><td>Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.</td></tr> <tr> <td>Node</td><td>Indicates the incident is related to a node problem.</td></tr> <tr> <td>OSPF</td><td>Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>RAMS</td><td>Indicates the incident is related to a Router Analytics Management System problem.</td></tr> <tr> <td>RMON</td><td>Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>RRP</td><td>(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.</td></tr> <tr> <td>STP</td><td>Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Syslog</td><td>NNMi does not use this Family with default configurations. It is available for incidents you define.</td></tr> <tr> <td>System and</td><td>Indicates the incident is related to a problem with a system</td></tr> </table>	Family	Description	Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.	HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).	Interface	Indicates the incident is related to a problem with one or more interfaces.	IP Subnet	Indicates the incident is related to a problem with the IP Subnet.	License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .	NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.	Node	Indicates the incident is related to a node problem.	OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	RAMS	Indicates the incident is related to a Router Analytics Management System problem.	RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.	STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.	System and
Family	Description																													
Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.																													
HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).																													
Interface	Indicates the incident is related to a problem with one or more interfaces.																													
IP Subnet	Indicates the incident is related to a problem with the IP Subnet.																													
License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .																													
NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.																													
Node	Indicates the incident is related to a node problem.																													
OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																													
RAMS	Indicates the incident is related to a Router Analytics Management System problem.																													
RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																													
RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.																													
STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																													
Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.																													
System and	Indicates the incident is related to a problem with a system																													

¹Hot Standby Router Protocol

Trap Logging Log Configuration, continued





Name	Description										
	Incident Family Attribute Values Provided by NNMi, continued <table> <tr> <th>Family</th><th>Description</th></tr> <tr> <td>Applications</td><td>or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.</td></tr> <tr> <td>Trap Analysis</td><td> <p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</p> <p>Indicates the incident is related to an SNMP trap storm.</p> </td></tr> <tr> <td>VLAN</td><td>Indicates the incident is related to a problem with a virtual local area network.</td></tr> <tr> <td>VRRP</td><td>(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).</td></tr> </table>	Family	Description	Applications	or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.	Trap Analysis	<p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</p> <p>Indicates the incident is related to an SNMP trap storm.</p>	VLAN	Indicates the incident is related to a problem with a virtual local area network.	VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).
Family	Description										
Applications	or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.										
Trap Analysis	<p>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) -- click here for more information.</p> <p>Indicates the incident is related to an SNMP trap storm.</p>										
VLAN	Indicates the incident is related to a problem with a virtual local area network.										
VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).										
Incident Message Format	Displays the Message Format for the associated SNMP Trap Incident Configuration, if any.										
Trap Enabled	Displays whether the associated SNMP Trap Incident Configuration, if any, is Enabled.										
Author	<p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <p>Click the  Lookup icon and select  Show Analysis to display details about the currently selected Author, select  Quick Find to access the list of existing Author values, or click  New to create one.</p>										

Node Group Logging Configuration Form

NNMi enables you override the Trap Logging Configuration for nodes in a specified Node Group.




To configure Node Group Trap Configuration:

¹Virtual Router Redundancy Protocol

1. Navigate to the **Incidents** folder:
 - a. From the workspace navigation pane, select the  **Configuration** workspace.
 - b. Expand the **Incidents** folder.
2. Expand the **Trap Server** folder.
3. Select **Trap Logging Configuration**.
4. Navigate to the **Node Group Logging Configuration** tab.
5. Do one of the following:
 - a. To add a configuration, click the  New icon, and continue.
 - b. To edit a configuration, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a configuration, select a row, and click the  Delete icon.
6. Make your Basic configuration choices (see [table](#)).
7. Make your Log Configuration choices (see [table](#)).
8. Click  **Save and Close** to save your changes and return to the previous form.

Note: See "[Manage Incoming SNMP Traps](#)" on page 871 for information about the criteria NNMi uses to determine when to receive or discard traps.

Node Group Logging Basic Configuration

Name	Description
Node Group	<p>Specifies the Node Group that contains the nodes for which you want to configure trap logging information.</p> <p>To specify a Node Group, click the  Lookup icon, and do one of the following:</p> <ul style="list-style-type: none">• To display a list of possible Node Groups, select  Quick Find. In the Quick Find dialog, select the Incident of interest.• To create a Node Group, select  New.
Ordering	<p>Ordering specifies the order in which the configuration should be considered for nodes that appear in multiple Node Groups and therefore might have conflicting Node Group Logging Configurations. NNMi uses the Node Group Logging Configuration that has the lowest Ordering value.</p> <p>For example, Ordering is used in the following scenario:</p>

Node Group Logging Basic Configuration, continued

Name	Description
	<ul style="list-style-type: none"> • A node is in both the Routers Node Group and the Switches Node Group. • Node Group Logging Configuration is specified for both Node Groups. • The Ordering value for the Routers Node Group is 3. • The Ordering value for the Switches Node Group is 5 <p>In this example, for any node that appears in both the Routers Node Group and the Switches Node Groups. NNMi uses the Node Group Logging Configuration specified for the Routers Node Group, which has the lowest Ordering number.</p>
Logging	<p>If the Enabled options is selected, NNMi logs this SNMP Trap to the <code>trap.log</code> and <code>trap.csv</code> log files for the nodes in the specified Node Group.</p> <p>If the Disabled option is selected, NNMi does not log the specified SNMP Trap configuration to the <code>trap.log</code> and <code>trap.csv</code> log files for nodes in the specified Node Group.</p> <p>If the Inherited option is selected, NNMi uses the Logging value from the Logging Configuration form. For example, if Logging is Disabled in the Logging Configuration for this trap, then logging is disabled for the nodes in the specified Node Group.</p> <p>This option is available only for Node Group Logging Configuration. See "Trap Logging Configuration Form" on page 1421 for more information.</p>

Trap Logging Log Configuration

Name	Description
Log Message Format	<p>Specify the information you want NNMi to include in the SNMP Trap's Message attribute value. You can use any combination of valid parameter strings and Custom Incident attributes to configure the Message.</p> <p>For more information, see:</p>

Trap Logging Log Configuration, continued

Name	Description												
	<p>"Valid Parameters for Trap Logging Messages" on page 1438</p> <p>"Include varbinds in Your Log Message Format " on page 1442</p>												
Severity	<p>The Severity represents the seriousness calculated for the SNMP trap. Use the Severity attribute to specify the Severity that should be assigned to the SNMP trap when it appears in the trap.log and trap.csv log files.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: If different from the associated SNMP Trap Incident Configuration, the Severity value overrides the SNMP Trap Incident Configuration Severity value.</p> </div> <p>Possible values are described in the following table.</p> <p>Incident Severity Values</p> <table> <tr> <th>Attribute</th><th>Description</th></tr> <tr> <td>Normal</td><td>Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.</td></tr> <tr> <td>Warning</td><td>Indicates there might be a problem related to the associated object.</td></tr> <tr> <td>Minor</td><td>Indicates NNMi has detected problems related to the associated object that require further investigation.</td></tr> <tr> <td>Major</td><td>Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.</td></tr> <tr> <td>Critical</td><td>Indicates NNMi has detected problems related to the associated object that require immediate attention.</td></tr> </table> <p>See "Monitor Incidents for Problems" for more information about these severity values.</p>	Attribute	Description	Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.	Warning	Indicates there might be a problem related to the associated object.	Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.	Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.	Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.
Attribute	Description												
Normal	Indicates there are no known problems related to the associated object. This severity is meant to be informational. Generally, no action is needed for these incidents.												
Warning	Indicates there might be a problem related to the associated object.												
Minor	Indicates NNMi has detected problems related to the associated object that require further investigation.												
Major	Indicates NNMi has detected problems related to the associated object to be resolved before they become critical.												
Critical	Indicates NNMi has detected problems related to the associated object that require immediate attention.												
Category	The Category attribute helps you organize your SNMP Traps. Select the category that you want to be associated with this SNMP Trap when it appears in the trap.log												

Trap Logging Log Configuration, continued

Name	Description														
	<p>and trap.csv log files.</p> <p>Note: If different from the associated SNMP Trap Incident Configuration, the Category value overrides the SNMP Trap Incident Configuration Severity value.</p> <p>Each of the possible Category values is described in the following table.</p> <p>Incident Categories Provided by NNMi</p> <table> <tr> <th>Category</th><th>Description</th></tr> <tr> <td>Accounting</td><td>Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Application Status</td><td>Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).</td></tr> <tr> <td>Configuration</td><td>Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.</td></tr> <tr> <td>Fault</td><td>Indicates a problem with the network, for example Node Down.</td></tr> <tr> <td>Performance</td><td>Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .</td></tr> <tr> <td>Security</td><td>Indicates there is a problem related to authentication. For example, an SNMP authentication failure.</td></tr> </table>	Category	Description	Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.	Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).	Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.	Fault	Indicates a problem with the network, for example Node Down.	Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .	Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.
Category	Description														
Accounting	Used to indicate problems related to usage statistics and allocation of costs associated with the billing of time and services provided by devices. This category is not used by NNMi with default configurations, but it is available for incidents you define.														
Application Status	Indicates there is a problem with the health of the NNMi software. Examples of these kinds of events include license expiration (see "Extend a Licensed Capacity" on page 1605) or that a certain NNMi process or service lost connection to the Process Status Manager (see "Stop or Start an NNMi Process" on page 87 and "Stop or Start NNMi Services" on page 93).														
Configuration	Indicates there is a problem with the configuration of a managed device. For example, there is a physical address mismatch.														
Fault	Indicates a problem with the network, for example Node Down.														
Performance	Indicates a Monitored Attribute value <i>crossed</i> a configured threshold. For example, Disk Space Utilization exceeds the configured threshold criteria for High Value = 90 percent .														
Security	Indicates there is a problem related to authentication. For example, an SNMP authentication failure.														

Trap Logging Log Configuration, continued

Name	Description												
	Incident Categories Provided by NNMi, continued <table> <tr> <th>Category</th><th>Description</th></tr> <tr> <td>Status</td><td>Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.</td></tr> </table>	Category	Description	Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.								
Category	Description												
Status	Indicates some kind of status message. Examples of these kinds of incidents include "SNMP Link Up" or an "HSRP Group status Normal" message.												
Family	<p>You can use Family values to further categorize the types of SNMP Traps that might be generated. Select the category that you want to be associated with this SNMP Trap when it appears in the <code>trap.log</code> and <code>trap.csv</code> log files.</p> <p>Note: If different from the associated SNMP Trap Incident Configuration, the Family value overrides the SNMP Trap Incident Configuration Severity value.</p> <p>Each of the possible Family values are described in the following table.</p> <p>Incident Family Attribute Values Provided by NNMi</p> <table> <tr> <th>Family</th><th>Description</th></tr> <tr> <td>Address</td><td>Indicates the incident is related to an address problem.</td></tr> <tr> <td>Aggregated Port</td><td>Indicates the incident is related to a Link Aggregation¹ or Split Link Aggregation² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced).</td></tr> <tr> <td>BGP</td><td>Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Board</td><td>Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr> <tr> <td>Card</td><td>Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for</td></tr> </table>	Family	Description	Address	Indicates the incident is related to an address problem.	Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .	BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.	Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for
Family	Description												
Address	Indicates the incident is related to an address problem.												
Aggregated Port	Indicates the incident is related to a Link Aggregation ¹ or Split Link Aggregation ² problem. See Interface Form: Link Aggregation Tab (NNMi Advanced) .												
BGP	Indicates the incident is related to a problem with BGP (Border Gateway Protocol). This family is not used by NNMi with default configurations, but it is available for incidents you define.												
Board	Indicates the incident is related to a board problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.												
Card	Indicates the incident is related to a card problem. This family is not used by NNMi with default configurations, but it is available for												

¹Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.





²Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

Trap Logging Log Configuration, continued

Name	Description
Incident Family Attribute Values Provided by NNMi, continued	
Family	Description
	incidents you define.
Chassis	Indicates the incident is related to a chassis problem.
Component Health	Indicates the incident is related to Node Sensor or Physical Sensor data collected by NNMi. See Chassis Form: Physical Sensors Tab and Card Form: Physical Sensors Tab for more information.
Connection	Indicates the incident is related to a problem with one or more connections.
Correlation	Indicates the incident has additional incidents correlated beneath it. These incidents are associated with a duplicate count so that you can determine the number of correlated incidents associated with it.
Custom Poller	Indicates the incident is related to the NNMi Custom Poller feature.
HSRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Hot Standby Router Protocol (HSRP¹).
Interface	Indicates the incident is related to a problem with one or more interfaces.
IP Subnet	Indicates the incident is related to a problem with the IP Subnet.
License	Indicates the incident is related to a licensing problem. See "Track Your NNMi Licenses" on page 1604 .
NNMi Health	Indicates the incident is related to NNMi Health. See the Check NNMi Health for more information.
Node	Indicates the incident is related to a node problem.
OSPF	Indicates the incident is related to an OSPF problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.
RAMS	Indicates the incident is related to a Router Analytics Management System problem.

¹Hot Standby Router Protocol

Trap Logging Log Configuration, continued

Name	Description																		
	Incident Family Attribute Values Provided by NNMi, continued																		
	<table><tr><th>Family</th><th>Description</th></tr><tr><td>RMON</td><td>Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr><tr><td>RRP</td><td>(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.</td></tr><tr><td>STP</td><td>Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.</td></tr><tr><td>Syslog</td><td>NNMi does not use this Family with default configurations. It is available for incidents you define.</td></tr><tr><td>System and Applications</td><td>Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.</td></tr><tr><td>Trap Analysis</td><td><div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) – click here for more information.</div><div>Indicates the incident is related to an SNMP trap storm.</div></td></tr><tr><td>VLAN</td><td>Indicates the incident is related to a problem with a virtual local area network.</td></tr><tr><td>VRRP</td><td>(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP¹).</td></tr></table>	Family	Description	RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.	STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.	Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.	System and Applications	Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.	Trap Analysis	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) – click here for more information.</div> <div>Indicates the incident is related to an SNMP trap storm.</div>	VLAN	Indicates the incident is related to a problem with a virtual local area network.	VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP ¹).
	Family	Description																	
	RMON	Indicates the incident is related to a Remote Monitor (IETF standard, RFC 1757) problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																	
	RRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with a Router Redundancy Protocol configuration.																	
	STP	Indicates the incident is related to Spanning-Tree Protocol problem. This family is not used by NNMi with default configurations, but it is available for incidents you define.																	
	Syslog	NNMi does not use this Family with default configurations. It is available for incidents you define.																	
	System and Applications	Indicates the incident is related to a problem with a system or application in your environment that is configured to send traps to the NNMi server, for example your corporate database application.																	
	Trap Analysis	<div>Requires HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET) – click here for more information.</div> <div>Indicates the incident is related to an SNMP trap storm.</div>																	
	VLAN	Indicates the incident is related to a problem with a virtual local area network.																	
VRRP	(<i>NNMi Advanced</i>) Indicates the incident is related to a problem with Virtual Router Redundancy Protocol (VRRP ¹).																		
Author	<div>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</div> <div><ul style="list-style-type: none">Click  Lookup and select  Show Analysis to display details about the currently selected Author.Click  Quick Find to access the list of existing Author values.Click  New to create an Author value.</div>																		

¹Virtual Router Redundancy Protocol

Valid Parameters for Trap Logging Messages

When configuring Trap Logging messages, consider using SNMP Trap Incident information as part of the message. NNMi provides the following parameter values. Use these parameters as variables when formatting an incident message.

Tip: See the [Using the Incident Form](#) for more information about the parameter values.

Note: NNMi stores varbind values as custom incident attributes (CIAs).

See "[Configure Trap Logging](#)" on page 1420 for more information about configuring messages.

Parameter strings are available for the following:

Note: See the following tables to view the valid parameters for Trap Logging messages: [Parameter Strings for all Incidents \(Attributes from an Incident form\)](#), [Parameter Strings for Node Source Objects \(Attributes from a Node form\)](#), and [Parameter Strings for all Incidents \(Attributes not Visible from any form\)](#).

- Parameter strings for all incidents (Incident form attributes) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Incident form attributes)

Parameter String	Description
\$category, \$cat	Value of the Category attribute in the Trap Logging Configuration. If no Trap Logging configuration is specified, NNMi uses the value Configuration.
\$family, \$fam	Value from the Family attribute in the Trap Logging Configuration. If no Trap Logging configuration is specified, NNMi uses the value Node
\$lifecycleState, \$lcs	By default, this value is Registered.
\$name	Value of the Name attribute from the Trap Logging Configuration.
\$nature, \$nat	By default, this value is Symptom.
\$origin, \$ori	By default, this value is SNMP Trap.
\$originOccurrenceTime, \$oot	Value from the Origin Occurrence Time attribute in the associated SNMP Trap Incident Configuration. When trap arrived at the trap server
\$priority, \$pri	By default, this value is None.
\$sev, \$severity	Value of the Severity attribute of the Trap Logging Configuration. If no Trap Logging configuration is specified, NNMi uses the value Normal.

- Parameter Strings for Node Source Objects (Node form attributes) ([Click here for a list of choices.](#))

Parameter Strings for Node Source Objects (Node form attributes)

Parameter String	Description
\$managementAddress, \$mga	The fully-qualified DNS name of the source address of the trap.
\$sourceNodeLongName, \$sln	The fully-qualified DNS name of the source address of the trap.
\$sourceNodeName, \$snn	The HostName of the trap source.

- Parameter Strings for all incidents (Additional information that is not visible in any form) ([Click here for a list of choices.](#))

Parameter Strings for all Incidents (Attributes not visible in any form)

Parameter String	Description
\$count, \$cnt	Value representing the number of varbinds that appear in the SNMP Trap.
\$oid	Value of the unique Object Identifier (OID) for the SNMP trap.
\$originOccurrenceTimeMs, \$oms	Time the trap was received in number of milliseconds (measured since January 1, 1970, 00:00:00 GMT - Greenwich Mean Time).

- Information established in varbinds ([Click here for a list of choices.](#))

Parameter Strings for varbinds

Parameter String	Description
\$<position_number>	Value of the position number for a varbind . For example, to indicate you want to use the varbind in position 1, enter: \$1 If you know the varbind position number, use this parameter.
\$<varbind_name>	Value of the name that is used for the varbind.
\$<varbind_oid>	Value of the object identifier for a specified varbind. For example, \$.1.3.6.1.6.3.1.1.5.1. Use this parameter when you are not certain of a varbind position number.
\$*	Used to indicate you want all of the varbind values, to be passed to the action configuration.

- Functions to generate values ([Click here for a list of choices.](#))

The function described in the following table replaces the specified numeric value with the associated text value stored in the varbind.

Note: The associated MIB must have been loaded using the [nnmloadmib.ovpl](#) command.

Functions to Generate Values Within the Incident Message

Function	Description
\$oidtext (\$<position_number>)	A <position_number> argument specifies the numeric value of the position number for a specific varbind . For example, \$oidtext(\$2). Note: The position number you enter must represent a varbind that contains an Object Identifier (OID) value.

Functions to Generate Values Within the Incident Message, continued

Function	Description
	<p>NNMi returns the textual value of the OID for the varbind specified.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ If the MIB is not loaded, NNMi returns the numeric OID value. ■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$oidtext (\$<varbind_oid>)	<p>The <varbind_oid> argument specifies the Object Identifier (OID) for a specific varbind. For example, \$oidtext(\$.1.3.6.1.6.3.1.1.5.1.)</p> <p>Tip: Use this argument to the \$oidtext() function when you are not certain of a varbind position number.</p> <p>NNMi replaces the numeric value with the textual value of the OID you specify.</p> <p>Note the following:</p> <ul style="list-style-type: none"> ■ If the MIB is not loaded, NNMi returns the numeric OID value. ■ If the OID has a MIB instance, the number representing the MIB instance is appended to the textual OID value.
\$text (\$<position_number>)	<p>The <position_number> argument specifies the numeric value of the varbind position number. For example, to indicate you want to use the varbind in position 1, enter: \$1.</p> <p>NNMi replaces the numeric value with the text value stored in the varbind.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>
\$text (\$<varbind_oid>)	<p>The <varbind_oid> argument specifies the object identifier for a specific varbind. For example, \$.1.3.6.1.6.3.1.1.5.1.</p> <p>Use this argument to the \$text function when you are not certain of a varbind position number.</p> <p>NNMi replaces the numeric value with the text value stored in the varbind.</p> <p>Note: If a text value is not available, NNMi returns the numeric value.</p>

Include varbinds in Your Log Message Format

You can use varbinds in your message format to extend the amount of information presented. SNMP trap varbinds are identified by the Abstract Syntax Notation value (ASN.1).

To include a varbind in your Trap Logging Configuration message format, type the dollar-sign character (\$) plus any of the following

- Varbind position number or asterisk (*) to include all varbind values
- Object identifier (oid) of the varbind (useful when the varbind position number is not consistent among vendors)

The following table presents some example formats with the subsequent output.

Example Incident Message Formats


Example Message Format	Output in Incident View
Possible trouble with \$3	Possible trouble with <varbind 3>
Possible trouble with \$11	Possible trouble with <varbind 11>
Possible trouble with \$77 (where the varbind position 77 does not exist)	Possible trouble with <Invalid or unknown varbind> 77
Possible trouble with \$3x	Possible trouble with <varbind 3>x
Possible trouble with \$1.2.3.4.5	Possible trouble with <value of the varbind with oid of 1.2.3.4.5>

Tip: NNMi provides an error message when a varbind cannot be found. For example, if you enter an unavailable varbind position, name, or object identifier (oid), NNMi returns an "Invalid or unknown varbind" error message.

Chapter 14: Using Route Analytics Management System (RAMS) with NNMi Advanced

Route Analytics Management System (RAMS) is an IP Route Analytics tool that monitors routing protocols and builds a real-time routing topology map. You can use RAMS data to enhance NNMi.

- After configuring RAMS as described in "[Configure HP Route Analytics Management System \(NNMi Advanced\)](#)" on page 1445, the NNMi Path View displays the following enhanced information:
 - NNMi displays the Path View map faster, because RAMS does not use data collected from SNMP MIBs to determine the routing paths (avoiding any SNMP timeout issues).
 - Path View might be more accurate than the Path View data collected from NNMi alone.
 - When RAMS data determines the router paths, NNMi ignores the `PathConnections.xml` file (see "[Configure a Path View Map](#)" on page 563).
- After you configure RAMS as described in "[HP RAMS MPLS WAN Configuration \(NNMi Advanced\)](#)" on page 1446, NNMi provides the following additional information:
 - The Inventory workspace's [MPLS WAN Clouds \(RAMS\) table view](#) shows data. Additional information is provided on each [MPLS WAN Cloud \(RAMS\) form](#).
 - A new NNMi map, the MPLS WAN Cloud Map view, is available from the Actions menu for participating objects (see [MPLS WAN Cloud Map](#)).
 - Path View shows all Equal Cost Multi-Paths (ECMP) rather than being limited to one route.



Note: (NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.

For more information on MPLS WAN, see the *HP Route Analytics Management System (RAMS) for MPLS WAN User's Guide*, which is available at:

<http://h20230.www2.hp.com/selfsolve/manuals>.

Related Topics

[Path Between Two Nodes](#)

[Path Calculation Rules](#)

[Path View Limitations](#)

HP RAMS MPLS WAN (NNMi Advanced)

HP Route Analytics Management System (RAMS) for MPLS WAN enables you to gather network connectivity information for enterprises that have multiple sites connected by a WAN through Internet Service Providers (ISPs). These ISPs use [MPLS](#)¹ within their own networks. MPLS enables the ISPs to support large numbers of Virtual Private Networks (VPNs). Although RAMS does not have visibility into the routing structure within the ISP network, it displays and analyzes routing topologies that extend across the WAN.

HP RAMS MPLS WAN is integrated with NNMi and is important if your enterprise has multiple sites that are connected by a Layer 3 VPN. Each of your sites will typically have one or more Customer Edge (CE) routers that are connected to the ISP's Provider Edge (PE) routers. The ISP handles all the routing (including [BGP](#)²), as well as the VPN tunneling through its own network. With MPLS WAN, you can use RAMS to monitor all the sites and provide enterprise connectivity information. The topology view shows how an enterprise site is connected to multiple sites through an MPLS WAN cloud.

Although detailed routing through the ISP is not available, RAMS indicates whether there is connectivity between the ISP's PE routers. When one of your sites advertises [routing prefixes](#)³, you can determine whether the ISP is correctly passing all the routing prefixes (not dropping any or sending additional prefixes).

For more information on MPLS WAN, see the *HP Route Analytics Management System User's Guide*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

Related Topics:

["Configure HP Route Analytics Management System \(NNMi Advanced\)" on the next page](#)

["Using Route Analytics Management System \(RAMS\) with NNMi Advanced" on the previous page](#)

["HP RAMS MPLS WAN Configuration \(NNMi Advanced\)" on page 1446](#)

¹Multiprotocol Label Switching

²Border Gateway Protocol

³A network protocol technique used to shorten or filter the amount of required routing information in each packet by declaring a prefix for an entire group of packets. This prefix also indicated the number of bits in the address.

Configure HP Route Analytics Management System (NNMi Advanced)





(NNMi Advanced, plus HP Route Analytics Management System (RAMS) for MPLS WAN) Route Analytics Management System (RAMS) is an IP Route Analytics tool that monitors routing protocols and builds a real-time routing topology map. RAMS data enhances the information available in NNMi Path View maps. See ["Using Route Analytics Management System \(RAMS\) with NNMi Advanced" on page 1443](#) for more information.

You can also use RAMS with the HP RAMS MPLS WAN feature, which enables you to gather network connectivity data between multiple sites connected by a WAN through Internet Service Providers (ISPs). See ["Using Route Analytics Management System \(RAMS\) with NNMi Advanced" on page 1443](#) for more information.

Note: (NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.

To enable NNMi to use RAMS data, you must use the RAMS form to configure each RAMS server you want to use. The RAMS form provides details about the RAMS appliance and the associated RAMS database to be used with NNMi.

To configure a RAMS server:

1. [Navigate to the RAMS Servers form.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Select **RAMS Servers**.
2. Do one of the following:
 - To establish a RAMS Server configuration, click the  New icon and continue.
 - To edit a RAMS Server configuration, select a row, click the  Open icon, and continue.
 - To delete a RAMS server configuration, select a row and click the  Delete icon.
3. Provide the required information (see [Basic Attributes table](#)).
4. Click  **Save and Close** to save your changes and return to the list of configured RAMS.

Basic Attributes

Attribute	Description
Host	Hostname (<i>not case-sensitive</i>) or IP address used to identify the RAMS appliance that you want NNMi to access.

Basic Attributes, continued

Attribute	Description
Query Password	Query password configured for the RAMS appliance.
Database Name	Name of the database that NNMi should access. This database must reside on the RAMS appliance that you have identified in the Name attribute.
Priority	Used when you configure more than one RAMS appliance. Determines the order in which NNMi attempts to access the configured RAMS appliances. The lower the number, the higher the priority. For example, the number 1 is the highest priority.

Related Topics

["Using Route Analytics Management System \(RAMS\) with NNMi Advanced" on page 1443](#)

["HP RAMS MPLS WAN Configuration \(NNMi Advanced\)" below](#)

HP RAMS MPLS WAN Configuration (NNMi Advanced)

For more information on MPLS WAN, see the *HP Route Analytics Management System (RAMS) for MPLS WAN User's Guide*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

The HP NNMi – HP RAMS MPLS WAN integration provides actions for accessing several MPLS WAN tools from the NNMi console.

Enabling the HP NNMi – HP RAMS MPLS WAN Integration:

This section describes the steps to enable the HP NNMi – HP RAMS MPLS WAN Integration.

Prerequisites:

- [Configure the RAMS Server](#)
- [Create an NNMi Web Service Client for RAMS](#)

To configure the connection between NNMi and the HP RAMS MPLS WAN, follow these steps:

1. In the NNMi console, open the HP NNMi – HP RAMS MPLS WAN Integration Configuration form:
 - a. Select **Integration Module Configuration**.
 - b. Select **HP RAMS MPLS RAMS**.
2. Select the **Enable Integration** check box to activate the integration fields on the form.

3. Enter the required information for connecting to the NNMi management server and to the RAMS server (see [table](#)).
4. Click **Submit**.

The status message displays. If the status message indicates a problem connecting to the NNMi management server, click **Return**, and change the values as suggested in the message.

Changing the HP NNMi – HP RAMS MPLS WAN Integration Configuration:

To change the connection between the NNMi and the HP RAMS MPLS WAN, follow these steps:

1. In the NNMi console, open the HP NNMi – HP RAMS MPLS WAN Integration Configuration form:
 - a. Select **Integration Module Configuration**
 - b. Select **HP RAMS MPLS RAMS**
2. Modify the configuration values as appropriate (see [table](#))
3. Verify that the **Enable Integration** check box in the form is selected
4. Click **Submit**.

The configuration settings are changed.

Disabling the HP NNMi – HP RAMS MPLS WAN Integration

To disable the connection between the NNMi and the HP RAMS MPLS WAN, follow these steps:

1. In the NNMi console, open the HP NNMi – HP RAMS MPLS WAN Integration Configuration form:
 - a. Select **Integration Module Configuration**
 - b. Select **HP RAMS MPLS RAMS**
2. Clear the **Enable Integration** check box
3. Click **Submit**.

The integration fields are disabled and the changes take effect immediately.

HP NNMi – HP RAMS MPLS WAN Integration Configuration Form Reference

The HP NNMi – HP RAMS MPLS WAN Integration Configuration form contains the parameters for configuring communications between NNMi and RAMS. This form is available from the Integration Module Configuration workspace.

Note: Only NNMi users with the Administrator NNMi role can access the HP NNMi – HP

RAMS MPLS WAN Integration Configuration form.

The following table lists the parameters for connecting RAMS to the NNMi management server:

Attribute	Description
NNMi Host	<p>The fully qualified domain name of the NNMi management server. This field is pre-filled with host name that was used to access the NNMi console. Ensure that this value is the name that is returned by the <code>nnmofficialfqdn.ovpl -t</code> command run on the NNMi management server.</p> <p>See the nnmofficialfqdn.ovpl for more information.</p>
NNMi Port	<p>The port for connecting to the NNMi console. This field is pre-filled with the NNMi port, as specified in the following file (see "About Environment Variables" on page 86 for more information):</p> <p>Windows: <code>%NnmDataDir%\conf\nnm\props\nms-local.properties</code></p> <p>Linux: <code>\$NnmDataDir/conf/nnm/props/nms-local.properties</code></p> <p>For non-SSL connections, use the value of <code>nmsas.server.port.web.http</code>, which is 80 or 8004 by default (depending on the presence of another web server when NNMi was installed).</p> <p>For SSL connections, use the value of <code>nmsas.server.port.web.https</code>, which is 443 by default.</p>
NNMi User	<p>The NNMi User attribute value must be NNMi Web Services Client (used <i>only to provide access for software</i> that is integrated with NNMi). For information on Configuring the NNMi user interface, see User Groups Provided in NNMi.</p>
NNMi Password	<p>The password for the specified NNMi user.</p>
RAMS MPLS WAN Rediscovery Interval (hours)	<p>The time interval in hours to run the RAMS MPLS WAN discovery process.</p>

Related Topics:

[Configure One or More Route Analytics Management Systems \(NNMi Advanced\)](#)

["Using Route Analytics Management System \(RAMS\) with NNMi Advanced" on page 1443](#)

HP RAMS and Global Network Management (NNMi Advanced)

HP Route Analytics Management System (RAMS) integrates with HP Network Node Manager i Software (NNMi) in a Global Network Management environment to enhance the Layer 3 network management.


An HP RAMS device gathers the following information:

- Routes used for the data transmission
- Path computation
- Connectivity details of the geographically dispersed customer enterprises through a provider (MPLS WAN cloud)

NNMi integrates this information, resulting in a combined data view.


HP RAMS and NNMi integration can be setup in a Global Manager environment in one of the following three ways:

NNMi integrates with RAMS standalone




- NNMi Global Network Manager discovers CEs and displays Enhanced Virtual Private Network (EVPN) data
- NNMi receives MPLS WAN cloud information from RAMS standalone
- NNMi receives incidents from RAMS

NNMi integrates with the RAMS Modeling Engine (Distributed environment, with Customer Edges (CEs) discovered at Global Manager level)



- NNMi Global Network Manager discovers CEs and displays EVPN
- NNMi receives MPLS WAN cloud information from the RAMS Modeling Engine
- RAMS Modeling Engine receives information from different Route Recorders. Each Route Recorder discovers one CE to form the MPLS WAN cloud
- NNMi receives incidents from RAMS

NNMi integrates with the RAMS Modeling Engine (Distributed environment, with Customer Edges (CEs) discovered at Regional Manager level)



- NNMi Regional Manager discovers CEs. The complete EVPN displays at the NNMi Global Manager level
- NNMi Global Network Manager receives MPLS WAN cloud information from the RAMS Modeling Engine

- The RAMS Modeling Engine receives information from different Route Recorders. Each Route Recorder discovers one CE to form the MPLS WAN cloud
- NNMi receives incidents from RAMS

Chapter 15: Extending NNMi Capabilities

NNMi enables you to extend its capabilities in the following ways:

- You can integrate other programs into the console through the NNMi console menus. Plus much more, see ["Control the NNMi Console Menus" below](#).
- You can work with MIB files to configure NNMi specifically for your environment. See ["Managing MIBs" on page 1490](#).
- HP offers extended features, see ["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515](#).
- There are many ways to blend other software products into NNMi. See ["Integrations with HP and Third-Party Products" on page 1519](#).
- ["Customize Object Attributes" on page 543](#)

Tip: To extend NNMi's monitoring behavior, ["Create Custom Polling Configurations" on page 478](#) so that NNMi monitors additional information using MIB expressions.

Control the NNMi Console Menus

NNMi enables you to configure the following menu items in the NNMi console menus:

- SNMP Line Graph Actions

When you configure SNMP Line Graphs, you specify the graph appearance, including the MIB expression used to determine the values to be graphed. See ["Configure SNMP Line Graph Actions" on page 1477](#) for more information.

- Launch Actions

When you configure Launch Actions, you provide access to in-house tools, Web sites, or a variety of other resources. URLs are used to configure this powerful feature of NNMi. You must follow ["W3C Rules for URLs" on page 1466](#). See ["Configure Launch Actions" on page 1462](#) for more information. The syntax used to define the URL provides variables that can incorporate real-time data from the NNMi database. Click here for a list of choices:

You control where each menu item appears in the menu structure:

- Establish a nested structure of expanding menus ►. See ["Create Menu Nesting" on the next page](#).
- Choose an Ordering number for each menu item. See ["Configure Menu Item Basic Details" on page 1456](#).

- Control when the menu item is available. See ["Configure Menu Item Context Basic Details" on page 1459](#) and ["Specify Optional Menu Item Enablement Filters" on page 1484](#).

Behavior of the Menu Items

If you do not assign an SNMP Line Graph or Launch Action to a particular menu item, the menu item never appears in any NNMi console menu.




Some Menu Item Actions require that a particular Object Type be selected for the menu item to be available. If the required Object Type is not selected, the color of the menu item turns from black to gray to indicate it is unavailable.

If you deselect the ☐ Enabled attribute on the Menu Item form, the menu item never appears in the NNMi console's expandable menu ► structure.

Create Menu Nesting

As an NNMi administrator, you configure how menu items are nested beneath the NNMi console's expandable menu ► structure. The expandable Menus can then contain menu items or other (cascading) expandable menu ► structures.

To configure a Menu ► structure, beneath which menu items can be nested:









1. [Navigate to the Menus form](#).
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menus**.
 - d. Do one of the following:
 - To create a new menu ► structure label, click the  New icon, and continue.
 - To edit an existing menu ► structure label, double-click the row representing the configuration you want to edit, and continue.
 - To delete a menu ► structure label, select a row, and click the  Delete icon.
2. Provide the required information to define the Parent-level menu ► structure label (see [basics table](#)).
3. Click  **Save and Close** to save and apply your changes.
4. Assign Menu Items to appear beneath the menu ► structure label. The Menu from step 2 is now available as a choice in the Parent Menu attribute drop-down list for Menu Items. See ["Configure Menu Item Basic Details" on page 1456](#).
5. To test your changes to the menu ► structure:

- a. If required, access a view or form that contains the appropriate object type.
- b. If required, select an object instance.
- c. Select the menu you configured.
- d. Verify your changes are working.

Configuration Settings for a Menu Nesting

Attribute	Description
Menu Label	<p>The text string that appears in the submenu. Ensure that your expandable menu ► label is unique and provides an accurate indication about the group of Menu Items that are available beneath this expandable parent menu ► label.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: If you add two Menu Labels with the same text string but different Unique Keys, it would be <i>possible</i> for both to show up beneath the same specified Parent Menu.</p> </div> <p>The maximum length is 40 characters. Alpha-numeric, spaces, and underline characters are permitted.</p>
Accessibility Key	<p><i>Optional:</i> The value you enter here does two things:</p> <ul style="list-style-type: none"> • Specifies which ASCII character is underlined in the NNMi expandable menu ► structure if that ASCII character is part of the text entered into the Menu Label attribute, above. If the specified ASCII character is not in the Menu Label text, the designated ASCII character appears in parentheses after the expandable menu ► label. • Determines which combination of keyboard clicks launches this expandable menu ► label. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: To expand NNMi menus, you can click with the mouse or use Ctrl-Shift and the underlined character (if any). NNMi uses Ctrl-Shift (instead of Alt) to avoid the browser's main menu behavior. For example, NNMi provides Ctrl-Shift+H, then n for Help → NNMi Documentation Library. If the NNMi menu does not expand as expected, your browser configuration already over-rides the NNMi configuration for that keyboard combination of Ctrl-Shift+<ASCII character>.</p> </div> <p>If you accidentally create duplicate Accessibility Keys <i>within the same block of menu items</i>, only the first instance works.</p> <p>To determine which ASCII characters are already in use, use the Configuration workspace, User Interface, Menu Items view and the table columns for Parent Menu and Accessibility Key to sort established entries.</p>

Configuration Settings for a Menu Nesting, continued

Attribute	Description
	<p>Caution: Do not change established Accessibility Keys for expandable menu ► labels provided by HP (associated with an author value that identifies an HP product).</p>
Unique Key	<p>Used as a unique identifier when exporting and importing menu definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the Menu Label value as part of the unique key as shown in the following example:</p> <pre>com.<company_name>.nnm.menu.<menu_Label></pre> <p>Type a maximum of 80 characters. Alpha-numeric and period characters are permitted. No spaces are permitted.</p> <p>Caution: This value cannot be changed after you click the  Save icon.</p>
Author	<p>Indicates who created or last modified the Menu nesting object.</p> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value.
Parent Menu	<p>Refine the nested location of this expandable menu ► label.</p> <p>Click the  Lookup icon next to the Parent Menu attribute, and do one of the following:</p> <ul style="list-style-type: none"> To select an existing parent-level expandable menu ► label from the drop-down list (nesting the new expandable menu ► structure at a lower level in the menu structure), click the  Quick Find icon. To create a new parent-level expandable menu ► structure for nesting, click the  New icon.
Ordering	<p>A numeric value. NNMi checks for configuration settings in the order you define (lowest number first). NNMi uses the first match found to determine the placement of this expandable menu ► structure within the menu you configured.</p> <p>The Ordering numbers are calculated separately for each submenu group.</p>

Configuration Settings for a Menu Nesting, continued



Attribute	Description
	Tip: It is recommended that ordering numbers are incremented by 10s to provide flexibility over time.
Prepend Separator	Based on the Ordering number, inserts a separator line <i>above</i> this expandable menu ► label. Tip: Use this attribute to separate unrelated menus.
Enabled	Use to temporarily disable a Menu configuration (this expandable menu ► structure does not appear when disabled): Disable <input type="checkbox"/> = Temporarily disable the selected configuration. Enable <input checked="" type="checkbox"/> = Enable the selected configuration.

Configure Menu Item Basic Details

The **Menu Items** tab of the **User Interface Configuration** option enables you to make changes or additions to the items available in the NNMi console menus. For example, you can configure SNMP Line Graphs and provide menu items that display in-house tools, Web sites, or access a variety of other resources.


Note: If you are configuring a Launch Action, you must select **Actions** as the Parent Menu or an expandable menu ► submenu beneath **Actions**.

To make changes or additions to the items available in the NNMi console menus:


1. [Navigate to the Menu Items view.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To create a new menu item, click the  New icon, and continue.
 - To edit an existing menu item, double-click the row representing the configuration you want to edit, and continue.
 - To delete a menu item, select a row, and click the  Delete icon.

2. Provide the required information to define the action (see [Basics](#) tables).





Caution: If you make changes to a Menu Item provided by NNMi, those changes are at risk of being overwritten in the future. See [Author form](#) for important information.

3. Provide the required Context details (see "[Configure Menu Item Context Basic Details](#)" on [page 1459](#)).
4. Click  **Save and Close** to save and apply your changes.
5. To test your changes to the menu you configured:
 - a. If required, access a view or form that contains the appropriate object type.
 - b. If required, select an object instance.
 - c. Click the menu you configured.
 - d. Verify your changes are working.

Basics

Attribute	Description
Menu Item Label	<p>The text string that appears as the menu link. Ensure that your menu label is unique and accurately reflects the intended use of the Menu Item.</p> <p>Note: If you add two Menu Item Labels with the same text string but different Unique Keys, it would be <i>possible</i> for both to show up beneath the same specified Parent Menu.</p>
Unique Key	<p>Used as a unique identifier when exporting and importing action definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the Menu Item Label value as part of the unique key as shown in the following example:</p> <pre>com.<company_name>.nnm.menu.item.<menu_item_label></pre> <p>Type a maximum of 80 characters. Alpha-numeric and period characters are permitted. Spaces and underline characters are not permitted.</p> <p>Caution: This value cannot be changed after you click the  Save icon.</p>
Author	<p>Indicates who created or last modified the Menu Item.</p> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p>

Basics, continued

Attribute	Description
	<ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value.
Parent Menu	<p>Specify where this action appears in the NNMi console's expandable menu ► structure:</p> <ul style="list-style-type: none"> Select any existing parent-level menu item from the drop-down list. Create a new parent-level menu item. See "Create Menu Nesting" on page 1453 for more information.
Ordering	<p>A numeric value. NNMi checks for configuration settings in the order you define (lowest number first). NNMi uses the first match found to determine the placement of this Menu Item within the group you configure.</p> <p>The Ordering numbers are calculated separately for each submenu group.</p> <p>Tip: It is recommended that ordering numbers are incremented by 10s to provide flexibility over time.</p>
Prepend Separator	<p>Based on the Ordering number, inserts a separator line <i>above</i> this menu item.</p> <p>Tip: Use this attribute to separate unrelated menu items.</p>
Enabled	<p>Use to temporarily disable a Menu Item configuration (when disabled, the Menu Item does not appear under the specified Parent Menu):</p> <p>Disable <input type="checkbox"/> = Temporarily disable the selected configuration.</p> <p>Enable <input checked="" type="checkbox"/> = Enable the selected configuration.</p>

Selection

Attribute	Description
Selection Type	<p><i>Optional.</i> The default is Single Selection.</p> <p>The Menu Item is always available if you specify No Selection or Any Selection.</p> <ul style="list-style-type: none"> If you specify any of the following, an error message appears when the user launches the action before selecting an appropriate object or objects: <ul style="list-style-type: none"> Any Selection means zero or more selections required. Single Selection means exactly one selection required.

Selection, continued

Attribute	Description
	<ul style="list-style-type: none">■ Multiple Selection means one or more selections required.• If you specify No Selection, the user must launch the action without selecting any objects. An error message appears if any objects are selected.

Only for Multiple Selection or Any Selection

Attribute	Description
Max Selection Count	<i>Only valid if Selection Type = Any Selection or Multiple Selection.</i> Zero means unlimited. Specify the maximum number of objects the user can select before launching this action.
Path View Only	If <input checked="" type="checkbox"/> enabled, your action appears <i>only</i> in the Path View window's menu. See "Attributes per Object Type for Full URLs" on page 1467 for additional information about Path View Full URL configuration choices. If <input type="checkbox"/> disabled, your action can appear in the menu of multiple views.


Description

Attribute	Description
Description	<i>Optional.</i> Provide a description of your action. Your description is visible only within this configuration form. Type a maximum of 1024 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.


Configure Menu Item Context Basic Details

NNMi enables you to configure NNMi console menu items using the Menu Item Context form.




To make changes or additions to the items available in the NNMi console menus:

1. [Navigate to the Menu Item Contexts form.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To create a new menu item, click the  New icon, and continue.
 - To edit an existing menu item, select a row, double-click the row representing the




configuration you want to edit, and continue.

- To delete a menu item, select a row, and click the  Delete icon.
- e. Provide the Basics for this action (see ["Configure Menu Item Basic Details" on page 1456](#)).

Caution: If the **Author** value is **HP Network Node Manager**, any changes are at risk of being overwritten in the future. See [Author form](#) for important information.

- f. Navigate to the **Menu Item Contexts** tab.
- g. Do one of the following:
 - To create a new Menu Item Context configuration, click the  New icon, and continue.
 - To edit an existing Menu Item Context configuration, double-click the row representing the configuration you want to edit, and continue.
 - To delete a Menu Item Context configuration, select a row, and click the  Delete icon.
- 2. Provide the Basic details for this Menu Item Context configuration. (see the [Basics](#) table).
- 3. *Optional.* Limit the use of the menu item to a subset of the chosen object-type instances by defining filter criteria (see ["Specify Optional Menu Item Enablement Filters" on page 1484](#)).
- 4. Click  **Save and Close** to save and apply your changes.
- 5. To test your changes to the menu you configured:
 - a. If required, access a view or form that contains the appropriate object type.
 - b. If required, select an object instance.
 - c. Click the menu you configured.
 - d. Verify your changes are working.

Basics

Attribute	Description
Menu Item Action	<p>Click the  ▼ Lookup icon next to the Menu Item Action attribute and select one of the following:</p> <ul style="list-style-type: none"> • Select  Open to view the current configuration. • Select  New Launch Action to create an Launch Action menu item (access in-house tools, Web sites, or a variety of other resources). See "Configure Launch

Basics , continued

Attribute	Description
	<p>Actions" on page 1462 for more information.</p> <ul style="list-style-type: none"> Select * New SNMP Line Graph Action to create a Line Graph. See "Configure SNMP Line Graph Actions" on page 1477 for more information.
Object Type	<p><i>Optional.</i> If you select All Object Types, yourLaunch Action or Graph Action is visible within the NNMi console menu in all views and forms. If you want your menu item to be available only within a view or form of a particular object type, select the desired Object Type from the drop-down menu.</p> <p>You can further limit the Action to a subset of object instances:</p>
Required NNMi Role ¹	<p>Specify the lowest NNMi Role allowed to access this action. From highest to lowest as follows:</p> <ul style="list-style-type: none"> Administrator Operator Level 2 Operator Level 1 Guest Web Service Client (<i>Only for software integrations with NNMi.</i> See "Integrations with HP and Third-Party Products" on page 1519.) <p>All User Groups associated with an NNMi Role that is a higher level than the NNMi Role you select can also access this action (see "Determine which NNMi User Group to Assign" on page 619).</p> <p>To determine the NNMi Role assigned to each User Group, in the Configuration workspace, expand the Security folder and select User Groups. For each User Group <i>provided by NNMi</i>, the Description attribute includes the NNMi Role associated with the User Group. (This setting cannot be modified in User Groups provided by NNMi.)</p> <div> <p>Caution: Each Tools and Action menu item provided by NNMi is associated with a <i>default NNMi Role</i>. (To determine the <i>default NNMi Role</i> assigned to each Action menu item, see "Actions Provided by NNMi" on page 41.) If you change the setting for a Menu Item provided by NNMi to a Role that is a <i>lower level Role</i> than the <i>default NNMi Role</i> assigned to the menu item, NNMi ignores that change. Any User Group with the lower level Role than the <i>default NNMi Role</i> cannot access the menu item.</p> </div>



¹Determined by your membership in one of four special NNMi User Groups (NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators, or NNMi Guest Users). This membership determines what you can see and do within the NNMi console.

Configure Launch Actions





The **Launch Actions** option enables you to configure Menu Items that will appear beneath the NNMi Actions ► menu structure. These additional menu items can access in-house tools, websites, or a variety of other resources.



To configure Launch Actions that users will access beneath the Actions menu:

Note: You can configure a Launch Actions only for the **Actions** Parent Menu.

1. [Navigate to the Menu Item Contexts form.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To edit an existing Launch Action menu item, double-click the row representing the configuration you want to edit, and continue.
 - To create a new Launch Action menu item, click the  New icon, and continue.
 - To delete an Launch Action menu item, select a row, and click the  Delete icon.
 - e. Provide the Basic details for this Menu Item (see ["Configure Menu Item Basic Details" on page 1456](#)).

Caution: If the Author attribute value is **HP Network Node Manager**, any changes are at risk of being overwritten in the future. See [Author form](#) for important information.

- f. Navigate to the **Menu Item Contexts** tab.
 - g. Do one of the following:
 - To edit an existing Menu Item Context, double-click the row representing the configuration you want to edit, and continue.
 - To create a new Menu Item Context, click the  New icon, and continue.
 - To delete a Menu Item Context, select a row, and click the  Delete icon.
2. Locate the **Menu Item Action** attribute. Click the  Lookup icon, and click the  **New Launch Action** icon.

3. In the **Full URL** attribute, type the URL and any required additional configuration syntax rules (see [Launch Action Basics](#)).
4. Click  **Save and Close** to apply your changes and return to the Menu Item Context form.
5. Limit the use of the Action menu item to a subset of the chosen object-type instances by defining filter criteria (see ["Specify Optional Menu Item Enablement Filters" on page 1484](#)).
6. Click  **Save and Close** to save and apply your changes.
7. To test your changes to the NNMi console menu:
 - a. If required, access a view or form that contains the appropriate object type.
 - b. If required, select an object instance.
 - c. Click the menu you configured.
 - d. Verify your changes are working.

Troubleshooting Tip: If a specified attribute does not exist (for example, you made a mistake when typing the attribute's name), the attribute passes through literally (unresolved). [For example:](#)

A node named "mynode" is selected, and the URL is:

```
http://example.com?name=${name}&error=${error}
```

The output would be:

```
http://example.com?name=mynode&error=${error}
```

Launch Actions Basics

Attribute	Description
Name	Type a meaningful and descriptive name to help you remember the type of action.
Full URL	<p>Add one or more definitions for the actual URL syntax.</p> <p>Type the full URL specification. The URL must comply with "W3C Rules for URLs" on page 1466. Include any required machine name and port number. Include any required parameters.</p> <ul style="list-style-type: none"> You can begin with either <code>http://</code> or <code>https://</code> <p>For an example, click here:</p> <p>To execute a Launch Action requesting something from NNMi:</p> <pre>http://< serverName</pre>

Launch Actions Basics, continued

Attribute	Description
	<p data-bbox="418 363 1255 426">>:<portNumber>/nnm/launch?cmd=showMenuItem&key=<MenuItemKey> [&nodename=<hostname or IP_address></p> <div data-bbox="435 468 1367 615" style="background-color: #f0f0f0; padding: 10px;"> <p data-bbox="435 468 1367 615">Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> </div> <p data-bbox="418 657 1383 751"><serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the <i>Enable URL Redirect</i> setting in User Interface Configuration, see "Configuring the NNMi User Interface" on page 524)</p> <p data-bbox="418 783 941 814"><portNumber> = the NNMi HTTP port number</p> <p data-bbox="418 846 1383 982">For a quick-reference list of all URL choices for launching NNMi, see Help → Documentation Library → Integrate NNMi Elsewhere with URLs. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.</p> <p data-bbox="418 1014 1383 1077">To execute a Launch Action requesting a script, application, or tool from your environment (not NNMi):</p> <p data-bbox="418 1108 1383 1245">http://<serverName>:<portNumber>/<application>?<yourURLparameter1>=\${<attribute>}&<yourURLparameter2>=\${<attribute>}</p> <div data-bbox="435 1266 1367 1476" style="background-color: #f0f0f0; padding: 10px;"> <p data-bbox="435 1287 1367 1455">Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the <i>HP Network Node Manager Developer Toolkit</i> for more information.</p> </div> <p data-bbox="418 1507 1101 1539"><serverName> = the appropriate fully-qualified domain name</p> <p data-bbox="418 1570 925 1602"><portNumber> = the appropriate port number</p> <ul data-bbox="386 1696 1383 1864" style="list-style-type: none"> <li data-bbox="386 1696 1383 1770">• You can also use other common URL protocols such as ftp://, mailto://, news://, or telnet://. <li data-bbox="386 1791 1383 1864">• The list of available parameters changes depending on which limiting factors you configure. The & is used as the separator between the <yourURLparameter> and

Launch Actions Basics, continued

Attribute	Description
	<p><code>\${<attribute>}</code> pairs.</p> <p>For an example, click here:</p> <pre>http://example.com/nodeReport.jsp?myNode=\${hostname} &mySnmpOid=\${systemObjectId}</pre> <p>If the application that your URL calls is installed on the NNMi management server, the syntax can be as follows:</p> <pre>/<application>?<yourURLparameter1>=\${<Attribute>} &<yourURLparameter2>=\${<Attribute>}</pre> <ul style="list-style-type: none"> ■ "Attributes per Object Type for Full URLs" on page 1467 (Limits the availability of the Action to a subset of one object type.) ■ "Database Object Identifiers for Full URLs" on page 1475 (Limits the availability of the Action to <i>one specific instance</i> of an object.) ■ "Capability Attributes in Full URLs" on page 1470 (Limits the availability of the Action to a subset of objects.) ■ "Custom Attributes in Full URLs" on page 1472 (Limits the availability of the Action to a subset of objects.) ■ "Custom Incident Attributes (CIAs) in Full URLs" on page 1473 (Limits the availability of the Action to a subset of Incidents.) <p>See "Attributes per Object Type for Full URLs" on page 1467 for more information about the valid attributes per Object Type.</p>
Enable Cumulative Launch	<p>If <input checked="" type="checkbox"/> enabled, any object attribute references in the Full URL are populated with values from all selected objects. The multiple values are separated by a comma character. For example, if the attribute is "name", the URL results would be "name1,name2,name3".</p> <p>If <input type="checkbox"/> disabled, the action launches a separate web page instance for each selected object.</p> <p>See "Attributes per Object Type for Full URLs" on page 1467 for details about including object attributes in your Full URL.</p>
Browser Width	<p><i>Optional.</i> When empty, the default browser settings are used. If the value is 1 or more, the browser is launched this number of pixels wide.</p>
Browser Height	<p><i>Optional.</i> When empty, the default browser settings are used. If the value is 1 or more, the browser is launched this number of pixels high.</p>

Launch Actions Basics, continued

Attribute	Description
Add Browser Decorations	<p>If <input checked="" type="checkbox"/> enabled, the web browser toolbar and menus appear when a user launches your URL.</p> <p>If <input type="checkbox"/> disabled, the web browser has no toolbar or menu when a user launches your URL.</p>

W3C Rules for URLs

The World Wide Web Consortium (W3C) allows only ASCII characters in URLs.

When configuring URLs, the following characters are always allowed:

- Alpha-numeric (A-Z a-z 0-9)
- - (hyphen)
- . (period)
- _ (underline)
- ~ (tilde)

Depending on the browser and the context, some characters require special formatting with Percent Encoding. A small number of possible values are shown in the quick reference table below.

You can designate the space character several ways:

- + (works in all browsers, recommended because it is easiest to read)
- %20 (Percent Encoded value, works in all browsers)
- space character (works in the browsers supported by NNMi, but is not guaranteed to work in all browsers)

RFC 3986 Characters Reserved as Delimiters

(If not specifying a delimiter, use Percent-Encoding value)

Character	:	/	?	#	[]	@	!	\$
Percent Encoded	%3A	%2F	%3F	%23	%5B	%5D	%40	%21	%24
Character	&	'	()	*	+	,	;	=
Percent Encoded	%26	%27	%28	%29	%2A	%2B	%2C	%3B	%3D

Additional Commonly Used Characters and Their Percent Encoding

Character	space	%	<	>
Percent Encoded	%20 (or + allowed)	%25	%3C	%3E

Attributes per Object Type for Full URLs

There are a variety of methods to limit Launch Actions:

`${<attribute>}` values can be included in the Full URL syntax for each Object Type. For example:

- To limit the use of an Action available only from an Interface form, include `${ifAlias}` as an `${<attribute>}` value.
- To limit the use of an Action available only from a Node form, specify hostname:
`http://${hostname}:<portNumber>/<application>?attributeName1=${sysContact}&attributeName2=${sysName}`

For information about the complete Full URL syntax, see ["Configure Launch Actions" on page 1462](#).

The following list includes the possible `${<attributes>}` that can be included in the Full URL for each Object Type:

Interface [\[parameter list for interface\]](#)

Note: You cannot use the `${hostedOn.hostname}` and `${customAttributes [name=<yourAttrName>].value}` in the same Full URL.

`${capabilities[capability.key=<UniqueKey>].capability.key}` <value of one specific Capability, see ["Capability Attributes in Full URLs" on page 1470](#) for more information>

`${customAttributes[name=<yourAttrName>].value}` <value of the matching Custom Attribute, see ["Custom Attributes in Full URLs" on page 1472](#) for more information>

`${ifAlias}` <value from the ifAlias attribute>

`${ifDescr}` <value from the ifDescription attribute>

`${ifIndex}` <value from the ifIndex attribute>

`${ifName}` <value from the ifName attribute>

`${ifType.label}` <value from the ifType attribute>

`${journal.notes}` <value from the Notes attribute>

`${managementMode}` <value from the Management Mode attribute>

`${name}` <value from the Name attribute>

`${overallStatus.lastChange}` <value from the Status Last Modified attribute>

`${overallStatus.status}` <value from the Status attribute>

`${physicalAddress}` <value from the Physical Address attribute>

`${speed}` <value from the ifSpeed attribute>

Access any attribute on the related Node form, for example:

`${hostedOn.hostname}` <value from the Hosted On attribute, source Node's Hostname attribute>

`${hostedOn.name}` <value from the source Node's Name attribute>

Access an attribute on the related Node's Device Profile form:

`${deviceProfile.devCategoryInterface}<value from the Category attribute's Label value>`
`${deviceProfile.devFamilyInterface}<value from the Family attribute's Label value>`
`${deviceProfile.devVendorInterface}<value from the Vendor attribute's Label>`

Access an attribute on the related SNMP Agent form:

`${hostedOn.snmpAgent.id}` <value from the source Node's SNMP Agent Id attribute>
`${hostedOn.snmpAgent.agentSettings.agentEnabled}` <value from the source Node's SNMP Agent Enabled attribute>

Interface Group [\[parameter list for interfaceGroup\]](#)

`${name}` <value from the Name attribute>
`${notes}` <value from the Notes attribute>
`${nodeGroup.name}` <value from the Node Group attribute>

Node [\[parameter list for node\]](#)

`${capabilities[capability.key=<UniqueKey>].capability.key}` <value of one specific Capability, see "Capability Attributes in Full URLs" on page 1470 for more information>
`${customAttributes[name=<yourAttrName>].value}` <value of the matching Custom Attribute, see "Custom Attributes in Full URLs" on page 1472 for more information>
`${hostname}` <value from the Hostname attribute>
`${journal.notes}` <value from the Notes attribute>
`${managementMode}` <value from the Management Mode attribute>
`${name}` <value from the Name attribute>
`${overallStatus.lastChange}` <value from the Status Last Modified attribute>
`${overallStatus.status}` <value from the Status attribute>
`${systemContact}` <value from the System Contact attribute>
`${systemDescription}` <value from the System Description attribute>
`${systemLocation}` <value from the System Location attribute, the current value of the sysLocation MIB variable>
`${systemName}` <value from the System Name attribute>
`${systemObjectId}` <value from the System Object ID attribute>

Access an attribute on the related Device Profile form:

`${deviceProfile.deviceModel}` <value from the Device Model attribute>
`${deviceProfile.SNMPObjectID}` <value from the SNMP Object ID attribute>
`${deviceProfile.devCategoryNode}` <value from the Category attribute's Label value>
`${deviceProfile.devFamilyNode}` <value from the Family attribute's Label value>
`${deviceProfile.devVendorNode}` <value from the Vendor attribute's Label value>

Access an attribute on the related SNMP Agent form:

`${snmpAgent.id}` <value from the Id attribute>
`${snmpAgent.agentSettings.managementAddress}` <value from the Management Address attribute>
`${snmpAgent.agentSettings.agentEnabled}` <value from the Agent Enabled attribute>

Access an attribute on the related Security Group form:

`${securityGroup.name}` <value from the Name attribute>
`${securityGroup.uuid}` <value from the UUID attribute>

Access an attribute on the related Tenant form:

`${tenant.name}` <value from the Name attribute>
`${tenant.uuid}` <value from the UUID attribute>

Node Group [\[parameter list for nodeGroup\]](#)

`${name}` <value from the Name attribute>
`${notes}` <value from the Notes attribute>
`${overallStatus.lastChange}` <value from the Status Last Modified attribute>
`${overallStatus.status}` <value from the Status attribute>

Incident [\[parameter list for incident\]](#)

`${category.label}` <value from the Category attribute>
`${cias[name=<cia.name>].value}` <value of one specific Custom Incident Attribute, see "Custom Incident Attributes (CIAs) in Full URLs" on page 1473 for more information>
`${duplicateCount}` <value from the Duplicate Count attribute>
`${family.label}` <value from the Family attribute>
`${formattedMessage}` <value from the Message attribute>
`${getAttrOrName(<attribute>)}` <value of the specified attribute of the Node associated with the Incident (if the Node exists in the database) or the *sourceNodeName* attribute of the Incident (if the Node was deleted from the database or never existed in the database). For example, `${getAttrOrName(hostname)}`>
`${journal.notes}` <value from the Notes attribute>
`${lifecycleState.label}` <value from the Lifecycle State attribute>
`${nature}` <value from the Correlation Nature attribute>
`${nodeUuid}` <value of the uuid for the Source Node, see "Database Object Identifiers for Full URLs" on page 1475>
`${nodeUuid.id}` <value of the id for the Source Node, see "Database Object Identifiers for Full URLs" on page 1475>
`${notes}` <value from the Correlation Notes attribute>
`${origin}` <value from the Origin attribute>
`${priority.label}` <value from the Priority attribute>
`${registration.created}` <value from Created attribute>
`${registration.modified}` <value from the Last Modified attribute>
`${severity}` <value from the Severity attribute>
`${sourceName}` <value from Name attribute of the source object>
`${sourceNodeName}` <value from the Name attribute of the source object>
`${sourceUuid}` <value of the uuid for the Source Object, see "Database Object Identifiers for Full URLs" on page 1475>
`${sourceUuid.id}` <value of the source object's id attribute>
Access an attribute on the related source object form:
`${sourceUuid.name}` <value of the source object's Name attribute>
Access an attribute on the related Node form:
`${nodeUuid.hostname}` <<value from the source Node's Hostname attribute or IP address if no hostname is available>
`${nodeUuid.name}` <value of the Name attribute of the Source Node>

Layer 2 Connection [\[parameter list for layer2Connection\]](#)

`${journal.notes}` <value from the Notes attribute>
`${name}` <value from the Name attribute of the connection>
`${source}` <value of the Topology Source attribute, the protocol used to create the connection>

IP Address [\[parameter list for address\]](#)

`${capabilities[capability.key=<UniqueKey>].capability.key}` <value of one specific Capability, see

"Capability Attributes in Full URLs" below for more information>

`$(journal.notes)` <value from the Notes attribute>
`$(managementMode)` <value from the Direct Management Mode attribute>
`$(name)` <value from the Name attribute>
`$(overallStatus.lastChange)` <value from the Status Last Modified attribute>
`$(overallStatus.status)` <value from the Status attribute>
`$(prefixLength)` <value from the Prefix Length attribute>
`$(value)` <value from the Address attribute>

IPSubnet [parameter list for subnet]

`$(journal.notes)` <value from the Notes attribute>
`$(name)` <value from the Name attribute>
`$(prefix)` <value from the Prefix attribute>
`$(prefixLength)` <value from the Prefix Length attribute>

Physical Component[parameter list for chassis or card]

`$(capabilities[CAPABILITY_NAME])` <value of one specific Capability, see "Capability Attributes in Full URLs" below for more information>
`$(capabilities[capability.key=<UniqueKey>].capability.key)` <value of one specific Capability, see "Capability Attributes in Full URLs" below for more information>
`$(firmwareVersion)` <value from the Firmware Version attribute>
`$(hardwareVersion)` <value from the Hardware Version attribute>
`$(index)` <value from the Index attribute>
`$(journal.notes)` <value from the Notes attribute>
`$(managementMode)` <value from the Management Mode attribute>
`$(modelName)` <value from the Model Name attribute>
`$(modelType)` <value from the Model Type attribute>
`$(monitoredAttributes.operationalState)` <value from the Operational State attribute>
`$(overallStatus.status)` <value from the Status attribute>
`$(overallStatus.lastChange)` <value from the Status Last Modified attribute>
`$(parents.name)` <value from the Parent Component attribute>
`$(physicalIndex)` <value from the Physical Index attribute>
`$(redundancyGroups.name)` <value from the Redundancy Group attribute>
`$(serialNumber)` `$(softwareVersion)` <value from the Serial Number attribute>
`$(type)` <value from the Type attribute>

Port [parameter list for port]


`$(associatedInterface.name)` <value from the Associated Interface attribute>
`$(configuredDuplexSetting)` <value from the Configured Duplex Setting attribute>
`$(index)` <value from the Index attribute>
`$(journal.notes)` <value from the Notes attribute>
`$(speed)` <value from the Speed attribute>
`$(type)` <value from the Type attribute>


Capability Attributes in Full URLs

There are a variety of methods to limit Launch Actions:

NNMi node, interface, IP address, and card objects can have capability attributes:

Capabilities can be provided from HP Network Node Manager i Software Smart Plug-ins (iSPIs) or from integrations with other programs. See the documentation that came with any NNM iSPIs installed in your network environment.

To determine which group of capabilities are available for a specific object, navigate to a view for the object, select an instance of the object. Click the  Open icon and navigate to the Capabilities tab. The items listed in the table are the Capabilities for that particular object instance. For example, the following illustration shows a Node form with three capability entries.



To pass Capability data within the Full URL, type (or copy and paste) the exact text string *from the object form, Capability tab, Unique Key attribute value*:

`${capabilities[capability.key=<UniqueKeyValue>].capability.key}`

Place the Capability into a location in the Full URL that enables the result you want:

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

```
http://<serverName>:<portNumber>/<application>?<yourURLparameter1>=
${capabilities[capability.key= <UniqueKey_1>].capability.key}
&<yourURLparameter2>= ${capabilities[capability.key= <UniqueKey_
2>].capability.key}
```

Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number


Note: If the Capability that you request in the Full URL does not exist for the selected Node or Interface, the resulting URL passes an empty string.


Custom Attributes in Full URLs

There are a variety of methods to limit Launch Actions:

Custom Attributes enable an NNMi administrator to add information to the Node object or Interface object. Custom Attributes can also be set by external applications that have been integrated with NNMi.

The [Node form: Custom Attributes tab](#) and [Incident form: Custom Attributes tab](#) display a table view of any Custom Attributes that have been added to the selected object. See ["Add a Custom Attribute to One Object" on page 543](#).

To determine which group of Custom Attributes are available for a specific Node or Interface, navigate to a Node view or Interface view, select an instance of the object, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the Custom Attributes for that particular node or interface. For example, the following illustration shows a Node form with two Custom Attribute entries.



To pass Custom Attribute data within the Full URL, type (or copy and paste) the exact text string *from the Node or Interface form, Custom Attributes tab*:

```
${customAttributes[name=<yourAttrName>].value}
```

Place the Custom Attribute into a location in the Full URL that enables the result you want:

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/<application>?<yourURLparameter1>=
${customAttributes[value= <yourAttrValue>].name}&<yourURLparameter2>=
${customAttributes[name= <yourAttrName>].value}
```

Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number

- Example 1:

```
mailto:${customAttributes[name=Admin].value}?subject=URGENT Action
Required&body=${customAttributes[name=message].value}&${hostname} router needs
attention.
```

Resulting URL:

```
mailto:JohnDoe@myCompany.com?subject=URGENT Action Required&body=Building-
5:Floor-23.&cisco4.myCo.com router needs attention.
```

- Example 2:

```
http://myCo.com/emailAdmin.jsp?name= ${hostname}&contact= ${customAttributes
[name= Admin].value}&body= ${customAttributes[name=message].value}
```

Resulting URL:

```
http://myCo.com/emailAdmin.jsp?name= cisco4.myCo.com&contact=
johnDoe@myCo.com&body= Building-5:Floor-23
```


Note: If the Custom Attribute that you request in the Full URL does not exist for the selected Node or Interface, the resulting URL passes an empty string.


Custom Incident Attributes (CIAs) in Full URLs

There are a variety of methods to limit Launch Actions:

Custom Incident Attributes (CIAs) are used to provide the following types of information within incidents:

- SNMP trap varbinds identified by the Abstract Syntax Notation value, ASN.1 (Name = the MIB varbind identifier, Type = asn_*)
- Custom attributes provided by NNMi (Name = cia.*, Type=String). See ["Custom Incident Attributes Provided by NNMi \(Information for Administrators\)"](#) on page 733.

To determine which group of CIAs is available for a specific incident-type (for example, CiscoLinkDown), navigate to an Incident view, select an instance of that incident-type, click the  Open icon and navigate to the Custom Attributes tab. The items listed in the table are the CIAs for that particular incident-type. For example, all CiscoLinkDown incidents would have the same group of CIAs shown in the illustration below.



Open Root Cause Incidents Incident **InterfaceDown**

Save and Close Delete Incident

Basics

Message

Interface Down

Severity Critical

Priority None

Lifecycle State Registered

Source Node CH-KV1

Source Object Se0/0/2

Assigned To

Correlated Children Custom Attributes Diagnostics Re

General Correlated Parents Correlated Children Custom Attributes Diagnostics Registration

1 - 2 of 2

Name	Type	Value
com.hp.ov.nms.apa.symptom	String	IfOperStatusDown
com.hp.ov.nms.apa.symptom_1	String	InterfaceAdminUpC

Updated: 3/29/12 04:56:24 PM Total: 2 Selected: 0 Filter: OFF

Analysis - Incident Summary : InterfaceDown - Message: Interface Down Severity: Critical Lifecycle State: R

To pass CIA data within the Full URL, type (or copy and paste) the exact text string *from the Incident form, Custom Attribute tab, Name attribute value*:

`${cias[name=<cia_name>].value}`

Place the CIA into a location in the Full URL that enables the result you want:

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

```
http://<serverName>:<portNumber>/ <application>?<yourURLparameter1>= ${cias  
[name=<cia_name_1>].value}&<yourURLparameter2>= ${cias[name=<cia_name_2>].value}
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number

Note: If the CIA that you request in the Full URL does not exist for the selected Incident, the resulting URL passes an empty string.

Database Object Identifiers for Full URLs

There are a variety of methods to limit Launch Actions:

If you need the Full URL to identify one specific record in the NNMi database, and find that it is not possible to provide a unique set of attribute values that distinguish that object instance from all other similar object instances, the *database unique identifiers* are valuable parameters.

The ID and UUID attributes are valid for all object types. NNMi displays the ID and UUID attribute values on the object form's Registration tab:

- \${uuid} Universally Unique Object Identifier -Unique across all databases.
- \${id} Unique Object Identifier - Unique across the Entire NNMi Database.

For example, the user can select an Interface object in the console, and use this Action to open the form of the Node in which the Interface resides:

```
/nnm/launch?cmd=showForm&objtype=Node&objid=${hostedOn.id}
```

Path View Attributes for Full URLs

There are a variety of methods to limit Launch Actions:


If you specified that a Launch Action appears only in the Path View menu, additional parameters are available:


[\\${pathStartNodeName}](#) <value of the Source attribute>
[\\${pathEndNodeName}](#) <value of the Destination attribute>

`${pathList}` <list of objects traversed along the path, separated by commas>
`${pathCalculationDate}` <date and time the path was calculated>


MIB Expressions in Full URLs

MIB Expressions enable an NNMi administrator to add SNMP MIB Expression information to a Graph.


To determine the MIB Expressions available, navigate to the **MIB Expressions** option in the  **Configuration** workspace. The items listed in the table are the MIB Expressions that have been created as shown in the following example:



Name	Conversion Algorithm	Author	Description
If%outErrors	Interface Name	HP Network Node	Percent of output
If%util	Interface Name	HP Network Node	Percent of availab
IfHC%inErrors	Interface Name	HP Network Node	Percent of input p
IfHC%outErrors	Interface Name	HP Network Node	Percent of output
IfHC%util	Interface Name	HP Network Node	Percent of availab
IfHCInOutOctets	Interface Name	HP Network Node	Total octets (byte

When using MIB Expressions in Graphs, provide the Unique Key value for the MIB Expression you want to use. To determine the Unique Key value, select the row containing the MIB Expression of interest, and click the  Open icon. Look for the Unique Key value.

The following illustration shows the Basics section of a MIB Expression form with a Unique Key value provided by NNMi.



MIB Expressions **MIB Expression ***

Save and Close Delete MIB Expression


▼ Basics

When modifying an existing MIB Expression, all Custom Poller Policies associated with variables that use this MIB Expression will be suspended when the modifications are saved.

To test your MIB Expression definition, select File → Save, then Actions → Graph MIB Expression. You will be asked to select a Node.

* Unique Key:

* Name:

* Author: 

To pass MIB Expression data within your Full URL, type (or copy and paste) the exact text string *from the Unique Key attribute* into the `expr=` parameter.

Place the `expr=[value]` into a location in your URL that enables the result you want as shown in the following example.

The following example displays a Line Graph of the percentage of input packets with errors for a selected interface.

Note: The Unique Key value appears in bold. Replace space characters with "+" or %20 (see ["W3C Rules for URLs" on page 1466](#)).

```
http://<serverName>:<portNumber>/nnm/  
launch?cmd=showLineGraph&init=ifindex=${ifIndex};expr=com.mycompany.ifInerrors;/  
label=Input+Errors;&title=Graph+SNMP+Interface+Input+Errors/  
&objtype=SnmpAgent&objidlist=${hostedOn.snmpAgent.id}
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

See ["Attributes per Object Type for Full URLs" on page 1467](#) for more information.



Configure SNMP Line Graph Actions

The **User Interface Configuration** option enables you to configure Line Graphs that are available from the NNMi Actions ► menu structure. These graphs display real-time SNMP data for a selected node or interface. This feature is useful when you want to monitor a numeric MIB or MIB Expression value for a node or interface over a specified time interval. For example, you might want to monitor network traffic using the `ifOutOctets` MIB variable for a specified node. Or you might want to graph a MIB variable, such as `Interface ifInOctets`, to verify that a problem has been fixed for a specified interface before closing an incident.




Note: The node for which you want to display information must support SNMPv1, SNMPv2c, or SNMPv3.

NNMi provides a set of Line Graphs for nodes and for interfaces. See [Line Graphs Provided by NNMi](#) for more information.


To configure additional Line Graphs:

1. [Navigate to the Menu Items form.](#)
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To create a Graph Action, click the  New icon, and continue.
 - To edit an existing Graph Action, double-click the row representing the configuration you want to edit, and continue.
 - To delete a Graph Action, select a row, and click the  Delete icon.
 - e. Provide the Basic details for this menu item (see ["Configure Menu Item Basic Details" on page 1456](#)).

Caution: If the **Author** value is **HP Network Node Manager**, any changes are at risk of being overwritten in the future. See [Author form](#) for important information.

2. Select **Menu Item Contexts**.
3. Do one of the following:
 - a. To create a Menu Item Context, click the  New icon, and continue.
 - b. To edit an existing Menu Item Context, double-click the row representing the configuration you want to edit, and continue.
 - c. To delete a Menu Item Context, select a row, and click the  Delete icon.
4. Provide the graph details for this Graph (see [Basics](#) table).
5. Provide the MIB Specification information (see ["MIB Specification Form" on page 1480](#)).
6. Click  **Save and Close** to save and apply your changes and return to the Menu Item Context form.
7. Limit the use of the Action menu item:
 - By object type (see ["Configure Menu Item Basic Details" on page 1456](#)).
 - By NNMi user role (see ["Configure Menu Item Basic Details" on page 1456](#)).

- By defining a filter for a subset of the chosen object-type instances (see ["Specify Optional Menu Item Enablement Filters" on page 1484](#)).

8. Click  **Save and Close** to save and apply your changes.

To test your changes to the Actions menu:

- If required, access a view or form that contains the appropriate object type.
- If required, select an object instance.
- Click the **Actions** menu.
- Verify your Graph is working.

Basics

Attribute	Description
Graph Title	Type a meaningful and descriptive title to display above the graph. The maximum length is 255 characters. Alpha-numeric characters, spaces, and periods are permitted.
Y-axis Label	Enter the text string to describe the Y-axis data displayed. NNMi displays this label vertically along the left-side of the Y axis. The maximum length is 255 characters. Alpha-numeric characters, spaces, and periods are permitted. If you do not want to display a label for the Y-axis, leave this attribute blank.
Number of Lines	Specify the number of lines that will be initially displayed on the graph. An operator can display additional lines when viewing the Line Graph. To use the Default value specified in the User Interface Configuration, leave this attribute value blank. The default value that NNMi provides is 20.
Maximum Time Range (Hours)	The maximum time period in hours in which to retain the Line Graph data point sets. When the Maximum Time Range number is reached, NNMi discards the oldest data point sets so that it can display the most recent data for the time range you specify. For example, if you enter 24 hours, when 24 hours has passed, NNMi removes data starting with the initial data point set so that it can display data for the most recent 24-hour interval. Enter a decimal number indicating the maximum number of hours in which to retain the Line Graph data. If you specify 0 (zero), NNMi determines the best setting for the Maximum Time Range based on the Poling Interval specified.
Update	The Update Interval in seconds to be used for collecting data to be displayed

Basics, continued







Attribute	Description
Interval (Seconds)	<p>on the graph.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: You can change the Update Interval for the current session when NNMi displays the graph.</p> </div> <p>To use the Default value specified in the User Interface Configuration, leave this attribute value blank.</p>
Fast Start	Select Fast Start when you want to increase the initial Polling Interval so that the initial data appears more quickly on the graph. When you select this option, NNMi increases the initial Polling Interval and then gradually decreases the Polling Interval until it reaches the Polling Interval configured for the graph.
Enable Cumulative Launch	<p>If <input checked="" type="checkbox"/> enabled, any object attribute references in the Full URL are populated with values from all selected objects. The multiple values are separated by a comma character. For example, if the attribute is "name", the URL results would be "name1,name2,name3".</p> <p>If <input type="checkbox"/> disabled, the action launches a separate web page instance for each selected object.</p> <p>See "Attributes per Object Type for Full URLs" on page 1467 for details about including object attributes in your Full URL.</p>
Browser Width	<i>Optional.</i> When empty, the default browser settings are used. If the value is 1 or more, the browser is launched with this number of pixels wide.
Browser Height	<i>Optional.</i> When empty, the default browser settings are used. If the value is 1 or more, the browser is launched with this number of pixels high.
Add Browser Decorations	<p>If <input checked="" type="checkbox"/> enabled, the web browser toolbar and menus appear when a user launches your URL.</p> <p>If <input type="checkbox"/> disabled, the web browser has no toolbar or menu when a user launches your URL.</p>

MIB Specification Form

The MIB Specification form enables you to indicate the following:

- The label to be displayed for each line that appears in the Line Graph Legend.
- The MIB Expression NNMi uses to gather the data shown in the graph.





To specify the Line Label and MIB Expression for an SNMP Line Graph Action:

1. Navigate to the **MIB Specification** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**.
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To create a new menu, click the  New icon.
 - To edit a menu, double-click the row representing the configuration you want to edit.
 - e. Navigate to the **Menu Item Contexts** tab.
 - f. Do one of the following:
 - To create a new Context configuration, click the  New icon.
 - To edit an existing Context configuration, double-click the row representing the configuration you want to edit.
 - g. In the **Menu Item Context** form, locate the **Menu Item Action** attribute.
 - h. Click the  Lookup icon next to the **Menu Item Action** attribute, and do one of the following:
 - To create a new Line Graph, click the  **New SNMP Line Graph Action** icon.
 - To edit the Line Graph associated with the Graph Action name displayed, double-click the row representing the configuration you want to edit.
 - i. Provide the Basic details for this Graph Action (see the ["Configure SNMP Line Graph Actions" on page 1477](#)).
 - j. Navigate to the **MIB Specifications** tab.
 - k. Do one of the following:
 - To create a new MIB Specification configuration, click the  New icon.
 - To edit an existing MIB Specification configuration, double-click the row representing the configuration you want to edit.
2. Provide the Basic details for this MIB Specification configuration. (see the [MIB Specification Basics](#) table).
3. Click  **Save and Close** to save and apply your changes.

MIB Specification Basics

Attribute	Description
Line Label	<p>Enter the label that you want to be displayed for each line that appears in the Graph legend.</p> <p>Type a maximum of 40 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.</p> <div data-bbox="440 499 1370 642"> <p>Note: When graphing multiple instances, the <i><instance_string></i> is appended to this value. See "MIB Expression Form (Line Graph)" on page 1500 for more information.</p> </div>
MIB Expression	<p>Use this attribute to specify the MIB information that you want NNMi to poll.</p> <p>A MIB expression must include at least one MIB Variable. It can also include one or more of the following:</p> <ul style="list-style-type: none"> • Constant • Arithmetic operator (+, -, *, /) <p>If the MIB Expression does not include any arithmetic operators, valid types for any MIB Variable in the MIB Expression include the following:</p> <ul style="list-style-type: none"> • Integer • Unsigned Integer • Octet String • Counter • Counter64 • Gauge • Time_Ticks <p>If the MIB Expression contains any constants or arithmetic operators, the MIB Expression must evaluate to a numeric type.</p> <div data-bbox="440 1577 1370 1722"> <p>Note: If the MIB Expression is collecting a single MIB variable of type Time_Ticks, NNMi evaluates the return value as an Integer. Otherwise, it is treated as type Counter.</p> </div> <p>When evaluating MIB expressions that include MIB variables of type Counter, Counter64, or Time_Ticks, NNMi evaluates the MIB Variable using the difference in value between the most recent poll and the poll before it. If you want NNMi to calculate a rate over time in seconds, divide the MIB Expression by sysUptime.</p>

MIB Specification Basics , continued

Attribute	Description
	<p>For example:</p> $(((\text{ifInOctets} + \text{ifOutOctets}) * 8 / \text{ifSpeed}) * 100) / \text{sysUpTime} * 0.01$ <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Tip: The sysUpTime variable is a value of hundredths of a second. When you want the rate in seconds, use sysUpTime*0.01 in the MIB expression as shown in the previous example.</p> </div> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: If you use a MIB variable of type Counter, Counter64, or Time_Ticks in the MIB Expression, NNMi automatically collects sysUpTime values if sysUpTime is not already in the MIB Expression. NNMi uses the sysUptime value to detect a system reboot. Any time a system reboot is detected, NNMi cannot determine the difference in values between polls for any Counter MIB variable and therefore does not calculate the MIB Expression for that poll.</p> </div> <ul style="list-style-type: none"> • If you select a MIB Variable from an Interface Table to include in the MIB Expression, note the following: <ul style="list-style-type: none"> ■ <i>Line Graph Only.</i> When evaluating MIB Expressions that include MIB variables of type Counter or Counter64, NNMi requests both the high capacity and low capacity counter variable for any interface instance. If the high capacity Counter64 is enabled for any given interface instance, NNMi uses the high capacity counter. ■ <i>Custom Poller Only.</i> When evaluating MIB Expressions that include MIB variables of type Counter, NNMi requests only the low capacity counter information for any interface instance. <p>You create a MIB Expression by using the MIB Expression form. To access the MIB Expression form, click the  Lookup icon and do one of the following:</p> <ul style="list-style-type: none"> • Select  Quick Find to select an existing MIB expression. • Select  Open to edit the current MIB expression. • Select  New to create a MIB expression. <p>See "MIB Expression Form (Line Graph)" on page 1500 for information about using the MIB Expression form.</p>
Instance Selection Algorithm	<p>Used to specify how you want NNMi to handle instance discovery for Line Graphs that display multiple instances. Possible values are:</p> <ul style="list-style-type: none"> • All - Use when you want NNMi to graph each instance of the object selected by the user. <p>Note the following:</p>

MIB Specification Basics , continued



Attribute	Description
	<ul style="list-style-type: none"> ■ When a node is selected, NNMI discovers all instances for that node, including the interfaces. When an interface is selected, NNMI graphs all selected interfaces. ■ NNMI ignores any values entered in the Instance List attribute. ■ When the Line Graph menu item is launched, NNMI populates <code>\${snmpAgent.id}</code> and <code>\${hostedOn.snmpAgent.id}</code> with the ID values from the selected objects. The multiple values are separated by a comma character. ■ NNMI displays a maximum of 100 instances. NNMI determines which 100 instances to display using the following calculation: $100 \text{ instances} / (\text{number of nodes selected}) * (\text{number of MIB expressions for the Action})$ ● Instance List - Use when you want to specify the instances to be included in the Line Graph <p>Note: You must specify the Instance List when using this option.</p>
Instance List (Comma Separated)	<p>Used to identify the instances to be graphed for an object.</p> <p>If your Menu Item Context is Node and you want to specify which nodes should be included on this Line Graph, enter the instance number for each of the node instances to be included on this Line Graph. For example, to graph CPU values, enter the instance number representing each CPU on the node, separated by commas.</p> <p>If your Menu Item Context is an Interface, these values are not used and the selected Interface(s)' <code>ifIndex</code> value is used as the SNMP instance.</p>

Specify Optional Menu Item Enablement Filters

If your SNMP Graph Action or Launch Action applies to Nodes, Interfaces, or Incidents, you can use the Filters Editor to create expressions that further define the context in which this Graph Action or Launch Action is available within NNMI. A Menu Enablement Filter limits the use of the Menu Item which uses this context. The Menu Item is disabled unless the selected object passes this filter.

Design complex Filters on paper as a Boolean expression first to minimize errors when entering your expressions using this Filters editor.


To create any Filter expressions:

1. Navigate to the **Menu Item Context** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Click to expand **User Interface**
 - c. Select **Menu Items**.
 - d. Do one of the following:
 - To create a Menu Item definition, click the  New icon.
 - To edit a Menu Item definition, double-click the row representing the configuration you want to edit.
 - e. Navigate to the **Menu Item Contexts** tab.
 - f. Do one of the following:
 - To create a Context configuration, click the  New icon.
 - To edit a Context configuration, double-click the row representing the configuration you want to edit.
2. Navigate to the **Menu Item Enablement Filter** tab.
3. Establish the appropriate settings for the filter you want to create. (See the [Custom Filter Editor Settings](#) table.)

When creating any filters, note the following:

- The Menu Item Enablement filters apply only to Node, Interface, and Incident Object Types. If you select an attribute that is not valid for the Object Type, that part of the filter is not applied.
- Boolean Attributes begin with "is" and must contain the value `true` or `false`.
- Each set of expressions associated with a Boolean Operator is treated as if it were enclosed in parentheses and evaluated together. View the expression displayed under **Filter String** to see the logic of the expression as it is created.
- The AND Boolean Operators must contain at least two expressions.
- The placement of your cursor and the subsequent text that is selected is important when performing operations using the Additional Filters Editor. For example, you append to or replace, the expression that is selected.
- The placement of your cursor and the subsequent text that is selected is especially important when adding your Boolean operators. See ["Add Boolean Operators in the Additional Filters Editor" on page 344](#) for more information.

- You can drag any of the following items to a new location in the Filter String:
 - Filter Editor Options: AND, OR, NOT, EXISTS, NOT EXISTS
 - Filter Expression (Attribute, Operator and Value)
- When moving items in the Filter String, note the following:
 - Click the item you want to move before dragging it to a new location.
 - As you drag a selected item, an underline indicates the target location.
 - If you are moving the selection up, NNMi places the item above the target location.
 - If you are moving the selection down, NNMi places the item below the target location.
 - If you attempt to move the selection to an invalid target location, NNMi displays an error message.

4. Click  **Save and Close** to save and apply your changes.

Custom Filter Editor Settings

Attribute	Description
Attribute	<p>The attribute name NNMi should use as the filter criteria. Possible attributes include the following:</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Boolean Attributes begins with "is" and must contain the value true or false.</p> </div> <p>Interface [click here for a list of attribute values]</p> <p>Unique Keys from the Interface Form: Capabilities Tab:</p> <ul style="list-style-type: none"> • capability (Unique Key of the Capability) <p>Values from the Interface Form: Custom Attributes Tab:</p> <ul style="list-style-type: none"> • customAttrName (Custom Attribute Name) • customAttrValue (Custom Attribute Value) <p>Node [click here for a list of attribute values]</p> <p>Values from the Basics information on the Node Form:</p> <ul style="list-style-type: none"> • isSnmpNode (Agent Enabled) • isSnmpInterface (Agent Enabled)

Custom Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> • isNnmSystemLocal (NNMi Management Server) <p>Values from the Node Form: General Tab:</p> <ul style="list-style-type: none"> • sysOidNode (System Object ID) • sysOidInterface (System Object ID) <p>Unique Keys from the Node Form: Capabilities Tab:</p> <ul style="list-style-type: none"> • capability (Unique Key of the Capability) <p>Values from the Node Form: Custom Attributes Tab:</p> <ul style="list-style-type: none"> • customAttrName (Custom Attribute Name) • customAttrValue (Custom Attribute Value) <p>Values from the Basics information on the Device Profile Form:</p> <ul style="list-style-type: none"> • devVendorNode (Device Vendor) • devFamilyNode (Device Family) • devVendorInterface (Device Vendor) • devFamilyInterface (Device Family) <p>Incident [click here for a list of attribute values]</p> <p>Values from the Incident Form: Custom Attributes Tab:</p> <ul style="list-style-type: none"> • customAttrName (Custom Attribute Name) • customAttrValue (Custom Attribute Value)
Operator	<p>The standard query language (SQL) operations to be used for the search. Valid operators are described below.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: Only the <code>is null</code> Operator returns null values in its search.</p> </div> <ul style="list-style-type: none"> • <code>=</code> Finds all values equal to the value specified. • <code>!=</code> Finds all values not equal to the value specified. • <code><</code> Finds all values less than the value specified. • <code><=</code> Finds all values less than or equal to the value specified.

Custom Filter Editor Settings, continued

Attribute	Description
	<ul style="list-style-type: none"> • > Finds all values greater than the value specified. • >= Finds all values greater than or equal to the value specified. • between Finds all values equal to and between the two values specified. • in Searches for a match in at least one of a series of values. • is not null Searches for all non-blank values. • is null Searches for all blank values. • like Enables you to find matches using the asterisk (*) and question mark (?) as wildcard characters. Question mark character means "any single character of any type at this location". Asterisk character means "any number of characters of any type at this location". • not between Finds all values except those between the two values specified. • not in Finds all values except those included in the list of values. • not like Finds all values except those included in the value specified. The not like operator enables you to use the asterisk (*) and question mark (?) as wildcard characters.
Value	<p>The value for which you want NNMi to search.</p> <p>Note the following:</p> <ul style="list-style-type: none"> • The values you enter are case sensitive. <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: When entering the Boolean values, <code>true</code> or <code>false</code>, use all lowercase.</p> </div> <ul style="list-style-type: none"> • NNMi displays a variable number of value fields depending on the Operator selected. For example, the <code>between</code> Operator causes two value fields to be displayed. • The <code>in</code> and <code>not in</code> operators require that each value be entered on a separate line.

Additional Filters Editor Buttons

Button	Description
Append	Appends the current expression (Attribute, Operator, and Value) to the selected expression already included in the filter string.
Insert	Inserts the current expression (Attribute, Operator, and Value) in front of the cursor

Additional Filters Editor Buttons, continued

Button	Description
	location within the Filter String.
Replace	Replaces the selected expression with the expression displayed in the Attribute, Operator, and Value fields.
AND	<p>Inserts the AND Boolean Operator in the selected cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
OR	<p>Inserts the OR Boolean Operator in the current cursor location.</p> <p>Note: View the expression displayed under Filter String to see the logic of the expression as it is created.</p>
NOT	<p>Can be used in any part of the Filter String to specify that NNMi should exclude nodes with values that pass the expression that immediately follows the NOT.</p> <p>For example, when evaluating the following Filter String, NNMi includes all nodes that have SNMP enabled and excludes any nodes with a Device Profile attribute value that includes Cisco as the Vendor value:</p> <pre>(isSysName = true AND NOT (devVendorNode=Cisco))</pre>
EXISTS	<p>Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider nodes that have Capabilities or Custom Attributes when evaluating the Filter String. For example, when evaluating the following Filter String, NNMi includes all nodes with a Capability having the Unique Value of com.hp.nnm.capability.metric.cse and ImportantRouters value of Building5:</p> <pre>(capability = com.hp.nnm.capability.card.cisco.c2900 AND EXISTS (customAttrName=ImportantRouters AND customAttrValue=Building5))</pre> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p>
NOT EXISTS	Used for filters that include Capabilities or Custom Attribute names and values in the Filter String. Indicates that you want NNMi to consider interfaces that do not have any Capabilities or Custom Attributes when evaluating the Filter String, but exclude the

Additional Filters Editor Buttons, continued

Button	Description
	<p>objects that match the expression that follows the NOT EXISTS.</p> <p>For example, when evaluating the following Filter String, NNMi includes all nodes with a hostname that includes router, followed by any number of characters, followed by hp.com and excludes any nodes with a Custom Attribute named ImportantRouters with the value of Building5:</p> <pre>(hostname like router*.hp.com AND NOT EXISTS (customAttrName=ImportantRouters AND customAttrValue=Building5))</pre> <p>Tip: When creating complex Filter Strings that include <code>customAttrName</code> and <code>customAttrValue</code> pairs as one component of an "or" statement, to prevent NNMi from excluding Nodes that have zero Custom Attributes, use EXISTS or NOT EXISTS criteria for the <code>customAttrName</code> and <code>customAttrValue</code> pair definitions.</p> <p>Otherwise Nodes that do not have any Custom Attributes are automatically excluded even if they have values that pass other aspects of your filter.</p>
Delete	<p>Deletes the selected expression.</p> <p>Note: If the Boolean Operator is selected, the Additional Filters Editor deletes all expressions associated with the Boolean Operator.</p>

Managing MIBs

NNMi uses [MIB file](#)¹ information to assist in monitoring the health of your network objects. NNMi also enables you to use MIB Expressions to specify additional information that NNMi should poll.

Tip: NNMi enables you to access the same MIB information in multiple ways. See the help topic for each of the following tasks to determine the options that best meet your needs.

To manage the currently available MIB Files for use within NNMi, perform any of the following tasks:

- ["Upload MIB Files for NNMi's Use" on the next page](#)
- ["Load MIBs" on page 1492](#)
- ["Unload MIBs" on page 1496](#)

¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

- ["Available MIBs Files and MIB Variables" on page 1498](#)
 - ["Loaded MIBs View" on page 1499](#)
 - [MIB Variables view](#)
- ["Configure MIB Expressions" on page 1500](#)
- ["Override MIB OID Types" on page 1512](#)



Tip: To determine a particular Node's MIB Variable Values, see:

- [Determine which MIBs a Specific Node Supports](#)
- [Run SNMP Walk Commands \(MIB Browser\)](#)

Upload MIB Files for NNMi's Use

To get a copy of a MIB file for NNMi's use, use the **Tools** → **Upload Local MIB File** menu item. The **Upload Local MIB File** enables you to browse to a vendor's site and upload the specified MIB file for subsequent MIB loading.

To upload MIB files:

1. Do one of the following:
 - a. Navigate to the MIB view or form. For example, select  **Configuration** workspace, **MIBs**.folder, **Loaded MIBs** view.
 - b. Navigate to the MIB Variable view or form. For example, select  **Inventory** workspace, **MIB Variables** view.
2. Select **Tools** → **Upload Local MIB File**.
3. Click **Browse** to locate the MIB file you want to upload.
4. Click **Upload** to upload the MIB file to the following directory (see ["About Environment Variables" on page 86](#) for more information):

Windows:

`%NnmDataDir%\shared\nnm\user-snmp-mibs`

Linux:

`$NnmDataDir/shared/nnm/user-snmp-mibs`

5. NNMi displays the following information:

- The full path to the MIB file.
 - Instructions for loading and listing MIB files.
6. Next steps using **Tools** → **Load/Unload MIB...**:
- ["Load MIBs" below](#) (to enable access to the MIB file's Variables)
 - ["Load SNMP Trap Incident Configurations using the Console" on page 876](#) (to use the MIB file's Notification specifications)

Load MIBs

Prerequisite: NNMi requires that a [MIB File](#) first be *uploaded* onto a specific directory on the NNMi management server. See ["Upload MIB Files for NNMi's Use" on the previous page](#).

NNMi automatically stores a set of MIB files on the NNMi management server during installation. These files are located in the following directory (see ["About Environment Variables" on page 86](#)):

Windows

%NmInstallDir%\misc\nnm\snmp-mibs

Linux

\$NmInstallDir/misc/nnm/snmp-mibs

To view the list of MIB Files currently loaded on the NNMi management server, use the ["Loaded MIBs View" on page 1499](#).

To enable NNMi's use of a MIB file, do one or more of the following:

- [In the console, load MIBs](#)
- [From the command line, load MIBs](#)

To unload a MIB file, see ["Unload MIBs" on page 1496](#) or use the `nnmloadmib.ovpl` command.

Tip: If you are using MIBs to create MIB Expressions for Custom Poller, also see ["Enable or Disable Custom Poller" on page 480](#) and ["Create a Custom Poller Collection" on page 481](#). If you are using MIBs to create Graphs, see ["Configure SNMP Line Graph Actions" on page 1477](#).

Load MIBs from the Console

To load additional MIBs, use the **Tools** → **Load/Unload MIB...** menu item. The **Load/Unload MIBs** option enables you to view the MIBs that are available to load or unload.

[Click here](#) for details.

MIBs Available to Load/Unload

Use this page to view MIB files that are stored on the NNMi management server. Additional MIBs can be [uploaded](#) into the user MIB directory (C:\ProgramData\HP\HP BTO Software\shared\nnm\user-snmp-mibs\). Any MIBs listed under "MIBs Loaded" can be unloaded using the "Unload MIB Definition" link in the Actions columns of this report. This tool loads MIBs for creating MIB Expressions or for mnemonic display using the MIB Browser using the "Load MIB Definition" link. If the MIB contains the TRAP-TYPE or NOTIFICATION-TYPE macros, a "Load Incident Configuration" link will be displayed which can load the macro as Incident configuration. You can also load and unload MIB definitions, as well as load Incident configurations, using the command line. For more information, see the [nnmloadmib.ovpl](#) and [nnmincidentcfg.ovpl](#) reference pages.

- MIBs Available to Load (User Provided)
- MIBs Available to Load (NNMi Provided)
- MIBs Loaded (User and NNMi Provided)

1 **Navigational Links**

MIBs Available to Load (User Provided)

No MIB files are available to load in the C:/ProgramData/HP/HP BTO Software/shared/nnm/user-snmp-mibs/ directory. Either no MIB files are stored on the NNMi management server or all of the MIB files stored on the management server have been loaded. [Click](#) to upload additional MIB files.

MIBs Available to Load (NNMi Provided)

The following MIB files are stored on the NNMi management server in the C:/Program Files (x86)/HP/HP BTO Software/misc/nnm/snmp-mibs directory and can be loaded into NNMi.

- IEEE/

	MIB	MIB File	Actions	Unloaded Prerequisite MIB Imports
1	IEEE8021-PB-MIB ieee8021PbMib ::= { ieee802dot1mibs 5 }	snmp-mibs/IEEE/IEEE8021-PB-MIB.mib	Display Load MIB Definition	IEEE8021-BRID
	IEEE8021-Q-BRIDGE-MIB	snmp-mibs/IEEE/IEEE8021	Display	IEEE8021-BRIDGE-MIB

2 **3** **4**

Load/Unload MIBs Web Page

Feature	Description
1	If any MIBs are stored on the NNMi management server (available for loading or already loaded), click the link to display the appropriate table.
2	If any MIB includes a conforming SNMPv2c SMI <i>MODULE-IDENTITY</i> , a text string displays that describes the MODULE-IDENTITY.
3	Possible actions:

Load/Unload MIBs Web Page, continued

	<ul style="list-style-type: none"> Click Display to open the MIB file¹ (source text file). Click Load MIB Definition to load the selected MIB.
4	<p>This column displays any MIBs that are "prerequisites" for the listed MIB, and still need to be manually loaded before you can load the listed MIB. These dependencies are gathered from the MIB's IMPORTS statement. For example:</p> <pre>RFC1382-MIB DEFINITIONS ::= BEGIN IMPORTS Counter, Gauge, TimeTicks FROM RFC1155-SMI OBJECT-TYPE FROM RFC-1212 DisplayString, transmission FROM RFC1213-MIB TRAP-TYPE FROM RFC-1215 EntryStatus FROM RFC1271-MIB PositiveInteger, IfIndexType FROM RFC1381-MIB;</pre>

You can also use the **Tools** → **Load/Unload MIB...** menu item to load any incident configuration associated with the MIB. See ["Load SNMP Trap Incident Configurations using the Console" on page 876](#) for more information.

To enable NNMi's use of a MIB file from the NNMi console:

- Click the **Tools** → **Load/Unload MIB...** menu item.

NNMi displays the following information:

- MIBs (User provided) that are stored on the NNMi management server and that were provided by the NNMi administrator.
- MIBs (NNMi provided) that NNMi has stored on the NNMi management server during installation.

¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

- MIBs that are loaded in the NNMi database.

See [Click here for more details](#) for more information.

2. Navigate to the Unloaded MIB view of interest. For example, **MIBs Available to Load (NNMi Provided)**.
3. In the **MIB** column, find the MIB you want to load. For example, **RFC1381-MIB**.
4. To view the MIB file (source text file) before loading, in the **Actions** column, click **Display**.
5. To load the MIB file in the Actions column, click **Load MIB Definition**.

NNMi displays the MIB file load progress including the following:

- The MIB root object identification (OID) number.
- Number of MIBs, MIB variables, enumerated values, table indices, and parent/child hierarchies created.
- Whether the MIB successfully loaded.

Also see the [nnmloadmib.ovpl](#) command.

To upload a local MIB file so that it is stored on the NNMi management server and available for loading, see ["Upload MIB Files for NNMi's Use" on page 1491](#).

To unload a MIB file, see ["Unload MIBs" on the next page](#).

Load MIBs from the Command Line

To load additional MIBs from the command line, use the [nnmloadmib.ovpl](#) command.

Note: You can also use the [nnmloadmib.ovpl](#) command with the `-list` option to view the list of MIBs currently stored in the NNMi database.

To enable NNMi's use of a MIB file from the command line:

1. Locate the [MIB file](#)¹ (source text file) you want to use.

Note: You can use the device vendor's website to locate the MIBs available for your devices.

¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

2. Copy the MIB file to the location of your choice. In the example used in the next step, the MIB file is copied to a /temp directory.
3. Use the [nnmloadmib.ovpl](#) command to load the MIB on the NNMi management server.

For example, to load the HOST-RESOURCES-MIB that was copied to the /temp directory, you would enter a command similar to the following:


If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

```
nnmloadmib.ovpl -u <NNMiadminUsername> -p <NNMiadminPassword> -load  
/temp/HostResources.mib
```

To unload a MIB, see ["Unload MIBs" below](#) or use the [nnmloadmib.ovpl](#) command.

Tip: If you are using MIBs to create MIB Expressions for Custom Poller, also see ["Enable or Disable Custom Poller" on page 480](#) and ["Create a Custom Poller Collection" on page 481](#). If you are using MIBs to create Graphs, see ["Configure SNMP Line Graph Actions" on page 1477](#).

Unload MIBs


To unload MIB files from the NNMi console, select the  **Configuration** workspace,, **MIBs** folder, **Loaded MIBs** view. Then, use the **Tools** → **Load/Unload MIB** menu. The **Load/Unload MIB** option also enables you to view the MIB files that are available to load or unload.

[Click here](#) for details.

MIBs Available to Load/Unload

Use this page to view MIB files that are stored on the NNMI management server. Additional MIBs can be [uploaded](#) into the user MIB directory (C:\ProgramData\HP\HP BTO Software\shared\nnm\user-snmp-mibs\). Any MIBs listed under "MIBs Loaded" can be unloaded using the "Unload MIB Definition" link in the Actions column of this report. This tool loads MIBs for creating MIB Expressions or for mnemonic display using the MIB Browser using the "Load MIB Definition" link. If the MIB contains the TRAP-TYPE or NOTIFICATION-TYPE macros, a "Load Incident Configuration" link will be displayed which can load the macro as Incident configuration. You can also load and unload MIB definitions, as well as load Incident configurations, using the command line. For more information, see the [nnmloadmib.ovpl](#) and [nnmincidentcfg.ovpl](#) reference pages.

- [MIBs Available to Load \(User Provided\)](#)
- [MIBs Available to Load \(NNMI Provided\)](#)
- [MIBs Loaded \(User and NNMI Provided\)](#)

1  [Navigational Links](#)



MIBs Loaded (User and NNMI Provided)

	MIB	MIB File	Actions
1	RFC1155-SMI	jar:file:/opt/OV/nonOV/jboss/hms/server/hms/lib/hms-mib-model.jar!/com/hp/ov/hms/mib/model/hibernate/rfc1155-RFC1155-SMI.mib	Display Load Incident Configuration Unload MIB Definition
2	RFC-1212 2	jar:file:/opt/OV/nonOV/jboss/hms/server/hms/lib/hms-mib-model.jar!/com/hp/ov/hms/mib/model/hibernate/rfc1212-RFC1212.mib	Display Load Incident Configu Unload MIB Definition 3
3	RFC1213-MIB	jar:file:/opt/OV/nonOV/jboss/hms/server/hms/lib/hms-mib-model.jar!/com/hp/ov/hms/mib/model/hibernate/rfc1213-RFC1213-MIB.mib	Display Load Incident Configuration Unload MIB Definition

Load/Unload MIBs Web Page

Feature	Description
1	If any MIB files are stored on the NNMI management server (available for loading or already loaded), click the link to display the appropriate table.
2	If any MIB includes a conforming SNMPv2c SMI <i>MODULE-IDENTITY</i> , a text string displays that describes the MODULE-IDENTITY. For example, the MODULE-IDENTITY in row 1 is <i>ianaifType</i>
3	Select Unload MIB Definition to unload the selected MIB.

To unload MIBs from the NNMI console:

1. Do one of the following:
 - a. Navigate to the MIB view or form. For example, Select  **Configuration** workspace, **MIBs** folder, **Loaded MIBs** view.
 - b. Navigate to the MIB Variable view or form. For example, Select  **Inventory** workspace, **MIB Variables** view.
2. Select **Tools** → **Load/Unload MIB**.

NNMi displays the following information:

- MIBs (User provided) that are stored on the NNMi management server and that were provided by the NNMi administrator.
- MIBs (NNMi provided) that NNMi has stored on the NNMi management server during installation.
- MIBs that are loaded in the NNMi database.

See [Click here for more details](#) for more information.

3. Navigate to the Loaded MIBs view.
4. In the MIB column, find the MIB you want to unload.
5. To view the MIB before unloading, in the Actions column, click **Display**.

NNMi displays the [MIB file](#)¹ (source text file).

6. To unload the MIB, in the Actions column, click **Unload MIB Definition**.

NNMi displays the MIB file load progress including the following:




- Name of the MIB file
- Whether the unload MIB command was successful

Also see the [nnmloadmib.ovpl](#) command.

Available MIBs Files and MIB Variables

Examine the available MIB files and MIB variables using the following methods:


¹Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

-  **Configuration** workspace, **MIBs** folder, "[Loaded MIBs View](#)" below
 - [MIB Form](#)
- For a list of all variables in all installed MIBs:
 -  **Configuration** workspace, , **MIBs** folder, **MIB Variables** view
 -  **Inventory** workspace, [MIB Variables view](#)
- [Display a MIB File's Source Text](#)
- [Using the MIB Browser](#)

NNMi enables you to take a proactive approach to network management by using MIB Expressions to specify additional information that NNMi should poll. See "[Configure MIB Expressions](#)" on the [next page](#) for more information.

Note: The MIB files that define the MIB variables included in the MIB Expression that you want NNMi to poll must be loaded on the NNMi management server.

Loaded MIBs View

Use the  **Configuration** workspace, **MIBs** folder, **Loaded MIBs** view to see the list of currently loaded MIB files on the NNMi management server.

Tip: You can also use the [nnmloadmib.ovpl](#) command with the `-list` option to view the list of MIB files stored in the NNMi database.

To view the MIBs Loaded on the NNMi management server:

1. Navigate to the **Configuration** workspace.
2. Expand **MIBs**.
3. Select **Loaded MIBs**.

NNMi displays the Name of the MIB and the relative MIB file name for each of the MIBs available.

See "[Load MIBs](#)" on page 1492 and [nnmloadmibs.ovpl](#) for information about how to load MIBs.

See "[Unload MIBs](#)" on page 1496 and [nnmloadmibs.ovpl](#) for information about how to unload MIBs.

See [Exploring SNMP MIB Source Information](#).

Note: The MIB defining a Variable you want to use in a MIB Expression must be loaded on the

NNMi management server.

Configure MIB Expressions

NNMi enables you to take a proactive approach to network management by using SNMP MIB Expressions to specify additional information that NNMi should poll. After you create the MIB Expression, you can display this information in Graphs or use it with the NNMi Custom Poller feature.

To specify a MIB Expression, provide the required information within one of the following contexts:

["MIB Expressions Form \(Custom Poller\)" on page 495](#)

["MIB Expression Form \(Line Graph\)" below](#)

See ["MIB Expressions in Full URLs" on page 1476](#) for more information about using MIB Expressions in Graphs.

See ["Create Custom Polling Configurations" on page 478](#) for more information about using MIB Expressions with Custom Poller.

The MIB Expressions view in the Configuration workspace includes the MIB Expressions provided by NNMi. See ["MIB Expressions View" below](#) for more information.

MIB Expressions View

Use the MIB Expressions view to determine the MIB Expressions available for use. You can use MIB Expressions when configuring Custom Poller and Graph Actions. See ["MIB Expressions Form \(Custom Poller\)" on page 495](#) and ["MIB Expression Form \(Line Graph\)" below](#) for more information.

Note: All MIB Expressions provided by NNMi use the Author value **HP Network Node Manager**.



To view the MIB Expressions available:

1. Navigate to the **Configuration** workspace.
2. Select the **MIBs** folder.
3. Select the **MIB Expressions** view.

The columns in this table view show the Name, Author, and Description for each available MIB Expression.

MIB Expression Form (Line Graph)

You can access the MIB Expression form in the following ways:

- From the  **Configuration** workspace > **MIBs** folder > **MIB Expressions** view.
- From the  **Configuration** workspace > **Monitoring** folder > **Custom Poller Configuration** form.
- From the **MIB Specification** form. (Used when configuring SNMP Graph actions.)

Tip: To determine a particular Node's MIB Variable Values, see [Run SNMP Walk Commands \(MIB Browser\)](#). This is useful for determining the following:

- What is possible to graph for a specified node. For example, you might want to determine whether a Node supports MIB Variables in the RMON2-MIB so that you can decide whether to configure a Line Graph using one or more of the RMON2-MIB's Variables.
- How often the MIB Variable values change. This information helps to determine whether a Line Graph would be a useful tool for monitoring the MIB Variable's values.


When you want to create a MIB Expression to be used in Line Graphs, use the **MIB Expressions** view.


Note:

- NNMi supports one MIB expression per Line Graph.
- You can re-use any MIB Expression that you create for NNMi Line Graphs or for Custom Poller. Use "[MIB Expressions View](#)" on the previous page to see a list of the available MIB Expressions. Use the "[Loaded MIBs View](#)" on page 1499 to see a list of the MIBs loaded on the NNMi management server.

See "[Configure MIB Expressions](#)" on the previous page for more information about configuring Line Graph. See "[MIB Expressions Form \(Custom Poller\)](#)" on page 495 for more information about using the **Custom Poller Configuration** form.

To create a MIB Expression using the MIB Expression form:


1. From the workspace navigation panel, select the  **Configuration** workspace.
2. Expand the **MIBs** folder.
3. Select the **MIB Expressions** view.
4. Do one of the following:

- To create a MIB Expression, click the  **New** icon.
 - To edit a MIB Expression, double-click the row representing the configuration you want to edit.
5. Provide the required basic settings (see the [MIB Expression Basic Attributes](#) table).
 6. *Only for Multiple Instance MIB Expressions.* Line Graphs that display multiple instances use the following syntax for the line label that appears in the Graph legend:

`<node_name> <Line_Label>.<instance_string>`

 In this instance, `<Line_Label>` is the Line Label value specified when using the MIB Specification form.

 Use the **Instance Display Configuration** section of the MIB Expression form to specify the configuration for the `<instance_string>` values (see the [Instance Display Configuration](#) table).

 See "[Use the MIB Expression Editor \(Line Graph\)](#)" on page 1506 for more information about multiple instance MIB Expressions.
 7. Click  **Save and Close**.
 8. To test your MIB Expression, select **Actions** → **Graph MIB Expression**. See "[Test a MIB Expression \(Line Graph\)](#)" on page 1505 for more information.






Tip: You can right-click any object in a table or map view to access the **Actions** menu.

- You must save the MIB Expression before you use **Actions** → **Graph MIB Expression**.
- The NNMi administrator determines the label that is used to identify the data instances that are displayed in Line Graphs using the Instance Display Configuration (see the [Instance Display Configuration](#) table). If the Instance Display Configuration is not set, NNMi identifies each instance that appears in a Line Graph using the Node's short DNS Name followed by the MIB Instance value in the format: `<node_name> -<MIB_instance_value>`.

MIB Expression Basic Attributes

Attribute	Description
Unique Key	Used as a unique identifier when exporting and importing MIB Expression definitions. To ensure that the value you enter is unique, it is recommended that you use the Java name space convention when providing this value. It is also useful to include the label value as part of the unique key as shown in the following example: <code>com.<your_company_name>.nnm.mibexp.<mib_expression_name></code>

MIB Expression Basic Attributes, continued

Attribute	Description
	<p>The maximum length is 80 characters.</p> <p>Note: Unlike the Unique Key attributes associated with other objects, you can change the MIB Expression configuration's Unique Key value at any time.</p>
Name	<p>The name you want to use for the MIB information being polled. This name can be the same name as a MIB Variable used in the MIB Expression, or you can enter a name of your choice.</p> <p>Type a maximum of 50 characters. Alpha-numeric and special characters (~ ! @ \$ % ^ * () _ +) are permitted. No spaces are permitted.</p>
Author	<p>Indicates who created or last modified the MIB Expression.</p> <p>Caution: If the Author attribute value is HP Network Node Manager, any changes are at risk of being overwritten in the future.</p> <ul style="list-style-type: none"> Click  Lookup and select  Show Analysis to display details about the currently selected Author. Click  Quick Find to access the list of existing Author values. Click  New to create an Author value.
Expression	<p>Click the  button to access the MIB Expression editor. See "Use the MIB Expression Editor (Line Graph)" on page 1506 for information about using the MIB Expression editor.</p> <p>Note: The MIB containing the variable must be loaded on the NNMi management server.</p>
Display numeric MIB OIDs in the Expression	<p>Enables you to display the MIB object identifier (OID) rather than the MIB variable name in the MIB Expression.</p> <p>Select Display numeric MIB OIDs in the Expression <input checked="" type="checkbox"/> to replace any MIB variable name with the MIB OID value in the MIB Expression.</p> <p>Clear Display numeric MIB OIDs in the Expression <input type="checkbox"/> to display the MIB variable names rather than the MIB OIDs within the MIB Expression.</p>
Description	<p>NNMi provides the Description attribute to help you further identify the current MIB Expression configuration.</p> <p>Use the description field to provide additional information that you would like to store about the current MIB expression configuration.</p>

MIB Expression Basic Attributes, continued

Attribute	Description
	Type a maximum of 2000 characters. Alpha-numeric and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Instance Display Configuration

Attribute	Description
Conversion Algorithm	<p>Used to determine the format in which the instance portion (<i><instance_string></i>) of the line label appears in the Line Graph legend.</p> <p>Line labels in a Line Graph use the following syntax: <i><node_name> <Line_Label>.<instance_string></i></p> <p>In this instance, <i><Line_Label></i> is the Line Label value specified when using the MIB Specification form.</p> <p>Possible Conversion Algorithms are:</p> <ul style="list-style-type: none"> • Numeric - Use this option to display the instance number returned by the SNMP query as the <i><instance_string></i> value. This format is useful when no meaningful name is available in the MIB. For example, Line Graphs that display CPU information might use this format. • MIB Variable - Use this option to display the value that is stored in the MIB variable you specify. To obtain each MIB variable value, NNMi appends the instance number to the MIB variable specified. The result from the SNMP query is converted to a text string and displayed as the <i><instance_string></i> value of the line label in the Line Graph legend. • Alphabetic - Use this option to display information for legacy Cisco Arrow Point load balancers. When using this algorithm, each instance number returned by the SNMP query is treated as a set of ASCII characters instead of numbers. For example, the instance 101.120.97.109.112.108.101 would be displayed as 'example' in the <i><instance_string></i> of the line label.. • Interface Name - Use this option to display the interface name (ifName, if any) as the <i><instance_string></i> value in the Line Graph legend. If the SNMP agent responds to an ifName request with null, the ifIndex value is queried and used instead. • Interface Name Indirect - Use this option to display the Interface Name value obtained from an indirect reference in the MIB table. For example, if the MIB variable you specify resides in an RMON MIB table, use this algorithm. If the SNMP agent responds to an ifName request with null, the ifIndex value is queried and used instead.
Display Variable	Select the MIB variable you want to display as the <i><instance_string></i> value in the line label of the Line Graph legend.

Instance Display Configuration, continued

Attribute	Description
	NNMi uses the Conversion Algorithm you specify to determine how to obtain the <i><instance_string></i> value.
Display Filter	<p>When you display the Line Graph, the data displayed in the Line Graph is filtered based on the criteria you provide here.</p> <p>Enter a valid regular expression that specifies the pattern you want NNMi to match when determining the values to display in the <i><instance_string></i> value of each line label.</p> <div>Note: NNMi uses the syntax defined for java regular expressions (java.util.regex Pattern class).</div> <p>NNMi finds the first character sequence that matches the Display Filter expression. If NNMi does not find a match for the Display Filter, it returns the Display Variable name.</p> <p>For example, if you have several interfaces with an ifDescr set to "FastEthernet" followed by a unique set of numbers for each interface (such as FastEthernet0/1, FastEthernet0/2, FastEthernet0/3, and so on), you can use the following Display Filter to display "Ethernet" followed by the unique set of numbers:</p> <pre>(Ethernet.*[0-9]+){1}</pre> <p>In the example, the following matches occur:</p> <ul style="list-style-type: none">• Ethernet matches Ethernet• The .* matches 0/• The [0-9]+ matches any sequence of numbers• The {1} specifies to match the expression exactly one time

Test a MIB Expression (Line Graph)

The Actions menu enables you to test the results of a MIB Expression using a Line Graph.

Note: You must save the MIB Expression before you use **Actions** → **Graph MIB Expression**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.



To graph the results for a MIB Expression:

1. Navigate to the **MIB Expression** form.
 - a. From the workspace navigation panel, select the **Configuration** workspace.
 - b. Expand the **MIBs** folder.
 - c. Select **MIB Expressions**.

Note: You can also access the MIB Expression form when creating Line Graphs and when creating Custom Poller Collections. See ["MIB Expression Form \(Line Graph\)" on page 1500](#) and ["MIB Expressions Form \(Custom Poller\)" on page 495](#) for more information.

2. Select the row representing the MIB Expression you want to graph.
3. Select **Actions** → **Graph MIB Expression**.

The dialog for selecting a node appears.

4. Click the  **Lookup** icon and select  **Quick Find**.
5. Select the node you want to use to test your MIB Expression results.

NNMi displays a Line Graph using the selected node and calculating the results for the MIB Expression you selected.

Note the following:

- *Line Graphs Only.* When evaluating MIB Expressions that include MIB variables of type Counter or Counter64, NNMi requests both the high capacity and low capacity counter variable for any interface instance. If the high capacity Counter 64 is enabled for any given interface instance, NNMi uses the high capacity counter.
- *Custom Poller Only.* When evaluating MIB Expressions that include MIB variables of type Counter, NNMi requests only the low capacity counter information for any interface instance.

Use the MIB Expression Editor (Line Graph)

Use the MIB Expression Editor to specify the MIB Variables and any Constant values or arithmetic operators you want to include in your MIB Expression.

For example, disk utilization could be calculated and polled using a MIB Expression similar to the following:


(hrStorageUsed / hrStorageSize)

See the [MIB Expression Editor Options](#) table for a description of each of the MIB Expression Editor options.

When using the MIB Expression Editor, note the following:

- As a general guideline, begin by writing out the MIB Expression. Then in the MIB Expression Editor, begin creating your MIB Expression by selecting your arithmetic operators (+, -, *, or /) from the outermost parenthesis to the innermost parenthesis. Each time you specify an arithmetic operator (+, -, *, or /), NNMi creates a set of parenthesis to specify the ordering of the mathematical calculation.
- When adding arithmetic operators (+, -, *, or /) to a MIB Expression, first click to select the location in the MIB Expression at which you want to add the arithmetic operator.
- Click to select the arithmetic operator (for example +) in the MIB Expression, before selecting the MIB variable or Constant value that you want to add, subtract, multiply or divide.

You can also use the following key bindings to add arithmetic operators:

- ALT+ (plus button)
- ALT- (minus button)
- ALT/ (divide button)
- ALT* (multiply button)
- NNMi inserts arithmetic operators, MIB Expressions, and Constant values from the left to right.
- To replace an arithmetic operator use the  (Change Operator) button (see [table](#)).
- To replace a MIB Variable or Constant value, click to select the existing value in the MIB Expression and then select the new MIB variable or enter the new Constant value.

Note: You can replace a MIB Variable with another MIB Variable or with a Constant value. You can replace a Constant value with a MIB Variable or Constant value.

- You can drag any of the following items to a new location in the MIB Expression:
 - MIB variable
 - Constant value
 - An operation, such as **(ifInOctets + ifOutOctets)**

[Click here](#) for more information about moving items in the MIB Expression to a new location.

When moving items in the MIB Expression, note the following:

- To move an arithmetic operation (for example, **(ifInOctets + ifOutOctets)**), click the arithmetic operator before dragging it to a new location.
- To move a MIB Variable or Constant Value, click the MIB Variable or Constant Value you want to move before dragging it to a new location.

- If you are moving the selected item to the right, NNMi places the item to the right of the new location.
- If you are moving the selected item to the left, NNMi places the item to the left of the new location.
- As you drag a selected item, an underline indicates the current target location.
- If you drag a selected item past the outermost parenthesis, it is deleted. If desired, you can re-enter the value in the new location.

MIB Expression Example

To create a MIB Expression that calculates the percentage of available bandwidth on a half-duplex interface, you might create the following MIB Expression:

$(((((\text{ifInOctets} + \text{ifOutOctets}) * 8) / \text{ifSpeed}) * 100)$

[Click here](#) for a step-by-step textual example of creating the same MIB Expression:

To create a MIB Expression that calculates the percentage of available bandwidth on a half-duplex interface, you might create the following MIB Expression:

$(((((\text{ifInOctets} + \text{ifOutOctets}) * 8) / \text{ifSpeed}) * 100)$

To create the expression above, begin by specifying each arithmetic operator from the outermost parenthesis to the innermost parenthesis.

1. Click  (multiply).

2. Click  (divide).

Now that you have multiple entries in your MIB Expression, click to select the location in the MIB Expression to which you want to add each remaining arithmetic operators.

3. In the MIB Expression, click  (divide).

The divide (/) arithmetic operator and its surrounding parenthesis should appear highlighted. Because NNMi inserts arithmetic operators, MIB variables, and Constant values from left to right, selecting / (divide) places the next arithmetic operator to the left of the divide arithmetic operator.

4. Click  (multiply).

The multiply (*) arithmetic operator and its parenthesis should appear to the left of the divide arithmetic operator you previously selected.

5. In the MIB Expression, click the leftmost * (multiply).


The multiply (*) arithmetic operator and its surrounding parenthesis should appear highlighted.

6. Click  (add).


The add (+) arithmetic operator and its parenthesis should appear to the left of the multiply (*) arithmetic operator you previously selected.

Now that you have specified the arithmetic operators, you are ready to add the MIB variables and Constant values. Begin by selecting the arithmetic operator in the MIB Expression to which you will add MIB variables, Constant values, or both. We will begin with the leftmost arithmetic operation.

Note: As you add your MIB variables or Constant values, make sure you first select the corresponding arithmetic operator within the MIB Expression.

7. In the MIB Expression attribute, click + (add).
8. Select the ifInOctets MIB Variable:
- Click  to open the MIB Variable Tree.
 - Navigate to **ifInOctets**.
 - Select **ifInOctets**.
 - Click **OK**.

The ifInOctets MIB variable should appear to the left of the add (+) arithmetic operator.

9. Select the ifOutOctets MIB Variable:
- Click  to open the MIB Tree.
 - Navigate to **ifOutOctets**.
 - Select **ifOutOctets**.
 - Click **OK**.

The ifOutOctets MIB variable should appear to the right of the add (+) arithmetic operator.


You are ready to specify the Constant value 8 that corresponds with the leftmost multiply (*) arithmetic operator.

10. Click the leftmost * multiply.
11. In the Constant attribute, enter 8 and click Enter.

The value 8 should appear to the right of the multiply (*) arithmetic operator that you previously selected.

12. In the MIB Expression, click divide (/).

13. Select the IfSpeed MIB Variable:

- a. Click  to open the MIB Tree.
- b. Navigate to ifSpeed.
- c. Double-click ifSpeed.
- d. Click **OK**.

The ifSpeed MIB Variable name should appear to the right of the divide (/) arithmetic operator you previously selected.

14. Click the rightmost * (multiply)


15. The Constant value 100 should appear to the right of the divide (/) arithmetic operator you previously selected.

16. In the Constant attribute, enter 100 and then click Enter.








17. Click **OK** to save your MIB Expression.

The following table describes each of the MIB Expression Editor options.

MIB Expression Editor Options

Attribute	Description
MIB Expression	Displays the MIB Expression as it is created. You can place the cursor in the MIB Expression field to specify where you want to add or replace an entry.
MIB Variable	<p>You must select a MIB Variable using the MIB Tree. Click the  icon to access the MIB tree and navigate to the MIB variable of interest.</p> <p>Note: If you do not see a MIB that you recently loaded, wait 1 minute for NNMi to cache the new MIB information, and then open the MIB Tree again.</p> <p>After you select a MIB Variable, NNMi displays the MIB Variable's name.</p> <p>If you choose a MIB Variable that has multiple instances, you MUST specify a MIB Filter Variable and MIB Filter. For example, because a node can have multiple interfaces, MIB Variables containing interface information have multiple instances, one for each interface. You are required to provide a MIB Filter value to select the interfaces you want NNMi to poll. If you do not specify a MIB Filter Variable and MIB Filter, NNMi assumes the MIB variable is non-repeating. Click here for more information.</p>

MIB Expression Editor Options, continued

Attribute	Description
	<p>For example, if you want to always gather additional HOST-RESOURCES-MIB status information about COM (communication) port devices, you would define the following:</p> <ul style="list-style-type: none"> • MIB Expression: hrDeviceStatus • MIB Filter Variable: hrDeviceDescr • MIB Filter: COM* <p>See "Create a Policy" on page 516 for more information about the MIB Filter.</p>
Constant Value	A numeric value to be used in the calculation for the MIB Expression. For example, you might want to include 100 as a constant when calculating percentages.
Enter	Includes the Constant Value in the MIB Expression.
	Adds the results.
	Subtracts the results.
	Multiplies the results.
	Divides the results.
	<p>Changes the selected operator (+, -, *, and /) to the operator that appears next in sequence (from left to right) in the MIB Expression Editor. (The example below shows the operator sequence in the MIB Expression Editor.)</p> <p>For example, if you place your cursor at an add (+) operator in the MIB Expression, the MIB Expression Editor changes the add (+) operator to the minus (-) operator. If you place your cursor at the divide (/) operator in the MIB Expression as shown in the example below, the MIB Expression Editor changes the operator to the add (+) operator.</p>  <p>When using the  (Change Operator) button, note the following:</p>

MIB Expression Editor Options, continued

Attribute	Description
	<ul style="list-style-type: none">You must select an operator in the MIB Expression before using the Change Operator (<>) button.You can replace a MIB Variable with another MIB Variable or with a Constant. You can replace a Constant value with a MIB Variable or Constant.
Delete	Deletes the entry that is selected. If no entry is selected, NNMi deletes the last entry in the MIB Expression.
OK	Closes the MIB Expression Editor and saves your changes.
Clear	Removes any entries in the MIB Expression.
Cancel	Closes the MIB Expression Editor without saving your changes.

Override MIB OID Types

NNMi's Custom Poller determines the MIB OID Types for each MIB OID that is used in a MIB Expression or MIB Filter and lists them in the **MIB OID Types** table in the **Configuration** workspace. These MIB OID Type configurations are then used by Custom Poller, as well as the NNMi Line Graph, and the Analysis Pane Gauges feature.

Note: If you delete a MIB OID Type entry that is used by Custom Poller, MIB OID Types reappear in the MIB OID Types table the next time any of the following occurs: 1) a Custom Poller Policy is activated, 2) a Custom Polled Instance is generated, or 3) a node in the Node Group associated with a Custom Poller Policy is discovered.

If you find that the results of a MIB Expression displayed in a Line Graph or a Gauge or used by Custom Poller are not as expected, you can use the MIB OID Types configuration to override values for the following items for a MIB Object Identifier (OID):

- Primitive Type
- Conversion Type
- Whether the MIB Variable should be treated as a single instance or as multiple instances.

Tip: To view the results of Custom Poller MIB expressions, export the data to a CSV file or use Report Groups and Report Collections to export the data to NNM iSPI Performance for Metrics. See ["Configure Basic Settings for a Custom Poller Collection" on page 484](#) and ["Create a Report Group \(NNM iSPI Performance for Metrics\)" on page 520](#) for more information. You can also view the results of MIB Expressions using Line Graphs. See [Monitor with Line Graphs](#) for more information.

Reasons to override MIB OID types include:


- Correcting the Primitive Type that is provided by the MIB vendor.
- To display Line Graph data as a different Primitive Type.

For example, when viewing a Line Graph of `locIfOutputQueueDrops` and `locIfInputQueueDrops` values from the `OLD-CISCO-INTERFACES` MIB, you might notice that NNMi is graphing large numbers. To make the Line Graph more meaningful, use the MIB OID Types configuration to change the MIB OID Primitive Type from Integer to Counter.

- To change the default Conversion Type value for a Primitive Type.

For example, you might want to change the MAC Address default OCTET STRING Conversion Type so that it is in a readable format.

To configure a MIB OID Type:

1. Navigate to the **Configuration** workspace.
2. Click to expand the **MIBs** folder.
3. Select **MIB OID Types**.
4. Do one of the following:
 - a. To create a MIB OID Type, click the  **New** icon.

Note: You should not need to create a MIB OID Type. Custom Poller automatically generates MIB OID Types as required.

- b. To edit a MIB OID Type, double-click the row representing the configuration you want to edit.
5. Provide the required basic settings (see the [MIB OID Types](#) table).

MIB OID Type Attributes

Attribute	Description
OID (Numeric)	The numeric representation of the OID (Object Identification) value for an associated MIB variable. <div>Tip: The NNMi Analysis Pane displays the textual representation of the OID for the selected MIB OID Type.</div>
Primitive Type	Defines the base type to be used for the associated MIB variable value. Valid values include the following: <ul style="list-style-type: none">• INTEGER• UNSIGNED_INTEGER

MIB OID Type Attributes, continued

Attribute	Description																
	<ul style="list-style-type: none"> • OCTET_STRING • COUNTER • COUNTER64 • GAUGE • TIME_TICKS • IP_ADDRESS 																
Conversion Type	<p>Used to handle data types returned for custom polled MIBs. NNMi enables you to change the default Conversion Type for each Primitive Type.</p> <p>Note: Only override the default if you want to change the way a value is represented. .</p> <p>Possible Conversion Types include:</p> <p>Valid Conversion Types</p> <table> <tr> <th>Conversion Type</th><th>Description</th></tr> <tr> <td>Default</td><td> <p>Converts to the valid (default) Conversion Type for the MIB's Primitive Type.</p> <p>See Primitive Type Defaults.</p> <p>Note: NNMi is not able to convert the Primitive Type if it does not have a corresponding Conversion Type.</p> </td></tr> <tr> <td>Big Integer</td><td>Converts integer-based 64-bit values.</td></tr> <tr> <td>Long Integer</td><td>Converts integer-based 32-bit values.</td></tr> <tr> <td>Standard String</td><td>Converts an array of bytes into a printable string using standard encoding.</td></tr> <tr> <td>Hex String</td><td>Converts an array of bytes directly into a string that represents those bytes. Useful for MAC addresses.</td></tr> <tr> <td>Byte Array</td><td>Converts directly to a byte array.</td></tr> <tr> <td>IP Address</td><td>Converts the value to an IP Address</td></tr> </table> <p>Each Primitive Type has the following default conversion type:</p>	Conversion Type	Description	Default	<p>Converts to the valid (default) Conversion Type for the MIB's Primitive Type.</p> <p>See Primitive Type Defaults.</p> <p>Note: NNMi is not able to convert the Primitive Type if it does not have a corresponding Conversion Type.</p>	Big Integer	Converts integer-based 64-bit values.	Long Integer	Converts integer-based 32-bit values.	Standard String	Converts an array of bytes into a printable string using standard encoding.	Hex String	Converts an array of bytes directly into a string that represents those bytes. Useful for MAC addresses.	Byte Array	Converts directly to a byte array.	IP Address	Converts the value to an IP Address
Conversion Type	Description																
Default	<p>Converts to the valid (default) Conversion Type for the MIB's Primitive Type.</p> <p>See Primitive Type Defaults.</p> <p>Note: NNMi is not able to convert the Primitive Type if it does not have a corresponding Conversion Type.</p>																
Big Integer	Converts integer-based 64-bit values.																
Long Integer	Converts integer-based 32-bit values.																
Standard String	Converts an array of bytes into a printable string using standard encoding.																
Hex String	Converts an array of bytes directly into a string that represents those bytes. Useful for MAC addresses.																
Byte Array	Converts directly to a byte array.																
IP Address	Converts the value to an IP Address																

MIB OID Type Attributes, continued

Attribute	Description																		
	Primitive Type Defaults																		
	<table><tr><th>Primitive Type</th><th>Default Conversion Type</th></tr><tr><td>INTEGER</td><td>Long Integer</td></tr><tr><td>UNSIGNED_INTEGER</td><td>Long Integer</td></tr><tr><td>OCTET_STRING</td><td>Standard String</td></tr><tr><td>COUNTER</td><td>Long Integer</td></tr><tr><td>COUNTER64</td><td>Big Integer</td></tr><tr><td>GAUGE</td><td>Long Integer</td></tr><tr><td>TIME_TICKS</td><td>Long Integer</td></tr><tr><td>IP_ADDRESS</td><td>IP Address</td></tr></table>	Primitive Type	Default Conversion Type	INTEGER	Long Integer	UNSIGNED_INTEGER	Long Integer	OCTET_STRING	Standard String	COUNTER	Long Integer	COUNTER64	Big Integer	GAUGE	Long Integer	TIME_TICKS	Long Integer	IP_ADDRESS	IP Address
	Primitive Type	Default Conversion Type																	
	INTEGER	Long Integer																	
	UNSIGNED_INTEGER	Long Integer																	
	OCTET_STRING	Standard String																	
	COUNTER	Long Integer																	
	COUNTER64	Big Integer																	
	GAUGE	Long Integer																	
	TIME_TICKS	Long Integer																	
IP_ADDRESS	IP Address																		
isTabular	<p>Specifies whether the MIB variable represented by the selected OID defines multiple instances grouped in a MIB table.</p> <p>Enabled <input checked="" type="checkbox"/>, indicates the associated MIB variable has multiple instances.</p> <p>Disabled <input type="checkbox"/>, indicates the associated MIB variable represents a single object instance.</p>																		

Purchase HP Network Node Manager i Smart Plug-ins and More

HP Network Node Manager i Software Smart Plug-ins (iSPIs) extend NNMi capabilities and enable you to manage your network in a way that makes sense in your organization. For example, each NNM iSPI might do the following:

- Enhance the data that is available.
- Add new workspaces, views, and forms.
- Add tabs to existing NNMi forms.
- Change the features of the NNMi user interface.

For more information:

- Contact your HP sales representative.
- See the documentation for each NNM iSPI, available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.
- See the NNMi Release Notes for a description, **Help** → **Documentation Library** → **Release Notes**

Available for purchase to use with NNMi and NNMi Advanced (separate license keys required):		License key includes NNMi Advanced plus more:	
		NNMi Premium	NNMi Ultimate
<p>HP Network Node Manager iSPI Network Engineering Toolset Software (NNM iSPI NET): See Help → Help for NNM iSPIs → NNM iSPI NET.</p> <p>For more information:</p>			
	Trap Analytics	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
	Visio Export	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
	Device Diagnostics Tip: Requires installation of a Diagnostic Server. See <i>HP Network Node Manager iSPI Network Engineering Toolset Diagnostics Server Release Notes</i> .	<input type="checkbox"/>	<input checked="" type="checkbox"/>
HP Network Node Manager Developer Toolkit		<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
Requires separate installation:			
HP Network Node Manager iSPI for IP Multicast Software See Help → Help for NNM iSPIs → iSPI for IP Multicast Help . See Views for IP Multicast .		<input type="checkbox"/>	<input checked="" type="checkbox"/>
HP Network Node Manager iSPI for IP Telephony Software See Help → Help for NNM iSPIs → IP Telephony Online Help . For more information:		<input type="checkbox"/>	<input checked="" type="checkbox"/>
HP Network Node Manager iSPI for MPLS Software See Help → Help for NNM iSPIs → iSPI for MPLS Help .		<input type="checkbox"/>	<input checked="" type="checkbox"/>

Available for purchase to use with NNMi and NNMi Advanced (separate license keys required):	License key includes NNMi Advanced plus more:	
	NNMi Premium	NNMi Ultimate
See Views for MPLS .		
HP Network Node Manager iSPI Performance for Metrics Software See <i>NNM iSPI Performance for Metrics Release Notes</i> . See Views for Performance Analysis .	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
HP Network Node Manager iSPI Performance for Quality Assurance Software See Help → Help for NNM iSPIs → iSPI Performance for QA Help for Operators . See Views for Performance Quality Assurance .	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
HP Network Node Manager iSPI Performance for Traffic Software See Help → Help for NNM iSPIs → iSPI Performance for Traffic Help for Administrators . See Views for Traffic Analysis .	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Related Topics:

["Track Your NNMi Licenses" on page 1604](#)

["Extend a Licensed Capacity" on page 1605](#)

["Integrations with HP and Third-Party Products" on page 1519](#)

Annotate NNM iSPI Performance for Metrics Reports

Requires HP Network Node Manager iSPI Performance for Metrics Software (NNM iSPI Performance for Metrics). To populate performance data in the dashboard views or enhance NNM iSPI Performance for Metrics reports by sharing NNMi configuration settings, install the *optional* Network Performance Server (NPS) – [click here for more information](#).

You can use Custom Attributes to include additional Node or Interface information in NNM iSPI Performance for Metrics reports.

For example, you might want to add information that identifies the interface Wide Area Network circuit.

To create a Node Custom Attribute to use in NNM iSPI Performance for Metrics reports:

1. Navigate to the nodes view (for example: **Inventory** → **Nodes**).
2. Use Ctrl-Click to select each node to which you want to add a Custom Attribute.

Tip: You can also select Nodes from a map view.

3. Select **Actions** → **Custom Attributes** → **Add**.
4. In the **Name** drop-down menu, select **NPS Annotation**.

NPS (Network Performance Server) is the database server installed with the HP Network Node Manager iSPI Performance for Metrics Software.

5. In the **Value** attribute, enter the value you want to appear with each node included in the NNM iSPI Performance for Metrics report.

The maximum length is 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Tip: Although NNMi lets you enter 2,000 characters, NNM iSPI Performance for Metrics Reports strip out all but the first 255 characters.

To create an Interface Custom Attribute to use in NNM iSPI Performance for Metrics reports:

1. Navigate to the Interfaces view (for example: **Inventory** → **Interfaces**).
2. Use Ctrl-Click to select each interface to which you want to add a Custom Attribute.

Tip: You can also select Interfaces from a map view.

3. Select **Actions** → **Custom Attributes** → **Add**.
4. In the **Name** drop-down menu, select **NPS Annotation**.
5. In the **Value** attribute, enter the value you want to appear with each interface included in the NNM iSPI Performance for Metrics report. For example, to identify a WAN circuit, the value might be: ATT Circuit ID 1237.

The maximum length is 255 characters. Alpha-numeric, spaces, and special characters (~ ! @ # \$ % ^ & * () _ + -) are permitted.

Tip: Although NNMi lets you enter 2,000 characters, NNM iSPI Performance for Metrics Reports strip out all but the first 255 characters.

To remove a Custom Attribute, select **Actions** → **Custom Attributes** → **Remove**.

Integrations with HP and Third-Party Products

You can configure multiple HP and third-party software products to share data with NNMi and receive data from NNMi. You can view details about each of these integrations in separate documents. To read any of these documents, do the following:

1. Point your web browser to the following website:
<http://h20230.www2.hp.com/selfsolve/manuals>
2. Supply your HP Passport credentials: **Sign-in to HP Passport**.
3. Select your search criteria:
 - Product
 - Version
 - Operating System
4. Select the link to `nnmi_doc_list_<version>.pdf`
5. Click the URL to the document you want to read.

Each integration adds some or all of the following functionality (depending on the integration):

- NNMi incidents are available in the integrated product's events viewer.
- NNMi receives and monitors traps related to the integrated product.
- NNMi operators can open some of the integrated product's views from within the NNMi console. Those views are in context of the object selected in the NNMi console (for example, node or interface).
- Operators of the integrated product can open some NNMi console views from within the integrated product. Those views are in context of the object selected in the integrated product.
- Network topology (inventory) information is shared between NNMi and the integrated product.

For information about the available integrations, see **Help** → **Documentation Library** → **Release Notes** and contact your HP sales representative.

Related Topics:

["Track Your NNMi Licenses" on page 1604](#)

["Extend a Licensed Capacity" on page 1605](#)

["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515](#)


Integration Configuration Form


You can configure a variety of HP and third-party software products (that run independently of NNMi) to integrate with NNMi. See **Help** → **Documentation Library** → **Release Notes**, and locate the **Support Matrix** for a complete list of supported products. You can view details about each of these integrations in separate documents. To read any of these documents, do the following:

1. Point your web browser to the following website:
<http://h20230.www2.hp.com/selfsolve/manuals>
2. Supply your HP Passport credentials: **Sign-in to HP Passport**.
3. Select your search criteria:
 - Product
 - Version
 - Operating System
4. Select the link to `nnmi_doc_list_<version>.pdf`
5. Click the URL to the document you want to read.

Each integration adds some or all of the following functionality (depending on the integration):

- NNMi incidents are available in the integrated product's events viewer.
- NNMi receives and monitors traps related to the integrated product.
- NNMi operators can open some of the integrated product's views from within the NNMi console. Those views are in context of the object selected in the NNMi console (for example, node or interface).
- Operators of the integrated product can open some NNMi console views from within the integrated product. Those views are in context of the object selected in the integrated product.
- Network topology (inventory) information is shared between NNMi and the integrated product.

Some of these products require that you provide information in the NNMi  **Integration Module Configuration** workspace. Use the appropriate integration configuration form to provide the information required for enabling an integration between NNMi and the associated product. For the latest information about an integration and the fields on its integration configuration form, do the following:

Note: HP Network Node Manager i Software Smart Plug-ins (iSPIs) do not use the  **Integration Module Configuration** workspace. NNM iSPIs have an entirely different configuration strategy. See "[Purchase HP Network Node Manager i Smart Plug-ins and More](#)"

[on page 1515.](#)

1. Point your web browser to the following website:
<http://h20230.www2.hp.com/selfsolve/manuals>
2. Supply your HP Passport credentials: **Sign-in to HP Passport.**
3. Select your search criteria:
 - Product
 - Version
 - Operating System
4. Select the link to `nnmi_doc_list_<version>.pdf`
5. Click the URL to the document you want to read.

Chapter 16: Integrating NNMi Elsewhere with URLs

Use URLs to provide access to the console or certain NNMi features. For example:

- Embed views within your company Web portal.
- Launch a map from within other applications, such as from an email.
- Launch a filtered view from a browser window to quickly find the information you need.
- Run a tool without opening the console.

The URLs you write must conform to ["W3C Rules for URLs" below](#).

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Prerequisite: NNMi requires authentication for access through URLs. See ["Authentication Requirements for URLs Access" on the next page](#).

Related Topics:

["Launch the Console \(showMain\)" on page 1526](#)

["Launch a View \(showView\)" on page 1527](#)

["Launch a Form \(showForm\)" on page 1568](#)

["Launch Menu Items \(runTool\)" on page 1584](#)

["Confirm that NNMi Is Running \(cmd=isRunning\)" on page 1602](#)

W3C Rules for URLs

The World Wide Web Consortium (W3C) allows only ASCII characters in URLs.

When configuring URLs, the following characters are always allowed:

- Alpha-numeric (A-Z a-z 0-9)
- - (hyphen)
- . (period)
- _ (underline)
- ~ (tilde)

Depending on the browser and the context, some characters require special formatting with Percent Encoding. A small number of possible values are shown in the quick reference table below.

You can designate the space character several ways:

- + (works in all browsers, recommended because it is easiest to read)
- %20 (Percent Encoded value, works in all browsers)
- space character (works in the browsers supported by NNMi, but is not guaranteed to work in all browsers)

RFC 3986 Characters Reserved as Delimiters
(If not specifying a delimiter, use Percent-Encoding value)

Character	:	/	?	#	[]	@	!	\$
Percent Encoded	%3A	%2F	%3F	%23	%5B	%5D	%40	%21	%24
Character	&	'	()	*	+	,	;	=
Percent Encoded	%26	%27	%28	%29	%2A	%2B	%2C	%3B	%3D

Additional Commonly Used Characters and Their Percent Encoding

Character	space	%	<	>
Percent Encoded	%20 (or + allowed)	%25	%3C	%3E

Authentication Requirements for URLs Access

Authentication requirements for URL access to various NNMi features are the same as for signing into the NNMi console. Each user must have a preconfigured user name, password, and default [NNMi User Group](#)¹ mapping. For more information, see:

- ["Choose a Mode for NNMi Access" on page 570](#)
- ["User Groups Provided in NNMi" on page 618](#)
- ["Configuring Sign-In to the NNMi Console" on page 657](#)

To bypass the NNMi sign-in page, do one of the following:

¹ NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

- Configure your network environment with Public Key Infrastructure (PKI) user authentication.

Note: If your network environment uses X.509 Certificates such as Public Key Infrastructure (PKI) user authentication, URL authentication requires a certificate (the same as accessing the main NNMi console). See , “Configuring NNMi to Support Public Key Infrastructure User Authentication” chapter in the *HP Network Node Manager i Software Deployment Reference* for more information, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

- Include the following two parameters in your URL string. Any URL request that contains j_username and j_password redirects, so the actual user name and password are not visible in the Web browser:
 - a. j_username
 - b. j_password

Caution: There is an inherent vulnerability in passing a plain text password as a URL parameter. Consider configuring the NNMi management server to use https/SSL (secure sockets layer encryption) so that user names/passwords are encrypted between client and server. To configure the NNMi Web server to use https instead of http, see the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*.

It is recommended that these parameters be used to bypass the NNMi sign-in page for only NNMi users mapped to the User Group: *NNMi Guest Users* (providing "read-only" access to a subset of console features). For example, if you have previously defined an account where both the user Name and Password are "guest", the following brings up a list of example URLs:

`http://<serverName>:<portNumber>/nnm/launch?j_username=guest&j_password=guest`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see "[Configuring the NNMi User Interface](#)" on page 524)


`<portNumber>` = the NNMi HTTP port number

If the user name and password are not valid, the NNMi sign-in page appears with an authentication error message.

Pass Environment Attributes

Environment Attributes (`envattrs`) are received from another application when NNMi is launched from that external application, see ["Launch a View \(showView\)" on page 1527](#) or ["Launch a Form \(showForm\)" on page 1568](#) for more information. These `envattrs` attributes are session-specific and not stored in the NNMi database. NNMi temporarily retains the `envattrs` name-value pairs. You can use `getEnvAttr` to retrieve a current `envattrs` value pair and pass it back to that application. [Click here for an illustrated example.](#)

You configured a button on your company website to launch NNMi and display the map of your network environment.



Note: See ["Configure Launch Actions" on page 1462](#) for information about adding menu items to the NNMi console menus.

You can send any number of Environment Attributes (`envattrs`) when launching NNMi from another website or program. You can use `getEnvAttr` to retrieve the current `envattrs` name=value pairs and pass them back:

```
${getEnvAttr(<applicationAttrName>)}
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<yourServerName>:<portNumber>/<application>?<yourURLparameter1>=
${getEnvAttr(<applicationAttrName1>)}&<yourURLparameter2>= ${getEnvAttr
(<applicationAttrName2>)}
```

Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number

For example, the following Full URL provides an Action within the NNMi console that returns the user to exactly the same place within your company website where the user was before launching NNMi:

```
http://<myHost>/<myApplication>?com.my.sessionId= ${getEnvAttr
(com.my.sessionId)}&com.my.objectName= ${getEnvAttr(com.my.objectName)}
```

The Full URL entry could result in the following URL:

```
http://<myHost>/<myApplication>com.my.sessionId=123&com.my.objectName=node25
```

Note: If the Environment Attribute that you request in your Action does not exist for the selected view or form, the resulting URL passes an empty string.

Launch the Console (showMain)

To launch the entire console, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=showMain
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

To launch the console and bypass log on, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=showMain&j_
username=<accountName>&j_password=<accountPassword>
```

Caution: Review the information in ["Authentication Requirements for URLs Access" on page 1523](#) before bypassing log on.

node

Launch a View (showView)

Tip: This technique launches views independent of the NNMi console. When using this URL method, do not launch the view into a browser window where the NNMi console is currently running. (If you are using Mozilla Firefox, see also [Configure Mozilla Firefox Timeout Interval.](#)) To continuously display up-to-date information in your network operation center (NOC), launch an Integration URL view.

To launch a default table view that displays all instances of a specified object type, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype= <x>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Default View for Each Object Type and Available Filters

x = objtype Value	Default View	Node Filter	Interface Filter
Incident	Incidents workspace, All Incidents table view	Yes	No
Node	Inventory workspace, Nodes table view	Yes	No
Interface	Inventory workspace, Interfaces table view	Yes	Yes
IPAddress	Inventory workspace, IP Addresses table view	Yes	Yes
IPSubnet	Inventory workspace, IP Subnets table view	No	No
NodeGroup	Inventory workspace, Node Groups table view	No	No
InterfaceGroup	Inventory workspace, Interface Groups table view	No	No

The following are optional filter parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype= <x>&nodegroup= <Name>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype= <x>&ifgroup= <Name>`

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <div> <p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p> </div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

Filter by Interface Group (launched Interface and IP Address views)

Attribute	Values
ifgroup	<p>The <i>case-sensitive</i> Name attribute value of the Interface Group to use as a filter for this view.</p> <div> <p>Note: The Interface Group name is translated. If your team shares NNMi within multiple locales, use ifgroupid or ifgroupuuid.</p> </div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
ifgroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
ifgroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype= <x>&menus=
<true|false>&newWindow= <true|false>&readonly=
<true|false>&readonlygroupselector = <true|false>&envattrs= <name1=
value>;<name2= value>
```

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<div> <p>Caution: The readonly setting overrides the readonlygroupselector setting. This means that when readonly is set to true and readonlygroupselector is set to false, users</p> </div>

Attributes for Launched Views , continued

Attribute	Values
	<p>are able to change the Node Group filter.</p> <p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
readonlygroupselector	<p>Caution: The readonly setting overrides the readonlygroupselector setting. This means that when readonly is set to true and readonlygroupselector is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from selecting a Node Group.</p> <p>Note: When readonlygroupselector is set to true, the Node Group filter selection box appears disabled.</p> <p>false = Enables the user to select a Node Group.</p>
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back to the originating external application.</p>

If you want to launch some other view, specify the view rather than the object type:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>
```

For more information, see:

["Launch an Incident View" below](#)

["Launch a Topology Maps Workspace View" on page 1536](#)

["Launch a Monitoring Workspace View" on page 1546](#)

["Launch a Troubleshooting Workspace View" on page 1550](#)

["Launch an Inventory Workspace View" on page 1559](#)

["Launch a Management Mode Workspace View" on page 1563](#)

["Launch a Configuration Workspace View" on page 1566](#)

Launch an Incident View

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Potential Incident Workspace Views and Available Filters

View Name	x = View ID	Node Filter	Interface Filter
All Incidents	allIncidentsTableView Tip: To display the All Incidents view filtered by a specified node, see " Launch the All Incidents View Filtered by Node " on page 1534	Yes	No
Closed Key Incidents	closedKeyIncidentsTableView	Yes	No
Custom Incidents	customIncidentTableView	Yes	No
Custom Open Incidents	customOpenIncidentTableView	Yes	No
My Open Incidents	myIncidentTableView	Yes	No
Open Key Incidents	openKeyIncidentsTableView	Yes	No
Open Root Cause Incidents	openRCIncidentTableView	Yes	No
Service Impact Incidents	serviceImpactIncidentTableView	Yes	No
SNMP Traps	snmpTrapsIncidentTableView	Yes	No
Unassigned Open Key Incidents	unassignedKeyIncidentsTableView	Yes	No

The following are optional filter parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&nodegroup= <Name>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <div> <p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p> </div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&menus=
<true/false>&newWindow= <true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> Open any forms from the view

Attributes for Launched Views , continued

Attribute	Values
	<ul style="list-style-type: none"> Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> Open any forms from the view Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <div style="border: 1px solid black; padding: 5px; margin-top: 10px;"> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p> </div>

Launch the All Incidents View Filtered by Node

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showIncidents&object-identity= <Name>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showIncidents&object-identity=
<Name>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Filter the All Incidents View by Node Name

Attribute	Values
Name	<p>The <i>case-sensitive</i> Name attribute value of the Node to use as a filter for this view.</p> <div><p>Note: The Node Name is translated. If your team shares NNMi within multiple locales, use the <code>showView</code> command with <code>nodegroupid</code> or <code>nodegroupuuid</code>. See "Launch an Incident View" on page 1531 for more information.</p></div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showIncidents&object-identity=
<Name>&menus= <true/false>&newWindow= <true/false>&readonly=
<true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are</p>

Attributes for Launched Views , continued

Attribute	Values
	<p>hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Launch a Topology Maps Workspace View

The URL required for each one is unique.

Tip: This technique launches views independent of the NNMi console. When using this URL method, do not launch the view into a browser window where the NNMi console is currently running. The view automatically updates every 30 seconds. This is useful if your network operation center (NOC) continuously displays a map of the most important nodes. See ["Configure Maps" on page 549](#). (If you use the Mozilla Firefox browser and are prompted to click Continue before the map appears, see [Configure Mozilla Firefox Timeout Interval](#).)

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

[Click here to show the example of a URL that opens the Node Group Overview map \(cmd=showNodeGroupOverview\).](#)

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroupOverview`


Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroupOverview&menus= <true/false>&newWindow= <true/false>&readOnly= <true/false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.
newWindow	true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view. false = Display the view within the current browser window (if not specified, the default is false).

Attributes for Launched Views , continued

Attribute	Values
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back to the originating external application.</p>

[Click here to show the example of a URL that opens the **Network Overview** map \(cmd=showNetworkOverview\).](#)

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNetworkOverview`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showNetworkOverview&menus=
<true|false>&newWindow= <true|false>&readonly= <true|false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.
newWindow	true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view. false = Display the view within the current browser window (if not specified, the default is false).
readonly	true = Prevents the user from doing either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object) false = Enables the user to do either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object)
envattrs	Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).

Attributes for Launched Views , continued

Attribute	Values
	<p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Click [here](#) to show the example of a URL that opens the **Networking Infrastructure Devices** node group map (cmd=showView).

See quick reference ["W3C Rules for URLs" on page 1522](#).

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype=
Node&nodegroup= Networking+Infrastructure+Devices
```


Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&objtype=
Node&nodegroup= Networking+Infrastructure+Devices&menus= <true|false>&newWindow=
<true|false>&readonly= <true|false>&readonlygroupselector=
<true|false>&envattrs= <name1= value>;<name2= value>
```


Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to true and <code>readonlygroupselector</code> is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
readonlygroupselector	<p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to true and <code>readonlygroupselector</code> is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from selecting a Node Group.</p> <p>Note: When <code>readonlygroupselector</code> is set to true, the Node Group filter selection box appears disabled.</p> <p>false = Enables the user to select a Node Group.</p>

Attributes for Launched Views , continued

Attribute	Values
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back to the originating external application.</p> </div>

Click [here](#) to show the example of a URL that opens the **Routers** node group map (cmd=showNodeGroup&name=Routers).

http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name= Routers


Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name=
Routers&menus= <true|false>&newWindow= <true|false>&readonly=
<true|false>&readonlygroupselector= <true|false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<div> <p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to <code>true</code> and <code>readonlygroupselector</code> is set to <code>false</code>, users are able to change the Node Group filter.</p> </div> <p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
readonlygroupselector	<div> <p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to <code>true</code> and <code>readonlygroupselector</code> is set to <code>false</code>, users are able to change the Node Group filter.</p> </div> <p>true = Prevents the user from selecting a Node Group.</p>

Attributes for Launched Views , continued

Attribute	Values
	<p>Note: When <code>readonlygroupselector</code> is set to <code>true</code>, the Node Group filter selection box appears disabled.</p> <p><code>false</code> = Enables the user to select a Node Group.</p>
<code>envattrs</code>	<p>Use Environment Attributes (<code>envattrs</code>) to pass <code><name=value></code> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (<code>node25</code>) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (<code>envattrs</code>) <code><name=value></code> pairs from NNMi, and pass them back to the originating external application.</p>

Click [here](#) to show the example of a URL that opens the **Switches** node group map (`cmd=showNodeGroup&name=Switches`).

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name= Switches`


Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name=
Switches&menus= <true|false>&newWindow= <true|false>&readonly=
<true|false>&readonlygroupselector= <true|false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<div> <p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to <code>true</code> and <code>readonlygroupselector</code> is set to <code>false</code>, users are able to change the Node Group filter.</p> </div> <p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)

Attributes for Launched Views , continued

Attribute	Values
readonlygroupselector	<p>Caution: The readonly setting overrides the readonlygroupselector setting. This means that when readonly is set to true and readonlygroupselector is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from selecting a Node Group.</p> <p>Note: When readonlygroupselector is set to true, the Node Group filter selection box appears disabled.</p> <p>false = Enables the user to select a Node Group.</p>
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back to the originating external application.</p>

Launch a Monitoring Workspace View

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView & view = <x>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Monitoring Workspace Views and Available Filters

View Name	x = View ID	Node Filter	Interface Filter
Non-Normal Node Sensors	nonNormalNodeSensorTableView	Yes	No
Non-Normal Physical Sensors	nonNormalPhysSensorTableView	Yes	No
Non-Normal Chassis	nonNormalChassisTableView	No	No
Non-Normal Cards	nonNormalCardTableView	No	No
Non-Normal Interfaces	nonNormalInterfaceTableView	Yes	Yes
Non-Normal Nodes	nonNormalNodeTableView	Yes	No
Non-Normal SNMP Agents	nonNormalSnmpAgentsTableView	No	No
Not Responding Addresses	notRespondingIPAddressTableView	Yes	Yes
Interface Performance	interfacePerformanceTableView	Yes	Yes
Card Redundancy Groups	cardRedundancyGroupsTableView	No	No
Router Redundancy Groups	routerRedundancyGroupsStatusTableView	No	No
Node Groups	nodeGroupsStatusTableView	No	No
Custom Node Collections	customPollerNodeCollectionsTableView	No	No
Custom Polled Instances	customPollerPolledInstancesTableView	No	No

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&nodegroup=
<Name>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&ifgroup=
<Name>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <div><p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p></div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

Filter by Interface Group (launched Interface and IP Address views)

Attribute	Values
ifgroup	<p>The <i>case-sensitive</i> Name attribute value of the Interface Group to use as a filter for this view.</p> <div><p>Note: The Interface Group name is translated. If your team shares NNMi within multiple locales, use ifgroupid or ifgroupuuid.</p></div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>

Filter by Interface Group (launched Interface and IP Address views), continued

Attribute	Values
ifgroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
ifgroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&menus=
<true/false>&newWindow= <true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	Use Environment Attributes (envattrs) to pass <name=value> pairs from an

Attributes for Launched Views , continued

Attribute	Values
	<p><i>external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Launch a Troubleshooting Workspace View

There are four types of views in the Troubleshooting workspace. The URL syntax required for each one is unique.

Tip: This technique launches views independent of the NNMi console. When using this URL method, do not launch the view into a browser window where the NNMi console is currently running. The view automatically updates every 30 seconds. This is useful if your network operation center (NOC) continuously displays a map of the most important nodes. See ["Configure Maps" on page 549](#). (If you use the Mozilla Firefox browser and are prompted to click Continue before the map appears, see [Configure Mozilla Firefox Timeout Interval](#).)

Click [here](#) to show examples of URLs that open a **Layer 2 Neighbor View** (cmd=showLayer2Neighbors).

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer2Neighbors
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer2Neighbors&nodename= <x>&hops= <#>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Layer 2 Neighbor View Attributes

Attribute	Value
nodename	The source node's DNS hostname (full or short) or IP address. If you use this attribute, NNMi tries to match the string you provide by following this procedure: <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.
hops	1 - 9

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer2Neighbors&menus=  
<true|false>&newWindow= <true|false>&readonly= <true|false>&envattrs= <name1=  
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.

Attributes for Launched Views , continued

Attribute	Values
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <div style="border: 1px solid black; padding: 5px; margin-top: 10px;"> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p> </div>

Click here to show examples of URLs that open a **Layer 3 Neighbor View** (cmd=showLayer3Neighbors).

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


`http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer3Neighbors`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer3Neighbors&nodename= <x>&hops= <#>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Layer 3 Neighbor View Attributes

Attribute	Value
nodename	The source node's DNS hostname (full or short) or IP address. If you use this attribute, NNMi tries to match the string you provide by following this procedure: <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.
hops	1 - 9
menus	true = Show the menus and window toolbar in the form. If not specified, the default is true. false = Hide the menus and window toolbar in the view.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showLayer3Neighbors&menus=
<true|false>&newWindow= <true|false>&readOnly= <true|false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs from an external application to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <div style="border: 1px solid black; padding: 5px; margin-top: 10px;"> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back to the originating external application.</p> </div>

Click [here](#) to show examples of URLs that open a **Path View** (cmd=showPath).

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


`http://<serverName>:<portNumber>/nnm/launch?cmd= showPath`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showPath&src= <x>&dest= <y>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Note: (NNMi Advanced) Path View works only with IPv4 addresses. The NNMi Advanced IPv6 address values are not valid choices for Path View. Any devices in your network that are configured with IPv6 addresses cannot be displayed on Path View maps.

Path View Attributes

Attribute	Value
src	<p>The source node's DNS hostname (full or short) or IP address.</p> <p>NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.
dest	<p>The destination node's DNS hostname (full or short) or IP address.</p> <p>NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.

The following are optional parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showPath&menus=
<true|false>&newWindow= <true|false>&readonly= <true|false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <div> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <name=value> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p> </div>


Click [here](#) to show examples of URLs that open a **Node Group Map View** (cmd=showNodeGroup).

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name= <x>`

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Node Group Map View Attributes

Attribute	Value
name	<p>The <i>case-sensitive</i> Name attribute value from the Node Group form.</p> <div>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
objid	<p>The id is the Unique Object Identifier (unique per object type in the NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>NNMi displays the id attribute value on the object form's Registration tab.</p>
objuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>NNMi displays the uuid attribute value on the object form's Registration tab.</p>

The following are optional parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showNodeGroup&name= <x>&menus= <true|false>&newWindow= <true|false>&readonly= <true|false>&readonlygroupselector= <true|false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes

in the documentation.

Attributes for Launched Views

Attribute	Values
menus	<p>true = Show the view's button bar. If not specified, the default is true.</p> <p>false = Hide the view's button bar to save space in the view.</p>
newWindow	<p>true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view.</p> <p>false = Display the view within the current browser window (if not specified, the default is false).</p>
readonly	<p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to true and <code>readonlygroupselector</code> is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from doing either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) <p>false = Enables the user to do either of the following:</p> <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
readonlygroupselector	<p>Caution: The <code>readonly</code> setting overrides the <code>readonlygroupselector</code> setting. This means that when <code>readonly</code> is set to true and <code>readonlygroupselector</code> is set to false, users are able to change the Node Group filter.</p> <p>true = Prevents the user from selecting a Node Group.</p> <p>Note: When <code>readonlygroupselector</code> is set to true, the Node Group filter selection box appears disabled.</p> <p>false = Enables the user to select a Node Group.</p>
envattrs	Use Environment Attributes (<code>envattrs</code>) to pass <code><name=value></code> pairs

Attributes for Launched Views , continued

Attribute	Values
	<p><i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype=Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <div>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <name=value> pairs from NNMi, and pass them back to the originating external application.</div>

Launch an Inventory Workspace View

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Inventory Workspace Views and Available Filters

View Name	x = View ID	Node Filter	Interface Filter
Nodes	allNodesTableView	Yes	No
Interfaces	allInterfacesTableView	Yes	Yes
IP Addresses	allIPAddressTableView	Yes	Yes
IP Subnets	allIPSubnetsTableView	No	No
VLANs	allVlansTableView	No	No
Cards	allCardsTableView	No	No
Ports	allPortsTableView	No	No
Nodes by Management Server	nodesByNNMiManagementServerTableView	No	No
Custom Nodes	customNodeTableView	Yes	No
Custom Interfaces	customInterfaceTableView	Yes	Yes
Custom IP Addresses	customIPAddressTableView	Yes	Yes
MIB Variables	mibVariablesTableView	No	No
Card Redundancy Groups	allCardRedundancyGroupsTableView	No	No
Router Redundancy Groups	routerRedundancyGroupsTableView	No	No
Node Groups	nodeGroupsTableView	No	No
Interface Groups	interfaceGroupsTableView	No	No

The following are optional filter parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&nodegroup= <Name>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&interfacegroup= <Name>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

Filter by Interface Group (launched Interface and IP Address views)

Attribute	Values
ifgroup	<p>The <i>case-sensitive</i> Name attribute value of the Interface Group to use as a filter for this view.</p> <p>Note: The Interface Group name is translated. If your team shares NNMi within multiple locales, use ifgroupid or ifgroupuuid.</p> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
ifgroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
ifgroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value,</p>

Filter by Interface Group (launched Interface and IP Address views), continued

Attribute	Values
	use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.

The following are optional parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&menus=
<true/false>&newWindow= <true/false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.
newWindow	true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view. false = Display the view within the current browser window (if not specified, the default is false).
readonly	true = Prevents the user from doing either of the following: <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object) false = Enables the user to do either of the following: <ul style="list-style-type: none"> • Open any forms from the view • Manipulate any objects in the view (for example, delete an object)
envattrs	Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program). For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows: <code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code>

Attributes for Launched Views , continued

Attribute	Values
	Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back <i>to the originating external application</i> .

Launch a Management Mode Workspace View

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.


`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Management Mode Workspace Views

View Name	x = View ID	Node Filter	Interface Filter
Unmanaged ¹ Nodes	unManagedNodeTableView	Yes	No
Unmanaged ² Interfaces	unManagedInterfaceTableView	Yes	Yes
Unmanaged ³ IP Addresses	unManagedIPAddressTableView	Yes	Yes
Unmanaged ⁴ Chassis	unManagedChassisTableView	Yes	No
Unmanaged ⁵ Cards	unManagedCardTableView	Yes	No
Unmanaged ⁶ Node Sensors	unManagedNodeSensorTableView	Yes	No
Unmanaged ⁷ Physical Sensors	unManagedPysSensorTableView	Yes	No
Scheduled Node Outages	scheduledNodeOutageTableView	Yes	No

The following are optional filter parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&nodegroup= <Name>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&ifgroup= <Name>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <div> <p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p> <p>If the Name value includes space characters, consider replacing the space</p> </div>

¹Indicates the Management Mode is "Not Managed" or "Out of Service".

²Indicates the Management Mode is "Not Managed" or "Out of Service".

³Indicates the Management Mode is "Not Managed" or "Out of Service".

⁴Indicates the Management Mode is "Not Managed" or "Out of Service".

⁵Indicates the Management Mode is "Not Managed" or "Out of Service".

⁶Indicates the Management Mode is "Not Managed" or "Out of Service".

⁷Indicates the Management Mode is "Not Managed" or "Out of Service".

**Filter by Node Group (launched Incident, Node, Interface, and IP Address views),
continued**

Attribute	Values
	character in your URL statement (see "W3C Rules for URLs" on page 1522).
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

Filter by Interface Group (launched Interface and IP Address views)

Attribute	Values
ifgroup	<p>The <i>case-sensitive</i> Name attribute value of the Interface Group to use as a filter for this view.</p> <div style="background-color: #f0f0f0; padding: 10px; margin: 10px 0;"> <p>Note: The Interface Group name is translated. If your team shares NNMi within multiple locales, use ifgroupid or ifgroupuuid.</p> </div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
ifgroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
ifgroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Interface Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&menus= <true/false>&newWindow= = <true/false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.
newWindow	true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view. false = Display the view within the current browser window (if not specified, the default is false).
readonly	true = Prevents the user from doing either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object) false = Enables the user to do either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Launch a Configuration Workspace View

Configuration workspaces require that the user be assigned to the **Administrative** role.

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes

in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi view with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

Use the browser buttons to close the view.

Configuration Workspace Views

View Name	x = View ID
Node Groups	nodeGroupsTableView
Interface Groups	interfaceGroupsTableView
ifTypes	allIfTypesTableView
Device Profiles	allDeviceProfilesTableView
Loaded MIBs	loadedMibsTableView
MIB Expressions	mibExpressionsTableView
RAMS Servers	ramsServerTableView

The following are optional parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showView&view= <x>&menus= <true/false>&newWindow= <true/false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Views

Attribute	Values
menus	true = Show the view's button bar. If not specified, the default is true. false = Hide the view's button bar to save space in the view.
newWindow	true = Display the view in a new browser window. This new window does not display the browser-specific menu bars. The browser-specific menu bars are hidden to provide the maximum amount of room for the requested view. false = Display the view within the current browser window (if not specified, the default is false).
readonly	true = Prevents the user from doing either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object) false = Enables the user to do either of the following: <ul style="list-style-type: none">• Open any forms from the view• Manipulate any objects in the view (for example, delete an object)
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Launch a Form (showForm)

To launch a particular form, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=showForm...`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Launch a form to see information about a particular node, interface, address, subnet, or incident. In the URL string, you must include one or more attributes that enable NNMi to find a specific object. If more than one object meets the criteria, NNMi opens the first one found. When designating more than one attribute, separate each with a semicolon character.

["Launch a Node Form" below](#)

["Launch an Interface Form" on page 1573](#)

["Launch an IP Address Form" on page 1575](#)

["Launch a Subnet Form" on page 1576](#)

["Launch an Incident Form" on page 1578](#)

["Launch a Node Group Form" on page 1580](#)

["Launch a Configuration Form" on page 1582](#)

Launch a Node Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Node&nodename= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Node&objattrs= name= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Node&objattrs= hostname= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Node&objattrs= snmpAgent.agentSettings.managementAddress= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Node&objattrs= systemName= <x>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

Node Form Attributes

Attribute	Values
nodename	<p>Provide the node's DNS hostname (full or short) or IP address.</p> <p>If you use this attribute, NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.
name	<p>The Name attribute value from the Node form.</p>

Node Form Attributes , continued

Attribute	Values
hostname	<p>The <i>case-sensitive</i> Hostname attribute value from the Node form of the discovered node must match what is entered here.</p> <p>NNMi follows a set of rules to dynamically generate the value stored in the NNMi database for each Node's Hostname. Click here for details.</p> <ul style="list-style-type: none"> • If the Node supports SNMP, NNMi requests the Hostname using the IP Address of the associated SNMP agent (the Management Address attribute value on the Node form). <p>When the NNMi administrator chooses Enable SNMP Address Rediscovery <input checked="" type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ▪ If the SNMP Agent does not respond, NNMi checks for another Management Address to request the Hostname, and the Hostname could change. ▪ If the SNMP Agent associated with the node changes, the Management Address and Hostname could change. <p>When the NNMi administrator disables Enable SNMP Address Rediscovery <input type="checkbox"/> in the Communication Configuration:</p> <ul style="list-style-type: none"> ▪ If the SNMP Agent does not respond, NNMi uses the previously gathered Management Address attribute value to request the Hostname. ▪ If the SNMP Agent associated with the node changes, NNMi uses the previously gathered Management Address attribute value to request the Hostname. <ul style="list-style-type: none"> • If the Node does not support SNMP, no Management Address is available. NNMi requests a Hostname starting with the lowest IP Address associated with the node (a Discovery Seed value or an IP address value gathered from a neighboring device). NNMi uses the first Hostname provided. The Hostname might change during a future discovery cycle. <div style="background-color: #f0f0f0; padding: 10px; margin-top: 10px;"> <p>Note: NNMi administrators can use NNMi property file settings to change the way NNMi determines Hostname values:</p> <ul style="list-style-type: none"> • <code>nms-topology.properties</code> file settings: If DNS is the source of the Node's Hostname, there are three choices. By default NNMi uses the exact Hostname </div>

Node Form Attributes , continued



Attribute	Values
	<p>from your network configuration. It is possible to change NNMi behavior to convert Hostnames to all uppercase or all lowercase. See the "Modifying NNMi Normalization Properties" section of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.</p> <ul style="list-style-type: none"> nms-disco.properties file settings: The Hostname is either requested from the Node's lowest loopback interface IP address that resolves to a Hostname or requested from the Node's designated Management Address (SNMP agent address). With either choice, when no IP address resolves to a Hostname, the IP address itself becomes the Hostname. See the "Maintaining NNMi" chapter of the <i>HP Network Node Manager i Software Deployment Reference</i>, which is available at: http://h20230.www2.hp.com/selfsolve/manuals.
snmpAgent.agentSettings.managementAddress	The Management Address attribute value from the SNMP Agent form of the agent assigned to the specified node. The value is an IP address.
systemName	System Name attribute value from the Node form, General tab .

The following are optional filter parameters:

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=Node&nodename= <x>&menus= <true/false>&envattrs= <name1= value>;<name2= value>`

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	<p>true = Show the view menus and the  Close button. If not specified, the default is true.</p> <p>false = Hide the view menus and the  Close button to save space in the view.</p>
envattrs	<p>Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to</p>

Attributes for Launched Forms , continued

Attribute	Values
	<p>preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <div><p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back to the originating external application.</p></div>

Launch an Interface Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Interface&objattrs= hostedOn.hostname= <x>;name= <y>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Interface&objattrs= hostedOn.hostname= <x>;ifName= <y>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Interface&objattrs= hostedOn.hostname= <x>;ifAlias= <y>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Interface&objattrs= hostedOn.hostname= <x>;ifIndex= <y>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

Interface Form Attributes



Attribute	Values
hostedOn.hostname	The <i>case-sensitive</i> Hostname of the Node in which the interface resides. This is the Hostname attribute value from the associated Node form .
name	The Name attribute value from the Interface form .
ifName	The IfName attribute value from the Interface form.
ifAlias	The IfAlias attribute value from the Interface form.
ifIndex	The IfIndex attribute value from the Interface form.

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
Interface&objattrs= hostedOn.hostname= <x>;name= <y>&menus=
<true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	<p>true = Show the view menus and the  Close button. If not specified, the default is true.</p> <p>false = Hide the view menus and the  Close button to save space in the view.</p>
envattrs	<p>Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p>

Attributes for Launched Forms , continued

Attribute	Values
	<p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back to the originating external application.</p>

Launch an IP Address Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= IPAddress&objattrs= value= <y>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

IP Address Form Attributes



Attribute	Values
value	The Address attribute value from the IP Address form .

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
IPAddress&objattrs= value= <y>&menus= <true/false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	true = Show the view menus and the  Close button. If not specified, the default is true. false = Hide the view menus and the  Close button to save space in the view.
envattrs	Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program). For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows: <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <name=value> pairs from NNMi, and pass them back <i>to the originating external application</i> .

Launch a Subnet Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
IPSubnet&objattrs= name= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
IPSubnet&objattrs= prefix= <x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
IPSubnet&objattrs= prefix= <x>;prefixLength= <y>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

IP Subnet Form Attributes



Attribute	Values
name	The <i>case-sensitive</i> Name attribute value from the IP Subnet form .
prefix	The Prefix attribute value from the IP Subnet form .
prefixLength	The Prefix Length attribute value from the IP Subnet form .

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
IPSubnet&objattrs= name= <x>&menus= <true/false>&envattrs= <name1=
value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	true = Show the view menus and the  Close button. If not specified, the default is true. false = Hide the view menus and the  Close button to save space in the view.
envattrs	<p>Use Environment Attributes (envattrs) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <div>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</div>

Launch an Incident Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Incident&objid= <x>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= Incident&objuuid= <x>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

Individual incident objects must be identified by their *database unique identifiers*.

Incident Attributes



Attribute	Values
objid	The Unique Object Identifier (unique per object type in the NNMi database). NNMi displays the <code>id</code> attribute value on the object form's Registration tab.
objuuid	The Universally Unique Object Identifier (unique across all databases). NNMi displays the <code>uuid</code> attribute value on the object form's Registration tab.

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&showForm&objtype=
Incident&objid= <x>&menus= <true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	true = Show the view menus and the  Close button. If not specified, the default is true. false = Hide the view menus and the  Close button to save space in the view.
envattrs	Use Environment Attributes (<code>envattrs</code>) to pass <code><name=value></code> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program). For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:

Attributes for Launched Forms , continued

Attribute	Values
	<p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back to the originating external application.</p>

Launch a Node Group Form

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= NodeGroup&name= <y>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= NodeGroup&nodegroupid= <y>`

`http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype= NodeGroup&nodegroupuuid= <y>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`


`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))


`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.

- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

Node Group Form Attributes



Attribute	Values
name	<p>The <i>case-sensitive</i> Name attribute value from the Node Group form.</p> <div> <p>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</p> </div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique per object type in the NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

The following are optional filter parameters:

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showForm&objtype=
NodeGroup&name= <y>&menus= <true/false>&envattrs= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	<p>true = Show the view menus and the  Close button. If not specified, the default is true.</p> <p>false = Hide the view menus and the  Close button to save space in the view.</p>
envattrs	Use Environment Attributes (envattrs) to pass <name=value> pairs <i>from an external</i>

Attributes for Launched Forms , continued

Attribute	Values
	<p><i>application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <pre>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattrs= com.my.sessionId= 123;com.my.objectName= node25</pre> <div>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattrs) <code><name=value></code> pairs from NNMi, and pass them back <i>to the originating external application</i>.</div>

Launch a Configuration Form

Configuration forms require that the user be assigned to the **Administrative** role.

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

```
http://<serverName>:<portNumber>/nnm/launch?cmd= showConfigForm&name= <y>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.



`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Note: If you are using Mozilla Firefox, [click here for more information](#).

Due to the Mozilla Firefox security implementation, launching an NNMi form with a URL has the following limitations:

- The  Close button does not work.
- The File → Close menu item does not work.
- The  Save and Close button saves data, but does not close the window.
- The File → Save and Close menu item saves data, but does not close the window.

Use the browser buttons to close the form.

Configuration Form Attributes


Attribute	Values
name	<p>The name attribute value specifies which form:</p> <ul style="list-style-type: none">• customcorrelation = the Custom Correlation Configuration• communication = the Communication Configuration form• custompoller = the Custom Poller Configuration form• discovery = the Discovery Configuration form• globalnetworkmanagement = the Global Network Management form• monitoring = the Monitoring Configuration form• incident = the Incident Configuration form• status = the Status Configuration form• trap = the Trap Forwarding Configuration form• ui = the User Interface Configuration form

The following are optional filter parameters:


```
http://<serverName>:<portNumber>/nnm/launch?cmd= showConfigForm&name= <x>&menus=  
<true/false>&envattr= <name1= value>;<name2= value>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Attributes for Launched Forms

Attribute	Values
menus	true = Show the view menus and the  Close button. If not specified, the default is true.

Attributes for Launched Forms , continued

Attribute	Values
	false = Hide the view menus and the  Close button to save space in the view.
envattr	<p>Use Environment Attributes (envattr) to pass <i><name=value></i> pairs <i>from an external application</i> to NNMi. Environment Attributes are session-specific and stored in memory (not in the NNMi database). The name-value pairs can be any arbitrary string (as required by the external program).</p> <p>For example, let's assume that NNMi was launched from an application that wants to preserve a session ID (123) and object attribute (node25) as follows:</p> <p><code>http://<yourServerName>/nnm?cmd= showView&objtype= Node&envattr=com.my.sessionId= 123;com.my.objectName= node25</code></p> <p>Note: See "Pass Environment Attributes" on page 1525 for information about how to retrieve these Environment Attributes (envattr) <i><name=value></i> pairs from NNMi, and pass them back <i>to the originating external application</i>.</p>

Launch Menu Items (runTool)

To execute a Launch Action requesting something from NNMi:

`http://<serverName>:<portNumber>/nnm/launch?cmd=showMenuItem&key=<MenuItemKey>[&nodename=<hostname or IP_address>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To execute a Launch Action requesting a script, application, or tool from your environment (not NNMi):

`http://<serverName>:<portNumber>/<application>?<yourURLparameter1>=${<attribute>}&<yourURLparameter2>=${<attribute>}`

Note: To extend the NNMi environment with additional applications, you must deploy them

into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number

Provide quick access to NNMi menu items wherever your team needs them:

["Actions: Execute a Launch Action" on page 1598](#)

["Launch the Actions: Communication Configuration Command" below](#)

["Launch the Actions: Configuration Poll Command" on the next page](#)

["Launch the Actions: Line Graph \(showLineGraph\)" on page 1587](#)

["Launch the Actions: Monitoring Settings Command" on page 1590](#)

["Launch the Actions: Ping Command" on page 1594](#)

["Launch the Actions: Status Details Command \(for Node Groups\)" on page 1595](#)

["Launch the Actions: Status Poll Command" on page 1596](#)

["Launch the Actions: Trace Route Command" on page 1598](#)

["Launch the File: Sign-Out Command" on page 1601](#)

["Launch the Tools: MIB Browser \(showMibBrowser\)" on page 1599](#)

["Launch the Tools: NNMi Status Command" on page 1600](#)

["Launch the Tools: Sign-In/Out Audit Log Command" on page 1601](#)

Launch the Actions: Communication Configuration Command

This URL is equivalent to the **Actions** → **Communication Settings** command in the console.

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To launch a window that reports the current ICMP and SNMP configuration for a node, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=commconf`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

After you specify a node, the real-time results of the ICMP and SNMP configuration report appear.

To launch the real-time results of the ICMP and SNMP configuration report, use the following URL:

http://<

serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=commconf&nodename=<x>

http://<

serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=commconf&IPAddress=<x>

http://<

serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=commconf&Interface=<x>

http://<

serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=commconf&snmpAgent=<x>

Communication Configuration Command Attributes

Attribute	Values
nodename	<p>The node's DNS hostname (full or short) or IP address.</p> <p>If you use this attribute, NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.

Related Topics:

["Troubleshooting Communication Settings" on page 187](#)

Launch the Actions: Configuration Poll Command

This URL is equivalent to the **Actions** → **Polling** → **Configuration Poll** command in the console.

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To launch a window that reports the current configuration for a node, use the following URL:

http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=configurationpoll

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

After you specify a node, the real-time results of the node's configuration appear.

To launch the real-time results of a node's configuration, use the following URL:

```
http://<
serverName
>:<portNumber>/nnm/launch?cmd=runTool&tool=configurationpoll&nodename=<x>
```

Configuration Poll Command Attributes

Attribute	Values
nodename	<p>The node's DNS hostname (full or short) or IP address.</p> <p>If you use this attribute, NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.

Related Topics:

[Verify Device Configuration Details](#)

Launch the Actions: Line Graph (showLineGraph)

Use the showLineGraph URL to launch a Line Graph that displays real-time SNMP data about a selected object. See ["Configure SNMP Line Graph Actions" on page 1477](#).

Note: If you are displaying graphs for NNMi objects, the node or interface for which you want to graph information must support SNMPv1, SNMPv2c, or SNMPv3.

Use the showLineGraph syntax in a URL when you want to do any of the following:

- Display a Line Graph in an application other than NNMi.
- Display a Line Graph outside of an application and add it to your Favorites browser list.

To launch a Line Graph with the `showLineGraph` syntax, use the following URL:

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

`http://<serverName>:<portNumber>/nnm/launch?cmd=showLineGraph [parameter list]`

`http://<serverName>:<portNumber>/nnm/launch?cmd=showLineGraph
&init=<x>&objtype=<x> &maxlines=<x> &maxtimerange=<x> &defaultsecs=
<x>&faststart=<true/false>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Line Graph Parameters

Parameter	Description
<code>&init</code>	Use to define the lines you want displayed in the graph: <ul style="list-style-type: none">• <code>instancetype</code> - Use to specify which instances of the SNMP MIB object to display.• One of the following for each line:<ul style="list-style-type: none">■ <code>oid</code> - Use to specify the SNMP MIB object identifier value of each instance.■ <code>expr</code> - Use to specify the name of a MIB Expression that will be used for gathering the values on the Line Graph.• <code>label</code> - Use to specify the label to be used in the legend that describes each line on the graph.
<code>&objtype</code>	Use to specify the Object Type.

Line Graph Parameters, continued

Parameter	Description
	<p>For a Node Object Type, this value must be <code>\${snmpAgent.id}</code>. For an Interface Object Type, this value must be <code>\${hostedOn.snmpAgent.id}</code></p> <p>Note: If you want to provide a Line Graph for a specified node, use the ID value for the node's SNMP Agent. NNMi displays the ID attribute value on the SNMP Agent form's Registration tab.</p>
<code>&maxlines</code>	Use to specify the number of lines that NNMi should initially display on the Line Graph. To use the default value specified in the User Interface Configuration, omit this parameter.
<code>&maxtimerange</code>	Use to specify the number of hours for the Maximum Time Range in which the data in the Line Graph should be retained. After the Maximum Time Range number is reached, NNMi discards the oldest data point sets so that it can display the most recent data for the time range specified.
<code>&defaultsecs</code>	Use to specify the Polling Interval in which the graph data should be collected. To use the default value specified in the User Interface Configuration, omit this parameter.
<code>&faststart</code>	<p>Use to specify whether to increase the initial Polling Interval so that the initial data appears more quickly on the graph. Possible values are <code>true</code> or <code>false</code>.</p> <p>When you specify <code>true</code> for this option, NNMi increases the initial Polling Interval and then gradually decreases the Polling Interval until it reaches the Polling Interval configured for the graph.</p> <p>When you specify <code>false</code>, NNMi uses the Polling Interval set for the graph.</p>
<code>&defaultfixedvertical</code>	<p>Used to specify whether to lock the Y-axis. Possible values are <code>true</code> or <code>false</code>.</p> <p>When you specify <code>true</code>, the Y-axis remains fixed at the minimum and maximum values for the current set of data regardless of the time segment selected. This means NNMi does not automatically re-adjust the Y-axis to match the data values for the selected time segment.</p> <p>When you specify <code>false</code>, NNMi automatically adjusts the Y-axis to match the data values for the selected time segment.</p>
<code>&ylabel</code>	Use to specify the label to be used for the Y-axis of the Line Graph.
<code>more...</code>	HP Network Node Manager i Software Smart Plug-ins (iSPIs) might provide more attributes to customize the line graph. See the

Line Graph Parameters, continued

Parameter	Description
	documentation for the NNM iSPIs installed in your network environment.

Launch the Actions: Monitoring Settings Command

This URL is equivalent to the **Actions** → **Monitoring Settings** command in the console.

Launch the real-time results of the Monitoring configuration report. You must specify the target object.

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

(*NNMi Advanced*) If the Global Network Management feature is enabled and you are signed into a Global Manager:

- Node managed by the Global Manager = **Actions** → **Configuration Details** → **Monitoring Settings** opens a report, provided by the Global Manager (NNMi management server).
- Node managed by a Regional Manager = **Actions** → **Configuration Details** → **Monitoring Settings** accesses that Regional Manager (NNMi management server) and requests the report.

Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the "Configuring Single Sign-On for Global Network Management" section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

To launch a window that displays a current Monitoring Settings report about a Node (SNMP Agent), use the following URL:

<http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=SnmpAgent&nodename=<x>>

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Monitoring Configuration Command Node Report Attributes

Attribute	Values
nodename	<p>The node's DNS hostname (full or short) or IP address.</p> <p>If you use this attribute, NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.

To launch a window that displays a current Monitoring configuration report about an Interface, use one of the following URLs:

NNMi displays the report for the first matching Interface found. Provide one or more attributes to ensure a unique match. See "[Launch an Interface Form](#)" on page 1573 for more information about each available attribute.

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=Interface&objattrs=hostedOn.hostname=<x>;name=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=Interface&objattrs=hostedOn.hostname=<x>;ifName=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=Interface&objattrs=hostedOn.hostname=<x>;ifAlias=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=Interface&objattrs=hostedOn.hostname=<x>;ifIndex=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Interface Form Attributes

Attribute	Values
hostedOn.hostname	The Hostname of the Node in which the interface resides. This is the Hostname attribute value from the associated Node form .
name	The Name attribute value from the Interface form .

Interface Form Attributes , continued

Attribute	Values
ifName	The ifName attribute value from the Interface form.
ifAlias	The ifAlias attribute value from the Interface form.
ifIndex	The ifIndex attribute value from the Interface form.

To launch a window that displays a current Monitoring Settings report about an IP Address, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=IPAddress&objattrs=value=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

IP Address Form Attributes

Attribute	Values
value	The Address attribute value from the IP Address form .

To launch a window that displays a current Monitoring Settings report about an Card, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=Card&objattrs=value=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Card Form Attributes

Attribute	Values
value	The card attribute value from the Card form .

To launch a window that displays a current Monitoring Settings report about a Router Redundancy Member (Instance), use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=RouterRedundancyInstance&objid=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Monitoring Configuration Command Router Redundancy Member Report Attributes

Attribute	Values
objid	The Unique Object Identifier (unique per object type in the NNMi database). This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.
objuuid	The Universally Unique Object Identifier (unique across all databases). This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.

To launch a window that displays a current Monitoring Settings report about a Tracked Object, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=TrackedObject&objid=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Monitoring Configuration Command Tracked Object Report Attributes

Attribute	Values
objid	The Unique Object Identifier (unique per object type in the NNMi database). This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.
objuuid	The Universally Unique Object Identifier (unique across all databases). This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.

To launch a window that displays a current Monitoring Settings report about a Node Sensor or Physical Sensor, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=NodeSensor&objid=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=NodeSensor&objuuid=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=PhysicalSensor&objid=<x>
```

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=monitoringconf&objtype=PhysicalSensor&objuuid=<x>
```

Note: If you copy/paste this URL, remove the spaces that were added for line-ending purposes in the documentation.

Monitoring Configuration Command Node Sensor or Physical Sensor Report Attributes

Attribute	Values
objid	The Unique Object Identifier (unique per object type in the NNMi database). NNMi displays the <code>id</code> attribute value on the Node form's Registration tab.
objuuid	The Universally Unique Object Identifier (unique across all databases). NNMi displays the <code>uuid</code> attribute value on the Node form's Registration tab.

Related Topics:

["Verify the Monitoring Settings" on page 474](#)

Launch the Actions: Ping Command

This URL is equivalent to the **Actions** → **Ping (from server)** command in the console.

To launch a window that requests you to enter a node name, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=ping`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

After you specify a node, the real-time results of the ping command appear.

To launch the real-time results of the ping command, use the following URL:

```
http://<
serverName
>:<
portNumber
>/nnm/launch?cmd=runTool&tool=ping&timeoutSecs=<x>&numPings=<x>&nodename=<x>
```

(*NNMi Advanced*) If the Global Network Management feature is enabled and you are signed into a Global Manager:

- Node managed by the Global Manager = **Actions** → **Ping** issues an ICMP request from the Global Manager (NNMi management server).
- Node managed by a Regional Manager = **Actions** → **Ping** accesses that Regional Manager (NNMi management server) and issues the ICMP request.

Note: You must sign into that Regional Manager unless your network environment enables Single Sign-On (SSO) to that Regional Manager through the Global Manager. For more information, see the “Configuring Single Sign-On for Global Network Management” section in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>.

Ping Command Attributes

Attribute	Values
nodename	A DNS-resolvable hostname or IP address. The nodename value is passed literally to the underlying command you specify. The nodename value (in this case) is not required to correlate with anything in the NNM database.
timeoutSecs	Amount of time NNMi waits before abandoning a ping request.
numPings	Maximum number of retries.

Related Topics:

[Test Node Access \(Ping\)](#)

Launch the Actions: Status Details Command (for Node Groups)

This URL is equivalent to the **Actions** → **Status Details** command in the console.

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To launch a real-time calculation of current status for a specified Node Group, use the following URL:

```
http://<
serverName
>:<portNumber>/nnm/launch?cmd=runTool&tool=nodegroupstatus&nodegroup=<x>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the “Working with Certificates for NNMi” chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:

```
http://h20230.www2.hp.com/selfsolve/manuals.
```

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

After you specify a node group, the real-time results of the node group's status calculation appear.

To launch a real-time calculation of current status for a specified Node Group and display a report of the information gathered, use the following URL:

```
http://<
serverName
>:<portNumber>/nnm/launch?cmd=runTool&tool=nodegroupstatus&nodegroup=<x>
```

Filter by Node Group (launched Incident, Node, Interface, and IP Address views)

Attribute	Values
nodegroup	<p>The <i>case-sensitive</i> Name attribute value of the Node Group to use as a filter for this view.</p> <div>Note: The Node Group name is translated. If your team shares NNMi within multiple locales, use nodegroupid or nodegroupuuid.</div> <p>If the Name value includes space characters, consider replacing the space character in your URL statement (see "W3C Rules for URLs" on page 1522).</p>
nodegroupid	<p>The id is the Unique Object Identifier (unique across the entire NNMi database). Provide the id of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the id attribute value for each object instance.</p>
nodegroupuuid	<p>The uuid is the Universally Unique Object Identifier (unique across all databases). Provide the uuid of the Node Group to use as a filter for this view.</p> <p>This attribute value is not visible on any form within the console. To find this value, use the nnmconfigexport.ovpl command-line tool to export an XML file that includes the uuid attribute value for each object instance.</p>

Related Topics:

[Check Status Details for a Node Group](#)

Launch the Actions: Status Poll Command

This URL is equivalent to the **Actions** → **Polling** → **Status Poll** command in the console.

NNMi calculates the status of devices each time additional information is gathered. You can instruct NNMi to gather real-time data for all the information that NNMi uses to calculate Status for the specified Node. A window displays with a report about which information was gathered. The NNMi administrator determines the list of information gathered by establishing Monitoring configuration settings. See ["Monitoring Network Health" on page 378](#) for more information.

Note: To see the resulting Node status, see [Verify Current Status of a Device](#).

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To launch a window that reports the current status for a node, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=statuspoll`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals`.

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

After you specify a node, the real-time results of the node's status appear.

To launch the real-time results of a node's status, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=statuspoll&nodename=<x>`

Status Poll Command Attributes

Attribute	Values
nodename	<p>The node's DNS hostname (full or short) or IP address.</p> <p>If you use this attribute, NNMi tries to match the string you provide by following this procedure:</p> <ul style="list-style-type: none">• Check the value of the Hostname (<i>case-sensitive</i>) on the Node form.• Check the values in the Address column of the table on the Node form, Addresses tab,• Check the value of the System Name field on the in the Node form, General tab.• Check the value in the Name field on the Node form.

Related Topics:

[Verify Current Status of a Device](#)

Launch the Actions: Trace Route Command

This URL is equivalent to the **Actions → Trace Route (from server)** command in the console.

To launch a window that requests you to enter a node name, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=traceroute`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help → Documentation Library → Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

After you specify a node, the real-time results of the trace route command appear.

To launch the real-time results of the trace route command, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=traceroute&nodename=<x>`

Trace Route Command Attributes

Attribute	Values
nodename	A DNS-resolvable hostname or IP address. The nodename value is passed literally to the underlying command you specify. The nodename value (in this case) is not required to correlate with anything in the NNM database.

Related topics:

[Find the Route \(traceroute\)](#)

Actions: Execute a Launch Action

The showMenuItem command launches a Menu Item that has been configured as a Launch Action in NNMi.

To execute a Launch Action requesting something from NNMi:

`http://<serverName>:<portNumber>/nnm/launch?cmd=showMenuItem&key=<MenuItemKey>[&nodename=<hostname or IP_address>`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

To execute a Launch Action requesting a script, application, or tool from your environment (not NNMi):

`http://<serverName>:<portNumber>/<application>?<yourURLparameter1>=${<attribute>}&<yourURLparameter2>=${<attribute>}`

Note: To extend the NNMi environment with additional applications, you must deploy them into a separate web-server or application-server on the same or different physical server from where the NNMi web-server or application-server is installed. See the *HP Network Node Manager Developer Toolkit* for more information.

<serverName> = the appropriate fully-qualified domain name

<portNumber> = the appropriate port number

Tip: After you specify a *case-sensitive* Hostname, the real-time results of the Launch Action appear.

Trace Route Command Attributes

Attribute	Values
MenuItemKey	The Unique Key used for the Menu Item configuration. See "Configure Menu Item Basic Details" on page 1456 for more information.
nodename	<i>Optional.</i> A DNS-resolvable hostname or IP address indicating the node on which the action should be executed.

See ["Configure Launch Actions" on page 1462](#) for information about creating a Launch Action.

Launch the Tools: MIB Browser (showMibBrowser)

This URL is equivalent to the **Tools** → **MIB Browser** command in the console.

To launch the MIB Browser, use the following URL:

```
http://<
serverName
>:<
portNumber>/nnm/launch?cmd=showMibBrowser&node=<name/address>&oid=<name/number>
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Related Topics:

[Run SNMP Walk Commands](#)

[Run SNMP Set Commands](#)

Launch the Tools: NNMi Status Command

This URL is equivalent to the **Tools** → **NNMi Status** command in the console.

To launch a report of the current status of all NNMi processes and services, use the following URL:

```
http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=nnmstatus
```

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

For a quick-reference list of all URL choices for launching NNMi, see **Help** → **Documentation Library** → **Integrate NNMi Elsewhere with URLs**. The Integrate NNMi Elsewhere with URLs page also contains a link to a list of sample URLs that you can copy/paste as a starting point.

Related Topics:

["Verify that NNMi Processes Are Running" on page 87](#)

[Check the Status of NNMi](#)

["NNMi Processes and Services" on page 86](#)

Launch the File: Sign-Out Command

This URL is equivalent to the **File** → **Sign Out** command in the console.

To provide a link that issues a sign-out command, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=signOut`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

This closes the user session and frees up any memory associated with the session.

Related Topics:

["Sign Out from the Console" on page 658](#)

Launch the Tools: Sign-In/Out Audit Log Command

This URL is equivalent to the **Tools** → **Sign In/Out Audit Log** command in the console.

To launch a window that reports the current configuration for a node, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=runTool&tool=signinaudit`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
`http://h20230.www2.hp.com/selfsolve/manuals.`

`<serverName>` = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

`<portNumber>` = the NNMi HTTP port number

NNMi logs the history of sign-in and sign-out activity for each user since the NNMi management server was last restarted.

Related Topics:

["Audit NNMi User Sign-In and Sign-Out Activity" on page 663](#)

Confirm that NNMi Is Running (cmd=isRunning)

To launch a message reporting whether NNMi is currently running, use the following URL:

`http://<serverName>:<portNumber>/nnm/launch?cmd=isRunning`

Note: If the NNMi Web server uses the https protocol, use https instead of http. See the "Working with Certificates for NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

<serverName> = the fully-qualified domain name of the NNMi management server (values allowed here are determined by the *Enable URL Redirect* setting in User Interface Configuration, see ["Configuring the NNMi User Interface" on page 524](#))

<portNumber> = the NNMi HTTP port number

One of the following messages appears:

- NNMi is running.
- A browser error message that the URL is unreachable.

Chapter 17: Maintaining NNMi

As an NNMi administrator, you will want to perform the following tasks when maintaining NNMi configurations and data.

- "Track Your NNMi Licenses" on the next page
- "Extend a Licensed Capacity" on page 1605
- "Export and Import Configuration Settings" on page 1610
- "Back Up and Restore NNMi" on page 1628
- "Archive and Delete Incidents" on page 1631

Check NNMi Health

As an NNMi administrator, you can check the status and overall health of NNMi using any of the following:

- Use **Help** → **System Information** to view NNMi and NNMi component health including NNMi's overall health status, information, and any issues related to the following:
 - Disk usage see [System Information: Health tab](#)
 - Global Network Management (*NNMi Advanced*) see [System Information: Server tab](#)
 - Memory see [System Information: Server tab](#) and [System Information: Health tab](#)
 - NNMi database see [System Information: Database tab](#)
 - SNMP requests and queues see [System Information: Custom Poller tab](#) and [System Information: Health tab](#)
 - System resources see [System Information: Health tab](#)

[Click here](#) for more information about NNMi's overall health status.

NNMi uses the following statuses when monitoring its health (see [System Information: Health tab](#) for more information.):

NNMi Overall Health Status

Status	Description
Warning	Indicates performance issues that are not significantly affecting NNMi.
Minor	Indicates problems that might result in out of date data. For example, an NNMi component, such as State Poller might be out of synch because it is operating outside of expected ranges.

NNMi Overall Health Status, continued

Status	Description
Major	Indicates problems that are significantly affecting the NNMi management server's operations, but are not yet critical. Major Status usually indicates that some action is required. For example, a trap threshold is reached.
Critical	Indicates NNMi is not functioning. For example, NNMi is out of memory, all database connections are lost, or a major NNMi component has failed.

- Use the **Tools** → **NNMi Self-Monitoring Graphs** to view information about NNMi components and their usage. NNMi Self-Monitoring Graphs include:
 - SNMP Trap Pipeline Rate
 - SNMP Trap Forwarding Rate
 - Discovery Progress
 - SNMP Requests

Tip: Use the SNMP Requests Graph to tune Communication Configuration settings.

- NNMi administrators can use the command line on any NNMi management server to generate a report about NNMi health. See the nnmhealth.ovpl Reference Page for more information.

Track Your NNMi Licenses

To assist you in tracking your NNMi licenses, NNMi displays a status message at the bottom of the main console whenever the number of nodes in the database reaches your licensed capacity limit (compared to the number of nodes discovered). Install additional licenses (for 50 node increments or more) to extend the limit.

To see a report of the current number of discovered nodes and the current NNMi licensed capacity limit, access **View Licensing Information** from either of the following locations:

- **Help** → **About HP Network Node Manager i software**
- **Help** → **System Information** on the **Product** tab.

There are five categories of NNMi Software Licenses. Within each category, there are three types (instant-on, temporary, or permanent):

- HP Network Node Manager i
- HP Network Node Manager i Advanced
- HP Network Node Manager i Premium

- HP Network Node Manager i Ultimate
- HP Network Node Manager Developer Toolkit (licenses for developers - SDK licenses).

When tracking license information, note the following:

- NNMi discovers and manages nodes up to the NNMi licensed capacity limit.
- If the number of discovered nodes reaches or exceeds the licensed capacity limit, no new nodes are discovered unless one of the following occurs:
 - Install a license extension, see ["Extend a Licensed Capacity" below](#).
 - Review your configuration settings and limit NNMi discovery to only the important nodes in your network environment (see ["Discovering Your Network" on page 194](#)). Then, delete nodes and let NNMi rediscovery reset the managed inventory of nodes (see ["Delete Nodes" on page 1635](#)).
- NNMi generates Incidents under the following circumstances:
 - The number of discovered nodes exceeds the current licensed capacity limit.
 - An Instant-On or Temporary license expires.
 - HP Network Node Manager i Software Smart Plug-ins (iSPIs) are purchased and installed on the NNMi management server. However, the NNMi licensed capacity limit does not match the NNM iSPI licensed capacity limit. See ["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515](#) for more information about the NNM iSPIs.

Related Topics:

["Extend a Licensed Capacity" below](#)

["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515](#)

["Integrations with HP and Third-Party Products" on page 1519](#)

Extend a Licensed Capacity

To extend the licensed capacity, purchase and install an additional NNMi, NNMi Advanced, NNMi Premium, or NNMi Ultimate license.

Contact your HP Sales Representative or your Authorized Hewlett-Packard Reseller for information about the NNMi licensing structure, and to learn how to add license tiers for enterprise installations. To obtain additional license keys, go to the HP License Key Delivery Service:
<https://webware.hp.com/welcome.asp>

For more information, see the *HP Network Node Manager i Software Interactive Installation Guide* and nnmlicense.ovpl.

Note: The licensed capacity count is cumulative for each licensed product (across all installed

license keys for that licensed product).

After you purchase a software license, install the NNMi Software License key using one of the following methods:

- **From the command line:**

- a. At the command prompt for the NNMi management server, type the following (see the [nnmlicense.ovpl](#) Reference Page and ["About Environment Variables" on page 86](#) for more information):

For *<product>*, use one of the following: NNMi, iSPI-NET, iSPI-Points, or PerfSPI

- **Windows:**

```
%NnmInstallDir%\bin\nnmlicense.ovpl <product> -f <license_file>
```

- **Linux:**

```
$NnmInstallDir/bin/nnmlicense.ovpl <product> -f <license_file>
```

- b. NNMi automatically completes the installation.

- **Using Autopass and your HP Order Number (not possible behind a firewall):**

- a. Open the Autopass user interface. At the command line for the NNMi management server, type the following (see the [nnmlicense.ovpl](#) Reference Page and ["About Environment Variables" on page 86](#) for more information):

For *<product>*, use one of the following: NNMi, iSPI-NET, iSPI-Points, or PerfSPI

- **Windows:**

```
%NnmInstallDir%\bin\nnmlicense.ovpl <product> -gui
```

- **Linux:**

```
$NnmInstallDir/bin/nnmlicense.ovpl <product> -gui
```

- b. On the left side of the Autopass window, click **License Management**.
- c. Click **Install License Key**.
- d. Click **Retrieve/Install License Key**.
- e. Enter your HP Order Number and follow the Autopass prompts to complete the License key retrieval process.
- f. Autopass automatically completes the installation.

Related Topics:

["Track Your NNMi Licenses" on page 1604](#)

["Purchase HP Network Node Manager i Smart Plug-ins and More" on page 1515](#)

["Integrations with HP and Third-Party Products" on page 1519](#)

["Delete Nodes" on page 1635](#)

Resolve Inconsistencies between State and Status

At times, differences between State and Status values might occur. These differences generally indicate the system is busy processing large volumes of data, perhaps due to a significant configuration change or network outage.

Note the following:

- NNMi updates State before Status. A delay in Status updates might be due in part to the processing required for root cause analysis performed by the Causal Engine.
- As NNMi completes this processing, the consistency of State and Status is restored.
- Associated incidents might also be delayed during this time.
- Status updates can run behind by the amount of time listed for *Delay Processing Input* in the **System Information** dialog's **Causal Engine** tab. See [System Information: Causal Engine tab](#).

If the consistency of State and Status is not restored, NNMi enables you to correct the State or Status inconsistencies for each of the following:

Resolve State or Status Inconsistencies on a Single Node

To correct either an unexpected State or inconsistent Status value on a node:

1. Navigate to the node view or map of interest and right-click the node
2. Select **Polling** → **Configuration Poll**
3. Select **Polling** → **Status Poll**

To correct inconsistent Status values on a node for which the State value is correct:

1. Navigate to the nodes view or map of interest and right-click the node
2. Select **Polling** → **Status Poll**

Resolve State or Status Inconsistencies on Multiple Nodes

To correct State or Status inconsistencies on multiple nodes, use the [nnmnode rediscover.ovpl](#) command.

The [nnmnode rediscover.ovpl](#) command, when used with the `-fullsync` option, enables you to re-synchronize the nodes specified.

The re-synchronization process performs the following for each node:

- Rediscovered the node.
- Reloads and refreshes the monitoring configuration for the node.
- Reanalyzes State and Status for the node.

To re-synchronize a single node:

```
nnmnodediscover.ovpl -node hostname -fullsync
```

To re-synchronize all nodes in a file:

```
nnmnodediscover.ovpl -file filename -fullsync
```

Tip: To quickly generate the file needed for this command-line tool, consider using the `nnmnodegroup.ovpl` command-line tool. See the [nnmnodegroup.ovpl](#) Reference Page.

To re-synchronize all the nodes on an NNMi management server:

```
nnmnodediscover.ovpl -all -fullsync
```

If a large number of nodes (for example, thousands) are being re-synchronized, it is recommended that you re-synchronize these nodes during off-peak periods, when possible.

NNMi must remain running until the re-synchronization is complete. If NNMi is stopped before the re-synchronization is complete, run the [nnmnodediscover.ovpl](#) command again and allow the re-synchronization to complete.

For more information, see [nnmnodediscover.ovpl](#).


If you have a Global Network Management environment, also see "[Node Synchronization Issues](#)" on page 125

Recalculate Management Mode for Out of Sync Physical Components

NNMi enables an NNMi administrators to recalculate the Management Mode of any physical components that have a **Direct Management Mode** of **Inherited**.

Use this option if you notice that the **Direct Management Mode** of a physical component is **Inherited**, but its **Management Mode** does not match the **Management Mode** of the object from which the Management Mode was inherited. For example, the Management Mode of a card might be inherited from the chassis on which it resides.

The following diagram illustrates the possible parent child relationships that might occur between a node and its physical components (chassis or card).



As an NNMi administrator, you can recalculate the **Management Mode** from a selected node, chassis or card:

1. Navigate to the **Inventory** view that contains the parent object.
2. Right-click the object and select **Management Mode>Recalculate Out of Sync Physical Components**.

Starting with the node, NNMi then recalculates each child object's Management Mode based on the Management Mode settings in the node hierarchy. See [How NNMi Assigns the Management Mode to an Object](#) for more information.

Note:

- The Management Mode of all physical components in the node hierarchy is recalculated, no matter which physical component is selected. For example, if you select a card object, NNMi recalculates the Management Mode for the node and any chassis and cards in the node hierarchy.

- The Management Mode of any Physical Sensor object that resides on a physical component in the node hierarchy is also recalculated. See [Physical Sensor View](#) for more information.

Export and Import Configuration Settings

See the [nnmconfigexport.ovpl](#) and [nnmconfigimport.ovpl](#) Reference Pages for more information, including the complete list of the command line arguments for each command.

The choices that you make when exporting NNMi configuration settings determine how that configuration information can be used. For example:

- Export a copy of the existing NNMi configuration settings before you try experimenting with a new idea. You can use that exported file to restore your configuration settings if your experiment does not work the way you thought it would work.
- Export the NNMi configuration settings from a server in your test environment. Import those configuration settings onto the NNMi management server that your team will use to manage your network environment.
- (*NNMi Advanced - Global Network Management feature*) Export configuration settings to share configuration settings among the Regional Managers in your network environment (for example, Node Group definitions and Trap Forward to Global Managers settings).

Carefully review the following topics to make an informed choice:

["Export/Import Behavior and Dependencies" below](#)

["Export a Snapshot of Your Configuration Settings" on page 1616](#)

["Import Configuration Files to Restore Previous Settings" on page 1618](#)

["Transfer Configuration Settings to Another NNMi Management Server" on page 1620](#)

["Troubleshooting Imports of Configuration Files" on page 1623](#)

Export/Import Behavior and Dependencies

Your configuration settings can be exported to make a copy, and then imported onto the same NNMi management server or another NNMi management server. The locale setting on the NNMi management server at the time of Export must match the locale setting on the NNMi management server at the time of Import.

You need to understand the behavior and dependencies (see the [table](#)). The choices that you make when exporting NNMi configuration settings determine how that configuration information can be used:

Replaces all. Export files with this behavior make changes to the NNMi database when Imported ([click here for more information](#)).

- NNMi replaces all object instances with matching key identifiers (see "[Troubleshooting Imports of Configuration Files](#)" on page 1623 for information about key identifiers).
- NNMi adds all object instances with key identifiers that do not exist in the NNMi database
- ***NNMi deletes all existing object instances with key identifiers that do not match any in the exported file.***

Incremental. Export files with this behavior make changes to the NNMi database when Imported ([click here for more information](#)).

- NNMi updates all object instances with matching key identifiers (see "[Troubleshooting Imports of Configuration Files](#)" on page 1623 for information about key identifiers).

Caution: NNMi also overwrites the values of any codes associated with these object instances (for example, incident family).

- NNMi adds all object instances with key identifiers that do not exist in the NNMi database.
- NNMi does not touch existing object instances with key identifiers that do not match any in the exported file.

Incremental (subset). Export files with this behavior include configuration changes that were made by one Author. Export files with this behavior make changes to the NNMi database when Imported ([click here for more information](#)).

- NNMi updates all object instances with matching key identifiers (see "[Troubleshooting Imports of Configuration Files](#)" on page 1623 for information about key identifiers).

Caution: NNMi also overwrites the values of any codes associated with these object instances (for example, incident family).

- NNMi adds all object instances with key identifiers that do not exist in the NNMi database.
- NNMi does not touch existing object instances with key identifiers that do not match any in the exported file.

Export/Import Behavior and Dependencies Among Configuration Areas

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
Author *	-c author	Incremental	No dependencies. Import requires one Export file (author.xml).

Export/Import Behavior and Dependencies Among Configuration Areas, continued

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
			* Not a workspace, but an important data object.
	-c author -a < <i>authorUniqueKey</i> >	Incremental (subset)	No dependencies. Import requires one Export file (author.xml).
Communication	-c comm	Replaces all	No dependencies. Import requires one Export file (comm.xml). Caution: SNMPv3 configuration settings cannot be exported because SNMPv3 data is encrypted based on the NNMi encryption key (generated during NNMi installation). Therefore, the SNMPv3 encrypted data cannot be imported into another installed version of NNMi because the encryption key is different.
Custom Correlations	-c customCorrelation	Incremental	
	-c device -a < <i>authorUniqueKey</i> >	Incremental (subset)	The required Author information is embedded in the Export file.
Custom Poller	-c custpoll	Incremental	Import requires five Export files, and they must be imported in this order: (1) mibexpr.xml, (2) author.xml, (3) device.xml, (4) nodegroup.xml, and (5) custpoll.xml Note: When importing modifications to an existing Custom Poller Collection, NNMi sets the Active State for all associated Policies to Suspended .
Device Profiles	-c device	Incremental	Import requires two Export files, and they must be imported in this order: (1) author.xml and (2) device.xml

Export/Import Behavior and Dependencies Among Configuration Areas, continued

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
	-c device -a < <i>authorUniqueKey</i> >	Incremental (subset)	Import requires one Export file (device.xml). The required Author information is embedded in the Export file.
Discovery	-c disco	Replaces all	Import requires seven Export files, and they must be imported in this order: (1) comm.xml, (2) discoseed.xml, (3) iftype.xml, (4) author.xml, (5) device.xml, (6) ifgroup.xml, and (7) disco.xml
Discovery Seeds	-c discoseed	Incremental	Import requires three Export files, and they must be imported in this order: (1) comm.xml, (2) security.xml, and (3) discoseed.xml
Global Network Management			No export/import permitted at this time.
Icons and icon images	-c icons	Incremental	No dependencies. Import requires one Export file (icons.xml)
	-c icons -a < <i>authorUniqueKey</i> >	Incremental (subset)	No dependencies. Import requires one Export file (icons.xml)
Incident	-c incident	Incremental	Import requires seven Export files, and they must be imported in this order: (1) account.xml, (2) author.xml, (3) device.xml, (4) nodegroup.xml, (5) iftype.xml, (6) ifgroup.xml, and (7) incident.xml
	-c incident -a < <i>authorUniqueKey</i> >	Incremental (subset)	Import requires one Export file (incident.xml). The required Author information is embedded in the Export file.
Interface Groups	-c ifgroup	Incremental	Import requires five Export files, and they must be imported in this order: (1) iftype.xml, (2) author.xml, (3) device.xml, (4) nodegroup.xml, and (5)

Export/Import Behavior and Dependencies Among Configuration Areas, continued

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
			ifgroup.xml
ifTypes	-c iftype	Incremental	Interface Types. No dependencies. Import requires one Export file (iftype.xml).
Menus	-c menu	Incremental	Import requires two Export files, and they must be imported in this order: (1) author.xml and (2) menu.xml
	-c menu -a < <i>authorUniqueKey</i> >	Incremental (subset)	Import requires one Export file (menu.xml). The required Author information is embedded in the Export file.
Menu items (formally URL Actions)	-c menuitem (formally -c urlaction)	Incremental	Import requires four Export files, and they must be imported in this order: (1) author.xml, (2) menu.xml, (3) mibexpr.xml, and (4) menuitem.xml
	-c menuitem -a < <i>authorUniqueKey</i> > (formally -c urlaction -a < <i>authorUniqueKey</i> >)	Incremental (subset)	Import requires one Export file (menuitem.xml). The required Author information is embedded in the Export file.
MIB Expressions	-c mibexpr	Incremental	Import requires two Export files, and they must be imported in this order: (1) author.xml and (2) mibexpr.xml
	-c mibexpr -a < <i>authorUniqueKey</i> >	Incremental (subset)	Import requires one Export file (mibexpr.xml). The required Author information is embedded in the Export file.
MIB OID Types	-c mibtypes	Incremental	
Monitoring	-c monitoring	Replaces all	Import requires six Export files, and they must be imported in this order: (1) author.xml, (2) device.xml, (3)

Export/Import Behavior and Dependencies Among Configuration Areas, continued

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
			nodegroup.xml, (4) iftype.xml, (5) ifgroup.xml, and (6) monitoring.xml
Node Groups	-c nodegroup	Incremental	<p>Import requires three Export files, and they must be imported in this order:</p> <p>(1) author.xml, (2) device.xml, and (3) nodegroup.xml</p> <div> Caution: Island Node Groups are never exported. See "Island Node Groups" on page 375. </div>
Node Group Map Settings	-c ngmap	Incremental	<p>Import requires four Export files, and they must be imported in this order:</p> <p>(1) author.xml, (2) device.xml, (3) nodegroup.xml, and (4) ngmap.xml</p> <div> Note: Any time you save a map, NNMi deletes any previous node locations. Therefore, each export contains only the node locations that were last saved. </div>
RAMS Servers	-c rams	Incremental	<p>HP Router Analytics Management System data from the RAMS Servers view (does not include data from the Integration Module Configuration <i>HP RAMS MPLS WAN</i>). See "HP RAMS MPLS WAN Configuration (NNMi Advanced)" on page 1446 for more information.</p> <p>No dependencies. Import requires one Export file (rams.xml).</p>
Security Groups Tenants	-c security		Exports Security Groups and Tenants.
Security Group Mappings	-c securitymappings		Exports Security Group Mappings.

Export/Import Behavior and Dependencies Among Configuration Areas, continued

Configuration Workspace's View Name	Export Option	Import Behavior	Dependencies
Status	-c status	Replaces all	No dependencies. Import requires one Export file (status.xml). The imported status applies to all Node Groups in the database.
Traps	-c trap	Incremental	Import requires three Export files: (1) author.xml, (2) incident.xml, and (3) nodegroup.xml
	-c trap -a < authorUniqueKey >	Incremental (subset)	The required Author and Node Group information is embedded in the Export file.
User Accounts User Account Mappings User Groups NNMi Roles	-c account	Incremental	Exports User Accounts, NNMi Roles, User Groups, and User Account Mappings. This command gathers data from multiple Configuration workspace views. Import requires one Export file (account.xml). The data from all the Configuration workspace views is embedded in the Export file.
User Interface	-c ui	Incremental	No dependencies. Import requires one Export file (ui.xml).

Export a Snapshot of Your Configuration Settings

If you export your configuration settings before you begin making changes, you can easily "undo" your changes if you decide that you do not like the results.

To export a snapshot of your configuration settings:

1. Import behavior is determined when you generate the Export files. Make sure you understand your Import behavior choices before you begin. See ["Export/Import Behavior and Dependencies" on page 1610](#) (consider printing that topic for reference).

Caution: The locale setting on the NNMi management server at the time of Export must match the locale setting on the NNMi management server at the time of Import.

Otherwise, you risk losing data. Also, make sure that both NNMi management servers have the same NNMi version/patch number.

2. A user name and password are required with the export command:

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the `nnmsetcmduserpw.ovpl` command to specify the valid user name and password (instead of `-u` and `-p`). The credentials set using the `nnmsetcmduserpw.ovpl` command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

```
-u <NNMiadminUserName> -p <NNMiadminPassword>
```

3. Check whether the configuration settings you want to export have dependencies, see ["Export/Import Behavior and Dependencies" on page 1610](#).
 - If no dependencies, export only the configuration settings you are planning to change.
 - If yes, decide whether you need a copy of the dependencies (only if you plan to make changes to those configuration settings, as well). Then export all the required files.
4. At the command line of the NNMi management server, type the command to generate the required export files.

- To export all configuration settings, use the following command:

```
nnmconfigexport.ovpl -c -all -f <directory>
```

You can use `-x <file_prefix>` to provide a unique prefix to the set of exported files. For example, use today's date or a clue about the reason you needed the files:

```
nnmconfigexport.ovpl -c -all -f <directory> -x <file_prefix>
```

- To export specific configuration settings `<X>` from multiple configuration workspace views, separate each with a comma (see ["Export/Import Behavior and Dependencies" on page 1610](#) or the `nnmconfigexport.ovpl` Reference Pages for the list of choices):

```
nnmconfigexport.ovpl -c <X>, <X>, <X> -f <directory>
```

You can use `-x <file_prefix>` to provide a unique prefix to the set of exported files. For example, use today's date or a clue about the reason you needed the files:

```
nnmconfigexport.ovpl -c <X>, <X>, <X> -f <directory> -x <file_prefix>
```

- To export configuration settings that were created by a particular author (for Author, Device Profiles, Incident, or URL Actions), add the `-a <authorUniqueKey>` attribute to the command and provide the Unique Key.

Note: Only one author per `-a <authorUniqueKey>` export command is allowed.

Find the Unique Keys for all authors by exporting an `author.xml` file, then open the file in a text editor and locate the Key attribute values.

Find the Unique Key for a particular Author, in the NNMi console:

- i. Open one of these Configuration workspaces in the NNMi console: Device Profiles Configuration, Incidents, or URL Actions.
 - ii. Select an object created by the Author of interest.
 - iii. Display the Author form, and copy the value of the Unique Key attribute.
5. Verify that the required xml files are in the specified directory.

Caution: Do not edit the exported file before importing.

You are now ready to make configuration changes.

To undo your configuration setting changes, see ["Import Configuration Files to Restore Previous Settings" below](#).

Import Configuration Files to Restore Previous Settings

If you have a set of export files, you can change the Configuration settings on your NNMi management server to match the settings in the exported files.

Note: You can change the names of the exported files before importing. The import still works the same.

Caution: Do not edit the exported file before importing.

To import a previous snapshot of your configuration settings:

1. Import behavior is determined when you generate the Export files. Make sure your exported files were generated in a manner that meets your current needs. See ["Export/Import Behavior and Dependencies" on page 1610](#) (consider printing that topic for reference).

Caution: The locale setting on the NNMi management server at the time of Export must match the locale setting on the NNMi management server at the time of Import. Otherwise, you risk losing data. Also, make sure that both NNMi management servers have the same NNMi version/patch number.

2. A user name and password are required with the import command:

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of `-u` and `-p`). The credentials set using the `nnmsetcmduserpw.ovpl` command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

```
-u <NNMiadminUserName> -p <NNMiadminPassword>
```

3. Check whether the configuration settings you want to import have dependencies, see ["Export/Import Behavior and Dependencies" on page 1610](#).
 - If no dependencies, import only the configuration settings you are planning to change.
 - If yes, decide if you need a copy of the dependencies (only if you made changes to those configuration settings, as well). Then import all the required files.

4. At the command line of the NNMi management server, type the command to import a file:

```
nnmconfigimport.ovpl -f <filename>
```

When importing multiple XML files at once using `-f <directory>`, the NNMi `nnmconfigimport.ovpl` command takes care of ordering issues.

- To import all configuration settings, use the following command:

```
nnmconfigimport.ovpl -f <directory>
```

You can use `-x <file_prefix>` to specify a unique prefix for a set of files:

```
nnmconfigimport.ovpl -f <directory> -x <file_prefix>
```

- To import specific configuration settings from multiple configuration areas, create a directory that contains the set of files you want to import.

At the command line of the NNMi management server, type the appropriate command to import files:

```
nnmconfigimport.ovpl -f <directory>
```

You can use `-x <file_prefix>` to specify a unique prefix for a set of files:

```
nnmconfigimport.ovpl -f <directory> -x <filePrefix>
```

- To import configuration settings that were created by specific authors (for Author, Device Profiles, Incident, or URL Actions), create a directory that contains the set of files you want to import.

At the command line of the NNMi management server, type the appropriate command to import the files:

```
nmmconfigimport.ovpl -f <file>
```

```
nmmconfigimport.ovpl -f <directory>
```

You can use `-x <file_prefix>` to provide a unique prefix for a set of exported files:

```
nmmconfigimport.ovpl -f <directory> -x <filePrefix>
```

5. If you encounter problems, see ["Troubleshooting Imports of Configuration Files" on page 1623](#).

Additional import options for timeout or memory issues:

You can append the following options to any import command if you encounter problems:

Option	Description	Default Setting
<code>-timeout <seconds></code>	For larger data imports, you might encounter timeout issues. To increase the number of seconds that NNMi waits (per file) during an import, append the <code>-timeout</code> option to the end of your command line.	1800 seconds (minimum)
<code>-memory < megabytes ></code>	For larger data imports, you might encounter memory issues. To increase the number of megabytes allotted to memory during an import, append the <code>-memory</code> option to the end of your command line.	512 megabytes

6. After completing the import, open NNMi and verify your configuration settings.

Transfer Configuration Settings to Another NNMi Management Server

You can export configuration settings and import them onto another NNMi management server to save time.

Note: You can change the names of the exported files before importing. The import still works the same.

Caution: Do not edit the exported file before importing.

To move configuration settings to another NNMi management server:

1. Import behavior is determined when you generate the Export files. Make sure you understand your Import behavior choices before you begin. See ["Export/Import Behavior and Dependencies" on page 1610](#) (consider printing that topic for reference).

Caution: The locale setting on the NNMi management server at the time of Export must match the locale setting on the NNMi management server at the time of Import. Otherwise, you risk losing data. Also, make sure that both NNMi management servers have the same NNMi version/patch number.

2. A user name and password are required with the export command:

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the [nnmsetcmduserpw.ovpl](#) command to specify the valid user name and password (instead of -u and -p). The credentials set using the [nnmsetcmduserpw.ovpl](#) command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

```
-u <NNMiadminUserName> -p <NNMiadminPassword>
```

3. Check whether the configuration settings you want to export have dependencies, see ["Export/Import Behavior and Dependencies" on page 1610](#).
 - If no dependencies, export only the configuration settings you are planning to change.
 - If yes, decide if you need a copy of the dependencies (only if you plan to make changes to those configuration settings, as well). Then export all the required files.
4. At the command line of the NNMi management server export all configuration settings, type the appropriate command:

```
nnmconfigexport.ovpl -c -all -f <directory>
```

You can use -x <file_prefix> to provide a unique prefix to the set of exported files. For example, use today's date or a clue about the reason you needed the files:

```
nnmconfigexport.ovpl -c -all -f <directory> -x <file_prefix>
```

Note: You can change the names of the exported files before importing. The import still works the same.

5. Delete any files that you do not need.
6. To export configuration settings that were created by a particular author (for Author, Device Profiles, Incident, or URL Actions), repeat the export command for each configuration item modified by that author. Add the -a <authorUniqueKey> attribute to the command and provide the Unique Key.

Note: Only one author per `-a <authorUniqueKey>` export command is allowed.

```
nnmconfigimport.ovpl -a <authorUniqueKey> -f <directory>
```

You can use `-x <file_prefix>` to provide a unique prefix to the set of exported files. For example, use today's date or a clue about the reason you needed the files:

```
nnmconfigimport.ovpl -a <authorUniqueKey> -f <directory> -x <file_prefix>
```

Find the Unique Keys for all authors by exporting an author.xml file, then open the file in a text editor and locate the Key attribute values.

[Find the Unique Key for a particular Author, in the NNMi console:](#)

- a. Open one of these Configuration workspaces in the NNMi console: Device Profiles Configuration, Incidents, or URL Actions.
 - b. Select an object created by the Author of interest.
 - c. Display the Author form, and copy the value of the Unique Key attribute.
7. Verify that all required xml files are in the specified directory.

To import the configuration settings onto the other NNMi management server:

1. Import behavior is determined when you generate the Export files. Make sure you understand your Import behavior choices before you begin. See ["Export/Import Behavior and Dependencies" on page 1610](#) (consider printing that topic for reference).

Caution: The locale setting on the NNMi management server at the time of Export must match the locale setting on the NNMi management server at the time of Import. Otherwise, you risk losing data. Also, make sure that both NNMi management servers have the same NNMi version/patch number.

2. A user name and password are required with the export command:

If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the `nnmsetcmduserpw.ovpl` command to specify the valid user name and password (instead of `-u` and `-p`). The credentials set using the `nnmsetcmduserpw.ovpl` command are valid for command execution by the same user. See ["Set Up Command Line Access to NNMi" on page 653](#) for more information.

```
-u <NNMiadminUserName> -p <NNMiadminPassword>
```

3. Verify that all required xml files are in the specified directory.
4. When importing multiple XML files at once using `-f <directory>`, the NNMi

`nnmconfigimport.ovpl` command takes care of ordering issues.

At the command line of the NNMi management server, type the appropriate command to import the configuration files that you gathered for transfer:

```
nnmconfigimport.ovpl -f <filename>
```

```
nnmconfigimport.ovpl -f <directory>
```

You can use `-x <file_prefix>` to specify a unique prefix for a set of files:

```
nnmconfigimport.ovpl -f <directory> -x <file_prefix>
```

5. If you encounter problems, see ["Troubleshooting Imports of Configuration Files" below](#).

Additional import options for timeout or memory issues:

You can append the following options to any import command if you encounter problems:

Option	Description	Default Setting
<code>-timeout <seconds></code>	For larger data imports, you might encounter timeout issues. To increase the number of seconds that NNMi waits (per file) during an import, append the <code>-timeout</code> option to the end of your command line.	1800 seconds (minimum)
<code>-memory < megabytes ></code>	For larger data imports, you might encounter memory issues. To increase the number of megabytes allotted to memory during an import, append the <code>-memory</code> option to the end of your command line.	512 megabytes

6. After completing the import, open NNMi and verify your configuration settings.

Troubleshooting Imports of Configuration Files

When importing incremental sets of configuration files, NNMi abandons the import if mismatched configuration objects are encountered. Each configuration object has a set of Unique Identifier values that must match for incremental updates, or must not match any existing data before NNMi adds the configuration object to the database, see tables below.

If you receive an error message while trying to import configuration information, use the information below to figure out how to use the error message to determine what to change before creating another export file (thus, solving the problem).

Note: You can change the names of the exported files before importing. The import still works the same.

Caution: Do not edit the exported file before importing.

Author Configuration Unique Identifiers

Configuration Item Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
Author = Author form	author = Unique Key attribute value	Yes	

Communication Configuration Unique Identifiers

Attribute Name = NNMi Console Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
CommunicationRegion = Communication Region form	uuid	No	<p>name = Name value</p> <p>ordering = Ordering value</p> <div> <p>Caution: SNMPv3 configuration settings cannot be exported because SNMPv3 data is encrypted based on the NNMi encryption key (generated during NNMi installation). Therefore, the SNMPv3 encrypted data cannot be imported into another installed version of NNMi because the encryption key is different.</p> </div>

Custom Correlation Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
CausalCorrelation = Causal Rule Form	uuid	No	
GeneralizedCorrelation = Correlation Rule Form	uuid	No	

Custom Poller Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
ComparisonMap = Comparison Map form	uuid	No	ordering = Ordering value
Policy = Custom Poller Policy form	uuid	No	The combination of these two:

Custom Poller Configuration Unique Identifiers, continued

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
			collection = Collection value ordering = Ordering value

Device Profile Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
DeviceCategory = Device Category form	key = Unique Key attribute	Yes	
DeviceFamily = Device Family form	key = Unique Key attribute	Yes	
DeviceProfile = Device Profile form	snmpObjectId = SNMP Object ID value	Yes	
DeviceVendor = Device Vendor form	key = Unique Key attribute	Yes	

Discovery Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
AutoDiscoveryRegion = Auto-Discovery Rule form	uuid	No	name = Name value ordering = Ordering value

Discovery Seed Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
DiscoverySeed = Discovery Seed form	host = Hostname (<i>not case-sensitive</i>) / IP Address value	Yes	

Incident Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
MgmtEventConfig = Management	uuid	No	name = Name value

Incident Configuration Unique Identifiers, continued

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
Event Configuration form			
SnmpTrapConfig = SNMP Trap Configuration form	uuid	No	iod = SNMP Object ID value name = Name value
PairwiseConfig = Pairwise Configuration form	uuid	No	name = Name value The combination of these two: firstIncidentName = First Incident Configuration value secondIncidentName = Second Incident Configuration value

Interface Groups Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
InterfaceGroup = Interface Group form	uuid	No	name = Name value

Interface Type Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
ifType	ifType attribute	Yes	

Menus Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
Menu = UI Configuration > Menus form	key = Unique Key attribute	Yes	

Menu Items Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
MenuItem = Menu Item form	key = Unique Key	Yes	

MIB Expressions Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
MibExpression = MIB Expression Form	key = Unique Key	Yes	

Monitoring Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
InterfaceSettings = Interface Settings form	uuid	No	ordering = Ordering value
NodeSettings = Node Settings form	uuid	No	ordering = Ordering value

Node Group Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
NodeGroup = Node Group form	uuid	No	name = Name value

Node Group Map Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
NodeGroupMapSettings = Node Group Map Settings Form	uuid	No	

RAMS Server Configuration Unique Identifiers (*NNMi Advanced, plus HP Route Analytics Management System (RAMS) for MPLS WAN*)

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
RamsServer = RAMS Server Form	uuid	No	

Security Groups Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
SecurityGroup = Security Group Form	uuid	No	

Security Group Mappings Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
UserToSecurityGroup = Security Group Mappings Form	uuid	No	

Node Group Status Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
NodeGroupStatusSettings = Node Group Status Settings Form	uuid	No	

User Interface Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
UserInterfaceConfiguration = User Interface Configuration Form	uuid	No	

User Accounts and Roles Configuration Unique Identifiers

Attribute Name	Primary Identifier	Editable Attribute?	Other Key Attributes that must be unique
Account = User Account form	uuid	No	name = Name value
UserGroup = User Group Form	name	yes	
UserGroupMember = User Account Mapping Form	uuid	no	

Back Up and Restore NNMi

As an NNMi administrator, develop a plan for NNMi backups.

For the most complete information, see the "NNMi Backup and Restore Tools" chapter in the *HP Network Node Manager i Software Deployment Reference*, which is available at: <http://h20230.www2.hp.com/selfsolve/manuals>. See also [nnmbbackup.ovpl](#), [nnmrestore.ovpl](#), [nnmbbackupembdb.ovpl](#), and [nnmrestoreembdb.ovpl](#) (**Help** → **Documentation Library** → **Reference Pages**, in the Administrator Commands category).

Use the [nnmbbackup.ovpl](#) and [nnmrestore.ovpl](#) command line tools to do any of the following:

- Back up the NNMi management server and restore data to the same machine.
- Back up the NNMi management server and use the [nnmrestore.ovpl](#) command to place the backed up configuration records and database records onto another NNMi management server. For example, moving NNMi to another NNMi management server due to a hardware failure on the original server.

Note: Both machines must have the same type of operating system and NNMi version and patch level. To move NNMi configuration settings from one computer to another computer that is running a different type of operating system, see "Export and Import Configuration Settings".

After you restore NNMi on the second NNMi management server, uninstall NNMi from the original NNMi management server. See the *HP Network Node Manager i Software Deployment Reference* for more information.

- Back up the NNMi management server as a safeguard before upgrading the operating system on the server.
- Back up the NNMi management server as a safeguard before updating to a newer version of NNMi.

Note: The back up and restore data might include data from any HP Network Node Manager i Software Smart Plug-ins (iSPIs) installed in your network environment. Check the documentation that came with each NNM iSPI for details.

Use the [nnmbbackupembdb.ovpl](#) and [nnmrestoreembdb.ovpl](#) tools to do the following:

- Back up the NNMi management server embedded database and restore data to the same machine.
- Back up the NNMi embedded database and use the [nnmrestoreembdb.ovpl](#) command to place the backed up database records onto another NNMi management server.

The following table summarizes backup and restore tools capabilities:

Command	Backup Embedded DB?	Backup Oracle DB?	Backup other configuration?	Online Backups?	Offline backups?
nnmbbackup.ovpl	Yes	No	Yes	Yes	Yes

Command	Backup Embedded DB?	Backup Oracle DB?	Backup other configuration?	Online Backups?	Offline backups?
nnmbackupembddb.ovpl	Yes	No	No	No	Yes

Note the following:

- If you use [nnmbackup.ovpl](#) for backup, then use [nnmrestore.ovpl](#) to restore the data.
- If you use [nnmbackupembddb.ovpl](#) for backup, then use [nnmrestoreembddb.ovpl](#) to restore the data.

Before you begin a backup, ensure you have adequate storage space for the backup copy. Verify that you have enough space to store the contents of the directories listed in the following table.

Note: You can compress the files after backup.

See also ["About Environment Variables" on page 86](#).

NNMi Directories

Operating System	Data	Default Location
Windows Server 2008 R2	Configuration Files	%NmInstallDir%
	Configuration Data	%NmDataDir%
	Embedded NNMi Database Storage	%NmDataDir%\shared\nnm\databases\Postgres If you chose the Oracle database instead of the embedded NNMi database at install time, you must use the Oracle tools for backup in addition to nnmbackup.ovpl.
Linux	Configuration Files	\$NmInstallDir
	Configuration Data	\$NmDataDir
	Embedded NNMi Database Storage	\$NmDataDir/shared/nnm/databases/Postgres If you chose the Oracle database instead of the embedded NNMi database at install time, you must use the Oracle tools for backup in addition to nnmbackup.ovpl.

Related Topics

["Export and Import Configuration Settings" on page 1610](#)

["Archive and Delete Incidents" on the next page](#)

Archive and Delete Incidents

NNMi provides the following options for archiving and deleting incidents:

Auto-trim oldest SNMP trap incident feature

To keep NNMi performing at a high level, NNMi drops incoming SNMP traps (including syslog messages), regardless of life-cycle state, after storing a specific number of SNMP traps in its database. You can use the auto-trim oldest SNMP trap incidents feature to control the number of SNMP traps (and syslog messages) stored in the NNMi database and to retain important incoming SNMP traps. For more information, see the "Configuring the Auto-Trim Oldest SNMP Trap Incidents Feature" section of the "Maintaining NNMi" chapter in the *HP Network Node Manager i Software Deployment Reference*.

Note: NNMi trims only non-root cause SNMP Trap incidents.

Incident Logging

To ensure that all incidents are archived, use Incident Logging. When using Incident Logging, NNMi logs an incident as soon as it is persisted, even if it is subsequently deleted. If you use the auto-trim oldest SNMP trap incidents feature instead, some incidents might not be archived. For example, if an incident is deleted while Dampened between the specified auto-trim interval, NNMi keeps no record of that incident. For more information about Incident Logging, see ["Configure Incident Logging" on page 884](#).

The `nnmtrimincidents.ovpl` command

NNMi enables you to archive and remove incidents that you no longer want to track. For example, this feature is useful if you want to purge the database of incidents that are older than a specified time period or date. Use the `nnmtrimincidents.ovpl` command to create a comma-separated-values (CSV) file containing the history of incidents, and then trim the volume of incidents to manage the size of your database.

To archive and then delete incidents in NNMi, use the `nnmtrimincidents.ovpl` command. You can choose to only archive or only delete your incidents as described in the arguments table that follows.

Note: By default, NNMi trims incidents without archiving them. To archive incidents before deleting them, use the `-trimAndArchive` option as described in the following [nnmtrimincidents.ovpl Arguments table](#) or use [Incident Logging](#).

Tip: You can also configure NNMi to trim incidents automatically. See the "Reducing the Number of Stored SNMP Trap Incidents" section in the *HP Network Node Manager i Software Deployment Reference*, which is available at:
<http://h20230.www2.hp.com/selfsolve/manuals>.

When archiving and deleting incidents, for the best performance results, archive and delete your incidents frequently to keep the size of the NNMi database as small as possible.

SNMP traps are a subset of NNMi incidents (see `-origin` in the arguments table that follows). NNMi monitors the volume of SNMP traps that are stored in the NNMi database. The maximum allowed number of SNMP traps is 100,000. Note the following:

- After 90 percent of the maximum limit for SNMP traps is reached or exceeded, NNMi generates an incident with Severity set to Warning to notify you that NNMi is approaching the maximum limit.
- After 95 percent of the maximum limit for SNMP traps is reached or exceeded, NNMi generates an incident with Severity set to Major to notify you that NNMi is approaching the maximum limit. In addition, NNMi only accepts traps required for Causal Engine analysis until the number of SNMP traps within the database has been reduced using the `nnmtrimincidents.ovpl` command.
- After the maximum SNMP trap limit is reached or exceeded, NNMi generates an incident with Severity set to Critical. NNMi no longer accepts any SNMP traps until the number of SNMP traps within the database has been reduced using the `nnmtrimincidents.ovpl` command.

Use the `nnmtrimincidents.ovpl` command to archive and delete your incidents based on any of the attributes described in the following table. See the `nnmtrimincidents.ovpl` command for more information, including a complete list of arguments for this command.

Note: The archive's comma-separated-values (CSV) file cannot be used to import the incidents back into NNMi.

nnmtrimincidents.ovpl Arguments

Incident Attribute	Description
-archiveOnly	Specifies that you want to only archive incidents rather than archive and then delete them.
-trimOnly	Specifies that you want to only delete incidents rather than archive and then delete them. Note: By default, NNMi trims incidents without archiving them.
-trimAndArchive	Specifies that you want to archive incidents before deleting them.
-date	The date must be entered in the following ISO 8601 format: <code><yyyy-mm-dd>T<hh>:<mm>:<ss>[Z,<hh>:<mm>,<ss>,<hh>:<mm>]</code> ISO Date Format: <ul style="list-style-type: none"> • yyyy — Four-digit year

nnmtrimincidents.ovpl Arguments, continued

Incident Attribute	Description
	<ul style="list-style-type: none"> <i>mm</i> — Two-digit month <i>dd</i> — Two-digit day <i>hh</i> — Two digits representing the hour (00 through 23) <i>mm</i> — Two digits representing the minutes (00 through 59) <i>ss</i> — Two digits representing the seconds (00 through 59) +<i><hh>:<mm></i> — Local time zone which is the hours (<i><hh></i>) and minutes (<i><mm></i>) ahead of Coordinated Universal Time -<i><hh>:<mm></i> — Local time zone which is the hours (<i><hh></i>) and minutes (<i><mm></i>) behind Coordinated Universal Time <p>For example: 2007-11-05T08:15:30-5:00 corresponds to November 5, 2007, 8:15:30 am, Eastern Standard Time.</p> <p>Note: You must specify either a -age or a -date value.</p>
-age	<p>The age of the incident specified in number of hours, days, weeks, or months.</p> <p>Note: You must specify either a -age or a -date value.</p>
-family	<p>The incident Family. See Incident Form: General Tab for a list of possible Family values.</p>
-incr	<p>The increment value that helps determine the -age value. Supported increments include hours, days, weeks, and months. The default increment value is days.</p>
-path	<p>Specifies the archive file name, including the complete path. The default archive file name is (see "About Environment Variables" on page 86 for more information):</p> <p><i><date></i> is the date in yyyy-mm-dd format</p> <p><i><ms></i> is milliseconds</p> <p>Windows:</p> <p>%NnmDataDir%\tmp\incidentArchive.<date>.<ms>.csv.gz</p> <p>Linux:</p>

nnmtrimincidents.ovpl Arguments, continued

Incident Attribute	Description
	<p><code>\$NnmDataDir/tmp/incidentArchive.<date>.<ms>.csv.gz</code></p> <p>Note: Each time you generate an archive, NNMi appends it to an existing file with the same name, if any. Therefore, to ensure that all archive files are preserved, provide a unique archive file name each time you want to archive incidents.</p>
-lifecycle	<p><i>Optional:</i> Identifies where the incident is in the incident lifecycle. Possible values are Registered, InProgress, Completed, and Closed.</p> <p>See About the Incident Lifecycle for more information about Lifecycle State.</p>
-name	Identifies the name of the incident configuration.
-nature	<p><i>Optional:</i> Identifies the nature of the incident. Possible values are: Info, None, RootCause, SecondaryRootCause, ServiceImpact, Dedup_Stream_Correlation, Rate_Stream_Correlation, StreamCorrelation, and Symptom.</p> <p>See Using the Incident Form for more information.</p>
-origin	Identifies the Origin of the incident configuration. Possible values are: ManagementSoftware , ManuallyCreated , RemotelyGenerated , SNMPTrap , Syslog , and Other . See Incident Form: General Tab for more information.
-u	<p>The user name required to run this command. This user name must be a valid NNMi user name with a role of either Administrator or System.</p> <p>Note: The user name might be a Principal object stored in the NNMi database or might be from Lightweight Directory Access Protocol (LDAP) or X.509 Certificates such as Public Key Infrastructure (PKI) user authentication in your environment. See "Choose a Mode for NNMi Access" on page 570.</p>
-p	<p>The associated password for the user name specified by the -u attribute value.</p> <p>If you do not want to enter an NNMi User Name attribute value and an NNMi Password attribute value at the command line, you can use the nnmsetcmduserpw.ovpl command to specify the valid user name and password (instead of -u and -p). The credentials set using the nnmsetcmduserpw.ovpl command are valid for command execution by the same user. See "Set Up Command Line Access to NNMi" on page 653 for more information.</p>
-quiet	Use this argument when you want to trim incidents without requiring user

nnmtrimincidents.ovpl Arguments, continued

Incident Attribute	Description
	prompts and responses. (Status information appears.)
-sysobjectid	<p>The industry standard SNMP system object ID (RFC 1213, MIB-II sysObjectID value that identifies vendor/make/model of a device) assigned to the incident configuration.</p> <p>For SNMP Trap incidents, this value is obtained from the incoming SNMP trap. For Management Event incidents generated by NNMi, the system OID is assigned by NNMi.</p>

For example, delete all incidents with lifecycle equal to Closed and age equal to or greater than 1 month.

```
nnmtrimincidents.ovpl -age 1 -incr months -lifecycle Closed -u  
<NNMiadminUsername> -p <NNMiadminPassword>
```

You can also specify a batch size when archiving or deleting incidents. Specify the maximum number of incidents to delete at one time within a single database transaction. This number then determines how often you see a status message that the deletions are complete. Using the default value of 1,000 as an example, NNMi displays a status message after successfully deleting each 1,000 incidents.

Note: The default value of 1,000 was selected to maintain a balance between performance and the frequency of progress messages for the archive and delete operation. This default determines the maximum number of incidents archived and deleted at one time within a single database transaction.

Related Topics

["Back Up and Restore NNMi" on page 1628](#)

Delete Nodes

Tip: To configure NNMi to automatically delete unresponsive nodes, see ["Configure Whether to Delete Unresponsive Nodes" on page 233](#).

To ensure that NNMi never discovers a particular Node in the future, change the Communication Configuration settings, see ["Configuring Communication Protocol" on page 129](#).

Sometimes it is useful to delete Nodes. For example:

- Remove any nodes that are no longer being used in the network.
- Avoid reaching the NNMi license limit for number of managed Nodes by deleting less important Nodes.
- When non-SNMP addresses that had the same DNS hostname are changed to have separate DNS hostnames, NNMi must completely rediscover the non-SNMP nodes to correctly update the database objects (for example, node, interface, address, connection, and incidents).


Note: If you delete a Node with many interfaces and VLANs, you might see an error message indicating that the Node could not be deleted. This means the database was busy with discovery. Try again between discovery cycles.

If a deleted Node is one of your seeds, delete that seed from the Discovery Seeds table as well. See "[Delete Discovery Seeds](#)" on page 310.

To understand the results of deleting a Node, [click here for more information](#).

- NNMi cleans up the database by deleting the following objects:
 - Any objects associated with the deleted Node (for example, all of that node's interfaces and IP addresses).
 - Any related objects that are empty after deleting the Node (for example, subnets).
 - Any connections with only zero or one end points after deleting the Node.
 - The History of the Node object and all related objects.
- The time required for NNMi to finish deleting depends on the number of objects or related objects being deleted.
- During future discovery cycles, if the deleted Node meets the criteria for an Auto-Discovery Rule and appears in a monitored router's ARP cache, NNMi adds the Node back into the NNMi database during the next discovery cycle. To prevent this, create an Excluded IP Addresses filter for the addresses (see "[Configure an Excluded IP Addresses Filter](#)" on page 274).
- During future monitoring cycles, NNMi polls only objects currently in the database.
- Each Incident associated with the deleted Node is modified in the following ways, but not deleted from the NNMi database:
 - The **Status** attribute changes to **Closed**.
 - The **Correlation Notes** indicate the deletion of the associated node, interface, or address.
 - The **RCA State** attribute changes to **FALSE**.

Note: Incidents generated from SNMP traps (received from the deleted Node) appear in the Incident views, but remain unresolved.

- If you are viewing a Node that has recently been deleted by another user, the deleted Node appears as a transparent icon on the map until the map is refreshed using the  **Refresh** icon. After **Refresh**, the deleted node is removed from the map. NNMi does not automatically refresh the connectivity or set of nodes in a map view, except on the **Initial Discovery Progress** and **Network Overview** maps.


A subset of NNMi users can delete nodes from a table view, map view, or Node form (depending on the assigned NNMi Role).

Note: By default NNMi Administrators can delete nodes. NNMi Administrators can configure NNMi to permit User Accounts assigned to the NNMi Operator Level 2 User Group to delete nodes. See the *HP Network Node Manager i Software Deployment Reference* for more information (**Help** → **Documentation Library**). Search for "Delete Node".

To delete one or more nodes (maximum 20 at one time):

1. **Unmanage the nodes you want to delete.**
 - a. In a table view, press Ctrl-Click to select each row that represents a node you want to unmanage.
 - b. Select **Actions** → **Management Mode** → **Unmanage**.

Tip: You can also right-click any object in a table or map view to access the items available within the **Actions** menu.

- c. Wait until the Status=*No Status* for each of the following objects:
 - Each Node to be deleted
 - Each Node's Interfaces, IP Addresses, Cards, Ports, and VLAN Ports
2. Do one of the following:
 - **Table views:** Press Ctrl-Click to select each row that represents the objects of interest, and click the  Delete icon. Each selected node is deleted from the NNMi database and removed from the current view.
 - **Map views:** click the map symbol representing the node you want to delete, and click **File** → **Delete Node**. The node is deleted from the NNMi database and removed from the current view.
 - **Node form:** select **File** → **Delete Node** and in the confirmation dialog, click **OK**. The form is automatically closed after NNMi deletes the Node.

Note: If the delete fails, use the [nnmnodedelete.ovpl](#) command. Wait for the command to complete.

To delete any number of nodes:

Use the `nnmnodedelete.ovpl` command. See the [nnmnodedelete.ovpl](#) Reference Page.

Related Topics

[Using Table Views](#)

[Using Map Views](#)


Delete One or More Objects

Each row in a table view and each symbol in a map view represents an instance of the object type being displayed. For example, in a node view, each row of the table represents an instance of a node in your network.

Some NNMi users can delete object instances. For example, you might need to delete a node that is no longer being managed. See ["Delete Nodes" on page 1635](#) for more information.


To delete an object instance:

1. Select the object of interest:
 - In a table view, select the row that represents the object.
 - In a map view, click the map symbol.
 - In a form, proceed to step 2.

2. To delete the object, click the  Delete icon.

The object is deleted from the NNMi database and removed from the current view.

To delete multiple object instances:

1. Select the objects of interest:
 - In a table view, press Ctrl-Click to select each row that represents each object you want to delete.
 - In a map view, Ctrl-Click each map symbol.
2. To delete the objects, click the  Delete icon.

Note: For Node objects, you can use this method to delete up to 20 nodes at one time. To

delete more than 20 nodes, see the [nnmnodedelete.ovpl](#) Reference Page.

Tip: For all other objects, you can delete any number.

Each object is deleted from the NNMi database and removed from the current view.

Related Topics

[Using Table Views](#)

[Using Map Views](#)

["Configure Whether to Delete Unresponsive Nodes" on page 233](#)

Glossary

A

AES

Advanced Encryption Standard

Anycast Rendezvous Point IP Address

Rendezvous Point addresses are loopback addresses used for routers in multi-cast network configurations.

Autonomous System

An Autonomous System (AS) is a collection of connected Internet Protocol (IP) routing prefixes that present a common, clearly defined Border Gateway Protocol (BGP) routing policy to the Internet by having an officially registered Autonomous System Number (ASN).

B

BGP

Border Gateway Protocol

C

Causal Engine

The NNMi Causal Engine analyzes the health of your network and provides the ongoing health status reading for each device. The Causal Engine also extensively evaluates problems and determines the root cause for you, whenever possible, sending incidents to notify you of problems. Any incident generated from a Causal Engine management event has an Origin of NNMi in your incident views.

CBC

Cipher Block Chaining

CE

Customer Edge router. The router in your network that sends data to an Internet Service Provider's router (the Provider Edge) on the path to the data's final destination.

CRC

Cyclic Redundancy Check

Custom Node Collection

A Custom Node Collection identifies a topology node that has at least one associated Custom Poller Policy. Because a topology node can be associated with more than one Policy, the same topology node might appear in multiple Custom Node Collections.

Custom Polled Instance

A Custom Polled Instance represents the results of a MIB variable when it is evaluated against a node. The first time a MIB variable is validated with discovery information, the results appear in the Monitoring workspace's Custom Polled Instances view. The Custom Polled Instance is updated whenever a change in State occurs and includes the most recent polled value that caused the State to change. These results are then used to determine the Status of the associated Custom Node Collection.

Custom User Groups

Custom User Groups are the User Groups that you create. These User Groups are additional to the NNMi User Groups, which are those User Groups that NNMi provides.

D

DES

Data Encryption Standard

E

EIGRP

Enhanced Interior Gateway Routing Protocol

EVPN

Ethernet Virtual Private Network.

G

global unicast address

(2000:: to 3fff:ffff:ffff:ffff:ffff:ffff:ffff:ffff) A publically routable IPv6 unicast address, used for communication between nodes anywhere on the internet. The first part of the address is a global routing prefix in the 2000::/3 address space for your organization (assigned by the Internet Service Providers). The complete host address can either be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

H

HMAC

Hash-based Message Authentication Code

hops

A hop is a node representing any network device, such as a workstation, gateway, or switch, which is connected by a link with no intermediate nodes.

HSRP

Hot Standby Router Protocol

I

IPv6 link-local address

A non-routable IPv6 unicast address only used for communication with other nodes

on the same link (LAN or VLAN). Link local addresses cannot be used for communication that must be forwarded through a router. IPv6 auto-configuration automatically assigns a unique link local address in the fe80::/10 address space to each IPv6-enabled interface on a system.

ISIS

Intermediate System to Intermediate System Protocol

J

Jython

Jython is a programming language (successor of JPython) uses Java class, instead of Python modules.

K

Key Incident

Incidents with both: (1) Severity = other than Normal. (2) Correlation Nature = equal to Root Cause, Service Impact, Stream Correlation, Rate Stream Correlation, Info, or None.

L

Layer 2

Refers to the Data Link layer of the multilayered communication model, Open Systems Interconnection (OSI). The Data Link layer moves data across the physical links in the network. The switches and switch-routers are devices that redirect data messages at the layer 2 level, using the destination Media Access Control (MAC) address to determine where to direct the message.

Layer 3

Refers to the Network layer of the multilayered communication model, Open Systems Interconnection (OSI). The

Network layer is concerned with knowing the address of the neighboring nodes in the network, selecting routes and quality of service, and recognizing and forwarding incoming messages to local host domains. The router and switch-router are the devices that redirect data messages at the Layer 3 level. Everything in a subnet is connected at the Layer 3 (IP) level.

Link Aggregation

Protocols used on Switches to configure multiple Interfaces (Aggregation Member Interfaces) to function as if they were one (an Aggregator Interface). When two Aggregator Interfaces establish a connection, that connection is an Aggregator Layer 2 Connection. The Aggregator Layer 2 Connection appears on Layer 2 Neighbor View maps as a thick line with an Interface icon at each end (representing the Aggregator Interface). When you double-click the thick line, it converts into multiple thin lines representing the participating Aggregation Member Layer 2 Connections with their Aggregation Member Interfaces at each end of the lines.

loopback address

The address associated with the loopback interface. The loopback interface is a virtual interface on a device that provides a route for internal communication. Many vendors provide a specially configured loopback for management purposes. Exact details of how loopbacks are configured varies by vendor and model. See each device's documentation for details. NNMi identifies these loopback addresses by using ifType Number 24, softwareloopback from the IANA ifType-MIB.

M

MAC address

The Media Access Control address (hardware address or physical address) that the factory burns into a network adapter or device with built-in networking capability. A MAC address has six pairs of hexadecimal digits, separated by colons or dashes. For example 02:1F:33:16:BC:55

MAC addresses

The Media Access Control address (hardware address or physical address) that the factory burns into a network adapter or device with built-in networking capability. A MAC address has six pairs of hexadecimal digits, separated by colons or dashes. For example 02:1F:33:16:BC:55

MD5

Message-Digest algorithm 5

MIB file

Management Information Base files are the basic building block of SNMP communication protocol. SNMP Agents are configured to respond to requests defined by a group of supported MIB files.

MPLS

Multiprotocol Label Switching

multicast address

Used to identify a group of hosts joined into a group. IPv4 multicast addresses are in the range 224.0.0.0 to 239.255.255.255 and IPv6 multicast addresses have the prefix ff00::/8.

multiconnection

A multiconnection is a thick line on a map view between two Node icons, two Node Group icons, or between a Node icon and

a Node Group icon (with no Interface icon or IP Address icon at either end of the line). This thick line represents a set of multiple connections that have been combined to preserve space and simplify the map. Your NNMi administrator specifies the number of connections that must exist before NNMi condenses them into a multiconnection line (User Interface Configuration's Multiconnection Threshold attribute). Double-click the thick line to convert it into the original set of connections with Interface icons or IP Address icons at either end of the lines.

N

NAT

Network Address Translation. NNMi supports the following protocols: Static Network Address Translation, Dynamic Network Address Translation, Dynamic Port Address Translation.

NIC

Network Interface Controller

NNMi Role

Determined by your membership in one of four special NNMi User Groups (NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators, or NNMi Guest Users). This membership determines what you can see and do within the NNMi console.

NNMi User Group

NNMi User Groups are those User Groups provided by NNMi. Users cannot access the NNMi console until their User Account is mapped to at least one of the following NNMi User Groups: NNMi Administrators, NNMi Level 2 Operators, NNMi Level 1 Operators (with more limited access privileges than Level 2 Operators), and NNMi Guest Users

Node

A physical or virtual collection of network interfaces that NNMi can pragmatically associate together.

O

OSPF

Open Shortest Path First Protocol

P

PE

Provider Edge router. The Internet Service Provider's router that receives your data on the path to your data's final destination. The Customer Edge (CE) router in your network connects to this PE.

private IP addresses

These are IPv4 addresses that can be reused in home and office local area networks (LANs). Following the standards set by RFC 1918 and RFC 4193 (10.*.*., 169.254.*., 172.16-31.*., and 192.168.*.)

R

RAMS

HP Router Analytics Management System

routing prefixes

A network protocol technique used to shorten or filter the amount of required routing information in each packet by declaring a prefix for an entire group of packets. This prefix also indicated the number of bits in the address.

S

SHA

Secure Hash Algorithm

Split Link Aggregation

Link Aggregation with more than two endpoints. Some vendors refer to this as Multi-Chassis Link Aggregation, SLAG, MLAG, or MC-LAG.

U

unique local address

(fd00:: to fdff:ffff:ffff:ffff:ffff:ffff:ffff:ffff) A privately routable IPv6 unicast address used only for communication between nodes within your organization. The unique local addresses cannot be routed to the public internet. The address consists of a routing prefix in the fd00:/8 address spaces, assigned locally by your organization. And the full host address might be manually configured or automatically assigned using IPv6 auto-configuration and neighbor discovery.

Unmanaged

Indicates the Management Mode is "Not Managed" or "Out of Service".

UUID

Universally Unique Object Identifier, which is unique across all databases.

V

VRRP

Virtual Router Redundancy Protocol

W

WAN Cloud

Layer 3 connectivity between your network and any MPLS networks.

We appreciate your feedback!

If you have comments about this document, you can [contact the documentation team](#) by email. If an email client is configured on this system, click the link above and an email window opens with the following information in the subject line:

Feedback on Online Help: Help for Administrators (Network Node Manager i Software 10.00)

Just add your feedback to the email and click send.

If no email client is available, copy the information above to a new message in a web mail client, and send your feedback to Ovdoc-nsm@hp.com.